Estimate of Magnetic Forces on Beam Sweeping Kickers

PBAR Note 632

Martin Hu

Feb. 23, 2000

The beam sweeping magnet kickers are two pairs of conductors placed 90 degrees apart inside a circular magnetic yoke. Each pair has the same excitation current in the opposite directions, and the two currents are a sine and a cosine in phase.

To estimate the magnetic forces on the kickers due to the excitation currents, we make the following simplifications:

1. The four conductors are all parallel to one another.
2. There are no relative motions within the system.
3. the magnetic yoke has $\mu = \infty$, and the fields are zero near the outside inner surface of the yoke.

Fig. 1 shows the cross section of the conductors. Conductors 1 and 3 have equal and opposite currents, conductors 2 and 4 have equal and opposite currents, and the current I_1 leads I_2 by 90 degrees. We can write I_1 as $I_{peak} \cdot \sin \theta$, I_2 as $I_{peak} \cdot \cos(\theta)$, I_3 as $-I_{peak} \cdot \sin(\theta)$, and I_4 as $-I_{peak} \cdot \cos(\theta)$, where I_{peak} is 10,000 amps. We now wish to calculate the net forces on a conductor due to the other three conductors and the magnetic yoke.

We make the simplifying assumption that the magnetic permittivity, μ , is infinite; in reality μ is about 60 and very little B-field escapes to the outside. Assuming that the B-field is zero right outside the yoke, we can then replace the yoke with 4 image currents in the same directions at a distance a so that the B-field does cancel at the outer circumference of the yoke (Fig. 2). The problem is now reduced to summing up all the forces on one conductor due to the other 7 currents. As shown in Fig. 1, for example for conductor 1, we decompose the forces on it into F_x (radially outward) and F_y (tangential). Then,

$$\begin{aligned} F_{1x} = & F_{21(x)} + F_{31(x)} + F_{41(x)} + F_{1i1(x)} + F_{2i1(x)} + F_{3i1(x)} + F_{4i1(x)} = \\ & \frac{\mu_0 I^2}{2\pi r} \cdot (-\sin \theta \cos \theta \sin \beta + \frac{1}{\sqrt{2}} \sin^2 \theta + \sin \theta \cos \theta \sin \beta + \\ & \frac{r}{a} \sin^2 \theta - \frac{r}{b} \sin \theta \cos \theta \sin \alpha + \frac{r}{a+\sqrt{2}r} \sin^2 \theta + \frac{r}{b} \sin \theta \cos \theta \sin \alpha), \end{aligned}$$

and

$$F_{1y} = F_{21(y)} + F_{31(y)} + F_{41(y)} + F_{1i1(y)} + F_{2i1(y)} + F_{3i1(y)} + F_{4i1(y)} =$$

$$\frac{\mu_0 l}{2\pi r} \cdot I_{peak}^2 \cdot (-\sin \theta \cos \theta \cos \beta + 0 - \sin \theta \cos \theta \cos \beta + 0 -$$

$$\frac{r}{b} \sin \theta \cos \theta \cos \alpha + 0 - \frac{r}{b} \sin \theta \cos \theta \cos \alpha),$$

where $\theta = \omega t$ is the reference phase angle of all currents, l is the length of the conductor, $l = 27.9cm$, $r = 2.00cm$, $a = 4.98cm$, $b = 6.55cm$, $\beta = 45^\circ$ and $\alpha = 12.5^\circ$. Then,

$$F_{1x} = 1.37 \sin^2 \theta,$$

and

$$F_{1y} = -2.00 \sin \theta \cos \theta,$$

where a positive F_x indicates an radially outward force, and a positive F_y indicates a force causing a counter-clockwise rotation. Similar analyses for the other three conductors yield

$$F_{1x} = F_{3x} = 1.37 \sin^2 \theta,$$

$$F_{2x} = F_{4x} = 1.37 \cos^2 \theta,$$

$$F_{1y} = F_{3y} = -2.00 \sin \theta \cos \theta,$$

and

$$F_{2y} = F_{4y} = 2.00 \sin \theta \cos \theta.$$

Fig. 3 shows the radial and tangential forces through a complete current cycle. We draw the following conclusion about the behavior of the conductors:

- Torques caused by the tangential forces about the central Z-axis cancel, hence there is no tendency for the circuit to rotate about the Z-axis.
- There is no radially inward force on any conductor during the entire cycle.
- Peak radial outward force ≈ 8.0 lb/in on each conductor.
- Peak tangential force ≈ 5.2 lb/in on each conductor.

Figure 1: Cross section of conductors; r is 2 cm.

Figure 2: Equivalent current distribution in which the magnetic shield ($\mu = \infty$) is replaced with 4 image currents.

Figure 3: The forces on conductors during a full cycle of current pulse.