-1-

LEGAL NOTICE

This report was prepared as an account of Government sponsored work. Neither the United States, nor the Commission, nor any person acting on behalf of the Commission:

A. Makes any warranty or representation, express or implied, with respect to the accuracy, completeness, or usefulness of the information contained in this report, or that the use of any information, apparatus, method, or process disclosed in this report may not infringe privately owned rights; or

B. Assumes any liabilities with respect to the use of, or for damages resulting from the use of any information, apparatus, method, or process disclosed in this report.

As used in the above, "person acting on behalf of the Commission" includes any employee or contractor of the Commission to the extent that such employee or contractor prepares, handles or distributes, or provides access to, any information pursuant to his employment or contract with the Commission.

Photostat Price \$ 4.80

Microfilm Price \$ 2.70

Available from the
Office of Technical Services
Department of Commerce
Washington 25, D. C.

AECU-3210

73-55-54

FREQUENCY COMPONENTS OF A STEP FUNCTION AND A SINUSOID

R. M. McGehee

ABSTRACT

Fourier analyses are made on two functions. The first is a step function formed from periodic samples of a sinusoid. If the frequency of the sinusoid is less than one-half of the sampling frequency, it is shown that the step function has no frequency components less than one-half of the sampling frequency other than that of the sinusoid itself. The second function is a sinusoid which has variable period, phase, and duration with respect to the interval of the analysis. It is shown that the insertion of a blank space in the period of analysis reduces greatly the uncertainty of the amplitude of the initial sinusoid as estimated from the results of the Fourier analysis. The results of the analyses are useful in the design and evaluation of certain analog data-analyzing systems.

Case No. 414.00

May 10, 1955

325 001

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency Thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

2

DISTRIBUTION:

G. A. Fowler, 5400
T. S. Church, 5410
T. F. Marker, 5420
H. H. Patterson, 5440
B. J. Bittner, 5412
J. P. Shoup, 5413
R. K. Moore, 5412-2
F. O. Lane, 5242
R. M. McGehee, 5413 (3)
R. K. Smeltzer, 1922-2
Max K. Linn, 1923 (6)
Physical Science Laboratories, N. M. A&M
Attn: Mr. P. D. Welch
Naval Research Laboratories, Washington, D.C.
Attn: Mr. D. Ringwalt

DO NOT
PHOTOSTAT

INTRODUCTION

Frequency analyses are often desired from data which are available only as a sequence of samples. If the samples were taken at uniform time intervals, a simple approximation to the function from which the samples were taken is a step function, constructed by assigning sample values in sequence to equal, consecutive time intervals; i.e., the function has the value of the first sample for a time interval, ΔT , then assumes the value of the second sample for a like interval, and so on through the sample sequence. The characteristics of the step-function approximation to a sinusoid are to be determined. From these, the step-function method may be evaluated. A summary of results is given on page 19.

A second problem arises in making the frequency analysis. In one method of analysis, the data are recorded on magnetic tape or drum which is then cycled rapidly, the signal being read off into a frequency analyzer. Frequency components of the signal would in general have random frequency and phase with respect to the cycling frequency. Also, closing of the data cycle may not be practical; there may be a gap in the signal cycle in which no data are recorded. To determine the theoretical limitations of this method of analysis, a Fourier analysis is made upon a sinusoid having variable period, phase, and duration with respect to the period of the analysis. The results of the analysis will be useful in design and evaluation of analog frequency analyzers. Summaries of important results are given on pages 24 and 29.

Quite probably, similar analyses have been performed, but these are unknown to the author. No search was made, for considerable time would be taken in making the search and in evaluating similar analyses if found. When making the analyses in detail, the results can be guided toward the problem at hand.

325 062

PROBLEM I

Assume a sine function of unit amplitude having an integral number of cycles, m , within an interval $0 \leq x \leq 2\pi$ and having its positive - going zero at $x = -a$; i.e.,

$$\sin m(x + a). \quad (1)$$

The sinusoid is sampled at a number of points equally spaced at intervals $\frac{2\pi}{n}$, beginning at $x = 0$. The value n is to be chosen greater than $2m$, so that the theoretical minimum number of sampling points, according to the sampling theorem, is always exceeded. A periodic sample sequence having a period 2π is then obtained. A step function is defined by assigning the value of each sample to the interval following it (Fig. 1).

$$f(x) = \sin m\left(i \frac{2\pi}{n} + a\right); \quad (2)$$

$$i \frac{2\pi}{n} < x < (i + 1) \frac{2\pi}{n};$$

$$i = 0, 1, 2, \dots, n - 1.$$

Let a take on discrete values a_j .

$$\varphi_{ij} = m\left(i \frac{2\pi}{n} + a_j\right); \quad (3)$$

$$F_{ij} = \sin \varphi_{ij}. \quad (4)$$

Then

$$f_j(x) = F_{ij}; i \frac{2\pi}{n} < x < (i + 1) \frac{2\pi}{n}. \quad (5)$$

Fig. 1 -- Sin 2(x + a)
n = 5

1. FOURIER ANALYSIS

Let

$$f(x) = \sum_{k=0}^{\infty} (A_k \cos kx + B_k \sin kx). \quad (6)$$

Then

$$A_0 = \frac{1}{2\pi} \int_0^{2\pi} f(x) dx, \quad B_0 = 0. \quad (7)$$

$$\left. \begin{aligned} A_k &= \frac{1}{\pi} \int_0^{2\pi} f(x) \cos kx \, dx \\ B_k &= \frac{1}{\pi} \int_0^{2\pi} f(x) \sin kx \, dx \end{aligned} \right\} \quad k = 1, 2, \dots \quad (8)$$

$$P = \frac{1}{2\pi} \int_0^{2\pi} f^2(x) \, dx. \quad (9)$$

Operations 7 through 9 are performed on the step function of Eq. 5, yielding:

$$A_{j0} = \frac{1}{n} \sum_{i=0}^{n-1} F_{ij}. \quad (10)$$

$$P_j = \frac{1}{n} \sum_{i=0}^{n-1} F_{ij}^2. \quad (11)$$

$$A_{jk} = \frac{2}{k\pi} \sin \frac{k\pi}{n} \sum_{i=0}^{n-1} F_{ij} \cos (2i+1) \frac{k\pi}{n}. \quad (12)$$

$$B_{jk} = \frac{2}{k\pi} \sin \frac{k\pi}{n} \sum_{i=0}^{n-1} F_{ij} \sin (2i+1) \frac{k\pi}{n}. \quad (13)$$

Let

$$C_{jk} = \sqrt{A_{jk}^2 + B_{jk}^2}. \quad (14)$$

The above expressions are very complex, and general conclusions cannot be drawn from them immediately. Two numerical examples are worked out. From these, it may be possible to predict a pattern which will lead to simplification of the expressions.

2. EXAMPLES

Example 1. Take $m = 1$, $n = 3$.

Fig. 2 -- $\sin(x + a_j)$ (15)

Three values are assigned to a_j .

$$j : 0 \quad 1 \quad 2$$

$$a_j : 0 \quad \frac{\pi}{4} \quad \frac{\pi}{2}$$

Numerical values are inserted in Eqs. 3, 4, 10, 11, 12, 13 and 14. The results are summarized in Table 1. Values were computed for $k = 1$ through 4.

Table 1

$$\left. \begin{array}{l} A_{j0} = 0 \\ P_j = 0.5 \end{array} \right\} \text{ for } j = 0, 1, 2$$

j	k	1	2	3	4
	A_{jk}				
0		-.716	.357	.000	.179
1		-.214	.107	.000	.054
2		.414	-.206	.000	-.107
	B_{jk}				
0		.414	.206	.000	-.104
1		.799	.398	.000	-.200
2		.716	.357	.000	-.179
	C_{jk}				
0		.827	.413	.000	.207
1		.827	.413	.000	.207
2		.827	.413	.000	.207

The values A_0 , P and C_k appear to be independent of the value of a . The value of A_0 is zero and the value of P is the same as that for the original sine wave.

If the value of C_k represents the amplitude of an alternating voltage component driving a unit resistance, the power produced by the component is:

$$P_k = \frac{C_k^2}{2} \quad (16)$$

Then

$$P = \frac{1}{2} \sum_{k=0}^{\infty} C_k^2 = 0.5 \quad (17)$$

Table 2

k	C_k^2	$\frac{\sum_k P_k}{P}$
1	.683	.683
2	.171	.854
3	.000	.854
4	.043	.897

Example 2.

$$m = 2, \quad n = 5.$$

Figure 1 illustrates this example. Three values are assigned to a_j .

$$j : 0 \quad 1 \quad 2$$

$$a_j : 0 \quad \frac{\pi}{8} \quad \frac{\pi}{4}$$

Numerical values are inserted in Eqs 3, 4, 10, 11, 12, 13 and 14. Values were computed for $k = 1$ through 4. The results are summarized in Table 3.

Table 3

$$\left. \begin{array}{l} A_{j0} = 0 \\ P_j = 0.5 \end{array} \right\} \text{ for } j = 0, 1, 2$$

j	k	1	2	3	4
		A_{jk}			
0		.000	-.720	.480	.000
1		.000	-.344	.229	.000
2		.000	.234	-.156	.000
		B_{jk}			
0		.000	.234	.156	.000
1		.000	.674	.450	.000
2		.000	.720	.480	.000
		C_{jk}			
0		.000	.757	.505	.000
1		.000	.757	.505	.000
2		.000	.757	.505	.000

Values of A_0 , P and C_k are again independent of the value of a . A_0 is zero and P is 0.5 in both examples. Nonzero values of C_k appear to be related to each other by the inverse ratio of the harmonic index, k . In example 2, the frequency lower than that of the original sinusoid is not present.

Table 4

k	C_k^2	$\frac{\sum_k P_k}{P}$
1	.000	.000
2	.573	.573
3	.255	.828
4	.000	.828

Further investigation of the general expressions will be made to prove or disprove the characteristics which are inferred from the examples; i.e.,

$$A_0 = 0.$$

$$P = 1/2.$$

C_k independent of a , and nonzero values related by the inverse ratio of the harmonic index, k .

An expression for C_k in terms of m , n and k is desired.

The occurrence of frequencies other than C_m in the band of interest is to be investigated.

3. SIMPLIFICATION OF EXPRESSIONS

Expressions to be evaluated:

$$\text{I.} \quad A_0 = \frac{1}{n} \sum_{i=0}^{n-1} \sin m(i \frac{2\pi}{n} + a). \quad (18)$$

$$\text{II.} \quad P = \frac{1}{n} \sum_{i=0}^{n-1} \sin^2 m(i \frac{2\pi}{n} + a). \quad (19)$$

$$\text{III.} \quad C_k^2 = A_k^2 + B_k^2. \quad (20)$$

$$A_k = \frac{2}{k\pi} \sin \frac{k\pi}{n} \sum_{i=0}^{n-1} \left[\sin m(i \frac{2\pi}{n} + a) \cdot \cos (2i + 1) \frac{k\pi}{n} \right]. \quad (21)$$

$$B_k = \frac{2}{k\pi} \sin \frac{k\pi}{n} \sum_{i=0}^{n-1} \left[\sin m(i \frac{2\pi}{n} + a) \cdot \sin (2i + 1) \frac{k\pi}{n} \right]. \quad (22)$$

$$I. \quad A_0 = \frac{1}{n} \sum_{i=0}^{n-1} \sin m(i\frac{2\pi}{n} + a) = \frac{1}{n} \cos a \sum_{i=0}^{n-1} \sin mi\frac{2\pi}{n} + \frac{1}{n} \sin a \sum_{i=0}^{n-1} \cos mi\frac{2\pi}{n}. \quad (23)$$

Let j represent the complex value $\sqrt{-1}$. The complex numbers

$$\epsilon^{jmi\frac{2\pi}{n}}, \quad i = 0, 1, 2, \dots, n-1,$$

$n > m$, both being integers,

are a set of points in the complex plane having unit radii from and spaced at equal angles about the origin. Thus

$$\sum_{i=0}^{n-1} \epsilon^{jmi\frac{2\pi}{n}} = 0. \quad (24)$$

$$\sum_{i=0}^{n-1} \cos mi\frac{2\pi}{n} + j \sum_{i=0}^{n-1} \sin mi\frac{2\pi}{n} = 0. \quad (25)$$

$$\sum_{i=0}^{n-1} \cos mi\frac{2\pi}{n} = 0, \quad \sum_{i=0}^{n-1} \sin mi\frac{2\pi}{n} = 0. \quad (26)$$

Thus

$$A_0 = 0. \quad (27)$$

II.

$$P = \frac{1}{n} \sum_{i=0}^{n-1} \sin^2 m(i\frac{2\pi}{n} + a)$$

$$= \frac{1}{n} \sum_{i=0}^{n-1} \frac{1}{2} [1 - \cos 2m(i\frac{2\pi}{n} + a)] = \frac{1}{2} - \frac{1}{2n} \sum_{i=0}^{n-1} \cos 2m(i\frac{2\pi}{n} + a). \quad (28)$$

By the initial assumption, $n > 2m$. Thus, according to the results in I above, the last summation is zero, and

$$P = \frac{1}{2}. \quad (29)$$

III.

$$C_k^2 = \frac{4}{k^2 n^2} \sin^2 \frac{k\pi}{n} \cdot \left\{ \left[\sum_{i=0}^{n-1} \sin m(i \frac{2\pi}{n} + a) \cos (2i + 1) \frac{k\pi}{n} \right]^2 + \left[\sum_{i=0}^{n-1} \sin m(i \frac{2\pi}{n} + a) \sin (2i + 1) \frac{k\pi}{n} \right]^2 \right\}. \quad (30)$$

Let

$$K^2 = \frac{4}{k^2 n^2} \sin^2 \frac{k\pi}{n}. \quad (31)$$

$$\begin{aligned} C_k^2 &= K^2 \left\{ \left[\sum_{i=0}^{n-1} \sin m(i \frac{2\pi}{n} + a) \cos (2i + 1) \frac{k\pi}{n} \right] \left[\sum_{r=0}^{n-1} \sin m(r \frac{2\pi}{n} + a) \cos (2r + 1) \frac{k\pi}{n} \right] \right. \\ &\quad + \left. \left[\sum_{i=0}^{n-1} \sin m(i \frac{2\pi}{n} + a) \sin (2i + 1) \frac{k\pi}{n} \right] \left[\sum_{r=0}^{n-1} \sin m(r \frac{2\pi}{n} + a) \sin (2r + 1) \frac{k\pi}{n} \right] \right\} \\ &= K^2 \sum_{i=0}^{n-1} \sum_{r=0}^{n-1} \left\{ \left[\sin m(i \frac{2\pi}{n} + a) \sin m(r \frac{2\pi}{n} + a) \right] \right. \\ &\quad \cdot \left. \left[\cos (2i + 1) \frac{k\pi}{n} \cos (2r + 1) \frac{k\pi}{n} + \sin (2i + 1) \frac{k\pi}{n} \sin (2r + 1) \frac{k\pi}{n} \right] \right\} \\ &= K^2 \sum_{i=0}^{n-1} \sum_{r=0}^{n-1} \left\{ \left[\sin m(i \frac{2\pi}{n} + a) \sin m(r \frac{2\pi}{n} + a) \right] \cos 2(i - r) \frac{k\pi}{n} \right\} \\ &= \frac{K^2}{2} \sum_{i=0}^{n-1} \sum_{r=0}^{n-1} \left\{ \left[\cos m(i - r) \frac{2\pi}{n} - \cos m \left((i + r) \frac{2\pi}{n} + 2a \right) \right] \cos 2(i - r) \frac{k\pi}{n} \right\} \\ &= \frac{K^2}{2} \sum_{i=0}^{n-1} \sum_{r=0}^{n-1} \left\{ \cos m(i - r) \frac{2\pi}{n} \cos 2(i - r) \frac{k\pi}{n} \right\} \\ &\quad - \frac{K^2}{2} \cos 2a \sum_{i=0}^{n-1} \sum_{r=0}^{n-1} \left\{ \cos m(i + r) \frac{2\pi}{n} \cos 2(i - r) \frac{k\pi}{n} \right\} \\ &\quad + \frac{K^2}{2} \sin 2a \sum_{i=0}^{n-1} \sum_{r=0}^{n-1} \left\{ \sin m(i + r) \frac{2\pi}{n} \cos 2(i - r) \frac{k\pi}{n} \right\}. \quad (32) \end{aligned}$$

The coefficients of $\cos 2a$ and $\sin 2a$ are first investigated.

$$\begin{aligned}
& \sum_{i=0}^{n-1} \sum_{r=0}^{n-1} \left\{ \cos m(i+r) \frac{2\pi}{n} \cos 2(i-r) \frac{k\pi}{n} \right\} = \frac{1}{2} \sum_{i=0}^{n-1} \sum_{r=0}^{n-1} \left\{ \cos \left[m(i+r) \frac{2\pi}{n} + k(i-r) \frac{2\pi}{n} \right] \right. \\
& \quad \left. + \cos \left[m(i+r) \frac{2\pi}{n} - k(i-r) \frac{2\pi}{n} \right] \right\} = \frac{1}{2} \sum_{i=0}^{n-1} \sum_{r=0}^{n-1} \left\{ \cos \left[i(m+k) \frac{2\pi}{n} + r(m-k) \frac{2\pi}{n} \right] \right. \\
& \quad \left. + \cos \left[r(m+k) \frac{2\pi}{n} + i(m-k) \frac{2\pi}{n} \right] \right\} = \sum_{i=0}^{n-1} \sum_{r=0}^{n-1} \cos \left[i(m+k) \frac{2\pi}{n} + r(m-k) \frac{2\pi}{n} \right] \\
& = \sum_{i=0}^{n-1} \sum_{r=0}^{n-1} \left\{ \cos i(m+k) \frac{2\pi}{n} \cos r(m-k) \frac{2\pi}{n} - \sin i(m+k) \frac{2\pi}{n} \sin r(m-k) \frac{2\pi}{n} \right\} \\
& = \left\{ \sum_{i=0}^{n-1} \cos i(m+k) \frac{2\pi}{n} \right\} \left\{ \sum_{r=0}^{n-1} \cos r(m-k) \frac{2\pi}{n} \right\} \\
& \quad - \left\{ \sum_{i=0}^{n-1} \sin i(m+k) \frac{2\pi}{n} \right\} \left\{ \sum_{r=0}^{n-1} \sin r(m-k) \frac{2\pi}{n} \right\} \\
& = \left\{ \sum_{i=0}^{n-1} \cos i(k+m) \frac{2\pi}{n} \right\} \left\{ \sum_{i=0}^{n-1} \cos i(k-m) \frac{2\pi}{n} \right\} \\
& \quad + \left\{ \sum_{i=0}^{n-1} \sin i(k+m) \frac{2\pi}{n} \right\} \left\{ \sum_{i=0}^{n-1} \sin i(k-m) \frac{2\pi}{n} \right\} . \tag{33}
\end{aligned}$$

If q is an integer less than n , it has been shown that

$$\sum_{i=0}^{n-1} \cos iq \frac{2\pi}{n} = 0 . \tag{34}$$

If p is an integer divisible by n ,

$$\sum_{i=0}^{n-1} \cos ip \frac{2\pi}{n} = n . \tag{35}$$

If p is an integer greater than but not divisible by n , let

$$p = q + sn, \text{ where } q < n \text{ and } s \text{ is an integer.} \quad (36)$$

$$\begin{aligned} \sum_{i=0}^{n-1} \cos ip \frac{2\pi}{n} &= \sum_{i=0}^{n-1} \cos i(q + sn) \frac{2\pi}{n} \\ &= \sum_{i=0}^{n-1} \left\{ \cos is2\pi \cos iq \frac{2\pi}{n} - \sin is2\pi \sin iq \frac{2\pi}{n} \right\} \\ &= \sum_{i=0}^{n-1} \cos iq \frac{2\pi}{n} = 0. \end{aligned} \quad (37)$$

Similarly, it may be shown that

$$\sum_{i=0}^{n-1} \sin ip \frac{2\pi}{n} = 0 \quad (38)$$

for all integral values of p .

The last expression of Eq. 33 is zero unless both $k + m$ and $k - m$ are divisible by n . Assume that $k - m$ is divisible by n ; i.e.,

$$\frac{k - m}{n} = Q, \text{ an integer.} \quad (39)$$

Then

$$\frac{k + m}{n} = Q + \frac{2m}{n}. \quad (40)$$

Since $n > 2m$, $k + m$ is not divisible by n .

Likewise, if $k + m$ is divisible by n , $k - m$ is not. Thus Eq. 33 has the value zero and the coefficient of $\cos 2a$ in Eq. 32 is zero.

Similarly, from the coefficient of $\sin 2a$ in Eq. 32,

$$\begin{aligned}
\sum_{i=0}^{n-1} \sum_{r=0}^{n-1} \left\{ \sin m(i+r) \frac{2\pi}{n} \cos 2(i-r) \frac{k\pi}{n} \right\} &= \frac{1}{2} \sum_{i=0}^{n-1} \sum_{r=0}^{n-1} \left\{ \sin \left[m(i+r) \frac{2\pi}{n} + k(i-r) \frac{2\pi}{n} \right] \right. \\
&+ \sin \left[m(i+r) \frac{2\pi}{n} - k(i-r) \frac{2\pi}{n} \right] \left. \right\} = \frac{1}{2} \sum_{i=0}^{n-1} \sum_{r=0}^{n-1} \left\{ \sin \left[i(m+k) \frac{2\pi}{n} + r(m-k) \frac{2\pi}{n} \right] \right. \\
&+ \sin \left[r(m+k) \frac{2\pi}{n} + i(m-k) \frac{2\pi}{n} \right] \left. \right\} = \sum_{i=0}^{n-1} \sum_{r=0}^{n-1} \left\{ \sin \left[i(m+k) \frac{2\pi}{n} + r(m-k) \frac{2\pi}{n} \right] \right\} \\
&= \left\{ \sum_{i=0}^{n-1} \sin i(m+k) \frac{2\pi}{n} \right\} \left\{ \sum_{r=0}^{n-1} \cos r(m-k) \frac{2\pi}{n} \right\} \\
&+ \left\{ \sum_{i=0}^{n-1} \cos i(m+k) \frac{2\pi}{n} \right\} \left\{ \sum_{r=0}^{n-1} \sin r(m-k) \frac{2\pi}{n} \right\} = 0. \quad (41)
\end{aligned}$$

Thus, C_k is independent of a .

$$C_k^2 = \frac{k^2}{2} \sum_{i=0}^{n-1} \sum_{r=0}^{n-1} \left\{ \cos m(i-r) \frac{2\pi}{n} \cos k(i-r) \frac{2\pi}{n} \right\} \quad (42)$$

$$K^2 = \frac{4}{k^2 \pi^2} \sin^2 \frac{k\pi}{n} \quad (31)$$

Simplifying Eq. 42,

$$\begin{aligned}
C_k^2 &= \frac{K^2}{4} \sum_{i=0}^{n-1} \sum_{r=0}^{n-1} \left\{ \cos \left[(m+k)(i-r) \frac{2\pi}{n} \right] + \cos \left[(m-k)(i-r) \frac{2\pi}{n} \right] \right\} \\
&= \frac{K^2}{n} \sum_{i=0}^{n-1} \sum_{r=0}^{n-1} \left\{ \cos i(m+k) \frac{2\pi}{n} \cos r(m+k) \frac{2\pi}{n} + \sin i(m+k) \frac{2\pi}{n} \sin r(m+k) \frac{2\pi}{n} \right. \\
&\quad \left. + \cos i(m-k) \cos r(m-k) \frac{2\pi}{n} + \sin i(m-k) \frac{2\pi}{n} \sin r(m-k) \frac{2\pi}{n} \right\} \\
&= \frac{K^2}{4} \left\{ \left[\sum_{i=0}^{n-1} \cos i(m+k) \frac{2\pi}{n} \right] \left[\sum_{r=0}^{n-1} \cos r(m+k) \frac{2\pi}{n} \right] \right. \\
&\quad + \left[\sum_{i=0}^{n-1} \sin i(m+k) \frac{2\pi}{n} \right] \left[\sum_{r=0}^{n-1} \sin r(m+k) \frac{2\pi}{n} \right] \\
&\quad + \left[\sum_{i=0}^{n-1} \cos i(m-k) \frac{2\pi}{n} \right] \left[\sum_{r=0}^{n-1} \cos r(m-k) \frac{2\pi}{n} \right] \\
&\quad \left. + \left[\sum_{i=0}^{n-1} \sin i(m-k) \frac{2\pi}{n} \right] \left[\sum_{r=0}^{n-1} \sin r(m-k) \frac{2\pi}{n} \right] \right\} \\
&= \frac{K^2}{4} \left\{ \left[\sum_{i=0}^{n-1} \cos i(m+k) \frac{2\pi}{n} \right]^2 + \left[\sum_{i=0}^{n-1} \cos i(m-k) \frac{2\pi}{n} \right]^2 \right\}. \tag{43}
\end{aligned}$$

Using Eqs. 35 and 37, Eq. 42 may be simplified to:

$$C_k^2 = \begin{cases} \frac{K^2 n^2}{4}, & \text{for } k = m \text{ and for } |k+m| \text{ or } |k-m| \text{ divisible by } n. \\ 0, & \text{when neither } |k+m| \text{ nor } |k-m| \text{ is divisible by } n. \end{cases} \tag{44}$$

$$C_k = \begin{cases} \frac{|\sin \frac{k\pi}{n}|}{\frac{k\pi}{n}}, & \text{for } k = m \text{ and for } |k+m| \text{ or } |k-m| \text{ divisible by } n. \\ 0, & \text{when neither } |k+m| \text{ nor } |k-m| \text{ is divisible by } n. \end{cases} \tag{45}$$

C_k is zero for all $k < m$, since $n > 2m$ and neither $|k + m|$ nor $|k - m|$ can be as large as n . The sampling procedure introduces no frequencies below that of the sinusoid sampled.

Equation 45 may be verified for the two examples previously given.

Example 1

$$m = 1, n = 3.$$

<u>k</u>	<u>k + m</u>	<u>k - m</u>	<u>C_k</u>
1	2	0	.827
2	3	1	.413
3	4	2	.000
4	5	3	.207

Example 2

$$m = 2, n = 5.$$

<u>k</u>	<u>k + m</u>	<u>k - m</u>	<u>C_k</u>
1	3	-1	.000
2	4	0	.757
3	5	1	.504
4	6	2	.000

Values check those calculated by the detailed procedure.

In each example, values of C_k are related to one another by the inverse ratio of the k 's. This behavior indicates that $|\sin k\pi/n|$ may be independent of k .

When $C_k = 0$,

$$\frac{k - m}{n} = p \text{ or } \frac{k + m}{n} = q, \quad (46)$$

where p and q are integers. (p may be zero.)

For $\frac{k - m}{n} = p$,

$$\left| \sin \frac{k\pi}{n} \right| = \left| \sin \left(p + \frac{m}{n} \right) \pi \right| = \sin \frac{m}{n} \pi. \quad (47)$$

For $\frac{k + m}{n} = q$,

$$\left| \sin \frac{k\pi}{n} \right| = \left| \sin \left(q - \frac{m}{n} \right) \pi \right| = \left| \sin \left(-\frac{m}{n} \right) \pi \right| = \sin \frac{m}{n} \pi. \quad (48)$$

325 014

Equation 45 may be written:

$$C_m = \frac{\sin \frac{m\pi}{n}}{\frac{m\pi}{n}} \quad (49)$$

$$C_k = \begin{cases} \frac{m}{k} C_m, & |k + m| \text{ or } |k - m| \text{ divisible by } n. \\ 0, & \text{neither } |k + m| \text{ nor } |k - m| \text{ divisible by } n. \end{cases} \quad (50)$$

The maximum frequency of interest in the present application will not exceed the frequency corresponding to $n/2$ cycles (this is the theoretical upper limit corresponding to n samples). It is highly desirable that no frequencies occur below this limit other than that for $k = m$.

The first frequency occurring above that for $k = m$ has the index k determined by

$$\frac{k + m}{n} = 1 \quad (51)$$

or

$$k = n - m. \quad (52)$$

now

$$m < \frac{n}{2} \quad (53)$$

and

$$n - m > n - \frac{n}{2}. \quad (54)$$

Thus

$$k > \frac{n}{2}. \quad (55)$$

It has been shown that the only frequency component produced by the step-function approximation to a sinusoid within a frequency band of one-half of the sampling frequency is the frequency of the sinusoid. The amplitude of this component may be written

$$C = \frac{\sin \pi \frac{f}{f_s}}{\pi \frac{f}{f_s}}, \quad (56)$$

where f is the actual frequency, f_s is the sampling frequency and

$$f_s > 2f. \quad (57)$$

In writing the previous results in the form of the above equation, it is assumed that values of m and n can be found such that an integral number of samples, n , can be taken over an integral number of cycles, m . If f_s and f are incommensurate, values of C can be determined to any required accuracy by taking sufficiently large values of m and n .* Thus the expression is valid for all f and f_s satisfying the stated conditions.

Table 5
Values of C

$\frac{2f}{f_s}$	$\frac{\pi}{2} \cdot \frac{2f}{f_s}$	$\sin \frac{f\pi}{f_s}$	C
0	0	0	1.000
0.1	$\pi/20$	.1563	.995
0.2	$\pi/10$	.309	.984
0.4	$\pi/5$	.587	.934
0.6	$3\pi/10$	.809	.858
0.8	$2\pi/5$	.951	.757
1.0	$\pi/2$	.1000	.637

In effect, the sampling procedure acts as a filter whose curve is obtained by plotting the above points, as is done in Fig. 3. In some applications, a filter having a curve the inverse of that given may be used to compensate the amplitude error caused by the sampling procedure.

4. FREQUENCIES HIGHER THAN ONE HALF OF THE SAMPLING FREQUENCY

Sampling of frequencies which are exact multiples of $f_s/2$ yields a result which is not significant, since sample values are a function of the relative phase of the sinusoid and the sampling points. Exact coincidence of an actual frequency with a multiple of the sampling frequency over a large number of samples is highly improbable in a physical problem, thus this limiting case is not important.

Frequencies higher than one half of the sampling frequency may occur. If these produce Fourier harmonics in the frequency range below one half of the sampling frequency, error will be introduced. If $2m/n$ is not an integer, Eq. 43 is valid for $m > n/2$. Consider values of m

$$\frac{n}{2} < m < n.$$

Let

$$m = \frac{n}{2} + r,$$

$$0 < r < \frac{n}{2}. \quad (58)$$

The value of C_m is not zero. Another value of C_k is also nonzero for $k < m$. This value is given by

$$\frac{k + m}{n} = 1. \quad (59)$$

*An infinite and time-stationary sequence is implied.

Fig. 3 -- Amplitude Curve

Solving Eq. 58 and 59 for k in terms of r ,

$$k = \frac{n}{2} - r = n - m. \quad (60)$$

Equation 60 shows that a frequency less than one half the sampling rate is introduced. Frequencies in the band $f_s/2 < f < f_s$ are in effect reflected into the band $0 < f < f_s$ about the frequency axis $f_s/2$; i.e.,

$$C(f_s - f) = \frac{\sin \pi(1 - \frac{f}{f_s})}{\pi(1 - \frac{f}{f_s})}. \quad (61)$$

In order that the amplitude of frequencies less than $f_s/2$ be evaluated correctly, it is necessary that no frequency components greater than $f_s/2$ exist in the original waveform.

5. SUMMARY

If a step function is produced from samples of a sinusoid, the samples being taken at a rate greater than twice the frequency of the sinusoid, the only frequency component of the step function in the frequency band below one half of the sampling frequency is that of the sinusoid. Since superposition applies, the original frequency components of a waveform from which a sample sequence has been taken can be determined without error* by frequency analysis of the step approximation if there are no frequency components in the waveform greater than one half the sampling frequency. The amplitude of a frequency component in the step approximation is related to the amplitude in the original waveform by the expression

$$\frac{A_s}{A} = \frac{\sin \pi \frac{f}{f_s}}{\pi \frac{f}{f_s}} \quad (62)$$

where

A is the amplitude of the original frequency component,
 A_s is the amplitude of that component in the step approximation,
 f is the frequency of the component, and
 f_s is the sampling frequency.

If frequency components greater than one half of the sampling frequency exist in the original waveform, frequency components are introduced into the band below one half of the sampling frequency. These components introduce an error which is inherent in the step-approximation methods.

* To determine frequency components with no error, an infinite and time-stationary sequence is implied.

PROBLEM II

A Fourier analysis is to be made on a sinusoid whose period, phase and frequency are variable with respect to the period of the analysis.

Fig. 1

$$f(x) = \begin{cases} \sin \left(\frac{2\pi x}{t} + \varphi \right), & 0 < x < pT, \\ 0, & pT < x < T. \end{cases} \quad (1)$$

The Fourier series has the form

$$f(x) = A_0 + \sum_{k=1}^{\infty} \left(A_k \cos \frac{2\pi kx}{T} + B_k \sin \frac{2\pi kx}{T} \right). \quad (2)$$

The Fourier coefficients are given by

$$A_0 = \frac{1}{T} \int_0^T f(x) dx. \quad (3)$$

$$A_k = \frac{2}{T} \int_0^T f(x) \cos \frac{2\pi kx}{T} dx. \quad (4)$$

$$B_k = \frac{2}{T} \int_0^T f(x) \sin \frac{2\pi kx}{T} dx. \quad (5)$$

The coefficients are

$$A_0 = \frac{t}{\pi T} \sin \pi p \frac{T}{t} \sin \left(\pi p \frac{T}{t} + \varphi \right) \quad (6)$$

$$A_k = \frac{1}{\pi} \left\{ \frac{1}{\frac{T}{t} + k} \sin \left[\pi \left(\frac{T}{t} + k \right) p \right] \sin \left[\pi \left(\frac{T}{t} + k \right) p + \varphi \right] + \frac{1}{\frac{T}{t} - k} \sin \left[\pi \left(\frac{T}{t} - k \right) p \right] \sin \left[\pi \left(\frac{T}{t} - k \right) p + \varphi \right] \right\}. \quad (7)$$

$$B_k = \frac{1}{\pi} \left\{ \frac{1}{\frac{T}{t} - k} \sin \left[\pi \left(\frac{T}{t} - k \right) p \right] \cos \left[\pi \left(\frac{T}{t} - k \right) p + \phi \right] - \frac{1}{\frac{T}{t} + k} \sin \left[\pi \left(\frac{T}{t} + k \right) p \right] \cos \left[\pi \left(\frac{T}{t} + k \right) p + \phi \right] \right\}. \quad (8)$$

Let

$$C_k = \sqrt{A_k^2 + B_k^2}, \quad (9)$$

$$r = \frac{T}{t}. \quad (10)$$

$$\pi^2 C_k^2 = \frac{\sin^2 \pi(r+k)p}{(r+k)^2} + \frac{\sin^2 \pi(r-k)p}{(r-k)^2} - 2 \frac{\sin \pi(r+k)p}{r+k} \cdot \frac{\sin \pi(r-k)p}{r-k} \cdot \cos(2\pi r p + 2\phi). \quad (11)$$

The mean square amplitude of $f(x)$ is designated the normalized power of the function.

$$P = \frac{1}{T} \int_0^T f^2(x) dx = \frac{p}{2} - \frac{1}{4\pi r} \sin(2\pi r p) \cos(2\pi r p + 2\phi). \quad (12)$$

Equating the power of the components to that of the function gives:

$$P = A_0^2 + \frac{1}{2} \sum_{k=1}^{\infty} C_k^2. \quad (13)$$

1. Consider first the characteristics of the C_k when there is no gap in the cycle ($p = 1$).

$$C_k^2 = \frac{1 - \cos 2\pi r}{\pi^2 r^2 \left[\left(\frac{k}{r} \right)^2 - 1 \right]^2} \left\{ \left(\frac{k}{r} \right)^2 + 1 + \left[\left(\frac{k}{r} \right)^2 - 1 \right] \cos(2\pi r + 2\phi) \right\}. \quad (14)$$

$$a. \quad \lim_{k \rightarrow \infty} C_k = 0. \quad (15)$$

$$b. \quad \lim_{r \rightarrow \infty} C_k = 0. \quad (16)$$

c. If r is an integer,

$$(1) \quad k \neq r, \quad C_k = 0. \quad (17)$$

$$(2) \quad k = r, \quad C_k = 1. \quad (18)$$

$$d. \quad \sum_{k=1}^{\infty} C_k^2 \leq 2P = 1 - \frac{1}{2\pi r} \sin 2\pi r \cos (2\pi r + 2\varphi)$$

$$\approx 1, \text{ for } r \text{ reasonably large.} \quad (19)$$

e. C_k^2 is a function of φ , r and k . The limits on its values are to be investigated. Consider first its behavior as a function of φ .

$$\frac{\partial C_k^2}{\partial \varphi} = -2 \frac{1 - \cos 2\pi r}{\pi^2 (k^2 - r^2)} \sin (2\pi r + 2\varphi). \quad (20)$$

The first derivative $\frac{\partial C_k^2}{\partial \varphi}$ is zero for

$$(1) \quad r \text{ an integer } (C_k = \delta_{jk}),$$

$$(2) \quad 2\pi r + 2\varphi = n\pi, \quad n \text{ an integer.}$$

$$\frac{\partial^2 C_k^2}{\partial \varphi^2} = -\frac{4}{\pi^2} \cdot \frac{1 - \cos 2\pi r}{k^2 - r^2} \cos (2\pi r + 2\varphi). \quad (21)$$

Maxima of C_k^2 occur for

$$r < k \text{ at } 2\pi r + 2\varphi = 2n\pi, \quad (22)$$

$$r > k \text{ at } 2\pi r + 2\varphi = (2n + 1)\pi. \quad (23)$$

Minima occur for

$$r < k \text{ at } 2\pi r + 2\varphi = (2n + 1)\pi, \quad (24)$$

$$r > k \text{ at } 2\pi r + 2\varphi = 2n\pi. \quad (25)$$

The C_k are always considered positive. Maximum and minimum values with respect to φ are given by

$$C_k \begin{cases} \text{max, } r > k \\ \text{min, } r < k \end{cases} = \frac{2r}{\pi(r+k)} \left| \frac{\sin \pi(r-k)}{r-k} \right|, \quad (26)$$

$$C_k \begin{cases} \text{max, } r < k \\ \text{min, } r > k \end{cases} = \frac{2k}{\pi(r+k)} \left| \frac{\sin \pi(r-k)}{r-k} \right|. \quad (27)$$

It may be shown that the minimum values decrease monotonically from unity to zero as $|r - k|$ increases from zero to unity. Maximum values increase somewhat as $|r - k|$ increases from zero and then decrease to zero as $|r - k|$ approaches unity. The first maximum value for $r > k$ occurs near

$$r - k = \frac{3}{2k\pi^2} \quad (28)$$

and is, approximately,

$$C_{k_{\max}, r > k} = 1 + \frac{3}{4k^2\pi^2} \quad (29)$$

Both of the expressions 26 and 27 have maxima near $|r - k| = n + 1/2$ for $|r - k| > 1$. The maximum values decrease in successive intervals as $|r - k|$ increases. Approximate behavior is sketched in Fig. 2.

Fig. 2

- f. For an estimate of the minimum energy in the spectral components adjacent to a given frequency $1/t$, assume r to be the arithmetic mean between two adjacent values of k . (Maximum energy in a given component occurs when r is approximately equal to a value of k . An attempt was made to solve for the minimum energy as a function of r . Expressions became quite complex, and the time for further investigation was not judged to be justified, since the result would likely be too complex for practical evaluation. The minimum energy will occur for a value of r near the mean value specified.)

Let

$$k_1 = r - q, \quad k_2 = r + q, \quad (30)$$

where

$$q = 0.5, 1.5, 2.5 \dots, r - 1.$$

The sum of two frequency components whose indexes are equally spaced about r is

$$C_{k_1}^2 + C_{k_2}^2 = \frac{2}{\pi^2 q^2} \left\{ 1 + \frac{q^2}{(4r^2 - q^2)^2} \cdot \left[4r^2 + q^2 + 2(4r^2 - q^2) \cos 2\varphi \right] \right\}. \quad (31)$$

The minimum value of this sum occurs for ϕ such that $\cos 2\phi = -1$. This value is

$$\left(c_{k_1}^2 + c_{k_2}^2 \right)_{\min} = \frac{2}{\pi^2 q^2} \left\{ 1 - \frac{q^2 (4r^2 - 3q^2)}{(4r^2 - q^2)^2} \right\}. \quad (32)$$

The second term in the braces is generally small compared to unity and is, approximately, $q^2/4r^2$. Values calculated from Eq. 32 are tabulated below:

Table 6

$\left(c_{k_1}^2 + c_{k_2}^2 \right)_{\min}$				
r	$q \rightarrow$	0.5	1.5	Σ
1.5		.789	-	-
2.5		.803	.083	.886
4.5		.808	.088	.896
6.5		.810	.089	.899
10.5		.811	.090	.900
∞		.811	.090	.901

g. Summary of Results When No Gap is Present in the Signal Cycle

The Fourier analysis of a sinusoid having random phase and period with respect to the interval over which the analysis is performed yields discrete frequency components having largest amplitudes in the neighborhood of the true frequency of the sinusoid. When the true frequency coincides with a Fourier harmonic, all power occurs in that Fourier harmonic. When the true frequency falls between two Fourier harmonics, power is dispersed in the Fourier harmonics over the entire spectrum. The power in the two harmonics adjacent to the true frequency varies between 80 and 100 per cent of the total power, depending principally upon the location of the true frequency with respect to the adjacent harmonics. Minimum power in the adjacent harmonics occurs when the true frequency lies approximately midway between these. The four frequencies nearest the true frequency contain between 90 per cent and 100 per cent of the total power.

2. Consider next the characteristics of the C_k when there is a blank space in the data period. Equation 11 is repeated here for convenient reference:

$$\begin{aligned} \pi^2 C_k^2 &= \frac{\sin^2 \pi(r-k)p}{(r-k)^2} + \frac{\sin^2 \pi(r+k)p}{(r+k)^2} \\ &- 2 \frac{\sin \pi(r-k)p}{r-k} \cdot \frac{\sin \pi(r+k)p}{r+k} \cos (2\pi rp + 2\phi) \end{aligned} \quad (11)$$

- a. When $|r-k| \ll r$, Eq. 11 simplifies to

$$C_k^2 = \frac{\sin^2 \pi(r-k)p}{(r-k)^2} \quad (33)$$

Errors introduced by neglecting the other terms of Eq. 11 will be disregarded in this section. These errors will be estimated in section e.

For convenience, let

$$d = 1 - p, \quad (34)$$

d representing the relative blank space in the period of the analysis.

From Eq. 12,

$$P \approx \frac{p}{2} = \frac{1-d}{2} \quad (35)$$

$$(1) \lim_{r \rightarrow k} C_k^2 = p^2 = (1-d)^2. \quad (36)$$

Designate this value of C_k^2 as C_r^2 , i.e.,

$$C_r^2 = (1-d)^2. \quad (37)$$

Then

$$\frac{C_r^2}{2P} = 1 - d. \quad (38)$$

(2) Let $k_1 = r - 1/2$, $k_2 = r + 1/2$. Then

$$C_{k_1}^2 + C_{k_2}^2 = \frac{4}{\pi^2} (1 + \cos \pi d). \quad (39)$$

$$\frac{C_{k_1}^2 + C_{k_2}^2}{2P} = \frac{4(1 + \cos \pi d)}{\pi^2(1-d)}. \quad (40)$$

For small values of d, the value of Eq. 38 decreases with increasing values of d, and the value of Eq. 40 increases with increasing d. The two values become equal for $d = 0.115$.

$$\left\{ \frac{C_r^2}{2P} = \frac{C_{k_1}^2 + C_{k_2}^2}{2P} \right\} = 0.885. \quad (41)$$

$$d = 0.115.$$

- b. The behavior of Eqs. 38 and 40 indicates that the amplitude uncertainty of a frequency component obtained from a data sequence by a method equivalent to the Fourier analysis may be reduced by the insertion of a blank space in the data period. To better establish this inference, let r have any value between indexes a and a + 1 of Fourier harmonics.

$$r = a + q. \quad (42)$$

$$0 \leq q \leq 1.$$

Using Eq. 33, the sum of the squared amplitudes of the two harmonics is

$$c_{a_1}^2 + c_{a_2}^2 = \frac{1 - \cos 2\pi q(1-d)}{2\pi^2 q^2} + \frac{1 - \cos 2\pi(1-q)(1-d)}{2\pi^2(1-q)^2}. \quad (43)$$

Using Eqs. 43 and 35, the relative power in the two harmonics is calculated for values of q and d and tabulated below:

Table 7

$$\frac{c_a^2 + c_{a+1}^2}{2P}$$

q	$d \rightarrow$	0.00	0.10	0.115	0.13	0.15	0.20
0.0		1.000	0.910	0.905	0.888	0.880	0.840
0.1		0.970	0.920	0.910	0.905	0.895	0.880
0.2		0.930	0.910	0.910	0.908	0.905	0.900
0.3		0.870	0.895	0.900	0.902	0.905	0.910
0.4		0.830	0.880	0.890	0.896	0.905	0.910
0.5		0.810	0.880	0.885	0.890	0.900	0.920

If the amplitude of a frequency component of a data sample is to be estimated from the two largest harmonics of a Fourier analysis, the insertion of a blank space of 10 percent to 15 percent of the analysis period reduces the uncertainty of the estimate from about 10 percent to 2 percent*. If the blank space is set to 13 percent, the amplitude uncertainty is reduced to 1 percent.

- c. To obtain an idea of the results if more than two harmonics are used to measure amplitudes, values of relative power were calculated for five cases.

- (1) The principal harmonic, $k = r$
- (2) The sum of two harmonics, $k_1 = r - 0.5$, $k_2 = r + 0.5$
- (3) The sum of three harmonics, $k_1 = r - 1$, $k_2 = r$, $k_3 = r + 1$
- (4) The sum of four harmonics

$$k_1 = r - 1.5, \quad k_2 = r - 0.5$$

$$k_3 = r + 0.5, \quad k_4 = r + 1.5$$

- (5) The sum of five harmonics

$$k_1 = r - 2, \quad k_2 = r - 1, \quad k_3 = r$$

$$k_4 = r + 1, \quad k_5 = r + 2.$$

* The amplitude error is about one-half of the power error.

Table 8

$$\frac{C_k^2}{2P}$$

$d r-k$	0.0	0.5	1.0	1.5	2.0
0.000	1.000	0.405	0.000	0.045	0.000
0.050	0.950	0.424	0.003	0.045	0.003
0.063	0.937	0.428	0.004	0.044	0.004
0.075	0.925	0.432	0.006	0.043	0.006
0.100	0.900	0.439	0.011	0.040	0.010
0.115	0.885	0.443	0.014	0.037	0.013
0.150	0.850	0.451	0.025	0.031	0.017
0.200	0.800	0.458	0.044	0.020	0.029
0.250	0.750	0.461	0.068	0.009	0.034

Table 9

$$\frac{\Sigma C_k^2}{2P}$$

$d r-k$	(1)	(2)	(3)	(4)	(5)
0.000	1.000	0.810	1.000	0.900	1.000
0.050	0.950	0.848	0.956	0.938	0.962
0.063	0.937	0.856	0.945	0.944	0.953
0.075	0.925	0.864	0.937	0.950	0.949
0.100	0.900	0.878	0.922	0.958	0.942
0.115	0.885	0.886	0.913	0.960	0.939
0.150	0.850	0.902	0.900	0.964	0.934
0.200	0.800	0.916	0.888	0.956	0.946
0.250	0.750	0.922	0.886	0.940	0.954

The values in Table 9 indicate that the optimum blank space for minimum variation in the sum changes with the number of harmonics included. No advantage is seen in including a large number of harmonics, and frequency resolution would be lost thereby.

- d. A method often used to obtain the frequency content of a data sequence is to record the data on a suitable medium, say magnetic tape, and then to close the ends of the recording to form a loop, the loop being cycled through a pickup and the signal fed into a harmonic analyzer. The analyzer contains either a band-pass filter whose center frequency may be varied, or a sequence of filters having different center frequencies. The filters may be capable of measuring individual harmonics or may have a pass-band covering several.

The preceding results show that the amplitude accuracy obtained in such analyses can be greatly improved by the insertion of a blank space in the data cycle. The optimum width of the space will depend upon the characteristics of the filter.

If the filter resolves individual harmonics and the actual amplitude is taken as proportional to the root mean square of the amplitudes of the two largest harmonics, a blank space of 12 to 15 per cent of the data cycle gives minimum uncertainty in the amplitude measurement.

If the filter passes several harmonics, the shape of the filter curve should be taken into account. This may be done by weighting the values of Table 8 by the filter curve, with the peak of the curve placed at r , and adding the results as was done (without weighting) to obtain Table 9. Table 8 may be extended if necessary until further harmonics become insignificant. The relative value of the blank space is taken as the value of d at which the values of the last two columns are equal. For sharply peaked filter curves, this value of d may not be obtainable. The filter curve should be rather flat over the width of two harmonics.

If, as often occurs, there are close-spaced frequencies or frequency drifts in the data sequence, it is desirable in many applications to have a filter passing essentially two or three harmonics and having a continuously variable center frequency. Such a filter would give nearly optimum frequency resolution but would not require the further interpretation needed if individual harmonics were measured.

e. Errors for Small Values of r

In preceding sections, the additional uncertainty arising when r is small was neglected. To estimate the limits of these errors, the following equation, corresponding to Eqs. 38 and 40 in section 2, was derived from Eqs. 11 and 12. In simplifying the expressions, it was assumed that $4r^2 \gg 1$. Terms having a maximum amplitude less than $1/4r^2$ compared to the dominant term were dropped.

$$\frac{C_r^2}{2P} = (1 - d) \left\{ \frac{1 + \frac{\sin 2\pi r d \cos(2\pi r d - 2\phi)}{\pi r(1 - d)}}{1 + \frac{\sin 2\pi r d \cos(2\pi r d - 2\phi)}{2\pi r(1 - d)}} \right\}. \quad (44)$$

$$\frac{C_{k_1}^2 + C_{k_2}^2}{2P} = \frac{4(1 + \cos \pi d)}{\pi^2(1 - d)} \left\{ \frac{1 + \frac{\sin \pi d \sin 2\pi r d \cos(2\pi r d - 2\phi)}{2r(1 + \cos \pi d)}}{1 + \frac{\sin 2\pi r d \cos(2\pi r d - 2\phi)}{2\pi r(1 - d)}} \right\}. \quad (45)$$

The relative error term in Eq. 44 is, approximately,

$$\left| \frac{\sin 2\pi r d \cos(2\pi r d - 2\phi)}{2\pi r(1 - d)} \right| \leq \frac{1}{2\pi r(1 - d)}. \quad (46)$$

For $r \geq 5$ and $d \leq 0.2$, the maximum error is less than 4 per cent (2 per cent in amplitude), decreasing with increasing r .

The relative error term in Eq. 45 is, approximately,

$$\left| \frac{1}{2r} \left\{ \frac{\sin \pi d}{1 + \cos \pi d} - \frac{1}{\pi(1 - d)} \right\} \sin 2\pi r d \cos(2\pi r d - 2\phi) \right| \leq \frac{1}{2r} \left| \tan \frac{\pi d}{2} - \frac{1}{\pi(1 - d)} \right|. \quad (47)$$

Table 10

d	$\tan \frac{\pi d}{2} - \frac{1}{\pi(1-d)}$
0.00	-.318
0.10	-.128
0.15	-.031
0.20	.070
0.25	.175

For $r > 5$ and $0.1 \leq d \leq 0.2$, the maximum error is less than 1.5 per cent.

For $r > 5$, the maximum error in the other terms dropped in deriving Eqs. 44 and 45 is about 1 per cent. Thus the maximum error in Eqs. 38 and 40, caused by omission of the smaller terms, is less than 5 per cent, giving an amplitude uncertainty of less than 2.5 per cent.

f. Summary

If the frequency content of a data sequence is to be measured by a method equivalent to a Fourier analysis, insertion of the proper blank space in the period of the analysis greatly reduces the uncertainty in the amplitudes of the frequency components. If the frequency components are well separated so that overlapping of harmonics from adjacent frequencies is insignificant, the maximum theoretical error will not exceed five per cent for frequencies having at least five cycles in the data sequence.

3. To obtain some idea of the characteristics of the C_k when the data sequence is a small part of the period of analysis, assume that r is large. For values of k near r , Eq. 11 simplifies to

$$C_k^2 \approx \frac{\sin^2 \pi(r-k) p}{\pi^2 (r-k)^2} \approx p^2. \quad (48)$$

The C_k are nearly independent of k .

Fourier analysis is not a satisfactory method for obtaining frequency information under these conditions. The data sequence may be considered as a transient phenomenon and analyzed accordingly. For example, a filter could be used to scan the data, its output being fed into a peak-reading voltmeter. This approach is completely different from that of the preceding problems, and will not be considered herein.

* * * * *

There are several points in the preceding analyses from which further investigations could start, perhaps leading to useful results. Results in general would have more specialized applications. Since the results obtained are satisfactory for the present purpose, no further study is undertaken now.

R. M. McGEHEE - 5413

Case No. 414.00

May 10, 1955

325 028

THIS PAGE
WAS INTENTIONALLY
LEFT BLANK