74

This is a preprint of a paper intended for publication in a journal or proceedings. Since changes may be made before publication, this preprint is made available with the understanding that it will not be cited or reproduced without the permission of the author.

UCRL -76702
PREPRINT

Conf-741113--13

LAWRENCE LIVERMORE LABORATORY
University of California/Livermore, California

OPTICAL PULSE COMPRESSION

A. J. Glass

April 16, 1975

MASTER

NOTICE
This report was prepared as an account of work sponsored by the United States Government. Neither the United States nor the United States Energy Research and Development Administration, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness or usefulness of any information, apparatus, product or process disclosed, or represents that its use would not infringe privately owned rights.

This paper was prepared for submittal to the Proceedings of the International Conference on Energy Storage, Compression, and Switching, held on November 5-7, 1974, in Torino, Italy.

OPTICAL PULSE COMPRESSION

A. J. Glass

Lawrence Livermore Laboratory, University of California
Livermore, California 94550

ABSTRACT

The interest in using large lasers to achieve a very short and intense pulse for generating fusion plasma has provided a strong impetus to re-examine the possibilities of optical pulse compression at high energy.

Pulse compression allows one to generate pulses of long duration (minimizing damage problems) and subsequently compress optical pulses to achieve the short pulse duration required for specific applications. The ideal device for carrying out this program has not been developed.

Of the two approaches considered in this report, the Gires-Tournois approach is limited by the fact that the bandwidth and compression are intimately related, so that the group delay dispersion times the square of the bandwidth is about unity for all simple Gires-Tournois interferometers. The Treacy grating pair does not suffer from this limitation, but is inefficient because diffraction generally occurs in several orders and is limited by the problem of optical damage to the grating surfaces themselves.

Nonlinear and parametric processes have been explored. Some pulse compression has been achieved by these techniques; however, they are generally difficult to control and are not very efficient.

INTRODUCTION

The subject of this paper is the storage, compression, and switching of energy in the form of electromagnetic waves of optical frequency, that is to say, light waves. We particularly emphasize the concept of optical pulse compression.^{1,2}

In any pulse compression scheme the bandwidth of the system limits the degree of compression. The compression of pulses of energy that travels in the form of waves is therefore limited by the frequency of the carrier. The advent of lasers, sources of coherent light, induces us to examine the possibility of performing pulse compression using light waves as carriers. The objective is, of course, to compress optical energy in time,

the light wave with the nominally transparent medium.³ A way of reducing this self-damage phenomenon is to stretch out the optical pulse and thereby lower the peak field at a given energy density. For efficiency, one would like to extract as much of the stored energy from the laser as possible. This requires that the laser be saturated; that is to say, that the energy density extracted from the laser be greater than the saturation energy density characteristic of the laser medium. However, in achieving this high energy density in a short pulse, we must be careful not to exceed the damage threshold of the laser medium.

There are four principal reasons for compressing optical pulses and, as shown below, they are primarily associated with very high-power lasers:

- The principal failure mode of high-power lasers is the destruction of the laser elements by the interaction of the intense electric field of

- In many applications, for example laser fusion, a short pulse duration is required and we quickly find that we are unable to achieve efficient energy extraction consistent with the required pulse duration. Again, a solution to this impasse is to generate a long pulse in which the energy can be efficiently and safely extracted from the laser amplifiers,

and subsequently compress the pulse.

- The original motivation for optical pulse compression, and the only application to which this concept has been applied, is to correct for the self-phase modulation induced in large laser amplifiers by the passage of the intense light and thereby to achieve bandwidth-limited pulses of extremely short duration.
- Finally, some applications require selecting a small fraction of a pulse and compressing it in time to have a synchronous probe for diagnostic purposes. This is particularly true in experiments like laser fusion.

PULSE COMPRESSION SCHEMES

There are certain common features of all pulse compression schemes. First of all, the pulse to be compressed must be coded; i.e., each temporal element of the pulse must be tagged or identified in some way. Four possible ways to code a pulse are as follows: associating each element of time with its separate frequency; splitting the pulse into a number of elements, each of which propagates at a different angle or in a different direction; associating each element of the pulse with a different polarization state; and coding the pulse by using its intensity variation if the application allows intensity-dependent effects for pulse compression.

Once the coding is impressed on the pulse, a selective or dispersive group delay element is introduced into the system. This is an element through which the time for the passage of the pulse depends on the coding. Finally, to achieve ideal compression of the pulse, we arrange the coding and the dispersive element so that all pieces of the pulse emerge from the dispersive element at the same time.

DISCRETE CODING SYSTEM

In Fig. 1 we see one example of a pulse compressor. Here we have illustrated an angular or direction-sensitive coding scheme. The initial pulse is divided into a number of discrete elements, each of these elements is propagated along a slightly different path through the

amplifier. The dispersive element that is introduced into this system is illustrated as a stacker in Fig. 1. When the pulse elements emerge from the amplifier, a system of beam splitters is used to recombine the separate pieces of the original pulse along a single propagation path. The delay times in the stacker are arranged to cause the various elements of the pulse emerging from the amplifier at different times, to emerge from the stacker simultaneously.

The disadvantage of a discrete coding system is that the compression ratio is greatly limited. The shortest pulse that can be achieved is no shorter than the duration of the individual elements. Also, beam splitters are very vulnerable to optical damage at high energy.

NONLINEAR PULSE COMPRESSION SCHEME

An example of a nonlinear pulse compression scheme is seen in Fig. 2. Here a short pulse, identified as the signal, is injected on one side into one end of a parametric amplifier and into the other end is injected a long pulse identified as the pump pulse. The parametric medium is chosen in such a way that the two pulses interact and the energy from the pump pulse is converted to the optical frequency of the signal pulse. The pulse which emerges is a highly amplified short pulse having the duration of the original injected signal, but carrying the energy of the long pump pulse. An example of such a device is the backward traveling Raman amplifier in which the parametric process is stimulated Raman scattering.⁴

The disadvantages of such a system are the intrinsic difficulty of controlling nonlinear processes and the requirement for a complicated system of beam splitters and dichroic elements for bringing the

Fig. 1. Angular stacker.

Fig. 2. Parametric converter.

pump and signal pulses into the medium from opposite ends and separating them after they have emerged from the parametric medium.

CONTINUOUS FREQUENCY CODING

The most commonly used technique of optical pulse compression is based on continuous frequency coding of the optical pulse. There is a slightly different value of the carrier frequency associated with each time element of the pulse. The optical frequency varies monotonically as a function of time through the pulse. This is known as chirping.

The chirp can be achieved by one of two methods, it can be self-generated by the nonlinear interaction of the pulse with the optical medium itself or it can be externally generated by means of an electro-optic shutter.^{5,6} The requirements on a dispersive delay line for optical pulse compression are precisely the same as the requirements for a high-resolution optical spectrometer. Two types of devices are commonly used. One is a totally reflecting Fabry-Perot resonator, first proposed by Gires and Tournais.⁷ The other is a pair of diffraction gratings, first proposed by Treacy.⁸ We shall discuss the special features of each of these devices.

We assume that the compressor is a loss-free device and therefore associated only with a frequency-dependent phase shift. If we inject an optical electric field E_0 at frequency ω then the field emerging from the device at frequency ω is identified as $E_1(\omega)$. We write the output wave in the form

$$E_1(\omega) = E_0(\omega) \exp(i\Phi(\omega)), \quad (1)$$

where $\Phi(\omega)$ is the phase shift in the device. As long as the chirp bandwidth is much less than the optical frequency, writing $\omega = \omega_0 + \nu$, we find

$$\Phi(\omega) = \Phi(\omega_0) + Q_1 \nu + Q_2 \nu^2/2 + \dots, \quad (2)$$

where the group delay $Q_1 = (d\Phi/d\omega)$ at $\omega = \omega_0$, and the group delay dispersion $Q_2 = (d^2\Phi/d\omega^2)$ at $\omega = \omega_0$.

If we neglect the effects of bandwidth, we can think of the optical pulse entering the compressor as made up of a series of packets of energy, each impressed on a carrier wave of a slightly different frequency. Each of these packets moves through the compressor at a slightly different speed, experiencing a slightly different delay. In this approximation, the output intensity is given by

$$I_1(t_1) = \int dt_0 I_0(t_0) \delta(t - t_0 + Q_1 + Q_2 \nu). \quad (3)$$

Here we assume that each group travels independently in time.

For a linear chirp, the frequency offset $\nu = \beta t_0$ and

$$I_1(t_1) = \int d\nu I_0(\nu) \delta\left(\nu - \frac{\beta(t_1 - Q_1)}{1 + \beta Q_2}\right). \quad (4)$$

If we examine the δ function carefully we see that the best compression can be achieved in those circumstances in which the denominator of the second term, $1 + \beta Q_2$, vanishes. Under these circumstances, the entire pulse will emerge at the time $t_1 = Q_1$, the average group delay through the compressor. The optimal compression criteria is thus given by the relation $\beta Q_2 = -1$.

In the more exact Fourier analysis of the problem, we express the chirped input pulse as

$$E_0(t_0) = A_0(t_0) \exp(i\beta t_0^2/2). \quad (5)$$

The output pulse takes the form

$$E_1(t) = \frac{1}{2\pi} \exp(i\Phi(\omega_0)) \int dt_0 A_0(t_0) \times \exp(i\beta t_0/2) \int d\nu \exp(iQ_2 \nu^2/2) \times \exp(i\nu(t - t_0 + Q_1)), \quad (6)$$

where the frequency integral is taken over the range of frequencies for which Q_2 is sensibly constant. A careful analysis of the pulse compression by this approach leads to the not surprising conclusion that the final pulse duration that can be achieved in any pulse compression device is limited to the inverse of the bandwidth, where the bandwidth is determined either by the range over which the frequency is chirped or the range over which the group delay dispersion can be treated as constant.

From these simple considerations we can obtain a figure of merit for any compression scheme. We identify T_0 as the initial duration of the input pulse and T_1 as the final duration of the compressed pulse. As we have just seen, the final duration T_1 is given by the reciprocal of the compressor bandwidth that, for a linear chirped pulse, is simply the reciprocal of the product of the chirp coefficient β and the initial pulse duration T_0 .

To obtain optimal compression, the group delay dispersion must be equal to $-1/\beta$, which from the previous analysis is simply $-T_0 T_1$. This expression is incomplete, since if $Q_2 = 0$, no compression results, and $T_0 = T_1$. We therefore write the optimal compression condition in the form $Q_2 \sim -(T_0 - T_1) T_1$. Multiplying this expression by the square of the bandwidth, we arrive at a dimensionless compression ratio given by $C = (T_0 T_1)^{-1}$, for optimal design. For high compression, $T_0 \gg T_1$ and C is just the compression ratio. Let us now discuss the dimensionless compression ratio C for the Gires-Tournois and grating pair compressions.

Gires-Tournois Approach. The Gires-Tournois interferometer has been extensively discussed in the literature.^{2,7} It consists of a fully reflecting, Fabry-Perot interferometer. The group delay dispersion in this device is given by

$$Q_2 = -\frac{2}{t_0} \frac{(1-r^2)}{4r} \frac{\sin \omega t_0}{\left[\left(\frac{1+r^2}{2r} \right) - \cos \omega t_0 \right]^2} \quad (7)$$

The back surface is assumed to be 100% reflecting. As we raise the reflectivity of the front surface of the device the maximum value of Q_2 increases. However, it turns out that the bandwidth decreases

as we raise the finesse of the interferometer in such a way that the dimensionless compression ratio C is always approximately equal to unity, independent of variation of the design parameters. Thus to achieve significant compression using the Gires-Tournois approach, a large number of interferometers are required. This leads to significant problems in the alignment of the device.

In Fig. 3 we see the functional form of the frequency dependence of the dispersive group delay, Q_2 . Here, for each value of the amplitude reflectivity r , Q_2 is normalized to its maximum value. As the reflectivity is increased, the maximum value increases, but as we can see from Fig. 3, the response curve becomes narrower in frequency. Numerical evaluation of these cases shows that the product of Q_2 times the square of the bandwidth is approximately 1, independent of the value of reflectivity. Here the bandwidth is defined as the frequency range over which the dispersive group delay Q_2 differs from its maximum value by no more than a factor of 2.

Treacy Approach. Treacy has proposed a pulse compression scheme based on a pair of diffraction gratings. Light is incident on the first diffraction grating blazed for efficient diffraction in a given order. The second grating is adjusted to recollimate the light, so that all frequencies emerge on parallel paths. A diagram of the grating pair is shown in Fig. 4. The group delay dispersion is given by

$$Q_2 = \frac{B t_0}{c} \left[(\omega t_0 \cos \gamma)^2 + 2\omega t_0 \sin \gamma - 1 \right]^{-3/2} \quad (8)$$

Fig. 3. Gires-Tournois response.

where the parameters are defined in Fig. 4.

Unlike the Gires-Tournois device, the grating pair is not limited in bandwidth. The group delay dispersion, Q_2 , can be increased independently of the bandwidth by the simple expedient of increasing the separation between the gratings. The grating pair is a strongly dispersive device, however. Figure 5 is a graph of Q_2/Bt_0 vs ωt_0 , plotted on a logarithmic scale to show how strongly the group delay dispersion Q_2 varies as a function of frequency. The dimensionless quantity, Q_2/Bt_0 , is effectively the group delay dispersion normalized in units involving the grating separation and grating spacing, and ωt_0 is the product of the carrier frequency times the characteristic time. The different values of the angle of incidence are represented by the different curves in Fig. 5. Despite the strong frequency dependence of the group delay dispersion in this device, the bandwidth limitation is not severe. Instead compression is limited by the range over which the pulse can be chirped and ultimately by the problem of overlapping orders of diffraction in the gratings themselves.

The grating pair has been used for the compression of ultrashort optical pulses. Pulses with initial durations of a few picoseconds have been compressed to durations as short as 10^{-13} sec to what

$$D = \frac{B}{C} \left[(\omega t_0 \cos \gamma)^2 + 2 \omega t_0 (\sin \gamma - 1) \right]^{-1/2}$$

B = Grating separation
 γ = Angle of incidence
d = Grating spacing
m = Diffraction order
 $t_0 = d/c$

Fig. 4. Grating pair. Bandwidth limitation is not severe. The quantity Q_2 can be increased independently of bandwidth by increasing B.

seemed to be bandwidth-limited pulses. Pulse compressions in the approximate range of 5 to 10 have been achieved. These were, however, pulses of low intensity and the measurements were carried out in a qualitative fashion.

SUMMARY

The compression of optical pulses is particularly suited to applications associated with high-power lasers. In this cursory survey of optical pulse compression, we examined the methods of pulse compression and the features common to all schemes. Of the schemes available, we emphasized the Gires-Tournois and the Treacy approaches, pointing out the advantages and disadvantages of each.

ACKNOWLEDGMENTS

This work was performed under the auspices of the U.S. Energy Research & Development Administration. It is a great pleasure to acknowledge fruitful discussions of the problems of pulse compression with Robert Fisher of the Los Alamos Scientific Laboratory and Roy Bastian of the Perkin-Elmer Corporation.

REFERENCES

1. J. A. Giordmaine, M. A. Duguay, and J. W. Hansen, *IEEE J. Quantum Electron.*, **QE-4**, 252 (1968).
2. A. Lauberau and D. von der Linde, *Z. Naturforsch.*, **25a**, 1626 (1970).

Fig. 5. Dependence of Q_2 on frequency.

3. A. J. Glass and A. H. Guenther, Laser Interaction and Related Phenomena, H. J. Schwartz and H. Hora, Eds., (Plenum Press, New York, 1974).
4. M. Maier, W. Kaiser, and J. A. Giordmaine, Phys. Rev. 177, 580 (1969).
5. R. A. Fisher and W. K. Bischel, Bull. Am. Phys. Soc. 18, 1586 (1973); Appl. Phys. Lett. 24, 468 (1974).
6. E. B. Treacy, Phys. Lett. A28, 34 (1968).
7. F. Gires and P. Tournois, C. R. Acad. Sci. 258, 6112 (1964).
8. E. B. Treacy, IEEE J. Quantum. Electron. QE-5, 454 (1969).

NOTES

"This report was prepared as an account of work sponsored by the United States Government. Neither the United States nor the United States Energy Research & Development Administration, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness or usefulness of any information, apparatus, product or process disclosed, or represents that its use would not infringe privately owned rights."