**Westinghouse
Astronuclear
Laboratory**

WANL-TME-2691
MAY 1970

DATA ITEM S-54

**STRUCTURAL SUPPORT COOLANT
VALVE ACTUATOR**

TRADE STUDY NO. 755

MASTER

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency Thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

Westinghouse Astronuclear Laboratory

Subcontract NP-1

CODE IDENT NO. 14683

WANL-TME-2691
MAY 1970

DATA ITEM S-54

STRUCTURAL SUPPORT COOLANT

VALVE ACTUATOR

TRADE STUDY NO. 755

NOTICE

This report contains information of a preliminary nature and was prepared primarily for internal use at the originating installation. It is subject to revision or correction and therefore does not represent a final report. It is passed to the recipient in confidence and should not be abstracted or further disclosed without the approval of the originating installation or USAEC Technical Information Center, Oak Ridge, TN 37830

APPROVED BY:

F. D. Retallick
F. D. Retallick, Manager
NERVA Engineering

INFORMATION CATEGORY

UNCLASSIFIED

AUTHORIZED CLASSIFIER

DATE

DISTRIBUTION OF THIS

SC

PAGE BLANK

ABSTRACT

Eleven actuator concepts for application as a Structural Support Coolant Valve Actuator (SSCVA) and one single system concept as a complete structural Support Supply System are evaluated. The 11 actuators are either pneumatic or electric and the single system concept is fluidic. Conceptual drawings are included for each concept. Failure mode analysis, fault tree analysis and safety analysis are performed on each concept. In addition, qualitative evaluations are made by WANL structural, thermal and radiation disciplines. A comparison matrix is included to summarize all of the pertinent information about each concept. Selected parameters such as weight, reliability, safety, experience and performance are used to select one concept of each type as the recommended approach.

Westinghouse recommends a Permanent Magnet Rotor Electric Stepper Motor as the electrically-operated selection and a Single Piston Rack and Pinion as the pneumatically operated selection.

Because of the anticipated future potential of an all-fluidic SSCVA system, Westinghouse further recommends that continuing assessment and development be carried out to determine its applicability and merits.

PAGE BLANK

TABLE OF CONTENTS

<u>Section</u>	<u>Page</u>
1.0 PURPOSE OF THE SSCV ACTUATOR TRADE STUDY No. 755	1-1
1.1 Functional Design Requirements	1-2
1.2 Technical Design Requirements	1-2
2.0 DESCRIPTION OF DESIGN APPROACHES	2-1
2.1 Rack and Pinion Proportional Pneumatic Concept	2-1
2.1.1 Mechanical Description	2-1
2.1.2 System Description	2-7
2.1.3 Radiation Evaluation	2-10
2.1.4 Thermal Evaluation	2-13
2.1.5 Structural Evaluation	2-14
2.1.6 Radiation Effects Evaluation	2-14
2.1.7 Reliability and Safety Evaluation	2-16
2.1.8 Evaluation of Concept	2-35
2.2 Helical CAM Proportional Pneumatic Concept	2-36
2.2.1 Mechanical Description	2-36
2.2.2 System Description	2-39
2.2.3 Radiation Evaluation	2-39
2.2.4 Thermal Evaluation	2-42
2.2.5 Structural Evaluation	2-42
2.2.6 Radiation Effects Evaluation	2-42
2.2.7 Reliability and Safety Evaluation	2-43
2.2.8 Evaluation of Concept	2-55

TABLE OF CONTENTS (CONTINUED)

<u>Section</u>	<u>Page</u>
2.3 Dynavector Proportional Concept	2-56
2.3.1 Mechanical Description	2-56
2.3.2 System Description	2-56
2.3.3 Radiation Evaluation	2-60
2.3.4 Thermal Evaluation	2-60
2.3.5 Structural Evaluation	2-61
2.3.6 Radiation Effects Evaluation	2-61
2.3.7 Reliability and Safety Evaluation	2-61
2.3.8 Discussion and Evaluation	2-71
2.4 Electric Stepping Motor Proportional Concept	2-72
2.4.1 Responsyn Concept	2-74
2.4.1.1 Mechanical Description	2-74
2.4.1.2 System Description	2-74
2.4.1.3 Radiation Evaluation	2-77
2.4.1.4 Thermal Evaluation	2-77
2.4.1.5 Structural Evaluation	2-77
2.4.1.6 Radiation Effects Evaluation	2-78
2.4.1.7 Reliability and Safety Evaluation	2-80
2.4.1.8 Evaluation of Concept	2-93
2.4.2 Slo-Syn Concept	2-96
2.4.2.1 Mechanical Description	2-96
2.4.2.2 System Description	2-96
2.4.2.3 Radiation Evaluation	2-96

TABLE OF CONTENTS (CONTINUED)

<u>Section</u>	<u>Page</u>
2.4.2.4 Thermal Evaluation	2-100
2.4.2.5 Structural Evaluation	2-100
2.4.2.6 Radiation Effects Evaluation	2-100
2.4.2.7 Reliability and Safety Evaluation	2-102
2.4.2.8 Evaluation of Concept	2-109
2.4.3 Dynavector Concept	2-111
2.4.3.1 Mechanical Description	2-111
2.4.3.2 System Description	2-111
2.4.3.3 Radiation Evaluation	2-114
2.4.3.4 Thermal Evaluation	2-114
2.4.3.5 Structural Evaluation	2-114
2.4.3.6 Radiation Effects Evaluation	2-116
2.4.3.7 Reliability and Safety Evaluation	2-117
2.4.3.8 Discussion and Evaluation of Concept	2-125
2.4.4 Permanent Magnet Rotor Electric Stepper Motor Concept	2-125
2.4.4.1 Mechanical Description	2-125
2.4.4.2 System Description	2-125
2.4.4.3 Radiation Evaluation	2-127
2.4.4.4 Thermal Evaluation	2-127
2.4.4.5 Structural Evaluation	2-129
2.4.4.6 Radiation Effects Evaluation	2-130
2.4.4.7 Reliability and Safety Evaluation	2-130
2.4.4.8 Evaluation of Concept	2-138

TABLE OF CONTENTS (CONTINUED)

<u>Section</u>		<u>Page</u>
2.5	AC Servomotor Proportional Concept	2-139
2.5.1	Mechanical Description	2-139
2.5.2	System Description	2-139
2.5.3	Radiation Evaluation	2-143
2.5.4	Thermal Evaluation	2-143
2.5.5	Structural Evaluation	2-143
2.5.6	Radiation Effects Evaluation	2-144
2.5.7	Reliability and Safety Evaluation	2-145
2.5.8	Evaluation of Concept	2-153
2.6	DC Motor Proportional Concept	2-154
2.6.1	Mechanical Description	2-154
2.6.2	System Description	2-154
2.6.3	Radiation Evaluation	2-158
2.6.4	Thermal Evaluation	2-158
2.6.5	Structural Evaluation	2-158
2.6.6	Radiation Effects Evaluation	2-159
2.6.7	Reliability and Safety Evaluation	2-160
2.6.8	Evaluation of Concept	2-168
2.7	Fluidic System Concept	2-169
2.7.1	Mechanical Description	2-172
2.7.2	System Description	2-176
2.7.3	Radiation Evaluation	2-176
2.7.4	Thermal Evaluation	2-178
2.7.5	Structural Evaluation	2-178

TABLE OF CONTENTS (CONTINUED)

<u>Section</u>	<u>Page</u>
2.7.6 Radiation Effects Evaluation	2-178
2.7.7 Reliability and Safety Evaluation	2-178
2.7.8 Evaluation of Concept	2-186
3.0 COMPARISON MATRIX OF DESIGN APPROACHES	3-1
4.0 SELECTION OF DESIGN APPROACH, CONCLUSIONS	
4.1 Fluidic Concept	4-3
4.2 Selection of an Analog Concept	4-3
4.2.1 Selection of an Analog Electric Actuator	4-4
4.2.2 Selection of an Analog Pneumatic Actuator	4-4
4.3 Final Actuator Selection	4-4
5.0 REFERENCES	5-1

PAGE BLANK

LIST OF ILLUSTRATIONS

<u>Figure</u>		<u>Page</u>
2-1	Actuator System Concepts	2-2
2-2	Pneumatic Rack and Pinion Actuator, Single Piston	2-4
2-3	Pneumatic Rack and Pinion Actuator - XE Type	2-5
2-4	Pneumatic Rack and Pinion - 1st Redesign	2-6
2-5	Actuator Single Piston Rack and Pinion Schematic	2-8
2-6	Rack and Pinion Proportional Pneumatic Actuator System Block Diagram	2-9
2-7	Proportional Pneumatic SSCV Actuator	2-11
2-8	Single Piston Rack and Pinion SSCV Actuator Summary Fault Tree	2-17
2-9	Two Piston Rack and Pinion Summary Fault Tree	2-27
2-10	Helical Cam Proportional Pneumatic Actuator	2-38
2-11	Helical Cam Proportional Pneumatic Actuator Schematic	2-40
2-12	Helical Cam Proportional Pneumatic Actuator System Block Diagram	2-41
2-13	Helical Cam Pneumatic SSCV Actuator Summary Fault Tree	2-44
2-14	Proportional SSCV Actuator Pneumatic Dynavector Concept	2-58
2-15	Dynavector Proportional Pneumatic Actuator System Block Diagram	2-59
2-16	Dynavector Pneumatic SSCV Actuator Summary Fault Tree	2-62

LIST OF ILLUSTRATIONS (CONTINUED)

<u>Figure</u>		<u>Page</u>
2-17	Responsyn Stepping Motor	2-75
2-18	Proportional Electrical Responsyn Direct Drive SSCV Actuator Concept	2-76
2-19	Responsyn Stepping Motor Electric Actuator Summary Fault Tree	2-81
2-20	Responsyn Electric Stepping Motor Planetary Drive Summary Fault Tree	2-82
2-21	Proportional Electric Slo-Syn Motor SSCV Actuator, Harmonic Drive	2-98
2-22	Harmonic Drive Transmission	2-99
2-23	Harmonic Drive/Slo-Syn Stepping Motor Summary Fault Tree	2-103
2-24	Proportional Electric Dynavector SSCV Actuator Concept	2-113
2-25	Dynavector Stepping Motor Electrical Actuator Summary Fault Tree	2-115
2-26	Proportional Electric PM Stepping Motor SSCV Actuator Harmonic Drive	2-128
2-27	Summary Fault Tree Permanent Magnet Rotor Stepping Motor	2-132
2-28	Proportional Electric AC Motor SSCV Actuator, Harmonic Drive	2-141
2-29	AC Servomotor Proportional SSCV Actuator System Block Diagram	2-142
2-30	Summary Fault Tree AC Motor Harmonic Drive Concept	2-151

LIST OF ILLUSTRATIONS (CONTINUED)

<u>Figure</u>		<u>Page</u>
2-31	Proportional SSCV Actuator DC Motor Electric Concept	2-156
2-32	DC Servomotor Proportional SSCV Actuator System	2-157
2-33	DC Motor Proportional Electric Actuator Summary Fault Tree	2-166
2-34	Fluidic Breakdown of System Concept Configuration	2-173
2-35	Fluidic System Concept	2-174
2-36	Diverter Subassembly	2-175
2-37	Fluidic SSCSS Control Block Diagram	2-177

LIST OF TABLES

<u>Table</u>		<u>Page</u>
2-1	Pertinent Drawings Relating to Each Study Concept	2-3
2-2	Nominal Radiation Environment at Actuator Location Forward of Pressure Vessel Closure	2-12
2-3	Detailed Fault Tree Analysis (Single Piston Pneumatic SSCV Actuator)	2-19
2-4	Single Piston, Rack and Pinion Pneumatic Actuator Summary Table	2-37
2-5	Detailed Fault Tree Analysis (Helical Cam Pneumatic Actuator)	2-45
2-6	Helical Cam Pneumatic Actuator Summary Table	2-57
2-7	Detailed Fault Tree Analysis (Dynavector Pneumatic Actuator)	2-63
2-8	Pneumatic Dynavector SSCV Actuator Summary Table	2-73
2-9	Detailed Fault Tree Analysis (Responsyn Direct Drive)	2-83
2-10	Detailed Fault Tree Analysis (Responsyn Planetary)	2-87
2-11	Direct Drive Responsyn SSCV Actuator Concept Summary Table	2-95
2-12	Planetary/Responsyn SSCV Actuator Concept Summary Table	2-97
2-13	Detailed Fault Tree Analysis (Slo-Syn Electric Stepping Motor)	2-104

LIST OF TABLES (CONTINUED)

<u>Table</u>		<u>Page</u>
2-14	Slo-Syn/Harmonic Drive SSCV Actuator Summary Table	2-112
2-15	Detail Fault Tree Analysis (Electric Dynavector Actuator)	2-118
2-16	Dynavector/Direct Drive SSCV Electric Actuator Summary Table	2-126
2-17	Detailed Fault Tree Analysis (Permanent Rotor Stepping Motor)	2-133
2-18	Permanent Magnet Stepper/Harmonic Drive SSCV Actuator Concept Summary Table	2-140
2-19	Detailed Fault Tree Analysis (AC Motor)	2-146
2-20	AC Servomotor SSCV Actuator Concept Summary Table	2-155
2-21	Detailed Fault Tree Analysis (DC Motor SSCVA)	2-161
2-22	DC Servo/Harmonic Drive SSCVA Actuator Concept Summary Table	2-170
2-23	Detailed Fault Tree Analysis Fluidic Concept	2-180
2-24	Component Failure Mode Analysis Fluidic Control Concept	2-182
2-25	Component Safety Criticality Fluidic Control Concept	2-187
3-1	Structural Support Coolant Valve Actuator Trade Study-Parameter Value Estimate Matrix	3-2
4-1	Structural Support Coolant Valve Actuator Trade Study-Summary Evaluation Matrix	4-2

1.0 PURPOSE OF THE SSCV ACTUATOR TRADE STUDY NO. 755

The actuator concepts selected for this trade study are those which exemplify a basic type or a particular design considered feasible for NERVA application. The specific goal of the trade study is to determine which of these actuator mechanism concepts would be the best candidate for development to eventually meet the program requirements. Other trade studies¹ have been addressed to the problem of specific types of Structural Support Coolant Supply Systems (SSCSS). Therefore, it is possible that the results of other studies may affect the actuator requirements. The actuator trade study is accomplished on the basis of the reference nuclear subsystem (NSS) design² which requires a proportional actuator device. Only those features that influence actuator performance parameters or can be classified as physical parameters, or affect the reliability of the actuator system, as it applies to the performance of its designated function in the nuclear subsystem, are considered in this trade study.

Certain physical features such as size and weight should be minimized with due consideration to the ultimate vehicle payload. Certain of these features, for all concepts considered, can be designed to meet the physical requirements and constraints imposed by the NSS.

The performance requirements for the Structural Support Coolant Valve (SSCV) Actuator have not been completely defined or established. Some required performance parameters have been identified in CP-677575, CP-677576, and DRM-51414, such as angular velocity, angular acceleration, bandwidth, torque, and resolution. In most cases, these parameters have been quantitatively defined but the values given are not presently appropriate. The reason for the lack of absolute values is that no valve design and insufficient valve data are available to allow a competent, realistic value to be obtained for most actuator performance requirements. To circumvent this problem, for the purpose of obtaining a trade study, a "best judgment" value is assigned for each performance parameter, obtained from available documentation, that can be regarded as questionable. Each actuator design concept considered in this trade study can be optimized to meet the performance and environmental requirements as imposed by the final design of the NSS. After the final SSCV design is selected and the operating characteristic of flow load versus input shaft position is known, the best judgment values used for the trade study can be re-evaluated and the selections updated.

In addition to dynamic performance, operating and storage environments and reliability are included as important factors of the trade study. Past tests and preliminary engineering estimates indicate that the environmental conditions (vibration, shock, radiation, temperature, etc.) impose a more formidable problem in design, to reliably obtain the required performance of an actuator mechanism, than that of obtaining adequate structural strength capability. In general, the materials used in the actuator mechanisms are not required to perform near their operating limits and are not considered to be a severe or limiting design consideration. In contrast, the apportioned reliability goal for an SSCV actuator system is considered to be an unprecedented value and the prime factor requiring major design efforts. Analytical evaluation of an actuator's reliability can be accomplished on a component-by-component basis allowing for a prediction of actuator system reliability. However, the ultimate reliability can only be conclusively proven through an extensive and lengthy reliability test program. For the purpose of this trade study, the reliability of each actuator concept is estimated and that estimate is used as an input to the final selection of a candidate.

1.1 FUNCTIONAL DESIGN REQUIREMENTS

The functional design requirements of the SSCV actuator system are as follows.

1.1.1 The actuator system must move and maintain the SSCV position in response to a command from the reactor control system³.

1.1.2 The actuator system must accomplish the required dynamic performance with the reliability specified within the environmental conditions and operating conditions of the NERVA Nuclear Subsystem Specification CP-677555⁴.

1.2 TECHNICAL DESIGN REQUIREMENTS

The following requirements are selected from the Structural Support and Coolant Supply (SSCSS) Specification, CP-677575³, dated January 23, 1969, and from the Structural Support Coolant Valve (SSCV) Actuator System Specification, EC-677576⁵, dated June 7, 1968.

The quantitative values obtained from each of the applicable specifications are not currently applicable. The values, as indicated in the specifications, are based upon a particular SSCV that is no longer considered as the primary valve candidate. The estimated values used for this trade study are indicated for clarification.

1.2.1 The SSCV Actuator (SSCVA) System shall have a maximum velocity capability of $\pm 10^\circ/\text{second}$ (estimated).⁵

1.2.2 The SSCVA shall have an acceleration capability of $\pm 20^\circ/\text{sec}/\text{sec}$ (estimated).⁵

1.2.3 The SSCVA closed loop frequency shall have a bandwidth of 1.0 Hz in response to sinusoidal input command signal analogous to a 1 degree peak-to-peak actuator output shaft motion. The bandwidth point is defined where the amplitude ratio of output (shaft motion) to input (command signal) is down 3.0 db.⁵

1.2.4 The SSCVA shall position the SSCV input shaft to within ± 0.5 degree.⁵

1.2.4.1 The SSCVA resolution shall be 0.6 degree as indicated in DRM-51414.

1.2.7 The SSCVA useful life (operating and storage life) shall be as defined in the SSCVA Specification CP-677575.

1.2.8 The SSCVA must operate in the environments specified in the NERVA NSS Specification CP-677555.

1.2.9 The SSCVA must operate on the pneumatic media of H_2 or He and/or electrical power as specified in CP-677555.

1.2.10 The apportioned reliability goal for the SSCVA as specified in CP-77576 is 0.99995.

1.2.11 The SSCVA transportability, safety, and general design features shall be as defined in CP-677576.

2.0 DESCRIPTION OF DESIGN APPROACHES

The actuator systems selected for evaluation in this trade study are selected with the intent of including and considering at least one candidate from each type of concept. All candidates, regardless of the success and experience gained in the XE program, are considered and none rejected or abandoned prematurely in the study effort. The trade study was conducted on a design concept basis with enough depth to assure accomplishment of the functional and performance objectives. If these objectives do not change markedly as the SSCV design evolves, the results of the study will, in general, be applicable.

In a parallel effort, the Control Drum Actuator System Trade Study, WANL-TME-1984, was completed and presented to the government in September, 1969. To take advantage of the work performed in that study, and to prevent duplication of effort, the proportional device candidates for consideration were jointly selected. The only concept of this actuator study not included in the control drum drive system study was the fluidic system design. This concept was conceived and studied as a Structural Support Coolant Supply System (SSCSS) as it does not have application in the control drum actuator system.

A summary of the trade study concepts is presented in block form in Figure 2-1. Table 2-1 presents the pertinent drawings relating to each concept.

The following subparagraphs of this section present descriptions, considerations, and analyses accomplished in the logic required to achieve a complete and thorough evaluation of each actuator system concept.

2.1 RACK AND PINION PROPORTIONAL PNEUMATIC CONCEPT

2.1.1 Mechanical Description

A general mechanical description of the single piston pneumatic rack and pinion actuator shown in Figure 2-2 is described below. For a more concise and detailed actuator description refer to the Control Drum Actuator Trade Study, TME-1984, Section 2.1.1.

The actuator design evolved from redesign efforts on the XE-Prime control drum actuator, Figure 2-3. The actuator design shown in Figure 2-4 is an intermediate concept

Figure 2-1 Actuator System Concepts

TABLE 2-1
PERTINENT DRAWINGS RELATING TO EACH STUDY CONCEPT

<u>Study Concept</u>	<u>Drawings</u>	
	<u>Actuator</u>	<u>Fault Tree</u>
Double Piston - Rack and Pinion	910E276	939J475
Single Piston - Rack and Pinion	None	939J476
Helical Cam	100E146	939J474
Dynavector - Pneumatic	939J955	939J960
Responsyn Motor - Direct Drive	711J757	939J964
Responsyn Motor - Planetary Drive	None	939J190
Slo-Syn Motor - Harmonic Drive	100E818	939J464
Dynavector - Electric	100E802	939J963
Permanent Magnet - Stepping Motor	100E819	939J965
AC Servo Motor	100E140	939J467
DC Motor	100E139	939J468
Fluidic	Artwork	100E804

Figure 2-2. Pneumatic Rack and Pinion Actuator - Single Piston

Figure 2-3. Pneumatic Rack and Pinion Actuator - XE Type

Figure 2-4. Pneumatic Rack and Pinion Actuator - 1st Redesign

arrived at in the redesign program. Each of these designs, Figures 2-2 and 2-3, resulted from major design simplifications, but retained the basic principles of the XE-Prime actuator design. The interim designs, Figures 2-3 and 2-4, are included in this section to present the design evolution of this particular concept.

The actuator is divided into four main component assemblies for discussion:

- 1) Servovalve Assembly
- 2) Feedback Potentiometer
- 3) Drive Train (piston and rack assembly; pinion output shaft; output shaft bearings; and rack backup bearing assembly).
- 4) Housing Enclosure

The servovalve receives the command signals from the NSS control system and converts them into a pressure differential across the piston mechanism as shown in Figure 2-5. This pressure differential causes translation of the piston and rack assembly that rotates the output shaft. The output shaft drives the feedback potentiometer which produces an electrical signal proportional to the output shaft rotation (i.e., SSCSS valve position). This electrical signal is fed back to the control system and compared to the command signal. Any difference between the command and feedback signals results in a command signal to further rotate the actuator shaft. This continues until the feedback signal equals the command signal. The actuator housing is the envelope of the actuator mechanism that provides porting and housing for the actuator subassemblies and pneumatic media.

2.1.2 System Description

A block diagram of the rack and pinion proportional pneumatic actuator system is shown in Figure 2-6. All of the subassemblies of the actuator system and their interrelationship with other systems within the NERVA engine are included in this diagram. The components indicated in the diagram that constitute the actuator system are the actuator mechanism, the actuator amplifier (including compensation and associated logic), and the actuator output drive shaft.

Figure 2-5. Actuator Single Piston Rack and Pinion Schematic

Figure 2-6. Rack and Pinion Actuator System Block Diagram

The actuator mechanism is mounted to a boss on the structural support coolant valve, as shown in Figure 2-7. This mounting method provides the interface required for remote or manual actuator removal and replacement. The actuator drive gas, coolant gas, exhaust gas, and output drive shaft cross this interface in performing their functions. All required system electrical conductors interface with the actuator mechanism through a connector mounted in the actuator housing. This electrical connector is designed to provide actuator remote removal and replacement capability.

The actuator control amplifier, combined with the actuator mechanism, and supplied with the proper electrical and pneumatic input, constitute a closed loop position control system. This servomechanism, through the actuator output shaft, changes the SSCV position, and thus the support system coolant flow, in accordance with the measured difference between the commanded actuator shaft angle and the measured actuator shaft angle. Actuator shaft movement is always in a direction which reduces the magnitude of this measured difference to zero.

2.1.3 Radiation Analysis

The radiation analysis is performed for the pneumatic actuator mounted to the pressure vessel. The analysis is applicable to the SSCV actuator because its exact location will be in the very close proximity of the drum actuator placement. The NSS reference design drawing 939J685, Sheet 3 of 3, Revision E, does not give a location for the SSCV and actuator. Therefore, for the purpose of this study the control drum actuator analysis is utilized.

The calculated nominal radiation environment at the proposed location on the pressure vessel closure is summarized in Table 2-2. Listed in the table are the total, fast, and thermal neutron flux levels and gamma dose rate at rated thermal power, 1575 Mw. These levels may be multiplied by the time at power* for a given mission to obtain a measure of the cumulative radiation damage to candidate actuator materials in the absence of annealing effects. For perspective, the integrated values are given for a 60 minute run at rated power.

As a relative measure of the expected actuator heat removal and coolant requirements, heating rates are given for stainless steel and aluminum. (For other actuator structural

* The effective time at power, including operation at intermediate power may be calculated by dividing the integrated energy in Mw-sec by 1575 Mw.

612930-6B

Figure 2-7. Proportional Pneumatic SSCV Actuator

TABLE 2- 2
NOMINAL RADIATION ENVIRONMENT AT ACTUATOR LOCATION
FORWARD OF PRESSURE VESSEL CLOSURE (1)

<u>Item</u>	<u>Radiation Level at 1575 Mw⁽²⁾</u>	<u>Time-Integrated Fluence or Dose in 60 Minutes</u>
1) Total Neutron Flux	$2.1 \times 10^{11} \text{ n/cm}^2\text{-sec}$	$7.6 \times 10^{14} \text{ n/cm}^2$
2) Fast Neutron Flux (E >1 Mev)	$6.4 \times 10^{10} \text{ n/cm}^2\text{-sec}$	$2.3 \times 10^{14} \text{ n/cm}^2$
3) Thermal Neutron Flux (E <1.4 ev)	$2.7 \times 10^8 \text{ n/cm}^2\text{-sec}$	$9.7 \times 10^{11} \text{ n/cm}^2$
4) Gamma Ray Dose	$1.8 \times 10^6 \text{ rads-C/hr}$	$1.8 \times 10^6 \text{ rads-C}$
5) Heating Rate, Stainless Steel	2.6 watt/lb = 0.0057 watt/gm = 8.9 Btu/hr-lb = 2.5 Btu/hr-in ³	
6) Heating Rate, Aluminum	2.3 watt/lb = 0.0051 watt/gm = 7.8 Btu/hr-lb = 0.76 Btu/hr-in ³	

(1) A factor of three uncertainty (1 σ) is associated with these values. The location assumed is at reactor coordinates R = 23.4 in., Z = 53.7 in. (Station zero is at dome end of core.)

(2) Calculated at end of 60 minute full power run.

materials, e.g., titanium, the stainless steel may be used owing to the approximately constant gamma energy absorption per unit mass of structural metals.)

The values in Table 2-2 were calculated for an earlier NSS reference design shown in WANL Dwg. No. 939J685A which contained a BATH internal shield; they are applicable at the same location relative to the core in the current NSS design, Dwg. No. 939J685E. Further information on the NSS radiation environment is given in DRM No. 1076 and 1069. The values shown are for the unperturbed radiation levels in the absence of an actuator.

As a preliminary estimate of the maximum value of these levels including calculational uncertainty, a factor of three is recommended that reflects past experience in NRX reactor testing; a more precise estimate of the uncertainty in each parameter will be developed by a systematic analysis of all available experimental data. Even with the suggested uncertainty, the maximum radiation levels are relatively low at the specified actuator location as a consequence of the shielding provided by the NSS internal shield.

2.1.4 Thermal Evaluation

A thermal evaluation of this particular actuator design concept is documented in Section 2.1.4, TME-1984, Control Drum Actuator Trade Study. The analysis is based upon heating rates occurring at the pressure vessel interface. The heating rates due to the radiation environment as used in the CDA analysis are considered conservative values for the SSCV actuator as its location will be above this station. The analysis refers to a heat conducting path from the CDA to the pressure vessel. This path will not be the same for the SSCVA. However, this exception is not considered to have a great effect in applying the analysis because there will be a similar heat conducting path in the SSCVA which is from the actuator to the SSCV and piping.

The pneumatic rack and pinion actuator, Figure 2-2, is designed to conveniently and easily supply and distribute coolant as required to all components of the actuator. There is no major or heavy material mass evident that would cause high thermal gradients or temperature levels. The major material used in the actuator is aluminum, which has a low volumetric heating rate and excellent thermal conductivity. The steel rack, pinion, and output shaft are fully and directly exposed to a coolant gas environment. No major asymmetric thermal condition is readily apparent in the actuator design.

A detailed analysis of the rack and pinion actuator is presented in R641811 which is the vendor's design and development report for the pneumatic actuators of the NERVA XE series. This analysis reports that the maximum temperature occurs in the actuator at the mounting clamp bolt. Using this temperature as a baseline, a calculation on the appropriate actuator hardware (bolt, nut, strap, and housing) results in a maximum bolt temperature of 455°R. Applying a factor of three uncertainty to the heating rates, the maximum bolt temperature becomes 515°R.

The most recent calculated heating rate values of 2 to 3 watts/lb (7 to 10 BTU/hr/lb) further reduces the thermal gradients of the actuator.

2.1.5 Structural Evaluation

The structural analysis as performed is as described in Section 2.1.5 of the Control Drum Actuator Trade Study, TME-1984. For the purposes of the SSCV Actuator Trade Study the same structural evaluation is considered appropriate. As a result of this analysis the actuator concept is considered to be structurally adequate or capable of becoming structurally adequate. For the details of the analysis, please refer to the CDA Trade Study.

2.1.6 Radiation Effects Evaluation

The total expected radiation environment to which this actuator will be subjected is given in Section 2.1.3. To assess the effects of this environment on the actuator, a comparison of known test environments with this expected environment will indicate the sensitivity of any given concept to successful operation in the expected radiation levels. The sensitive components in this concept are the torque motor, potentiometer, piston rings and shaft seals, and electrical insulation and potting compounds. All other materials used in the construction of the actuator are metals. Although detail designs are not available, final material selection will be made from lists of qualified materials or will be separately qualified.

2.1.6.1 Torque Motor

The torque motor contains two items which are considered sensitive to a radiation environment, the permanent magnets and the electrical coil. Changes in magnetic properties are reported after radiation exposures approximating $3 \times 10^{18} \text{ n cm}^{-2}$.^(6,7) This is approximately three orders of magnitude above the expected NERVA level. Other experiments at approximately the same neutron fluence show very little effect. Irradiation of a torque motor, similar to the NERVA design in the GTR facility, to $7 \times 10^{16} \text{ n cm}^{-2}$ produces an anomaly in the torque motor behavior. This anomaly is probably caused by the cryogenic environment rather than the radiation. The anomaly does not affect the performance of the torque motor. In addition, a prototype torque motor was operated in the NRX-A6 pneumatic actuator side-by-side test⁽⁸⁾ to levels approximately two orders of magnitude higher than the expected NERVA levels with no evidence of change. Test results of the Lewis Research Center Program⁽⁹⁾ at the Plum Brook Reactor also show no anomalies.

Electrical coils are part of all the mentioned torque motor tests and evidence no signs of damage. However, it is planned to take advantage of improvements in the state-of-the-art in insulation materials and use the polyimide series for future wire insulation to improve radiation tolerance and increase coil reliability.

2.1.6.2 Potentiometer

A prototype potentiometer is also included in the tests. A reported failure in the Lewis tests⁽⁹⁾ caused some concern until a subsequent post-irradiation examination revealed that the failure was caused by a softening and subsequent flowing of a potting compound not included in the GTR and NRX-A6 tests. The material that failed was included in very early potentiometers but has since been removed. Future controls will assure using only those specified materials that will not be subject to property changes under radiation environment.

2.1.6.3 Piston Rings, Shaft Seals, Electrical Insulation and Potting Materials

Although these items and materials are adequate for use in the NERVA environment, it is planned to take advantage of the improvements in the state-of-the-art in insulation materials. Polyimide materials, now used in the piston rings and seals, will be used in wire insulation and potting materials to increase radiation tolerance and reliability.

2.1.7 Reliability and Safety Evaluation

The reliability of each candidate actuator system is evaluated on the basis of a fault tree analysis and a failure mode analysis. The safety evaluation is accomplished by applying a safety criticality rating to those modes identified in the failure mode analysis. The following subparagraphs explain in detail the approaches and results of the analyses conducted for the rack and pinion pneumatic actuator concept.

2.1.7.1 Fault Tree Evaluation

A fault tree is generated for each actuator concept. The fault tree defines those actuator system failures which result in failure of the nuclear subsystem. Each failure is evaluated to determine which components of the actuator could cause the identified system failure. Several components affect the mission success in more than one failure. This factor is taken into account in establishing the fault trees. The fault tree is used to obtain a relative evaluation of the reliability of the various actuator concepts.

The reliability evaluation of each actuator concept is accomplished by assigning a relative weighting number to all failure events identified at the lowest level in the fault tree analysis. The relative weighting number assigned is based on an arbitrary scale from 1 to 100. Each number is an estimated measure of the difficulties of design, manufacture, inspection, assembly and testing the identified component's ability to perform during its useful life in the actuator. The number 100 represents the most difficult level and the number 1, the least difficult.

A group of engineers has reviewed each fault tree, has estimated the difficulty of the design task for each specific failure event identified on the tree, and has assigned a relative weighting number to each failure event. A total number is derived from each fault tree and this number measures the relative probability of failure of each alternate design concept with the others. The total number is obtained by adding the numbers assigned through the progression identified in the logic displayed by the fault tree.

Figure 2-8 shows in summary form the main contributors to the failure of each actuator concept. The second level of blocks are those actuator failure events that cause NSS failure. The third level of blocks which "OR" into the main failure blocks relate to the specific components within the actuator concept that contribute to the main block failure. The numbers

SUMMARY FAULT TREE

Figure 2-8 SSCV Actuator, Single Piston, Rack and Pinion (Summary Fault Tree)

in parenthesis are the logic totals of all the lower level blocks feeding into any given block. The identifying numbers outside of each block are the same as the appropriate block on the fault tree diagram. A listing of the failure events is shown in Table 2-3. These failure events are located in the fault tree by their identifying numbers which appear above the blocks on the fault tree. The events are listed in an indented manner which also indicates levels on the fault tree. The weighting numbers assigned to the events are listed on the right side of the page and are similarly indented. Therefore, weighting numbers which are indented closest to the center of the page are failure events which are the lowest level on the fault tree. As these are logically combined to produce the combined relative probabilities of failure, the sub-totals progress toward the right of the page.

The final total of the weighted numbers (1470) appears at the head of the list on the right-hand side of the page. The totals for the higher level events of the fault tree have been indicated in parenthesis in the blocks of the summary fault tree, Figure 2-7. Through use of the block identifying numbers, the source of the relative failure probability weighting number in each block can be identified to the reliability evaluation list and also to the fault tree drawing.

The relative probability of failure number is used to compare actuator concepts, but it has no significance as a quantitative measure of the probability of failure. The calibration process, which immediately follows the reliability evaluation list, is used to convert the results obtained to a quantitative reliability estimate for the particular concept.

The calibration process (Section 2.1.7.1.1) consists of selecting a failure event which is amenable to analysis by the stress/strength overlap method, computing the probability of failure for this event, and comparing the result with the weighting number arrived at in the reliability evaluation list for the same event. By adjusting the computed probability of failure in the ratio of the weighting number for that single failure event to the relative probability of failure number total obtained from the reliability evaluation list, a quantitative estimate of the true probability of failure for the actuator system is obtained.

To increase the degree of confidence, the calibration process is repeated (Section 2.1.7.1.2) using a second selected failure event. The most conservative estimate obtained is used as the quantitative estimate of the true probability of failure.

TABLE 2-3
DETAILED FAULT TREE ANALYSIS
(Single Piston Pneumatic SSCV Actuator)

Single Piston - Rack and Pinion Proportional Pneumatic SSCV Actuator Reliability - Fault Tree Analysis 939J476, Estimated Reliability 0.9₅85 1470

1.	Actuator Coolant Gas Consumption Rate Exceeds Specified Rate Limits		70
1.1	Pedestal Fails to Contain Pressure		6
1.1.1	Pedestal Body Fails	1	
1.1.2	Pedestal Weld Fails	5	
1.2	Interface Seal Joint Fails		54
1.2.1	Pedestal Seal Surface Fails to Contain Pressure	1	
1.2.2	Actuator Seal Surface Fails to Contain Pressure	1	
1.2.3	Seal Fails to Contain Pressure	30	
1.2.4	Seal Joint Separates	22	
1.2.4.1	Actuator Flange Fractures	1	
1.2.4.2	Pedestal Flange Fractures	1	
1.2.4.3	Clamp Loses Force	20	
1.2.4.3.1	L.H. Bolt Loses Torque	5	
1.2.4.3.2	Clamp Spring Gradient Changes	10	
1.2.4.3.3	R.H. Bolt Loses Torque	5	
1.3	Actuator Mechanism Fails to Control Coolant		10
1.3.1	Lower Shaft Seal Fails	10	
2.	Actuator Fails to Achieve Time/Position Band		1320
2.1	Actuator Piston Pressures are not Correct Values		679
2.1.1	Servo valve Converts Signal Incorrectly	135	

2.1.1.1	Torquemotor Characteristics Change		119
2.1.1.1.1	Coil Fails		60
2.1.1.1.2	Armature Assembly Fails		25
2.1.1.1.2.1	Weld Fails	10	
2.1.1.1.2.2	Armature Spring Fails	2	
2.1.1.1.2.3	Frame Fails	3	
2.1.1.1.2.4	Armature Fails	10	
2.1.1.1.3	Field Assembly Fails		4
2.1.1.1.3.1	Pole Piece Fails	1	
2.1.1.1.3.2	Bottom Shunt Fails	1	
2.1.1.1.3.3	Top Piece Fails	1	
2.1.1.1.3.4	Magnets Fail	1	
2.1.1.1.4	Coil Lead Wires Fail		30
2.1.1.2	Valve Characteristics Change		16
2.1.1.2.1	Flapper Screw Fails		7
2.1.1.2.1.1	Screw Breaks Mech.	2	
2.1.1.2.1.2	Lock Screw Fails Allowing Flapper Screw to Move	5	
2.1.1.2.2	Nozzle Assembly Fails		4
2.1.1.2.2.1	Nozzle Core Fails	3	
2.1.1.2.2.2	Manifold Fails	1	
2.1.1.2.3	Fasteners Fail		5
2.1.2	Actuator System Loses Drive Gas Pressure		544
2.1.2.1	Flow Passages Blocked by Contamination		10
2.1.2.2	Mechanisms Pressures Wrong Value		480

2.1.2.2.1 Gas Filters Drop Pressure Due to Contamination		AGC
2.1.2.2.2 Housing Assembly Fails		54
2.1.2.2.2.1 Mechanism Body Fails	1	
2.1.2.2.2.2 Cylinder Liner Fails	1	
2.1.2.2.2.3 Piston Fails	10	
2.1.2.2.2.4 Cylinder Cover Fails	5	
2.1.2.2.2.5 Rack Backup Bearing Seal Joint Fails	37	
2.1.2.2.2.5.1 Seal Fails	30	
2.1.2.2.2.5.2 Backup Bearing Container Seal Surface Fails	1	
2.1.2.2.2.5.3 Housing Seal Surface Fails	1	
2.1.2.2.2.5.4 Fasteners Fail	5	
2.1.2.2.3 Internal Seal Joints Fail		426
2.1.2.2.3.1 P-1 Nozzle Seal Joint Fails	67	
2.1.2.2.3.1.1 Bottom Seal Fails	30	
2.1.2.2.3.1.2 Top Seal Fails	30	
2.1.2.2.3.1.3 Nozzle Sealing Surface Fails	1	
2.1.2.2.3.1.4 Port Sealing Surface Fails	1	
2.1.2.2.3.1.5 Fasteners Fail Allowing Joint to Separate	5	
2.1.2.2.3.2 P-2 Nozzle Seal Joint Fails	67	
2.1.2.2.3.2.1 Bottom Seal Fails	30	
2.1.2.2.3.2.2 Top Seal Fails	30	
2.1.2.2.3.2.3 Nozzle Sealing Surface Fails	1	
2.1.2.2.3.2.4 Port Sealing Surface Fails	1	
2.1.2.2.3.2.5 Fasteners Fail	5	

2.1.2.2.3.3	Cylinder Liner Housing Seal Joint Fails	2	
2.1.2.2.3.3.1	Liner Fails	1	
2.1.2.2.3.3.2	Housing Fails	1	
2.1.2.2.3.4	P-2 Inlet/Lee Plug Joint Fails	2	
2.1.2.2.3.5	P-1 Cylinder Cover/Liner Joint Fails	35	
2.1.2.2.3.5.1	Seal Fails	30	
2.1.2.2.3.5.2	Cylinder Seal Surface Fails	1	
2.1.2.2.3.5.3	Cover Seal Surface Fails	1	
2.1.2.2.3.5.4	Cover Fasteners Fail	3	
2.1.2.2.3.6	P-2 Shaft Seal Joint Fails	130	
2.1.2.2.3.6.1	Shaft Fails at Seal Support	10	
2.1.2.2.3.6.2	Housing Seal Surface Fails	20	
2.1.2.2.3.6.3	Seal Fails	100	
2.1.2.2.3.7	P-1 Piston Seal Joint Fails	121	
2.1.2.2.3.7.1	Piston Seal Fails	100	
2.1.2.2.3.7.2	Cylinder Liner Seal Surface Fails	20	
2.1.2.2.3.7.3	Piston Seal Surface Fails	1	
2.1.2.2.3.8	Supply Port Tee Plug Fails	2	
2.1.2.3	Mechanism/Pedestal Seal Joint Fails	54	
2.1.2.3.1	Pressure Vessel Seal Surface Fails	1	
2.1.2.3.2	Mechanism Seal Surface Fails	1	
2.1.2.3.3	Drive Supply Seal Fails	30	
2.1.2.3.4	Seal Joint Separates	22	
2.1.2.3.4.1	Actuator Flange Fractures	1	

2.1.2.3.4.2 Pedestal Flange Fractures	1	
2.1.2.3.4.3 Clamp Loses Force	20	
2.1.2.3.4.3.1 Left Hand Bolt Loses Torque	5	
2.1.2.3.4.3.2 Clamp Spring Gradient Changes	10	
2.1.2.3.4.3.3 Right Hand Bolt Loses Torque	5	
2.1.3 Exhaust Restricted Causing High Back Pressure		AGC
2.1.4 Drive Gas Supply to Mechanism is not Proper Value		AGC
2.2 Actuator Receives Improper Command Signal from Amplifier		249
2.2.1 Amplifier Supply Voltage is not Correct Value		AGC
2.2.2 Amplifier Fails Internally		30
2.2.3 Amplifier Receives Improper Feedback Signal		219
2.2.3.1 Potentiometer Supply Voltage is Wrong Value	30	
2.2.3.1.1 Mechanism Wiring Harness Fails	30	
2.2.3.1.2 Voltage Supplied to System is in Error	AGC	
2.2.3.2 Feedback Potentiometer Output Fails	154	
2.2.3.2.1 Potentiometer Electrically Fails	101	
2.2.3.2.1.1 Track Resistance Value Changes	10	
2.2.3.2.1.2 Protective Resistor Changes Value	10	
2.2.3.2.1.3 Wiper Resistance Changes Value	1	
2.2.3.2.1.4 Wiper/Track Contact Resistance Changes	80	
2.2.3.2.2 Angular Relationship Pot to SSCV Changes	21	
2.2.3.2.2.1 Pot Position Changes Relative to Out put Shaft	20	
2.2.3.2.2.2 Out put Shaft Changes Relative to SSCV	1	
2.2.3.2.3 Potentiometer Mechanically Fails	32	

2.2.3.2.3.1 Potentiometer Shaft Fails	1		
2.2.3.2.3.2 Wiper Spring Gradient Changes	1		
2.2.3.2.3.3 Bearings Fail	10		
2.2.3.2.3.4 Potentiometer Housing Fractures	20		
2.2.3.3 Feedback Signal Transmitted Improperly		35	
2.2.3.3.1 Wiring Harness Actuator/Amplifier Fails		AGC	
2.2.3.3.2 Mechanism Wiring Harness Fails		30	
2.2.3.3.3 Electromagnetic Interference Distorts Signal		5	
2.3 Out put Shaft Fails to Position SSCV			110
2.3.1 Crown Spline Fails		10	
2.3.2 Shaft Breaks		20	
2.3.3 Rack/Pinion Joint Fails		80	
2.4 Actuator Internal Load Changes			282
2.4.1 Potentiometer Load Changes		10	
2.4.2 Actuator Drive Train Loads Change		272	
2.4.2.1 Rack Backup Bearing Assembly Changes		32	
2.4.2.1.1 Retainer Fails	2		
2.4.2.1.2 Spring Fails	10		
2.4.2.1.3 Bearings Fail	10		
2.4.2.1.4 Shaft Fails	5		
2.4.2.1.5 Fasteners Fail	5		
2.4.2.2 Cylinder Liner Changes Load Value		80	
2.4.2.3 Pinion Bearings Change Load Value		60	
2.4.2.4 Pinion Changes Loading		20	

2.4.2.5	Piston/Rack Assembly Changes Load Value	80	
2.4.2.5.1	Piston Head Fails	10	
2.4.2.5.2	Piston/Rack Joint Fails	20	
2.4.2.4.3	Piston Seal Fails	20	
2.4.2.5.4	Piston Ring Fails	20	
2.4.2.5.5	Rack Fails	10	
2.5	SSCV Load Characteristics Change		EC
3.	Actuator Electrical Power Consumption Rate Exceeds Limits		80
3.1	Actuator/Amplifier External Cable Short Circuits		AGC
3.2	Actuator Amplifier Short Circuits		20
3.3	Mechanism Short Circuits Internally		60
3.3.1	Potentiometer Short Circuits	10	
3.3.2	Wiring Harness System Short Circuits	40	
3.3.2.1	Wiring Insulation Fails	10	
3.3.2.2	Pedestal Short Circuits	20	
3.3.2.3	Connector Short Circuits	10	
3.3.3	Torque Motor Short Circuits	10	

In a similar manner, a fault tree analysis was performed on the two piston actuator concepts. A fault tree, Drawing 939J475, was used for the evaluation resulting in a weighted number total of 1862. Figure 2-9 is the summary form of the detailed fault tree analysis performed.

2.1.7.1.1 Fault Tree Calibration. The calibration process for the fault tree consists of selecting a failure event which is amenable to analysis by the stress/strength overlap method and comparing the probability of failure computed thereby, with the weighting number previously assigned in the reliability evaluation list. By adjusting the computed probability of failure in the ratio of the previously assigned weighting number for that single failure event to the total relative probability of failure obtained from the reliability evaluation list, an estimate of the true probability of failure for the complete actuator system is obtained.

Calibration: Single Piston Rack and Pinion Proportional Pneumatic
SSCV Actuator Fault Tree (939J476)

1) Design Data - Pinion Gear

Teeth - Design Data	N = 28 Teeth
	P = 32
	P.D. = 0.875 in.
	$\phi = 20^\circ$ (Pressure Angle)
	f = 0.875 (Face Width at P.D.)

Piston - Design Data	Dia. = 1.800 in.
	Area = 2.54 in. ²

2) Applied Loads - Pinion Gear

Load Applied to Teeth by Drive Pressure

Mean Supply Pressure = 200 psig

Mean load assuming 3/4 of supply pressure can be impressed across piston by servovalve.

$$\text{Mean Load} = \frac{3}{4} P_s A = \frac{3}{4} (200) (2.54) = 380 \text{ lb}$$

Maximum Supply Pressure = 250 psig

$$\text{Maximum Load} = \frac{3}{4} P_s A = \left(\frac{3}{4}\right) (250) (2.54) = 475 \text{ lb}$$

Figure 2-9 Two-Piston Rack and Pinion Concept Summary Fault Tree

3) Pinion Tooth Stress

Lewis Equation⁽¹⁰⁾

$$\sigma = \frac{F_T P}{f_y}$$

$$y = 0.353$$

$$\text{Mean Stress } \sigma_{\text{mean}} = \frac{(380)}{(0.875)} \frac{(32)}{(0.353)} = 39,400 \text{ psi}$$

$$\text{Maximum Stress } \sigma_{\text{maximum}} = \frac{(475)}{(0.875)} \frac{(32)}{(0.353)} = 49,200 \text{ psi}$$

4) Standard Deviation Calculation

Assume the above stresses are population statistics. • • • Sample size $N_L = \infty$.

$$\bar{X}_L = 39,400 \text{ psi}$$

$$3 \sigma \text{ limit load} = \sigma_{\text{max}} = 49,200 \text{ psi}$$

$$S_L = \frac{\sigma_{\text{max}} - \bar{X}_L}{3} = \frac{49,200 - 39,400}{3} = \frac{9,800}{3} = 3,270$$

$$S_L = 3,270 \text{ psi}$$

5) Material Property Data

$$\bar{X}_M = 125,000 \text{ psi}^{(11)}$$

Assume $N_M = \infty$.

$$\text{Assume } S_M = 0.1 \bar{X}_M = (125,000) (0.1) = 12,500.$$

(From similar materials, S_M is equal to $0.05 \bar{X}_M$; therefore, 10 percent is conservative.)⁽¹²⁾

$$S_M = 12,500 \text{ psi}$$

6) Reliability Calculation

$$X_R = \frac{X_M - X_L}{\sqrt{S_M^2 + S_L^2}} = \frac{125,000 - 39,400}{\sqrt{(12.5 \times 10^3)^2 + (3.27 \times 10^3)^2}}$$

$$= \frac{85,600}{\sqrt{(156 \times 10^6) + (10.7 \times 10^6)}} = \frac{85,600}{\sqrt{166.7 \times 10^6}} = \frac{85,600}{12,900}$$

$$X_R = 6.64$$

7) Technique⁽¹³⁾

$$X_R = 6.64$$

$$\text{Reliability} = .9_{10}^{83}$$

$$\text{Failure Probability} = 17 \times 10^{-12}$$

8) Estimated Reliability

Using this calibration as representative of an arbitrary figure 80 on Fault Tree 939J476 for the "Rack/Pinion Fault Failure" (Block 2.3.3), a failure probability for the total concept can be obtained.

$$\frac{F. P.}{17 \times 10^{-12}} = \frac{1470}{80}$$

$$F. P. = (17 \times 10^{-12}) \left(\frac{1470}{80} \right)$$

$$F. P. = (17 \times 10^{-12}) (18.4) = 312 \times 10^{-12}$$

$$\text{Concept Estimated Reliability } R_M = .9_{9}^{688}$$

2.1.7.1.2 Alternate Calibration. In order to increase the degree of confidence, the calibration process is repeated using a second selected failure event and the most conservative estimate thereby obtained used as the estimate of the true probability of failure.

Calibration: Torquemotor

- 1) Torsion Bar - Refer to Drawing 800C664 (Fault Tree 939J476 Block 2.1.1.1.2.2). Assume armature has a maximum end motion of ± 0.010 in. at a radius of 0.825 in. Maximum rotation (twist) of torsion bar

$$\tan \theta = \frac{0.010}{0.825}$$

$$\theta = 0.01212 \text{ rad}$$

Torque required to rotate rod through angle θ

$$T^1 = \frac{T}{2} = \frac{GL}{L} \theta$$

From Drawing 800C664

$$D = 0.0732$$

$$L = 0.187 - 2(0.020) = 0.147 \text{ in. (Minimum Length)}$$

$$J = \frac{\pi r^4}{2} = \frac{\pi(0.0366)^4}{2} = \frac{\pi 180 \times 10^{-8}}{2} = 282 \times 10^{-8}$$

$$J = 2.82 \times 10^{-6}$$

$$G = 10.6 \times 10^6 \text{ psi (301 SS - AGC 2275)}$$

$$T^1 = \frac{10.6 \times 10^6 (2.82 \times 10^{-6})}{0.147} (1.212) \times 10^{-2} = 2.47$$

$$T^1 = 2.47 \text{ in.-lb}$$

$$\text{Stress in bar} = \frac{T_r^1}{J} = \frac{2.47 (0.0366)}{2.82 \times 10^{-6}} = 32,100 \text{ psi}$$

$$\text{Shear stress} = 32,100 \text{ psi}$$

2) Standard Deviation Calculation

Assume this is the mean assembly stress in bar.

$$\therefore \bar{X}_L = 32,100 \text{ psi}$$

Assume the standard deviation is 0.1 of the mean.

$$\therefore S_L = 0.1 \bar{X}_L = 3,210 \text{ psi}$$

Let $N_L = \infty$ and the above sample statistics become population statistics.

$$\therefore \bar{\mu}_L = \bar{X}_L = 32,100 \text{ psi}$$

$$\therefore \sigma_L = S_L = 3,210 \text{ psi}$$

3) Material Property Data

Assume material is AISI 301, full hard condition.

DRM 51239 (Material Property Estimates)

at 75°F - yield strength

$$\bar{\mu}_m = 154,900 \text{ psi}$$

$$\sigma_m = 7,000 \text{ psi}$$

But the shear strength is equal to 0.5 yield strength and assume the variation is the same.

$\therefore$ Shear yield

$$\bar{\mu}_m = 77,450 \text{ psi}$$

$$\sigma_m = 7,000 \text{ psi}$$

4) Reliability Calculation

$$X_R = \frac{\bar{\mu}_m - \bar{\mu}_L}{\sqrt{\sigma_m^2 + \sigma_L^2}} = \frac{77,450 - 32,100}{\sqrt{7,000^2 + 3,210^2}} = \frac{45,350}{\sqrt{49 \times 10^6 + 10.3 \times 10^6}}$$

$$X_R = \frac{45,350}{\sqrt{59.3 \times 10^6}} = \frac{45,350}{7,700} = 5.9$$

$$X_R = 5.9$$

5) Technique⁽¹³⁾

$$X_R = 5.9$$

$$\text{Reliability} = .98$$

$$\text{Failure Probability} = 2 \times 10^{-9} \quad (\text{For torsion bar})$$

6) Estimated Reliability

Using this calibration as representative of an arbitrary Figure 2 on Fault Tree 939J476 for the "Armature Spring Fails" (Block 2.1.1.1.2.2):

$$\frac{\text{F. P.}}{2 \times 10^{-9}} = \frac{1470}{2}$$

$$\text{F. P.} = (2 \times 10^{-9}) (735.0)$$

$$\text{F. P.} = 1470 \times 10^{-9}$$

$$R_M = .9585$$

2.1.7.2 Failure Mode Evaluation

A failure mode analysis is prepared for each control drum actuator concept under consideration. As the actuator concepts are not completely detailed designs, the failure mode analyses are studies of arbitrarily selected groups of parts that form basic components within each actuator rather than studies of individual parts. In generating the failure mode analyses, each component is analyzed for possible modes of failure. These failure modes are identified and listed. Then, each failure mode is analyzed and the component failure mechanisms which cause the particular failure mode are identified and listed.

A reliability comparison of each actuator concept is accomplished by using a rating technique which utilizes a relative failure probability number based on a scale ranging from 1 to 10. The relative failure probability number is assigned to each component failure mechanism and represents an estimated probability of failure due to the particular failure mechanism. On the scale, 1 represents the lowest probability of failure and 10 represents the highest.

Engineering judgement is used in estimating the relative failure probability number for each failure mechanism. A total number is calculated by adding the relative probability numbers. This technique is considered acceptable since the failure modes listed are independent and mutually exclusive of one another.⁽¹⁴⁾ The total number indicates the relative reliability of the actuator concept; the lower the number, the more reliable the particular concept is relative to the others. Each concept is compared with the others on the basis of the total relative failure probability number. The failure mode analysis for this particular actuator concept is reported in detail in the Control Drum Actuator Trade Study Report. The total relative failure probability number reported in this analysis is 171. The two piston actuator total is 220. In performing the analysis it was recognized that the work accomplished was directly applicable to the Structural Support Coolant Supply System (SSCSS) actuator trade study. To avoid repeating the details of the analysis for the purpose of this subject study only the total relative failure probability number is reported. Refer to the CDA Trade Study Report⁽¹⁵⁾ for the details of the analysis.

2.1.7.3 Safety Evaluation

The inherent safety and criticality of any failure is an important parameter to be considered in making a selection of a recommended concept. To determine a relative safety and criticality ranking for each concept, failure modes are identified. For each of the failure modes listed, mechanisms of obtaining that failure mode are established as they relate to a particular design. Each of these failure mechanisms is given a numerical ranking consistent with its effect on the NSS and engine mission. Four categories of criticality are used to determine the safety rating of each concept as follows:

<u>Ranking</u>	<u>Description</u>
4	Failures resulting in gross core failure or possibly affecting structural integrity; crew safety jeopardized; African window safety in question.
3	Failures requiring corrective action resulting in reductions in chamber pressure/temperature below the emergency recovery mode level.
2	Failures requiring corrective action resulting in reduction in chamber temperature/pressure but not below emergency recovery mode level; completion of mission in question.
1	Failures resulting in insignificant effects on chamber temperature/pressure.

By assigning each mechanism of failure to one of the above categories and finally obtaining a sum of all of the failure mechanisms, a total relative criticality ranking is obtained for each concept. The lower the total number estimate for a concept, the safer that concept is in relationship to the other concepts considered. The CDA trade study report, WANL-TME-1984, ⁽¹⁵⁾ presents a tabulation of the failures, mechanism of failure and criticality ranking of failure for the single piston rack and pinion pneumatic actuator. Also shown is the total

criticality ranking for this concept. For the purpose of this report, only the results of the analysis are reported. Those results are:

<u>Actuator Concept</u>	<u>Weighted Total</u>
Single Piston Actuator	346
Double Piston Actuator	364

2.1.8 Evaluation of Concept

The proportional pneumatic rack and pinion actuator concept is the only concept that has been used in the NERVA project. Although the simple single piston design has never been built, its forerunner has been used successfully on the XE program and has accumulated many hours of operating experience under all expected NERVA environments. Past experience together with design effort have resulted in a concept which is the best proportional pneumatic candidate. The redesign effort extensively simplifies the XE design while retaining the basic principles which have been successful.

The servovalve, which is the heart of the pneumatic designs, has been redesigned to remove undesirable features. The redesign improves reliability and performance but maintains the simple principles and features of the original design. The basic torque motor flapper concept is retained. The redesign emphasis is to improve construction. The dynamic pressure feedback bellows of the XE design is removed and a new annular nozzle concept is incorporated without a drastic departure from the original concept.

The concentrically mounted three-deck potentiometer is a departure from the XE configuration but retains the same construction materials. The potentiometer is assembled concentric with the actuator shaft, thus utilizing the same bearings. In this design, the potentiometer track design is longer, giving a greater arc length per degree of shaft rotation and allowing greater linearity or easier manufacture. This increase in track length may allow incorporation of a wire wound potentiometer instead of the plastic composition potentiometer now considered in all designs. The limiting parameter for a wire wound potentiometer is the system resolution which is a function of wire spacing. With a larger diameter potentiometer, more wire turns per degree of arc can be wound on the potentiometer, thus improving resolution.

The single piston proportional pneumatic actuator is a highly compact actuator design. Its width at the output shaft centerline is about 4-1/8 inches. Its height above the SSCV mounting boss is about 4-3/4 inches. The clearance required above the actuator for removal is about 2-3/4 inches to clear the output shaft. Its weight is estimated at about 8 pounds.

Coolant requirements for a one hour run at the heating rates estimated for NERVA, about 3 watts per pound, are less than 1/2 pound and can probably be eliminated. Coolant passages have been provided in the event later analysis indicates that they are necessary. Maximum drive gas at 100°R and 215 psia for a one hour run is about 36 pounds. Electrical power is required to supply the amplifier and feedback potentiometers, but it is all in the control range and is considered small enough to be neglected in this study. A preliminary estimate of the concept reliability obtained by calibrating the fault tree is .9₅⁸⁵.

No problems are anticipated with this design from the standpoint of materials, performance or ability to meet and operate in the prescribed environments. Table 2-4 is a listing of some of the more significant advantages and disadvantages of the single piston, rack and pinion pneumatic actuator.

2.2 HELICAL CAM PROPORTIONAL PNEUMATIC CONCEPT

2.2.1 Mechanical Description

Figure 2-10 depicts the helical cam actuator mounted to the SSCV. A complete and accurate description may be obtained in TME 1984, Control Drum Actuator Trade Study, Section 2.2.1. A summary description will be given in this section.

The actuator consists of the following four major subassemblies:

- 1) Servovalve Assembly
- 2) Feedback Potentiometer
- 3) Drive Train (piston, helical cam, ball, shaft, and bearings)
- 4) Actuator Housing

The servovalve receives electrical command signals from the NSS control system and converts the signal into pressure differentials across the piston. The piston moves along its

TABLE 2-4

SINGLE PISTON, RACK AND PINION PNEUMATIC ACTUATOR SUMMARY TABLE

<u>Advantages</u>	<u>Disadvantages</u>
1. Power Media for H ₂ is Readily Available from Engine Source.	1. Severe Weight Penalty Exists for the Drive Gas Startup Pneumatic Supply System Weight Required Due to Actuator Consumption of H ₂ .
2. Experience and Background of the XE Actuator Program is Directly Applicable.	2. Servo valve Susceptible to Malfunction at Cryogenic Temperatures if H ₂ Supply is not Free of Trace Gas Contaminants.
3. Possibility Exists for Use of Wire-Wound Feed-back Potentiometer, Thus Improving Potentiometer Reliability	3. Vibration Environmental Capabilities Unknown for NERVA Values. No random Vibration Data for Similar Device have been Collected.
4. Highly Probable that No Coolant Gas Flow will be Required.	4. Bias Spring Probably Required to Remove Backlash from Drive System.
5. Environmental Capabilities are Very Good in Regard to Cryogenic and Radiation Tolerances.	
6. Mechanism Weight is Low.	
7. Maintainability is Considered Excellent Based Upon XE Experience.

Figure 2-10. Helical Cam Proportional Pneumatic Actuator

longitudinal axis due to the pressure differentials. This movement is translated by the drive train into an output shaft rotation. The feedback potentiometer rotates with the output shaft, Figure 2-11, producing an electrical signal which is analogous to shaft position. When the actuator is mounted to the SSCV, the output shaft position and SSCV position are identical. The actuator housing provides porting and containment for the required pneumatic media and physically joins the actuator subassemblies to form an actuator mechanism.

2.2.2 System Description

A block diagram of the helical cam proportional pneumatic actuator system is shown in Figure 2-12. All of the subassemblies of the actuator system and their interrelationship with other systems within the NERVA engine are indicated in this diagram. Components in the diagram which constitute the actuator system are the actuator mechanism, the actuator amplifier (including compensation and associated logic) and the actuator output drive shaft.

The actuator mechanism is attached to a mounting boss on the structural support coolant valve as shown in Figure 2-10. This mounting provides the interface for remote or manual removal and replacement. Drive gas, coolant gas, exhaust gas, and the output drive shaft cross this interface in performing their respective functions. All electrical conductors enter the actuator through a connector mounted in the actuator body. This connector is also designed for actuator remote removal and replacement capability.

The actuator control amplifier, combined with the actuator mechanism, and supplied with the proper electrical and pneumatic inputs, constitute a closed loop position control system. This servomechanism positions the actuator output shaft and changes the SSCV position, thus the support system coolant flow, in accordance with the difference between the commanded SSCV angle and the measured actuator shaft angle. Actuator movement is in such a direction as to reduce the magnitude of this difference to zero.

2.2.3 Radiation Analysis

Table 2-2 and Section 2.1.3 explains the radiation environment expected for this actuator application. The presence of the actuator at this location will have no effect on the radiation environment. Therefore, the data of Table 2-2 are unchanged. In most instances, the presence of the actuator will reduce the levels so that the use of the unperturbed numbers is generally conservative.

Figure 2-11 Helical Cam Proportional Pneumatic Actuator Schematic

Figure 2-12 Helical Cam Actuator System Block Diagram

2.2.4 Thermal Evaluation

A thermal evaluation of this actuator concept was performed on the basis of its use as a control drum actuator. Application of this evaluation to the SSCV actuator concept is slight conservative but adequate for the purpose of this trade study. For the details of the evaluation, refer to the CDA Trade Study, TME 1984, Section 2.2.4.⁽¹⁵⁾ Should this concept become a prime candidate, a more detailed and thorough thermal analysis would be performed.

2.2.5 Structural Evaluation

The helical cam proportional pneumatic actuator is similar to the rack and pinion actuator discussed in Section 2.1.5.⁽¹⁵⁾ Structurally, the only difference between the two actuators is the method of converting linear motion to rotary motion. The structural evaluation of the servovalve assembly, feedback potentiometer, and housing enclosure is identical to that of the rack and pinion actuator discussed in Section 2.1.5.⁽¹⁵⁾

The drive train of the helical cam actuator converts the linear motion of the piston to rotary motion by two balls which are trapped in the spiral grooves cut externally in the output shaft and internally in the piston assembly. The major areas of structural concern are the balls and spiral grooves. The balls which transmit the axial force from the piston to output shaft must be able to roll freely in the grooves. Sliding or rubbing of the balls will cause surface wear to both the balls and grooves, and additional functional resistance will be introduced into the system. Contact stresses in the balls may be high if the maximum pressure drop is applied to the piston. Consideration must be given to material selection and thermal distortion of the balls and grooves.

The drive train of the helical cam actuator is a more complex mechanism and has more potential problem areas than that of the rack and pinion actuator.

2.2.6 Radiation Effects Evaluation

The components of the helical cam actuator concept and the rack and pinion actuator concept, presented in Section 2.1, have identical radiation sensitivity problems. Because of this gross similarity, the "Radiation Effects Evaluation" presented in Section 2.1.6 is considered directly applicable and is referred to for this portion of the helical cam actuator concept study.

2.2.7 Reliability and Safety Evaluation

The reliability of each actuator system concept was evaluated on the basis of a fault tree analysis and a failure mode analysis. The safety evaluation was accomplished by assigning a safety criticality rating to each event in the failure mode analysis. The details of each method of analysis are described in the following sub-paragraphs.

2.2.7.1 Fault Tree Evaluation

A portion of the reliability evaluation for this particular actuator concept was accomplished through a fault tree analysis. Section 2.1.7.1 of this report contains an accurate description as to how the fault trees are generated, calibrated, and implemented in evaluating the reliability of a particular actuator concept. Figure 2-13 presents in summary form the helical cam actuator system fault tree. The result of this analysis is the total of the weighted number (1830) which appears in the detailed fault tree as presented in Table 2-5.

2.2.7.2 Failure Mode Evaluation

A failure mode analysis is prepared for each actuator system concept under consideration. As the actuator concepts are not completely detailed designs, the failure mode analyses are studies of arbitrarily selected groups of parts that form basic components within each actuator rather than studies of individual parts. In generating the failure mode analyses, each component is analyzed for possible modes of failure. These failure modes are identified and listed. Then, each failure mode is analyzed and the component failure mechanisms which cause the particular failure mode are identified and listed.

A reliability comparison of each actuator concept is accomplished by using a rating technique which utilizes a relative failure probability number based on a scale ranging from 1 to 10. The relative failure probability number is assigned to each component failure mechanism and represents an estimated probability of failure due to the particular failure mechanism. On the scale, 1 represents the lowest probability of failure and 10 represents the highest.

Engineering judgement is used in estimating the relative failure probability number for each failure mechanism. A total number is calculated by adding the relative probability

Figure 2-13 SSCV Actuator, Helical Cam - Pneumatic Summary Fault Tree

TABLE 2-5
DETAILED FAULT TREE
(Helical Cam Pneumatic actuator)

Helical Cam Proportional Pneumatic Actuator Reliability -
Fault Tree Analysis 939J474 Estimated Reliability 0.9₅82 1830

1.	Actuator Coolant Gas Consumption Rate Exceeds Specified Rate Limits		216
1.1	Interface Seal Joint Fails at Shaft		54
1.1.1	Pedestal Seal Surface Fails to Contain Pressure	1	
1.1.2	Actuator Seal Surface Fails to Contain Pressure	1	
1.1.3	Seal Fails to Contain Pressure	30	
1.1.4	Seal Joint Separates	22	
1.1.4.1	Actuator Flange Fractures	1	
1.1.4.2	Pedestal Flange Fractures	1	
1.1.4.3	Clamp Loses Force	20	
1.1.4.3.1	R. H. Bolt Loses Torque	5	
1.1.4.3.2	L. H. Bolt Loses Torque	5	
1.1.4.3.3	Clamp Spring Gradient Changes	10	
1.2	Interface Seal Joint Fails at Filter		54
1.2.1	Pedestal Seal Surface Fails to Contain Pressure	1	
1.2.2	Actuator Seal Surface Fails to Contain Pressure	1	
1.2.3	Seal Fails to Contain Pressure	30	
1.2.4	Seal Joint Separates	22	
1.2.4.1	Actuator Flange Fractures	1	
1.2.4.2	Pedestal Flange Fractures	1	

TABLE 2-5 (CONTINUED)

1.2.4.3	Hold Down Bolts Lose Force	20	
1.2.4.3.1	R. H. Bolt Loses Torque	5	
1.2.4.3.2	L. H. Bolt Loses Torque	5	
1.2.4.3.3	Clamp Spring Gradient Changes	10	
1.3	Actuator Mechanism Fails to Control Coolant		108
1.3.1	Mechanism Seal Surface Fails		1
1.3.2	Lower Shaft Seal Fails		100
1.3.3	Shaft Seal Surface Fails		1
1.3.4	Pedestal Fails to Control Coolant		6
1.3.4.1	Body Fails	5	
1.3.4.2	Weld Fails	1	
2.	Actuator Fails to Achieve Time/Position Band		1534
2.1	Actuator Piston Pressures are not Correct Values		490
2.1.1	Servo Valve Converts Signal Incorrectly		135
2.1.1.1	Torquemotor Characteristics Change	119	
2.1.1.1.1	Coil Fails	60	
2.1.1.1.2	Armature Assembly Fails	25	
2.1.1.1.2.1	Weld Fails	10	
2.1.1.1.2.2	Armature Spring Fails	2	
2.1.1.1.2.3	Frame Fails	3	
2.1.1.1.2.4	Armature Fails	10	
2.1.1.1.3	Field Assembly Fails	4	

TABLE 2-5 (CONTINUED)

2.1.1.1.3.1	Pole Piece Fails	1	
2.1.1.1.3.2	Bottom Shunt Fails	1	
2.1.1.1.3.3	Top Piece Fails	1	
2.1.1.1.3.4	Magnets Fail	1	
2.1.1.1.4	Coil Lead Wires Fail	30	
2.1.1.2	Valve Characteristics Change		16
2.1.1.2.1	Flapper Screw Position Changes	7	
2.1.1.2.1.1	Screw Breaks Mech.	2	
2.1.1.2.1.2	Lock Screw Fails Allowing Flapper Screw to Move	5	
2.1.1.2.2	Nozzle Assembly Fails	4	
2.1.1.2.2.1	Nozzle Core Fails	3	
2.1.1.2.2.2	Manifold Fails	1	
2.1.1.2.3	Fasteners Fail	5	
2.1.2	Actuator System Loses Drive Gas Pressure		455
2.1.2.1	Flow Passages Blocked by Contamination	10	
2.1.2.2	Mechanisms Pressures Wrong Value	415	
2.1.2.2.1	Clogged Filter Drops Pressure	AGC	
2.1.2.2.2	Housing Assembly Fails	17	
2.1.2.2.2.1	Mechanism Body Fails	1	
2.1.2.2.2.2	Cylinder Liner Fails	1	
2.1.2.2.2.3	Piston Fails	10	
2.1.2.2.2.4	Cylinder Cover Fails	5	

TABLE 2-5 (CONTINUED)

2.1.2.2.3	Internal Seal Joints Fail		398
2.1.2.2.3.1	P-Nozzle Seal Joint Fails	67	
2.1.2.2.3.1.1	Bottom Seal Fails	30	
2.1.2.2.3.1.2	Top Seal Fails	30	
2.1.2.2.3.1.3	Nozzle Sealing Surface Fails	1	
2.1.2.2.3.1.4	Port Sealing Surface Fails	1	
2.1.2.2.3.1.5	Fasteners Fail Allowing Joint to Separate	5	
2.1.2.2.3.2	P-2 Nozzle Seal Joint Fails	67	
2.1.2.2.3.2.1	Bottom Seal Fails	30	
2.1.2.2.3.2.2	Top Seal Fails	30	
2.1.2.2.3.2.3	Nozzle Sealing Surface Fails	1	
2.1.2.2.3.2.4	Port Sealing Surface Fails	1	
2.1.2.2.3.2.5	Fasteners Fail	5	
2.1.2.2.3.3	Cylinder Liner Housing Seal Joint Fails	2	
2.1.2.2.3.3.1	Liner Fails	1	
2.1.2.2.3.3.2	Housing Fails	1	
2.1.2.2.3.4	P-1 Cylinder Cover Seal Joint Fails	11	

TABLE 2-5 (CONTINUED)

2.1.2.2.3.4.1	Seals Fail (2)	6	
2.1.2.2.3.4.2	Mechanism Seal Surfaces Fail (2)	1	
2.1.2.2.3.4.3	Cover Seal Surfaces Fail (2)	1	
2.1.2.2.3.4.4	Cover Fasteners Fail Allowing Joint to Separate	3	
2.1.2.2.3.5	P-2 Shaft Seal Joint Fails		130
2.1.2.2.3.5.1	Seal Shaft Surface Fails	10	
2.1.2.2.3.5.2	Housing Seal Surface Fails	20	
2.1.2.2.3.5.3	Seal Fails	100	
2.1.2.2.3.6	P-1 Piston Seal Joint Fails		121
2.1.2.2.3.6.1	Piston Seal Fails	100	
2.1.2.2.3.6.2	Cylinder Liner Seal Surface Fails	20	
2.1.2.2.3.6.3	Piston Seal Surface Fails	1	
2.1.2.3	Pedestal Seal Joint Fails		30
2.1.2.3.1	Pedestal Seal Surface Fails		1
2.1.2.3.2	Mechanism Seal Surface Fails		1
2.1.2.3.3	Drive Filter Seal Fails		6
2.1.2.3.4	Seal Joint Separates		22

TABLE 2-5 (CONTINUED)

2.1.2.3.4.1	Actuator Flange Fractures	1	
2.1.2.3.4.2	Pedestal Flange Fractures	1	
2.1.2.3.4.3	Clamp Loses Holding Force	20	
2.1.2.3.4.3.1	R. H. Bolt Loses Torque	5	
2.1.2.3.4.3.2	L. H. Bolt Loses Torque	5	
2.1.2.3.4.3.3	Clamp Spring Gradient Changes	10	
2.1.3	Exhaust Restricted Causing High Back Pressure		AGC
2.1.4	Drive Gas Supply to Mechanism is not Proper Value		AGC
2.2	Actuator Receives Improper Command Signal from Amplifier		249
2.2.1	Amplifier Supply Voltage is not Correct Value		AGC
2.2.2	Amplifier Fails Internally		30
2.2.3	Amplifier Receives Improper Feedback Signal		219
2.2.3.1	Potentiometer Supply Voltage is Wrong Value		30
2.2.3.1.1	Mechanism Wiring Harness Fails	30	
2.2.3.1.2	Voltage Supplied to System is in Error		AGC
2.2.3.2	Feedback Potentiometer Output Fails		154
2.2.3.2.1	Potentiometer Electrically Fails	101	
2.2.3.2.1.1	Track Resistance Value Changes	10	

TABLE 2-5 (CONTINUED)

2.2.3.2.1.2	Protective Resistor Changes Value	10	
2.2.3.2.1.3	Wiper Resistance Changes Value	1	
2.2.3.2.1.4	Wiper/Track Contact Resistance Changes	80	
2.2.3.2.2	Angular Relationship Pot to SSCV Changes	21	
2.2.3.2.2.1	Pot Position Changes Relative to Output Shaft	20	
2.2.3.2.2.2	Output Shaft Changes Relative to SSCV	1	
2.2.3.2.3	Potentiometer Mechanically Fails	32	
2.2.3.2.3.1	Potentiometer Shaft Fails	1	
2.2.3.2.3.2	Wiper Spring Gradient Changes	1	
2.2.3.2.3.3	Bearings Fail	10	
2.2.3.2.3.4	Potentiometer Housing Fractures	20	
2.2.3.3	Feedback Signal Transmitted Improperly	35	
2.2.3.3.1	Wiring Harness Pedestal to Amplifier Fails	AGC	
2.2.3.3.2	Actuator System Wiring Harness Fails	30	
2.2.3.3.3	Electromagnetic Interference Distorts Signal	5	
2.3	Output Shaft Fails to Position SSCV		260
2.3.1	Crown Spline Fails	10	
2.3.2	Shaft Breaks	20	
2.3.3	Transmission Assembly Fails	230	

TABLE 2-5 (CONTINUED)

2.3.3.1	Cam Follower Fails (2)	80	
2.3.3.2	Cam Fails (2)	10	
2.3.3.3	Retainer Fails	80	
2.3.3.4	Balls Fail (2)	20	
2.3.3.5	Piston Ball Track Fails	20	
2.3.3.6	Shaft Ball Track Fails	20	
2.4	Actuator Internal Load Changes		435
2.4.1	Potentiometer Load Changes	10	
2.4.2	Actuator Drive Train Loads Change	425	
2.4.2.1	Cylinder Liner Changes Load Value	80	
2.4.2.2	Bearings Change Load Value	60	
2.4.2.3	Transmission System Load Value Changes	285	
2.4.2.3.1	Piston Head Fails	10	
2.4.2.3.2	Transmission Assembly Fails	230	
2.4.2.3.2.1	Cam Follower Fails (2)	80	
2.4.2.3.2.2	Cam Fails (2)	10	
2.4.2.3.2.3	Retainer Fails	80	
2.4.2.3.2.4	Balls Fail (2)	20	
2.4.2.3.2.5	Piston Ball Track Fails	20	
2.4.2.3.2.6	Shaft Ball Track Fails	20	
2.4.2.3.3	Piston Seal Fails	20	
2.4.2.3.4	Piston Ring Fails	20	

TABLE 2-5 (CONTINUED)

2.4.2.3.5	Piston/Piston Joint Track Fails	5	
2.5	Coolant Valve Load Characteristics Change		EC
3.	Actuator Electrical Power Consumption Rate Exceeds Limits		80
3.1	Pedestal/Amplifier External Cable Short Circuits		AGC
3.2	Actuator Amplifier Short Circuits		20
3.3	Mechanism Short Circuits Internally		60
3.3.1	Potentiometer Short Circuits	10	
3.3.2	Wiring Harness System Short Circuits	40	
3.3.2.1	Wiring Insulation Fails	10	
3.3.2.2	Pedestal Wiring Short Circuits	20	
3.3.2.3	Connector Short Circuits	10	
3.3.3	Torquemotor Short Circuits	10	

numbers. This technique is considered acceptable since the failure modes listed are independent and mutually exclusive of one another.⁽¹⁴⁾ The total number then indicates the relative reliability of the actuator concept; the lower the number, the more reliable the particular concept is relative to the others. Each concept is compared with the others on the basis of the total relative failure probability number. The failure mode analysis for this particular actuator concept is reported in detail in the Control Drum Actuator Trade Study Report.⁽¹⁵⁾ The total relative failure probability number reported in this analysis is 197. In performing the analysis it is recognized that the work accomplished is directly applicable to the Structural Support Coolant Supply System (SSCSS) actuator trade study. To avoid repeating the details of the analysis and for the purpose of this subject study only the total relative failure probability number is reported.

2.2.7.3 Safety Evaluation

The inherent safety and criticality of any failure is an important parameter to be considered in making a selection of a recommended concept. To determine a relative safety and criticality ranking for each concept, failure modes are identified. For each of the failure modes listed, mechanisms of obtaining that failure mode are established as they relate to a particular design. Each of these failure mechanisms is given a numerical ranking consistent with its effect on the NSS and engine mission. Four categories of criticality are used to determine the safety rating of each concept as follows:

<u>Ranking</u>	<u>Description</u>
4	Failures resulting in gross core failure or possibly affecting structural integrity; crew safety jeopardized; African window safety in question.
3	Failures requiring corrective action resulting in reductions in chamber pressure/temperature below the emergency recovery mode level.

2	Failures requiring corrective action resulting in reduction in chamber temperature/pressure but not below emergency recovery mode level; completion of mission in question.
1	Failures resulting in insignificant effects on chamber temperature/pressure.

By assigning each mechanism of failure to one of the above categories, and finally obtaining a sum of all of the failure mechanisms, a total relative criticality ranking is obtained for each concept. The lower the total number estimate for a concept, the safer that concept is in relationship to the other concepts considered. The CDA Trade Study,⁽¹⁵⁾ presents a tabulation of the failures, mechanisms of failure and criticality rating of failure for the helical cam pneumatic actuator. The total criticality ranking for this concept is 197.

2.2.8 Evaluation of Concept

The major difference between this helical cam pneumatic actuator concept and the rack and pinion concept is the way the piston linear motion is translated into rotary output shaft motion. The single piston, piston seal, and piston liner portion from the rack and pinion concept is retained as well as the feedback potentiometer, servovalve, and control amplifier. However, the helical cam concept employs a markedly different drive train. This drive train design is a major innovation and as best as can be determined, no actuator of this type is presently available commercially.

The development of this actuator would necessitate a major development program. In comparison, it is felt that at the present state-of-the-art the unit is inferior to the single piston, rack and pinion concept and no desirable advantage is to be gained over the rack and pinion concept through an advancement of the state-of-the-art. The weight, size, and drive and coolant gas consumptions are approximately the same as the single piston rack and pinion concept. The reliability estimate indicates that this concept would not be as reliable as either of the other pneumatic proportional concepts.

Coolant requirements, based upon a one-hour run, at the heating rates calculated for NERVA of 3 watts/lb are very low and possibly may be eliminated. Drive gas at 100°R and 200 psig for a one hour run would total 36 pounds. Electrical power is small enough to be considered negligible for the purpose of this study. Reliability, based upon the calibrated fault tree, is 0.9₅82. Table 2-6 lists some of the more significant advantages and disadvantages.

2.3 DYNAVECTOR* PROPORTIONAL PNEUMATIC CONCEPT

2.3.1 Mechanical Description

The Dynavector actuator was developed by the Bendix Corporation. To adapt this particular rotary actuator concept to the NERVA reactor as the SSCV actuator, it is necessary to specify a new model of, or modify an existing Dynavector actuator. The actuator system concept which utilizes the Dynavector with modifications is shown in Figure 2-14. The major modifications to the device were to incorporate a servovalve and feedback potentiometer. Secondary modifications were also made which provide coolant flow for the actuator (if coolant should be required) and adapt the mechanism to the particular interfaces of the SSCSS such as mounting to the SSCV, shaft coupling to the SSCV, and electrical and pneumatic interfacing with the proper engine systems.

A complete and thorough description of the pneumatic Dynavector and its basic operation as well as a description of the SSCV actuator Dynavector concept, Figure 2-14, are presented in the Control Drum Actuator Trade Study, Section 2.3.⁽¹⁵⁾

2.3.2 System Description

A block diagram of the Dynavector proportional pneumatic actuator system is shown in Figure 2-15. This block diagram shows all of the subassemblies that make up the actuator system and their interrelationship with other systems within the NERVA engine system. The components in the diagram that constitute the actuator system are the actuator mechanism, the actuator amplifier (including compensation and associated logic) and the actuator output drive shaft.

*Registered trademark Bendix Corporation

TABLE 2-6

HELICAL CAM PNEUMATIC ACTUATOR SUMMARY TABLE

<u>Advantages</u>	<u>Disadvantages</u>
1. Power Media of H_2 is Readily Available from Engine Source.	1. No Experience or Background in the Unique Transmission System of this Actuator.
2. Possibility Exists for Use of a Wire-Wound Feedback Potentiometer, thus Improving Potentiometer Reliability.	2. Severe Weight Penalty Exists for the Drive Gas Startup Pneumatic Supply System Weight Required Due to Actuator Consumption of H_2 .
3. Some Portions of XE Actuator Experience and Background are Directly Applicable to this Actuator Design, that is, Servovalve, Potentiometer, etc.	3. Transmission's Vibration and Shock Environmental Capabilities are Unknown.
4. Mechanism Weight is Low.	4. Servovalve Susceptible to Malfunction at Cryogenic Temperature if H_2 Supply is Not Free of Trace Gas Contaminants.
5. Highly Probable that No Coolant Gas Will Be Required.	5. Dynamic Shaft Seal May be Required at SSCV Interface.
	6. Anti-Backlash Device May Be Required on Output Shaft.

Figure 2-14 Proportional SSCV Actuator Pneumatic Dynavector Concept

Figure 2-15 Dynavector Proportional Pneumatic Actuator System Block Diagram

The actuator mechanism mounts to a flange on the Support System Coolant Valve (SSCV) which provides the interface for remote or manual removal and replacement. Drive gas, coolant gas, exhaust gas and output drive shaft cross this interface to perform their respective functions. All electrical wires enter and exit the actuator through a plug mounted directly to the actuator body. This plug also has been designed with remote removal and replacement in mind.

The amplifier, combined with the actuator mechanism and supplied with the proper electrical and pneumatic inputs, constitute a closed loop SSCV position control system. This servomechanism positions the actuator output shaft (and therefore changes SSCV position and reactor reactivity) in accordance with the difference between the commanded actuator angle and the measured actuator angle. Actuator movement reduces the magnitude of this difference to zero.

2.3.3 Radiation Evaluation

The radiation analysis presented in Section 2.1.3 is directly applicable as the radiation analysis of the Dynavector actuator system concept. The physical presence of this mechanism in the radiation field environment will have no effect on the radiation levels as used in Table 2-2. In most instances, the presence of the actuator will reduce the levels so that use of the unperturbed numbers is generally conservative.

2.3.4 Thermal Evaluation

The thermal evaluation was performed on the pneumatic Dynavector concept and reported in the CDA Trade Study TME 1984⁽¹⁵⁾ Section 2.3.4. This evaluation was made on the basis that the actuators are used as a control drum actuator. However, for the intent and purpose of the SSCV actuator trade study, the CDA evaluation is considered applicable.

In general, the regions of primary interest for thermal analysis will include the relatively thick metal sections, such as housing flanges, or the asymmetrical metal sections where maximum temperature levels or distortions would be expected to occur. Should this study result in the selection of the Dynavector as a primary candidate, further and more detailed analysis would be required.

2.3.5 Structural Evaluation

The structural evaluation as reported in the CDA Trade Study,⁽¹⁵⁾ Section 2.3.5, is directly applicable as the structural evaluation of the subject SSCV pneumatic Dynavector actuator concept. Should the final result of this trade study be to select the Dynavector concept, further detailed structural analysis will be required.

2.3.6 Radiation Effects Evaluation

The total radiation environment to which this particular actuator concept will be subjected is given in Section 2.1.3. With regard to radiation sensitive components, the evaluation presented in Section 2.1.6 of this report is considered directly applicable and is referred to for use in this portion of the Dynavector actuator concept study. The only exception taken to application of the evaluation in Section 2.1.6 is that the piston seals referred to are not a part of the Dynavector actuator and, therefore, are extraneous to the subject evaluation.

2.3.7 Reliability and Safety Evaluation

The philosophy and approach used in evaluating the reliability and safety of actuator concepts is presented in Section 2.1.7. The details of the approach as applied to the evaluation of this particular actuator concept are reported in the following sub-paragraphs.

2.3.7.1 Fault Tree Evaluation

A portion of the reliability evaluation for this particular actuator concept is accomplished through a fault tree analysis. Section 2.1.7.1 gives an accurate description as to how the fault trees are generated, calibrated, and implemented in evaluating the reliability of a particular actuator concept. Figure 2-16 is the summary of the fault tree analysis performed for the pneumatic Dynavector concept. The particular fault tree used was Drawing No. 939J960. Table 2-7 presents the detailed fault tree, weighted numbers assigned, and the final total of weighted numbers (1754).

Figure 2-16 Dynavector Pneumatic SSCV Actuator Summary Fault Tree

TABLE 2-7
DETAILED FAULT TREE
(Dynavector Pneumatic Actuator)

Dynavector Proportional Pneumatic Actuator Reliability - Fault Tree Analysis 939J960 Estimated Reliability 0.9 ₅ ⁸³			1754
1. Actuator Coolant Gas Consumption Rate Exceeds Specified Rate Limits			87
1.1 Interface Seal Joint Fails		52	
1.1.1 Pedestal Seal Surface Fails to Contain Pressure	AGC		
1.1.2 Actuator Seal Surface Fails to Contain Pressure	1		
1.1.3 Seal Fails to Contain Pressure	30		
1.1.4 Seal Joint Separates	21		
1.1.4.1 Actuator Flange Fractures	1		
1.1.4.2 Pedestal Flange Fractures	AGC		
1.1.4.3 Clamp Loses Force	20		
1.1.4.3.1 L.H. Bolt Loses Torque	5		
1.1.4.3.2 Clamp Spring Gradient Changes	10		
1.1.4.3.3 R.H. Bolt Loses Torque	5		
1.2 Actuator Mechanism Fails to Control Coolant		35	
1.2.1 Shaft Seal Joint Fails	30		
1.2.2 Shaft Seal Joint Housing Fails	5		
1.2.3 Orifice Fails	AGC		
2. Actuator Fails to Achieve Time/Position Band			1607
2.1 Actuator Chamber Pressures are not Correct Values		584	
2.1.1 Servovalve Converts Signal Incorrectly		135	
2.1.1.1 Torquemotor Characteristics Change	119		
2.1.1.1.1 Coil Fails	60		

2.1.1.1.2 Armature Assembly Fails	25	
2.1.1.1.2.1 Weld Fails	10	
2.1.1.1.2.2 Armature Spring Fails	2	
2.1.1.1.2.3 Frame Fails	3	
2.1.1.1.2.4 Armature Fails	10	
2.1.1.1.3 Field Assembly Fails	4	
2.1.1.1.3.1 Pole Piece Fails	1	
2.1.1.1.3.2 Bottom Shunt Fails	1	
2.1.1.1.3.3 Top Piece Fails	1	
2.1.1.1.3.4 Magnets Fail	1	
2.1.1.1.4 Coil Lead Wires Fail	30	
2.1.1.2 Valve Characteristics Change	16	
2.1.1.2.1 Flapper Screw Position Changes	7	
2.1.1.2.1.1 Flapper Screw Fails Mech.	2	
2.1.1.2.1.2 Lock Screw Fails, Flapper Screw Moves	5	
2.1.1.2.2 Nozzle Assembly Fails	4	
2.1.1.2.2.1 Nozzle Core Fails	3	
2.1.1.2.2.2 Manifold Fails	1	
2.1.1.2.3 Fasteners Fail	5	
2.1.2 Actuator Loses Drive Gas Pressure		449
2.1.2.1 Flow Passages are Blocked	10	
2.1.2.2 Supply Inlet Seal Joint Fails	14	
2.1.2.2.1 Seal Fails Mechanically	5	
2.1.2.2.2 Joint Loses Seating Torque	7	

2.1.2.2.2.1 Fitting Rotates Loose	5	
2.1.2.2.2.2 Fitting Threads Fail	1	
2.1.2.2.2.3 Housing Threads Fail	1	
2.1.2.2.3 Housing Seal Surface Fails		1
2.1.2.2.4 Fitting Seal Surface Fails		1
2.1.2.3 Gas Inlet Fitting Fails		1
2.1.2.4 Servovalve Seal Joint Fails		134
2.1.2.4.1 P-1 Nozzle Seal Joint Fails		67
2.1.2.4.1.1 Bottom Seal Fails	30	
2.1.2.4.1.2 Top Seal Fails	30	
2.1.2.4.1.3 Nozzle Sealing Surface Fails	1	
2.1.2.4.1.4 Port Sealing Surface Fails	1	
2.1.2.4.2.5 Fasteners Fail	5	
2.1.2.5 Ring Gear to Cover Seal Joint Fails		40
2.1.2.5.1 Front Cover Fails		10
2.1.2.5.2 Ring Gear Fails		20
2.1.2.5.3 Back Cover Fails		10
2.1.2.6 Metal Seal Joint Fails		66
2.1.2.6.1 Front Cover Seal Fails	30	
2.1.2.6.2 Rear Cover Seal Surface Fails		1
2.1.2.6.3 Rear Cover Seal Fails		30
2.1.2.6.4 Front Cover Seal Surface Fails		1
2.1.2.6.5 Fasteners Fail		2
2.1.2.6.6 Reaction Gear Seal Surface Fails		2

2.1.2.7 Vanes Fail (9)	180	
2.1.2.8 Actuator Body Fails	4	
2.1.2.8.1 Reaction Gear Cracks	1	
2.1.2.8.2 Ring Gear Cracks	1	
2.1.2.8.3 Back Cover Cracks	1	
2.1.2.8.4 Front Cover Cracks	1	
2.2 Actuator Receives Improper Command Signal from Amplifier		249
2.2.1 Amplifier Supply Voltage is not Correct Value		AGC
2.2.2 Amplifier Fails Internally		30
2.2.3 Amplifier Receives Improper Feedback Signal		219
2.2.3.1 Potentiometer Supply Voltage is Wrong Value	30	
2.2.3.1.1 Mechanism Wiring Harness Fails	30	
2.2.3.1.2 Voltage Supplied to System is in Error	AGC	
2.2.3.2 Feedback Potentiometer Out put Fails	154	
2.2.3.2.1 Potentiometer Electrically Fails	101	
2.2.3.2.1.1 Track Resistance Value Changes	10	
2.2.3.2.1.2 Protective Resistor Changes Value	10	
2.2.3.2.1.3 Wiper Resistance Changes Value	1	
2.2.3.2.1.4 Wiper/Track Contact Resistance Changes	80	
2.2.3.2.2 Angular Relationship Pot to Valve Changes	21	
2.2.3.2.2.1 Pot Position Changes Relative to Output Shaft	20	
2.2.3.2.2.2 Output Shaft Changes Relative to Valve	1	
2.2.3.2.3 Potentiometer Mechanically Fails	32	

2.2.3.2.3.1 Potentiometer Shaft Fails	1		
2.2.3.2.3.2 Wiper Spring Gradient Changes	1		
2.2.3.2.3.3 Bearings Fail	10		
2.2.3.2.3.4 Potentiometer Housing Fractures	20		
2.2.3.3 Feedback Signal Transmitted Improperly		35	
2.2.3.3.1 Wiring Harness to Amplifier Fails	AGC		
2.2.3.3.2 Mechanism Wiring Harness Fails	30		
2.2.3.3.3 Electromagnetic Interference Distorts Signal	5		
2.3 Output Shaft Fails to Position Valve			110
2.3.1 Crown Spline Fails		10	
2.3.2 Output Gear/Shaft Spline Joint Fails		80	
2.3.3 Shaft Breaks		20	
2.4 Actuator Internal Load Changes			664
2.4.1 Potentiometer Load Changes		10	
2.4.2 Actuator Drive Train Loads Change		654	
2.4.2.1 Ring Gear/Back Cover Friction Increases		62	
2.4.2.1.1 Reaction Gear Contracts	1		
2.4.2.1.2 Ring Gear Expands or Warps	10		
2.4.2.1.3 Bearings Allow Ring Gear to Skew	30		
2.4.2.1.3.1 Bearing Fails	10		
2.4.2.1.3.2 Cover Fails Allowing Bearing to Move	5		
2.4.2.1.3.3 Bearing Retainer Fails	10		
2.4.2.1.3.4 Output Shaft Fails Allowing Bearing to Move	5		
2.4.2.1.4 Shaft Fails Allowing Ring Gear to Move	1		

2.4.2.1.5	Contaminants Lodge in the Gear Cover Clearance	20
2.4.2.2	Ring Gear Front Cover Friction Increases	62
2.4.2.2.1	Reaction Gear Contracts	1
2.4.2.2.2	Ring Gear Expands or Warps	10
2.4.2.2.3	Bearings Allow Ring Gear to Skew	30
2.4.2.2.3.1	Bearing Fails	10
2.4.2.2.3.2	Cover Fails Allowing Bearing to Move	5
2.4.2.2.3.3	Bearing Retainer Fails	10
2.4.2.2.3.4	Output Shaft Fails Allowing Bearing to Move	5
2.4.2.2.4	Shaft Fails Allowing Ring Gear to Move	1
2.4.2.2.5	Contaminants Lodge in the Gear Cover Clearance	20
2.4.2.3	Reaction Gear Ring Gear Loads Increase	20
2.4.2.3.1	Ring Gear Fails	5
2.4.2.3.2	Reaction Gear Fails	5
2.4.2.3.3	Contaminants Bind Gear Mesh	10
2.4.2.4	Vane Load Levels Increase	3 60
2.4.2.4.1	Vanes Fail and Bind Motion	180
2.4.2.4.2	Ring Gear Vane Sockets Fail	90
2.4.2.4.3	Reaction Gear Vane Sockets Fail	90
2.4.2.5	Ring Gear Output Gear Joint Fails	50
2.4.2.5.1	Ring Gear Fails	20
2.4.2.5.2	Output Gear Fails	20
2.4.2.5.3	Contaminants in Gear Mesh	10
2.4.2.6	Shaft Seal Friction Increases	100

2.5 Control Drum Characteristics Change	AGC
3. Actuator Electrical Power Consumption Rate Exceeds Limits	60
3.1 Actuator/Amplifier External Cable Short Circuits	AGC
3.2 Actuator Amplifier Short Circuits	20
3.3 Mechanism Short Circuits Internally	40
3.3.1 Potentiometer Short Circuits	10
3.3.2 Wiring Harness System Short Circuits	20
3.3.3 Torquemotor Short Circuits	10

2.3.7.2 Failure Mode Evaluation

A failure mode analysis is prepared for each control drum actuator concept under consideration. As the actuator concepts are not completely detailed designs, the failure mode analyses are studies of arbitrarily selected groups of parts that form basic components within each actuator rather than studies of individual parts. In generating the failure mode analyses, each component is analyzed for possible modes of failure. These failure modes are identified and listed. Then, each failure mode is analyzed and the component failure mechanisms which cause the particular failure mode are identified and listed.

A reliability comparison of each actuator concept is accomplished by using a rating technique which utilizes a relative failure probability number based on a scale ranging from 1 to 10. The relative failure probability number is assigned to each component failure mechanism and represents an estimated probability of failure due to the particular failure mechanism. On the scale, 1 represents the lowest probability of failure and 10 represents the highest.

The failure mode analysis for this particular actuator concept is reported in detail in the CDA Trade Study Report.⁽¹⁵⁾ The total relative failure probability number reported in this analysis is 210. In performing the analysis it is recognized that the work accomplished is directly applicable to the SSCSS actuator trade study. To avoid repeating the details of the analysis, and for the purpose of this subject study, only the total relative failure probability number is reported.

2.3.7.3 Safety Evaluation

The inherent safety and criticality of any failure is an important parameter to be considered in making a selection of a recommended concept. To determine a relative safety and criticality ranking for each concept, failure modes are identified. For each of the failure modes listed, mechanisms of obtaining that failure mode are established as they relate to a particular design. Each of these failure mechanisms is given a numerical ranking consistent with its effect on the NSS and engine mission. Four categories of criticality are used to determine the safety rating of each concept as follows:

<u>Ranking</u>	<u>Description</u>
4	Failures resulting in gross core failure or possibly affecting structural integrity; crew safety jeopardized; African window safety in question.
3	Failures requiring corrective action resulting in reductions in chamber pressure/temperature below the emergency recovery mode level.
2	Failures requiring corrective action resulting in reduction in chamber temperature/pressure but not below emergency recovery mode level; completion of mission in question.
1	Failures resulting in insignificant effects on chamber temperature/pressure.

By assigning each mechanism of failure to one of the above categories, and finally obtaining a sum of all of the failure mechanisms, a total relative criticality ranking is obtained for each concept. The lower the total number estimate for a concept, the safer that concept is in relationship to the other concepts considered. The CDA Trade Study⁽¹⁵⁾ presents a tabulation of the failures, mechanism of failure and criticality ranking of failure for the Dynavector pneumatic actuator. The total criticality ranking for this concept is 352.

2.3.8 Evaluation of Concept

Basically, this proposed NERVA concept utilizes a standard Dynavector actuator modified to accept a feedback potentiometer and a servovalve. The feedback potentiometer is the same as that developed in the XE program, but it could be designed to utilize the concentrically mounted potentiometers of the other pneumatic designs. The potentiometer will be isolated from induced shaft vibration by mounting with a bellows coupling. The potentiometer to be used in this concept is a first redesign of the XE version. The servovalve is the same design as shown in all the proportional pneumatic actuator concepts.

The concept of a pneumatic Dynavector actuator applied to the NERVA environment is, in essence, the crux of the problem. The only information available in regard to performance and capability of the basic unit is at elevated and/or ambient temperatures. No Dynavector has yet been critically subjected to the extreme operational conditions of hydrogen gas at 140°R or lower, or radiation, shock, or vibration.

A rather ambitious development program would be required to evaluate the ability of the Dynavector to withstand NERVA operation and environment. First, the vane-to-housing and vane-to-gear joints are regarded as highly susceptible to wear, binding and leakage. Second, the ability to control the critical clearance between the end caps and reaction gear must be present. This clearance must be controlled at a value of 4 to 6 ten thousandths to minimize drive gas leakage. The question immediately arises as to how well this clearance be maintained over the broad temperature range of operation as required in the NERVA project.

Reliability estimates indicate that it is not as reliable as the single piston rack and pinion design and would offer no incentive for use. Little or no experience exists with this concept in the NERVA environment, which is a distinct disadvantage. The actuator radial width at the output shaft centerline is about 6.1 inches. Its height above the mounting boss is about 7 inches. Clearance required above the actuator for removal is 1.1 inches to clear the output shaft. Its weight is about 12 pounds. Coolant requirements for a one hour run at the heating rates estimated for NERVA, about 3 watts per pound, are less than one-half pound and can probably be neglected. Maximum drive gas at 100°R and 200 psi for a one hour run is about 36 pounds. Electrical power is required to supply the amplifier and feedback potentiometer, but is all in the control range and is considered small enough to be neglected for this study. A preliminary estimate of the concept reliability obtained by calibrating the fault tree is 0.9₅83. Table 2-8 is a summary listing some of the more significant advantages and disadvantages.

2.4 ELECTRIC PROPORTIONAL ACTUATOR - STEPPING MOTOR CONCEPT

Electric stepping motors have been used successfully in space and nuclear applications. In some of these applications the environment to which the motor was subjected was

TABLE 2-8

PNEUMATIC DYNAVECTOR SSCV ACTUATOR SUMMARY TABLE

<u>Advantages</u>	<u>Disadvantages</u>
1. Servovalve Design of Other Candidate Pneumatic Actuators is Directly Applicable.	1. Environmental Capabilities are Unknown.
2. Mechanism Weight is Low.	2. Ability to Seal H_2 Internally with Controlled Clearances Over Temperature Ranges Required and Wearing of Parts is Highly Questionable.
3. Mechanism Readily Remotely Removable.	3. Severe Weight Penalty Exists for the Drive Gas Startup Pneumatic Supply System Weight Required Due to Actuator Consumption of H_2 .
4. Highly Probable that No Coolant Gas Will Be Required.	4. Very Little Experience or Background Exists For this Design Applied to NERVA Environmental Conditions.
5. XE Actuator Potentiometer Experience is Directly Applicable.	5. Servovalve Susceptible to Malfunction at Cryogenic Temperatures if H_2 Supply is not Free of Trace Gas Contaminants.
	6. Maintainability Factors are Unknown.
	7. Dynamic Shaft Seal Required at Mounting Pedestal Interface.
	8. Vibration Effects of Orbiting Ring Gear Unknown.

similar to those expected in the NERVA application. The programs involving stepping motors are the Mariner and Surveyor spacecraft, a lithium cooled reactor (1964), SNAP-50, SNAP-10A and SNAP-8. Detailed information regarding the use of the stepper motor in these programs with a descriptive background of stepping motors for actuation devices is presented in the CDA Trade Study Report,⁽¹⁵⁾ Section 2.4.

2.4.1 Responsyn Concept

2.4.1.1 Mechanical Description

The Responsyn stepping motor used in this actuator concept is shown in Figure 2-17. As depicted, the motor incorporates a Harmonic drive system as a transmission. This motor unit can be used to directly drive the SSCV as shown in Figure 2-18, or it can be used by incorporating a single pass planetary gear train. The CDA Trade Study Report,⁽¹⁵⁾ Section 2.4.1, gives a complete mechanical description of both concepts, and is directly applicable for the purpose of this SSCV actuator trade study.

2.4.1.2 System Description

The Responsyn stepping motor converts digital, electrical format into uniform discrete valve angle positions within the resolution requirements of the SSCSS. The digital format is a four-bit cyclic binary code in which two adjacent bits are in the "ON" state while the other two are in the "OFF" state. The "ON" state represents a constant current in a particular phase winding of the motor while the "OFF" state represents no current.

Because of the precise angular positioning ability of the Responsyn motor, the valve position may be programmed to move to a predetermined angle (shim worth). This can be achieved by counting the number of pulses delivered to the control system code generator. In this manner the actuator may be operated in an open loop fashion since the amount and rate of angular change are both controllable. The actuator may also be operated as a closed loop system where the input pulses are proportional to the difference between the commanded valve position and the position indicator (feedback potentiometer) output.

A detailed explanation of this control system scheme is given in the CDA Trade Study Report TME 1984.⁽¹⁵⁾ It is recommended as a reference for the details of the SSCV actuator system.

Figure 2-17 Responsyn Stepping Motor

612930-7B

Figure 2-18 Proportional Electric Responsyn Direct Drive SSCV Actuator

2.4.1.3 Radiation Analysis

The radiation analysis reported in Section 2.1.3 is directly applicable to the Responsyn stepping motor electrical actuator system concept. The radiation environment listed in Table 2-2 is unperturbed by the presence of the SSCV actuator mechanism. In addition, the predicted levels are considered conservative, when applied to the SSCV actuator analysis.

2.4.1.4 Thermal Evaluation

The radiation heating environment of the proposed electrical SSCV actuator, Responsyn concept is similar to that of the other candidate actuators, and it is expected that in this low heating rate environment, the actuator structure and components may be adequately cooled. The coolant requirements will vary as the size and weight of the actuator and its internal heat generation rate.

The Electric Actuator has heavy iron or steel masses in the motor rotor and thick stator coils and metal poles that will require adequate cooling. These heavy sections appear capable of being designed to assure thermal adequacy in the operating environment.

The Responsyn stepping motor incorporates a flexspline power and gear reduction transmission system. This flexspline would be operating in a cryogenic environment. Care in the selection of material used in this component will be required, as it is a component with cycling loads imposed on it at cryogenic conditions in a nuclear radiation field.

The alternate to the flexspline is a planetary gear assembly. One concern in this type of operation is the effect on alignment and gear wear of thermal expansion variation from ambient (or above ambient) temperatures to cryogenic temperatures in which the planetary gear will operate.

2.4.1.5 Structural Evaluation

The basic difference between the pneumatic actuators and the electric actuators is the method of supplying torque to the drive shaft. The drive gas and servovalve assembly, which are required in the pneumatic actuators, are eliminated in the electric actuator concepts. The Responsyn stepping motor actuator consists of three main assemblies, feedback potentiometer, drive assembly, and housing enclosure.

The feedback potentiometer is primarily an electrical device used to measure output position and no structural problems are anticipated.

The basic component in the drive assembly of this actuator is the Responsyn stepping motor. The major structural components which actually form the transmission are a rigid, internally splined circular spline, a non-rigid, extremely splined flexspline, and a wave generator which deflects the flexspline. If this design is selected, these structural components will be analyzed in detail and the structural reliability of the complete stepping motor should be determined by component testing. A potential problem area may be in the selection of a suitable material for the cryogenic operation of the flexspline.

In the Responsyn actuator concept, the motor output shaft is splined directly to the drive shaft; whereas, the planetary drive concept Responsyn actuator incorporates a speed reducer between the motor output shaft and the drive shaft. The speed reducer is a single pass planetary gear train. If the planetary drive Responsyn actuator is selected, the bending stresses, contact stresses, fatigue life, surface wear, material selection and thermal distortions of the gears will be considered in depth.

The housing enclosure for the Responsyn actuator is in general similar to that of the rack and pinion pneumatic actuator discussed in Section 2.1.5. Cooling gas is supplied to the Responsyn actuator housing exactly in the same manner as in the pneumatic actuators. If the Responsyn actuator is selected, the major areas of structural analysis concern will include mechanical and thermal stresses in the housing enclosure and the flange clamp loads and stresses. Proof tests should be performed on the asymmetrical housing enclosure to confirm the analytical stress analysis.

A V-Band clamp is used at the interface flange of the actuator housing. The clamping load and stresses in a V-Band clamp are difficult to predict analytically, because they are greatly influenced by the friction forces in the mating parts at assembly. Component tests should be performed to determine the loads and stresses in the clamp.

2.4.1.6 Radiation Effects Evaluation

The total expected radiation environment to which this actuator will be subjected

is given in Section 2.1.3. To assess the effects of this environment on the actuator, a comparison of known test environments with this expected environment will indicate the sensitivity of any given concept to successful operation in the expected radiation levels. The sensitive components in this concept are the motor coils, the potentiometer, the shaft seals, and the electrical insulation and potting compounds. All other materials used in the construction of the actuator are metals. Although detail designs are not available, final material selection will be made from lists of qualified materials or will be separately qualified.

2.4.1.6.1 Motor Coils. Although motors have not been directly tested on the NERVA program, tests on other devices give important information concerning the expected performance of motor winding rails in a radiation environment. The electric coils contained in a pneumatic actuator torque motor and in the lock shut-off solenoid are similar to those used in electric motor construction. Tests conducted in a radiation environment at the GTR facility, during the NRX-A6 pneumatic actuator side-by-side test,⁽⁸⁾ and tests conducted by the Lewis Research Center at the Plum Brook Reactor⁽⁹⁾ all included the electric coils mentioned above. No coil anomalies were reported during any of these tests. However, it is planned to take advantage of improvements in the state-of-the-art in insulation materials and use the polyimide series for future coil insulations to further improve radiation tolerance and increase coil reliability.

2.4.1.6.2 Potentiometer. A prototype potentiometer was also included in the tests described in the above section. A reported failure in the Lewis tests⁽⁹⁾ caused some concern until a subsequent post-irradiation examination revealed the failure was caused by a softening and flowing of a potting compound not included in the above mentioned GTR and NRX-A6 tests. Subsequent builds did not use this potting compound. Future controls will assure using only those specified materials that will not be subject to property changes under radiation environment.

2.4.1.6.3 Shaft Seals, Electrical Insulation and Potting Materials

Although these items and materials have been proven adequate for use in the NERVA environment, it is planned to take advantage of the improvements in the state-of-the-art in insulation materials. Furthermore, to expand the use of polyimide materials in wire insulation and potting materials to benefit in radiation tolerance and reliability.

2.4.1.7 Reliability and Safety Evaluation

The philosophy and approach in evaluating the reliability and safety of each actuator concept is presented in Section 2.1.7 of this report. The details of the approaches as applied to the evaluation of this particular actuator concept are reported in the following sub-paragraphs.

2.4.1.7.1 Fault Tree Evaluation

A portion of the reliability evaluation for this particular concept was accomplished through a fault tree analysis. Section 2.1.7.1 gives a precise description as to how the fault trees are generated, calibrated, and implemented in evaluating the reliability of a particular actuator concept. Figures 2-19 and 2-20 are the summary of the respective fault trees and the weighted numbers used for evaluation of each Responsyn concept. Tables 2-9 and 2-10 present a listing of the detailed fault trees and their assigned weighted numbers.

2.4.1.7.2 Failure Mode Evaluation

A failure mode analysis is prepared for each control drum actuator concept under consideration. As the actuator concepts are not completely detailed designs, the failure mode analyses are studies of arbitrarily selected groups of parts that form basic components within each actuator rather than studies of individual parts. In generating the failure mode analyses, each component is analyzed for possible modes of failure. These failure modes are identified and listed. Then, each failure mode is analyzed and the component failure mechanisms which cause the particular failure mode are identified and listed.

A reliability comparison of each actuator concept is accomplished by using a rating technique which utilizes a relative failure probability number based on a scale ranging from 1 to 10. The relative failure probability number is assigned to each component failure mechanism and represents an estimated probability of failure due to the particular failure mechanism. On the scale, 1 represents the lowest probability of failure and 10 represents the highest.

Engineering judgement is used in estimating the relative failure probability number for each failure mechanism. A total number is calculated by adding the relative probability numbers. This technique is considered acceptable since the failure modes listed are independent and mutually exclusive of one another.⁽¹⁴⁾ The total number then indicates the relative

Figure 2-19 Resposyn Stepping Motor Electric Actuator Summary Fault Tree

Figure 2-20 Responsyn Electric Stepping Motor - Planetary Drive Summary Fault Tree

TABLE 2-9

DETAILED FAULT TREE ANALYSIS
(Responsyn Direct Drive)

Direct Drive Responsyn Stepping Motor Proportional Electric Actuator Reliability
 Fault Tree Analysis 939J953 Estimated Reliability 9₅89

			1048
1. Actuator Coolant Gas Consumption Exceeds Specified Limits			95
1.1 Actuator Housing Fails to Contain Coolant Gas			55
1.1.1 Cover Fails to Contain Coolant Gas		5	
1.1.2 Cover to Body Interface Joint Fails		9	
1.1.2.1 Seal Fails	6		
1.1.2.2 Cover Fasteners Fail	3		
1.1.3 Housing Body Fails to Contain Coolant Gas		1	
1.1.4 Electrical Connector Fails to Contain Gas		40	
1.1.4.1 Seal Fails	30		
1.1.4.2 Fasteners Lose Clamping Force	5		
1.1.4.3 Connector Body Fails to Contain Gas	5		
1.2 Housing to Pedestal Interface Fails to Contain Gas			40
1.2.1 Interface Inlet Coolant Seal Fails		30	
1.2.2 Fasteners Lose Clamping Force		5	
1.2.3 Interface Exhaust Coolant Passage Seal Fails		5	
2. Actuator Fails to Position Control Drum Within Time Position Band			871
2.1 Actuator Fails to Convert Electrical to Mechanical Power			131
2.1.1 Electrical Connector Fails to Transmit Proper Signal		10	
2.1.1.1 Conductor Fails to Transmit Signal	5		
2.1.1.2 Insulator Fails Permitting Short Circuit	5		

TABLE 2-9 (CONTINUED)

2.1.2	Motor Fails Electrically		86
2.1.2.1	Wiring Failure		80
2.1.2.2	Pole Pieces Break		1
2.1.2.3	Flexspline Magnetic Properties Deteriorate		5
2.1.3	Actuator Internal Wiring Harness Fails		35
2.1.3.1	Conductor Fails		5
2.1.3.2	Insulation Fails		25
2.1.3.3	Terminal Mechanically Fails		5
2.2	Improper Command Received from Amplifier		279
2.2.1	Amplifier Control Voltage Incorrect		AGC
2.2.2	Amplifier Fails Internally		30
2.2.3	Amplifier Feedback Signal Incorrect		249
2.2.3.1	Potentiometer Supply Voltage Wrong Value		30
2.2.3.1.1	Actuator System Wiring Harness Fails	30	
2.2.3.1.2	Voltage Supplied is in Error	AGC	
2.2.3.2	Feedback Potentiometer Output Fails		154
2.2.3.2.1	Potentiometer Electrically Fails	101	
2.2.3.2.1.1	Track Resistance Value Changes	10	
2.2.3.2.1.2	Protective Resistor Changes Value	10	
2.2.3.2.1.3	Wiper Resistance Value Changes	1	
2.2.3.2.1.4	Wiper to Track Contact Resistance Changes	80	
2.2.3.2.2	Angular Relationship Pot to Drum Changes	21	
2.2.3.2.2.1	Pot Position Relative to Shaft Changes	20	
2.2.3.2.2.2	Shaft Relative to Drum Changes	1	

TABLE 2-9 (CONTINUED)

2.2.3.2.3	Potentiometer Mechanically Fails	32	
2.2.3.2.3.1	Potentiometer Shaft Fails	1	
2.2.3.2.3.2	Wiper Spring Gradient Changes	1	
2.2.3.2.3.3	Bearings Fail	10	
2.2.3.2.3.4	Potentiometer Housing Fractures	20	
2.2.3.3	Feedback Signals Transmitted Improperly	65	
2.2.3.3.1	Wiring Harness Pedestal to Amplifier Fails	AGC	
2.2.3.3.2	Pedestal Wiring Harness Fails	30	
2.2.3.3.3	Mechanism Wiring Harness Fails	30	
2.2.3.3.4	Electro-Magnetic Interference Distorts Signal	5	
2.3	Actuator External Control Drum Loads Change		EC 677559
2.4	Actuator Internal Loads Change		461
2.4.1	Flexspline Fails to Transmit Sufficient Torque	260	
2.4.1.1	Teeth Fail to Transmit Torque	150	
2.4.1.1.1	Teeth Break	100	
2.4.1.1.2	Teeth Wear	50	
2.4.1.2	Fastener Interferes with Motion	10	
2.4.1.3	Laminations Fail	20	
2.4.1.3.1	Laminations Crack or Buckle	10	
2.4.1.3.2	Magnetic Material to Cup Bond Breaks	10	
2.4.1.4	Cup Fails to Transmit Motion	80	
2.4.1.4.1	Weld Fails	30	
2.4.1.4.2	Cup Breaks	50	
2.4.2	Motor Fails Mechanically to Provide Sufficient Torque	91	
2.4.2.1	Spline Mesh Friction Increases	5	
2.4.2.2	Fasteners Interfere with Motion	10	

TABLE 2-9 (CONTINUED)

2.4.2.3	Stator Wiring Interferes with Motion	76	
2.4.2.3.1	Actuator Housing Distorts	1	
2.4.2.3.2	Stator Potting Material Deteriorates	10	
2.4.2.3.3	Conductor at I.D. of Motor Breaks	5	
2.4.2.3.4	Pole Pieces Break	60	
2.4.3	Output Shaft-Pot Bearings Friction Level Increases		70
2.4.4	Output Shaft Fails to Transmit Torque		40
2.4.4.1	Teeth Break	10	
2.4.4.2	Shaft Breaks	20	
2.4.4.3	Cup to Shaft Coupling Fails	10	
3.	Actuator Electrical Power Rate Exceeds Specified Limits		82
3.1	Actuator Short Circuits		41
3.1.1	Potentiometer Internal Short Circuit	10	
3.1.2	Stator Wiring Insulation Fails Allowing Short Circuit	10	
3.1.3	Wiring Harness System Short Circuits	21	
3.1.3.1	Interface Connector Short Circuits	10	
3.1.3.2	Wiring Insulation Fails	10	
3.1.3.3	Terminal Fails	1	
3.2	Amplifier Internal Short Circuit		20
3.3	Pedestal Short Circuit Failure		21
3.3.1	Wiring Insulation Fails Permitting Short Circuit	10	
3.3.2	Terminal Mechanical Failure	1	
3.3.3	External Connector Fails Allowing Short Circuit	10	
3.4	Amplifier/Actuator External Cable Short Circuit Failure		AGC

TABLE 2-10

DETAILED FAULT TREE ANALYSIS
(Responsyn Planetary)

Responsyn Planetary Drive Stepping Motor Proportional Electric Actuator Reliability
Fault Tree Analysis 939J952 Estimated Reliability .9587

1271

1. Actuator Coolant Gas Consumption Exceeds Specified Limits			123
1.1 Actuator Housing Fails to Contain Coolant Gas			15
1.1.1 Cover Fails to Contain Coolant Gas		5	
1.1.2 Cover to Body Interface Joint Fails		9	
1.1.2.1 Seal Fails	6		
1.1.2.2 Cover Fasteners Fails	3		
1.1.3 Housing Body Fails to Contain Coolant Gas		1	
1.2 Housing to Pedestal Interface Fails to Contain Gas			40
1.2.1 Interface Inlet Coolant Seal Fails		30	
1.2.2 Fasteners Lose Clamping Force		5	
1.2.3 Interface Exhaust Coolant Passage Seal Fails		5	
1.3 Actuator Pedestal Fails to Contain Coolant Gas			68
1.3.1 Weld Fails		15	
1.3.2 Inlet Line Connector Joint Fails to Contain Gas		12	
1.3.2.1 Seal Fails	5		
1.3.2.2 Connector Loosens	7		
1.3.3 Housing Body Ruptures		1	
1.3.4 Electrical Connector Joint Fails to Contain Gas		40	
1.3.4.1 Seal Fails	30		
1.3.4.2 Fasteners Fail	5		
1.3.4.3 Connector Body Fails	5		
2. Actuator Fails to Position Control Drum Within Time Position Band			1066

TABLE 2-10 (CONTINUED)

2.1	Actuator Fails to Convert Electrical to Mechanical Power		131
2.1.1	Electrical Connector Fails to Transmit Proper Signal		10
2.1.1.1	Conductor Fails to Transmit Signal	5	
2.1.1.2	Insulator Fails Permitting Short Circuit	5	
2.1.2	Motor Fails Electrically		86
2.1.2.1	Wiring Failure	80	
2.1.2.2	Pole Pieces Break	1	
2.1.2.3	Flexspline Magnetic Properties Deteriorate	5	
2.1.3	Actuator Internal Wiring Harness Fails		35
2.1.3.1	Conductor Fails	5	
2.1.3.2	Insulation Fails	25	
2.1.3.3	Terminal Mechanically Fails	5	
2.2	Improper Command Received from Amplifier		279
2.2.1	Amplifier Control Voltage Incorrect		AGC
2.2.2	Amplifier Fails Internally		30
2.2.3	Amplifier Feedback Signal Incorrect		249
2.2.3.1	Potentiometer Supply Voltage Wrong Value	30	
2.2.3.1.1	Actuator System Wiring Harness Fails	30	
2.2.3.1.2	Voltage Supplied is in Error	AGC	
2.2.3.2	Feedback Potentiometer Output Fails	154	
2.2.3.2.1	Potentiometer Electrically Fails	101	
2.2.3.2.1.1	Track Resistance Value Changes	10	
2.2.3.2.1.2	Protective Resistor Changes Value	10	
2.2.3.2.1.3	Wiper Resistance Value Changes	1	
2.2.3.2.1.4	Wiper to Track Contact Resistance Changes	80	
2.2.3.2.2	Angular Relationship Pot to Drum Changes	21	

TABLE 2-10 (CONTINUED)

2.2.3.2.2.1	Pot Position Relative to Shaft Changes	20		
2.2.3.2.2.2	Shaft Relative to Drum Changes	1		
2.2.3.2.3	Potentiometer Mechanically Fails		32	
2.2.3.2.3.1	Potentiometer Shaft Fails	1		
2.2.3.2.3.2	Wiper Spring Gradient Changes	1		
2.2.3.2.3.3	Bearings Fail	10		
2.2.3.2.3.4	Potentiometer Housing Fractures	20		
2.2.3.3	Feedback Signals Transmitted Improperly		65	
2.2.3.3.1	Wiring Harness Actuator to Amplifier Fails		AGC	
2.2.3.3.2	Pedestal Wiring Harness Fails	30		
2.2.3.3.3	Mechanism Wiring Harness Fails	30		
2.2.3.3.4	Electro-Magnetic Interference Distorts Signal	5		
2.3	Actuator External Control Drum Loads Change			EC
2.4	Actuator Internal Loads Change			64I
2.4.1	Flexspline Fails to Transmit Sufficient Torque		260	
2.4.1.1	Teeth Fail to Transmit Torque		150	
2.4.1.1.1	Teeth Break	100		
2.4.1.1.2	Teeth Wear	50		
2.4.1.2	Fastener Interferes with Motion		10	
2.4.1.3	Magnetic Material Characteristics Change		20	
2.4.1.3.1	Laminations Crack or Buckle	10		
2.4.1.3.2	Magnetic Material to Cup Bond Breaks	10		
2.4.1.4	Cup Fails to Transmit Motion		80	
2.4.1.4.1	Weld Fails	30		
2.4.1.4.2	Cup Breaks	50		
2.4.2	Motor Fails Mechanically			91
2.4.2.1	Spline Mesh Friction Increases			

TABLE 2-10 (CONTINUED)

2.4.2.2	Fasteners Interfere with Motion	10	
2.4.2.3	Stator Wiring Interferes with Motion	76	
2.4.2.3.1	Actuator Housing Distorts	1	
2.4.2.3.2	Stator Potting Material Deteriorates	10	
2.4.2.3.3	Conductor at I.D. of Motor Breaks	5	
2.4.2.3.4	Pole Pieces Break	60	
2.4.3	Output Shaft-Pot Bearings Friction Level Increases		70
2.4.4	Output Shaft Fails to Transmit Torque		30
2.4.4.1	Teeth Break	10	
2.4.4.2	Shaft Breaks	20	
2.4.5	Motor to Transmission Coupling Fails		80
2.4.5.1	Bearing Fails	50	
2.4.5.2	Coupling Gear Teeth Fail/Wear	10	
2.4.5.3	Fastener Loses Clamping Force	20	
2.4.6	Power Transmission Fails		110 ✓
2.4.6.1	Spider Fails	20	
2.4.6.2	Bearing Retainer Fails	5	
2.4.6.3	Driver Gear Teeth Wear/Fail	5	
2.4.6.4	Fastener Loses Clamping Force	5	
2.4.6.5	Bearing Fails	60	
2.4.6.6	Planet Gear Teeth Wear/Fail	15	
3.	Actuator Electrical Power Rate Exceeds Specified Limits		82
3.1	Actuator Short Circuits		41
3.1.1	Potentiometer Internal Short Circuit	10	
3.1.2	Stator Wiring Insulation Fails Allowing Short Circuit	10	
3.1.3	Wiring Harness System Short Circuits	21	

TABLE 2-10 (CONTINUED)

3.1.3.1 Interface Connector Short Circuits	10	
3.1.3.2 Wiring Insulation Fails	10	
3.1.3.3 Terminal Fails	1	
3.2 Amplifier Internal Short Circuit		20
3.3 Pedestal Short Circuit Failure		21
3.3.1 Wiring Insulation Fails	10	
3.3.2 Terminal Mechanical Failure	1	
3.3.3 External Connector Short Circuit	10	
3.4 Amplifier/Actuator External Cable Short Circuit Failure		AGC

reliability of the actuator concept; the lower the number, the more reliable the particular concept is relative to the others. Each concept is compared with the others on the basis of the total relative failure probability number.

The failure mode analysis for each of these particular actuator concepts is reported in detail in the Control Drum Actuator Trade Study Report, TME 1984.⁽¹⁵⁾ The total relative failure probability number reported in this analysis is 122 for the direct drive and 135 for the planetary drive. In performing the analysis, it was recognized that the work accomplished is directly applicable to the SSCSS actuator trade study. To avoid repeating the details of the analysis and for the purpose of this subject study only the total relative failure probability number is reported.

2.4.1.7.3 Safety Evaluation

The inherent safety and criticality of any failure is an important parameter to be considered in making a selection of a recommended concept. To determine a relative safety and criticality ranking for each concept, failure modes have been identified. For each of the failure modes listed, mechanisms of obtaining that failure mode are established as they relate to a particular design and each of these failure mechanisms is given a numerical ranking consistent with its effect on the NSS and engine mission. Four categories of criticality are used to determine the safety rating of each concept as follows:

<u>Ranking</u>	<u>Description</u>
4	Failures resulting in gross core failure or possibly affecting structural integrity; crew safety jeopardized; African window safety in question.
3	Failures requiring corrective action resulting in reduction in chamber pressure/temperature below the emergency recovery mode level.

2	Failures requiring corrective action resulting in reduction in chamber temperature/pressure but not below emergency recovery mode level; completion of mission in question.
1	Failures resulting in insignificant effects on chamber temperature/pressure.

By assigning each mechanism of failure to one of the above categories, and finally obtaining a sum of all of the failure mechanisms, a total relative criticality ranking is obtained for each concept. The lower the total number estimate for a concept, the safer that concept is in relationship to the other concepts considered. The CDA Trade Study Report, TME 1984,⁽¹⁵⁾ presents a tabulation of the failures, mechanism of failure and criticality ranking of failure for the Responsyn stepping motor actuator. The total criticality ranking for this concept from that analysis is 120 for the direct drive and 160 for the planetary drive system.

2.4.1.8 Evaluation of Concept

The high reliability of the direct drive Responsyn actuator in comparison to other electrical actuator concepts is due primarily to its fewer parts, its simple internal transmission and its all low-speed bearings. Drive component alignment is not critical and there is little change in performance with temperature. Its advantages in common with other stepping motor concepts are low inertia with resultant fast response, inherent braking and fast reversibility.

Relatively higher power requirements and the large envelope diameter required and the fact that the Responsyn requires continuous power to hold position are all definite disadvantages for this concept.

An industrial model Responsyn stepping motor (Model HDUM-30-100-04) was procured and tested at WANL under the scope of test documents TS:85DA-182-0 and TS:85DA-186-0. Primary testing was performed to establish frequency response, transient response, linearity, resolution and power requirements as well as loss of power failure modes. Test procedure and results are reported in WANL-TME-1921. The test results indicate that the

Responsyn direct drive, while having a very high reliability potential and excellent operating characteristics, would require a good deal more power and a larger envelope than the other electrical stepping motor actuator candidates being considered for NERVA application. The use of a smaller Responsyn by adding a single stage planetary reduction to more nearly match the Responsyn to the load reduces the power requirements at the expense of reliability.

The Responsyn direct drive proportional electric actuator width at the output shaft centerline is about 6.9 inches. Its height above the mounting boss is also about 6.9 inches. The clearance required above the actuator for removal is about 1-3/4 inches to clear the output shaft. The direct drive Responsyn actuator is estimated to weigh about 17 pounds.

Coolant requirements for a one-hour run at the heating rates estimated for NERVA, about 3 watts per pound, are less than 1 pound and in all likelihood can be neglected. The main electrical power required is on the order of 100 watts with a reduced power of 50 watts assumed to provide a holding torque when the actuator is not moving. Signal level power to supply the feedback potentiometers and control amplifier is small and has been neglected for this comparative study. A preliminary estimate of the concept reliability obtained by calibrating the fault tree is $.9_{5}^{89}$. Table 2-11 is a listing of some of the more significant advantages and disadvantages of the direct drive Responsyn concept.

To reduce the power requirements and more nearly match the load, a smaller Responsyn with an additional planetary gear stage instead of direct drive high reliability was considered. The Responsyn planetary proportional electric actuator width at the shaft centerline is about 6.5 inches. Its height above the SSCV mounting boss is about 5.1 inches. Clearance required above the actuator for removal is about 3.9 inches to clear the output shaft and planetary gear reduction which has been recessed into the pedestal. The planetary drive Responsyn actuator is about 9.8 pounds.

Coolant requirements for a one hour run at the heating rates estimated for NERVA, about 3 watts per pound, are less than 1/2 pound and can probably be neglected. The main electrical power required is on the order of 30 watts with a reduced power to 15 watts assumed to provide a holding torque when the actuator is not moving. Signal level power to supply the feedback potentiometers and control amplifier is small and has been neglected for this comparative study. A preliminary estimate of the concept reliability obtained by calibrating

TABLE 2-11

RESPONSYN DIRECT DRIVE SSCV ACTUATOR CONCEPT SUMMARY TABLE

<u>Advantages</u>	<u>Disadvantages</u>
1. Few Moving Parts.	1. High Power Consumption.
2. Low Speed Bearings	2. Low Efficiency.
3. Velocity Programmable.	3. High Current.
4. Inherent Braking.	4. Mechanism Weight is High.
5. Excellent Response Time.	5. Must be Energized Continuously to Hold Position Against Valve Hydraulic Loads.
6. High Resolution.	

the fault tree is .9₅⁸⁷. Table 2-12 is a listing of some of the significant advantages and disadvantages of the Responsyn planetary concept.

2.4.2 Slo-Syn Concept

2.4.2.1 Mechanical Description

The application of a Slo-Syn motor, Figure 2-21, as an SSCV actuator system concept is basically the same system as described in the CDA Trade Study, TME 1984⁽¹⁵⁾ Section 2.4.2. The major difference is that for the SSCV application the motor size would be larger and the driver would be a high speed translator. By using a larger torque output motor and a high speed translator the torque-speed characteristics required for the SSCV application can be achieved when driving through a Harmonic drive transmission as shown in Figure 2-22.

2.4.2.2 System Description

The Slo-Syn stepping motor converts digital, electrical format into uniform discrete valve angle positions within the resolution requirements of the SSCSS. The digital format is a four-bit cyclic binary code in which two adjacent bits are in the "ON" state while the other two are in the "OFF" state. The "ON" state represents a constant current in a particular phase winding of the motor while the "OFF" state represents no current.

Because of the precise angular positioning ability of the Slo-Syn motor, the valve position may be programmed to move to a predetermined angle (shim worth). This can be done by counting the number of pulses delivered to the control system code generator. In this manner, the actuator may be operated in an open loop fashion because the amount and rate of angular change are both controllable. The actuator may also be operated as a closed loop system where the input pulses are proportional to the difference between the commanded valve position and the position indicator (feedback potentiometer) output.

A detailed explanation of this control system scheme is given in the CDA Trade Study Report TME 1984⁽¹⁵⁾ and is a reference for details of the SSCV actuator system.

2.4.2.3 Radiation Analysis

The radiation analysis reported in Section 2.1.3 is directly applicable to the Slo-Syn stepping motor electrical actuator system concept. The radiation environment listed in Table 2-2 is unperturbed by the presence of the actuator mechanism. In addition, the predicted levels are considered conservative.

TABLE 2-12

RESPONSYN/PLANETARY SSCV ACTUATOR CONCEPT SUMMARY TABLE

<u>Advantages</u>	<u>Disadvantages</u>
1. Relatively Low Speed Bearings.	1. High Power Consumption.
2. Velocity Programmable By Pulse Rate.	2. Low Efficiency.
3. Inherent Braking.	3. High Current.
4. Closed Loop Response Meets or Exceeds Requirements.	4. Mechanism Weight is Relatively High.
5. High Resolution.	5. Must be Energized Continuously to Hold Position Against Valve Hydraulic Loads.

612930-4B

Figure 2-21 Proportional Electric Slo-Syn Motor SSCV Actuator, Harmonic Drive

(b) Simplified Transmission Assembly

Figure 2-22 Harmonic Drive Transmission

2.4.2.4 Thermal Evaluation

The radiation environment of the Slo-Syn concept is generally similar to the Responsyn concept with low heating rates and SSCV cryogenic coolant available. The problems associated with adequate cooling of the electrical motor rotor and stator are also similar. The flexible-spline drive would require close detailed analysis to assure its thermal and structural adequacy in the operating environment. Thus, the Slo-Syn type stepping motor is judged to be thermally very similar to the Responsyn Stepping motor.

2.4.2.5 Structural Evaluation

Structurally, the Slo-Syn stepping motor actuator is similar to the Responsyn stepping motor discussed in Section 2.4.1.5. The basic difference between the two designs is the type of electric stepping motor used to generate torque.

The Responsyn motor is a variable reluctance motor with an integral transmission (the rotating magnetic field surrounds the rigid spline, flexspline and output shaft). The Slo-Syn motor is a permanent magnet rotor stepping motor connected to a separate transmission. The rotating magnetic field in the Slo-Syn motor drives the rotor shaft which is connected to the transmission. The transmission consists of a rigid, internally splined circular spline, a non-rigid, externally splined flexspline, and a wave generator which are similar to those in the Responsyn motor. If the Slo-Syn actuator is selected from this trade study, the structural reliability of the Slo-Syn unit should be verified by analysis and/or component tests.

The structural evaluation of the transmission, feedback potentiometer and housing enclosure for this actuator is identical to that of the Responsyn actuator discussed in Section 2.4.1.5.

2.4.2.6 Radiation Effects Evaluation

The total expected radiation environment to which this actuator will be subjected is given in Section 2.1.3. To assess the effects of this environment on the actuator, a comparison of known test environments with this expected environment will indicate the sensitivity of any given concept to successful operation in the expected radiation levels. The sensitive components in this concept are the motor coils, the potentiometer, the shaft seals, and the electrical

insulation and potting compounds. All other materials used in the construction of the actuator are metals. Although detail designs are not available, final material selection will be made from lists of qualified materials or will be separately qualified.

2.4.2.6.1 Motor Coils

Although motors have not been directly tested on the NERVA program, tests on other devices give important information concerning the expected performance of motor winding rails in a radiation environment. The electric coils contained in a pneumatic actuator torque motor and in the lock shut-off solenoid are similar to those used in electric motor construction. Tests conducted in a radiation environment at the GTR facility, during the NRX-A6 pneumatic actuator side-by-side test,⁽⁸⁾ and tests conducted by the Lewis Research Center at the Plum Brook Reactor⁽⁹⁾ all included the electric coils mentioned above. No coil anomalies were reported during any of these tests. However, it is planned to take advantage of improvements in the state-of-the-art in insulation materials and use the polyimide series for future coil insulations to further improve radiation tolerance and increase coil reliability.

2.4.2.6.2 Potentiometer

A prototype potentiometer was also included in the tests described in the above section. A reported failure in the Lewis tests⁽⁹⁾ caused some concern until a subsequent post-irradiation examination revealed the failure was caused by a softening and flowing of a potting compound not included in the GTR and NRX-A6 tests. The material that failed was used in very early model potentiometers but has since been removed. Future controls will assure using only those specified materials that will not be subject to property changes under radiation environments.

2.4.2.6.3 Shaft Seals, Electrical Insulation and Potting Materials

Although these items and materials are adequate for use in the NERVA environment, it is planned to take advantage of the improvements in the state-of-the-art in insulation materials. Polyimide materials will be used in wire insulation and potting materials to increase radiation tolerance and reliability.

2.4.2.7 Reliability and Safety Evaluation

The philosophy and approach in evaluating the reliability and safety of each actuator concept is presented in Section 2.1.7. The details of the approaches as applied to the evaluation of this particular actuator concept are reported in the following sub-paragraphs.

2.4.2.7.1 Fault Tree Evaluation

A portion of the reliability evaluation for this particular actuator concept was accomplished through a fault tree analysis. Section 2.1.7.1 gives a precise description as to how the fault trees are generated, calibrated, and implemented in evaluating the reliability of a particular actuator concept. Figure 2-23 is a summary of the fault tree used in the evaluation. Table 2-13 presents the details of the fault tree and weighted evaluation used for each failure. The total of the weighted numbers is 1282.

2.4.2.7.2 Failure Mode Evaluation

A failure mode analysis is prepared for each actuator system concept under consideration. As the actuator concepts are not completely detailed designs, the failure mode analyses are studies of arbitrarily selected groups of parts that form basic components within each actuator rather than studies of individual parts. In generating the failure mode analyses, each component is analyzed for possible modes of failure. These failure modes are identified and listed. Then, each failure mode is analyzed and the component failure mechanisms which cause the particular failure mode are identified and listed.

A reliability comparison of each actuator concept is accomplished by using a rating technique which utilizes a relative failure probability number based on a scale ranging from 1 to 10. The relative failure probability number is assigned to each component failure mechanism and represents an estimated probability of failure due to the particular failure mechanism. On the scale, 1 represents the lowest probability of failure and 10 represents the highest.

Engineering judgement is used in estimating the relative failure probability number for each failure mechanism. A total number is calculated by adding the relative probability numbers. This technique is considered acceptable since the failure modes listed are independent and mutually exclusive of one another.⁽¹⁴⁾ The total number then indicates the relative

Figure 2-23 Harmonic Drive/Slo-Syn Stepping Motor Summary Fault Tree

TABLE 2-13

**DETAILED FAULT TREE ANALYSIS
(Slo-Syn Electric Stepping Motor)**

Slo-syn Stepping Motor/Harmonic Drive Motor Proportional Electric Actuator Reliability
Fault Tree Analysis 939J957 Estimated Reliability .9587

1282

1. Actuator Coolant Gas Consumption Exceeds Specified Limits		95
1.1 Actuator Housing Fails to Contain Coolant Gas		55
1.1.1 Cover Fails to Contain Coolant Gas	5	
1.1.2 Cover to Body Interface Joint Fails	9	
1.1.2.1 Seal Fails	6	
1.1.2.2 Cover Fasteners Fail	3	
1.1.3 Housing Body Fails to Contain Coolant Gas	1	
1.1.4 Electrical Connector Fails to Contain Gas	40	
1.1.4.1 Seal Fails	30	
1.1.4.2 Fasteners Lose Clamping Force	5	
1.1.4.3 Connector Body Fails to Contain Gas	5	
1.2 Housing to Pedestal Interface Fails to Contain Gas		40
1.2.1 Interface Inlet Coolant Seal Fails	30	
1.2.2 Fasteners Lose Clamping Force	5	
1.2.3 Interface Exhaust Coolant Passage Seal Fails	5	
2. Actuator Fails to Position Control Drum Within Time Position Band		1126
2.1 Actuator Fails to Convert Electrical to Mechanical Power		141
2.1.1 Electrical Connector Fails to Transmit Proper Signal	10	
2.1.1.1 Conductor Fails to Transmit Signal	5	
2.1.1.2 Insulator Fails Permitting Short Circuit	5	

TABLE 2-13 (CONTINUED)

2.1.2	Motor Fails Electrically		96
2.1.2.1	Wiring Failure	80	
2.1.2.2	Pole Pieces Break	1	
2.1.2.3	Loss of Permanent Magnet Bond to Shaft	5	
2.1.2.4	Loss of Rotor Permanent Magnet Properties	10	
2.1.3	Actuator Internal Wiring Harness Fails		35
2.1.3.1	Conductor Fails	5	
2.1.3.2	Insulation Fails	25	
2.1.3.3	Terminal Mechanically Fails	5	
2.2	Improper Command Received from Amplifier		249
2.2.1	Amplifier Control Voltage Incorrect		AGC
2.2.2	Amplifier Fails Internally		30
2.2.3	Amplifier Feedback Signal Incorrect		219
2.2.3.1	Potentiometer Supply Voltage Wrong Value	30	
2.2.3.1.1	Actuator System Wiring Harness Fails	30	
2.2.3.1.2	Voltage Supplied is in Error	AGC	
2.2.3.2	Feedback Potentiometer Output Fails		154
2.2.3.2.1	Potentiometer Electrically Fails	101	
2.2.3.2.1.1	Track Resistance Value Changes	10	
2.2.3.2.1.2	Protective Resistor Changes Value	10	
2.2.3.2.1.3	Wiper Resistance Value Changes	1	
2.2.3.2.1.4	Wiper to Track Contact Resistance Changes	80	
2.2.3.2.2	Angular Relationship Pot to Drum Changes		21
2.2.3.2.2.1	Pot Position Relative to Shaft Changes	20	
2.2.3.2.2.2	Shaft Relative to Drum Changes	1	

TABLE 2-13 (CONTINUED)

2.2.3.2.3	Potentiometer Mechanically Fails	32	
2.2.3.2.3.1	Potentiometer Shaft Fails	1	
2.2.3.2.3.2	Wiper Spring Gradient Changes	1	
2.2.3.2.3.3	Bearings Fail	10	
2.2.3.2.3.4	Potentiometer Housing Fractures	20	
2.2.3.3	Feedback Signals Transmitted Improperly		35
2.2.3.3.1	Wiring Harness Actuator to Amplifier Fails	AGC	
2.2.3.3.2	Mechanism Wiring Harness Fails	30	
2.2.3.3.3	Electro-Magnetic Interference Distorts Signal	5	
2.3	Actuator External Control Drum Loads Change		EC
2.4	Actuator Internal Loads Change		736
2.4.1	Harmonic Drive Torque Output Low		260
2.4.1.1	Teeth Fail to Transmit Torque	15	
2.4.1.1.1	Teeth Break	10	
2.4.1.1.2	Teeth Wear	5	
2.4.1.2	Fastener Interferes with Motion	10	
2.4.1.3	Wave Generator Rotation Fails	155	
2.4.1.3.1	Bearing Friction Increases	130	
2.4.1.3.2	Eliptoidal Cam Breaks	5	
2.4.1.3.3	Flexible Outer	20	
2.4.1.4	Cup Fails to Transmit Motion	80	
2.4.1.4.1	Weld Fails	30	
2.4.1.4.2	Cup Breaks	50	
2.4.2	Motor Fails Mechanically		366
2.4.2.1	Bearing Friction Increases	280	
2.4.2.2	Fasteners Interfere with Motion	10	

TABLE 2-13 (CONTINUED)

2.4.2.3	Stator Wiring Interferes with Motion		76	
2.4.2.3.1	Actuator Housing Distorts	1		
2.4.2.3.2	Stator Porting Material Deteriorates	10		
2.4.2.3.3	Conductor at I.D. of Motor Breaks	5		
2.4.2.3.4	Pole Pieces Break	60		
2.4.3	Output Shaft-Pot Bearings Friction Level Increases		70	
2.4.4	Output Shaft Fails to Transmit Torque		40	
2.4.4.1	Teeth Break		10	
2.4.4.2	Shaft Breaks		20	
2.4.4.3	Cup to Shaft Coupling Fails		10	
3.	Actuator Electrical Power Rate Exceeds Specified Limits			61
3.1	Actuator Short Circuits			41
3.1.1	Potentiometer Internal Short Circuit		10	
3.1.2	Stator Wiring Insulation Fails Allowing Short Circuit		10	
3.1.3	Wiring Harness System Short Circuits		21	
3.1.3.1	Interface Connector Short Circuits	10		
3.1.3.2	Wiring Insulation Fails	10		
3.1.3.3	Terminal Fails	1		
3.2	Amplifier Internal Short Circuit			20
3.3	Amplifier/Actuator External Cable Short Circuit Failure			AGC

reliability of the actuator concept; the lower the number the more reliable the particular concept is relative to the others. Each concept was compared with the others on the basis of the total relative failure probability number.

The failure mode analysis for this particular actuator concept is reported in detail in the Control Drum Actuator Trade Study Report, TME-1984.⁽¹⁵⁾ The total relative failure probability number reported in this analysis is 136. In performing the analysis it is recognized that the work accomplished is directly applicable to the SSCSS actuator trade study. To avoid repeating the details of the analysis for the purpose of this study, only the total relative failure probability number is reported.

2.4.2.7.3 Safety Evaluation

The inherent safety and criticality of any failure is an important parameter to be considered in making a selection of a recommended concept. To determine a relative safety and criticality ranking for each concept, failure modes have been identified. For each of the failure modes listed, mechanisms of obtaining that failure mode are established as they relate to a particular design and each of these failure mechanisms has been given a numerical ranking consistent with its effect on the NSS and engine mission. Four categories of criticality are used to determine the safety rating of each concept as follows:

<u>Ranking</u>	<u>Description</u>
4	Failures resulting in gross core failure or possibly affecting structural integrity; crew safety jeopardized; African window safety in question.
3	Failures requiring corrective action resulting in reductions in chamber pressure/temperature below the emergency recovery mode level.

2	Failures requiring corrective action resulting in reduction in chamber temperature/pressure but not below emergency recovery mode level; completion of mission in question.
1	Failures resulting in insignificant effects on chamber temperature/pressure.

By assigning each mechanism of failure to one of the above categories, and finally obtaining a sum of all of the failure mechanisms, a total relative criticality ranking is obtained for each concept. The lower the total number estimate for a concept, the safer that concept is in relationship to the other concepts considered. The CDA Trade Study Report, TME-1984,⁽¹⁵⁾ tabulates the failures, mechanism of failure and criticality ranking of failure for the Slo-Syn stepping motor actuator. The total criticality ranking for this concept is 138.

2.4.2.8 Evaluation of Concept

The permanent magnet character of the Slo-Syn rotor produces certain major advantages peculiar to designs of this type. The magnetic detenting inherent in this concept and the high-speed reduction ratio of the Harmonic drive transmission result in a "fail in place" mode of failure without incorporating additional components into the mechanism. Exact position definition and low power requirements also recommend this concept relative to the other electric actuators.

Permanent magnet rotor electric stepper actuator concepts are nearly identical in operation and configuration; the only significant differences are the number of stator poles and the rotor mechanical construction. The Slo-Syn motor has eight stator poles and maintains the air gap between similar magnetic materials with the permanent magnet pieces magnetizing the rotor discs by intimate surface contact.

The Slo-Syn configuration allows the maintenance of the air gap dimension throughout the operating temperature range.

Emphasis in the development of the Slo-Syn actuator will be upon design of the wave generator bearing and establishing a satisfactory material for the flexspline. Other areas common to most electric actuator concepts requiring substantial development effort are the concentric potentiometer, wiring insulation and motor coil encapsulant.

The Slo-Syn configuration stepping motor has been manufactured by Superior Electric Company for a number of years and has been used extensively in industrial, military and space applications. Special versions of this motor were used in the SNAP-50 and SNAP-10A programs, in applications similar to those in NERVA. Although SNAP-50 was never built, prototype actuators were built and evaluated, including radiation testing, for use on this program. The SNAP-10A reactor was operated successfully for 43 days in space during the 1965 SNAPSHOT program.

The Harmonic drive transmission has also been used successfully in various SNAP programs. Operation in all of these programs was at elevated temperatures. NERVA low temperature and vacuum operation requirements will necessitate extensive development work.

Two industrial model Slo-Syn stepping motors (Model H550L) were procured and tested at WANL to establish dynamic operating characteristics and verify analytical design parameters. Primary testing was performed to determine frequency response, transient response, linearity, resolution and power requirements as well as loss of power failure modes. All parameters of concern met the specification requirements. A DRM presenting these test results is being prepared. Additional testing, with the motor immersed in LN_2 , was conducted to investigate the change in operating characteristics during temperature transient to cryogenic conditions. It was determined that the Slo-Syn rotor configuration permits operation at cryogenic temperature with negligible loss of output torque due to dimension change across the air gap.

Coolant requirements for a one hour run at the heating rates estimated for NERVA, about 3 watts per pound, are less than 1/2 pound per actuator and can probably be neglected. The main electrical power required is on the order of 24 watts with a reduced power to 10 watts assumed to provide a holding torque when the actuator is not moving. Signal level power

to supply the feedback potentiometers and control amplifiers is small and has been neglected for this comparative study. A preliminary estimate of the concept reliability obtained by calibrating the fault tree is $.9587$. Table 2-14 is a listing of some of the significant advantages and disadvantages of the Slo-Syn/Harmonic Drive Concept.

The actuator width at the SSCV shaft centerline is about 7.2 inches. Its height above the mounting boss is about 9 inches. The clearance required above the actuator for removal is 0.75 inch to assure clearance of the output shaft from the mounting boss.

2.4.3 Electric Dynavector Concept

2.4.3.1 Mechanical Description

This SSCV actuator system concept, Figure 2-24, uses a variable reluctance electric stepping motor which is being developed by the Bendix Research Laboratories. The motor essentially is an adaptation of the pneumatic Dynavector concept using an epicyclic transmission producing a high-speed reduction and torque increase at the mechanism output shaft.

The actuator subsystems are:

- 1) Drive subsystem.
- 2) Feedback subsystem.
- 3) Coolant subsystem.
- 4) Housing enclosure subsystem.

A precise description of this actuator system is given in the CDA Trade Study Report, TME 1984.⁽¹⁵⁾

2.4.3.2 System Description

The Dynavector stepping motor converts digital, electrical format into uniform discrete valve angle positions within the resolution requirements of the SSCSS. The digital format is a four-bit cyclic binary code in which two adjacent bits are in the "ON" state while the other two are in the "OFF" state. The "ON" state represents a constant current in a particular phase winding of the motor while the "OFF" state represents no current.

Because of the precise angular positioning ability of the Dynavector motor, the valve position may be programmed to move to a predetermined angle (shim worth). This can be

TABLE 2-14

SLO-SYN/HARMONIC DRIVE SSCV ACTUATOR CONCEPTS SUMMARY TABLE

<u>Advantages</u>	<u>Disadvantages</u>
1. Low Weight.	1. Moderately High Speed Bearing.
2. Magnetic Detenting at a Low Value is Available.	2. Rotor Construction is More Complex than Other Similar Devices.
3. Velocity Programmable by the Frequency of the Input Pulses.	
4. Small Overall Size	
5. Inherent Braking Due to P.M. Rotor and Stator Attractions.	
6. Few Moving Parts.	
7. High Resolution Obtained by Small Step Angle.	
8. Relatively Low Power Required to Hold Position Against Valve Hydraulic Loads.

Figure 2-24 Proportional Electric Dynavector SSCV Actuator Concept

achieved by counting the number of pulses delivered to the control system code generator. In this manner, the actuator may be operated in an open loop fashion as both the amount and rate of angular change are controllable. The actuator may also be operated as a closed loop system where the input pulses are proportional to the difference between the commanded valve position and the position indicator (feedback potentiometer) output.

A detailed explanation of this control system is given in the CDA Trade Study Report, TME 1984,⁽¹⁵⁾ and is recommended as a reference for details of the SSCV actuator system.

2.4.3.3 Radiation Analysis

Table 2-2 and Section 2.1.3 explain the radiation environment used in studying the SSCV actuators. This environment will remain unchanged for the Dynavector concept because the results of Table 2-2 are unperturbed due to the presence of the actuator. In addition, these values are considered conservative when applied to the SSCV actuator.

2.4.3.4 Thermal Evaluation

The thermal-nuclear environment of the Dynavector electric stepping motor concept is, in general, similar to that of prior actuators and the thermal performance is also expected to be similar to that of other stepping motor designs. It is expected that the actuator structure can be adequately cooled although the coolant requirements will vary as a function of the actuator size and its internal heat generation. Internal coolant passages, if required, will have to be incorporated into the motor mechanism housing structure so as not to interfere with its electrical function. Regions of primary thermal analysis interest will include the relatively thick wall sections, such as housing flanges, or the asymmetrical metal sections, where maximum temperature levels or thermal distortions would be expected to occur. Further design and analyses would be required to fully identify such regions.

2.4.3.5 Structural Evaluation

The Dynavector stepping motor actuator is an electrical adaptation to the Dynavector pneumatic actuator. The three main assemblies in the Dynavector electric actuator are the drive system assembly, feedback potentiometer and housing enclosure. The feedback potentiometer and housing enclosure are similar to those assemblies of the Responsyn actuator discussed in Section 2.4.1.5 and the same structural evaluation applies to both designs.

Figure 2-25 Dynavecator Stepping Motor Electrical Actuator Summary Fault Tree

Structurally, the drive system of this actuator is similar to that of the Dynavector pneumatic actuator discussed in Section 2.3.5. Both designs have a unique epicyclic gear transmission consisting of a stationary gear, ring gear and output gear. The basic difference between the two concepts is the method of producing the rotating radial force vector. In the Dynavector pneumatic actuator the radial force vector is produced pneumatically by sequentially pressurizing the displacement chambers, and the radial force vector is produced magnetically in the Dynavector electric by sequentially energizing the motor stator poles. If this actuator is selected from the trade study, system torques and forces, bending stresses, contact stresses, fatigue life, surface wear, material selection, and thermal stresses and distortions of the gears will be considered in detail. The structural reliability of this actuator drive system should be verified by component tests.

2.4.3.6 Radiation Effects Evaluation

The total expected radiation environment to which this actuator will be subjected is given in Section 2.1.3. To assess the effects of this environment on the actuator, a comparison of known test environments with this expected environment will indicate the sensitivity of any given concept to successful operation in the expected radiation levels. The sensitive components in this concept are the motor coils, the potentiometer, the shaft seals, and the electrical insulation and potting compounds. All other materials used in the construction of the actuator are metals. Although detail designs are not available, final material selection will be made from lists of qualified materials or will be separately qualified.

2.4.3.6.1 Motor Coils

Although motors have not been directly tested on the NERVA program, tests on other devices give important information concerning the expected performance of motor winding rails in a radiation environment. The electric coils contained in a pneumatic actuator torque motor and in the lock shut-off solenoid are similar to those used in electric motor construction. Tests conducted in a radiation environment at the GTR facility, during the NRX-A6 pneumatic actuator side-by-side test,⁽⁸⁾ and tests conducted by the Lewis Research Center at the Plum Brook Reactor⁽⁹⁾ all included the electric coils mentioned above. No Coil Anomalies were reported during any of these tests. However, it is planned to take advantage of improvements

in the state-of-the-art in insulation materials and use the polyimide series for future coil insulations to further improve radiation tolerance and increase coil reliability.

2.4.3.6.2 Potentiometer

A prototype potentiometer was also included in the tests described above. A reported failure in the Lewis tests⁽⁹⁾ caused some concern until a subsequent post-irradiation examination revealed the failure to be caused by a softening and flowing of a potting compound not included in the above mentioned GTR and NRX-A6 tests. Subsequent builds did not use this potting compound. Future controls will assure that only those specified materials that will not be subject to property changes under radiation environment will be used.

2.4.3.6.3 Shaft Seals, Electrical Insulation and Potting Materials

Although these items and materials have been proven adequate for use in the NERVA environment, it is planned to take advantage of the improvements in the state-of-the-art in insulation materials and expand the use of polyimide materials to wire insulation and potting materials to benefit in radiation tolerance and reliability.

2.4.3.7 Reliability and Safety Evaluation

The philosophy and approach in evaluating the reliability and safety of each actuator concept is presented in Section 2.1.7. The details of the approaches as applied to the evaluation of this particular actuator concept are reported in the following sub-paragraphs.

2.4.3.7.1 Fault Tree Evaluation

A portion of the reliability evaluation for this particular concept was accomplished through a fault tree analysis. Section 2.1.7.1 gives an accurate description as to how the fault trees are generated, calibrated, and implemented in evaluating the reliability of a particular actuator concept. Figure 2-25 is the summary of the fault tree and the numbers generated in evaluating this electric Dynavector concept. Table 2-15 is a listing of the detailed fault tree and the weighted numbers as assigned. The total of the weighted numbers is 1137.

TABLE 2-15

DETAILED FAULT TREE ANALYSIS
(Electric Dynavector Actuator)

Dynavector Stepping Motor - Proportional Electric Actuator Reliability
 Fault Tree Analysis 939J961 Estimated Reliability .9₅89

1137

1.0	Actuator Coolant Gas Consumption Exceeds Specified Limits		85
1.1	Cover Fails to Contain Coolant Gas	1	
1.2	Cover to Body Interface Joint Fails to Contain Coolant Gas	11	
1.2.1	Seal Fails to Contain Coolant Gas (2)	6	
1.2.2	Cover Fasteners Lose Clamping Force	5	
1.3	Pot Housing to Cover Interface Joint Fails to Contain Coolant Gas	10	
1.3.1	Seal Fails to Contain Coolant Gas	6	
1.3.2	Pot Housing Fasteners Lose Clamping Force	4	
1.4	Housing Body Fails to Contain Coolant Gas	1	
1.5	Pedestal/Housing Interface Joint Fails to Contain Gas	11	
1.5.1	Seal Fails to Contain Coolant Gas	6	
1.5.2	Fasteners Lose Clamping Force	5	
1.6	Electrical Connector Joint Fails to Contain Gas	40	
1.6.1	Seal Fails to Contain Gas	30	
1.6.2	Fasteners Lose Clamping Force	5	
1.6.3	Connector Body Fails to Contain Gas	5	
1.7	Inlet Line Connector Joint Fails to Contain Gas	12	
1.7.1	Seal Fails to Contain Coolant Gas	5	
1.7.2	Connector Loosens	6	
2.0	Actuator Fails to Position Control Drum Within Time Position Band		991
2.1	Actuator Fails to Convert Elec. Power to Mech. Power	126	
2.1.1	Electric Connector Fails to Transmit Proper Signal	10	

TABLE 2-15 (CONTINUED)

2.1.1.1	Conductor Fails to Transmit Signal	5	
2.1.1.2	Insulator Fails Allowing Short Circuit	5	
2.1.2	Motor Fails Electrically		81
2.1.2.1	Wiring Failure	80	
2.1.2.2	Pole Piece Failure	1	
2.1.3	Actuator Internal Wiring Harness Fails		35
2.1.3.1	Conductor Fails to Transmit Signal	5	
2.1.3.2	Insulation Fails	25	
2.1.3.3	Terminal Fails	5	
2.2	Actuator External Control Drum Load Changes		EC 677559
2.3	Amplifier Receives Improper Feedback Signal		219
2.3.1	Potentiometer Supply Voltage is Wrong Value		30
2.3.1.1	Actuator System Wiring Harness Fails	30	
2.3.1.2	Voltage Supplied to System is in Error	AGC	
2.3.2	Feedback Potentiometer Output Fails		154
2.3.2.1	Potentiometer Electrically Fails	101	
2.3.2.1.1	Track Resistance Value Changes	10	
2.3.2.1.2	Protective Resistor Value Changes	10	
2.3.2.1.3	Wiper Resistance Value Changes	1	
2.3.2.1.4	Wiper to Track Contact Resistance Value Changes	80	
2.3.2.2	Angular Relationship Pot To Drum Changes	21	
2.3.2.3	Potentiometer Mechanically Fails	32	
2.3.2.3.1	Potentiometer Shaft Fails	1	
2.3.2.3.2	Wiper Spring Gradient Changes	1	
2.3.2.3.3	Bearings Fail	10	
2.3.2.3.4	Potentiometer Housing Fractures	20	

TABLE 2-15 (CONTINUED)

2.3.3	Feedback Signals Transmitted Improperly		35
2.3.3.1	Wiring Harness Actuator to Amplifier Fails	AGC	
2.3.3.2	Mechanism Wiring Harness Fails	30	
2.3.3.3	Electro-Magnetic Int. Distorts Signal	5	
2.4	Output Shaft Fails to Position Drum		110
2.4.1	Crown Spline Teeth Fail	10	
2.4.2	Shaft Breaks	20	
2.4.3	Output Gear/Shaft Spline Joint Fails	80	
2.5	Actuator Internal Load Changes		506
2.5.1	Potentiometer Loads Change	10	
2.5.1.1	Bearings Fail	4	
2.5.1.2	Housing Fails	2	
2.5.1.3	Shaft Fails	2	
2.5.1.4	Coupling Fails	2	
2.5.2	Actuator Drive Train Load Changes Value		390
2.5.2.1	Ring Gear/Housing Bearing Fraction Increases	140	
2.5.2.1.1	Upper Ring Gear Bearing Surface Fails	40	
2.5.2.1.2	Lower Ring Gear Bearing Surface Fails	40	
2.5.2.1.3	Upper Housing Bearing Surface Fails	30	
2.5.2.1.4	Lower Housing Bearing Surface Fails	30	
2.5.2.2	Upper Output Shaft Bearing Fails	30	
2.5.2.3	Lower Output Shaft Bearing Fails	30	
2.5.2.4	Upper Ground Gear/Ring Gear Loads Increase	70	
2.5.2.4.1	Ring Gear Fails	30	
2.5.2.4.2	Ground Gear Fails	30	
2.5.2.4.3	Contaminants in Gear Mesh	10	

TABLE 2-15 (CONTINUED)

2.5.2.5	Lower Ground Gear/Ring Gear Loads Increase	70	
2.5.2.5.1	Ring Gear Fails	30	
2.5.2.5.2	Ground Gear Fails	30	
2.5.2.5.3	Contaminants in Mesh	10	
2.5.2.6	Ring Gear/Output Gear Loads Increase	50	
2.5.2.6.1	Ring Gear Fails	20	
2.5.2.6.2	Ground Gear Fails	20	
2.5.2.6.3	Contaminants in Mesh	10	
2.5.3	Motor Fails Mechanically to Provide Torque	116	
2.5.3.1	Fasteners Interfere with Rotating Parts	10	
2.5.3.2	Ring Gear Body Fails	30	
2.5.3.3	Stator Wiring Interferes with Parts	76	
2.5.3.3.1	Actuator Housing Distorts	1	
2.5.3.3.2	Stator Potting Deteriorates	10	
2.5.3.3.3	Conductor at O.D. of Motor Breaks	5	
2.5.3.3.4	Pole Piece Breaks	60	
2.6	Actuator Receives Improper Command	30	
2.6.1	Power Supplies Fail	AGC	
2.6.2	Amplifier Fails Internally	30	
3.0	Actuator Electrical Power Rate Exceeds Specified Limit	61	
3.1	Actuator Short Circuits	41	
3.1.1	Pot Internal Short Circuit Failure	10	
3.1.2	Stator Wiring Insulation Fails	10	
3.1.3	Wiring Harness Short Circuits	21	
3.1.3.1	Electrical Connector Short Circuits	10	

TABLE 2-15 (CONTINUED)

3.1.3.2 Wiring Insulation Fails/Short Circuits	10	
3.1.3.3 Terminal Short Circuits	1	
3.2 Amplifier Internal Short Circuit		20
3.3 Amplifier/Actuator External Cable Short Circuit		AGC

2.4.3.7.2 Failure Mode Evaluation

A failure mode analysis is prepared for each actuator system concept under consideration. As the actuator concepts are not completely detailed designs, the failure mode analyses are studies of arbitrarily selected groups of parts that form basic components within each actuator rather than studies of individual parts. In generating the failure mode analyses, each component is analyzed for possible modes of failure. These failure modes are identified and listed. Then, each failure mode is analyzed and the component failure mechanisms which cause the particular failure mode are identified and listed.

A reliability comparison of each actuator concept is accomplished by using a rating technique which utilizes a relative failure probability number based on a scale ranging from 1 to 10. The relative failure probability number is assigned to each component failure mechanism and represents an estimated probability of failure due to the particular failure mechanism. On the scale, 1 represents the lowest probability of failure and 10 represents the highest.

Engineering judgement is used in estimating the relative failure probability number for each failure mechanism. A total number is calculated by adding the relative probability numbers. This technique is considered acceptable since the failure modes listed are independent and mutually exclusive of one another.⁽¹⁴⁾ The total number then indicates the relative reliability of the actuator concept; the lower the number the more reliable the particular concept is relative to the others. Each concept was compared with the others on the basis of the total relative failure probability number.

The failure mode analysis for this particular actuator concept is reported in detail in the Control Drum Actuator Trade Study Report, TME-1984.⁽¹⁵⁾ The total relative failure probability number reported in this analysis is 125. In performing the analysis it is recognized that the work accomplished is directly applicable to the SSCSS actuator trade study. To avoid repeating the details of the analysis for the purpose of this study only the total relative failure probability number is reported.

2.4.3.7.3 Safety Evaluation

The inherent safety and criticality of any failure is an important parameter to be considered in making a selection of a recommended concept. To determine a relative safety

and criticality ranking for each concept, failure modes have been identified. For each of the failure modes listed, mechanisms of obtaining that failure mode are established as they relate to a particular design and each of these failure mechanisms has been given a numerical ranking consistent with its effect on the NSS and engine mission. Four categories of criticality are used to determine the safety rating of each concept as follows:

<u>Ranking</u>	<u>Description</u>
4	Failures resulting in gross core failure or possibly affecting structural integrity; crew safety jeopardized; African window safety in question.
3	Failures requiring corrective action resulting in reductions in chamber pressure/temperature below the emergency recovery mode level.
2	Failures requiring corrective action resulting in reduction in chamber temperature/pressure but not below emergency recovery mode level; completion of mission in question.
1	Failures resulting in insignificant effects on chamber temperature/pressure.

By assigning each mechanism of failure to one of the above categories, and finally obtaining a sum of all of the failure mechanisms, a total relative criticality ranking is obtained for each concept. The lower the total number estimate for a concept, the safer that concept is in relationship to the other concepts considered. The CDA Trade Study, TME-1984,⁽¹⁵⁾ tabulates the failures, mechanism of failure and criticality ranking of failure for the Dynavector electric actuator. The total criticality ranking for this concept is 134.

2.4.3.8 Evaluation of Concepts

The electric Dynavector actuator is based upon the pneumatic Dynavector technology developed by Bendix Research Labs. Bendix has successfully adapted the Dynavector concept to a single small electric actuator and has completed a study for the government applying the electric Dynavector to missile fin control. Development of an electric Dynavector will require a major developmental effort in the areas of bearing surfaces, ring gear mesh tolerances, and means of restraining the ring gear when de-energized. The end-mounted potentiometer is adaptable from the XE pneumatic configuration and requires little development.

The Dynavector proportional electric actuator width at the output shaft centerline is about 4.6 inches. Its height above the SSCV mounting boss is about 5.7 inches. Clearance required above the actuator for removal is about 1.0 inch to clear the output shaft. The dynavector actuator is about 6.8 pounds.

Coolant requirements for a one hour run at the heating rates estimated for NERVA, about 3 watts per pound, are less than one-half pound and can probably be neglected. The main electrical power required is about 44 watts, with a reduced power of 22 watts assumed to provide a holding torque when the actuator is not moving. Signal level power to supply the feedback potentiometer and actuator amplifiers is small and has been neglected for this comparative study. A preliminary estimate of the concept reliability obtained by calibrating the fault tree is 0.9₅89. Table 2-16 is a summary listing some of the more significant advantages and disadvantages.

2.4.4 Permanent Magnet Rotor Electric Stepper Motor Concept

2.4.4.1 Mechanical Description

This SSCV actuator as shown in Figure 2-26 uses an electric stepping motor manufactured by Sigma Instruments, Inc. It is a permanent magnet precision stepping motor, analogous in operation to a synchronous induction motor. For a complete and thorough mechanical description of this SSCV actuator concept refer to the CDA Trade Study Report, TME 1984.⁽¹⁵⁾

2.4.4.2 System Description

The permanent magnet stepping motor converts digital, electrical format into uniform discrete valve angle positions within the resolution requirements of the SSCSS. The digital

TABLE 2-16

DYNAVECTOR/DIRECT DRIVE SSCV ELECTRIC ACTUATOR CONCEPT SUMMARY TABLE

<u>Advantages</u>		<u>Disadvantages</u>	
1.	Low Speed Bearings	1.	Estimated as a High Development Effort/Cost Required.
2.	Small Overall Physical Size	2.	High Friction Components
3.	Velocity Programmable by Pulse Rate.	3.	Information Based Upon a One of a Kind Prototype Motor.
		4.	High Power Consumption
		5.	Low Efficiency
		6.	Power Required Continually or Brake Added to Combat Hydraulic Loads from Valve While Holding Position.

format is a four-bit cyclic binary code in which two adjacent bits are in the "ON" state while the other two are in the "OFF" state. The "ON" state represents a constant current in a particular phase winding of the motor while the "OFF" state represents no current.

Because of the precise angular positioning ability of the permanent magnet stepping motor, the valve position may be programmed to move to a predetermined angle (shim worth). This can be done by counting the number of pulses delivered to the control system code generator. In this manner, the actuator may be operated in an open loop fashion as both the amount and rate of angular change are controllable. The actuator may also be operated as a closed loop system where the input pulses are proportional to the difference between the commanded valve position and the position indicator (feedback potentiometer) output.

A detailed explanation of this control system scheme is given in the CDA Trade Study Report, TME 1984,⁽¹⁵⁾ and is recommended as a reference for the details of this SSCV actuator system concept.

2.4.4.3 Radiation Analysis

The radiation analysis reported in Section 2.1.3 is directly applicable to the permanent magnet stepping motor electrical actuator system concept. The radiation environment listed in Table 2-2 is unperturbed by the presence of the actuator mechanism. In addition, the predicted levels are considered conservative.

2.4.4.4 Thermal Evaluation

The thermal-nuclear environment of the permanent magnet rotor electric stepping motor concept is, in general, similar to that of prior actuators and its thermal performance is also expected to be similar to that of other stepping motor designs. It is expected that the actuator structure can be adequately cooled although the coolant requirements will vary as a function of the actuator size and its internal heat generation. Internal coolant passages will have to be incorporated into the motor mechanism housing structure so as not to interfere with its electrical function. Regions of primary thermal analysis interest will include the relatively thick wall sections, such as housing flanges, or the asymmetrical metal sections, where maximum temperature levels or thermal distortions would be expected to occur. Further design and analyses would be required to fully identify such regions.

612930-3B

Figure 2-26 Proportional Electric P M Stepping Motor SSCV Actuator, Harmonic Drive

2.4.4.5 Structural Evaluation

Structurally, permanent magnet rotor stepping motor actuator is similar to the Responsyn actuator discussed in Section 2.4.1.5 and the Slo-Syn actuator discussed in Section 2.4.2.5. The motor is a permanent magnet rotor precision stepping motor with an integral transmission. The transmission which surrounds the rotor and stator consists of a rigid, internally splined circular spline, a non-rigid, externally splined flexspline, and a wave generator. If the permanent magnet rotor actuator is selected, the structural reliability of the unit will be verified by analysis and/or component tests.

The structural evaluation of the transmission, feedback potentiometer, and housing enclosure for this actuator is identical to that of the Responsyn actuator discussed in Section 2.4.1.5.

2.4.4.6 Radiation Effects Evaluation

The total expected radiation environment to which this actuator will be subjected is given in Section 2.1.3. To assess the effects of this environment on the actuator, a comparison of known test environments with this expected environment will indicate the sensitivity of any given concept to successful operation in the expected radiation levels. The sensitive components in this concept are the motor coils, the potentiometer, the shaft seals, and the electrical insulation and potting compounds. All other materials used in the construction of the actuator are metals. Although detail designs are not available, final material selection will be made from lists of qualified materials or will be separately qualified.

2.4.4.6.1 Motor Coils. Although motors have not been directly tested on the NERVA program, tests on other devices give important information concerning the expected performance of motor winding rails in a radiation environment. The electric coils contained in a pneumatic actuator torque motor and in the lock shut-off solenoid are similar to those used in electric motor construction. Tests conducted in a radiation environment at the GTR facility, during the NRX-A6 pneumatic actuator side-by-side test,⁽⁸⁾ and tests conducted by

the Lewis Research Center at the Plum Brook Reactor all included the Electric Coils mentioned above. No coil anomalies were reported during any of these tests. However, it is planned to take advantage of improvements in the state-of-the-art in insulation materials and use the polyimide series for future coil insulations to further improve radiation tolerance and increase coil reliability.

2.4.4.6.2 Potentiometer. A prototype potentiometer was also included in the tests described in the above section. A reported failure in the Lewis tests⁽⁹⁾ caused some concern until a subsequent post-irradiation examination revealed the failure was caused by a softening and flowing of a potting compound not included in the GTR and NRX-A6 side-by-side tests. Future controls will assure using only those specified materials that will not be subject to property changes under radiation environment.

2.4.4.6.3 Shaft Seals, Electrical Insulation and Potting Materials. Although these items and materials are adequate for use in the NERVA environment, it is planned to take advantage of the improvements in the state-of-the-art in insulation materials. Polyimide materials will be used in wire insulation and potting materials to increase radiation tolerance and reliability.

2.4.4.7 Reliability and Safety Evaluation

The philosophy and approach taken in evaluating the reliability and safety of each actuator concept is presented in Section 2.1.7 of this report. The details of the approaches as applied to the evaluation of this particular actuator concept are reported in the following sub-paragraphs.

2.4.4.7.1 Fault Tree Evaluation

A portion of the reliability evaluation for this particular concept was accomplished through a fault tree analysis. Section 2.1.7.1 gives an accurate description as to how the fault trees are generated, calibrated, and implemented in evaluating the reliability of a

particular actuator concept. Figure 2-27 is the summary of the fault tree and weighted numbers used in this evaluation. Table 2-17 is a listing of the entire fault tree and the assigned weighted numbers. The total of the weighted numbers is 1363.

2.4.4.7.2 Failure Mode Evaluation

A failure mode analysis is prepared for each actuator system concept under consideration. As the actuator concepts are not completely detailed designs, the failure mode analyses are studies of arbitrarily selected groups of parts that form basic components within each actuator rather than studies of individual parts. In generating the failure mode analyses, each component is analyzed for possible modes of failure. These failure modes are identified and listed. Then, each failure mode is analyzed and the component failure mechanisms which cause the particular failure mode are identified and listed.

A reliability comparison of each actuator concept is accomplished by using a rating technique which utilizes a relative failure probability number based on a scale ranging from 1 to 10. The relative failure probability number is assigned to each component failure mechanism and represents an estimated probability of failure due to the particular failure mechanism. On the scale, 1 represents the lowest probability of failure and 10 represents the highest.

Engineering judgement is used in estimating the relative failure probability number for each failure mechanism. A total number is calculated by adding the relative probability numbers. This technique is considered acceptable since the failure modes listed are independent and mutually exclusive of one another.⁽¹⁴⁾ The total number then indicates the relative reliability of the actuator concept; the lower the number the more reliable the particular concept is relative to the others. Each concept is compared with the others on the basis of the total relative failure probability number.

The failure mode analysis for this particular actuator concept is reported in detail in the CDA Trade Study Report, TME-1984.⁽¹⁵⁾ The total relative failure probability number reported in this analysis is 137. In performing the analysis it is recognized that the work accomplished is directly applicable to the SSCSS actuator trade study. To avoid repeating the details of the analysis for the purpose of this subject study only the total relative failure probability number is reported.

Figure 2-27 Permanent Magnet Stepping Motor Summary Fault Tree

TABLE 2-17

DETAILED FAULT TREE ANALYSIS
(Permanent Rotor Stepping Motor)

Permanent Magnet Rotor Concept - Stepping Motor Proportional Electric
 Actuator Reliability Fault Tree Analysis 939J966 Estimated Reliability .9586,

1363

1. Actuator Coolant Gas Consumption Exceeds Specified Limits		95
1.1 Actuator Housing Fails to Contain Coolant Gas		55
1.1.1 Cover Fails to Contain Coolant Gas	5	
1.1.2 Cover to Body Interface Joint Fails	9	
1.1.2.1 Seal Fails	6	
1.1.2.2 Cover Fasteners Fail	3	
1.1.3 Housing Body Fails to Contain Coolant Gas	1	
1.1.4 Electrical Connector Fails to Contain Gas	40	
1.1.4.1 Seal Fails	30	
1.1.4.2 Fasteners Lose Clamping Force	5	
1.1.4.3 Connector Body Fails to Contain Gas	5	
1.2 Housing to Pedestal Interface Fails to Contain Gas		40
1.2.1 Interface Inlet Coolant Seal Fails	30	
1.2.2 Fasteners Lose Clamping Force	5	
1.2.3 Interface Exhaust Coolant Passage Seal Fails	5	
2. Actuator Fails to Position Control Drum Within Time Position Band		1207
2.1 Actuator Fails to Convert Electrical to Mechanical Power		138
2.1.1 Electrical Connector Fails to Transmit Proper Signal	10	
2.1.1.1 Conductor Fails to Transmit Proper Signal	5	
2.1.1.2 Insulator Fails Permitting Short Circuit	5	
2.1.2 Motor Fails Electrically	93	

2-133

TABLE 2-17 (CONTINUED)

2.1.2.1	Wiring Failure	80	
2.1.2.2	Loss of Permanent Magnet Bonding to Shaft	2	
2.1.2.3	Pole Pieces Break	1	
2.1.2.4	Loss of Rotor Permanent Magnet Properties	10	
2.1.3	Actuator Internal Wiring Harness Fails		35
2.1.3.1	Conductor Fails	5	
2.1.3.2	Insulation Fails	25	
2.1.3.3	Terminal Mechanically Fails	5	
2.2	Improper Command Received from Amplifier		249
2.2.1	Amplifier Supply Voltage Incorrect Value		AGC
2.2.2	Amplifier Fails Internally		30
2.2.3	Amplifier Feedback Signal Incorrect		219
2.2.3.1	Potentiometer Supply Voltage Wrong Value	30	
2.2.3.1.1	Actuator Wiring Harness Fails	30	
2.2.3.1.2	Voltage Supplied is in Error	AGC	
2.2.3.2	Feedback Potentiometer Output Fails		154
2.2.3.2.1	Potentiometer Electrically Fails	101	
2.2.3.2.1.1	Track Resistance Value Changes	10	
2.2.3.2.1.2	Protective Resistor Changes Value	10	
2.2.3.2.1.3	Wiper Resistance Value Changes	1	
2.2.3.2.1.4	Wiper to Track Contact Resistance Changes	80	
2.2.3.2.2	Angular Relationship Pot to Drum Changes	21	
2.2.3.2.2.1	Pot Position Relative to Shaft Changes	20	
2.2.3.2.2.2	Shaft Relative to Drum Changes	1	
2.2.3.2.3	Potentiometer Mechanically Fails	32	

TABLE 2-17 (CONTINUED)

2.2.3.2.3.1	Potentiometer Shaft Fails	1		
2.2.3.2.3.2	Wiper Spring Gradient Changes	1		
2.2.3.2.3.3	Bearings Fail	10		
2.2.3.2.3.4	Potentiometer Housing Fractures	20		
2.2.3.3	Feedback Signals Transmitted Improperly		35	
2.2.3.3.1	Wiring Harness Actuator to Amplifier Fails	AGC		
2.2.3.3.2	Mechanism Wiring Harness Fails	30		
2.2.3.3.3	Electro-Magnetic Interference Distorts Signal	5		
2.3	Actuator External Control Drum Loads Change			EC
2.4	Actuator Internal Loads Change			820
2.4.1	Harmonic Drive Fails to Transmit Sufficient Torque		260	
2.4.1.1	Teeth Fail to Transmit Torque		15	
2.4.1.1.1	Teeth Break	10		
2.4.1.1.2	Teeth Wear	5		
2.4.1.2	Fastener Interferes with Motion		10	
2.4.1.3	Wave Generator Rotation Impaired		155	
2.4.1.3.1	Bearing Friction Increases	130		
2.4.1.3.2	Eliptoidal Cam Breaks	5		
2.4.1.3.3	Flexible Outer Race Breaks	20		
2.4.1.4	Cup Fails to Transmit Motion		80	
2.4.1.4.1	Weld Fails	30		
2.4.1.4.2	Cup Breaks	50		
2.4.2	Motor Fails Mechanically		450	
2.4.2.1	Bearing Friction Increases		280	
2.4.2.2	Fasteners Interfere with Motion		10	
2.4.2.3	Stator Wiring Interferes with Motion		160	

TABLE 2-17 (CONTINUED)

2.4.2.3.1	Actuator Housing Distorts	1		
2.4.2.3.2	Stator Potting Material Deteriorates	10		
2.4.2.3.3	Conductor at I.D. Of Motor Breaks	5		
2.4.2.3.4	Pole Pieces Break	144		
2.4.3	Output Shaft-Pot Bearings Friction Level Increases		70	
2.4.4	Output Shaft Fails to Transmit Torque		40	
2.4.4.1	Teeth Break		10	
2.4.4.2	Shaft Breaks		20	
2.4.4.3	Cup to Shaft Coupling Fails		10	
3.	Actuator Electrical Power Rate Exceeds Specified Limits			61
3.1	Actuator Short Circuit Failure			41
3.1.1	Potentiometer Internal Short Circuit		10	
3.1.2	Stator Wiring Insulation Fails Allowing Short Circuit		10	
3.1.3	Wiring Harness System Short Circuits		21	
3.1.3.1	Connector Short Circuits		10	
3.1.3.2	Wiring Insulation Fails		10	
3.1.3.3	Terminal Fails		1	
3.2	Amplifier Internal Short Circuit			20
3.3	Amplifier/Actuator External Cable Short Circuit Failure			AGC

2.4.4.7.3 Safety Evaluation

The inherent safety and criticality of any failure is an important parameter to be considered in making a selection of a recommended concept. To determine a relative safety and criticality ranking for each concept, failure modes have been identified. For each of the failure modes listed, mechanisms of obtaining that failure mode are established as they relate to a particular design and each of these failure mechanisms is given a numerical ranking consistent with its effect on the NSS and engine mission. Four categories of criticality are used to determine the safety rating of each concept as follows:

<u>Ranking</u>	<u>Description</u>
4	Failures resulting in gross core failure or possibly affecting structural integrity; crew safety jeopardized; African window safety in question.
3	Failures requiring corrective action resulting in reductions in chamber pressure/temperature below the emergency recovery mode level.
2	Failures requiring corrective action resulting in reduction in chamber temperature/pressure but not below emergency recovery mode level; completion of mission in question.
1	Failures resulting in insignificant effects on chamber temperature/pressure.

By assigning each mechanism of failure to one of the above categories, and finally obtaining a sum of all of the failure mechanisms, a total relative criticality ranking is obtained

for each concept. The lower the total number estimate for a concept, the safer that concept is in relationship to the other concepts considered. The CDA Trade Study Report, TME-1984,⁽¹⁵⁾ tabulates the failures, mechanism of failure and criticality ranking of failure for the permanent magnet stepper motor. The total criticality ranking for this concept is 137.

2.4.4.8 Evaluation of Concept

The PM stepper actuator concept is nearly identical in operation and configuration to other permanent magnet rotor actuator concepts; the only significant differences are the number of stator poles and the rotor mechanical construction. This motor has 24 stator poles and maintains the air gap between magnetic pole pieces and a full permanent magnet material disc.

The motor has a relatively high flux density and thus, in general, requires less input power to attain a given torque output. However, the dissimilar materials bounding the air gap may present operating difficulties in change of air gap dimension or interference during temperature transients, and warrants a detailed analysis and development tests.

Other areas, common to most actuator concepts, requiring development effort are the concentric potentiometer, wiring insulation and motor coil encapsulant.

The permanent magnet rotor motor upon which this concept is based is representative of a type of stepping motor built by a number of manufacturers, among them IMC, A. W. Haydon, CDC, Aeroflex, and Sigma Instruments, Inc. This type of stepping motor has been used extensively as a servomotor in space applications such as Surveyor, Mariner, Lunar Orbiter and reactor applications such as SNAP and LCRE.

The Harmonic drive transmission has also been used successfully in various SNAP programs. Operation in all of these programs was at elevated temperature, however, and low temperature operation requirements will necessitate additional analysis and development tests.

The permanent magnet rotor proportional electric actuator width at the SSCV centerline is about 4.9 inches. Its height above the SSCV mounting face is about 4.5 inches. Clearance required above the actuator for removal is about 2.5 inches to clear the output shaft. The permanent magnet rotor stepping motor is estimated to weigh about 6.7 pounds.

Coolant requirements for a one hour run at the heating rates estimated for NERVA, about 3 watts per pound, are less than 1/2 pound and can probably be neglected. The main electrical power required is about 32 watts with no power required during non-moving phases of reactor operating time because of the high detent torque available. Signal level power to supply the feedback potentiometers and control amplifier is small and has been neglected for the comparative study. A preliminary estimate of the concept reliability obtained by calibrating the fault tree is $.9_{5}^{86}$. Table 2-18 is a listing of some of the more significant advantages and disadvantages.

2.5 AC SERVOMOTOR PROPORTIONAL CONCEPT

The AC servomotor actuator is a two-phase, 400Hz motor using a high ratio Harmonic drive speed reducing transmission. The concept's transmission, housing and feedback device are similar to some of the stepping motor concepts presented in Section 2.4. The motor is based upon the electric control drum actuator developed in 1963 by Westinghouse Research Laboratories under contract to WANL.

2.5.1 Mechanical Description

A complete detailed mechanical description of this SSCV actuator concept can be obtained from the CDA Trade Study Report, TME-1948,⁽¹⁵⁾ Section 2.5.1. This concept, as applied in the Structural Support Coolant System and mounted on the SSCV is shown in Figure 2-28.

2.5.2 System Description

The ac servomotor actuator system block diagram is shown in Figure 2-29. The system uses a two-phase high-speed induction motor. The fixed phase is excited by a constant ac-current. The control phase is excited by a variable amplitude ac-current which is displaced from the fixed phase by ± 90 degrees.

TABLE 2-18

PERMANENT MAGNET STEPPER/HARMONIC DRIVE SSCV ACTUATOR CONCEPT SUMMARY
SUMMARY TABLE

<u>Advantages</u>	<u>Disadvantages</u>
1. Low weight	1. Moderately high speed bearing
2. High magnetic detent forces are available to hold position without power	2. Moderately high gear reduction
3. High resolution	
4. Small overall size	
5. Inherent braking	
6. Few moving parts	
7. Programmable velocity	
8. Can be operated without feedback potentiometers in the control loop	
9. Control transistors can be operated in a switching mode for highest reliability.

Figure 2-28 Proportional Electric AC Motor SSCV Actuator, Harmonic Drive

Figure 2-29 A C Servomotor Proportional SSCV Actuator System Concept - Block Diagram

The output of the motor is coupled to the actuator output shaft by a gear arrangement which reduces speed and increases torque to meet the SSCV requirements. The actuator output shaft is coupled to the SSCV by a drive shaft. An angular position indicator is provided to measure the actuator output shaft angle for both control and diagnostic purposes.

The ac-current for the control phase of the servomotor is generated by the actuator amplifier which contains the necessary compensation and modulation to control the servomotor. The amplifier is driven by an error signal which is the difference between the valve position command and the output position indicator signals.

Electrical power is supplied to the actuator amplifier. The required power is in the form of both ac and dc currents. Hydrogen coolant is supplied to the actuator from the SSCV coolant flow.

2.5.3 Radiation Analysis

Table 2-2 of this report provides the radiation environment used in evaluating the SSCV actuator concepts. This environment will be unperturbed by the presence of the actuator mechanism and, therefore, remains unchanged.

2.5.4 Thermal Evaluation

The thermal-nuclear environment of the ac servomotor proportional concept is similar to that of prior actuators and the thermal performance is also expected to be similar. It is expected that the actuator structure can be adequately cooled, although the coolant requirements will vary as a function of the actuator size and its internal heat generation. Internal coolant passages will have to be incorporated into the motor mechanism housing structure so as not to interfere with its electrical function. Regions of primary thermal analysis interest will include the relatively thick wall sections, such as housing flanges, or the asymmetrical metal sections, where maximum temperature levels or thermal distortions would be expected to occur.

2.5.5 Structural Evaluation

The structural evaluation of the AC servomotor actuator is identical to that of the Slo-Syn actuator discussed in Section 2.4.2.5. The only difference between these two designs

is the substitution of an ac motor for an electric stepping motor. If this actuator is selected from the trade study, the structural reliability of the AC motor will be verified by analysis and component tests.

2.5.6 Radiation Effects Evaluation

The total expected radiation environment to which this actuator will be subjected is given in Section 2.1.3. To assess the effects of this environment on the actuator, a comparison of known test environments with this expected environment will indicate the sensitivity of any given concept to successful operation in the expected radiation levels. The sensitive components in this concept are the motor coils, the potentiometer, the shaft seals, and the electrical insulation and potting compounds. All other materials used in the construction of the actuator are metals. Although detail designs are not available, final material selection will be made from lists of qualified materials or will be separately qualified.

2.5.6.1 Motor Coils

Although motors have not been directly tested on the NERVA program, tests on other devices give important information concerning the expected performance of motor winding rails in a radiation environment. The electric coils contained in a pneumatic actuator torque motor and in the lock shut-off solenoid are similar to those used in electric motor construction. Tests conducted in a radiation environment at the GTR facility, during the NRX-A6 pneumatic actuator side-by-side test,⁽⁸⁾ and tests conducted by the Lewis Research Center at the Plum Brook Reactor⁽⁹⁾ all included the electric coils mentioned above. No coil anomalies were reported during any of these tests. However, it is planned to take advantage of improvements in the state-of-the-art in insulation materials and use the polyimide series for future coil insulations to further improve radiation tolerance and increase coil reliability.

2.5.6.2 Potentiometer

A prototype potentiometer was also included in the tests described in the above section. A reported failure in the Lewis tests⁽⁹⁾ caused some concern until a subsequent post-irradiation examination revealed the failure was caused by a softening and flowing of a potting compound not included in the GTR and NRX-A6 side-by-side tests. Future controls will assure using only those specified materials that will not be subject to property changes under radiation environment.

2.5.6.3 Shaft Seals, Electrical Insulation and Potting Materials

Although these items and materials are adequate for use in the NERVA environment, it is planned to take advantage of the improvements in the state-of-the-art in insulation materials. Polyimide materials will be used in wire insulation and potting materials to increase radiation tolerance and reliability.

2.5.7 Reliability and Safety Evaluation

The philosophy and approach in evaluating the reliability and safety of each actuator concept is presented in Section 2.1.7 of this report. The details of the approaches as applied to the evaluation of this particular actuator concept are reported in the following sub-paragraphs.

2.5.7.1 Fault Tree Evaluation

A detailed description of a fault tree method of analysis is presented in Section 2.1.7 of this report. The detailed fault tree for this AC motor concept is listed in Table 2-19. This detailed fault tree is also presented in summary form in Figure 2-30.

2.5.7.2 Failure Mode Evaluation

A failure mode analysis is prepared for each actuator system concept under consideration. As the actuator concepts are not completely detailed designs, the failure mode analyses are studies of arbitrarily selected groups of parts that form basic components within each actuator rather than studies of individual parts. In generating the failure mode analyses, each component is analyzed for possible modes of failure. These failure modes are identified and listed. Then, each failure mode is analyzed and the component failure mechanisms which cause the particular failure mode are identified and listed.

A reliability comparison of each actuator concept is accomplished by using a rating technique which utilizes a relative failure probability number based on a scale ranging from 1 to 10. The relative failure probability number is assigned to each component failure mechanism and represents an estimated probability of failure due to the particular failure mechanism. On the scale, 1 represents the lowest probability of failure and 10 represents the highest.

TABLE 2-19

DETAILED FAULT TREE ANALYSIS (AC Motor)

A.C. Motor Harmonic Drive Proportional Electric Actuator Reliability
 Fault Tree Analysis 939J956 Estimated Reliability .9585

1498

1. Actuator Coolant Gas Consumption Exceeds Specified Limits		95
1.1 Actuator Housing Fails to Contain Coolant Gas		55
1.1.1 Cover Fails to Contain Coolant Gas	5	
1.1.2 Cover to Body Interface Joint Fails	9	
1.1.2.1 Seal Fails	6	
1.1.2.2 Cover Fasteners Fail	3	
1.1.3 Housing Body Fails to Contain Coolant Gas	1	
1.1.4 Electrical Connector Fails to Contain Gas	40	
1.1.4.1 Seal Fails	30	
1.1.4.2 Fasteners Lose Clamping Force	5	
1.1.4.3 Connector Body Fails to Contain Gas	5	
1.2 Housing to Pedestal Interface Fails to Contain Gas		40
1.2.1 Interface Inlet Coolant Seal Fails	30	
1.2.2 Fasteners Lose Clamping Force	5	
1.2.3 Interface Exhaust Coolant Passage Seal Fails	5	
2. Actuator Fails to Position Control Drum Within Time Position Band		1262
2.1 Actuator Fails to Convert Electrical to Mechanical Power		201
2.1.1 Electrical Connector Fails to Transmit Proper Signal	10	
2.1.1.1 Conductor Fails to Transmit Signal	5	
2.1.1.2 Insulator Fails Permitting Short Circuit	5	

TABLE 2-19 (CONTINUED)

2.1.2	Motor Fails Electrically		121
2.1.2.1	Wiring Failure in Stator Winding	40	
2.1.2.2	Pole Pieces Break	1	
2.1.2.3	Wiring Failure in Rotor Winding	80	
2.1.3	Actuator Internal Wiring Harness Fails		35
2.1.3.1	Conductor Fails	5	
2.1.3.2	Insulation Fails	25	
2.1.3.3	Terminal Mechanically Fails	5	
2.1.4	Pedestal Wiring Harness Fails to Transmit Signal		35
2.1.4.1	Conductor Fails to Transmit Signal	5	
2.1.4.2	Insulation Fails Allowing Short Circuit	25	
2.1.4.3	Terminal Mechanical Failure	5	
2.2	Improper Command Received from Amplifier		249
2.2.1	Amplifier Control Voltage Incorrect		AGC
2.2.2	Amplifier Fails Internally		30
2.2.3	Amplifier Feedback Signal Incorrect		219
2.2.3.1	Potentiometer Supply Voltage Wrong Value	30	
2.2.3.1.1	Actuator System Wiring Harness Fails	30	
2.2.3.1.2	Voltage Supplied is in Error	AGC	
2.2.3.2	Feedback Potentiometer Output Fails	154	
2.2.3.2.1	Potentiometer Electrically Fails	101	
2.2.3.2.1.1	Track Resistance Value Changes	10	
2.2.3.2.1.2	Protective Resistor Changes Value	10	
2.2.3.2.1.3	Wiper Resistance Value Changes	1	
2.2.3.2.1.4	Wiper to Track Contact Resistance Changes	80	

TABLE 2-19 (CONTINUED)

2.2.3.2.2	Angular Relationship Pot to Drum Changes	21	
2.2.3.2.2.1	Pot Position Relative to Shaft Changes	20	
2.2.3.2.2.2	Shaft Relative to Drum Changes	1	
2.2.3.2.3	Potentiometer Mechanically Fails	32	
2.2.3.2.3.1	Potentiometer Shaft Fails	1	
2.2.3.2.3.2	Wiper Spring Gradient Changes	1	
2.2.3.2.3.3	Bearings Fail	10	
2.2.3.2.4	Potentiometer Housing Fractures	20	
2.2.3.3	Feedback Signals Transmitted Improperly	35	
2.2.3.3.1	Wiring Harness Actuator to Amplifier Fails	AGC	
2.2.3.3.2	Mechanism Wiring Harness Fails	30	
2.2.3.3.3	Electro-Magnetic Interference Distorts Signal	5	
2.3	Actuator External Loads Change		EC
2.4	Actuator Internal Loads Change		812
2.4.1	Flexspline Torque Output Low		260
2.4.1.1	Teeth Fail to Transmit Torque	15	
2.4.1.1.1	Teeth Break	10	
2.4.1.1.2	Teeth Wear		
2.4.1.2	Fastener Interfers with Motion	10	
2.4.1.3	Wave Generator Rotation Fails	155	
2.4.1.3.1	Bearing Friction Increases	130	
2.4.1.3.2	Elliptoidal Cam Breaks	5	
2.4.1.3.3	Flexible Outer Race Breaks	20	
2.4.1.4	Cup Fails to Transmit Motion	80	
2.4.1.4.1	Weld Fails	30	
2.4.1.4.2	Cup Breaks	50	

TABLE 2-19 (CONTINUED)

2.4.2	Motor Fails Mechanically		442
2.4.2.1	Bearing Friction Increases	280	
2.4.2.2	Fasteners Interfere with Motion	10	
2.4.2.3	Stator Wiring Interferes with Motion	76	
2.4.2.3.1	Actuator Housing Distorts	1	
2.4.2.3.2	Stator Porting Material Deteriorates	10	
2.4.2.3.3	Conductor at I.D. of Motor Breaks	5	
2.4.2.3.4	Pole Pieces Break	60	
2.4.2.4	Rotor Wiring Interferes with Rotation	76	
2.4.2.4.1	Actuator Housing Distorts	1	
2.4.2.4.2	Rotor Porting Material Deteriorates	10	
2.4.2.4.3	Conductor at Circumference of Rotor Breaks	5	
2.4.2.4.4	Pole Pieces Break	60	
2.4.3	Output Shaft-Pot Bearings Friction Level Increases	70	
2.4.4	Output Shaft Fails to Transmit Torque	40	
2.4.4.1	Teeth Break	10	
2.4.4.2	Shaft Breaks	20	
2.4.4.3	Cup to Shaft Coupling Fails	10	
3.	Actuator Electrical Power Rate Exceeds Specified Limits		141
3.1	Actuator Short Circuits		121
3.1.1	Potentiometer Internal Short Circuit	10	
3.1.2	Stator Wiring Insulation Fails Allowing Short Circuit	10	
3.1.3	Wiring Harness System Short Circuits	21	
3.1.3.1	Interface Connector Short Circuits	10	
3.1.3.2	Wiring Insulation Fails	10	
3.1.3.3	Terminal Fails	1	

TABLE 2-19 (CONTINUED)

3.1.4 Rotor Wiring Insulation Fails	80
3.2 Amplifier Internal Short Circuit	20
3.3 Amplifier/Actuator External Cable Short Circuit Failure	AGC

Figure 2-30 AC Motor Harmonic Drive Concept Summary Fault Tree

Engineering judgement is used in estimating the relative failure probability number for each failure mechanism. A total number is calculated by adding the relative probability numbers. This technique is considered acceptable since the failure modes listed are independent and mutually exclusive of one another.⁽¹⁴⁾ The total number then indicates the relative reliability of the actuator concept; the lower the number the more reliable the particular concept is relative to the others. Each concept is compared with the others on the basis of the total relative failure probability number.

The failure mode analysis for this particular actuator concept is reported in detail in the Control Drum Actuator Trade Study Report.⁽¹⁵⁾ The total relative failure probability number reported in this analysis is 147. In performing the analysis it was recognized that the work accomplished was directly applicable to the Structural Support Coolant Supply System (SSCSS) actuator trade study. To circumvent repeating the details of the analysis for the purpose of this subject study only the total relative failure probability number is reported.

2.5.7.3 Safety Evaluation

The inherent safety and criticality of any failure is an important parameter to be considered in making a selection of a recommended concept. To determine a relative safety and criticality ranking for each concept, failure modes have been identified. For each of the failure modes listed, mechanisms of obtaining that failure mode are established as they relate to a particular design and each of these failure mechanisms has been given a numerical ranking consistent with its effect on the NSS and engine mission. Four categories of criticality are used to determine the safety rating of each concept as follows:

<u>Ranking</u>	<u>Description</u>
4	Failures resulting in gross core failure or possibly affecting structural integrity; crew safety jeopardized; African window safety in question.
3	Failures requiring corrective action resulting in reductions in chamber pressure/temperature below the emergency recovery mode level.

2	Failures requiring corrective action resulting in reduction in chamber temperature/pressure but not below emergency recovery mode level; completion of mission in question.
1	Failures resulting in insignificant effects on chamber temperature/pressure.

By assigning each mechanism of failure to one of the above categories, and finally obtaining a sum of all of the failure mechanisms, a total relative criticality ranking is obtained for each concept. The lower the total number estimate for a concept, the safer that concept is in relationship to the other concepts considered. The CDA Trade Study Report, TME-1984⁽¹⁵⁾ tabulates the failures, mechanism of failure and criticality ranking of failure for the AC motor electric actuator. The total criticality ranking for this concept is 166.

2.5.8 Evaluation of Concept

Requirements for 400 Hz, two phase power, high speed bearings and stopping circuitry in the form of a capacitor shorting system or mechanical brake severely limit the adaptability of an ac motor to SSCV application. All of the development work necessary in building a stepping motor actuator must also be accomplished for the ac motor actuator in addition to the items noted above. An optimized ac motor actuator will be the heaviest of the electric concepts as well as the most difficult to stabilize and control. Stabilization networks in ac motors are notably more complex than equivalent dc systems. Temperature changes in ac motor windings directly affect stability and the use of passive elements for stability require use of elaborate modulating and demodulating schemes.

The AC proportional electric actuator width at the control drum centerline is about 4.8 inches. Its height above the pressure vessel mounting boss is about 7.2 inches. Clearance required above the actuator for removal is about .75 inch to clear the output shaft. The AC motor actuator concept is estimated to weigh about 7.9 pounds. Coolant requirements for a one hour run at the heating rates estimated for NERVA, about 3 watts per pound, are less than 1/2 pound and can probably be neglected. The main electrical power required is about 45

watts with a reduced power of 30 watts required to hold the actuator in position when it is not moving. Signal level power to supply the feedback potentiometer and control amplifier is small and has been neglected for this comparative study. A preliminary estimate of the concept reliability, obtained by calibrating the fault tree, is $.9_{5}85$. Table 2-20 is a listing of some of the more significant advantages and disadvantages of the ac servomotor concept.

2.6 DC MOTOR PROPORTIONAL CONCEPT

The DC motor actuator is adapted from the dc motors developed for use in aircraft control surface actuation. These motors have been refined to the point where they are very efficient, have excellent response time, low weight and small overall size relative to other electric motors. Most dc motors used in spare applications are limited to short duration or to binary ON-OFF service.

2.6.1 Mechanical Description

The DC motor SSCV actuator concept, Figure 2-31, is very similar to the AC and Slo-Syn actuator concept in that the transmission, feedback device, housing, and coolant system are identical. The only physical difference is in that the motor is a DC servomotor using a small diameter, high resistance rotor. A complete and accurate mechanical description of this actuator concept is available in the CDA Trade Study Report, TME 1984,⁽¹⁵⁾ Section 2.6.1.

2.6.2 System Description

The dc servomotor actuator system block diagram is shown in Figure 2-32. The system uses a series wound stator dc motor. The motor produces an output torque in proportion to a dc current input.

The output of the motor is coupled to the actuator output shaft by a gear arrangement which reduces speed and increases torque to meet the performance requirements. The actuator output shaft is coupled to the SSCV drive shaft. An angular position indicator is provided to measure the actuator output shaft angle for both control and diagnostic purposes.

The dc current which controls the motor is generated by the actuator amplifier which contains the necessary compensation to stabilize the closed loop control system. The amplifier

TABLE 2-20

AC SERVO/HARMONIC DRIVE SSCV ACTUATOR CONCEPT SUMMARY TABLE

<u>Advantages</u>	<u>Disadvantages</u>
1. No Obvious Advantages.	1. High Speed Bearings Have Adverse Effect on Reliability.
	2. AC Power Required
	3. Low Efficiency
	4. Capacitor Shorting Used to Stop Motor.
	5. Requires Convection Cooling
	6. Heavy in Comparison to Other Concepts
	7. A Brake or Continuous Power Required to Hold Position Against Valve Hydraulic Loads.
	8. Stability Affected by Temperature Range Experienced in NERVA.
	9. Compensation Relatively More Difficult Than Other Concepts.

Figure 2-31 Proportional Electric DC Motor SSCV Actuator, Harmonic Drive

Figure 2-32 DC Servomotor Proportional SSCV Actuator System Concept

is driven by an error signal which is the difference between the position command and output position indicator signals.

Electrical power is supplied to the actuator amplifier and hydrogen coolant gas is supplied to the actuator. A function of the coolant gas is to quench the arc generated by the brushes of the dc motor. The coolant gas must provide a minimum pressure in the actuator any time the motor is in operation.

2.6.3 Radiation Analysis

Table 2-2 of Section 2.1.3 provides the radiation environment used in evaluating the SSCV actuator concepts. This environment will be unperturbed by the presence of the actuator mechanism and therefore remains unchanged. In most cases, the presence of the actuator reduces the values so that application of the unperturbed values is somewhat conservative.

2.6.4 Thermal Evaluation

The thermal-nuclear environment of the DC proportional concept is, in general, similar to that of section 2.1.4 and the thermal performance is also expected to be similar. It is expected that the actuator structure can be adequately cooled although the coolant requirements will vary as a function of the actuator size and its internal heat generation. Internal coolant passages will have to be incorporated into the motor mechanism housing structure so as not to interfere with its electrical function. Regions of primary thermal analysis interest will include the relatively thick wall sections, such as housing flanges, or the asymmetrical metal sections, where maximum temperature levels or thermal distortions would be expected to occur.

2.6.5 Structural Evaluation

The structural evaluation of the dc servomotor actuator is identical to that of the Slo-Syn actuator discussed in Section 2.4.2.5. The only difference between these two designs is the substitution of a dc motor for an electric stepping motor. If this actuator is selected from the trade study, the structural reliability of the dc motor will be verified by analysis and/or component tests.

2.6.6 Radiation Effects Evaluation

The total expected radiation environment to which this actuator will be subjected is given in Section 2.1.3. To assess the effects of this environment on the actuator, a comparison of known test environments with this expected environment will indicate the sensitivity of any given concept to successful operation in the expected radiation levels. The sensitive components in this concept are the motor coils, the potentiometer, the shaft seals, and the electrical insulation and potting compounds. All other materials used in the construction of the actuator are metals. Although detail designs are not available, final material selection will be made from lists of qualified materials or will be separately qualified.

2.6.6.1 Motor Coils

Although motors have not been directly tested on the NERVA program, tests on other devices give important information concerning the expected performance of motor winding rails in a radiation environment. The electric coils contained in a pneumatic actuator torque motor and in the lock shut-off solenoid are similar to those used in electric motor construction. Tests conducted in a radiation environment at the GTR facility, during the NRX-A6 pneumatic actuator side-by-side test,⁽⁸⁾ and tests conducted by the Lewis Research Center at the Plum Brook Reactor⁽⁹⁾ all included the electric coils mentioned above. No coil anomalies were reported during any of these tests. However, it is planned to take advantage of improvements in the state-of-the-art in insulation materials and use the polyimide series for future coil insulations to further improve radiation tolerance and increase coil reliability.

2.6.6.2 Potentiometer

A prototype potentiometer is also included in the tests described in the above section. A reported failure in the Lewis tests⁽⁹⁾ caused some concern until a subsequent post-irradiation examination revealed the failure was caused by a softening and flowing of a potting compound not included in the GTR and NRX-A6 side-by-side test. The material that failed was used in very early model potentiometers but has now been removed. Future controls will assure using only those specified materials that will not be subject to property changes under radiation environment.

2.6.6.3 Shaft Seals, Electrical Insulation and Potting Materials

Although these items and materials are adequate for use in the NERVA environment, it is planned to take advantage of the improvements in the state-of-the-art in insulation materials. Polyimide materials will be used in wire insulation and potting materials to increase radiation tolerance and reliability.

2.6.7 Reliability and Safety Evaluation

The philosophy and approach taken in evaluating the reliability and safety of each actuator concept is presented in Section 2.1.7 of this report. The details of the approaches as applied to the evaluation of this particular actuator concept are reported in the following sub-paragraphs.

2.6.7.1 Fault Tree Evaluation

A detailed explanation of the fault tree method of analysis is presented in Section 2.1.7 of this report. The detailed fault tree for this DC motor concept is listed in Table 2-21. The summary form of this fault tree is presented in Figure 2-33.

2.6.7.2 Failure Mode Evaluation

A failure mode analysis is prepared for each actuator concept under consideration. As the actuator concepts were not completely detailed designs, the failure mode analyses are studies of arbitrarily selected groups of parts that form basic components within each actuator rather than studies of individual parts. In generating the failure mode analyses, each component is analyzed for possible modes of failure. These failure modes are identified and listed. Then, each failure mode is analyzed and the component failure mechanisms which cause the particular failure mode are identified and listed.

A reliability comparison of each actuator concept is accomplished by using a rating technique which utilizes a relative failure probability number based on a scale ranging from 1 to 10. The relative failure probability number is assigned to each component failure mechanism and represents an estimated probability of failure due to the particular failure mechanism. On the scale, 1 represents the lowest probability of failure and 10 represents the highest.

Engineering judgement is used in estimating the relative failure probability number for each failure mechanism. A total number is calculated by adding the relative probability

TABLE 2-21

DETAILED FAULT TREE ANALYSIS (DC Motor SSCVA)

D.C. Motor Proportional Electric Actuator Reliability
 Fault Tree Analysis 939J957 Estimated Reliability .9583

1688

1.0	Actuator Coolant Gas Consumption Exceeds Specified Limits		95
1.1	Actuator Housing Fails to Contain Coolant Gas		55
1.1.1	Cover Fails to Contain Coolant Gas	5	
1.1.2	Cover to Body Interface Joint Fails	9	
1.1.2.1	Seal Fails	6	
1.1.2.2	Cover Fasteners Fail	3	
1.1.3	Housing Body Fails to Contain Coolant Gas	1	
1.1.4	Electrical Connector Fails to Contain Gas	40	
1.1.4.1	Seal Fails	30	
1.1.4.2	Fasteners Lose Clamping Force	5	
1.1.4.3	Connector Body Fails to Contain Gas	5	
1.2	Housing to Pedestal Interface Fails to Contain Gas		40
1.2.1	Interface Inlet Coolant Seal Fails	30	
1.2.2	Fasteners Lose Clamping Force	5	
1.2.3	Interface Exhaust Coolant Passage Seal Fails	5	
2.0	Actuator Fails to Position Control Drum Within Time Position Band		1162
2.1	Actuator Fails to Convert Electrical to Mechanical Power		401
2.1.1	Electrical Connector Fails to Transmit Proper Signal	10	
2.1.1.1	Conductor Fails to Transmit Signal	5	
2.1.1.2	Insulator Fails Permitting Short Circuit	5	
2.1.2	Actuator Internal Wiring Harness Fails	35	

2-161

TABLE 2-21 (CONTINUED)

2.1.2.1	Conductor Fails	5	
2.1.2.2	Insulation Fails	25	
2.1.2.3	Terminal Mechanically Fails	5	
2.1.3	Motor Fails Electrically		366
2.1.3.1	Wiring Failure in Rotor Winding	80	
2.1.3.2	Wiring Failure in Stator Winding	40	
2.1.3.3	Pole Pieces Break	1	
2.1.3.4	Commutation Failure	245	
2.1.3.4.1	Brush Holder/Spring Failure	15	
2.1.3.4.1.1	Fastener Failure	5	
2.1.3.4.1.2	Brush Holder Fails	5	
2.1.3.4.1.3	Loss of Spring Gradient	5	
2.1.3.4.2	Brush Failure	100	
2.1.3.4.2.1	Material Deterioration	60	
2.1.3.4.2.2	Material Mechanical Failure	40	
2.1.3.4.3	Wiring Failure	50	
2.1.3.4.3.1	Conductor Fails	10	
2.1.3.4.3.2	Insulation Fails	40	
2.1.3.4.4	Slip Ring Failure	80	
2.1.3.4.4.1	Mechanical Failure	30	
2.1.3.4.4.2	Electrical Failure	50	
2.2	Improper Command Received from Amplifier		249
2.2.1	Amplifier Control Voltage Incorrect		AGC
2.2.2	Amplifier Fails Internally		30
2.2.3	Amplifier Feedback Signal Incorrect		219

TABLE 2-21 (CONTINUED)

2.2.3.1	Potentiometer Supply Voltage Wrong Value		30	
2.2.3.1.1	Actuator System Wiring Harness Fails		30	
2.2.3.1.2	Voltage Supplied is in Error		AGC	
2.2.3.2	Feedback Potentiometer Output Fails			154
2.2.3.2.1	Potentiometer Electricall Fails		101	
2.2.3.2.1.1	Track Resistance Value Changes	10		
2.2.3.2.1.2	Protective Resistor Changes Value	10		
2.2.3.2.1.3	Wiper Resistance Value Changes	1		
2.2.3.2.1.4	Wiper to Track Contact Resistance Changes	80		
2.2.3.2.2	Angular Relationship Pot to Drum Changes		21	
2.2.3.2.2.1	Pot Position Relative to Shaft Changes	20		
2.2.3.2.2.2	Shaft Relative to Drum Changes	1		
2.2.3.2.3	Potentiometer Mechanically Fails		32	
2.2.3.2.3.1	Potentiometer Shaft Fails	1		
2.2.3.2.3.2	Wiper Spring Gradient Changes	1		
2.2.3.2.3.3	Bearings Fail	10		
2.2.3.2.3.4	Potentiometer Housing Fractures	20		
2.2.3.3	Feedback Signals Transmitted Improperly			35
2.2.3.3.1	Wiring Harness Actuator to Amplifier Fails		AGC	
2.2.3.3.2	Mechanism Wiring Harness Fails		30	
2.2.3.3.3	Electro-Magnetic Interference Distorts Signal		5	
2.3	Actuator External Control Drum Loads Change			EC
2.4	Actuator Internal Loads Change			812
2.4.1	Flexspline Torque Output Low			260
2.4.1.1	Teeth Fail to Transmit Torque		15	

TABLE 2-21 (CONTINUED)

2.4.1.1.1	Teeth Break	10	
2.4.1.1.2	Teeth Wear	5	
2.4.1.2	Fastener Interferes with Motion		10
2.4.1.3	Wave Generator Rotation Fails		155
2.4.1.3.1	Bearing Friction Increases	130	
2.4.1.3.2	Eliptoidal Cam Breaks	5	
2.4.1.3.3	Flexible Outer Race Breaks	20	
2.4.1.4	Cup Fails to Transmit Motion		80
2.4.1.4.1	Weld Fails	30	
2.4.1.4.2	Cup Breaks	50	
2.4.2	Motor Fails Mechanically		442
2.4.2.1	Bearing Friction Increases	280	
2.4.2.2	Fasteners Interfere with Motion	10	
2.4.2.3	Stator Wiring Interferes with Motion	76	
2.4.2.3.1	Actuator Housing Distorts	1	
2.4.2.3.2	Stator Porting Material Deteriorates	10	
2.4.2.3.3	Conductor at I.D. of Motor Breaks	5	
2.4.2.3.4	Pole Pieces Break	60	
2.4.2.4	Rotor Wiring Interferes with Rotation		76
2.4.2.4.1	Actuator Housing Distorts	1	
2.4.2.4.2	Rotor Porting Material Deteriorates	10	
2.4.2.4.3	Conductor at Circumference of Rotor Breaks	5	
2.4.2.4.4	Pole Pieces Break	60	
2.4.3	Output Shaft-Pot Bearings Friction Level Increases		70
2.4.4	Output Shaft Fails to Transmit Torque		40
2.4.4.1	Teeth Break		10

TABLE 2-21 (CONTINUED)

2.4.4.2 Shaft Breaks	20	
2.4.4.3 Cup to Shaft Coupling Fails	10	
3.0 Actuator Electrical Power Rate Exceeds Specified Limits		131
3.1 Actuator Short Circuits		111
3.1.1 Potentiometer Internal Short Circuit	10	
3.1.2 Stator Wiring Insulation Fails Allowing Short Circuit	10	
3.1.3 Wiring Harness System Short Circuits	21	
3.1.3.1 Interface Connector Short Circuits	10	
3.1.3.2 Wiring Insulation Fails	10	
3.1.3.3 Terminal Fails	1	
3.1.4 Rotor Wiring Insulation Fails	70	
3.2 Amplifier Internal Short Circuit		20
3.3 Amplifier/Actuator External Cable Short Circuit Failure		AGC

Figure 2-33 DC Motor Proportional Electric Actuator Summary Fault Tree

numbers. This technique is considered acceptable since the failure modes listed are independent and mutually exclusive of one another.⁽¹⁴⁾ The total number then indicates the relative reliability of the actuator concept; the lower the number, the more reliable the particular concept is relative to the others. Each concept is compared with the others on the basis of the total relative failure probability number.

The failure mode analysis for this particular actuator concept is reported in detail in the Control Drum Actuator Trade Study Report, TME-1984.⁽¹⁵⁾ The total relative failure probability number reported in this analysis is 171. In performing the analysis it is recognized that the work accomplished is directly applicable to the SSCSS actuator trade study. To avoid repeating the details of the analysis for the purpose of this subject study only the total relative failure probability number is reported.

2.6.7.3 Safety Evaluation

The inherent safety and criticality of any failure is an important parameter to be considered in making a selection of a recommended concept. To determine a relative safety and criticality ranking for each concept, failure modes have been identified. For each of the failure modes listed, mechanisms of obtaining that failure mode are established as they relate to a particular design and each of these failure mechanisms is given a numerical ranking consistent with its effect on the NSS and engine mission. Four categories of criticality are used to determine the safety rating of each concept as follows:

<u>Ranking</u>	<u>Description</u>
4	Failures resulting in gross core failure or possibly affecting structural integrity; crew safety jeopardized; African window safety in question.
3	Failures requiring corrective action resulting in reductions in chamber pressure/temperature below the emergency recovery mode level.

2	Failures requiring corrective action resulting in reduction in chamber temperature/pressure but not below emergency recovery mode level; completion of mission in question.
1	Failures resulting in insignificant effects on chamber temperature/pressure.

By assigning each mechanism of failure to one of the above categories, and finally obtaining a sum of all of the failure mechanisms, a total relative criticality ranking is obtained for each concept. The lower the total number estimate for a concept, the safer that concept is in relationship to the other concepts considered. The CDA Trade Study Report, TME-1984,⁽¹⁵⁾ tabulates the failures, mechanism of failure and criticality ranking of failure for the DC electric motor actuator. The total criticality ranking for this concept is 194.

2.6.8 Evaluation of Concept

The DC self-commutated motor has a small envelope and is relatively lightweight compared to some of the other electric concepts. Response time is excellent; however, an armature shorting technique will probably be utilized to stop the motor at position without excessive coasting.

A major problem exists in developing a reliable commutation system. Aside from the problems affecting all dc motors, (brush failure, spring gradient loss, film deposition, etc.,) the development effort must also solve the problem of corona discharge and arc quenching in the four torr atmosphere the actuator will face on startup. Other areas, common to most electric actuator concepts, requiring substantial development effort are the concentric potentiometer, wiring insulation, high-speed bearings and motor coil encapsulant.

Velocity limits are a requirement placed on the actuator by NSS control and safety. To achieve these limits with a dc motor, a tachometer or the derivative of position is required. It is questionable whether the signal to noise ratio of the position derivative could be made low enough to be used as an input to the motor, particularly with the large gear reduction

required between the motor output and the potentiometer shaft. A tachometer built integrally with the motor shaft appears to be the best solution.

The self-commutating DC proportional electric actuator width at the output shaft centerline is about 7.2 inches. Its height above the mounting boss is about 9.0 inches. Clearance required above the actuator for removal is about .75 inch. The self-commutating dc motor concept is estimated to weigh about 7.1 pounds. Coolant requirements for a one hour run at the heating rates estimated for NERVA, about 3 watts per pound, are less than 1/2 pound and can probably be neglected. The main electrical power required is about 20 watts with a reduced power of about 5 watts and is assumed to provide a holding torque against the anti-backlash spring when the actuator is not moving. Signal level power to supply the feedback potentiometers and actuator control amplifier is small and has been neglected for this comparative study. A preliminary estimate of the concept reliability, obtained by calibrating the fault tree, is 0.9_{-5}^{+83} . Table 2-22 is a listing of some of the more significant advantages and disadvantages of the DC servomotor concept.

2.7 FLUIDIC SYSTEM CONCEPT

The NERVA program is predicated on a very ambitious and unprecedented reliability goal which becomes a paramount consideration when selecting Structural Support Coolant Valve (SSCV) Actuator concepts to be incorporated as subjects of this trade study. In concert with the commendable high reliability goal of NERVA and the directive to design an engine based upon the technology of the future, it follows that a cardinal consideration is to evaluate a concept based upon the new scientific field of Fluidics.

Of all the "pro" arguments advanced today by those engineers and scientists who are working in this new and expanding field, the major factor recognized is the high reliability which is attainable through Fluidics. In a recent issue of the technical magazine Instruments and Control Systems, Vol. 39, an article entitled "Prospects for Fluidics", H. Burke Horton of Sperry Rand Corporation, Univac Division, said the following in relation to the use of fluidics in a nuclear reactor: "The other specialized area is concerned with invulnerability to ionizing radiation. For control functions close to the core of a nuclear reactor, or for long exposure to ionizing radiation in space, fluid devices may be used for some purposes because they are less vulnerable than electronic devices."

TABLE 2- 22

DC SERVO MOTOR/HARMONIC DRIVE SSCV ACTUATOR CONCEPT SUMMARY TABLE

<u>Advantages</u>		<u>Disadvantages</u>	
1.	Low Weight	1.	High Speed Bearings.
2.	Probably Requires Less Power Than Other Concepts.	2.	Brush Commutation.
3.	High Short Time Stall Torque Due to High Gear Reduction.	3.	Armature Shorting to Stop.
4.	Small Overall Size.	4.	Very High Currents at Increased Loads. Possible to Burn Out Motor Armature.
		5.	Requires Convection Cooling.
		6.	Probably Requires Tachometer for Stabilization and Velocity Limits.
		7.	Probably Requires a Brake or Zero Position Lock.
		8.	Low Torque at the Motor Output Shaft.

A similar article appeared in Machine Design, February 7, 1966, entitled "Fluidics Today" by Melvin E. Long, Associate Editor. In this article, Mr. Long stated, "The elimination of moving mechanical parts in fluidic devices yields simplicity, high reliability, and practically unlimited life. In addition, fluidic devices are unaffected by high temperature, shock, vibration and nuclear radiation. . . . " The arguments advanced for fluidics are promising and very difficult to refute. For this reason, this portion of the SSCV actuator trade study is directed toward an evaluation of a Fluidic Concept.

Not all of the argument for fluidics is as purely speculative such as those quoted. There are several applications in aerospace and other related fields which are known and listed here for further support as to the feasibility of fluidics in NERVA.

- 1) At least two Soviet orbital spacecraft are known to have utilized analog and digital fluidic systems. (Electro-Tech, March 1967)
- 2) The Army Missile Command has sponsored the development of a pure-fluid missile control system for the "test instrumentations missile" (TIM), which is a modification of the Little John rocket. (Electro-Tech, March, 1967)
- 3) General Electric has developed a fluidic proportional thruster system for sounding rocket application under contract to NASA/Ames Research Center. (ASME 68-WA/FE-32)
- 4) Corning Glass and Honeywell have developed fluidic fuel control systems for commercial turbine engines. Automatic flight controls have also been developed in which all elements of the autopilot are fluidic. Stability augmentation systems have been devised to replace existing electronic equipment of the Boeing CH-46A helicopter and the Bell UH-1C helicopter. (Engineer, February 1969)
- 5) Bendix, under contract with NASA-Langley, has developed a fluidic system for push-pull secondary injection thrust vector control of a solid rocket engine. (Fluidics Quarterly 1967)
- 6) Sperry Gyroscope Company has devised a fluidic attitude-control system for a space vehicle used for interplanetary missions. (Electro-Tech, 1967)

2.7.1 Mechanical Description

A technical illustration of the Fluidic System Concept configuration is shown in Figure 2-34. To provide further insight, an exploded view is shown in Figure 2-35.

- 1) The Logic
- 2) The Driver
- 3) The Diverter

2.7.1.1 The Logic Subassembly

This unit consists of three control solenoids, a four stage binary counter, four control gates, and four summing points. The control solenoids are ON-OFF solenoid valves. Each valve is built in an "H" configuration for reliability. These normally closed valves are the only moving parts in the entire system. The four-stage binary counter is a pure fluidic "flip-flop" device. Each counter stage is used to control a control gate as shown in Figure 2-35. The four control gates are pure fluidic, bi-stable devices operating on the Coanda principle. The output of the gates are summed by the physical containment of the related system piping. The flow is piped to a simple mechanical pipe joint such as a "branch tee".

2.7.1.2 The Drive Subassembly

The unit consists of staged proportional amplifiers. Each is a true fluidic amplifier which contains no electronics or moving parts. The units are jet-on-beam devices operating in a cascading fashion to ultimately form the control flow for the diverter. For reference design purposes, there are three staged amplifiers shown upstream of the diverter, each with a gain of 10. This is not necessarily true as there apparently are no units with this gain factor presently available, although it is a theoretically attainable gain factor.

2.7.1.3 The Diverter Subassembly

The diverter, Figure 2-36, prime component in the system, is a beam-deflection device, similar to a fluidic differential amplifier. High energy LH_2 is supplied to the diverter directly from the turbopump. As the LH_2 passes through a rectangular power nozzle into an interaction region, it becomes a power jet. The control signal, in jet form, is also directed into the interaction region from nozzles on each side of the power jet and perpendicular to it.

FLUIDIC SSCSS CONTROL

Figure 2-34 Fluidic System Concept Configuration

Figure 2-35 Breakdown of Fluidic System Concept

Figure 2-36 Diverter Subassembly

The momentum flux of the power jet and the forces exerted on it by the control jets determine the direction the stream will assume after it leaves the interaction region. The control jets apply a combination of pressure and momentum flux forces. When the stream leaves the interaction region, the shape of its velocity profile is approximately gaussian. The profile broadens and decreases in centerline velocity as it moves downstream. At a distance downstream of the interaction region, the resulting jet flow is divided and collected in the shim and bypass apertures.

2.7.2 System Description

The system is presented in block diagram form in Figure 2-37. Engine programmed commands are received in the form of pulses at the three control solenoids. Sequential pulsing of the "count up" solenoid increases the binary counter through 15 states to a maximum shim flow condition. The "1" outputs of the individual counter stages trigger control gates which develop a differential pressure at the logic summing point output. This differential pressure signal is directly related to the binary counter state and is varied in equal incremental steps by change in the binary counter state. Pulsing of the "count down" solenoid reduces the state of the binary counter with corresponding reduction in the differential pressure signal. A single pulse at the reset solenoid returns the binary counter to the initial all "0" state.

The differential pressure signal is the control signal for the first of the staged proportional amplifiers. The output of the staged amplifiers in turn controls the flow diverter. The flow diverter, as explained in paragraph 2.7.1.3, receives the hydrogen main stream system flow directly from the turbopump. This main stream flow, in the form of a power jet, is directed in a proportional manner to the outlet region where it is divided into the shim (coolant) and bypass apertures.

2.7.3 Radiation Evaluation

The radiation analysis of section 2.1.3 is directly applicable to the fluidic concept. The radiation levels listed in Table 2-2 remain unchanged because the presence of this concept in that particular region will have little or no effect on the predicted radiation levels. Actually, the fluidic system concept is likely to be installed in a zone slightly more removed from the NSS than the position used as reference for the analysis. For this reason, the information in Table 2-2 is considered conservative.

Figure 2-37 Fluidic SSCSS Control Block Diagram

2.7.4 Thermal Evaluation

The heating rates predicted for this particular environment are rather low and are not expected to present any particular problem to the design. The components of the concept which may be considered an internal heat source are the solenoid valves used in the logic portion of the design. With the evaluation of a detail design, a thermal analysis will be made and proper coolant provided in this region, if deemed necessary. The power source for the fluidic concept is the hydrogen flow itself which is expected to enter the system at nearly 60°R. At this low temperature, it appears that only cryogenic operation should be a cause for design emphasis. As the concept of a fluidic system expands and detail components are designed, a complete, accurate, and thorough thermal analysis will be made. At this point in time, the design has no apparent thermal problem.

2.7.5 Structural Evaluation

No detailed structural evaluation has been made due to the design state of this concept. The system concept shall be, by and large, a pressure vessel oriented design and should present no serious problems. The related piping attendant with this system will have to be analyzed from a dynamics viewpoint to determine if any vibration or mechanical shock modes may be a particular problem. As the design evolves and more details are available, a structural analysis will progress accordingly.

2.7.6 Radiation Effects Evaluation

The hardware of the fluidic concept is metal. The only area which will require design attention in regard to radiation effects will be the coils in the solenoid valves. This is not anticipated to be a problem because radiation tolerant insulation and encapsulating materials are available. If the fluidic concept develops toward a final design system, then a complete and detailed radiation effects analysis would be required as the design details evolve.

2.7.7 Reliability and Safety Evaluation

The evaluation of the reliability and safety of the fluidic concept is accomplished in the same manner as all of the previous actuator system concepts. The reliability is assessed by fault tree analysis and by failure mode analysis.

Fluidic devices have three modes of failure which can impair operation of the system:

1) Structural Failure

All structural parts are made of the same material. Component pieces are either cast or laminated. Seal failure, rupture of the device walls or fasteners will cause leakage and control disruption. However, as it is essentially a block of metal with no moving parts, the fluidic concept is less susceptible to mechanical failure than any of the other actuator/valve concepts, or even the engine plumbing system in general.

2) Contamination

Significant particulate contamination can clog passageways in the early logic control elements and disrupt control of the diverter stage. However, cleanliness requirements, particulate size, etc., for the fluidic system are likely to be not as stringent as those of the reactor core elements and, therefore, propellant contamination levels that satisfy the core will satisfy the fluidic system.

3) Noise

Acoustic disturbances can have a pronounced effect on confined jets, inducing turbulence in laminated jets and altering stream wall attachment in digital elements. The cause and mechanism of this phenomena is not fully understood and will require extensive developmental testing to assure elimination of this effect in the early logic stages of the fluidic system.

The fluidic portion of the system receives control signals in the form of hydraulic pulses. These pulses are developed by the three solenoids under electrical control of the engine programmer. The solenoids represent the only moving part mechanisms in the overall system control and are the least reliable pieces in the system. Solenoid reliability will require significant development. This, most likely, in an "H" configuration where multiple concurrent malfunctions must occur to cause the solenoid to fail.

2.7.7.1 Fault Tree Evaluation

A complete and accurate description of the method employed in performing a fault tree analysis is given in Section 2.1.7.1 of this report. The particular detailed fault tree and weighted numbers pertaining to this fluidic system concept are given in Table 2-23. It is apparent from the brevity of this detailed fault tree that the failures in the fluidic concept are

TABLE 2-23
DETAILED FAULT TREE
(Fluidic Concept)

Fluidic Concept - SSCSS Reliability - Fault Tree
Analysis 100E804 Estimated Reliability $.9_{659}$.

405

1.	Electrical Consumption Rate Exceeds Specified Limits due to Short Circuit	2	
2.	Valve Fails to Control Flow per Specification	340	
2.1	Control Element Fails to Function Properly	70	
2.1.1	Supply Line to Solenoid Body Leaks at Interface	10	
2.1.2	Supply Interface Seal Failure	52	
2.1.3	Leak due to Mechanical Failure of Housing	8	
2.2	Solenoid Valve Inoperative	230	
2.2.1	Insulation Failure, Coils Short Circuit	50	
2.2.2	Conductor Breaks Coil Open	30	
2.2.3	Solenoid Mechanically Fails, Plunger Stuck	150	
2.3	Solenoid Fails Open, Plunger Interference	40	
3.	Flow Leakage Rate Exceeds Limit	63	
3.1	Housing Ruptures	6	
3.2	Main Interface Fasteners Fail	5	
3.3	Receiver Interface Seal Fails	52	

very few compared to the other system fault trees. The total weighted number, 405, is the best reliability figure arrived at in this entire trade study.

2.7.7.2 Failure Mode Evaluation

As this system concept is not a completely detailed design, the failure mode analysis is not done by analyzing each individual part, but rather upon analyzing arbitrary selected groups of parts that form basic components within the concept. In generating the failure mode analysis, each component is analyzed for possible failure modes. These failure modes are identified and listed. Then, each failure mode is analyzed and the component failure mechanisms which cause the particular failure mode are identified and listed.

A reliability comparison of each system concept is accomplished by using a rating technique which uses a relative failure probability number based on a scale ranging from 1 to 10. The relative failure probability number is assigned to each component failure mechanism and represents an estimated probability of failure due to the particular failure mechanism. On the scale, the Number 1 represents the lowest probability of failure and the Number 10 represents the highest.

Engineering judgement is used in estimating the relative failure probability number for each failure mechanism. A total number is calculated by adding the relative probability numbers. This technique is considered acceptable since the failure modes listed are independent and mutually exclusive of one another.⁽¹⁴⁾ The total number then indicates the relative reliability of the system concept; the lower the number the more reliable the particular concept relative to the others. Each concept is compared with the others on the basis of the total relative failure probability number. The failure mode analysis for the Fluidic System Concept is shown in Table 2-24.

2.7.7.3 Safety Evaluation

The inherent Safety and Criticality of any failure is an important parameter to be considered in making a selection of a recommended concept. To determine a relative Safety and Criticality ranking for each concept, failure modes have been identified. For each of the failure modes listed, mechanisms of obtaining that failure mode have been established as they

TABLE 2-24
COMPONENT FAILURE MODES ANALYSIS

SHEET 1 OF 4

Fluidic Concept

DATE 11-3-69 PREPARED BY I. R. Spezialetti DEPARTMENT Reliability SUBSYSTEM SSCVA

DATE _____ APPROVED BY /s/ R.A.C. COMPONENT Control Logic DWG NUMBERS 100E804

W59150

TOTAL RATING 43

Mode Ident. No.	Component Failure Mode of Failure	Component Mechanism of Failure	Mission Phase	Failure Probability Rating
1.1	Control Logic fails so coolant supply flow can not be increased	a. Housing fractures, causing leakage b. Count-up solenoid shorts out or opens c. Count-up solenoid mechanical failure, making solenoid inoperative		1 3 6
1.2	Control Logic fails so coolant supply flow cannot be decreased	a. Housing fractures, causing leakage b. Count-down solenoid shorts out or opens c. Count-down solenoid mechanical failure, making solenoid inoperative		1 3 6
1.3	Control Logic fails so as to become unstable	a. Housing fractures, causing leakage		1

TABLE 2-24 (continued)
COMPONENT FAILURE MODES ANALYSIS

SHEET 2 OF 4

DATE 11-3-69 PREPARED BY I. R. Spezialetti DEPARTMENT Reliability SUBSYSTEM Fluidic Concept SSCVA
 DATE _____ APPROVED BY /s/ R.A.C. COMPONENT Proportional Amplifiers DWG NUMBERS 100E804

W59150

Mode Ident. No.	Component Failure Mode of Failure	Component Mechanism of Failure	Mission Phase	Failure Probability Rating
2.1	Amplifiers fail so as to provide less flow than demanded, and resulting in excessive external leakage	a. Amplifier housing fractures causing leakage b. Supply manifold joint seal surface damaged c. Supply manifold joint fasteners break or loosen d. Diverter Interface joint seal surface damaged e. Diverter Interface joint fasteners break or loosen		1 1 1 1 1

TABLE 2-24 (continued)

COMPONENT FAILURE MODES ANALYSISSHEET 3 OF 4

Fluidic Concept

DATE 11-3-69 PREPARED BY I. R. Spezialetti DEPARTMENT Reliability SUBSYSTEM SSCVADATE _____ APPROVED BY /s/ R.A.C. COMPONENT Flow Diverter DWG NUMBERS 100E804

W59150

Mode Ident. No.	Component Failure Mode of Failure	Component Mechanism of Failure	Mission Phase	Failure Probability Rating
3.1	Flow Diverter fails so as to provide less flow than demanded, and resulting in excessive external leakage	a. Diverter housing fractures causing leakage b. Inlet flow joint seal surface damaged c. Inlet flow joint fasteners break or loosen d. Amplifier interface joint seal surface damaged		1 1 1 1
3.2	Flow Diverter fails so as to provide more flow than demanded, or to cause flow instability	a. Amplifier interface joint seal surface damaged		1

TABLE 2-24 (continued)

COMPONENT FAILURE MODES ANALYSIS

SHEET 4 OF 4

Fluidic Concept

DATE 11-3-69 PREPARED BY I. R. Spezialetti DEPARTMENT Reliability SUBSYSTEM SSCVADATE APPROVED BY /s/ R.A.C. COMPONENT Seals, Working Fluid DWG NUMBERS 100E804

W59150

Mode Ident. No.	Component Failure Mode of Failure	Component Mechanism of Failure	Mission Phase	Failure Probability Rating
4.1	Seals fail so as to reduce the coolant flow to less than demanded, and resulting in excessive external leakage	a. Inlet flow to Diverter Seal leaks b. Supply Manifold to Amplifiers Seal leak c. Amplifier/Diverter Interface Seals leaks		3 3 6
4.2	Seals fail so as to reduce or increase the coolant flow as compared to demanded, or to cause flow instability	a. Amplifier/Diverter Interface Seals leaks		Included in 4.1.c above

relate to a particular design and each of these failure mechanisms has been given a numerical ranking consistent with its effect on the NSS and engine mission. Four categories of criticality have been used to determine the safety rating of each concept as follows.

<u>Ranking</u>	<u>Description</u>
4	Failures resulting in gross core failure or possibly affecting structural integrity; crew safety jeopardized; African window safety in question.
3	Failures requiring corrective action resulting in reductions in chamber pressure/temperature below the Emergency Recovery Mode level.
2	Failures requiring corrective action resulting in reduction in chamber temperature/pressure but not below Emergency Recovery Mode level; completion of mission in question.
1	Failures resulting in insignificant effects on chamber temperature/pressure.

By assigning each mechanism of failure to one of the above categories, and finally obtaining a sum of all of the failure mechanisms, a total relative criticality ranking is obtained for each concept. The lower the total number estimate for a concept, the safer that concept is in relationship to the other concepts considered. The following Table 2-25 presents a tabulation of the Failures Mechanism of Failure and Criticality Ranking of Failure for the Fluidic System Concept. The total criticality ranking for this concept is 54.

2.7.8 Evaluation of Concept

The fluidics state-of-the-art is not such that an existing system can be adapted to the SSCSS requirements. The emphasis in fluidics has been used primarily in machine tool

TABLE 2-25

COMPONENT FAILURE MODES ANALYSIS

SHEET 1 OF 4

DATE 11-3-69 PREPARED BY I. R. Spezialetti DEPARTMENT Reliability SUBSYSTEM Fluidic Concept SSCVA
 DATE APPROVED BY /s/ R. A. C. COMPONENT Control Logic DWG NUMBERS 100E804

W59150

TOTAL RATING 54

Mode Ident. No.	Component Failure Mode of Failure	Component Mechanism of Failure	Mission Phase	Failure Probability Rating
1.1	Control Logic fails so coolant supply flow can not be increased	a. Housing fractures, causing leakage b. Count-up solenoid shorts out or opens c. Count-up solenoid mechanical failure, making solenoid inoperative	Steady State & Startup	4 4 4
1.2	Control Logic fails so coolant supply flow cannot be decreased	a. Housing fractures, causing leakage b. Count-down solenoid shorts out or opens c. Count-down solenoid mechanical failure, making solenoid inoperative	Steady State & Startup	4 4 4
1.3	Control Logic fails so as to become unstable	a. Housing fractures, causing leakage	Steady State & Startup	2

TABLE 2-25 (continued)

COMPONENT FAILURE MODES ANALYSISSHEET 2 OF 4

DATE 11-3-69 PREPARED BY I. R. Spezialetti DEPARTMENT Reliability SUBSYSTEM Fluidic Concept SSCVA
 DATE _____ APPROVED BY /s/ R.A.C. COMPONENT Proportional Amplifiers DWG NUMBERS 100E804

W59150

Mode Ident. No.	Component Failure Mode of Failure	Component Mechanism of Failure	Mission Phase	Failure Probability Rating
2.1	Amplifiers fail so as to provide less flow than demanded, and resulting in excessive external leakage	a. Amplifier housing fractures causing leakage b. Supply manifold joint seal surface damaged c. Supply manifold joint fasteners break or loosen d. Diverter Interface joint seal surface damaged e. Diverter Interface joint fasteners break or loosen	Steady State & Startup	2 2 2 2 2

TABLE 2-25 (continued)
COMPONENT FAILURE MODES ANALYSIS

SHEET 3 OF 4

Fluidic Concept

DATE 11-3-69 PREPARED BY I. R. Spezialetti DEPARTMENT Reliability SUBSYSTEM SSCVA
 DATE _____ APPROVED BY /s/ R. A. C. COMPONENT Flow Diverter DWG NUMBERS 100E804

W59150

Mode Ident. No.	Component Failure Mode of Failure	Component Mechanism of Failure	Mission Phase	Failure Probability Rating
4.1	Flow Diverter fails so as to provide less flow than demanded, and resulting in excessive external leakage	a. Diverter housing fractures causing leakage b. Inlet flow joint seal surface damaged c. Inlet flow joint fasteners break or loosen d. Amplifier interface joint seal surface damaged	Steady State & Startup	2 2 2 2
3.2	Flow Diverter fails so as to provide more flow than demanded, or to cause flow instability	a. Amplifier interface joint seal surface damaged	Steady State & Startup	2

TABLE 2-25 (continued)

COMPONENT FAILURE MODES ANALYSIS

SHEET 4 OF 4

Fluidic Concept

DATE 11-3-69 PREPARED BY I. R. Spezialetti DEPARTMENT Reliability SUBSYSTEM SSCVADATE APPROVED BY /s/ R. A. C. COMPONENT Seals, Working Fluid DWG NUMBERS 100E804

W59150

Mode Ident. No.	Component Failure Mode of Failure	Component Mechanism of Failure	Mission Phase	Failure Probability Rating
4.1	Seals fail so as to reduce the coolant flow to less than demanded, and resulting in excessive external leakage	a. Inlet flow to Diverter Seal leaks b. Supply Manifold to Amplifiers Seal leak c. Amplifier/Diverter Interface Seals leaks	Steady State & Startup	2 2 2
4.2	Seals fail so as to reduce or increase the coolant flow as compared to demanded, or to cause flow instability	a. Amplifier/Diverter Interface Seals leaks	Steady State & Startup	2

2-190

coolant systems and batching process control. The SSCSS application, while similar to some of these applications, is unique in the medium, rate of flow, and small pressure drop requirements. It is further complicated by the possibility that 2-phase flow may occur in the system and will require evaluation.

A cursory evaluation of this fluidic concept has been made by Westinghouse R&D Division Fluidic Engineering personnel and the workability established. Westinghouse R&D is presently making a more detailed evaluation of the concept to establish the feasibility of meeting the requirements of the SSCSS specification with the fluidic configuration.

Relative to the other SSCSS actuator/valve concepts under consideration, the fluidic system concept (replacing both the actuator and valve) offers distinct advantages in reliability, power requirements, weight and control complexity. In addition, it is unaffected by radiation, vibration and temperature extremes. As there are no wearing parts in the fluidic concept, the possibility of introducing contaminants into the reactor dome is eliminated.

Because the fluidic concept will have to be developed essentially from scratch, extensive design, development and testing time will have to be done. The investment of effort to develop the fluidic concept will necessarily be heavier than that of the other actuator concepts. However, the end product will be the best in performance and in nearly all other categories, and will be applicable to engine technology beyond R-1 and other aerospace projects as well.

3.0 COMPARISON OF DESIGN APPROACHES

Table 3-1, the Parameter Value Estimate Matrix, is compiled to compare the various studied concepts on a basis of common criteria requirements. In the matrix are actuator performance criteria as well as other criteria considered pertinent to the trade study. Once the pertinent actuator parameters are defined, the matrix evaluates the ability of each actuator concept to perform the parameters specified. This evaluation is accomplished in the matrix by relating the actuator ability to a weighted factor method, thus quantitating the relative abilities of each actuator concept. The final comparison is made within the matrix by computing a total figure of merit. This final value is attained by multiplying the weighting factor assigned to a particular column by the particular actuator rating for that parameter, and summing the figures obtained for each performance parameter column.

In compiling the matrix, there are two basic assumptions made in regard to the electric actuator drive power requirements. These assumptions are:

- 1) The transient duty cycle will be 25 percent of the total (one hour) operating time.
- 2) The load spring will require a holding torque output from the actuator during those operational phases requiring the actuator to hold position.

It is an extremely difficult task to objectively compare certain of these actuators on the basis of power consumption because of the unknown ratio of holding to transient consumption periods. In addition, it is recognized that in the case of the commutated DC motor, the power consumption will be directly related to the torque required and for a PM stepping motor the power consumption will be at the constant maximum rated power no matter what the torque level required. The matter is further complicated by the fact that only the PM stepping motor requires no power to hold a given position. This is due to the inherent detent torque capability in a PM stepper.

Listed across the top of the matrix are the parameters used to evaluate each concept. The actuator concepts are listed in the left column. The next two columns, respectively, are the study layout drawing number and the fault tree drawing number. The following five columns are grouped under one title - "Drive Power Requirements". The column "Type" lists the

TABLE 3-1

STRUCTURAL SUPPORT COOLANT VALVE ACTUATOR TRADE STUDY PARAMETER VALUE ESTIMATE MATRIX

Actuator Type	Concept Study Layout	Fault Tree Drawing	Type	Drive Power Requirements					Actuator Weight	System Weight Excluding Valve	Applicable Developmental Test Experience		Number of Items	Reliability		Safety	Stress, Thermal & Radiation	Con't Stall Torque (in-lb)	Comments
				Transient	Holding	25% Duty Integrated Power (60 Min.)	Power Supply Weight	01 lb w/hr			WANL	Other		Fault Free	Failure Mode				
ANALOG-ELECTRIC	Direct Drive Responsyn	711J757	939J964	D.C.	100 W	50 W	63 W hr	6.0 lb at 300 $\frac{lb}{Kw\ hr}$	17 lb	23 lb	Prototype lab tests (TME-1921); pot component development tests.	60	1048	122	120	Although no detail designs are available, no significant structural problems are anticipated, and preliminary radiation information indicates that no high-temperature or material degradation problems of significance exist in shielded location. Cryogenic temperature operation necessitates particular attention to stress calculations and analysis of possible two phase flow problems in fluidic valve.	200	Flexible laminated magnetic rotor requires special attention to potential wear and stress problems.	
	Planetary Transmission Responsyn	Similar to 939J462	939J190	D.C.	30 W	15 W	19 W hr	2.0 lb	9.8 lb	11.8 lb	Similar to direct drive Responsyn.	70	1271	135	160		100	Above comment applies; potential problems amplified by higher speeds and more bearings.	
	Permanent Magnet Stepper	100E819	939J965	D.C.	32 W	0	8 W hr	1.0 lb	6.7 lb	7.7 lb	Similar to Slo-Syn in concept; pot tests applicable.	SNAP LCRE	65	1363	137		134	320	If permanent magnet material other than Alnico V is used, susceptibility to radiation damage must be evaluated.
	Slo-Syn Stepper	100E818	939J464	D.C.	24 W	10 W	14 W hr	1.5 lb	7.4 lb	8.9 lb	Prototype lab tests (TME-1921); potentiometer component tests.	SNAP ZEPO	75	1282	136		138	150	Relatively wide application of Slo-Syn and Harmonic drive components lends confidence to this design concept.*
	Electric Dynavector	100E802	939J963	D.C.	44 W	22 W	27 W hr	2.7 lb	6.8 lb	9.5 lb	Potentiometer component development tests only.		70	1137	125		134	140	Only one unit ever built and tested. Large development effort required.
	2 ϕ A.C. Servo	100E140	939J467	400 Hz A.C.	45 W	30 W	33 W hr	3.3 lb	7.9 lb	11.2 lb	Potentiometer component tests only.	W R & D (NERVA)	80	1498	147		166	110	Relatively high speed rotor bearings require special attention to potential wear problems.
	Commutated D.C. Servo	100E139	939J468	D.C.	20 W	5 W	9 W hr	1.0 lb	7.1 lb	8.1 lb	Potentiometer component tests only.	SNAP APOLLO	75	1688	171		194	340	Potential problem areas include high speed rotor bearings and excessive brush and commutator wear.**
ANALOG-PNEUMATIC	2 Piston Rack and Pinion	910E276	939J475	GH ₂ at 215 psia	Consumption rate at 215 psia is .01 lb/sec at 1400°R or .004 lb/sec at 500°R. Electrical power consumption is negligible.			14.4 lb of GH ₂ at 5000R	12.2 lb of gas storage vessel for one startup (Assumes 44 lb lb of 500°R gas)	14.6 lb	41.2 lb	Extensive XE-1 & 2, A6 side-by-side, Plum Brook, 44 actuators total.	113	1862	220	364	300	Extensive developmental experience on XE actuators lends credence to the applicability of this design.	
	1 Piston Rack and Pinion	Similar to 939J470	939J476							8.1 lb	34.7 lb	Similar to two-position concept but only component tests directly applicable.	75	1470	171	346	250	XE experience largely applicable to this design concept, plus its relative simplicity, indicate good probability of meeting program requirements.	
	1 Piston Helical Cam	100E146	939J474							9.8 lb	36.4 lb	Potentiometer servovalve piston ring component tests only.	70	1830	197	364	200	Unproven ball cage design may be a source of excessive friction or wear.	
	Pneumatic Dynavector	939J955	939J960							11.9 lb	38.5 lb	Potentiometer 2 servovalve component tests only.	150	1754	210	352	100	Differential expansion attending thermal environment could result in troublesome seal leakage problems.	
FLUIDIC	Solenoid Controlled Digital	914E346	100E804	Power consumption negligible					25 lb including valve	25 lb including valve	Prototype component lab study tests only.	20	405	43	54	N...	Appears to be a natural. High reliability and high weight may justify sacrifice of commonality with drum actuators.		

* Matching speed and torque to requirements may be difficult

** Short period torques may be much higher than listed.

(Ref. DDM 51544) Although no detail design are available, no significant structural problems are anticipated, and preliminary radiation information indicates that no high temperature or material degradation problems of significance exist in studied location. Cryogenic temperature operation necessitates particular attention to stress calculations and analysis of possible two phase flow problems in fluidic valve.

various power types used which are ac or dc electric, and GH_2 pneumatic. Next, the "Transient" power column lists that power required when the actuator is moving and supplying torque, while the "Holding" power column is an estimate of the power required to hold valve position against flow and spring loads. The system "Integrated Power" column is an estimate of the total power consumed for a one-hour reactor run. The duty cycle assumed for this estimate consists of a 25 percent moving and 75 percent holding ratio for operating time. The column "Power Supply Weight" is calculated from the integrated power estimate assuming 0.1 pounds per watt hour. The pneumatic weight is based upon a 44 lb/lb at 500°R penalty using a calculated servovalve flow consumption for a one-minute startup. The required coolant is calculated to remove both electrical heat and gamma heat, but the coolant requirements are not assessed against the concepts since none is assumed to be dumped overboard.

The actuator weight column lists an estimate based on the concept size and the materials of construction and does not represent a detailed piece-by-piece calculation. All calculations are done on the same basis and the number is assumed to be good for comparative purposes.

The total system related weight excludes the valve and piping and is the weight of the actuator plus the power supply system weight assessed against each concept. The applicable experience column attempts to list WANL experience as well as other nuclear or related space experience. In some cases, only component experience is listed.

The number of items is a number giving the relative complexity of the concept. It is not an exact part count since each screw, washer, etc., is not included, but it does represent the sum of the item or groups of similar items. The numbers under the relative reliability columns are taken directly from the fault trees and failure modes. They represent the comparative reliability of each concept with the lower numbers being the more reliable in each case.

The "Safety" column lists the direct results of the safety and criticality ranking for each concept. "Stress, Thermal, and Radiation" are a summary of the related sections discussed in each concept write up. Finally, the "Comments" is a column reserved for any remarks which were felt to be pertinent to the overall evaluation of the concept being evaluated.

4.0 SELECTION OF DESIGN APPROACH, CONCLUSIONS

The final selection of a recommended design approach should be the result of this trade study. However, after completing the evaluation of the various alternates, it becomes evident that the other important factors of a systems nature are in a position to swing the study one way or another. The comparison matrix is used to select one candidate from each functional group, that is, one proportional electric, one proportional pneumatic and the fluidic. Results of other systems studies⁽¹⁶⁾ can strongly influence selection between groups. The comparison matrix, Table 4-1, shows the five weighting factors across the top as Reliability, Related System Weight, Related Experience, Performance (Stall Torque) and Safety with weightings of 0.40, 0.25, 0.20, 0.05, and 0.10, respectively. The actuator candidates are shown at the left of the table. All columns have a relative merit number which has been normalized around the best candidate in that column. The highest number represents the best concept for each column. The weighted merit number then is the product of the relative merit and the weighting factor. The figure of merit is the sum of all the weighted merit numbers for each concept.

A single reliability number is obtained by normalizing the numbers obtained from the fault trees, normalizing the numbers obtained from the failure mode analysis, and averaging the two to obtain the relative merit number shown in Table 4-1.

The related system weight relative merit is obtained by normalizing the related system weight from Table 3-1. The related experience relative merit is based on engineering judgement with the XE actuator experience serving as the basis for the judgement.

Since all actuators are designed to meet the minimum performance requirements, normalization is based on stall torque, a side benefit of the particular design concept. The highest stall torque is assigned a relative merit of 1.00. The safety relative merit is obtained by normalizing the numbers from the safety criticality table for each concept. Referring to the results of Table 4-1, the prime selections for each of the three basic systems studied are the permanent magnet stepper motor (analog electric), single piston rack and pinion (analog pneumatic), and the digital diverter (fluidic). In a parallel effort to this trade study, a study

TABLE 4-1

STRUCTURAL SUPPORT COOLANT VALVE ACTUATOR TRADE STUDY - SUMMARY EVALUATION MATRIX

<div> <div>Weighted Relative Merit</div> <div>Weighted Merit</div> </div>		Reliability	Related System Weight	Related Experience	Performance	Safety	(Totalized Weighted Merit) Figure of Merit
Weighting Factor		.40	.25	.20	.05	.10	
ANALOG ELECTRIC	Direct Drive Responsyn	.874 .350	.322 .081	.4 .080	.50 .025	1.00 .100	.636
	Plan. Trans. Responsyn	.757 .303	.637 .159	.2 .040	.25 .012	.750 .075	.589
	Perm. Mag. Stepper	.728 .291	1.0 .250	.6 .120	.75 .038	.895 .090	.789
	Slo-Syn Stepper	.750 .300	.860 .215	.8 .160	.37 .018	.870 .087	.780
	Electric Dynavector	.829 .332	.785 .194	.1 .020	.35 .017	.895 .090	.653
	2 Ø A. C. Servo	.670 .268	.672 .168	.3 .060	.27 .013	.723 .072	.581
ANALOG PNEUMATIC	Commutated D. C. Servo	.584 .234	.937 .234	.4 .080	.85 .042	.618 .062	.652
	2 Piston R & P	.484 .194	.280 .070	1.0 .200	.75 .037	.330 .033	.534
	1 Piston R & P	.631 .252	.369 .092	.9 .180	.62 .032	.347 .035	.591
	1 Piston Heli-Cam	.527 .211	.341 .085	.3 .060	.50 .025	.330 .033	.414
	Pneumatic Dynavector	.519 .208	.311 .078	.2 .040	.25 .012	.341 .034	.372
FLUIDIC	Digital Diverter	1.00 .400	1.00 .25	.1 .020	1.00 (Assumed) .050	1.00 (Assumed) .100	.820

has been performed by AGC⁽¹⁶⁾ to select either electrical or pneumatic as the basic power system for NERVA. The results of that study would dictate the choice of an analog electric versus an analog pneumatic actuator, but would have little or no effect on the selection of the fluidic concept. It might be concluded therefore, and logically so, that the fluidic concept is the selection to be made on the basis of this trade study since the results show that it is a far better candidate by virtue of its high relative weighted figure of merit (0.820) and its immunity to the results of any other trade study. However, this study must be clearly understood prior to suggesting any design selection. The systems studied range from a completely designed and fabricated concept of an actuator system, which was successfully developed and tested in a long-range program for the NERVA engine, to a purely conceptual design based upon a new engineering technology which is just now gaining recognition. The question to be answered then is how to remain objective in light of this fact. It is suggested that the design selection be to develop either the permanent magnet stepper or single piston rack and pinion based upon the engine power system selected, and to evaluate, in a parallel path, the application of fluidics to the NERVA SSCVA system.

4.1 FLUIDIC CONCEPT

A fluidic SSCVA system is an interesting possibility for a NERVA engine in phase with 1978 technology. However, chronologically speaking, the program would have to be directed to develop such a unit in the near future in order to achieve the level required in this technology by 1978. It is recommended that continuing assessment and development of a fluidic system be carried out in parallel with the development of a conventional actuator for NERVA.

4.2 SELECTION OF AN ANALOG CONCEPT

The final selection of an analog actuator is strongly influenced by system considerations such as electric power supply specific weights, pneumatic supply system specific weights, and recovery of pneumatic actuator working fluids. Electric actuators, particularly electric stepping motors, are potentially the best candidates for this application.

4.2.1 Selection of an Analog Electric Actuator

Of the electric candidates considered, the permanent magnet rotor types have several advantages over the other concepts. Experience on the SNAP program in a reactor environment similar to NERVA environment in addition to the other inherent advantages of the permanent magnet stepper motor make the Slo-Syn concept one of the best concepts of the electric stepper motor actuators. The other permanent magnet type is smaller and lighter and contains more poles. Its larger design step makes it more readily adaptable to the SSCVA application. Inherent high detent torque also recommends the PM rotor concept. The DC motor concept appears desirable from a power utilization standpoint, but the inherent problems connected with mechanical brush commutation, required velocity limit tachometer, and mandatory analog electronics eliminate it as the selected design. Therefore, the trade study results in the selection of the permanent magnet rotor concept as the best electric proportional SSCV actuator.

4.2.2 Selection of an Analog Pneumatic Actuator

Of the pneumatic candidates considered, all past NERVA technology experience has been with the basic rack and pinion design. All pneumatic concepts considered have employed the same servovalve and feedback device. The only difference in the pneumatic concept is the means employed to change the pneumatic pressures to output rotary motion. Because the concepts considered do not appear to have any obvious advantage in reliability, machinability, or performance over the basic rack and pinion concept, no reason exists to abandon the rack and pinion concept which has been so successful on the technology program. An extensive redesign effort has been accomplished to simplify the basic XE design, to increase the reliability, to reduce the weight and size, and to adapt it for use to the SSCVA.

4.3 FINAL ACTUATOR SELECTION

As shown in Table 4-1, the results of this study indicate that the best electric analog actuator is the permanent magnet rotor electric stepper motor concept and the best pneumatic analog actuator is the single piston rack and pinion concept.

As this study progressed, it became evident that the final selection between basic types, that is between pneumatic and electric, would be strongly influenced by engine system parameters. For instance, the specific weight of an electrical power supply or the reliability of a pneumatic storage system could swing the selection heavily in favor of one basic type or the other. However, if an objective look is taken at all of the requirements that must be met by a successful design, it is fairly obvious that the most difficult requirement to meet is the reliability goal which is several orders of magnitude better than any reported in the literature. A look at the results of the reliability and safety evaluations shows that several causes for failure resulting in undesirable failure modes are present in the pneumatic devices that are not present in the selected electric concepts. For instance, nothing can fail within a stepper motor mechanism which can cause a drum run-out or run-in. This is not true of a pneumatic device which can have servovalve failures or contamination causing an undesired run-in or run-out.

Based on these results then, unless some overriding, compelling reason exists for selecting the pneumatic device, the WANL recommendation based on known or assumed requirements is to develop the permanent magnet rotor electric stepper motor for use in the SSCV actuator. Also, in a parallel effort, WANL recommends continuing work on the fluidic concept until such time as a final design can be selected.

5.0 REFERENCES

- 1.0 Trade Study No. 701, "Controls Concept Trade Study, " TME-1967.
- 2.0 WANL Drawing No. 939J685, Revision E, "Study Layout of Reference Design NERVA Reactor".
- 3.0 Specification No. CP-677575, "Performance/Design and Qualification Requirements, Structural Support Coolant System for CP-677555A, NERVA Nuclear Subsystem, " January 23, 1969.
- 4.0 Specification No. CP-677555, "Performance/Design and Qualification Requirements for the NERVA Nuclear Subsystem".
- 5.0 Specification No. CP-677576, Part I, "Performance/Design and Qualification Requirement Structural Support Coolant Value (SSCV) Actuator System."
- 6.0 Boltax, A., "Behavior of Semiconductors and Magnetic Materials in Radiation Environment, " Electrical Manufacturing 63, 92 (March, 1969).
- 7.0 Kucher, F., and Bowman, R. E., "Effects of Radiation on Materials and Components, " Reinhold Publishing.
- 8.0 WANL-TNR-224, "NRX-A6 Final Report" (January 1969).
- 9.0 Robinson, D. J., Mayer, J. T., and Wyer, R. R., "NERVA Control Drum Actuator Irradiation Test Program, " NASA TND-5347 (July 1969).
- 10.0 Shipley, J. E., Machine Design, McGraw Hill Book Company, Inc., N.Y., 1956.
- 11.0 Table IV, "Nitalloy 135 MOD, Room Temperature Average Yield Strength, " Nitalloy Corporation, 1954.
- 12.0 Shollenberger, R., Telephone Conversation, June 3, 1969.
- 13.0 DeSalvo, D. J., "Structural Reliability Analysis Techniques and Reflector Example, " October, 1968.
- 14.0 Lloyd, D. K., and Lipow, M., "Reliability Management, Methods and Mathematics, " pg. 77, May 1964.
- 15.0 WANL-TME-1984, Data Item S-54, "Control Drum Actuator Trade Study No. 754.
- 16.0 AGC Trade Study No. 032, "Actuator Drive Power".

TITLE	
	DATA ITEM S-54 Structural Support Coolant Valve Actuator Trade Study 755	
DOCUMENT NO.		DATE
WANL-TME-2691		3/19/70
ABSTRACT One SSCV actuator candidate is selected for development to meet program requirements. Four pneumatic-type proportional actuators, seven electrical-type proportional actuators, and one fluidic type system are considered. Comparison is made on five basic parameters: Reliability, related system weight, related experience, performance, and safety. Concepts selected are: Pneumatic, Single Piston Rack and Pinion; Electric, Permanent Magnet Rotor Electric Stepper Motor, and Fluidic. Recommended is Permanent Magnet Rotor Electric Stepper Motor with a fluidic system as a full back-up.		
DATA ITEM NO.		SECURITY CLASSIFICATION OF DOCUMENT
S-54		Unclassified
CDRL LINE NO.		TOTAL NO. OF PAGES
TBD		201
KEY WORDS Actuators, Structural Support, Valve, Pneumatic, Electric Proportional, Stepper Motors, DC Motors, AC Motors, Reliability, Concepts Fault Tree, Failure Mode, Safety.		
AUTHOR/EDITOR		PREPARING DEPT
R. A. Clark, Jr.		Design Engineering
W Form 59943		DOCUMENT INFORMATION SUMMARY

 Fold
or Cut

 Fold
or Cut