MAY 16 1967

Carl K. K. K.

HC 3.00; MN 65

This is a preprint of a paper intended for publication in a journal or proceedings. Since changes may be made before publication, this preprint is made available with the understanding that it will not be cited or reproduced without the permission of the author.

UCRL -70282
PREPRINT

CONF. 670806. -1

MASTER

Lawrence Radiation Laboratory
UNIVERSITY OF CALIFORNIA
LIVERMORE

**OUTPUT POWER CHARACTERISTICS
OF THERMIONIC CONVERTER ARRAYS
UNDER PARTIAL FAILURE CONDITIONS**

James R. Long

April 24, 1967

LEGAL NOTICE

This report was prepared as an account of Government sponsored work. Neither the United States, nor the Commission, nor any person acting on behalf of the Commission

A. Makes any warranty or representation, expressed or implied, with respect to the accuracy, completeness, or usefulness of the information contained in this report, or that the use of any information, apparatus, method, or process disclosed in this report may not infringe privately owned rights, or

B. Assumes any liabilities with respect to the use of, or for damages resulting from the use of any information, apparatus, method, or process disclosed in this report

As used in the above, "person acting on behalf of the Commission" includes any employee or contractor of the Commission, or employee of such contractor, to the extent that such employee or contractor of the Commission, or employee of such contractor prepares, disseminates, or provides access to, any information pursuant to his employment or contract with the Commission, or his employment with such contractor

This paper was prepared for submittal to the 1967 Intersociety Energy Conversion Engineering Conference, Miami, Florida, August 13-17, 1967.

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

769
1

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency Thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

OUTPUT POWER CHARACTERISTICS
OF THERMIONIC CONVERTER ARRAYS
UNDER PARTIAL FAILURE CONDITIONS¹

James R. Long
Lawrence Radiation Laboratory, University of California
Livermore, California

April 24, 1967

ABSTRACT

The output characteristics of thermionic converter arrays are determined as a function of interconnection scheme, interconnection resistance, converter failure modes and patterns, and converter characteristics. The arrays studied consisted of series strings of converters paralleled with each other by resistive interconnections. The use of additional interconnections is considered to form three-dimensional arrays in which edge effects inherent in planar arrays are eliminated. From an analytical point of view, the applicability of a strictly linear model for the converter is improved with three-dimensional arrays. The output of a three-dimensional array under failure conditions is not significantly greater than that of a planar array, and array shape does not have a strong influence on power output. The array reliability is shown to be greater than the converter reliability. A study of the effect of introducing a statistical distribution of converter parameters appears to show less power loss under failure conditions. A study of the effect of matching the load impedance of a failed array shows that the impedance change is small.

¹Work performed under the auspices of the U. S. Atomic Energy Commission.

INTRODUCTION

Thermionic converters are being considered as possible power generators in space. The main problem in their use is obtaining usable voltage levels, even in the event of component failure. This paper reports on a study of several pertinent parameters of an array of converters, including interconnection topology, interconnection resistance, converter failure modes and patterns, and converter characteristics.

DISCUSSION

An assembly of small thermionic converters connected in an array represents a partial solution to the problem of obtaining usable voltage levels from thermionic converters. Resistive interconnection of series strings of converters with parallel strings provides built-in redundancy to enhance reliability by minimizing the effect of individual component failure. If only short-circuit failures were possible, the single-series strings of converters would suffice to obtain higher voltage levels; however, mechanisms for open-circuit failure also exist. If an open-circuit failure should occur in a single-series string of converters, the power generating capability of the whole string would be lost. The introduction of parallel paths partially solves this problem.

Holland [1]² assumed a source of thermal energy that can be described as a heat source, which resulted in failure propagation due to a failed converter. The assumption of a temperature source eliminates this mode of failure propagation in the converter array.

²Numbers in brackets refer to similarly numbered references at end of paper.

Figure 1 illustrates a six-in-series, three-in-parallel planar array. Larger arrays could be built up from such small arrays; it is believed that at some point the additional incremental advantage gained by larger interconnected arrays would be offset by the additional weight of the interconnections. The analysis of interconnected small arrays has not been pursued.

The applicability of a strictly linear ideal model used to describe the thermionic converter was tested. It was found that array topology became quite complicated before the model could be considered a good one under failure conditions. The more complicated arrays were considered useful because they minimized the load change imposed on neighboring converters due to a failure, which also minimized the loss of power. This effect would be more pronounced in a non-ideal converter, but the results obtained from the ideal model are believed to be representative of the effect of the various parameters studied.

It should be noted that in several cases intuition was a very poor guide in proposing an array with improved characteristics. This problem is primarily due to the fact that array output under failure conditions is the average of two distinct cases. An array with an open-circuit failure is quite different from one with a short-circuit failure.

ARRAY SHAPE AND INTERCONNECTION RESISTANCE

The power output of planar and three-dimensional arrays with three converters in parallel and two- through ten-in-series was calculated as a

function of interconnection resistance with both open-circuit (high resistance) and short-circuit failures. The results for each array size with one converter failure were plotted to determine the expected power output and the optimum interconnection resistance. The analysis is described and the plots presented in Appendix I. The probability of either an open-circuit or short-circuit failure was chosen to be one-half, since mechanisms for both modes of failure exist and no reliability data are available. Figures 2 and 3 summarize the results as a function of array shape. The results indicate that the power lost is relatively independent of array shape, and is approximately equal to twice the maximum power generating capability of a single converter.

The optimum value of the interconnection resistance appears to decrease with increasing number in series. This result is thought to be due to edge effects. If an array were infinite or closed, symmetry arguments would say that all interconnection resistances should be the same. In our case, the converters at the top and bottom of the array have an interconnection resistance on only one side, which would indicate that these resistances should be larger in value. This argument would explain the observed result of the optimum single-value interconnection resistance, decreasing with increasing number of converters in series.

To test this assumption the optimum interconnection resistance was calculated for each position in a 3×5 , 3D array. It was found that the values near the top and bottom of the array were larger than in the center; however, the decrease in expected power loss was very small. Thus, it is believed that this added complication is not worthwhile in construction of an array.

In contrast to the findings of Holland, who assumed a heat source, array shape was found not to be important when a temperature source is assumed; however, edge effects do appear to be important. In the analysis of the planar arrays, it was found that greater power loss occurred with failures at the edges of the array. Thus it was assumed that adding more interconnection resistances to form a three-dimensional array eliminating side-edge effects would produce less power loss. This assumption proved to be wrong.

THREE-DIMENSIONAL ARRAYS

The three-dimensional array was made by connecting each converter to every other of its parallel neighbors in the other series strings. (See Fig. 4a for an example of a ten-in-series, three-in-parallel array, and Fig. 4b for a two-in-series, five-in-parallel array). The power losses in these cases were found to be very slightly less (of the order of 1%) than in the planar case. Thus, the added complications of three-dimensional arrays do not significantly improve the power-generating characteristics of the arrays. It was found that the optimum interconnection resistance for the three-dimensional case is larger than for the planar case, indicating that the relative severity of the effects of open and short failures is different in the three-dimensional case. This detrimental effect appears to counteract the improvement to be expected from the elimination of side-edge effects.

The maximum and minimum loading on a converter neighboring a failed converter are shown for a planar 10×3 array (Fig. 5), a three-dimensional 10×3 array (Fig. 6), and a three-dimensional 2×5

array (Fig. 7). Both the planar and three-dimensional 10×3 arrays show quite severe loading. The judgement of the severity of converter loading is based on the nonlinearity of constant emitter temperature I-V characteristic curves of existing converters (i. e., RCA 1198A). The 2×5 three-dimensional array was analyzed to determine whether the loading effect on neighboring parallel converters could be improved. The results show that the loading of parallel neighbors in this case is not severe. The loading of the series converter in this case is severe, but since there were only two converters in series, it is to be expected. A three-dimensional array with five converters in parallel and five to ten in series would be expected to show small loadings for both parallel and series neighbors to a failed converter.

The planar or three-dimensional three-in-parallel arrays were used to study the characteristics of other arrays because the output power is the only result used and in the ideal model case the output power differs very little as a function of topology.

MULTIPLE FAILURES AND RELIABILITY

The planar ten-in-series, three-in-parallel array was optimized for two like failures and mixed failures. The expected power losses were approximately twice those for one failure. The optimum interconnection resistance value decreased to approximately three-quarters of the single-failure optimum value (the results are shown in Fig. 8). The expected number of failures in the small arrays considered was near one; thus, the optimum interconnection resistance value for one expected failure was used for further calculations.

The effects of multiple failures (up to 15) were calculated for the 10×3 planar array optimized for one expected failure. This information is used to predict array reliability.

The reliability figures are calculated from the binominal expansion (see Appendix II). Two cases are considered: converter reliability of 0.950 (probability of not failing during mission duration), and a reliability of 0.990.

The system problem to be considered here is the determination of the power level of the system which will be considered a system failure. This problem can be solved in reverse by demanding a particular system reliability and determining from that the failure power level. The results of this analysis are shown in Table I.

This table shows, for example, that four failures are allowable if 70% power output is considered a system failure. The system reliability is then 0.980 for a converter reliability of 0.950. For a converter reliability of 0.99, the system reliability is better than 0.9999. These results represent a significant increase in system reliability. The expected number of failures in the array calculated is 1.5 for 0.950 converter reliability and 0.3 for 0.990 converter reliability.

STATISTICAL DISTRIBUTION OF PARAMETERS

To determine the effect of variations among converter parameters, the 10×3 three-dimensional array was analyzed with a normal distribution of the ideal converter model parameters. The normal distribution was

centered about the original values of resistance and source voltage. Standard deviations and cut-off values were placed at two levels; cut-off $\pm 50\%$, $\sigma = 9\%$; and cut-off $\pm 10\%$, $\sigma = 1.8\%$. The resulting power losses are indicated in Fig. 9 and 10. The results show that the output power is depressed under no-failure conditions but the loss is not as large under failure conditions as in the uniform model case; the effect is actually quite small. The significance of this finding is that parameter distribution does not strongly affect the array output.

LOADING EFFECT

When a failure occurs, the effective source impedance of an array changes. This means that the load resistance for maximum power output will change. The loading effect was calculated for the 10×3 three-dimensional array and the results are shown in Fig. 11.

It can be seen from these results that a converter failure short circuit shifts the optimum load resistor to a smaller value, and vice versa. The increase in array power output is only 0.1% , so that load matching under failure conditions does not increase array power output significantly or, conversely, the loss in power output due to not matching the load is not great.

Another result of this small loading effect is that when small arrays are assembled into larger ones, the effect on one array of a failure in a neighboring array will be small.

CONCLUSIONS

The results of this study indicate that the power output of a converter array is insensitive to parameters such as array topology, distributed parameter values, and interconnection resistance as a function of position. Enhancement of system reliability has been shown to be possible.

It is not clear at this time whether the complication of the array proposed to eliminate the effects of the nonlinearity of real thermionic converters will be necessary, since the constant emitter temperature load lines of existing converters do not show gross nonlinearity.

Further work could profitably be done on the analysis of interconnectors of small arrays, the effects of real converters, and the solution of more complicated topologies in small arrays.

APPENDIX I

DETERMINATION OF ARRAY CHARACTERISTICS

The output of an array model is calculated directly by solving the current loop equations of the network. This calculation is repeated for a range of values of the interconnection resistance and for both open and short-circuit failures of individual elements. The average power output is calculated for single failures located at each position in the array for both short and open-circuit failures. The average power output results are plotted versus interconnection resistance. The intersection of the two curves represents the maximum power output, into the same load, obtainable if open and short-circuit failures are equally likely. If the probability of open and short-circuit failures are not equally likely, the curve must be weighted by the relative probabilities to obtain the maximum expected value of output under failure conditions and the appropriate value of interconnection resistance. In this study only the 50-50% probability case was evaluated. The weighting technique is:

$O(r)$ = Average output power with open failure as a function of interconnection resistance.

$S(r)$ = Average output power with short failure as a function of interconnection resistance.

P_o = Probability of open failure (relative).

P_s = Probability of short failure (relative).

$$P_o O(r) + P_s S(r) = \text{MAX} \quad (1)$$

$$P_o \frac{dO(r)}{dr} + P_s \frac{dS(r)}{dr} = 0 \quad (2)$$

Solve for "r," the optimum interconnection resistance value. Inserting this value of r into Eq. (1) yields the expected power output. This technique assumes that failure probability is independent of position in the array.

This series of calculations was performed to determine the effect of array shape on power output and interconnection resistance. Fig. 12 shows the results for planar arrays of dimension 10×3 to 2×3 , respectively.

The result of monitoring the current redistribution under failure conditions indicated that failures near the edges were more detrimental. Thus, a series of calculations was performed on three-dimensional arrays which eliminate parallel edge effects. The results of these calculations are shown in Fig. 13 for 10×3 to 2×3 arrays, respectively.

APPENDIX II
RELIABILITY CALCULATIONS

The binomial expansion will describe the probability of occurrence of "r" or less failures among "n" components if the probability of individual component failures is "p".

$$P(r, n) = \sum_{i=0}^{i=r} {}^nC_i P^i (1-p)^{n-i} \quad (\text{where } {}^nC_i = \text{combinations of } n \text{ things taken } i \text{ at a time})$$

The numbers for Table I in the text were calculated from this equation. The value of "n" was 30 converters; the value of "n" is in the table. The value of (1-p) is mentioned as 0.950 and 0.990.

REFERENCE

¹J. W. Holland, "Thermionic Reactor Network Reliability," ENEA-IEE
Conf. on Thermionic Electrical Power Generation, London, England,
Sept. 1965.

TABLE I. Results of multiple failure analysis.

<u>No. Failures</u>	<u>% Output Power</u>	<u>System Reliability</u>	
		<u>0.950</u> <u>Converter</u>	<u>0.990</u> <u>Converter</u>
0	100	0.34	0.74
1	93	0.55	0.96
2	86	0.81	0.997
3	79	0.93	0.9999
4	72	0.98	
5	67	0.994	

FIGURE CAPTIONS

- Fig. 1. A Six-in-Series, Three-in-Parallel Planar Array
- Fig. 2. Percent Power Lost vs Array Shape (Planar) Optimized for One Failure (100% Equals Power-Generating Capability of One Converter)
- Fig. 3. Interconnection Resistance vs Array Shape (Planar) Optimized for One Failure, Open or Short
- Fig. 4a. A Six-in Series, Three-in-Parallel, Three-Dimensional Array
- Fig. 4b. A Two-in-Series, Five-in-Parallel, Three-Dimensional Array
- Fig. 5. The Ten-in-Series, Three-in-Parallel, Planar Array Current Redistribution Results
- Fig. 6. The Ten-in-Series, Three-in-Parallel, Three-Dimensional Array Current Redistribution Results
- Fig. 7. The Two-in-Series, Five-in-Parallel, Three-Dimensional Array Current Redistribution Results
- Fig. 8. Power Output vs Interconnection Resistance for two Failures as Indicated for Ten-in-Series, Three-in-Parallel Planar Array
- Fig. 9. Power Lost vs Interconnection Resistance for Ten-in-Series, Three-in-Parallel, Three-Dimensional Array. Parameter Distribution $\pm 50\%$ cut-off, $\pm 9\%$ standard deviation
- Fig. 10. Power Lost vs Interconnection Resistance for Ten-in-Series, Three-in-Parallel, Three-Dimensional Array. Parameter Distribution $\pm 10\%$ cut-off, $\pm 1.8\%$ standard deviation.
- Fig. 11. Power Output vs Load Resistance for Ten-in-Series, Three-in-Parallel, Three-Dimensional Array for One Failure as Indicated

Fig.12. Power Output vs Interconnection Resistance for One Failure as Indicated, Planar Array

A	10×3	F	5×3
B	9×3	G	4×3
C	8×3	H	3×3
D	7×3	I	2×3
E	6×3		

Fig.13. Power Output vs Interconnection Resistance for One Failure as Indicated, Three-Dimensional Array

A	10×3	F	5×3
B	9×3	G	4×3
C	8×3	H	3×3
D	7×3	I	2×3
E	6×3

INTERCONNECTION RESISTANCE
THERMIONIC CONVERTER

Long - Fig. 2

MEAN-RESISTANCE-TO-CONNECTION

Long - Fig. 3.

LEGEND	
SYMBOL	DESCRIPTION
CONVERTER
BUS CONNECTION
RESISTIVE INTERCONNECTION

Long - Fig. 4a

LEGEND	
SYMBOL	DESCRIPTION
	CONVERTER
	BUS CONNECTION
	RESISTIVE INTERCONNECTION

Long - Fig. 4b

Long - Fig. 5

Long - Fig. 6

Long - Fig. 7

Long - Fig. 8

Long - Fig. 9

Long - Fig. 10

Long - Fig. 11

VERTICAL NO'S = POWER OUTPUT (WATTS)
 HORIZONTAL NO'S = INTERCONNECTION RESISTANCE (Ω)

|| ○ = OPEN FAILURE
 || + = SHORT FAILURE

VERTICAL NO'S = POWER OUTPUT (WATTS)

HORIZONTAL NO'S = INTERCONNECTION RESISTANCE (Ω)

|| ○ = OPEN FAILURE
|| + = SHORT FAILURE

DISTRIBUTION

LRL Internal Distribution

Michael M. May

J. R. Freeman

2

H. McDonald

E. La Franchi

J. Long

6

R. K. Wakerling, Berkeley

TID File

30

External Distribution

Division of Technical Information Extension, Oak Ridge

LEGAL NOTICE

This report was prepared in the course of Government sponsored work. Neither the United States, nor the Commission, nor any person acting on behalf of the Commission

A. Make any warranty or representation, expressed or implied, with respect to the accuracy, completeness, or usefulness of the information contained in this report, or that the use of any information, apparatus, method, or process disclosed in this report, may not infringe privately owned rights, or

B. Assume any liability with respect to the use of, or for damages resulting from the use of, any information, apparatus, method or process disclosed in this report.

As used in the above "person acting on behalf of the Commission" includes any employee or contractor of the Commission, or employee of such contractor, to the extent that such employee or contractor of the Commission or employee of such contractor prepares, disseminates, or provides access to any information pursuant to his employment or contract with the Commission or his employment with such contractor.

VM:dh