A COMPACT PROGRAMMABLE CONTROL PANEL

for

COMPUTER CONTROL SYSTEMS*

by

B. L. Hartway

Los Alamos Scientific Laboratory
University of California
Los Alamos, New Mexico 87544

CONF-730310--23

SUMMARY

The Card Programmable Function Button Panel is basically a manual data entry device used for computer program assignment and binary control. However, it has the ability to be reassigned in over one thousand different configurations by changing a computer-read program card which also provides labeling of the panel's control buttons and indicator lights. The multiple assignment capability is accomplished by an optically-read ten-bit binary code on the program card. The panel is packaged in a 3-wide 8 3/4 inch high AEC Standard Nuclear Instrument Module (NIM). The front panel contains 30 control-button/indicator-light pairs which are labeled by the dollar-bill-sized program cards. The cards are made of a thin white plastic with a special writing surface. The recessed indicator-light matrix thus provides separate backlighting through each of the button-adjacent printed partitions of the over-laying program cards. Binary code bit-locations are printed across the bottom edge of the card, and the cards are encoded by punching out the appropriate code using a standard hand punch. The panel contains all the electronics necessary for lamp drivers, lamp test, lamp dimmers, as well as the logic for the registration, validation, reading, and transmission of the card's binary code to the computer. Separate electronics provides for button-switch debouncing, encoding, key-roll-over protection, and indicator-status memory. Electronic and mechanical construction details are reviewed as well as a brief description of the panel's use on the operator's control consoles at the Clinton P. Anderson Meson Physics Facility of the Los Alamos Scientific Laboratory (herein referred to as LAMPF).

INTRODUCTION

For even the simplest of computer control systems there exists a need for a number of dedicated control buttons with corresponding indicator lights to control and monitor vital process and data. On larger computer control systems with various interactive CRT terminals additional function buttons and status indicators are needed for fingertip command/readout of routinely used programs and parameters that might otherwise occupy valuable space on the working CRT displays. Visualize a computer control console operator deeply involved in an interactive data/graphic display, and suddenly needing another simple but undisplayed control program or routine without interrupting his present display. In such an instance it is convenient to have an auxiliary hardware panel nearby with such routine programs available. Ideally, this control panel would be configured to suit the immediate task at hand. Unfortunately, once begun,

dedicated function panels tend to grow without limit, especially if different operators utilize the console for different routines or systems and, therefore, prefer their own special arrangements. The solution, of course, is to have a small bank of function buttons and status indicators which can be almost instantly configured for different requirements as they occur, without going through additional programming assignments. Ideally, the operator produces his favorite configuration from his own shirt pocket, places it over a blank control panel, and that panel becomes the configuration of the card automatically. Such a system has not only been devised, but there are three such devices on each of the two identical control consoles in the Central Control Room (CCR) at LAMPF.⁽¹⁾ These Card Programmable Function Button Panels have now been in operation for over a year, and are considered to be highly effective in solving the problem of multiple-configured computer control consoles.

Figure 1. The Card Programmable Function Button Panel is shown with a Program Card being inserted into the panel's card reader slot. The computer-read binary code can be easily seen across the bottom edges of the Program Cards laying on the table. The cards are easily labeled with pencil or ink, and the binary codes are punched with a hand punch. When a Program Card is in use, the indicator matrix backlights the separate partitions of the card with one color for "OFF" and a different color for "ON".

MASTER

*Work performed under the auspices of the United States Atomic Energy Commission.

USE AT LAMPF

Assume that you are one of many among a large group of variously disciplined scientific staff, having access to the control consoles of a large and complex computer controlled particle accelerator.* The two identical control consoles in the Central Control Room are equipped with various scopes, knobs, indicators, readouts, buttons, and a keyboard. Accelerator beam time is tremendously valuable, your allotted time at the console is limited. Time is of the essence, so you want to take the fullest advantage of a pre-organized experimental routine. Since the control console devices are assigned through program control, they carry only arbitrary reference labels such as knob 1, Readout 5, button 16, storage scope 2, etc. You will want different combinations of these controls in various configurations at different times in your routine to be of most efficient use to you. Although the all powerful interactive-graphics and character scopes could be used to display your program formats, you prefer to dedicate these devices to analytical displays of the experiment as it progresses.

You remove a Program Card from your shirt pocket and insert it in a slot in one of three available Card Programmable Function Button Panels. The panel's indicator matrix turns on, providing background illumination for your labels beside each button. This card will be used for overall program control and status monitoring. You remove two more cards and insert them in the remaining two panels, providing you with your remaining sets of programs, control algorithms, and display configurations necessary for an organized computer interactive system. You now concentrate on your scientific investigation without needless distractions such as tedious keyboard entries and corresponding references to the program directories.

Figure 2. One of the two identical CCR Control Consoles, showing the location of the three Card Programmable Function Button Panels. The long panel in the Console's center section is identical to the panels described in this paper, except for its physical size. The larger panel is intended as an aid in segregating programs and routines used for accelerator operations from those used for research and development.

Figure 3. Card Programmable Function Button Panel being used for control of the accelerator's Cockcroft-Walton Injector System; in this instance making use of program assignment to adjacent knobs and readouts.

CALCULATOR		GENERAL STATUS		INTECTOR CONTROLS		ΔT (MINUTES)	
CLEAR	0	CALCULATED	HANDLED	DATA MODE	ARMED STATUS	DEMAND	
2 nd	1	NO SOURCE	VIDEO	TEST MODE	ARM CODE	INPUT	
4 th	1	TA PD	ARC DOWN	SEARM	NO FMS	360 DE	
5 th	2	SECTION A	JUST DOWN	CN KUNUP	EXTRACTOR	DE BRAND	
6 th	3	POSITION	NO RESIDUE	FL DOWN	REC MIGHT	PROF 30.5	
10 th	4	SECTION 2	CONTROL	EA LOG	MC PLICK	120-80 BRN	
Log 3	5	SECTION C	CONTROL	TRD LOS	ARC DEMAND	INCHABLE P	
1 ENL 6	6	SECTION D	TWEN	TRD SIGHT	FLIGHT	80.8 W	
ENTER	7	SECTION E	SEAM PLAY	TRD WAD	NO FMS	SUMMARY	
=	8	SECTION F	DOWN	TRD STOP	FINCH EAS	100 (100)	W SCAR
+	9	SECTION G	DOWN	OUTSIDE		ACTUP (20)	
X	0/0	SECTION H	DOWN	CAN PRO		(100) (100)	
÷	10					SEAM LENGTH	ARMED 5
Change Exp	ENTER Exp	DATE 65				YEAR	
1 st CHAN 7		CLEAR 65		REL 10 ARMED	CLEAR ARMED	YEAR 10	
2 nd CHAN 8							
3 rd CHAN 9							
4 th CHAN 10							
5 th CHAN 11							
6 th CHAN 12							
7 th CHAN 13							
8 th CHAN 14							
9 th CHAN 15							
10 th CHAN 16							
11 th CHAN 17							
12 th CHAN 18							
13 th CHAN 19							
14 th CHAN 20							
15 th CHAN 21							
16 th CHAN 22							
17 th CHAN 23							
18 th CHAN 24							
19 th CHAN 25							
20 th CHAN 26							
21 st CHAN 27							
22 nd CHAN 28							
23 rd CHAN 29							
24 th CHAN 30							
25 th CHAN 31							
26 th CHAN 32							
27 th CHAN 33							
28 th CHAN 34							
29 th CHAN 35							
30 th CHAN 36							
31 st CHAN 37							
32 nd CHAN 38							
33 rd CHAN 39							
34 th CHAN 40							
35 th CHAN 41							
36 th CHAN 42							
37 th CHAN 43							
38 th CHAN 44							
39 th CHAN 45							
40 th CHAN 46							
41 st CHAN 47							
42 nd CHAN 48							
43 rd CHAN 49							
44 th CHAN 50							
45 th CHAN 51							
46 th CHAN 52							
47 th CHAN 53							
48 th CHAN 54							
49 th CHAN 55							
50 th CHAN 56							
51 st CHAN 57							
52 nd CHAN 58							
53 rd CHAN 59							
54 th CHAN 60							
55 th CHAN 61							
56 th CHAN 62							
57 th CHAN 63							
58 th CHAN 64							
59 th CHAN 65							
60 th CHAN 66							
61 st CHAN 67							
62 nd CHAN 68							
63 rd CHAN 69							
64 th CHAN 70							
65 th CHAN 71							
66 th CHAN 72							
67 th CHAN 73							
68 th CHAN 74							
69 th CHAN 75							
70 th CHAN 76							
71 st CHAN 77							
72 nd CHAN 78							
73 rd CHAN 79							
74 th CHAN 80							
75 th CHAN 81							
76 th CHAN 82							
77 th CHAN 83							
78 th CHAN 84							
79 th CHAN 85							
80 th CHAN 86							
81 st CHAN 87							
82 nd CHAN 88							
83 rd CHAN 89							
84 th CHAN 90							
85 th CHAN 91							
86 th CHAN 92							
87 th CHAN 93							
88 th CHAN 94							
89 th CHAN 95							
90 th CHAN 96							
91 st CHAN 97							
92 nd CHAN 98							
93 rd CHAN 99							
94 th CHAN 100							
95 th CHAN 101							
96 th CHAN 102							
97 th CHAN 103							
98 th CHAN 104							
99 th CHAN 105							
100 th CHAN 106							
101 st CHAN 107							
102 nd CHAN 108							
103 rd CHAN 109							
104 th CHAN 110							
105 th CHAN 111							
106 th CHAN 112							
107 th CHAN 113							
108 th CHAN 114							
109 th CHAN 115							
110 th CHAN 116							
111 st CHAN 117							
112 nd CHAN 118							
113 rd CHAN 119							
114 th CHAN 120							
115 th CHAN 121							
116 th CHAN 122							
117 th CHAN 123							
118 th CHAN 124							
119 th CHAN 125							
120 th CHAN 126							
121 st CHAN 127							
122 nd CHAN 128							
123 rd CHAN 129							
124 th CHAN 130							
125 th CHAN 131							
126 th CHAN 132							
127 th CHAN 133							
128 th CHAN 134							
129 th CHAN 135							
130 th CHAN 136							
131 st CHAN 137							
132 nd CHAN 138							
133 rd CHAN 139							
134 th CHAN 140							
135 th CHAN 141							
136 th CHAN 142							
137 th CHAN 143							
138 th CHAN 144							
139 th CHAN 145							
140 th CHAN 146							
141 st CHAN 147							
142 nd CHAN 148							
143 rd CHAN 149							
144 th CHAN 150							
145 th CHAN 151							
146 th CHAN 152							
147 th CHAN 153							
148 th CHAN 154							
149 th CHAN 155							
150 th CHAN 156							
151 st CHAN 157							
152 nd CHAN 158							
153 rd CHAN 159							
154 th CHAN 160							
155 th CHAN 161							
156 th CHAN 162							
157 th CHAN 163							
158 th CHAN 164							
159 th CHAN 165							
160 th CHAN 166							
161 st CHAN 167							
162 nd CHAN 168							
163 rd CHAN 169							
164 th CHAN 170							
165 th CHAN 171							
166 th CHAN 172							
167 th CHAN 173							
168 th CHAN 174							
169 th CHAN 175							
170 th CHAN 176							
171 st CHAN 177							
172 nd CHAN 178							
173 rd CHAN 179							
174 th CHAN 180							
175 th CHAN 181							
176 th CHAN 182							
177 th CHAN 183							
178 th CHAN 184							
179 th CHAN 185							
180 th CHAN 186							
181 st CHAN 187							
182 nd CHAN 188							
183 rd CHAN 189							
184 th CHAN 190							
185 th CHAN 191							
186 th CHAN 192							
187 th CHAN 193							
188 th CHAN 194							
189 th CHAN 195							
190 th CHAN 196							
191 st CHAN 197							
192 nd CHAN 198							
193 rd CHAN 199							
194 th CHAN 200							
195 th CHAN 201							
196 th CHAN 202							
197 th CHAN 203							
198 th CHAN 204							
199 th CHAN 205							
200 th CHAN 206							
201 st CHAN 207							
202 nd CHAN 208							
203 rd CHAN 209							
204 th CHAN 210							
205 th CHAN 211							
206 th CHAN 212							
207 th CHAN 213							
208 th CHAN 214							
209 th CHAN 215							
210 th CHAN 216							
211 st CHAN 217							
212 nd CHAN 218							
213 rd CHAN 219							
214 th CHAN 220							
215 th CHAN 221							
216 th CHAN 222							
217 th CHAN 223							
218 th CHAN 224							
219 th CHAN 225							
220 th CHAN 226							
221 st							

Figure 4A. Typical Program Cards

1. Calculator card makes panel into a calculator.
2. General Status card used for accelerator status monitoring.
3. Injector Controls card (shown in use in Figure 3).
4. AT card used for accelerator control when making critical diagnosis and alignment of proton's time-of-flight.

Figure 4B. Preparation of Program Cards.

*The author refers to the LAMPF Accelerator -- an 800 MeV linear proton accelerator built for the USAEC by the Los Alamos Scientific Laboratory of the University of California. It is located in Los Alamos, New Mexico, and achieved its designed full energy potential of 800 MeV in June of 1972.

MASTER

DESIGN OBJECTIVES

The concept of a programmable control panel is certainly not new, but it was decided early in the LAMPF project that we needed to find such a device which would specifically fulfill the following requirements:

- Panel to be low cost, easy to fabricate, simple to use, easy to maintain.
- Programmable overlays easy to make, handle, reasonable size of matrix yet not unwieldy, not restrained to fixtures or holders when not in use, yet easy to install without misalignment problems in any of several locations.
- Software support to be powerful yet flexible.
- Easy to implement by non-programmer-type users.
- Electronics to provide feedback signals adequate enough to instill confidence in users.

The end result was to be that a user could layout a custom panel configuration with his own particular control algorithms, being efficiently suited to his control requirements. Ideally, this configuration would be on a relatively small card that he could label himself and carry from one location to another to be put into service at the most suitable location. Such a system was to be equally useful for experiments, development, operations, and maintenance.

The extent to which these design objectives have been met by the LAMPF Card Programmable Function Button Panel are discussed in the following sections.

PROGRAM CARD DESIGN

The design and physical realization of the program card is critical to the success of any card programmable control panel. Therefore, with the above design objectives in mind, the program cards for the LAMPF Card Programmable Function Button Panel have been designed with the following features:

- Pocket size (2 1/2" x 7") with thirty locations (2 x 15 matrix).
- Material is a commercial drafting material . . . pliable, 0.008" thick translucent-white polyester, with matte drawing surface for ease of writing and erasing with pencil or ink - yet can be made permanent by acrylic plastic spray. The polyester material is resistant to curl and shrinkage due to heat or humidity, and can be used in office copiers for making duplicate cards or copying specific cards for records and documents or multiple use.
- Card's indicator matrix area is preprinted with numbered partitions and there are spaces for a card title and originator's name. The card material provides excellent legend contrast and allows even, backlighted illumination.
- Card is square, with no special shapes or cutouts necessary -- easily handmade if desired, economically printed. The ten-bit binary code and four-bit registration/validation code locations are printed across the bottom edge of the card, and any desired code is easily hand-punched.

MECHANICAL DESIGN

General Packaging

The panel's reader assembly, card guide, indicator matrix, function buttons, and status lights are all contained in a front sub-panel and bezel, which are carefully machined to provide accurate and stable alignment. The electronics is contained on four printed circuit cards mounted in a card cage inside the module. The rear panel provides space for all power and input/output connectors, and also the lamp brightness controls.

All components, except the machined front bezel, are off-the-shelf commercial items, and packaging

consists of mounting these items inside a standard 8 3/4" high, 3-wide, Nuclear Instruments Module (NIM).

Reader Sub-Assembly

The program card reader assembly consists of standard, commercial, paper-tape (0.1" between hole spacing) source/sensor pairs; mounted in a carefully machined mounting plate type sub-assembly, as shown in Figure 5. Each source/sensor component contains nine bit-locations and two are used side-by-side, giving a total usable capacity of eighteen bits (only fourteen bits are presently used in the LAMPF units). The two halves of the sub-assembly are accurately aligned by virtue of match-machined parts, so that the entire reader sub-assembly can be moved about within the panel as required for alignment with the program card's slot. This arrangement allows rapid and reliable alignment of the panel's card reading system.

Figure 5. Detail, Sub-Assembly

Indicator Matrix

The indicator matrix is a self-contained assembly, complete with lamps and filters. Each partition contains two aircraft-style (T-1 3/4) lamps, and the lamps and associated filters can be changed from the front without special tools.

Front Sub-Panel & Bezel

The front bezel is machined from 1/4" thick aluminum, and given a clear anodize finish. The indicator matrix is recessed 1/8" in a machined slot in this bezel, which thus provides an accurate program card alignment guide and holder, requiring no further guides, clamps, or covers to maintain the cards in their proper position.

An uncluttered and streamlined appearance for the front bezel is accomplished by mounting all the front panel components on a sub-panel behind the bezel, and the bezel and reader cover being fastened with blind screws into the rear of the bezel.

ELECTRONICS DESIGN

General

A simplified schematic for the electronics contained in the panel is given in Figure 6. This electronics is contained on printed circuit cards as outlined below. (The pushbutton switch debouncing and encoding circuits, and the addressable memory for the indicators were not included in the panel since they already existed elsewhere in the system. By slight repackaging, however, these circuits could easily be incorporated into the panel.)

Reader Logic Card

The program cards are read by the solid-state source/sensor array, and the resultant logic states are deciphered by the reader logic card as one of two possible conditions: 1) a registered and valid card has been inserted, or 2) a card has been withdrawn. The card's registration and validation information is contained in the card bits A, B, C, D, while the ten-bit binary card number is contained in the card bits 0 through 9. The logic shown will respond only to a card which has the code $\bar{A}B\bar{C}D$ as a valid card. Card registration is automatically checked by the proper sensing of the bits $\bar{A}B$ and $\bar{C}D$, since they are at opposite sides of the card, and any crookedness would result in a loss of validation codes. Thus, a reversed or crooked card will not initiate any action. When a VALID CARD IN condition first occurs, a 1/2 second delay is initiated to allow for the card to settle in the slot. If the VALID CARD IN condition still exists after this delay, the computer is interrupted with a command to enable the panel for the program card

number as given by the ten card bits 0 through 9. When a card is removed, the logic senses the code $\bar{A}B\bar{C}D$ as a CARD OUT condition, waits 1/2 second, and interrupts the computer with a command to disable the card program previously assigned to that panel. Note that without the delay feature it would be possible to send erroneous interrupt signals to the computer as the bottom edge of the card crossed the sensors. Also, since the sensors are capable of high-frequency oscillation under certain conditions, Schmitt buffers have been added to each sensor's output.

Lamp Controller Card

The Lamp Controller Card contains separate voltage regulators for the ON and OFF lamps to facilitate color brightness balancing as required by various room lighting conditions. Both regulators are controlled by logic, which turns off all lamps when a card is out or when the computer program is not ready, and blinks all lamps and activates a "clacker" when the computer executes the called program. (The clacker is in actuality a large relay mounted on the inside of the module, its only purpose being to produce an audible feedback signal.)

Lamp Driver Cards (2 Required)

The Lamp Driver Cards receive lamp status commands from the computer, via an external addressable memory, and turn on the correct lamps using complimentary transistor drivers. These cards also incorporate a lamp test feature (the test button is located under the top edge of the program card).

Figure 6. Card-Programmable Function Button Panel - Simplified Schematic Diagram.

Figure 7. Hardware and Software Flowcharts for Card-Programmable Function Button Panel.

SOFTWARE DESIGN

The software routine used at LAMPF was developed over a period of time, taking good advantage of user feedback. Efforts were made to keep the system sub-routines for program card definition and status lamp operations as straightforward as possible. The resultant software routine, along with hardware logic, is shown in Figure 7.

To use a program card the user punches three IBM cards to identify the program card number and the program-calls desired for each of the thirty function buttons. This set of definitions is called a card table. If he wants to use the indicators beside the buttons, he defines their operation through the use of a FORTRAN subroutine called LIGHT. Only two indications are presently used at LAMPF, yellow for OFF and green for ON.

Various forms of software-controlled feedback have been incorporated into the use of the panel in the form of status lights and operator messages. By the use of program reservations, sufficient software control has been added, so that a user will not accidentally intrude upon another user's routines. All programs are written in terms of servicing a particular program card number rather than a physical card location. This allows the card's program to be basically independent of various panel locations. However, a card program can be related to physical location (such as knobs, buttons, scopes, etc.) if desired, since the panel's location is given to the computer at the same time the program card number is entered.

Although program card validation is accomplished by the panel's electronics, it could be just as easily done by the software of the system in the form of

additional hardware of software reservations or conditions. Note that Figure 7 makes no mention of action when a card is removed, since this action is merely the reverse of the sequence shown (e.g. clearing reservations instead of making them, turning lights off instead of on, etc.)

CONCLUDING REMARKS

It is becoming increasingly common for apparatus of science to be embraced by the control of a computer. Each new device presents it's own set of algorithms, which requires control and status monitor panels unique to that device. Obviously, interactive computer graphics systems provide an ideal solution in such situations, but equally versatile hardware is found to be lacking. The author feels that the Card Programmable Function Button Panel described in this paper should make a significant step towards reducing this man-machine interface gap.

ACKNOWLEDGMENTS

The author would like to thank the following people for their valuable assistance and suggestions: Don Swanson, Dick Thomas, Cliff Flopper, Sally Shlaer, and Herman Vigil.

REFERENCES

1. B. L. Hartway, C. M. Flopper, J. Bergstein, "The Central Control Room Man-Machine Interface at the Clinton P. Anderson Meson Physics (LAMPF) Facility," 1973 Particle Accelerator Conference, San Francisco, March 5-7, 1973.