David S. Gilmer
Ecology & Behavioral Biology
University of Minnesota
Minneapolis, Minnesota 55455

MASTER

A DEVICE FOR MONITORING PRESENCE AND ACTIVITY OF RADIO-MARKED ANIMALS

David S. Gilmer, James Ford Bell Museum of Natural History,
University of Minnesota, Minneapolis

V. B. Kuechle, James Ford Bell Museum of Natural History,
University of Minnesota, Minneapolis

I. Joseph Ball, Jr., James Ford Bell Museum of Natural History,
University of Minnesota, Minneapolis.

Abstract: A simple, portable, and economical recording system consisting of a receiver, signal conditioner, recorder, and power source is described. The system was designed to monitor the signal strength from a radio-marked animal at a particular location. Information is stored on recorder chart paper. Radio-marked ducks have been successfully monitored at nest sites, potholes, and other locations.

Use of radiotelemetry as a technique to study wild animals has developed rapidly within the last 10 years. Because most field telemetry projects are not designed to obtain data on a continuous basis as described by Cochran et al. (1965) and Cochran (1967), a large proportion of the available information is not collected. This recording system was developed to monitor radio-marked animals at particular locations in field studies where ruggedness, portability and cost were of primary concern. Williams and Williams (1970) briefly describe a recording

This report was prepared as an account of work sponsored by the United States Government. Neither the United States nor the United States Atomic Energy Commission, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness or usefulness of any information, apparatus, product or process disclosed, or represents that its use would not infringe privately owned rights.

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency Thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

system for monitoring the presence and relative activity of radio-marked bats. A recording device for monitoring the presence of radio-marked seals on the surface of sea ice was mentioned by Siniff et al. (1969).

Funds for development of the system were provided by the Northern Prairie Wildlife Research Center, Jamestown, North Dakota; by NIH Training Grant No. 5 T01 GM01779-04 from the National Institute of General Medical Sciences; and by the U.S. Atomic Energy Commission, COO-1332-63.

We acknowledge J. R. Tester, L. M. Cowardin, and H. W. Miller for reviewing the manuscript and R. A. Reichle for preparing the drawings.

MATERIALS AND METHODS

The recording system, block diagrammed in Fig. 1, consists of a receiver, signal conditioner, recorder, and power source. The receiver produces an audio output from an incoming signal. A signal conditioner converts the receiver output into a d-c current which activates the recorder stylus. Stylus movement is recorded on pressure sensitive paper of a single channel d-c recorder (Model No. 288, recorder paper Style A, Rustrak Instrument Div., Gulton Industries Inc., Manchester, New Hampshire).

The receiver is tuned aurally by using headphones to select the desired frequency and by observing the recorder to obtain desired stylus deflections. Range of the system can be varied by adjusting the rf gain of the receiver or antenna gain.

Selection of the type of antenna will depend on the relative positions of the antenna and the animal to be monitored. If the antenna can be placed near the center of the area to be monitored, a nondirectional antenna is the best choice. When the antenna must be placed away from the animal, a directional antenna should be used.

The receiver, signal conditioner, and recorder are powered by a single 12-volt source. A freshly-charged, 60 ampere-hour automotive storage battery will operate the system for approximately 3 weeks. Two 6-volt lantern batteries (connected in series) will last for approximately 72 hours. The system, including the two 6-volt dry cell batteries and a weatherproof marine-plywood box, weighs approximately 20 pounds.

A signal conditioner is not available from commercial sources; however, it can be constructed from the schematic diagram (Fig. 2). Component values and lay-out are not critical. The transistor acts as a switch allowing a variable amount of current to flow through the meter depending on signal amplitude and pulse width if the signal is pulsing. Almost any audio NPN transistor will work. Resistor R_1 serves to limit the maximum current through the recorder meter. It can be chosen using the relationship $R_1 = \frac{V_s}{I_{max}} - \frac{R_m}{m}$, where V_s is the supply voltage; I_{max} , the full scale meter reading, and $\frac{R_m}{m}$ the meter resistance (which can be neglected if the full scale reading is 500 microamperes or more). Capacitor C prevents the stylus from fluttering when a signal from a pulsing transmitter is

being recorded. Resistor R_2 isolates the headset so that it can be inserted and removed without affecting the meter reading. The 27K-ohm resistor is suitable for 2000-ohm headsets; its value should be increased if the meter level is affected by the headset and reduced if the audio level in the headset is insufficient. Any receiver having sufficient audio output to drive a headset is satisfactory, otherwise an additional stage of audio gain should be used. The receiver should have sufficient bandwidth so that minor shifts in the receiver or transmitter frequency will not have significant effect on the chart record.

Recorders are available with different meter movements and drive motors. Interchangeable gear train assemblies permit a wide range of chart speeds. We regarded a 0- to 1-ma movement and an unregulated drive motor to be the best choice considering cost and versatility. Other movements will work providing R_1 is changed accordingly. Chart speed for an unregulated motor was accurate to within ± 3 minutes per hour as long as battery voltage was maintained above 11.5 volts. Improved speed regulation can be achieved by using a recorder with speed regulation or a voltage regulated power supply. Cost of the recorder with an unregulated motor is about \$140; cost with speed regulation is about \$210. Estimated cost for signal conditioner components is \$10.

This recording system has been used successfully during two field seasons where temperatures ranged from 29F to 86F. It was used primarily to record presence and activity of nesting mallards (Anas platyrhynchos) and wood ducks (Aix sponsa),

but was also used to monitor radio-marked ducks on small potholes and hens with broods. Once the specific area to be monitored (nest, pothole, river segment, or similar area) was determined, the recording system was positioned to permit periodic recorder maintenance without disturbing the animal. System checks were usually made daily to correct small time errors in the recorder, to retune the receiver if necessary, and to review the record of the monitored animal. Coaxial cable was used to connect the recording system and the antenna, which may be remote from the system. Good results were obtained using a small whip antenna positioned within several feet of a nest location. A directional loop antenna could be located as far as 30 yards from a nest and a Yagi antenna permitted monitoring an animal from several hundred yards.

An attempt was always made to position the antenna and adjust the receiver so that if the animal left a designated area the recorder would indicate a zero reading. Each recording situation will probably be slightly different and the system should be carefully installed and tested under conditions and ranges anticipated in the field. The investigator should be aware that discrepancies in the chart record might occur if the transmitting antenna produces a sharp null.

No major effort was made to distinguish graphic records produced by different types of activity such as feeding, preening, and courtship display. However, comparisons of graphic records and visual observations may indicate that certain types of activity exhibit distinct graphic records.

RESULTS

A 5-hour recording of activity of an incubating wood duck, equipped with a breast-mounted transmitter with body loop antenna is shown in Fig. 3. Time of arrival and departure at a nest cavity as well as various movements of the hen while in the cavity are indicated. Note that departure of the wood duck from the cavity is indicated at about 5:50 pm and its return at about 7:20 pm. The system was adjusted to indicate a zero reading when the bird left the general vicinity of the cavity. Several movements of the animal while in the nest cavity are indicated by minor stylus excursions. Two of these are noted in Fig. 3 at A and B.

Monitoring an animal with the recording system provided much useful information on the animal's activity schedule. Overall tracking efficiency was increased by knowing the approximate time an animal could be expected to depart a given location.

LITERATURE CITED

- Cochran, W. W. 1967. Radiolocation and tracking of animals - an inexpensive triangulation recorder. A.I.B.S. BioInstrumentation Advisory Council Info. Module M14. 31pp.
- Cochran, W. W., D. W. Warner, J. R. Tester, and V. B. Kuechle. 1965. Automatic radio-tracking system for monitoring animal movements. BioScience 15(2):98-100.
- Siniff, D. B., J. R. Tester and V. B. Kuechle. 1969. Population studies of Weddell seals at McMurdo Station. Antarctic Journal of the U. S. IV(4):120-121.
- Williams, T. C. and J. M. Williams. 1970. Radio tracking of homing and feeding flights of a neotropical bat, Phyllostomus hastatus. Anim. Behav. 18(2):302-309.

Fig. 1. Block diagram of a radio transmitter and the recorder system.

Fig. 2. Schematic diagram of the signal conditioner.

Fig. 3. Five-hour recording of the activity of an incubating wood duck hen on July 3, 1970. Examples of movements inside the cavity are indicated at A(3:00 pm) and B (3:40 pm).

Departure from the cavity is indicated at C (5:50 pm) and arrival at D (7:20 pm). The chart speed of this recorder was 1 inch per hour and the chart roll lasted 31.5 days.