FINAL REPORT
(Volume 2 - Appendixes)

LASER FUSION STUDY

June 1975

Prepared for:

University of California
Lawrence Livermore Laboratory
Livermore, California 94550

NOTICE
This report was prepared as an account of work sponsored by the United States Government. Neither the United States nor the United States Department of Energy, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product or process disclosed, or represents that its use would not infringe privately owned rights.

Electro-Optical and Data Systems Group
AEROSPACE GROUPS
Hughes Aircraft Company • Culver City, California

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

EB

TABLE OF CONTENTS

Appendix

A	Sensor Performance Calculation Techniques	A-1
B	Focus Sensing	B-1
C	Purchased Item Data	C-1
D	Pointing and Focusing Configuration Tradeoff Studies	D-1
E	False Start Centering Sensor	E-1
F	RCA Application Notes on Quad Detection	F-1
G	Elliptical Flex Pivot Analysis	G-1
H	Servo Mirrors Cross Coupling	H-1
I	Optical Misalignment Analysis	I-1
J	Stress Induced Birefrigent Quarter-Wave Retarder	J-1
K	Data Bulletin on Incramute Damping Alloy	K-1
L	The Utilization of Stepping Motors	L-1
M	Computer Program Listing for Stepper Motor Load Simulation	M-1

APPENDIX A
SENSOR PERFORMANCE CALCULATION TECHNIQUES

APPENDIX A. SENSOR PERFORMANCE CALCULATION TECHNIQUES

The general approach for sensor analysis is summarized in Table A-1. The basic sensor performance criteria are modulation index, MI, average signal level and sensitivity to aberrations. MI is the modulation of the carrier signal per unit of the variable. Average signal level is utilized with detector noise for the particular sensing technique to compute the S/N. The MI and S/N are utilized to calculate noise error as follows.

$$\text{rms noise error} = \frac{1}{\text{MI} \left(\frac{1}{\mu\text{m}} \right) \frac{S(\text{rms})}{N(\text{rms})}}$$

In two channel sensing techniques the MI and channel unbalance are used to compute the offset or drift error as follows:

$$\text{offset error} = \frac{\text{unbalance} (\%)}{\text{MI} (\%/\mu\text{m})}$$

Table A-1. Sensor performance analysis approach

- Criteria
 - Modulation index
 - Average signal level
 - Sensitivity to aberrations
- Theoretical derivation using gaussian aperture function and XN diffraction limited gaussian blur in focal plane
- Evaluation of sensors for ideal conditions
- Geometrical and diffraction analysis with computer
 - Parabolic apodization
 - Gaussian apodization (for comparison)
 - Aberrations
- Evaluation of sensors for susceptibility to various aberrations

The unbalance can occur in detectors, optical path transmission, or electronic gain. In this report, MI is always computed in units as seen at the target, i. e., $MI = 10\%/ \mu m$ means that for $1 \mu m$ error at the target, the carrier signal will be modulated by 10 percent at the detector. The third criterion, sensitivity to aberration, is somewhat less tangible since aberration is not specific. Aberrations tend to cause, first, a loss in MI due to increase in blur diameter in the focal plane and, second, an offset due to non-symmetry in both the transverse direction and the axial direction.

The basic sensing techniques were first analyzed and evaluated via theoretical derivations utilizing a Gaussian aperture function and a 2.5 times diffraction limited Gaussian spot in the focal plane. Gaussian functions were utilized in order to make the mathematics manageable. The value of the theoretical derivation is that by examining the equation an insight may be obtained as to what part the parameters play and where to start when optimizing. Subsequently the theoretically acceptable techniques were evaluated utilizing the geometrical and diffraction analysis data from the computer. The parabolic apodization computer data were compared with the theoretical Gaussian data for validity. Finally the sensors were examined for susceptibility to various aberrations. The results are discussed in detail in Volume 1, Section II of the report.

Modulation index is the rate of change of signal per unit of variable, normalized to the average power. This is given by:

$$MI = \frac{\partial P(x)}{\partial x} \frac{1}{P_{avg}}$$

where:

$P(x)$ = optical power into detector as a function of x

x = variable of interest

P_{avg} = average power

and:

$$P(x) = \int_x I(x) dx$$

Figure A-1 shows the derivation of MI for a single axis of a quad detector used in the conventional manner, and Figure A-2 shows the improvement that can be obtained putting a dead zone in between the elements. It should be noted that this increase in MI comes about because the average power, P_{avg} , diminishes faster than the rate of change in power, $\partial P / \partial x$, therefore there would be a loss in S/N that is greater than the loss in MI so that there would be a net increase in noise error. The purpose in increasing MI is to reduce the channel balance requirements in a situation where balance error is larger than noise error.

Figure A-3 shows the geometry of the energy balance technique for focus sensing with a definition of terms. Figure A-4 shows how the error modulation is generated and gives the equations.

Figure A-1. Modulation coefficient for Gaussian blur at detector.

Figure A-2. MI, blur not centered or detector masked.

Figure A-3. Geometry of Energy balance technique for focus sensing.

$$MI = \left. \frac{2 I(Z)}{2Z} \cdot \frac{1}{I(Z)} \right|_{Z=Z_0} = \left. \frac{2 Z_0 / \xi^2}{1 + (Z/\xi)^2} \right|_{Z_0 = \xi} = \left. \frac{1}{\xi} \right|_{\xi = 24 \mu M} = 4\% / \mu M$$

$$\text{WHERE: } \xi = \frac{2(f/NO.)^2 NA}{N} \left| \frac{f/2}{N=3} \right| = 24 \mu M$$

Figure A-4. Generation of modulation for focus sensing.

APPENDIX B
FOCUS SENSING

APPENDIX B

FOCUS SENSING

There are many methods of sensing focus, but the most precise methods utilize one basic concept: balancing the energy on either side of focus. The different ways in which this can be implemented are listed in Table B-1. First on the list is two separate detectors which is illustrative of the basic concept. Two detectors, identical in area and gain are located optically on either side of the desired location for focus. When the detectors are equally illuminated, then the geometrical focus is exactly centered. The weakness in this implementation is that the detectors must be matched* and aligned carefully, including the size and shape of the aperture in front of the detector and the beamsplitters between the detectors. The simplest way for getting around the matching is to utilize a single detector and either axially scan the detector or the focal plane. Scanning the focal plane is undesirable since this implies axially translating a lens without transverse motion. Scanning or dithering the detector requires axial motion without transverse motion of the detector, which again requires a complex mechanism. The easiest single detection implementation is to optically commute or switch the focal plane via a chopper. This is accomplished by combining two unequal optical paths with beamsplitter so that the result is two focal points separated by the desired amount, and locating the detector in the center. When the two paths are alternately chopped the detector is illuminated so that it effectively samples before and then after the focal plane. The detector output is an AC modulation proportional to the error. This process is described in Volume 1, Section 3 of this report. This focus sensor was judged the least complex and most accurate of all focusing techniques and so became the baseline design.

Number five, the astigmatic focus sensor, requires the introduction of astigmatism into the system and utilizes a quad detector. The quad is oriented at 45 degrees to the axes of astigmatism so that adjacent detectors

*As required by MI. See Appendix A.

Table B-1. Energy balance focus sensing

1. Two detectors on each side of focus
2. Single Detector, dither focusing lens
3. Single Detector, dither detector
4. Single Detector, optical commutation
5. Quad detector and astigmatism
6. Two detectors, dual Foucault chopper

see unequal illumination except when the system is focused so that the quad is directly centered between the sagittal and tangential foci. This is a form of energy balance in that sagittal focus is balanced against tangential. This implementation also requires that detectors, etc. be carefully balanced to obtain the required accuracy. This scheme has the advantage that the quad can be used for pointing also, so that alignment is insured and all energy used. All of the previously mentioned schemes have the same MI so the balance requirements are the same. The commuting technique can best meet balance requirements because the same detector and detector aperture are used. The optical path transmission must be matched, but the optical path is not likely to drift.

The following listed articles may be used for reference as examples of focus techniques currently in use. The device described by Simpson of NBS which is a two detector energy balance, obtains a precision of 10^{-2} μm with f/1 optics. This indicates the feasibility of the baseline system in which the channel balance problem has been improved considerably. Also, Simpson apparently has not optimized his device.

BIBLIOGRAPHY

1. J. A. Simpson, et al, Optical Engineering, 3, 95, (1973).
2. J. Simon, Applied Optics, 10, 2337 (1970).
3. J. Arol Simpson, , 1378
4. D. Rosenberger, Alta Frequenza, Vol. XLI, No. 10, 103E (1972).
5. R. A. Morgan, Product Engineering, April 11, 1966, 37.

APPENDIX C
PURCHASED ITEM DATA

PHOTODETECTORS

FULLY DEPLETED P-I-N SILICON QUADRANT PHOTODIODE

- HIGH QUANTUM EFFICIENCY AT 1.06 MICROMETERS
 (70%)
- FAST RESPONSE TIME
- LOW CAPACITANCE
- CUSTOM MADE TO CUSTOMER SPECIFICATIONS
- ZERO DEAD SPACE BETWEEN ELEMENTS

RCA silicon quadrant photodiodes incorporate all the features of fully depleted devices and have been optimized for use with lasers in the near infrared, particularly gallium arsenide (0.9 μm) and neodymium (1.06 μm). The fully depleted structure eliminates series resistance from the residual bulk material and the capacitance of the device is kept to a minimum. Antireflection coatings are applied to enhance the quantum efficiency for a given depletion layer width. Since the quantum efficiency in the near infrared, capacitance, and speed of response, are interdependent, a trade-off is necessary between these parameters; the TA8301 represents the best performance available for response times of approximately 10 nanoseconds, whereas the TA8302 offers improved quantum efficiency at 1.06 μm (in excess of 70%) with some sacrifice to speed. Sensitive areas up to 3 cm^2 are available and devices are encapsulated to meet individual requirements.

Information furnished by RCA is believed to be accurate and reliable. However, no responsibility is assumed by RCA for its use, nor for any infringements of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of RCA.

This document and the type of device is intended for engineering evaluation only. The design and data are subject to change. Unless otherwise indicated, no obligations are assumed for notice of change or for the continued manufacture of this device.

RCA

RCA LIMITED | Electronic Components
 Ste. Anne de Bellevue 810, Quebec | Canada
 Telephone: (514) 453-9000

$$1 \text{ cm}^2 = \pi r^2 \quad r = \frac{1}{\sqrt{\pi}} = .564 \text{ cm}$$

$$= 5.64 \text{ mm}$$

$$d = 11.28 \text{ mm} = .45''$$

TECHNICAL DATA (T = 300°K)

Parameter	Symbol	TA8301*	TA8302*	Units	Conditions
1 SENSITIVE AREA	A	1	1	cm ²	
2 OPERATING VOLTAGE (typical)	V	200	200	volts	
3 LEAKAGE CURRENT (typical)	I	3	3	microamperes	At 200 volts (See Fig. 2)
4 CAPACITANCE	C	30	20	picofarads	At 200 volts
QUANTUM EFFICIENCY	η	0.9 0.45	0.9 0.7	electrons/ incident photon	At 0.9 μm , 200 volts, 25Hz At 1.06 μm , 200 volts, 25Hz (See Fig. 1)
RESPONSIVITY	I_s/ϕ_s	0.65 0.38	0.65 0.6	amperes/ watt	At 0.9 μm , 200 volts, 25Hz At 1.06 μm , 200 volts, 25Hz
5 RESPONSE TIME	τ	10	25	nanoseconds	At 200 volts
6 CUT-OFF FREQUENCY	f_c	30	15	megahertz	3db point at 200 volts under short circuit conditions
QUADRANT TRANSITION		less than 0.010*			See Fig. 3
7 CROSSTALK		less than 3%/quadrant			10K load
UNIFORMITY		Better than 5%			

* (FORMERLY LDO SERIES)

NOTES:

- 1) Sensitive areas greater or less than 1cm² are available on request.
- 2) The operating voltage must be sufficient to fully deplete the device.
- 3) Guard rings may be used to minimize leakage current.
- 4) Capacitance is effectively independent of voltage under normal operating conditions.
- 5) The response time will be approximately equal to the electron transit time, which is a function of voltage, or the RC time, whichever is greater.
- 6) The frequency response of the diode will ultimately be limited by the charge collection time under short circuit conditions. This frequency will vary to some extent with the wavelength of the incident radiation. Further information can be obtained from our Applications Note no. 1 on photodiodes.
- 7) Crosstalk is defined as the output from adjacent quadrants when all the incident radiation is concentrated in one quadrant. It is given approximately by the ratio of the load resistance to the quadrant isolation resistance, which is typically greater than 1 Megohm.

FIGURE 1: SPECTRAL RESPONSE AT 300°K with antireflection coating for ≈ 1.0 micrometers (operating voltage 200 volts)

FIGURE 2: DARK CURRENT vs TEMPERATURE

FIGURE 3: QUADRANT TRANSITION

MECHANICAL COMPONENTS

M slo-syn[®] SERIES

RATINGS & SPECIFICATIONS[†]

MOTOR TYPE	2% ACCURACY	M081-FC08	M081-FC03	M081-FC05	M081-FC04	M081-FC09	M081-FC07	M081-FC06	M081-FC08	M081-FC09	M081-FC11	M081-FC14				
2% ACCURACY	10649-FC08	M081-FC03	M081-FC05	M081-FC04	M081-FC09	M081-FC07	M081-FC06	M081-FC08	M081-FC09	M081-FC11	M081-FC14	M111-FD12	M111-FD15	M112-FJ12	M112-FJ15	
STEP ANGLE	1.8°	1.8°	1.8°	1.8°	1.8°	1.8°	1.8°	1.8°	1.8°	1.8°	1.8°	1.8°	1.8°	1.8°	1.8°	1.8°
TOTAL STEPS PER REVOLUTION	200	200	200	200	200	200	200	200	200	280	200	200	200	200	200	200
TIME FOR SINGLE STEP 1 (0.4 sec.)	2.0	2.5	2.2	2.8	2.4	2.6	3.1	3.9	3.9	4.1	3.4	4.4	4.0	5.5	6.0	6.0
DC VOLTS	1.3	5.1	1.7	4.3	2.2	3.4	1.8	2.9	2.9	2.8	2.3	2.3	1.7	3.6	1.8	1.8
AMPS PER WINDING	3.9	2.0	4.3	1.8	4.6	2.3	4.8	3.05	4.6	5.5	7.0	6.1	8.0	6.1	12.7	12.7
RESISTANCE (OHMS PER WINDING 25°C)	0.33	5.1	0.37	2.6	0.48	1.16	0.39	0.55	0.55	0.52	0.31	0.37	0.21	0.60	0.14	0.14
INDUCTANCE (MILLI-REHS PER WINDING)	0.63	10.0	0.8	5.7	1.2	2.9	1.5	3.8	2.5	2.9	1.65	2.4	1.3	5.3	1.0	1.0
NOMINAL RATED TORQUE (OZ-IN)	35	35	65	65	100	100	110	110	200	300	300	425	425	640	840	840
HOLDING TORQUE* (OZ-IN)	53	53	100	100	150	150	150	150	300	450	450	625	625	1125	1725	1725
RESONANT TORQUE (OZ-IN)	5	5	8	8	10	10	5	5	10	15	15	15	15	30	30	30
ROTOR INERTIA (LB-IN ²)	0.03	0.03	0.08	0.08	0.11	0.11	0.12	0.22	0.47	0.64	0.64	1.34	1.34	2.75	2.75	2.75
TORQUE TO INERTIA RATIO	42 × 10 ³	42 × 10 ³	30 × 10 ³	30 × 10 ³	33 × 10 ³	33 × 10 ³	16.3 × 10 ³	16.3 × 10 ³	17.2 × 10 ³	16.8 × 10 ³	15.8 × 10 ³	11.2 × 10 ³	11.2 × 10 ³	9.8 × 10 ³	9.8 × 10 ³	9.8 × 10 ³
NUMBER OF LEADS ON TERMINALS	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6	6
SHAFT DIAMETER (INCHES)	.250	.250	.250	.250	.250	.250	.375	.375	.375	.375	.375	.375	.375	.625	.625	.625
MAXIMUM OVERHAUL LOAD (LB)	15	15	15	15	15	15	25	25	25	25	25	25	25	25	25	25
MAXIMUM THRUST LOAD (LB)	25	25	25	25	25	25	50	50	50	50	50	50	50	50	50	50
APPLD. WEIGHT (LB)	NET	1 1/4	1 1/4	2	2	2 3/4	2 3/4	3 1/4	3 1/4	5 1/2	7 1/4	7 1/4	8	8	14 1/2	14 1/2
	SHIPPING	1 1/2	1 1/2	2 1/2	2 1/2	3 1/4	3 1/4	5	4	6 1/4	9	9	9 1/4	9 1/4	15 1/4	15 1/4

[†] With 24 volt d-c drive. See step function curve, Figure 20.

* Both windings energized at rated current.

† Ratings shown are typical values, not for specification.

‡ Approximate value with motor or coil energized.

The following special types are also available. To order, add the designated suffix to the standard motor type number.

Double End Shaft — Has output shaft that extends from both ends of motor. Add suffix E.

High Temperature — Utilize Class H organic materials and high temperature greases. Add suffix H.

Vacuum — Use Class B organic materials and high vacuum bearing lubricant for operation in vacuums to 10⁻⁶ Torr. Maximum permissible motor shell temperature is 100°C. Add suffix V.

Radiation Resistant — Will withstand a radiation dosage of 3000 megarads and can be operated in ambient temperatures to 100°C. Add suffix R.

Militarized — Meet or exceed the requirements of military specifications CCM-836-A (materials), MIL-T-17113 (shock) and MIL-E-4970A (vibration, salt spray, humidity, fungus and temperature). Add suffix M.

Viscous Damped — Has a fluid damping system to provide a step function approaching critical damping. Available on M081, M092 and M093 motors only. Add suffix D.

Encoder Motors — Have integrally mounted incremental photo encoders which allow continuous monitoring of motor speed, position and direction of rotation. Add suffix C1 for single 200 pulse per revolution channel, C2 for two 200 pulse per revolution channels with a 90° phase relationship or C3 for two 200 pulse per revolution channels as on the C2 plus a zero reference channel.

STEP FUNCTION

Single step time (t₁) for each motor is given in rating chart

FIGURE 20

Selecting A Standard Precision Ball Bearing Screw

Model Number	P-0405	P-0410	P-0610	P-0805	P-0810	P-1210	G-0705	G-1004	G-1205	G-1505	G-1504	G-2005	G-2004	G-2002
Rated Dynamic Load (lbs)* @ 100,000 " travel	31	39	84	46	93	127	4,460	7,500	6,270	7,080	9,820	8,600	11,900	41,030
@ 1,000,000 " travel	15	18	39	22	46	59	2,072	3,480	2,912	3,290	4,560	3,984	5,523	19,040
@ 10,000,000 " travel	—	—	—	—	—	—	962	1,615	1,352	1,527	2,117	1,849	2,564	8,838
Rated Static Load (lbs)	170	170	370	370	530	800	16,000	25,600	26,700	32,000	38,400	42,600	51,300	104,000
Screw Diameter (inches)	250	250	375	500	500	750	750	1,000	1,250	1,500	1,500	2,000	2,000	2,000
Lead (inches)**	050	100	100	050	100	100	200	.50	200	200	250	200	250	500
Maximum Standard Length	See Critical Speed Curves, page 13 and Column Load Curves, page 12 for maximum desirable length for your application													
Nominal Backlash (inch) (non-preloaded)	002	002	004	002	004	004	007	009	007	007	009	007	009	020
Accuracy	Standard: 0.0005 inch per foot cumulative						Available in four standard accuracies: 0.0002 inch per foot cumulative, 0.0005 0.001 inch per foot cumulative, 0.006 inch per foot cumulative							
Material	Screw	17-4 PH Stainless Steel						4150 HVDS aircraft quality vacuum degassed steel						
	Nut	17-4 PH Stainless Steel						8620 HVDS aircraft quality vacuum degassed steel						
Hardness	Surface	38-45 Rockwell C						56-62 Rockwell C						
	Core	38-45 Rockwell C						25-35 Rockwell C						
Finish	32 microinch normal						32 microinch normal. Also available if desired with phosphate coat black oxide							
Temperature Range (* F)	-100° F to +200° F						-100° F to +300° F							

Nuts

Single Nut

Double nut preloaded
housing

Single Nut

Double Nut Preloaded

Ends

Universal End

For Single Bearing

For Duplex Bearings

* For preloaded units refer to chart, page 11.

** Right hand thread standard. Left hand thread available on request.

G-2202	G-2504	G-2502	G-3002	G-3502	G-4002	G-5001	G-6001
44,350	13,800	47,600	53,750	59,580	65,100	208,600	235,700
20,600	6,410	22,100	24,950	27,650	30,230	96,900	109,450
9,582	2,975	10,258	11,581	12,834	14,032	44,977	50,502
117,600	64,000	130,900	157,000	183,000	209,500	456,000	547,000
2,250	2,500	2,500	3,000	3,500	4,000	5,000	6,000
500	250	500	500	500	500	1,000	1,000

020 009 020 020 020 020 042 042

inch per foot cumulative

zinc plate, silver plate, cadmium plate, or thin dense chrome

Preloaded Housing For Base Mounting

Preloaded Housing For Flange Mounting

For Multiple Sets of Duplexed Bearings

For Pillow Block

Life Expectancy

The life of a ball bearing screw is the total amount of travel, in inches, with a stated load. These load-life relationships are analogous to the B₁₀ Rating common to the ball bearing industry. The relationship of load to life is an inverse cube ratio. Reducing the load by 1/2 increases life 8 times. Doubling the load decreases life to 1/8 the original expectation. Therefore, the life of a ball bearing screw is predictable. See charts pp.10, 11.

Column Loading

Column loading is the compression load on the screw. This load has a tendency to buckle the screw, and is dependent on screw diameter, screw length and type of mounting. If the load is in tension, then column loading (compression) does not apply. See chart p. 12.

Critical Speed

Critical speed is the speed at which the nut or screw has a tendency to develop severe vibrations, and is dependent on screw diameter, screw length and type of mounting. See chart p. 13.

Preloading

Zero backlash and maximum stiffness can be obtained by preloading. Beaver standard precision ball bearing screws Series G are available with three pre-load configurations. In addition to a simple double nut preloaded assembly, housing type assemblies are available for base or flange mounting. Series P are available with a housing type preloaded double nut. See charts pp. 11, 14.

Dimensions: Series P

Single Nut Non-Preloaded

Model No.	A Inches	B Inches	C Inches	Nominal Backlash (inch)
P-0405	250	687	5625	.002
P-0410	250	875	5625	.002
P-0610	375	937	7500	.004
P-0805	500	737	8437	.002
P-0810	500	937	9082	.004
P-1210	750	937	12500	.004

Double Nut Preloaded Housing

Model No.	A Inches	B Inches	C Inches	D Thread	E Inches
P-0405	250	2.093	750	1-1/16-24 UNEF-2A	.31
P-0410	250	2.468	750	11/64-24 UNEF-2A	.31
P-0610	375	2.687	1.000	13/16-20 UNEF-2A	.37
P-0805	.500	2.821	1.000	15/16-20 UNEF-2A	.37
P-0810	.500	2.718	1.187	1-20 UNEF-2A	.37
P-1210	.750	2.750	1.500	1-5/16-18 UNEF-2A	.37

Universal End

Model No.	A Inches	B Inches
P-0405	.500	1876/ 1873
P-0410	.500	1876/ 1873
P-0610	.750	2501/ 2498
P-0805	.750	3751/ 3748
P-0810	.750	3751/ 3748
P-1210	1.000	5002/ 4999

Dimensions: Dog Stops

When using dog stops, determine ball thread length by adding desired travel to dimensions shown.

Model No.	A	B	C	D	E	F
G-0705	3.65	6.06	6.25	6.25	.53	1.12
G-1004	4.34	7.25	7.43	7.43	.59	1.43
G-1205	4.12	6.75	6.93	6.93	.53	1.62
G-1505	4.37	7.00	7.15	7.15	.65	1.93
G-1504	4.75	7.75	8.00	8.00	.71	2.00
G-2005	4.75	7.37	7.50	7.50	.78	2.43
G-2004	5.12	8.12	8.37	8.37	.81	2.50
G-2002	7.75	13.00	13.50	13.50	.93	3.18
G-2202	7.75	13.00	13.50	13.50	.93	3.43
G-2504	5.12	8.12	8.37	8.37	.81	3.06
G-2502	7.62	12.87	13.37	13.37	.93	3.68
G-3002	7.62	12.87	13.37	13.37	.93	4.18
G-3502	8.25	13.50	14.00	14.00	1.06	4.68
G-4002	9.06	14.50	15.12	15.12	1.18	5.18
G-5001	15.06	25.25	25.87	25.87	1.50	7.43
G-8001	15.06	25.25	25.87	25.87	1.62	8.43

On the following three pages, catalogue data on AeroTech, Inc. tilt and translation stages are presented. As the result of telephone conversations and correspondence between Hughes and AeroTech engineers the following additional information has been obtained.

- 1) The scale factor of the ATT185-3 is approximately 0.4 arc-secs/degree.
- 2) The fine screw may be adapted to be driven by a motor but a coupling must be provided between the motor and shaft which will allow the screw to traverse in and out. The minimum torque required would be about 35 oz-inches.
- 3) Resolution is defined as the distance the stage or table will move with a 1/2 degree turn on the fine adjustment screw. This is about the smallest turn that most people can achieve.
- 4) It is possible to retrofit a manual stage to be motor driven but only on the fine adjustment.
- 5) All motor driven translation stages (ATS-301M, etc.) can be purchased with a double ended shaft on the motor.
- 6) The temperature sensitivity of the ATS-301 is less than 12.7×10^{-6} inches/ $^{\circ}\text{F}$. The temperature sensitivity of the ATT185-3 is 0.3 arc-secs/ $^{\circ}\text{F}$.
- 7) The long term stability or creep of these devices is unknown at the present time.

AOM100 Series (Ultra Precise) Optical Mounts

The AOM100 (Ultra Precise) Series Optical Mounts, available in 1-, 3- and 6-inch frame sizes, combine high resolution with maximum stability, making them ideal for laser holography, interferometry and other exacting optical system applications. The optical cell of the 100 Series is suspended by a unique kinematic diaphragm support

mechanism which is adjustable in azimuth and elevation via the patented Aerotech coarse/fine positioner.

For convenience, 100 Series Mounts are available with adapters for intermediate size optics.

SPECIFICATIONS

	100-1	100-3	100-6
Resolution	.1 arc sec	.05 arc sec	.025 arc sec
Range	4°	4°	4°
Clear Aperture	.88"	2.75"	5.68"
Weight	0.5 lb	1.5 lbs	6 lbs
Finish	Black anodize	Black anodize	Black anodize
Component Size	1"	3"	6"

DIMENSIONS

Model	A	B	C	D	E	F	G	H	J	K	L	M
AOM100-1	4.50	2.48	1.59	3.00	1.56	1.36	1.25	.40	.13	.159	1/4-20	
AOM100-3	8.06	4.38	2.12	5.00	2.00	2.12	1.37	.68	.31	1.75	7/32 1/4-20	
AOM100-6	11.88	5.00	3.38	9.12	3.00	3.96	2.50	See M	.25	4.50	9/32 No Hole	

* 2 holes located on optical center line.

ATT185 Series (Pitch-Roll) Tilt Tables

The ATT185 (Pitch-Roll) Tilt Tables provide a means for leveling instruments or tilting components over a large angular range with continuous fine resolution. These tables have a two-axis Gimbal support and feature a flat unobstructed mounting surface with an ample supply of threaded mounting holes. The 185 Series tables are easily adaptable to the Aerotech Linear and Rotary Translation Stage[®] for producing multi-axis positioning systems.

SPECIFICATIONS

	185-3	185-5
Range	± 10°	± 10°
Resolution	.2 arc sec	.1 arc sec
Weight	1.1 lbs	3.1 lbs
Finish	Black anodize	Black anodize
Material	Aluminum	Aluminum
Mounting Surface	3" x 3"	5" x 5"

C-11

ATS300 Linear Translation Stage

The Model ATS300 Translation Stage provides precision linear motion over a half inch range with continuous one micro inch resolution.

By utilizing Aerotech's patented coarse/fine positioning mechanism, these stages provide quick linear travel while still having full range of the fine adjustment at any position. Multiple-

axis configurations, such as (XY) and (XYZ), are available using these stages, making them ideal for accurately positioning small optical components.

This high strength aluminum, black anodized unit is equipped with eight tapped holes to facilitate the mounting of various components and can be fastened to any flat base surface by means of four #6 socket head cap screws.

As an added feature, providing mechanical position readout, the ATS300 stages are available with linear scales (English or metric) with verniers as well as scored fine adjustment barrels.

SPECIFICATIONS

Weight	1 1/4 lbs
Range	1/4"
Resolution	1 micro inch
Material	Aluminum
Finish	Black anodize
Window	None
Load Carrying Capability	Horizontal 50 lbs Vertical 20 lbs

Linear Bearings	Crossed roller
Configurations	X, (XY), (XYZ)
Z Axis Adapter	None
Linear Scales and Vernier	Optional
Scored Barrels	Optional

ATS301, 302 and 303 Linear Translation Stages

The Models ATS301, 302 and 303 Translation Stages, providing one, two and three inches of travel respectively, use the Aerotech coarse/fine positioner allowing one micro inch continuous resolution over their complete travel. By utilizing precision preloaded linear roller bearings with a friction coefficient of less than .003 and a constant force spring mechanism, these stages exhibit backlash and play-free operation making them ideal for attaining accurate, repeatable motion with minimum force.

All models are provided with convenient mounting holes for auxiliary equipment, are drilled and tapped for (XY) (fig.1) or (XYZ) (fig.2) configurations, and can be attached to any flat surface by means of two #10 socket head screws.

Models ATS301 and 302 are available with a 3 1/2" X 2" clear aperture designated by the suffix "W" on the part number.

SPECIFICATIONS

	301	302	303
Weight	4 lbs	4 lbs	4 lbs
Range	1"	2"	3"
Resolution	1 micro inch	1 micro inch	1 micro inch
Material	Aluminum	Aluminum	Aluminum
Finish	Black anodize	Black anodize	Black anodize
Window—add suffix "W"	3 1/2" X 2"	3 1/2" X 2"	None
Load Carrying Capability	Horizontal 100 lbs Vertical 20 lbs	Horizontal 100 lbs Vertical 20 lbs	Horizontal 100 lbs Vertical 20 lbs
Linear Bearings	Crossed roller	Crossed roller	Crossed roller
Configurations	X, (XY), (XYZ)	X, (XY), (XYZ)	X, (XY), (XYZ)
Z Axis Adapter	Light- and heavy-duty	Light- and heavy-duty	Light- and heavy-duty
Linear Scales and Vernier	Optional	Optional	Optional
Scored Barrels	Optional	Optional	Optional

DIMENSIONS

Model	A	B
ATS301	.50	1.50
ATS302	1.00	1.87
ATS303	1.50	2.25

ATS301M, 302M and 301MM Motor-Driven Translation Stages

The Model ATS301M and 302M motor-driven linear translation stages (providing one and two inches of travel respectively) offer quick and accurate positioning utilizing 200-step-per-revolution stepping motors.

Linear position accuracy and repeatability are assured by employing an ultra-precise ground lead screw, while dynamic stability and excellent runout are controlled by high-quality cross-roller linear bearings. The 301M and 302M tables offer .0001 inch-per-step resolution while the 25mm travel model (ATS301MM) offers 1 micron-per-step resolution.

All models are provided with convenient threaded insert mounting holes for auxiliary equipment, are drilled

and tapped for (XY) and (XYZ) configurations and can be attached to any flat surface by means of two #10 socket head screws.

The ATS301M, 302M and 301MM are coated with an extra-hard (63 Rockwell) finish and are available on special order for 10^{-6} Torr vacuum operation.

SPECIFICATIONS

	301M	302M	301MM
Weight	6 lbs	6 lbs	6 lbs
Range	1"	2"	25mm
Finish	Hard black anodize	Hard black anodize	Hard black anodize
Resolution	200 steps/rev 400 steps/rev .0001"	200 steps/rev 400 steps/rev .0001"	200 steps/rev 400 steps/rev 1 micron
Load Carrying Capability	Horizontal 100 lbs Vertical 20 lbs	Horizontal 100 lbs Vertical 20 lbs	Horizontal 100 lbs Vertical 20 lbs
Repeatability (unidirectional)	.000025"	.000025"	.5 microns
Drive Mechanism	Precision lead screw	Precision lead screw	Precision lead screw
Maximum Slew Speed	2000 steps/sec	2000 steps/sec	2000 steps/sec
Window—add suffix "W"	3 1/2" x 2"	3 1/2" x 2"	3 1/2" x 2"
Vacuum capability (optional)	10^{-6} Torr	10^{-6} Torr	10^{-6} Torr

DIMENSIONS

Model	A
ATS301M	1.00
ATS302M	2.60
ATS301MM	25mm

ATS301MR Motor-Driven Rotary Translation Stage

The Model ATS301MR Rotary Translation Stage offers quick, accurate and continuous 360° positioning utilizing 200-step-per-revolution stepping motors. Position accuracy and repeatability are assured by employing an ultra-precise

worm-drive mechanism, while dynamic stability and minimum wobble are maintained by a dual (high-quality) ball bearing support system.

The ATS301MR is available with a 1 1/2-inch clear aperture and two or one-half arc minute-per-step resolution. It is easily adaptable to any of the one- and two-inch linear models and can be fitted to operate in a 10^{-6} Torr vacuum.

SPECIFICATIONS

Weight	5 lbs	Load Carrying	Horizontal 25 lbs
Range	360° continuous	Capability	Vertical .2 arc min
Resolution	200 steps/rev 2 arc min 1/2 arc min	Repeatability (unidirectional)	4"
(2 models)	400 steps/rev 1 arc min 1/4 arc min	Table-top Diameter	4"
Material	Aluminum	Maximum Slew Speed	2000 steps/sec
Finish	Black anodize	Clear Aperture	1 1/2"
		Optional Vacuum Capability	10^{-6} Torr
		Accuracy (lead error accumulative)	3 arc min

1
2
3
4
5
6
7
8
9
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
84

APPENDIX D
POINTING AND FOCUSING CONFIGURATION TRADEOFF STUDIES

2

APPENDIX D

POINTING AND FOCUSING CONFIGURATION TRADEOFF STUDIES

The term configuration is intended to denote the portion of the studies that are devoted to determining where the sensor should be located, how the beam is focused on the target and how and where to enter the beam, i. e., where and how to locate the black box called the sensor. The term optical configuration relates to where the laser beam is focused in relation to the target. The term system configuration encompasses the optical configuration and location of sensor, entry into beam, etc. Sensor design studies are for the purpose of determining the "best" technique for measuring pointing and focus, i. e., what is in the black box. The configuration studies could not, of course, be done alone without any consideration of the sensor, but only the barest concept of sensing techniques were involved. The goals of the configuration studies were to come up with an arrangement in which the least complicated (least expensive), most reliable sensor can be incorporated. Of primary importance in the configuration is the reference for the sensor. Is it mechanical, self-referencing, comparative reference, absolute reference, etc.? A perfect nulling sensor is only as good as the knowledge of the reference for the null. The most desirable configuration is one in which the reference is mechanical with tolerances such that stability is assured. The next more desirable configuration is one in which the reference can be readily checked, preferably with the sensor itself. [The baseline system configuration is a combination of the above as will be discussed later.]

OPTICAL CONFIGURATIONS

It was assumed that the surrogate target should be a ball since no other geometric shape is the same from all directions. The variable in the optical configuration is the position of the laser focal point with respect to the surrogate target. Figure D-1 shows the five possibilities.

In case I, the laser is focused at the center of the ball. The ball acts as a perfect non-aberating reflector, and the beam is returned exactly on itself. Transverse motion of the ball causes the return beam to be deflected angularly; and, conversely, an angular deflection of the input beam causes a

Figure D-1. Five surrogate target-to-focal point position possibilities.

transverse motion of the focal point that results in an angular deflection of the output beam that is equal and opposite to the input beam angle. The relation between angular deflection of the beam and transverse motion of the focal point with respect to the ball is independent of ball size, but there is transverse motion of the beam that is inversely proportional to the ball size. It should be noted that the criteria for pointing is the transverse distance from the ball center to the focal point of the laser beam. Angular motion of the beam is only a measure of this transverse error. A sensor for case I can be located anywhere in the laser chain, from input pinhole to the final focus lens. The main consideration is access to the beam and other factors such as field of view for acquisition, optical attenuation and aberrations. Since it was decided that the sensor must sample the entire beam, a sensor for case I must have an aperture equal to the beam diameter at the point of entry.

Case II is the condition where the lens is focused exactly at the focal point of the ball so that the beam from the ball back to the lens is collimated and hence is refocused at the back focal point of the ball. Transverse motion of the ball causes the output focal point to shift transversely as shown in Figure D-2. The rate of focal point shift with input angle or ball motion is inversely proportional to ball diameter. The reflected beam diameter, from the ball to the lens, is proportional to the ball diameter.

The focal point for case III is located between the focal point of the ball and the center of the ball. As the focal point of the lens is shifted axially from the focal point of the ball (case II) to the center of the ball (case I) the focal point of the reflected beam shifts axially from the back focal length of the lens to the (apparent) focal point for the source. This factor provides the flexibility for locating the target at any desired intermediate distance and the sensor aperture can be smaller than the original beam and still capture all of the beam.

Case IV shows the laser focal point just ahead of the ball focal point, so that the reflected beam from the ball is imaged in the plane of the lens as if it were being used as a field lens. Transverse motion of the ball or input angular motion cause the reflected cone to pivot about the focal point of the lens as the second focal point moves in the plane of the lens.

Case V shows the laser focused on the front surface of the ball. The ball is acting as a retro and the beam is being returned exactly on itself. Note that transverse motion of the ball does not cause angular motion of the return beam as did case I. Transverse motion of the ball causes a transverse shift of the return beam that is directly proportional to the ball motion and inversely proportional to the ball diameter. In this case the information regarding the transverse error between the ball and the focal point is contained in the transverse motion of the beam.

Figure D-2. Case II with transverse error

SYSTEM CONFIGURATIONS

An important fact to note is that at any focal plane in the system, sensitivity is a constant. Sensitivity is defined as follows:

$$\frac{\text{Transverse Magnification}}{\text{Blur Diameter}} = \text{constant}$$

$$\frac{\text{Axial Magnification}}{\text{Depth of Focus}} = \text{constant}$$

Transverse magnification in any focal plane is proportional to the $f/\text{no.}$ at that focal plane as is the blur diameter. Axial magnification is proportional to the $(f/\text{no.})^2$ as is the depth of focus. Since this is true, sensitivity cannot be improved through clever manipulation of focal lengths or $f/\text{no.}$'s. Sensitivity can be degraded with a configuration through introduction of aberrations. The optical configuration can be arranged, however, to match blur to component size, to minimize tolerance requirements, etc.

In the following paragraphs, the system configurations given major consideration are briefly described and the reasons for rejection are given. There were many others, both completely unique and/or variations on these that were conceived and discarded on the blackboard and on the back of envelopes. These however represent the system configuration that were considered more worthy, for a time at least.

Configuration I is shown in Figure D-3. The focal point is at the center of the target and the sensor is located at reference pinhole right after the MO. The primary advantage of this configuration is that all chains utilize the same single sensor. This sensor requires no reference sensor since it is mounted on the original source of the laser signal, the reference pinhole. The primary disadvantages accrue because the alignment laser energy must

Figure D-3. System Configuration-I

traverse the laser chain twice. The returning signal is attenuated an additional 45 db and the aberrations are doubled. The worst effect is due to non-axially symmetric aberrations which introduce a pointing error. This occurs when, for instance, coma causes the centroid of energy at the focused spot to be transversely shifted from the optical axis. A sensor at the target end of the chain would sense this shift and correct accordingly. However, when the signal traverses the laser chain again the centroid is transversely shifted again so that the centroid error at the input sensor is doubled. When the sensor nulls the error at the input then the centroid at the target is over corrected. Since the non-symmetric aberrations cannot be predicted at this time this configuration was rejected. Another possible problem was a conflict between the many spatial filters in the chain and the sensor field of view required for acquisition.

Configuration II is shown in Figure D-4. The focal point is located the same as configuration I, at the center of the ball, but the sensor is a 25 cm aperture located near the final lens. Entry to the beam is achieved by using the last polarizer in the laser chain as a beamsplitter. At the time this configuration was under consideration, the polarizers were transmissive, as shown in the figure; however, the function is the same with reflective polarizers. The reference for this sensor is the incoming beam from the laser chain, as seen through the retro. It is important whether the steering mirrors are before or after the sensor. If they are before the sensor, then the reference must be sensed continuously while aligning to the target, whereas if they are after, the sensor can be reference aligned before aligning to the target. In either case, if the sensor is located in the 25 cm beam alignment to the reference is touchy. The reference alignment sensitivity is $2.5 \mu\text{rad}/\mu\text{m}$,

Figure D-4. System Configuration-II

which means, that if the sensor is angularly misaligned by $2.5 \mu\text{rad}$, then there will be a $1 \mu\text{m}$ pointing error at the target. The most serious defect in this configuration is the reference for focus, since this sensor must utilize the beam from the laser chain.* If the beam is perfectly collimated, then the focal point of the incoming beam and the reflected beam are at the same location. If the input beam is divergent, then the return beam will be convergent by the same amount. The input focal point will be behind the sensor lens focal point and the reflected beam will be ahead by the same amount. To correctly sense focus, the distance from the sensor lens focal point must be measured on an absolute basis, and then the reflected focal point driven an equal but opposite distance. This, of course, results in an unnecessarily complex sensor, since it would require two focus sensors with absolute measuring capability. An alternative is to precisely control the divergence of the input beam, either collimated or non-collimated and to calibrate the sensor for a known input beam divergence. The sensitivity to divergence error is $0.7 \mu\text{m}/\mu\text{rad}$, i. e., a divergence error of $1.4 \mu\text{rad}$ would cause a focal error of $1 \mu\text{m}$.

Configuration II was rejected as being both too complex (expensive) and/or because it would put excessive requirements on the laser chain. Also the sensitivity to sensor misalignment would require that the sensor be realigned just prior to performing the target pointing and focusing alignment.

A variation of configuration II is to locate the sensor at some convenient location within the laser chain. The same general discussion as for configuration II applies. The sensitivity to angular misalignment is, however, reduced according to the reduction in beam diameter at the point of entry into the chain.

Configuration III is shown in Figures D-5 and D-6. In this scheme, a very small surrogate target is used, and the focal point is selected at the target focal point (or just in front of it. See case I or IV in Figure D-1) so

*As opposed to the baseline system that utilizes the beam only for pointing reference and uses the sensor location for focus. The baseline sensor measures the error between the focal point and the ball directly.

Figure D-5. System
Configuration-III

Figure D-6. Generation of Modulation at lens

that the reflected beam is refocused at the lens. Then the input beam is deflected so that the reflected spot is centered on the mask, as shown in Figure D-6, and nutated about the optical axis. The sensor, which is located at the first polarizer, is just a collector, i. e., measures only the amount of energy into its aperture. The error modulation is created at the mask so that neither angle or transverse position is important after the mask. The scheme requires that the beam be centered when the nutation device is removed. This can be accomplished by utilizing an indexing rotating wedge as the nutater. Since derivative angle is the nutation angle, the beam is aligned precisely to the nutation axis when the wedge is removed. The location of the wedge is not critical to the operation so neither bearing runout nor indexing must be accurate.

Table D-1 gives a list of the parameters for this technique and their relation to surrogate target size.

This scheme is very attractive when the reference problem is considered, since the focusing lens itself becomes the reference and the error signal is generated at the target chamber and not in a sensor that must be referenced. Also, the sensor is only a single detector energy-in-the bucket type collector.

The disadvantages of this scheme are that it is sensitive to non-symmetrical aberrations; and, more important, there does not seem to be a workable focus sensing technique that is compatible. It is for these reasons and the undesirability of nutation, that this pointing technique was rejected.

Configuration IV is shown in Figure D-7. This configuration is similar to configuration III in that the reflected beam is reimaged in the plane of the focusing lens, but a second lens, in the sensor, is used to reimage the focusing lens mask and the reflector beam onto a detector. Since the mask can be used as a reference, the sensor now has a reference in the detector plane. Note that the focusing lens is acting as a field lens to the reflected beam, and hence does not effectively introduce optical power on the second pass. If a small (1 mm) surrogate target is used, then the f-cone into the sensor is very large ($\approx f/2000$), so that the tolerance on the axial location of the sensor (for focus) is large. A relatively large field of view is required to see the mask. The large field of view is undesirable when the field of view is compared to the accuracy required for pointing. A 1 mm surrogate target

Table D-1. Parameter table for nutation on mask scheme

Ball Diameter	* Blur Diameter Diff Lim Array Disc	Sens M/M	Reticle Tol at 1 μm	Mod Coef %/M	* Input Angle #	* # ΔD Input Trans at 48M	Focus at Δ	Conditions
d	$\frac{10\lambda F^2}{dD}$	$\frac{4F}{d}$	$\frac{4 \times 10^{-6} F}{d}$	$\frac{100D}{\lambda F}$	$\frac{dD}{8F^2}$	$\frac{6dD}{F^2}$	$\frac{d^2}{2F}$	General (Uniform Blur = $2.44 \lambda / D$)
d	$\frac{30\lambda F^2}{dD}$	$\frac{4F}{d}$	$\frac{4 \times 10^{-6} F}{d}$	$\frac{33D}{\lambda F}$	$\frac{dD}{8F^2}$	$\frac{6dD}{F^2}$	$\frac{d^2}{2F}$	X3 Diff lim
d	$\frac{3 \times 10^{-5}}{d}$	$\frac{2}{d}$	$\frac{2 \times 10^{-6}}{d}$	16×10^6	$\pm \frac{d}{8}$	$\pm 6d$	d^2	Lens focused on ball so that focal point is in plane of lens
1 mm	3 cm	2×10^3	2mm	16×10^6	125 μrad	0.6 cm	1 μm	$\lambda = 10^{-6}$
2 mm	1.5 cm	10^3	1 mm	16×10^6	250 μrad	1.2 cm	4 μm	
8 mm	0.4 cm	250	1/4 mm	16×10^6	1 mrad	4.8 cm	64 μm	
5 mm	0.6 cm	400	0.4 mm	16×10^6	625 μrad	3 cm	25 μm	
5 cm	0.6 mm	40	40 μm 1.6 mils	11	6 mrad	—	—	

F = lens focal length
D = input beam diameter
d = ball diameter
 λ = wavelength

Units in meters and radians

Lens focused on ball so that focal point is in plane of lens

*D = aperture diameter (deflection to get to edge of aperture)

Figure D-7

gives a sensitivity at the lens of 1 mm blur motion per 1 μm error (assuming an $f/2$ focusing lens) and image of the mask on the lens would be equivalent to a 250 μm field. Since the sensitivity is inversely proportional to target size a smaller target would effectively decrease the field subtended by the mask; however, decreasing the field also complicates acquisition.

The disadvantages of this configuration are that it is difficult to illuminate the mask so that it can be seen by the sensor. There is the difficulty in configuring an inexpensive detector for sensing the blur location with respect to the image of the mask. Another factor is that there may be a "hole" in the center of the focusing lens for suppression of internal reflections. This "hole" would then be in an image plane of the system, which is undesirable. This configuration was rejected because of the difficulty in illuminating the mask, the sensor complexity required for sensing the mask image and the "hole" in the lens being in the image plane.

It should be noted that for this configuration the tolerances for alignment and stability of alignment for the sensor are very good and are, in fact, the same as for the baseline configurations.

Configuration V is shown in Figure D-8. In this configuration, the focal point is at the surface of the ball so that it acts as a perfect retro. The input beam is deflected at an angle such that the return beam is translated laterally so that it is centered at the edge of the aperture, again defined by a mask. Modulation is generated by rotating the input beam at this angle. If the input beam is rotating around the optical axis with no error, then the return beam is moving transversely with a circular motion about the optical axis and the

Figure D-8. System configuration-V

center of the beam will be vignetted symmetrically by the mask. If there is an error, then the axis of the nutation cone is offset by that error and the return beam will be vignetted unsymmetrically. A single collecting sensor for all chains can be located back near the pinhole since aberrations in the return path have no effect. However the sensor would need to be sensitive due to the attenuation. The advantages are that the error is generated at the target chamber and hence is self-referencing, and only one sensor is needed for all chains. A 1 mm ball gives a modulation index of about 30 percent/ μm . The nutation of the beam could be implemented with a rotating wedge (see Figure D-9) just past the pinhole on the master oscillator bench. Since the nutation is not affected by lateral position of the wedge, bearing runout and indexing accuracy are not important. In order to get the beam through the laser chain the nutation angle at the pinhole must be less than about $100 \mu\text{rad}$, so the surrogate target would have to be small, on the order of $100 \mu\text{m}$. Since the beam is focused on the surface of the target, the surface quality would have a serious effect on this sensing technique. The configuration was rejected because it was felt that placing such requirements on surface quality for such a small ball would be too gamey.

Figure D-9. Nutation of beam by wedge

Configuration V is shown in Figure D-10. The focal point is slightly after the focal point the small (1 mm) ball so that the reflected beam is focused at a quad detector that is just behind the lost polarizer which is used as a beam-splitter. This arrangement provides the ultimate in simplicity for sensing pointing error. If a 1 mm target is used then the $1/e$ blur diameter is about 5 mm for a 2.5 timer diffraction limited system, and the transverse alignment sensitivity is on the order of 1 mm for 1 μ m of error. Since no other optics are used, there is no angular misalignment sensitivity. The problem with this configuration is in obtaining a compatible focus sensing scheme. Since the depth of focus is on the order of 20 M, the two energy balancing schemes for focusing are the astigmatic technique and the scheme where the focus is dithered plus and minus by moving a focusing lens, and the energy is collected by a single detector through a pinhole. (See Appendix B) The astigmatic technique was considered to be less desirable due to the requirement for balancing detector elements. The dither technique was considered undesirable because the 25 cm focusing lens would have to be dithered.

Figure D-10. Configuration-VI

Configuration V was modified slightly to incorporate a lens in front of the detector, thereby giving up the insensitivity to angular alignment, but providing a means for incorporating a better focus scheme, as well as providing a more convenient blur diameter on the pointing quad. This modification led directly to the configuration described in Volume 1, Section 2 of the report as the baseline system.

APPENDIX E
FALSE START CENTERING SENSOR

APPENDIX E

FALSE START CENTERING SENSOR

In the earlier phases of the study, a method of sensing beam centering on the final focusing lens was devised which later proved to be faulty in concept. In this appendix, the original concept is described as well as the reasons it does not work. This is offered because Hughes thinks this self-made trap is an easy one in which to fall. The following is presented as a caveat to other researchers in this field.

The original intention was to combine the final lens centering sensor with the pointing and focus sensor by placing an additional quad detector in the focal plane of the image of the focusing lens as reflected from the surrogate target. As illustrated in Figure E-1, the focusing lens can be thought of as an object, O. This object appears as a virtual image, I, reflected from the surrogate target. The virtual image is, in turn, viewed by the focusing lens and recast as an image I". This later image, the one cast by the final focusing lens, may be virtual or real depending upon:

- whether the incident laser beam is convergent or divergent and
- the point of "correct" focus established by the focus sensor concept employed

The image, I", is then focused as a real image, I''' by the sensor lens and lays in the plane of the centering quad.

In Figure E-1, in which dimensions are grossly exaggerated for clarity, the incident beam was chosen to be collimated and the point of "correct" focus was chosen to be at the center of the ball. This is not the system configuration; however, the interrelationships to be discussed still apply. In this figure, a sensor is shown with a quad aligned on the focused image of the focused point, indicating alignment in pointing and a quad which is aligned to the image of the lens.

It would seem that pointing and centering alignment prevails and that decentering would cause an error to be detected by the centering quad.

Figure E-1. Lens centering original concept

Indeed, if one were to insert a blocking edge as indicated in the figure, the quad would sense an unbalance which would imply decentering.

In Figure E-2, a true centering error is illustrated; however, the central ray of the incident beam passes through the center of the surrogate target and is reflected back upon itself. No centering error is detected. The reason for this is that the object, O, whose position is finally detected by the position of its image I''' with respect to the quad, is really the beam footprint on the focusing lens and not the focusing lens itself.

The point here is that the achievement of perfect pointing is concomitant with the central ray passing through the center of the surrogate target. The returning central ray is, therefore, coincident with the incoming central ray and is centered on the incoming beam.

The above is true for any focus criterion; i.e., center of the sphere, surface of the sphere, half-radius point or intermediate points.

E-4

Figure E-2. Lens centering concept caveat

APPENDIX F
RCA APPLICATION NOTES ON QUAD DETECTOR

RCA Application note PE-514,
Dr. R. J. McIntyre, et. al.,
Solid State Detectors for Laser Applications.

APPENDIX G
ELLIPTICAL FLEX PIVOT ANALYSIS

FREQUENCIES, STRESSES, AND STIFFNESSES FOR ELLIPTICAL FLEX PIVOTS

INTRODUCTION

Circular and elliptical flex pivots have been used to support Hughes designed beam steering mirrors. The configuration of these flex pivots is defined in Figure 1. In the past these flex pivots were rough sized by assuming an effective constant cross-section over the entire pivot length. The final dimensions of these pivots were obtained by a relatively costly, time consuming iterative process using eight beam STARDYNE finite element models.

THE ELLIPTICAL PIVOT SHAPE IS GOVERNED BY THE EQUATION

$$\left(\frac{X}{a}\right)^2 + \left(\frac{Y}{b}\right)^2 = 1$$

NOTE THAT ALL CROSS SECTIONS (A-A) FOR ALL ELLIPTICAL PIVOTS ARE CIRCULAR

SPECIAL CASES:

- 1) $a = b$, THE PIVOT HAS A CIRCULAR SHAPE
- 2) $b = 0$, THE PIVOT HAS A CONSTANT CROSS SECTION

Figure 1. Elliptical flex pivot configuration definition.

A GE265 time-sharing program is herein described which enables the design engineer or structural analyst to quickly, easily, and accurately determine the natural frequencies, and infinite life offset and dither capabilities, stiffness matrices, and equivalent eight-beam finite element models of elliptical flex pivot mounts for beam-steering mirrors.

PROGRAM INSTRUCTIONS

1) Signing on to the GE 265 time-sharing system

After dialing 5011, the following information will be requested:

LOG NUMBER --
EMPLOYEE NUMBER --
SYSTEM --
NEW OR OLD --
OLD PROBLEM NAME --

The computer will indicate when it is ready to receive data.

2) Inputting the data string

For the elliptical flex pivot suspension system shown in Figure 2 the data string reads as follows:

525 DATA L, R₀, R₁, E, G, W, I_x, I_y, I_z, X₀

where

L = length of flex pivot, in.
R₀ = base radius of flex pivot, in.
R₁ = throat radius of flex pivot, in.
E = elastic modulus, psi
G = shear modulus, psi

Figure 2. Definition of FLXPVT input variables.

W = weight of steering mirror, lb.

I_x = principal rotary weight inertia of steering mirror about an axis through its c.g. parallel to the x axis, lb-in²

I_y = principal rotary weight inertia of steering mirror about an axis through its c.g. parallel to the y axis, lb-in²

I_z = principal rotary weight inertia of steering mirror about an axis through its c.g. parallel to the z axis, lb-in²

X_0 = offset of steering mirror c.g. along positive x axis (negative as shown), in.

Please note that the following program limitations must be observed:

1. The type of system analyzed by FLXPVT is restricted to those having mirror c.g.'s located only along the flex pivot x -axis.
2. Only principal weight moments of inertia are allowed.
3. Care must be observed in specifying the sign of X_0 . The c.g. of most mirror systems will usually be located at the midsections (throat) of the pivot, i.e., at $X_0 = +L/2$.

4. W has weight units, lbs., and I has weight moment of inertia units, lb-in.².

3) Running the FLXPVT program

Type

RUN

The computer will printout the input data and results of the problem.

SAMPLE PROBLEM

Consider a system for which

$$L = 0.625 \text{ inch (pivot length)}$$

$$R_0 = 0.256 \text{ inch (pivot base radius)}$$

$$R_1 = 0.1445 \text{ inch (pivot throat radius)}$$

$$E = 17.0 \times 10^6 \text{ psi (elastic modulus for titanium)}$$

$$G = 6.51 \times 10^6 \text{ psi (shear modulus for titanium)}$$

$$W = 41.36 \text{ lbs (mirror weight)}$$

$$I_x = 1274.4 \text{ lb-in}^2 \text{ (twist inertia)}$$

$$I_y = 458.4 \text{ lb-in}^2 \text{ (rocking inertia)}$$

$$I_z = 859.1 \text{ lb-in}^2 \text{ (rocking inertia)}$$

$$X_0 = +0.3125 \text{ inch (distance from coordinate system origin to mirror c.g.)}$$

For this system, the data string reads as follows:

525 DATA 0.625, 0.256, 0.1445, 17.0 E6,

6.51 E6, 41.36, 1274.4, 458.4,

859.1, .3125

If repeated iterations involving only one or two changes in the data string are to be run, a more convenient way to input the data would be as follows:

525	DATA	0.625
526	DATA	0.256
527	DATA	0.1445
528	DATA	17.0E6
529	DATA	6.51E6
530	DATA	41.36
531	DATA	1274.4
532	DATA	458.4
533	DATA	859.1
534	DATA	0.3125

This format allows changes of a single piece of data without rewriting the entire data string.

For this system, the FLXPVT program will compute the following:

- 1) The six natural frequencies
- 2) Maximum offset and dither excursions for infinite flex pivot fatigue life.
- 3) The section properties describing an eight-beam, finite element flex pivot model suitable for incorporation into a larger, more complex system model.
- 4) The 12 x 12 stiffness matrix

The program output is:

FLXPVT 16:15 MON. 11/18/74

FREQUENCIES, STRESSES, AND STIFFNESS MATRICES FOR
ELLIPTICAL FLEX PIVOTS

FLEX PIVOT LENGTH L, IN = .625
FLEX PIVOT BASE RADIUS RO, IN = .256
FLEX PIVOT THROAT RADIUS RI, IN = .1445
FLEX PIVOT ELASTIC MODULUS E, PSI = 17000000
FLEX PIVOT SHEAR MODULUS G, PSI = 6510000
FLEX PIVOT SUSPENDED WEIGHT W, LBS = 41.36
FLEX PIVOT SUSPENDED X WEIGHT ROTARY INERTIA IX, LB-IN² = 1274.4
FLEX PIVOT SUSPENDED Y WEIGHT ROTARY INERTIA IY, LB-IN² = 458.4
FLEX PIVOT SUSPENDED Z WEIGHT ROTARY INERTIA IZ, LB-IN² = 859.1
FLEX PIVOT SUSPENDED WEIGHT C.G. OFFSET XO, IN = .3125

FLEX PIVOT X TRANSLATION FREQUENCY, HZ = 736.532

FLEX PIVOT Y TRANSLATION FREQUENCY, HZ = 301.069

FLEX PIVOT Z TRANSLATION FREQUENCY, HZ = 303.504

FLEX PIVOT X ROTATION FREQUENCY, HZ = 9.24191

FLEX PIVOT Y ROTATION FREQUENCY, HZ = 17.3043

FLEX PIVOT Z ROTATION FREQUENCY, HZ = 12.7424

ALLOWABLE OFFSET AND DITHER FOR INFINITE LIFE
ASSUMING 100 KSI UTS MATERIAL

OFFSET-RAD	DITHER-RAD
0	5.43416E-03
1.08683E-03	4.89074E-03
2.17366E-03	4.34733E-03
3.26049E-03	3.80391E-03
4.34733E-03	3.26049E-03
5.43416E-03	2.71708E-03
6.52099E-03	2.17366E-03
7.60782E-03	1.63025E-03
8.69463E-03	1.08683E-03
9.78148E-03	5.43416E-04
1.08683E-02	1.45519E-11

SECTION PROPERTIES FOR EQUIVALENT 8 ELEMENT STARDYNE MODEL

ELEMENT	A	J	I2=I3	K2=K3
1 - 8	.134397	2.87475E-03	1.43738E-03	0.89
2 - 7	.08766	1.22299E-03	6.11495E-04	0.89
3 - 6	7.24304E-02	8.34953E-04	4.17477E-04	0.89
4 - 5	6.66731E-02	7.07493E-04	3.53746E-04	0.89

THE 12 X 12 FLEX PIVOT STIFFNESS MATRIX IS:

2.29475E+06	0	0	0	0
0	-2.29475E+06	0	0	0
0	0	0	0	0
0	376328.	0	0	0
-117789.	0	-376328.	0	0
0	352994.	0	0	0
0	0	376328.	0	117789.
0	0	0	-376328.	0
-352994.	0	0	0	0
0	0	0	11132.7	0
0	0	0	0	-11132.7
0	0	0	0	0
0	0	117789.	0	51403.2
-125021.	0	0	-117789.	0
0	-117789.	0	0	0
51403.2	0	117789.	0	0
0	-125021.	0	0	0
-2.29475E+06	0	0	0	0
0	2.29475E+06	0	0	0
0	0	0	0	0
0	-376328.	0	0	0
117789.	0	376328.	0	0
0	-352994.	0	0	0
0	0	-376328.	0	-117789.
0	0	0	376328.	0
352994.	0	0	0	0
0	0	0	-11132.7	0
0	0	0	0	11132.7
0	0	0	0	0
0	0	-352994.	0	-125021.
0	0	0	352994.	0
345642.	0	0	0	0
0	352994.	0	0	0
-125021.	0	-352994.	0	0
0	345642.	0	0	0

Table 1 summarizes the results of the FLXPVT run and compares them with the eight-element STARDYNE model results.

Table 1. Comparison of FLXPVT and STAFDYNE results

Description of Results	FLXPVT	STARDYNE (8 element model)
In-plane x twist frequency	9.24 Hz	9.14 Hz
Out-of-plane y rocking frequency	12.74 Hz	12.74 Hz
Out-of-plane z rocking frequency	17.30 Hz	17.44 Hz
In-plane y translation frequency	301.00 Hz	291.00 Hz
In-plane z translation frequency	304.00 Hz	291.00 Hz
Line-of-sight x thrust frequency	737.00 Hz	732.00 Hz
Maximum dither rotations for infinite fatigue life assuming 100 ksi UTS material	5.43 mrad	5.68 mrad

Comments

- 1) The discrepancies between the FLXPVT and STARDYNE results are caused by the difference in the number of elements used by each program in subdividing the flex pivot. The STARDYNE model used only eight elements to model the pivot. The FLXPVT program, however, used a numerical integration scheme in the analytical solution for which the pivot was divided into 100 elements. It should be noted, however, that even with the seemingly "crude" eight-element STARDYNE model, frequency results matched the FLXPVT results within 3.3 percent. The 6 percent error in the offset-dither results stems from the sensitivity of bending stresses with respect to section properties. The natural frequencies are a function of the square root of the section properties and hence are less sensitive to changes in the section.

- 2) It should be noted that the offset dither results were developed with the following assumptions:

- a) $F_{tu} = 100,000 \text{ psi}$
- b) $\sigma_{\text{endurance}} = 1/3 F_{tu}$
- c) $\sigma_{\text{tensile allowable}} = 2/3 F_{tu}$

The endurance limit thus calculated should be conservative.

However, the effect of stress raisers and surface finish may cause this endurance limit to be unconservative. The offset-dither results should therefore be interpreted carefully.

- 3) The two special cases of a circular pivot ($a \approx b$) and a constant cross section pivot ($b = 0$) are easily handled.
- 4) The accuracy of the FLXPVT solution may be altered if desired by changing the parameter "N" in statement 105. Changing "N" will probably have little effect on the results however.
- 5) Manipulation of the stiffness matrix will produce the external forces needed to produce a given displacement (see "Theory").
- 6) The four sets of beam section-properties calculated can be incorporated into larger finite element models. Alternatively, the 12×12 stiffness matrix can be put in the larger model as a matrix alteration.

THEORY

Formulation of System Stiffness Matrix

Consider the elliptical flex pivot suspension system shown in Figure 3. The strain energy in the system can be written as

Figure 3. Elliptical flex pivot suspension system.

$$\begin{aligned}
 U = & \frac{1}{2} \int_0^L \frac{V_{x1}^2 dx}{EA(x)} + \frac{1}{2} \int_0^L \frac{V_{y1}^2 dx}{GA(x)} + \frac{1}{2} \int_0^L \frac{V_{z1}^2 dx}{GA(x)} \\
 & + \frac{1}{2} \int_0^L \frac{M_{x1}^2 dx}{GJ(x)} + \frac{1}{2} \int_0^L \frac{(M_{y1} + V_{z1}x)^2 dx}{EI(x)} \\
 & + \frac{1}{2} \int_0^L \frac{(M_{z1} - V_{y1}x)^2 dx}{EI(x)}
 \end{aligned}$$

where $\alpha = 1.12$ is the shear shape factor for circular cross-sections.

The non-zero terms of the 6 x 6 flexibility matrix are

$$a_{11} = \frac{\partial^2 U}{\partial^2 V_{x1}} = \int_0^L \frac{dx}{EA(x)}$$

$$a_{22} = \frac{\partial^2 U}{\partial^2 V_{y1}} = \int_0^L \frac{\sigma dx}{GA(x)} + \int_0^L \frac{x^2 dx}{EI(x)}$$

$$a_{33} = \frac{\partial^2 U}{\partial^2 V_{z1}} = \int_0^L \frac{\sigma dx}{GA(x)} + \int_0^L \frac{x^2 dx}{EI(x)}$$

$$a_{44} = \frac{\partial^2 U}{\partial^2 M_{x1}} = \int_0^L \frac{dx}{GJ(x)}$$

$$a_{55} = \frac{\partial^2 U}{\partial^2 M_{y1}} = \int_0^L \frac{dx}{EI(x)}$$

$$a_{66} = \frac{\partial^2 U}{\partial^2 M_{z1}} = \int_0^L \frac{dx}{EI(x)}$$

$$a_{26} = a_{62} = \frac{\partial^2 U}{\partial V_y \partial M_{z1}} = \int_0^L \frac{x dx}{EI(x)}$$

$$a_{35} = a_{53} = \frac{\partial^2 U}{\partial V_{z1} \partial M_{y1}} = - \int_0^L \frac{x dx}{EI(x)}$$

The 6x6 stiffness matrix is obtained by inverting this flexibility matrix; that is

$$[k] = [a]^{-1}$$

The 12x12 stiffness matrix for subsequent STARDYNE analysis, relating displacements and rotations at end 1 ($x = y = z = 0$) to those at end 2 ($x = L, y = z = 0$), can be obtained by applying a coordinate transformation to the 6x6 stiffness matrix; that is

$$[k]_{12 \times 12} = [\beta]^T [k]_{6 \times 6} [\beta]$$

where

$$\{u\}_{6 \times 1} = [\beta]_{6 \times 12} \{u\}_{12 \times 1}$$

or

$$\begin{Bmatrix} V_{x1} \\ V_{y1} \\ V_{z1} \\ M_{x1} \\ M_{y1} \\ M_{z1} \end{Bmatrix} = \begin{bmatrix} 1 & 0 & 0 & 0 & 0 & 0 & -1 & 0 & 0 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 & 0 & 0 & 0 & -1 & 0 & 0 & 0 & +L \\ 0 & 0 & 1 & 0 & 0 & 0 & 0 & 0 & -1 & 0 & -L & 0 \\ 0 & 0 & 0 & 1 & 0 & 0 & 0 & 0 & 0 & -1 & 0 & 0 \\ 0 & 0 & 0 & 0 & 1 & 0 & 0 & 0 & 0 & 0 & -1 & 0 \\ 0 & 0 & 0 & 0 & 0 & 1 & 0 & 0 & 0 & 0 & 0 & -1 \end{bmatrix} \begin{Bmatrix} V_{x1} \\ V_{y1} \\ V_{z1} \\ M_{x1} \\ M_{y1} \\ M_{z1} \\ V_{x2} \\ V_{y2} \\ V_{z2} \\ M_{x2} \\ M_{y2} \\ M_{z2} \end{Bmatrix}$$

The sign convention associated with this 12 x 12 stiffness matrix is defined in Figure 4.

Figure 4. Flex pivot sign convention.

Formulation of System Mass Matrix

The kinetic energy of the flex pivot suspension system shown in Figure 5 is

Figure 5. Flex pivot displacement detail.

$$\begin{aligned}
 KE = & \frac{1}{2} M \dot{x}^2 + \frac{1}{2} M (\dot{y} + x_0 \dot{\theta}_z)^2 + \frac{1}{2} M (\dot{z} - x_0 \dot{\theta}_y)^2 \\
 & + \frac{1}{2} J_x \dot{\theta}_x^2 + \frac{1}{2} J_y \dot{\theta}_y^2 + \frac{1}{2} J_z \dot{\theta}_z^2
 \end{aligned}$$

The non-zero terms of the 6x6 mass matrix are

$$m_{11} = \frac{\partial^2 KE}{\partial \dot{x}^2} = M$$

$$m_{22} = \frac{\partial^2 KE}{\partial \dot{y}^2} = M$$

$$m_{33} = \frac{\partial^2 KE}{\partial \dot{z}^2} = M$$

$$m_{44} = \frac{\partial^2 KE}{\partial \dot{\theta}_x^2} = J_x$$

$$m_{55} = \frac{\partial^2 KE}{\partial \dot{\theta}_y^2} = J_y + Mx_o^2$$

$$m_{66} = \frac{\partial^2 KE}{\partial \dot{\theta}_z^2} = J_z + Mx_o^2$$

$$m_{26} = m_{62} = \frac{\partial^2 KE}{\partial y \partial \dot{\theta}_z} = Mx_o$$

$$m_{35} = m_{53} = \frac{\partial^2 KE}{\partial z \partial \dot{\theta}_y} = -Mx_o$$

Extraction of System Natural Frequencies

The equations of motion for the elliptical flex pivot suspension system in matrix form are

$$(-\omega^2 [m] + [k]) \{u\} = \{0\}$$

Noting that the equations of motion for x translation and θ_x rotation are decoupled gives

$$f_x = \frac{1}{2\pi} \sqrt{\frac{k_{11}}{m_{11}}}$$

$$f_{\theta_x} = \frac{1}{2\pi} \sqrt{\frac{k_{44}}{m_{44}}}$$

Noting that the equations of motion for y translation and θ_z rotation are coupled gives a characteristic equation of the form

$$\begin{aligned} 0 = & \omega^4 (m_{22}m_{66} - m_{26}^2) - \omega^2 (m_{22}k_{66} + m_{66}k_{22} - 2m_{26}k_{26}) \\ & + (k_{22}k_{66} - k_{26}^2) \end{aligned}$$

for which the associated natural frequencies are

$$f_{\theta_z} = \frac{1}{2\pi} \sqrt{\frac{b - \sqrt{b^2 - 4ac}}{2a}}$$

$$f_y = \frac{1}{2\pi} \sqrt{\frac{b + \sqrt{b^2 - 4ac}}{2a}}$$

where

$$a = m_{22}m_{66} - m_{26}^2$$

$$b = m_{22}k_{66} + m_{66}k_{22} - 2m_{26}k_{26}$$

$$c = k_{22}k_{66} - k_{26}^2$$

Noting that the equations of motion for z translation and θ_y rotation are coupled gives a characteristic equation of the form

$$0 = \omega^4(m_{33}m_{55} - m_{35}^2) - \omega^2(m_{33}k_{55} + m_{55}k_{33} - 2m_{35}k_{35}) + (k_{33}k_{55} - k_{35}^2)$$

for which the associated natural frequencies are

$$f_{\theta_y} = \frac{1}{2\pi} \sqrt{\frac{b - \sqrt{b^2 - 4ac}}{2a}}$$

$$f_z = \frac{1}{2\pi} \sqrt{\frac{b + \sqrt{b^2 - 4ac}}{2a}}$$

where

$$a = m_{33}m_{55} - m_{35}^2$$

$$b = m_{33}k_{55} + m_{55}k_{33} - 2m_{35}k_{35}$$

$$c = k_{33}k_{55} - k_{35}^2$$

Allowable Offset and Dither for Infinite Life

The allowable offset and dither for infinite fatigue life can be obtained using the modified Goodman diagram shown below.

Figure 6. Modified Goodman diagram.

where

σ = mean stress

$\Delta\sigma$ = alternating stress

F_{tu} = ultimate tensile stress

This curve can be expressed in the form

$$\frac{3\sigma}{2F_{tu}} + \frac{3\Delta\sigma}{F_{tu}} = 1$$

Since flexure tilt is proportional to bending stress, the above expression can be recast in the form

$$\theta + 2\Delta\theta = \frac{2}{3} \theta_o$$

where

θ = mean angular offset

$\Delta\theta$ = angular dither

$$\theta_o = \pi/4 r_l^2 F_{tu} s_{55}$$

APPENDIX A
PROGRAM LISTING

FLXPVT

```

5 PRINT "FREQUENCIES, STRESSES, AND STIFFNESS MATRICES FOR"
10 PRINT "ELLIPTICAL FLEX PIVOTS"
15 PRINT
20 DIM A(6,12),K(12,12),M(6,6),B(6,12),C(12,6)
25 MAT A=ZER(6,6)
30 MAT K=ZER(6,6)
35 PO=3.1415927
40 READ L,RO,RI,E,G,W,I1,I2,I3,XO
45 PRINT "FLEX PIVOT LENGTH L, IN ="L
50 PRINT "FLEX PIVOT BASE RADIUS RO, IN ="RO
55 PRINT "FLEX PIVOT THROAT RADIUS RI, IN ="RI
60 PRINT "FLEX PIVOT ELASTIC MODULUS E, PSI ="E
65 PRINT "FLEX PIVOT SHEAR MODULUS G, PSI ="G
70 PRINT "FLEX PIVOT SUSPENDED WEIGHT W, LBS ="W
75 PRINT "FLEX PIVOT SUSPENDED X WEIGHT ROTARY INERTIA IX, LB-IN+2 ="I1
80 PRINT "FLEX PIVOT SUSPENDED Y WEIGHT ROTARY INERTIA IY, LB-IN+2 ="I2
85 PRINT "FLEX PIVOT SUSPENDED Z WEIGHT ROTARY INERTIA IZ, LB-IN+2 ="I3
90 PRINT "FLEX PIVOT SUSPENDED WEIGHT C.G. OFFSET XO, IN ="XO
95 AO=L/2
100 BO=RO-RI
105 N=100
110 FOR X=L/N TO L STEP L/N
115 R=RO-BO*SQR(1-((X-AO)/AO)^2)
120 A=P0*R^2
125 I=A*R^2/4
130 A(1,1)=A(1,1)+L/N/E/A
135 A(2,2)=A(3,3)=A(2,2)+L/N*X^2/E/I
140 A(5,5)=A(6,6)=A(5,5)+L/N/E/I
145 A(2,6)=A(6,2)=A(2,6)+L/N*X/E/I
150 NEXT X
155 A(2,2)=A(3,3)=A(2,2)+1.12*E/G*A(1,1)
160 A(4,4)=E/G/2*A(5,5)
165 A(3,5)=A(5,3)=-A(2,6)
170 MAT K=INV(A)
175 M(1,1)=M(2,2)=M(3,3)=W/386
180 M(4,4)=11/386
185 M(5,5)=(12+W*XO^2)/386
190 M(6,6)=(13+W*XO^2)/386
195 M(2,6)=M(6,2)=W*XO/386
200 M(3,5)=M(5,3)=-W*XO/386
205 A2=M(2,2)*M(6,6)-M(2,6)^2
210 A3=M(3,3)*M(5,5)-M(3,5)^2
215 B2=M(2,2)*K(6,6)+M(6,6)*K(2,2)-2*M(2,6)*K(2,6)
220 B3=M(3,3)*K(5,5)+M(5,5)*K(3,3)-2*M(3,5)*K(3,5)
225 C2=K(2,2)*K(6,6)-K(2,6)^2
230 C3=K(3,3)*K(5,5)-K(3,5)^2
235 C2=SQR(B2+2-4*A2*C2)
240 C3=SQR(B3+2-4*A3*C3)
245 TO=1E5*PO/4*RI^3*A(5,5)
250 F1=1/2/PO*SQR(K(1,1)/M(1,1))

```

FLXPVT CONTINUED

```

255 F2=1/2/PO*SQR((B2+C2)/2/A2)
260 F3=1/2/PO*SQR((B3+C3)/2/A3)
265 F4=1/2/PO*SQR(K(4,4)/M(4,4))
270 F5=1/2/PO*SQR((B3-C3)/2/A3)
275 F6=1/2/PO*SQR((B2-C2)/2/A2)
280 PRINT
285 PRINT "FLEX PIVOT X TRANSLATION FREQUENCY, HZ ="F1
290 PRINT
295 PRINT "FLEX PIVOT Y TRANSLATION FREQUENCY, HZ ="F2
300 PRINT
305 PRINT "FLEX PIVOT Z TRANSLATION FREQUENCY, HZ ="F3
310 PRINT
315 PRINT "FLEX PIVOT X ROTATION FREQUENCY, HZ ="F4
320 PRINT
325 PRINT "FLEX PIVOT Y ROTATION FREQUENCY, HZ ="F5
330 PRINT
335 PRINT "FLEX PIVOT Z ROTATION FREQUENCY, HZ ="F6
340 PRINT
345 PRINT "ALLOWABLE OFFSET AND DITHER FOR INFINITE LIFE"
350 PRINT "ASSUMING 100 KSI UTS MATERIAL"
355 PRINT
360 PRINT "OFFSET-RAD","DITHER-RAD"
365 PRINT
370 FOR I=0 TO 2*TO/3 STEP .2*TO/3
375 PRINT I,TO/3-I/2
380 NEXT I\PRINT
385 PRINT "SECTION PROPERTIES FOR EQUIVALENT 8 ELEMENT STARDYNE MODEL"
390 PRINT
395 PRINT "ELEMENT","A","J","I2=I3","K2=K3"
400 PRINT\R3=R0
405 FOR X=L/8 TO L/2 STEP L/8
410 R=R0-B0*SQR(1-((X-A0)/A0)^2)
415 R4=(2*R+R3)/3
420 R3=R
425 A=PO*R4+2
430 I=A*R4+2/4
435 PRINT 8*X/L;"-";I+8*(1-X/L);A,2*I,I,"0.89"
440 NEXT X\PRINT
445 MAT B=ZER(6,12)
450 B(1,1)=B(2,2)=B(3,3)=B(4,4)=B(5,5)=B(6,6)=1
455 B(1,7)=B(2,8)=B(3,9)=B(4,10)=B(5,11)=B(6,12)=-1
460 B(2,12)=L
465 B(3,11)=-L
470 MAT A=ZER(6,12)
475 MAT A=K*B
480 MAT C=ZER(12,6)
485 MAT C=TRN(B)
490 MAT K=ZER(12,12)
495 MAT K=C*A
500 PRINT

```

FLXPVT CONTINUED

```
505 PRINT "THE 12 X 12 FLEX PIVOT STIFFNESS MATRIX IS:"  
510 PRINT  
515 MAT PRINT K  
520 GOTO 575  
525 DATA .625  
530 DATA .256  
535 DATA .1445  
540 DATA 17E6  
545 DATA 6.51E6  
550 DATA 41.36  
555 DATA 1274.4  
560 DATA 458.4  
565 DATA 859.1  
570 DATA .3125  
575 END
```

APPENDIX H
SERVO MIRRORS CROSS COUPLING

APPENDIX H. SERVO MIRRORS CROSS COUPLING

This Appendix describes cross coupling in angle and translation beam control systems which utilize steering mirrors.

OPERATIONAL CHARACTERISTICS

Figure H-1 shows a simplified schematic of the steering mirror control system. Mirror A is utilized primarily to control transverse motion at the reference (sensor) plane and Mirror B is utilized primarily to control angle at the reference plane. The so called cross coupling comes about because of the attempt to utilize only one mirror for each function.

Figure H-2 is a servo block diagram of the measurement chain of one axis for a beam angle and transverse control system. This diagram will also be used to generate the servo block diagram. Table H-1 lists the symbols used in Figure H-2. The dotted lines in Figure H-2 enclose that part of the servo for which a measurement is made of angle only. Figure H-2 can be used to determine the necessary bandwidth needed for the servos.

The sources of servo disturbances illustrated in Figure H-2, have been lumped together into three power spectral densities (PSD): (1) an angular vibration power spectral density, (2) a translational vibration power spectral density, and (3) an acoustic pressure power spectral density. A

Figure H-1. Simplified schematic of angle and transverse beam control system

Figure H-2. Error measurement chain

simple calculation based on the above PSDs can indicate the required bandwidth.

The error from torque disturbance, T_D , is given by

$$\theta_{\epsilon} \approx \frac{T_D \sqrt{R} K_{\theta}}{\omega_B^2}$$

$$X_{\epsilon} \approx \frac{T_D \sqrt{R} K_x}{\omega_A}$$

where: ω_A = loop bandwidth for servo A

ω_B = loop bandwidth for servo B

R = lead ratio of Type II servo (optimum $\approx 2, 4$)

Table H-1. List of symbols

α_M	=	Measured angular error
Y_M	=	Measured translation error
α_1	=	Position of the mirror A
α_2	=	Position of mirror B
T_{C1}	=	Torque command to A
T_{C2}	=	Torque command to B
T_{D1}	=	Torque disturbance to A
T_{D2}	=	Torque disturbance to B
α_R	=	Angle disturbance of the reference package
Y_R	=	Translation disturbance of the reference package
Y_1	=	Translation disturbance of A
Y_2	=	Translation disturbance of B
$\partial\alpha_M/\partial\alpha_2$	=	Optical angle gain for angular motions of B
$\partial\alpha_M/\partial\alpha_1$	=	Optical angle gain for angular motions of A
$\partial Y_M/\partial\alpha_2$	=	Optical translation gain for angular motions of B
$\partial Y_M/\partial\alpha_1$	=	Optical translation gain for angular motions of A
$\partial\alpha_M/\partial\alpha_R$	=	Optical angle gain for angular motions of reference
$\partial Y_M/\partial\alpha_R$	=	Optical translation gain for angular motion of reference
$\partial Y_M/\partial Y_R$	=	Optical translation gain for translations of reference
$\partial Y_M/\partial Y_1$	=	Optical translation gain for translations of A
$\partial Y_M/\partial Y_2$	=	Optical translation gain for translations of B

$$K_{\theta} = \frac{\text{angular error}}{\text{mirror angle}}$$

$$K_x = \frac{\text{transverse error}}{\text{mirror angle}}$$

These relationships define the bandwidth requirements for the servos. It should be noted that servo bandwidth is directly related to servo gain for correcting of torque disturbances.

SYSTEM ARCHITECTURE AND COMPONENTS

The key feature of the system architecture is that the intersensor and interaxis sources of crosscoupling are compensated for by the signal processing and the choice of drive axes for mirror A and mirror B.

The sources of intersensor cross coupling is schematically shown in Figure H-2. In this diagram, note that if the angle error signal α_M is solely used to generate the drive signal for mirror B (i.e. at the exclusion of Y_M), then motion of B will generate a Y_M error signal. In the same manner, if Y_M exclusively is used to generate the drive signal for mirror A (i.e. T_{CI}), then the resultant motion of A (i.e. α_1) generates an angle error. This cross coupling is acceptable based on the preceding error analysis if loop stability can be maintained.

Stability can be guaranteed with two different servo design approaches. The first approach is to modify the drive signals by inclusion of a feedforward terms from the complementary loop. The intent here is to undo the cross coupling. The amount of feedforward needed can easily be calculated by forming a matrix of the feedback terms as indicated

$$\begin{bmatrix} \alpha_M \\ Y_M \end{bmatrix} = \begin{bmatrix} \partial \alpha_M / \partial \alpha_1 & \partial \alpha_M / \partial \alpha_2 \\ \partial Y_M / \partial \alpha_1 & \partial Y_M / \partial \alpha_2 \end{bmatrix} \begin{bmatrix} \alpha_1 \\ \alpha_2 \end{bmatrix} = A \begin{bmatrix} \alpha_1 \\ \alpha_2 \end{bmatrix}$$

The feedforward gains are just the elements of A^{-1} . Now the modified error signals are given by

$$\begin{bmatrix} \alpha M^* \\ Y_{M^*} \end{bmatrix} = A^{-1} \begin{bmatrix} \alpha M \\ Y_M \end{bmatrix} = A^{-1} A \begin{bmatrix} \alpha_1 \\ \alpha_2 \end{bmatrix} = \begin{bmatrix} \alpha_1 \\ \alpha_2 \end{bmatrix}$$

This form of processing is termed feedback decoupling. The signal processing done is effectively an observer of the servo outputs. The problem with this scheme is that the dynamics of A and B must be matched well to achieve high bandwidths for the angle loop.

The second approach is to not include the feed forward terms, and to separate the bandwidths of the angle and translation loops. With this scheme, the servo block diagram for the angle loop is given in Figure H-3.

Figure H-3. Angle servo block diagram — no decoupling

Note that in Figure H-3, the closed loop dynamics of the complementary loop is in the feedback path. If it is assumed that the angle loop bandwidth is higher than the translation loop bandwidth, then Figure H-4 represents a simplified Bode diagram of the angle loop open loop response.

Figure H-4. Angle loop frequency response

Note the poles and zeros of the translation loop have a stabilizing effect on the response at the expense of a small amount of error rejection.

Similarly, the translation loop frequency response is plotted in Figure H-5. Note here that the effect of the angle loop dynamics is destabilizing. However, since the loop gain does not have to be high for this loop sufficient gain margin can be achieved so that the system remains stable.

Note that in the above discussion that it has been tacitly assumed that the mirror A would be used as the driver mirror for the translation zero. The reason for this is to maximize the distance from the sensor to the translation steering mirror in order to reduce the required dynamic range to steer out a translation error.

The second type of cross coupling accounted for is interaxis cross coupling. This cross coupling arises from the fact that the natural drive axes of the steering mirrors are their major and minor diameters. The sensors will sense angle and translation errors about two orthogonal axes. If these axes are projected along the optical axis back to the reference surface, the image of the projection on the reference surface will be a pair of perpendicular lines. The optical axes of the sensors can be rotated so that the lines in the image on the reference surface are vertical and horizontal. In this case,

Figure H-5. Translation loop frequency response

the projection of the sensor axes on to the surface of mirror A will also form an orthogonal set, and these two lines are the desired axes of rotation. Fortunately, these lines are parallel to the A mirror major and minor diagonals. Hence, the desired drive axes and the natural drive axes are aligned. However, the projection of the sensor axes onto B mirror are neither orthogonal nor are they aligned with the natural drive axes of the mirror. In fact, no orientation of the sensor axes will result in simultaneously having orthogonal drive axes on both mirrors. Hence, the case chosen is the best attainable. Figure H-6 is a sketch of the drive axes on the elliptical B mirror. In order to drive the mirror about its normal axes and have it respond about the desired axis, a decoding matrix must be used to condition the drive signals as shown in Figure H-7.

Finally, Figure H-8 is a simplified block diagram of the servo including the necessary encoding matrices and internal loops. Table H-20 is a list of symbols for Figure H-8. In Figure H-8, the dotted lines enclose the angle-only servo.

Figure H-6. B Mirror drive axis locations

Figure H-7. Drive encoding matrix

H-9

Figure H-8. Simplified block diagram of servo

Table H-2. Symbols used in Figure H-8

G_{CP1} H_{CP1} G_{CP2} H_{CP2}	}	Position loop compensation
G_{C1} H_{C1} G_{C2} H_{C2}	}	Current loop feedback gain
$J_{\alpha 1}$ $J_{\beta 1}$	}	B inertia
$J_{\alpha 2}$ $J_{\beta 2}$	}	A inertia
α_1 β_1 α_2 β_2	}	Mirror positions
$\partial\theta\alpha/\partial\alpha_1$ $\partial\theta\alpha/\partial\alpha_2$ $\partial\theta\beta/\partial\beta_1$ $\partial\theta\beta/\partial\beta_2$	}	Optical loop feedback gains
$\theta C\alpha$ $\theta C\beta$ $X C\alpha$ $X C\beta$	}	Loop inputs

APPENDIX I
OPTICAL MISALIGNMENT ANALYSIS

APPENDIX I. OPTICAL MISALIGNMENT ANALYSIS

Each of the 20 laser beams is provided with an automatic optical alignment system that directs the laser energy precisely onto the target. Each alignment system employs a pair of two-axis steerable mirrors that function together to correct both translational and rotational misalignments of the laser beam.

The implementation of the alignment mirror servos requires a detailed understanding of the kinematic relationships between the many possible optical system misalignments and the detector error signals. The purpose of this study is to develop mathematical expressions for the detector error signals as functions of the system misalignments. The resulting equations express the sensitivity of the system to misalignments of the various optical elements and provide the basis for implementation of the mirror servos.

The description of the optical alignment system presented here is restricted to two-dimensional space. The extension of the concepts to three-dimensional space can be carried out in a straightforward manner.

CONFIGURATION OF OPTICAL ALIGNMENT SYSTEM

The optical configuration of the alignment system is illustrated schematically in Figure I-1. The diverging laser beam emanating from point i_0 illuminates the target chamber focusing lens. Between the laser source and the lens is a pair of steerable alignment mirrors that operate together to correct both translational and rotational misalignments of the beam. The first pointing mirror corrects the translational misalignment, and the second pointing mirror corrects the rotational misalignment.

The target chamber lens focuses the incoming beam to an image at point i_1 . The spherical mirror (ball) intercepts the focused beam and reflects it back onto the target chamber lens. The ball produces a virtual image at point i_2 . The target chamber lens then directs the outgoing beam onto the alignment mirrors and produces an image at point i_3 . The beam is therefore reflected from the alignment mirrors in both the incoming and outgoing portions of its path.

l_0

LASER SOURCE

l_0

l_3

QUAD
DETECTOR

l_4

NOT TO SCALE

l_8

l_9

l_6

2

Figure I-1. Optical system configuration

The detector lens intercepts the converging beam and focuses it on the quadrant detector at point i_4 . The quadrant detector provides a measure of the beam pointing error. The detector signal is used to drive the alignment mirror servo.

DEFINITION OF NOMINAL GEOMETRY

When all misalignments are zero, the resulting system configuration is referred to as the nominal system geometry. The misalignments are regarded as perturbations about the nominal geometry.

The locations of optical images relative to the various reflecting and refracting surfaces of the optical system are part of the nominal system geometry. The image locations are found by applying the appropriate lens and mirror formulas. Since the misalignment analysis considers only perturbations about the nominal geometry it does not deal with the lens and mirror formulas directly.

The nominal geometry is summarized in Table I-1. The distances listed in the table are defined in Figure I-1.

When all misalignments are zero, the central ray of the laser beam traces a path through the system optics called the nominal optical axis. Translational and rotational misalignments of the beam and of the optical surfaces are measured relative to the nominal optical axis.

SIMPLIFIED OPTICAL THEORY FOR ALIGNMENT SYSTEM ANALYSIS

A simplified optical theory is adequate for the analysis of the optical alignment system. This theory involves the following assumptions:

1. The lenses can be regarded as thin. Therefore translational misalignments of the laser beam at each lens can be measured along an axis through the center of the lens and normal to the nominal optical axis.
2. Lens and mirror aberrations can be ignored.

Table I-1. Summary of nominal
system geometry

l_0	= 151.14 m
l_1	= 1.76 m
l_2	= 7.10 m
l_3	= 39.650 cm
l_4	= 39.573 cm
l_5	= 39.959 cm
l_6	= 38.84 m
l_7	= 11.14 m
l_8	= 50.00 cm
l_9	= 18.84 m
R	= 1 mm

Distances are defined in Figure I-1.

3. The laser beam can be diverging, converging, or collimated as it passes through various portions of the system optics. In any case the misalignment of the beam can be specified by dealing only with the central ray of the beam. The misalignment analysis is therefore reduced to the problem of tracing the path of the central ray through the optical train.

MISALIGNMENT NOMENCLATURE

Since many misalignments must be identified, an organized system of notation is helpful. The following general rules are applied in the nomenclature.

Each optical element is identified by a number as follows:

- ① Translational alignment mirror (incoming beam)
- ② Rotational alignment mirror (incoming beam)
- ③ Target chamber focusing lens (incoming beam)
- ④ Ball
- ⑤ Target chamber focusing lens (outgoing beam)
- ⑥ Rotational alignment mirror (outgoing beam)
- ⑦ Translational alignment mirror (outgoing beam)
- ⑧ Detector lens

Translational misalignments of the central ray measured at each optical surface are denoted by the general symbol Δ_i where i is an integer that identifies the surface according to the list given above.

Rotational misalignments of the central ray at a point between two optical surfaces are denoted by the general symbol δ_i where i is an integer that identifies the surface from which the ray has come.

Translational misalignments of the lenses are denoted by the general symbol Δ_{li} where i is an integer that identifies the surface. Since the integer pairs (1, 7), (2, 6), and (3, 5) refer to the same surfaces the lower number will be used in each case to avoid duplication in the notation.

At each place where the beam is focused to an image point (real or virtual) the general symbol h_i is used to denote the deviation of the image point (and of the central ray) from the nominal optical axis. The subscript i refers to the surface that forms the image.

Two additional symbols not included in the general notation described above are defined as follows:

Δ_c = translation of center of ball relative to nominal optical axis

Δ_d = translation of quadrant error detector relative to nominal optical axis

All translational and rotational misalignments are measured relative to the nominal optical axis. Translational misalignments are regarded as positive if they are above the axis and negative if they are below the axis. Rotational misalignments are considered positive in the counterclockwise direction.

The deflection angles of the steerable alignment mirrors are denoted as follows:

δ_{m1} = deflection angle of translational alignment mirror

δ_{m2} = deflection angle of rotational alignment mirror

The mirror angles are positive in the counterclockwise direction.

DERIVATION OF MISALIGNMENT EQUATIONS

The purpose of this section is to derive the mathematical relationships between the misalignment quantities for the various optical surfaces. In each case the translational and rotational misalignments of the central ray on the output side of the surface are expressed as functions of the translational and rotational misalignments on the input side of the surface. In some cases an expression is also derived for the image point deviation from the nominal optical axis.

Translational and Rotational Alignment Mirrors (Incoming Beam)

A diagram showing the geometry of the steerable alignment mirrors is given in Figure I-2. The translational and rotational misalignments of the laser sources are denoted by Δ_0 and δ_0 , respectively. The misalignment quantities pertaining to mirror ① are

$$\Delta_1 = \Delta_0 + \ell_0 \delta_0 \quad (I-1)$$

$$\delta_1 = -\delta_0 + 2\delta_{m1}$$

The misalignment quantities pertaining to mirror ② are

$$\Delta_2 = \Delta_1 - \ell_1 \delta_1 \quad (I-2)$$

$$\delta_2 = -\delta_1 + 2\delta_{m2}$$

Figure I-2. Geometry of alignment mirrors
(incoming beam)

The translational misalignment at surface ③ is

$$\Delta_3 = \Delta_2 + l_2 \delta_2 \quad (I-3)$$

Eqs. (I-1), (I-2), and (I-3) can be combined to give

$$\begin{aligned} \delta_2 &= \delta_0 - 2 \delta_{m1} + 2 \delta_{m2} \\ \Delta_3 &= \Delta_0 + (l_0 + l_1 + l_2) \delta_0 - 2(l_1 + l_2) \delta_{m1} + 2 l_2 \delta_{m2} \end{aligned} \quad (I-4)$$

Target Chamber Focusing Lens (Incoming Beam)

The geometry of the target chamber focusing lens (surface ③) is shown in Figure I-3. The image h_2 shown at the left side of the diagram is the virtual image formed by surface ②. This image can be expressed as a function of δ_2 and Δ_3

$$h_2 = \Delta_3 - (\ell_0 + \ell_1 + \ell_2) \delta_2 \quad (I-5)$$

The image h_3 formed by surface ③ is related to h_2 by

$$\frac{-(h_3 - \Delta_3)}{h_2 - \Delta_3} = \frac{\ell_3}{\ell_0 + \ell_1 + \ell_2} \quad (I-6)$$

Figure I-3. Geometry of target chamber focusing lens (incoming beam)

Solving Eq. (I-6) for h_3 gives

$$h_3 = -\frac{\ell_3}{\ell_0 + \ell_1 + \ell_2} h_2 + \left(1 + \frac{\ell_3}{\ell_0 + \ell_1 + \ell_2}\right) \Delta \ell_3 \quad (I-7)$$

Substituting Eq. (I-5) into Eq. (I-7) gives

$$h_3 = -\frac{\ell_3}{\ell_0 + \ell_1 + \ell_2} \Delta_3 + \ell_3 \delta_2 + \left(1 + \frac{\ell_3}{\ell_0 + \ell_1 + \ell_2}\right) \Delta \ell_3 \quad (I-8)$$

The rotational misalignment δ_3 can be expressed in terms of Δ_3 and h_3

$$\delta_3 = \frac{h_3 - \Delta_3}{3} \quad (I-9)$$

Substituting Eq. (I-8) into Eq. (I-9) gives

$$\delta_3 = -\left(\frac{1}{\ell_3} + \frac{1}{\ell_0 + \ell_1 + \ell_2}\right) \Delta_3 + \delta_2 + \left(\frac{1}{\ell_3} + \frac{1}{\ell_0 + \ell_1 + \ell_2}\right) \Delta \ell_3 \quad (I-10)$$

Ball

The geometry of the ball is shown in Figure I-4. The incident central ray and the reflected central ray both make an angle ϕ relative to the normal to the surface of the ball. The normal to the surface at the point of incidence of the central ray makes an angle δ_c relative to the nominal optical axis.

The translational misalignment Δ_4 is expressed as

$$\Delta_4 = \Delta_3 + \ell_4 \delta_3 \quad (I-11)$$

The angle of incidence (or reflection) can be expressed as

$$\phi = \delta_4 - \delta_c = \delta_c - \delta_3 \quad (I-12)$$

Solving Eq. (I-12) for δ_4 gives

$$\delta_4 = -\delta_3 + 2\delta_c \quad (I-13)$$

Figure I-4. Geometry of ball

The misalignment δ_c can be written as

$$\delta_c = - \frac{\Delta_4 - \Delta_c}{R} \quad (I-14)$$

where Δ_c is the translational misalignment of the ball. The distance Δ_c is not shown in Figure I-4 to avoid cluttering the diagram. Substituting Eq. (I-14) into Eq. (I-13) gives

$$\delta_4 = -\delta_3 + \frac{2}{R} (\Delta_c - \Delta_4) \quad (I-15)$$

Substituting Eq. (I-11) into Eq. (I-15) gives

$$\delta_4 = -\frac{2}{R} \Delta_3 + \frac{2}{R} \Delta_c - \left(\frac{2 \ell_4}{R} + 1 \right) \delta_3 \quad (I-16)$$

The virtual image h_4 formed by the ball is

$$h_4 = \Delta_4 + (\ell_5 - \ell_4) \delta_4 \quad (I-17)$$

The distance Δ_5 at which the outgoing central ray intercepts the target chamber focusing lens (surface ⑤) is

$$\Delta_5 = \Delta_4 - \ell_4 \delta_4 \quad (I-18)$$

Target Chamber Focusing Lens (Outgoing Beam)

The geometry of the target chamber focusing lens for the outgoing beam (surface ⑤) is shown in Figure I-5. The image h_5 is related to h_4 by

$$\frac{-(h_5 - \Delta_{l3})}{h_4 - \Delta_{l3}} = \frac{\ell_6}{\ell_5} \quad (I-19)$$

Substituting Eqs. (I-18) and (I-21) into Eq. (I-22) gives

$$\delta_5 = \left(\frac{1}{\ell_5} + \frac{1}{\ell_6} \right) \Delta_4 + \left(1 - \frac{\ell_4}{\ell_5} - \frac{\ell_4}{\ell_6} \right) \delta_4 - \left(\frac{1}{\ell_5} + \frac{1}{\ell_6} \right) \Delta_{\ell_3} \quad (\text{I-23})$$

Translational and Rotational Alignment Mirrors (Outgoing Beam)

The geometry of the steerable alignment mirrors is shown in Figure I-6 for the outgoing beam. The misalignment quantities pertaining to surface ⑥ are

$$\Delta_6 = \Delta_5 + \ell_2 \delta_5 \quad (\text{I-24})$$

$$\delta_6 = -\delta_5 + 2 \delta_{m2}$$

The misalignment quantities pertaining to surface ⑦ are

$$\Delta_7 = \Delta_6 + \ell_1 \delta_6 \quad (\text{I-25})$$

$$\delta_7 = -\delta_6 + 2 \delta_{m1}$$

The translational misalignment at the detector lens (surface ⑧) is

$$\Delta_8 = \Delta_7 - \ell_7 \delta_7 \quad (\text{I-26})$$

Eqs. (I-24) and (I-25) can be combined to give

$$\Delta_7 = \Delta_5 - (\ell_1 + \ell_2) \delta_5 + 2 \ell_1 \delta_{m2} \quad (\text{I-27})$$

$$\delta_7 = \delta_5 - 2 \delta_{m2} + 2 \delta_{m1}$$

NOA = NOMINAL OPTICAL AXIS

Figure I-6. Geometry of alignment mirrors (outgoing beam)

Detector Lens

The geometry of the detector focusing lens is shown in Figure I-7. The rays coming from the right side of the lens are converging toward an image point designated h_7 on the diagram. The interposition of the detector lens causes the rays to be focused to a new image point designated h_8 . The image distance h_7 is given by

$$h_7 = \Delta_8 - \ell_9 \delta_7 \quad (I-28)$$

Figure I-7. Detector focusing lens

The image distance h_8 is related to h_7 by

$$\frac{h_8 - \Delta_{l8}}{h_7 - \Delta_{l8}} = \frac{l_8}{l_9} \quad (I-29)$$

Solving Eq. (I-29) for h_8 gives

$$h_8 = \frac{l_8}{l_9} h_7 + \left(1 - \frac{l_8}{l_9}\right) \Delta_{l8} \quad (I-30)$$

Substituting Eq. (I-28) into Eq. (I-30) gives

$$h_8 = \frac{l_8}{l_9} \Delta_{l8} - l_8 \delta_7 + \left(1 - \frac{l_8}{l_9}\right) \Delta_{l8} \quad (I-31)$$

The rotational misalignment δ_8 can be expressed as

$$\delta_8 = \frac{\Delta_{l8} - h_8}{l_8} \quad (I-32)$$

Substituting Eq. (I-31) into Eq. (I-32) gives

$$\delta_8 = \left(\frac{1}{\ell_8} - \frac{1}{\ell_9} \right) \Delta_8 + \delta_7 - \left(\frac{1}{\ell_8} - \frac{1}{\ell_9} \right) \Delta_{\ell 8} \quad (\text{I-33})$$

Quadrant Error Detector

The quadrant error detector is mounted on the same assembly as the detector lens. Consequently, its misaligned position can be expressed in terms of the misalignments of the detector lens as shown in Figure I-8. The translational and rotational misalignments of the lens are denoted by $\Delta_{\ell 8}$ and $\delta_{\ell 8}$, respectively. Therefore the deviation of the detector from the nominal optical axis is

$$\Delta_d = \Delta_{\ell 8} - \ell_8 \delta_{\ell 8} \quad (\text{I-34})$$

Figure I-8. Quadrant detector misalignment

OVERALL SYSTEM MODEL AND DETECTOR ERROR EQUATIONS

Overall System Model

The equations derived in the previous section provide an overall mathematical description of the optical alignment system. There are many ways in which these equations can be combined to produce a system block diagram. In any case the block diagram will have the form shown in Figure I-9. The actual system pointing error (expressing the deviation of the focused laser beam from the target) is defined by

$$\epsilon_1 = h_3 - \Delta_c \quad (\text{I-35})$$

where h_3 is given by Eq. (I-8), and Δ_c is the translational misalignment of the ball normal to the nominal optical axis. The actual system centering

Figure I-9. Optical alignment system

error (expressing the translational misalignment of the beam measured at the target chamber focusing lens) is defined by

$$\epsilon_2 = \Delta_3 - \Delta_{\ell 3} \quad (\text{I-36})$$

where Δ_3 is given by Eq. (I-3) or Eq. (I-4), and $\Delta_{\ell 3}$ is the translational misalignment of the lens normal to the nominal optical axis. The measured system pointing error (expressing the misalignment measured by the quadrant error detector) is defined by

$$\epsilon_3 = h_8 - \Delta_d \quad (\text{I-37})$$

where h_8 is given by Eq. (I-31) and Δ_d is the translational misalignment of the detector given by Eq. (I-34).

An expanded block diagram expressing ϵ_1 , ϵ_2 , and ϵ_3 as functions of the system misalignment quantities is given in Figure I-10. This diagram is based specifically on Eqs. (I-1), (I-2), (I-3), (I-8), (I-10), (I-11), (I-16), (I-17), (I-18), (I-23), (I-24), (I-25), (I-26), (I-31), (I-33), (I-34), (I-35), (I-36), and (I-37).

Each of the alignment error quantities, ϵ_1 , ϵ_2 , and ϵ_3 on the right side of the diagram of Figure I-9 can be related to the misalignment quantities on the left side of the diagram by a set of coefficients α_{ij} . The specific equations are

$$\begin{aligned} \epsilon_1 &= \alpha_{11}\Delta_0 + \alpha_{12}\delta_0 + \alpha_{13}\Delta_{\ell 3} + \alpha_{14}\Delta_c + \alpha_{15}\Delta_{\ell 8} + \alpha_{16}\delta_{\ell 8} \\ &\quad + \alpha_{17}\delta_{m1} + \alpha_{18}\delta_{m2} \\ \epsilon_2 &= \alpha_{21}\Delta_0 + \alpha_{22}\delta_0 + \alpha_{23}\Delta_{\ell 3} + \alpha_{24}\Delta_c + \alpha_{25}\Delta_{\ell 8} + \alpha_{26}\delta_{\ell 8} \\ &\quad + \alpha_{27}\delta_{m1} + \alpha_{28}\delta_{m2} \\ \epsilon_3 &= \alpha_{31}\Delta_0 + \alpha_{32}\delta_0 + \alpha_{33}\Delta_{\ell 3} + \alpha_{34}\Delta_c + \alpha_{35}\Delta_{\ell 8} + \alpha_{36}\delta_{\ell 8} \\ &\quad + \alpha_{37}\delta_{m1} + \alpha_{38}\delta_{m2} \end{aligned} \quad (\text{I-38})$$

Table I-2. Misalignment coefficients

		Translation of Source	Rotation of Source, Meters	Translation of Target Chamber Focusing Lens	Translation of Ball	Translation of Detector Lens	Rotation of Detector Lens, Meters	Alignment Mirror Angle, Meters	Alignment Mirror Angle, Meters
Actual Pointing Error	ϵ_1	-0.2478×10^{-2}	0	0.1002×10^1	-1	0	0	-0.7491×10^0	0.7578×10^0
Actual Centering Error	ϵ_2	1	0.1600×10^3	-1	0	0	0	-0.1772×10^2	0.1420×10^2
Measured Pointing Error	ϵ_3	-0.3447×10^{-1}	0.1343×10^1	0.1995×10^2	-0.1988×10^2	-0.2655×10^{-1}	0.5060×10^0	-0.1470×10^2	0.1491×10^2
Scaled Measured Pointing Error	ϵ'_3	-0.1733×10^{-2}	0.6755×10^{-1}	0.1003×10^1	-1	-0.1335×10^{-2}	0.2514×10^{-1}	-0.7391×10^0	0.7499×10^0
Inter-mensual Error	$\epsilon_1 - \epsilon'_3$	-0.7448×10^{-3}	-0.6755×10^{-1}	-0.5903×10^{-3}	0	0.1335×10^{-2}	-0.2514×10^{-1}	-0.9992×10^{-2}	0.7915×10^{-2}

$$\epsilon'_3 = \frac{-1}{-19.88} \epsilon_3 = 0.05029 \epsilon_3$$

Figure I-10. Optical alignment system block diagram

Numerical values for the α coefficients can be calculated using the relationships expressed in the block diagram of Figure I-10 and the numerical data of Table I-1. A summary of the α coefficients is given in Table I-2. In addition to the coefficients for ϵ_1 , ϵ_2 , and ϵ_3 the table also lists the coefficients for two additional quantities, the scaled pointing error ϵ'_3 and the instrumental error $\epsilon_1 - \epsilon'_3$. These additional quantities are defined and discussed in the following paragraphs.

Scaled Pointing Error

Any system misalignment between the laser source and the target (the ball) will produce an actual pointing error at the target. The appropriate scale factors relating the individual misalignments to target error are given by the α coefficients pertaining to ϵ_1 in Table I-2. The coefficient for Δ_c has a magnitude of unity because this misalignment refers to translation of the target itself.

Similarly, any system misalignment between the laser source and the quadrant error detector will produce a measured error at the detector. The appropriate scale factors relating the individual misalignments to detector error are given by the α coefficients pertaining to ϵ_3 in Table I-2. The coefficient pertaining to Δ_c has a value of -19.88. This means that any misalignment that produces a unit error at the target will produce an error of 19.88 units at the detector. There is consequently a scale factor that can be applied to the detector signal. This scale factor is given by the ratio of the two coefficients of Δ_c .

$$\text{scale factor} = \frac{-1}{-19.88} = 0.05029 \quad (I-39)$$

The scaled pointing error ϵ'_3 is determined by multiplying ϵ_3 by the scale factor.

$$\epsilon'_3 = 0.05029 \epsilon_3 \quad (I-40)$$

The scaled pointing error provides the best available estimate of the actual error at the target. The individual α coefficients for the scaled pointing error are listed in Table I-2.

Instrumental Error

The actual pointing error at the target is ϵ_1 . The best available measurement of this pointing error is provided by the scaled measured pointing error ϵ'_3 defined by Eq. (I-40). The difference between ϵ_1 and ϵ'_3 represents that part of the pointing error that cannot be corrected by the alignment mirror servos. This residual error is called the instrumental error.

$$\text{instrumental error} = \epsilon_1 - \epsilon'_3 \quad (\text{I-41})$$

A set of α coefficients for the instrumental error is given in Table I-2. Each of the coefficients for the instrumental error is determined by taking the difference between the corresponding coefficients of ϵ_1 and ϵ'_3 .

APPENDIX J
STRESS INDUCED BIREFRIGENT
QUARTER-WAVE RETARDER

APPENDIX J. STRESS INDUCED BIREFRIGENT QUARTER-WAVE RETARDER

During one of the early technical interface meetings between Lawrence Livermore Laboratory and Hughes personnel, it was suggested that a quarter-wave retarder could be substituted for the final, 25 cm diameter Farady rotator that was, at that time, envisioned for isolation.

Hughes proposed the development of a stress induced birefringent retarder and researched the idea for enough to formulate a seven month effort which would lead to a full size prototype. The success criterion is the attainment of 23 dB attenuation with less than 1/10th-wave wavefront distortion. Subsequently, the final Farady rotator was eliminated from the Shiva design.

In the event that final stage isolation becomes a necessity and because such a device may be of use to other areas within the Lawrence Livermore Laboratory, we present in this appendix the technical output of this effort.

ADVANTAGES

The stress induced birefringent quarter-wave retarder offers many advantages over the Farady rotator as the final isolator in the Shiva system.

- It is much less expensive than the Farady rotator
- Quiescent state is the same as the activated state
- No synchronism is required
- Circularly polarized light hits the target
- No capacitor banks are required
- No magnetic or electric fields are created, thus eliminating those sources of noise

PRECURSOR TASKS TO PROTOTYPE FABRICATION

The following tasks constitute a program which culminates in the fabrication of a prototype retarder.

1. Design and fabricate a one inch, variable pressure cell for measurement of the stress-optical coefficient.
2. Design and fabricate a one inch cube of fused silica.
3. Measure the stress-optical coefficient for wavelengths in the visible and extending into the near infrared (1.06 μm minimum).
4. Design and fabricate two fused silica windows with 25 cm clear apertures.
5. Design and fabricate two pressure frames for above windows.
6. Assemble two quarter retarders (at 1.06 μm).
7. Measure retardation uniformity with visible light.
8. Measure retardation uniformity at 1.06 μm .
9. Measure flatness of window interferometrically while under pressure.
10. Deliver a 1.06 μm , 25 cm quarter-wave retarder.
11. Prepare report of test results.

STRESS INDUCED QUARTER-WAVE PLATE

When unstrained, certain materials such as glass and quartz are optically isotropic; but, when subject to stress, they become anisotropic. This principle is the basis for the development of stress induced retardation plates.

The relative retardation is directly proportional to the difference in principal stresses, written as

$$R = C (\sigma_p - \sigma_q) d \quad (J-1)$$

where

R = retardation in $\text{\AA}$

σ_p and σ_q = principle stresses in bars

d = thickness in mm

The constant of proportionality C is the stress-optical coefficient. The unit is the brewster which is equal to $10^{-13} \text{ cm}^2/\text{dyne}$. For British units, the equation is:

$$R = 1.752 C (\sigma_p - \sigma_q) d \quad (\text{J-2})$$

where

C is in brewsters

σ is in psi

d is in inches

REQUIRED PRESSURE

Hughes proposes to fabricate a 25 cm clear aperture by 1 cm thick, quartz plate with a quarter-wave retardation at $1.06 \mu\text{m}$. The retardation will be induced by applying pneumatic pressure along two opposing edges. The required pressure can be determined from Equation (J-1) given the stress-optical coefficient at $1.06 \mu\text{m}$. This coefficient has been measured in the visible wavelength region by Jog*, et al, as shown by the solid line in Figure J-1. The dashed line in Figure J-1 is an extrapolation of Jog's data. From this extrapolation, the estimate of the stress-optical coefficient at $1.06 \mu\text{m}$ is $C = 3.18$ brewsters. The estimated pressure for a quarter-wave retardation at $1.06 \mu\text{m}$ is 1,200 psi.

The first task will be to measure the stress-optical coefficient to obtain a better estimate of the necessary pressure. A set up for making these

*JOG, E.S. and Krishanan, R.S., "Dispersion of the Photoelastic Constants of Fused Silica," Nature 179, 540, March 9, 1957.

Figure J-1. Stress-optical coefficient of fused silica

measurements is shown in Figure J-2. A cube of quartz is stressed by a clamp and placed in a spectrophotometer between two polarizers. Given the

Figure J-2. Setup to measure stress-optical coefficient

clamping pressure, the stress-optical coefficient can be determined at each maximum and minimum of the transmission scan (Figure J-3).

Figure J-3. Transmittance scan of a retardation plate between two polarizers

PRESSURE UNIFORMITY

Stress nonuniformity will result in retardation nonuniformity which will result in isolator leakage. The electric field, after transmission through a retarder can be written as

$$E_x = E_{ox} \cos \phi/2 + E_{oy} \sin \phi/2 \quad (J-3)$$

$$E_y = E_{ox} \sin \phi/2 + E_{oy} \cos \phi/2 \quad (J-4)$$

where

E_{ox} = initial X-directed field

E_{oy} = initial Y-directed field

ϕ = retardation

Assume

$$E_{oy} = 0$$

$$\phi = \pi + \Delta\phi$$

where

$$\Delta \phi \ll 1$$

Then, Eqs. (J-3) and (J-4) become

$$E_x = \frac{1}{2} \Delta \phi E_{ox}$$

$$E_y = E_{ox}$$

Then X-polarized power

$$P_x \propto E_x^2 = \frac{1}{4} (\Delta \phi)^2 E_{ox}^2$$

The extinction coefficient

$$W \equiv P_x / P_o = \frac{1}{4} (\Delta \phi)^2$$

or

$$\Delta \phi = 2 \sqrt{W} \quad (J-5)$$

This is the allowable phase error for a given extinction coefficient. In terms of retardation, the phase is

$$\phi = 2\pi (R/\lambda) \quad (J-6)$$

or by Eq. (J-1)

$$\phi = 2\pi CP d/\lambda \quad (J-7)$$

Thus

$$\frac{\Delta\phi}{\phi} = \frac{\Delta P}{P} \quad (J-8)$$

Combining Eqs. (J-5) and (J-8) with $\phi = \pi$

$$\frac{\Delta P}{P} = \frac{2\sqrt{W}}{\pi} \quad (J-9)$$

The desired extinction coefficient is 23 dB or 0.005. Thus, from Eq. (J-9)

$$\frac{\Delta P}{P} = 4.5 \text{ percent}$$

The design goal will be

$$\frac{\Delta P}{P} \leq 1 \text{ percent}$$

The best quartz obtainable on short notice has a specification for residual birefringence of 10 nm/cm. The associated phase error at 1.06 μm for a 1 cm thick plate is

$$\Delta\phi = 5.9 \times 10^{-2} \text{ rads.}$$

If this phase error is added to the phase error due to a 1 percent pressure variation, the resulting extinction from Eqs. (J-8) and (J-9) is

$$W = 2 \times 10^{-3}$$

or

$$W = 27 \text{ dB}$$

Ennos* constructed a stressed induced quarter-wave plate at $5461\text{\AA}$. His plate was quartz, $1/4$ inch thick by approximately 1.3 inches square. As seen from Figure J-4, the phase error over most of the plate was less than 0.9 degrees or 0.0157 rad. This would give an extinction (for two passes) of 60 dB. Figure J-5 shows the plate in the unpressurized state.

EXPERIMENTAL ANALYSIS

As an aid in determining the pressure uniformities, the retardation plate will be first analyzed using visible light. Since the retardation plate will be

Contour values expressed as percentages of one-quarter wavelength relative to the centre.

Figure J-4. Optical retardation of compressed silica plate

* Ennos, A. E., "High-precision tunable retardation plate for use with visible and ultra-violet light," *Optica Acta* 10, 105-113, April 1963.

Contour values expressed as percentage variation from one-quarter wavelength at the centre.

Figure J-5. Optical retardation of unstressed silica plate showing residual strain

a quarter-wave at $1.06 \mu\text{m}$, there will be some point in the visible wavelength region where it will be a half-wave. Figure J-6 shows the expected visible retardation calculated from Figure J-1.

The retardation plate will be analyzed using a polariscope setup as shown in Figure J-7. The source is focused by lens L1 on pinhole P, filtered by F, collimated by lens L2, and polarized by a prism polarizer. The linearly polarized light is circularly polarized by the quarter-wave plate, diverged by lens L3, and recollimated by mirror M1. After passing through the retardation plate, the light is linearly polarized and then analyzed by a prism polarizer rotated 90 degrees with respect to the first polarizer. The analyzed light can be viewed on a screen or photographed. With this visible light analyzer, Hughes will be better able to determine sources of pressure nonuniformity.

Following visible analysis, the retardation plate will be analyzed by the polariscope modified as shown in Figure J-8. The visible light source will be replaced by a YAG laser. The image (split off by the beam splitter B) of

Figure J-6. Visible retardation for a quarter-wave retarder at $1.06 \mu\text{m}$

Figure J-7. Visible polariscope

Figure J-8. Infrared polariscope

the retardation plate will be scanned by a silicon detector. Contours or equal retardation, similar to those shown in Figure J-4, will be plotted from the data.

MECHANICAL DESIGN

The mechanical design task associated with the proposed quarter-wave plate experiment consists of designing a specialized window frame to impose stress induced birefringence in a glass plate. The primary requirement is that the frame apply a very uniform unidirectional stress along two edges of the glass plate. In addition, to satisfy the objectives of this experiment, the frame must have the capability of varying and accurately measuring the applied stress, accurately holding the glass while minimizing any forces not in the desired stress direction, and must exhibit long-term stability of applied stress.

The proposed window frame, shown in Figure J-9, is designed to satisfy these requirements. The frame applies stress to two opposing edges of the glass by means of a fluid pressure system. The window frame assembly consists of two bladders enclosed in bladder cavities, top and bottom, support channels on each side connecting the two bladder cavities, fill and relief valves for the bladders, and a sealed bellows connected to one of the bladders giving a capability for fine adjustment of pressure. These various elements are identified in Figure J-9. With a static fluid pressure system

Figure J-9. Mechanical design of proposed window frame

for applying stress, stress uniformity will be nearly perfect as long as the bladders do not impose elastic forces. Thus, the bladders will be designed of a very flexible material and also with thin walls. Either liquid or gas could be used as a working fluid, but there are many apparent advantages to using a gas such as dry nitrogen. A gas will not contaminate optics should there be any leakage. Also, using a gas will desensitize the frame from changes in applied stress due to changes in temperature or changes in volume caused by slight leakage. The cavities which constrain the top and bottom edges of the glass would be machined to close tolerances to match the thickness of the glass, thus eliminating edge effects (force vectors not parallel to the desired direction) and preventing extrusion or rupturing of the bladders. Once the bladders are filled to the nominal required pressure, fine adjustment of this stress will be accomplished using the attached bellows. If a gas is used to fill the bladders, very precise adjustments in pressure can be made due to the compressability of the gas. As a result, the exact stress required for quarter-wave retardance can be induced.

Prior to birefringence tests with the precision window pressure frame described above, it is desirable to determine the stress/birefringence coefficient for the glass using only a small cube of glass and not requiring very precise stress uniformity. The design of a frame to accomplish this goal is shown in Figure J-10. The stress would be applied mechanically using a screw mechanism and flat ground plates to push against the glass. Stress would be measured by means of a load cell. This frame is designed for easy and fast adjustments of applied stress without concern for fine adjustment capability or long term stability.

Figure J-10. Frame design for stress testing

APPENDIX K
DATA BULLETIN ON INCRAMUTE DAMPING ALLOY

International Copper Research Association, Inc.

AAM:bs

HEADQUARTERS

1000 BROADWAY, NEW YORK, N.Y. 10018
TELEPHONE (212) 675-1000

March 31, 1975

Mr. B.G. Abshire,
Bldg. 5/M/S B136,
Hughes Aircraft Company,
Culver City,
California.

Dear Mr. Abshire:

Enclosed is the information you requested.

The major INCRAMUTE licencees in the USA are Ampco Metals of Milwaukee, Wisconsin and Olin in East Alton, Illinois. The former has been producing castings, whereas the latter has been concentrating on sheet strip and plate.

If there is any additional information you may require, please contact me.

Sincerely,

A handwritten signature in cursive script, appearing to read 'Alvin A. Machonis'.

Alvin A. Machonis
Projects Manager, Metallurgy.

K-1

INTRODUCTION

Over the years control of noise and vibration has been very much on a seat-of-the-pants basis, yet it has been remarkably successful in many instances. However, as in many cases of technological progress, the details of how and why these empirical solutions work are understood only after their values have been proven. Today as more actual problem sources are seriously attacked, more scientific and sophisticated approaches are being used.

Most techniques used today in reducing noise and vibration involve special materials which have been developed on such a trial-and-error basis. Now, with the advent of a greater financial commitment to noise abatement as a result of government pressure, the available materials are being increased and combined on a more scientific basis. This article deals with a metal which has an unusually high damping capacity in comparison to other metals, thus offering the design engineer a new latitude for controlling noise in machinery and other devices.

NOISE CONTROL

Practical schemes for noise or vibration control may involve one or both of two basic approaches (a) isolation, i.e. prevention of the vibrational energy from reaching the

receiver by reducing its ability to radiate; and (b) vibrational energy dissipation, i.e. making the vibrational energy pass through a material which will absorb it by converting it to heat.

A spring mount is a good example of an isolation system where a high force, low amplitude vibration is converted into a high amplitude, low force vibration. The base can better absorb the lowered force thereby reducing the transmission of the noise. A more sophisticated spring mount usually incorporates a dashpot or a polymeric absorber which converts some of the vibrational energy to heat.

Metallic materials do not, in general, have the ability to absorb energy without suffering permanent damage. Metals such as lead, magnesium, and soft copper are "quiet" when struck because the driving force of the vibration plastically deforms the metal in a permanent way. Harder engineering materials that are most frequently used for commercial products cannot be so easily damaged and hence are "good transmitters of noise and vibration. An exception to the compromise of sacrificing mechanical properties of the metal in order to reduce noise transmission is a series of alloys which have internal mechanisms other than plastic

deformation for dissipating energy. Their distinctive characteristic is that the process of converting mechanical energy into heat does not affect the performance of the metal as a structural material in the way that would be expected if plastic deformation were taking place. Most engineering designs are calculated to avoid plastic deformations by a wide safety margin.

INCRAMUTE

One such alloy is called INCRAMUTE and contains 58% copper, 40% manganese and 2% aluminium. It was developed by the International Copper Research Association and it is now being tested for selected applications. The tables shown in the data sheet give a summary of the properties of the alloy.

The most significant factor which must be considered when the alloy is being used for vibration control is that the amount of energy which is absorbed in each cycle is a function of the amount of stress to which the INCRAMUTE is subjected. The data show that the alloy is most effective when it is stressed to values above 10,000 p.s.i. In many machine components the stress values are below this level; hence a redesign may be necessary to raise the stress to such a value. A special case involves impact loads

where the mean stress may be low, but repeated impacts which generate noise may cause stress pulses of the correct magnitude.

SAW BLADES (CARBIDE TIPPED)

A circular saw blade is a good example of how the impact of the teeth with the workpiece causes stress pulses in the blade which generate noise. The stress waves may cause the blade to vibrate in a manner of a vibrating membrane and/or the teeth may vibrate as an appendage to the blade. Another major source of noise in a saw blade is wind noise which can only be reduced by altering the design of the blade and/or the teeth. The use of high damping materials has been shown to be effective on circular saw blades. For instance, polymeric materials affixed according to constrained layer methods to the side of the blade have been shown to be effective in reducing noise, but seriously restrict the depth of cut. Blades which are made from two sheets of steel adhesively laminated together are also quieter, but experience service problems unrelated to damping. Plugs of soft metal have also been tried with some success but are limited because the deformation of the soft metal plugs tends to reduce their influence with age.

It would seem that an ideal solution would be to make blades entirely from INCRAMUTE. However, this is not possible

because the mechanical properties are not equivalent to the hardened steel now being used. To bypass this problem techniques are now being developed to produce a steel which is covered on both sides with metallurgically bonded INCRAMUTE. A layer 0.010-0.020" thick on each side of the steel has been shown to be effective in reducing noise. Work is now under way to develop a commercially viable process for producing this INCRAMUTE-steel trimetal composite.

RAILROAD WHEELS

Most commuters are aware of the piercing squeal of a rail car negotiating a sharp curve. This is caused by the repeated fracture of the cold weld made between the wheel and the rail due to the extremely high local stress. This results in strain pulses within the wheel which cause it to vibrate in the audible range. Acoustic wheels of several types are available but they are expensive. In general they use various schemes for incorporating a polymeric material between a hardened steel tire and a hub which may be aluminium or steel. Aluminium is preferred from a weight standpoint. These wheels have production and service problems which could be alleviated if a high damping metallic material would be an effective replacement to the polymeric isolator. Wheels composed of a steel tire and an INCRAMUTE

hub are now being fabricated and will be tested on a rail vehicle.

MINING EQUIPMENT

Tests recently conducted by the U.S. Bureau of Mines have shown that the incorporation of a high damping metal as a rotation chuck in a mining drill has been effective in reducing noise. Sufficient noise reduction was achieved so that one manufacturer of this type of equipment is redesigning the rotation chuck so as to allow the use of a composite steel-INCRAMUTE unit and thereby optimize durability in combination with damping capacity.

Another part of the Bureau of Mines program showed that constrained layer damping using polymeric materials and steel reduced the noise generated by the drilling tool. These systems, however, were subject to damage when the side of the drill tool contacted the rock walls of the hole being drilled. A shrink-fitted tube of INCRAMUTE is being substituted in order to reduce cost, improve durability and reduce noise.

GEARS

The noise in gear systems is generally of two types: one is due to the design clearances and the method of the teeth meshing and the other is due to resonance of a gear at specific frequencies which are related to the number of

teeth and the revolutions per minute. A higher quality gear is usually effective in reducing the first source, but the resonance condition requires a change in the rpm and/or tooth number. In variable speed power drives such as truck transmissions this problem is not easily designed out. A high damping gear would be beneficial. However, the service temperature is 250-300°F which is above the Neel point for INCRAMUTE. At temperatures above 175°F the high damping properties are lost and return when the alloy cools below 175°F. There is no change in the mechanical properties. New versions of the alloy are now under development which promise improved high temperature stability for the damping properties.

For light duty it is envisioned that the gears would be made entirely from INCRAMUTE or the high temperature modification of INCRAMUTE if the service environment so dictates. For heavy duty gears, a hardened steel tire containing the teeth would be shrink fitted to an INCRAMUTE hub similar to the railroad wheel. Using these types of gears the resonance peaks in a variable speed transmission would be substantially reduced.

COMMERCIAL AVAILABILITY

Production size quantities of INCRAMUTE have been turned out by a number of mills in the U.S. In general, conventional

equipment and processing techniques were used. Plate from 2" thick down to 1/4" was produced. Cold rolling was also carried out to process 1/2" plate into sheet to 0.060" in thickness. Thinner gauges were also fabricated, but an intermediate anneal was required. Bar stock and tubing were extruded without serious problem.

A variety of castings are being made and in general the availability of castings is better than the wrought mill products. To a great degree the problem is one of developing a market of sufficient size to make this an attractive alloy for the mills to produce on a routine basis.

International Copper Research Association, Inc.

INCRA is a non-profit organization
incorporated in the State of New York, New York, U.S.A.
INCRA is a member of the International Copper Association, Inc.

January 1975

INCRAMUTE High-Damping Alloy

Data Sheet

INCRA has developed a new copper-manganese alloy --- INCRAMUTE --- which possesses a unique combination of properties valuable for controlling noise in structural components of machines and devices --- high inherent damping (or deadening of vibration) with the strength of structural steel.

The discovery of INCRAMUTE makes possible noise reduction, elimination of unwanted resonances and reduction of structurally propagated sound in machine components. At the same time, parts fabricated of INCRAMUTE can support reasonably high engineering stresses.

PRINCIPAL CHARACTERISTICS

*Damping expressed as a loss factor varies over a range from 1 to 7×10^{-2} with the higher values occurring at stresses of the order of 20,000 psi. This damping is independent of frequency.

These values are far greater than for
any other engineering alloy of comparable
tensile properties.

*Good mechanical properties (equivalent to structural steel).

*Good fabricability and castability. Plate, sheet, strip, bar, tube and castings are readily produced.

DESCRIPTION

1. Nominal Composition:

56% copper
42% manganese
2% aluminum

2. Damping:

Damping is stress dependent and frequency independent, as measured over the range of 2 to 10,000 cps. Logarithmic decrement of structural vibration amplitude decay corrected to a uniformly stressed tensile/compressive element is given below. The table compares the INCRAMUTTE alloy and some alloys now in use that exhibit varying damping properties.

COMPARISON OF DAMPING

Logarithmic Decrement (Damping)

Maximum Cyclic Stress (psi) (MN/m ²)		Material					
		Incramute I	Gray Cast Iron	2024- F4 Aluminium	C1018 Steel	410 SS	Nivco 10
10,000	69	0.1910	0.0650	0.0044	0.0138	0.003	0.0437
2,000	14	0.0780	0.0531	0.0044	0.0031	0.0006	0.0270
1,000	7	0.0608	0.0408	0.0041	0.0017	0.0004	0.0219

Conversion to Other Damping Units

Loss coefficient equals logarithmic decrement divided by π (3.1416).

Specific damping capacity equals logarithmic decrement multiplied by 2.

Quality factor is the inverse of loss coefficient.

3. Mechanical Properties:

Solution Heat Treated and Aged (High-Damping) Condition

1. CASTINGS

1 - to 3-inch (2.5-7.6 cm) Section Thickness

	<u>English</u>	<u>S. I.</u>
Tensile Strength	68 ksi	469 MN/m ²
Yield Strength	38 ksi	262 MN/m ²
Elongation	38%	38%
Modulus of Elasticity	12 x 10 ⁶ psi	82.7 x 10 ³ MN/m ²

2. SHEET AND PLATE

0.020 to 0.25 Inch (.05-.65 cm) Thickness

	<u>English</u>	<u>S. I.</u>
Tensile Strength	78 ksi	538 MN/m ²
Yield Strength	32 ksi	221 MN/m ²
Elongation	32%	32%
Modulus of Elasticity	14 x 10 ⁶ psi	96.5 x 10 ³ MN/m ²
Fatigue Strength (Reverse Bending, 100 x 10 ⁶ Cycles)	19 ksi	131 MN/m ²

3. BAR

2-inch (5 cm) Diameter Extrusion

	<u>English</u>	<u>S. I.</u>
Tensile Strength	79 ksi	545 MN/m ²
Yield Strength	49 ksi	338 MN/m ²
Elongation	34.5%	34.5%

4. Physical Properties:

Solidus: 1565°F (851°C)

Liquidus: 1680°F (916°C)

Mean Coefficient of Thermal Expansion: 12.5 x 10⁻⁶ in/in/°F
67-572°F (19-300°C) (22.5 x 10⁻⁶ cm/cm/°C)

Modulus of Elasticity: 12-14 x 10⁶ psi (82.7-96.5 x 10³ MN/m²)
(Solution Heat Treated and Aged)

Density: 0.27 lb/in³ (7.48 gm/cc)
(Solution Heat Treated and Aged)

Thermal Conductivity: 6.8 Btu/sq ft/ft/hr/°F
(0.028 cal/sq cm/cm/sec/°C) (Approx.)

Non-Ferromagnetic

5. Heat Treatment:

- (a) Solution anneal - ½ hour at 1300-1400°F (704-760°C)
- (b) Quench - any suitable medium needed to control distortion.
- (c) Age - 9 hours, 750°F (399°C)

ALTERNATIVE AGING CYCLES FOR INCRAMUT® 1

Temperature °F °C		Time (hrs)
650	343	113
700	371	30
750	399	9
800	427	3
850	454	1

6. Dimensional Stability:

Good at all temperatures below 700°F (371°C). Aging produces a 0.6% linear shrinkage as compared to the solution quenched material.

7. Machinability:

Equivalent to aluminum bronze.

8. Joining:

A. Welding

RECOMMENDED TECHNIQUES FOR WELDING INCRAMULLE I

Manual Welding GTA	Automatic Welding EB
(1) Low Heat Input	(1) Low Heat Input
(2) Wide Gap, Beveled Butt Joints	(2) Flush Butt Joint
(3) Ample Filler Metal	(3) No Filler Metal Addition
(4) Close Fitted Hold-down and Backup Plates	(4) Close Fitted Hold-down and Backup Plates
(5) Inert Gas Backup	(5) Vacuum Environment
(6) High Frequency Stabilized A.C.	

The following schedules are presented as examples of sound welding practice which incorporates these recommended techniques:

Gas Tungsten Arc Schedule (Manual Welding)

	Thickness		
	0.020 inch (0.05 cm)	0.100 inch (0.25 cm)	0.250 inch (0.64 cm)
Torch Gas	Argon	Argon	Argon
Backup Gas	Argon	Argon	Argon
Backup Plate	Copper	Copper	Copper
Hold-down Clamps	Stainless Steel	Stainless Steel	Stainless Steel
Speed	30 in (76 cm)/min	30 in (76 cm)/min	20 in (51 cm)/min
Amperage	20	70	165
Voltage	10	14	14

RECOMMENDED FILLER WIRE SIZES FOR WELDED INCRAMUTE I

INCRAMUTE Thickness		Filler Wire Diameter	
(inch)	(cm)	(inch)	(cm)
0.02	0.05	1/32	0.08
0.06	0.15	3/64	0.12
0.125	0.32	1/16	0.16
0.250	0.64	1/8	0.32

TYPICAL MECHANICAL PROPERTIES OF WELDED INCRAMUTE I (GTA OR EB WELDED)

0.1 to 0.25 inch (0.25-0.64 cm)

Condition	Tensile Strength		Yield Strength, 0.2% Offset		Elong. (%)	Tensile Fracture
	(ksi)	(MN/m ²)	(ksi)	(MN/m ²)		
As-welded in solution heat treated and aged (high-damping) condition	72	496	40	276	26	H. A. Z.
Welded in cold-rolled condition and heat treated and aged to high-damping condition	75	517	40	276	36	P. M.

8. Joining (continued)

B. Brazing

All surfaces should be mechanically abraded to remove the oxide surface layer. Brazing is carried out in a normal manner using a reducing flame.

Braze Strength - The strengths developed in brazed INCRAMUTE I joints are primarily a function of the braze alloy. The table below shows values which are typical for Easy Flo brazing alloy.

INCRAMUTE I BRAZEMENT STRENGTH, EASY FLO ALLOY

	<u>ksi</u>	<u>MN/m²</u>
Shear Strength	17.0	117.2
Tensile Strength	40.0	275.8

Using this or similar braze alloys, a 3T overlap, i.e., a joint which overlaps three times the thickness of the material, will sustain a stress in excess of the yield strength of the INCRAMUTE I.

LIMITATIONS

INCRAMUTE I will lose its damping characteristics at temperatures above approximately 1750°F. However, it regains full damping upon cooling below this temperature without any influence on mechanical properties. Modifications to the basic composition are underway to raise this temperature limit.

APPENDIX L
THE UTILIZATION OF STEPPING MOTORS

This Appendix is used with the permission of E. C. Welch.

THE UTILIZATION OF STEPPING MOTORS

by

**E. C. WELCH
Vice President**

**AUTOMATION DEVELOPMENT COMPANY
A Division of American Digital Corporation
Culver City, California**

THE UTILIZATION OF STEPPING MOTORS ©
Copyright 1968

by

Automation Development Company
A Division of American Digital Corporation
9905 West Jefferson Boulevard
Culver City, California

TABLE OF CONTENTS		Page
I.	Definition of a Stepping Motor	1
II.	Definition of a Step Motor Servo System	3
III.	Step Motor Servo Advantages	5
	A. Stability and Flexibility	5
	B. Accuracy	7
	C. Multiplicity	7
	D. Torque and Braking Capability	7
	E. Controller Reliability and Power Efficiency	8
IV.	Limitations of Stepping Motors	8
	A. Acceleration Limitations	8
	B. Load Limitations	10
	C. Motor Electrical Efficiency	14
V.	Typical Applications	14
	A. Step Motor Servo Clock System	14
	B. Manual Input Step Servo Positioning System	15
	C. Closed Loop Step Servo Positioning System	15
	D. Step Motor Servo Velocity Control System	17
	E. Step Motor Servo System with Digital Feedback	19
	F. Load Adaptive Step Motor Servo System	19

LIST OF ILLUSTRATIONS		Page
Figure No.		
	Frontispiece Typical Stepping Motors and Controllers	ii
1	Typical 90°/Step Permanent Magnet Step Motor	2
2	Basic Variable Reluctance Step Motor	2
3	Typical 15°/Step Variable Reluctance Step Motor	4
4	Conventional Servo Positioning System	4
5	Step Motor Servo Positioning System	6
6	Typical Permanent Magnet Step Motor Speed Torque Curve	6
7	Typical Variable Reluctance Step Motor Speed Torque Curve	13
8	Step Motor Servo Clock System	13
9	Manual Input Step Motor Positioning System	16
10	Closed Loop Step Motor Position System	16
11	Step Motor Velocity Control System	18
12	Step Motor System with Digital Feedback	18
13	Load Adaptive Step Motor Servo System	20

TYPICAL STEPPING MOTORS AND CONTROLLERS

THE UTILIZATION OF STEPPING MOTORS

I. Definition of a Stepping Motor

The stepping motor is a relatively new servo system component which has a number of advantages, and some disadvantages, as compared to the conventional servo motor.

Two basic types of high speed bi-directional stepping motors presently dominate in servo type applications.. The first of these utilizes a two-phase field or stator winding, and a cylindrical permanent magnet rotor which is magnetized across its diameter. This type is usually designated as a permanent magnet (PM) type. The second type usually employs a three-phase stator winding and a toothed rotor made from soft iron. This type is designated as a variable reluctance (VR) type. The PM type, shown in Figure 1, produces a torque due to the attraction or repulsion of the poles of the permanent magnet rotor by the poles of the stator. Like poles repel and unlike poles attract. The rotor then rotates until it has aligned its south pole with a stator north pole and its north pole with a stator south pole, at which time the torque produced is zero and the rotor comes to rest. If the battery is disconnected from the phase A coils and instead similarly connected to the phase B coils, such that the pole to the right is a south pole, then a torque is produced which will turn the rotor to the right (CW) until its north pole aligns with the new south pole. The PM motor has now completed its first CW step. The rotor will remain in this position until the current is removed from the Phase B coils. If the battery is now reconnected to the phase A coils, but with the opposite polarity to that originally used for phase A, a south pole will be produced at the stator bottom pole and the rotor north pole will again turn through 90° to align with the new south pole. It may easily be visualized that this reconnecting, or switching, of the battery alternately from phase A to phase B may be continued in a sequence which will make the rotor continue to rotate CW in 90° steps as long as is desired. The rotor is smoothly accelerated and decelerated by the magnetic forces, and there are no impact shocks transmitted to the load. Likewise, if the sequence is reversed the rotor will turn CCW in 90° steps rather than CW. It is significant that the rotor is forcibly held at each of the four positions in turn by magnetic forces, and may only be moved by exerting other forces or torques on the rotor shaft which are greater in magnitude than the magnetic forces; or by switching the current from one set of stator coils (phase) to the other. PM motors are also made with a larger number of poles on the rotor and stator which produces smaller stepping angles, such as 45°/step and smaller.

The operation of the VR motor, shown in Figure 2, is quite similar. The sequence ABC produces CW stepping in 60° increments, and the sequence ACB produces CCW stepping. The VR rotor is made from soft iron and has no magnetic poles of its own. Torque is produced by the magnetic forces attempting to line up the magnetically asymmetrical rotor between the

TYPICAL 90°/STEP PERMANENT MAGNET STEP MOTOR

Figure 1

BASIC VARIABLE RELUCTANCE STEP MOTOR

Figure 2

poles, in the same manner as iron filings align themselves between the poles of a horseshoe magnet. This simple rotor, used for clarity, may be visualized as a "two tooth" rotor. Actual VR motor rotors have a larger number of radial projections or teeth, typically 8 teeth for a 15° per step VR motor. In this case, the stator would have 12 poles with the coils suitably connected in groups of 4 to give the desired three phases A, B, and C. A sketch of such a motor is shown in Figure 3.

II. Definition of a Step Motor Servo System

A conventional servo positioning system is schematically shown in Figure 4. It typically requires a voltage input command, V_c , proportional to the desired position. The servo motor, through a gear reducer, drives the load to be positioned and a position sensing device which produces a feedback voltage, V_f , indicating the position of the load. These two electrical signal voltages are subtracted to obtain an error voltage signal, V_e , proportional to the difference between the desired load position and the actual load position. A servo controller is required to amplify and suitably process the error voltage, V_e , such that the servo motor is driven in the proper direction and with a controlled velocity which will bring the load to a stop at the desired position. When the load settles at the desired position, V_e is zero and the positioning of the load is completed. Due to the feedback employed, the characteristics of both the motor and controller must be carefully matched to the load, otherwise undesirable side effects such as slow response, poor accuracy, excessive overshooting, or even unstable oscillation may occur. These undesirable effects are avoided by proper servo system design, using well developed analytical and computational techniques. However, changes in the load or the operating conditions may require a reanalysis and redesign of the servo system.

A typical positioning system using a stepping motor (SM) is shown in Figure 5. The SM drives the load through a gear reducer, as in the conventional system. The controller consists of a group of semi-conductor switches which will switch the motor coil currents in a sequence to give the desired direction of rotation. Typically the controller will have a CW input terminal and a CCW input terminal, and connections for the motor leads and the D.C. supply voltage or battery. The controller is arranged such that the switching sequence is commanded by electrical pulses directed to the desired input, CW or CCW. Each pulse directed to the CW input channel will cause the motor and the load to rotate one step in the CW direction. Likewise, each pulse directed to the CCW channel will cause the motor and the load to rotate one step in the CCW direction. The magnitude of each step is fixed by the motor design and the ratio of the gear reducer. A 90/1 reduction with a 90° /step motor will give 1° /step at the load. If smaller steps are desired, the gear reduction ratio may be increased. If the initial position of the load is known, then it may be rotated to any desired position by keeping track of the number of pulses directed to the controller. An electronic or electro-

TYPICAL 15°/STEP VARIABLE RELUCTANCE STEP MOTOR

Sequence ACB gives
CW rotation, and ABC
gives CCW rotation.

Figure 3

CONVENTIONAL SERVO POSITIONING SYSTEM

Figure 4

mechanical counter may be used to perform this counting, and give a direct reading of the load position in degrees. Alternatively, a manually rotated pulse transducer which produces a fixed number of pulses per revolution may be used to command the load position. In this case, the counter is not required. Digital data systems such as tape programmers and digital computers can readily produce the required pulses and avoid the necessity for a digital to analog converter, which would be required with the conventional servo system.

The required initial position of the load can in some cases be determined visually. In case of a remote load a cam driven switch at the load, as shown in Figure 5, may be used to operate an index lamp and establish a known initial position. This position reference may also be consulted at intervals during normal operation to verify the load position.

III. Step Motor Servo Advantages

A. Stability and Flexibility

PM step motors are inherently stable due to the rotating magnetic field of the rotor. This rotating field can be utilized to produce a damping or braking action which is analogous to the downhill braking supplied by the drive motors in electric locomotives. Also, since no continuous feedback is required there is no possibility of oscillations or instability due to improper servo loop design or changes in load from that used in the original design. VR step motor rotors do not provide such a rotating magnetic field, and may require damping by external means. The required damping may be supplied by a mechanical damper on the motor backshaft, or by appropriate controller design. Either type of SM is magnetically locked in position between steps unless forcibly moved by external forces or torques which exceed the motors capability, or the motor is commanded to rotate by the controller switching the coil currents. Therefore, no drift can occur. As long as the load is not excessive and the motor can rotate, it must bring the load to the desired position with an error which is less than one step. This error is non-cumulative so that subsequent stepping commands do not increase the error.

The step motor controller is essentially independent of the load. The only significant requirement is that the motor be capable of moving and driving the load, and that the controller be capable of switching the motor coil currents. Changes in load, as long as they remain within the capability limits of the motor, will require no reanalysis or redesign of the system. If it is also necessary to drive the load at a desired constant speed, no change in design is required. If the controller is driven from an oscillator or pulse source producing pulses at a desired rate, then the load will be driven in synchronism at a corresponding exact average speed; up to the point at which the speed or load capacity of the motor is exceeded.

STEP MOTOR SERVO POSITIONING SYSTEM

Figure 5

TYPICAL PERMANENT MAGNET STEP MOTOR SPEED TORQUE CURVE

Figure 6

The flexibility of the step motor servo also encompasses the type of data transmission required to bring the pulses to the controller. Since only on-off pulse data is required, noisy telephone or radio channels may be utilized. It is only necessary to detect the presence or absence of a command pulse in the noise to be able to regenerate the original pulse in usable form. This regenerated pulse will then command the desired step equally as well as the original pulse.

B. Accuracy

The positioning accuracy of the SM must always be better than one step. Static friction, present in both the motor and load, will cause an uncertainty in the exact stopping position of the step motor at the end of a stepping motion. However, for any load which the motor can successfully drive, this uncertainty must always be some fraction of a complete step. Since reduction gearing will allow the step size to be made arbitrarily small, the angular accuracy of the SM positioner is only limited by the accuracy of the reduction gears. Small in-line gearheads, mounted to the front of the motor are usually limited to approximately 10 arc minutes zero to peak error over 360° rotation of the output shaft. Larger precision gearboxes, which can utilize large diameter gears, can achieve accuracies of approximately 1-3 min. of arc zero to peak. Highly specialized super accurate gears have been made which will allow the gear reducer error to be reduced to approximately 3-10 arc seconds.

C. Multiplicity

If a number of loads must all be simultaneously driven to the same position, or all be driven at the exact same speed; the step motor servo positioning system, Figure 5, offers a simple solution. If the power output capability of the controller is sufficient, any number of SM's may be connected to the controller output in parallel. Since the windings of all motors are now connected identically, and the same windings of all motors are excited simultaneously, their rotors must all be simultaneously driven to the same position. The loads of all motors are then driven in exact synchronism and will stay in synchronism even though the load varies, up to the point at which the load capability of one or more of the motors is exceeded.

Due to the individual position feedback required for each load in the conventional servo, Figure 4, separate motors, position sensors, controllers, and subtractors are required for each load. This duplication of components increases cost and decreases reliability.

D. Torque and Braking Capability

Volume for volume, the SM will produce a higher maximum torque at stall than the commonly used two phase

induction or hysteresis synchronous motor. The PM stepping motor, or a properly damped VR stepping motor, has a broad speed torque curve with an area which is usually larger than that of an equivalent size conventional servo motor. This large area indicates superior horsepower producing capability for the stepping motors.

The stopping or braking capability of the SM is exceptional. If the motor is operated within its normal stepping rate capability, up to 5000 RPM for some types, it is capable of stopping within one step. No extra steps (a number greater than the number of command pulses) are gained by overstepping the stopping position during the deceleration process. The motor decelerates and comes to rest at the correct position. It is significant that a step command in the opposite direction of rotation is not required to achieve this rapid deceleration, only a termination of the stepping commands in the existing direction of rotation is required. Conversely, the conventional two-phase servo motor can only achieve rapid deceleration by a reversal of the motor input voltage by the controller. This reversal commands the motor to produce a torque in the opposite direction until its speed is reduced as desired. Even with such a reversal, the deceleration capability of the two-phase servo motor is not as great as that of the SM. This rapid deceleration upon termination of a stepping command has considerable value in the application of SM's to sampled data and digital servo systems.

E. Controller Reliability and Power Efficiency

The step motor controller requires only crude D. C. power as an input, typically 28±5 VDC. The controller then provides all of the power input requirements of the SM. Since the controller is only required to act as a switch, to suitably switch the power to the required motor windings, a power efficiency of approximately 90% may be achieved. Reliable solid state switching techniques are used and the solid state components may be conservatively operated due to the high efficiency. Conversely, an A.C. power source, typically 115V 60 cps or 26V or 115V 400cps, is required for the two-phase servo motor. If A.C. power is not available, it must be generated by an inverter circuit which alone may be as complex as the SM controller. In addition, the conventional motor requires its own specialized servo loop controller which typically includes signal amplification, demodulation, remodulation, and power amplification. This controller may be several times as complex as the SM controller, and its power efficiency on the order of 30% to 60%.

IV. Limitations of Stepping Motors

A. Acceleration Limitation

With the motor rotor and load initially at rest, and

for a suddenly applied train of stepping command pulses; above a certain maximum pulse rate the motor does not have sufficient torque to pull the motor rotor, and the load, into synchronism with the command pulse rate without missing steps. If accurate positioning of the load is to be achieved under these conditions, the SM must respond to the suddenly applied group of command pulses without hesitation in starting such that command pulses are not missed. The motor must respond to each pulse input with a corresponding step. The SM is only capable of maintaining positioning accuracy, under such sudden starting conditions, up to a certain maximum command pulse rate called the maximum synchronous stepping rate. Beyond this stepping rate the SM may hesitate and miss steps in starting, or may refuse to start at all.

If the SM is first started at or below the maximum synchronous stepping rate, the stepping rate may then be further increased up to what is called the maximum slewing rate. Beyond this point, the SM falls out of synchronism with the pulse rate and will not restart until the pulse rate is decreased below the maximum synchronous stepping rate. If the SM is running at or near the maximum slewing rate and the pulse train is suddenly terminated, then the motor may over step and gain extra steps. Since these steps were not commanded by a corresponding pulse input, they represent a position error. The speed at which the pulse rate may be increased beyond the maximum synchronous rate to the maximum slewing rate steadily decreases as the maximum slewing rate is approached. If the speed of pulse rate increase and decrease is suitably controlled above the maximum synchronous rate, and the SM is always stopped, started, or reversed, at pulse rates at or below the maximum synchronous rate; then the slewing region may be utilized and still maintain the desired positioning accuracy. This mode of operation is commonly referred to as a "controlled acceleration and deceleration mode."

If the train of command pulses is suddenly switched from the CW input of the controller to the CCW input, which requires the SM to decelerate to a stop and then pull into synch. in reverse, a further speed limitation exists. This stepping speed is called either the maximum synchronous reversing rate, or the random stepping rate. The random stepping rate may be as low as one half of the maximum synchronous rate (starting rate) and only one fourth or one fifth of the maximum slewing rate. Typical maximum motor shaft speeds for the various stepping modes are as follows:

1)	Maximum synchronous reversing rate	2000 RPM
2)	Maximum synchronous rate (Starting)	3000 RPM
3)	Maximum slewing rate	8000 RPM

The corresponding stepping rate depends upon the stepping angle. For a shaft speed of 1000 RPM, the corresponding stepping rate for four typical stepping angles are as follows:

Step Angle
in Deg.

Steps per Sec.
Per 1000 RPM

1.8
15
45
90

3,333
400
133
67

Instant reversal of the command pulses from CW to CCW can be avoided in many system applications, with higher usable SM speeds as the reward for the extra effort. With the above stepping speed limitations in mind it becomes apparent that gear reducers must be used with discretion. A larger reduction will give a smaller step size and higher positioning accuracy, however, it also reduces the maximum shaft speed. An overly stringent requirement for accuracy may overly limit the speed capability. Conversely the maximum shaft speed should not be overly specified, or the attainable accuracy may suffer.

B. Load Limitations

Since the SM must be capable of high acceleration and deceleration in order to maintain positioning accuracy under the conditions of suddenly applied starting or reversing pulse sequences; it is more sensitive to inertia load than the conventional servo motor. The conventional servo motor depends upon the position sensor and the feedback loop for its positioning accuracy. For a suddenly applied position command, inertia load will cause the conventional motor to hesitate or lag behind the command for a considerable time. The motor then attains high speed and catches up with the command. No permanent position error results from the initial lag. Inertia load will also cause the conventional motor to overshoot the desired position by a considerable amount and then finally settle at the desired position. The major effect of the inertia load is to slow the response of the conventional servo system and increase the time required for the load to reach the desired position. Inertia load causes no loss in accuracy of the final rest position, if the servo loop is properly designed for the load. Conversely, the SM requires no external position feedback or rate feedback to operate as either a load positioning servo system or as a velocity servo. However, this unique capability may only be exploited when the SM is capable of pulling the load into synchronism with the existing stepping commands without missing steps. The SM will miss steps if it lags too far behind the position commanded by the SM controller in starting or reversing (approximately 180° for a $90^\circ/\text{step}$ PM motor and $22\frac{1}{2}^\circ$ for a $15^\circ/\text{step}$ VR motor). The SM has no inherent means to correct this position error and it will continue to exist until the position system is reinitialized by visual observation, or by use of an index indicator as shown in Figure 5.

The maximum synchronous starting rate and maximum

synchronous reversing rate are both decreased by inertia load. Therefore, both the running torque (friction) load and the inertia load must be considered in applying the S.M. Reduction gearing is of great benefit in decoupling or isolating the SM from the load, as well as increasing the available torque output and increasing the accuracy by decreasing the step size. Doubling the gear reduction ratio will reduce the inertia load seen by the motor to one fourth of the original value. Simultaneously, the output torque available is doubled and the step size is reduced by one half. Under no load conditions motors with small stepping angles will, in general, have a higher maximum synchronous stepping rate than motors with large stepping angles. However, the maximum shaft speed in RPM will probably be close to the same value. Since the motor with the smaller stepping angle has a shorter angular distance to travel, it can, in general, complete the step in less time than the step motor with a larger stepping angle. When driving inertia loads this situation may very well be reversed, with the large step angle motor capable of driving the load at a greater number of steps per second than the small step angle motor. The larger step angle motor will allow a larger gear reduction to be used than can be used with the smaller step angle motor, for the same step size at the load. The increased torque output and isolation from the load inertia obtained with the larger gear reduction will, in many cases, allow the large step angle motor to achieve the highest loaded stepping rate. Table I compares the relative torque multiplication and inertia load reduction obtainable through gear reduction. In each case, the gear reduction ratio is chosen such as to give the same step size for all motors.

TABLE I

Step Size	Torque Multiplication	Inertia Load Reduction
1.8°	1/1	1/1
15°	8.33/1	69.3/1
45°	25/1	625/1
90°	50/1	2500/1

With only running friction load (coulomb plus viscous), PM stepping motor performance is easily predicted over the operating range of interest. At high and medium speeds the stepping motor shaft is in continuous rotation at nearly a constant speed. The motor shaft rotates through the last command step increment but has not had time to come to rest before the next step command is received. Under these conditions, it is relatively easy to measure and plot average shaft speed and average torque. In this region, and with only friction load, PM step motor performance may be predicted from speed torque curves in the same manner as the conventional servo motor. At low speeds the SM shaft does come to rest between the stepping commands. Measuring average values of

speed and torque becomes difficult at these low rates, since SM torque output capability is a function of both shaft speed and position and both variables are changing over a considerable range. This difficulty is purely one of instrumentation, no undesirable type of motor operation occurs in this region. If the SM will drive the load at the higher speeds, then it will also drive the load at the low speeds where specification is difficult. Since this low speed region is normally of little practical interest, it is usually left as a gap in the speed torque curve. The maximum torque the motor is capable of developing (motor rotor held stationary at the maximum torque position) is usually specified, and is defined as the maximum holding torque. Due to the change in torque with rotor position (varies from the maximum holding torque value to zero over the step increment) the SM cannot generate a running torque equal to the holding torque. For a typical PM motor the maximum running torque is approximately 0.6 of the holding torque.

A typical speed torque curve for a PM motor is shown by the continuous line in Figure 6. If an inertia load is now added to the friction load, the stepping capability is reduced. The dashed curve of Figure 6 shows the stepping performance when an inertia load (as seen at the motor shaft) just equal to the inertia of the rotor of the motor is added. A typical plot of torque vs rotor position for the PM motor is also shown in Figure 6. Similar curves for the VR type stepping motor are shown in Figure 7. Note that these curves have a hook, and for some VR motors there may be a number of such hooks throughout the operating region. Any of these hooks which have a negative slope should be viewed with alarm, since they represent regions of unpredictable motor operation. The data from most suppliers does not adequately define such regions. In many cases, an average curve is drawn through these regions. However, most suppliers' data does note that, "VR stepping motors may require external damping." Electrical damping supplied by the controller, or mechanical damping supplied by a damper unit added to the motor back shaft, may be used to straighten out the hooks until the regions of negative slope are eliminated. Under these conditions the VR motor will operate very reliably. However, performance with inertia load is much more difficult to predict than with the PM motor. When adequate damping is added to the VR motor its stepping performance may be considerably degraded from that indicated on the suppliers' data sheet. Most of this uncertainty and difficulty is caused by the somewhat unpredictable nature of the VR motor, not subterfuge by the supplier. When properly tamed, the VR motor is capable of stepping at quite high rates, due to its relatively small stepping angle of typically 15° .

SM's are presently best suited to instrument servo or low power applications. In present motor design, it is not feasible to simultaneously obtain high stepping rate capability, large load handling capability (especially inertia load) and a large stepping angle. As the motor is made larger, to obtain larger

TYPICAL VARIABLE RELUCTANCE STEP MOTOR SPEED TORQUE CURVE

Figure 7

STEP MOTOR SERVO CLOCK SYSTEM

Figure 8

load capability, the inertia of the rotor increases at an even faster rate than the increase in load capability. This disproportionate increase in rotor inertia then limits the stepping speed of the larger motor. This same effect occurs in the conventional two-phase servo motor. As the motor is made larger for higher power output, its speed of response (ability to accelerate, reverse, etc.) decreases. The most responsive conventional servo systems utilize small instrument size motors. In present step motor designs the only route to simultaneous high stepping rate and high torque output, is small stepping angles. As previously described, this small stepping angle restricts the capability of the motor to drive inertia loads and also the maximum RPM.

C. Motor Electrical Efficiency

Stepping motors, like torque motors, are often required to operate under very slow speed or stalled conditions. Under these conditions the motor input power is high. Since the mechanical power output is negligible, the motor must dissipate all of the input power as heat. The first means of combating the heat problem is to design a motor with good magnetic efficiency, in order to minimize the power input required. The second means, is to operate the SM efficiently by the controller. Different suppliers operate SM's in a number of different stepping sequences. Some are economical in cost and component count, while others are more complex but operate the motor more efficiently. Even under ideal conditions SM's must dissipate considerable heat, if either high stepping speed or high torque is required. The operating temperature may be reduced by mounting the motor to an adequate heat sink with a good thermal bond. Also, some suppliers list finned radiators which may be slipped over the motor case. These radiators will significantly reduce the motor temperature, especially if a forced air flow is available. Motor stepping speed and torque decrease as the winding temperature increases. It is therefore worth some effort to minimize the operating temperature. Well designed stepping motors will operate reliably at high case temperatures, however, bearing life may be degraded if the case temperature exceeds approximately 180°C. At ambient temperatures below 90°C, it is usually not difficult to maintain the motor case temperature below the 180°C point.

In cases where available power is at a premium, or motor temperature must be reduced to a minimum, special controller designs are available which will greatly reduce the required input power under low speed and stalled conditions. These controllers are somewhat more complex than the usual type.

V. Typical Applications

A. Step Motor Servo Clock System

This example, shown in Figure 8, is chosen to illustrate a utilization of the multiplicity capability of the SM.

A one pulse per second pulse generator, which may be made to almost any degree of accuracy desired, supplies CW command pulses to the controller. The SM, through a suitable gear reducer, drives each clock mechanism. All SM's are connected in parallel to the controller and must therefore all step in synchronism. The long term accuracy of the clock system is then equal to that of the pulse generator. Only a single controller is required to command all SM's simultaneously. Other similar applications include the simultaneous pointing of the many antennas of an interferometer type radio telescope array, or the simultaneous tuning of a number of circuits in a transmitter.

B. Manual Input Step Motor Servo Positioning System

Manual control of load position is accomplished by the system shown in Figure 9. A knob driven pulse generator is used to generate a number of pulses proportional to the knob rotation. Actually, two pulse trains are utilized which give direction information (CW or CCW), as well as commanding the correct number of steps. These pulses are fed to the controller, which in turn drives the SM the correct number of steps. If required, a cam switch and index indicator lamp will provide a means of initially synchronizing the knob position and the load position. Additional SM driven loads may be added in parallel if desired, or a digital "Load Position Display" driven by a SM may be added as shown. This display allows initial synchronization to be readily accomplished, and continuously displays the load position.

C. Closed Loop Step Servo Positioning System

The system shown in Figure 10 uses a position sensor and a position feedback loop. This feedback, used in conjunction with the SM provides a number of advantages as compared to the conventional servo motor with position feedback. First, the multiplicity principle still applies. Any number of loads or position display indicators may be driven in synchronism. Only one controller and one position feedback are required. The feedback, in this case, will eliminate the need for an index indicator. Second, an unweighted binary (digital) output signal indicating load position at all times is available. This digital output is readily usable by many digital data systems. Third, the closed loop step servo positioning system is inherently a time optional system. The usually complex optimum switching boundary computer required to implement a time optimal system is not required. The simple differential amplifier shown provides the required function. Controlling the gain of this amplifier sets the magnitude of the dead zone shown in Figure 10. As soon as the position error exceeds the dead zone, the servo drives at maximum effort to the commanded position. Due to the inherent rapid braking capability of the SM, it is easily able to stop within the dead zone upon reaching the commanded position. No reversal of the controller output is required to achieve rapid braking.

MANUAL INPUT STEP MOTOR POSITIONING SYSTEM

Figure 9

CLOSED LOOP STEP MOTOR POSITION SYSTEM *

Figure 10

*Patent Number
3,228,025

Under these unusual conditions, stability of the loop is easily realized. A simple rule of thumb has been developed for stability as follows:

- 1) Set the pulse generator at a rate less than the maximum synchronous rate of the SM under maximum load conditions. (highest load anticipated).
- 2) Set the differential amplifier gain such that the total dead zone width is 3 and 1/2 steps if zero overshoot is required. If a single step overshoot is tolerable, then make the total dead zone width 2 steps.

Under these conditions the system will be stable. The accuracy (worst case) will be either ± 1.75 steps or ± 1 step, depending upon the criterion chosen. If greater accuracy is desired, the gear reducer ratio may be increased so as to decrease the step size. Since the SM always runs at its maximum speed whenever the error exceeds the threshold, it has the characteristics typical of a time optimal system. This property allows the SM system to exceed the speed of response of the conventional servo system under many conditions. It is only under conditions of a large position change command, where the conventional motor has time to reach full speed; that the conventional motor can utilize its typically superior maximum full speed capability to advantage. For smaller position change commands the conventional motor does not have time to reach full speed, and also must begin decelerating considerably in advance of the final position commanded. Under these conditions the SM, running at its maximum synchronous speed all the way, will reach the desired position in less time than the conventional motor. A mathematical treatment of the use of SM's in time optimal systems can be found in Ref. I.

D. Step Motor Servo Velocity Control System

An analog voltage to pulse rate converter is utilized, as shown in Figure 11, to mechanize a velocity control system. An analog voltage input command will control both the direction and the average speed of the load. The polarity of the input voltage determines the direction (CW or CCW), and the magnitude determines the average velocity. Such a system makes a flexible analog integrator with a digital (decade counter) display. As in the previous case, an unweighted binary (digital) output is available. In this case the output represents the value of the total integral, or the load position. This system may also be used in a closed loop with interesting properties resulting. If used with position feedback, the controller effort will be as shown in the diagram of Figure 11. The system is now somewhat analogous to the conventional positioning system with velocity feedback, and also has the characteristics of a different class of time optimal system. The system as shown also performs as an ideal "brushless D.C. motor". Only crude D.C. power is required and it has inherent precise speed control.

STEP MOTOR VELOCITY CONTROL SYSTEM

STEP MOTOR SYSTEM WITH DIGITAL FEEDBACK

E. Step Motor Servo System with Digital Feedback

The rapid starting and automatic deceleration (not necessary that the error signal reverse for rapid deceleration) capabilities of the SM are also of considerable advantage in the conventional closed loop digital servo, as shown in Figure 12. The usually required binary subtractor and ladder network, required to give a region of proportional analog control, are not required with the SM system. Only a binary polarity detector is required. The stability criterion is similar to that of the SM system with analog position feedback, except that in this case the step size should be no larger than one half of a least significant bit. In addition, considerable saving in complexity is realized due to the simplicity and efficiency of the SM controller.

F. Load Adaptive Step Motor Servo System

In some applications, unpredictable variations in the magnitude and characteristics of the load can occur. With the basic step motor servo the stepping rate must be set at a value which is less than the maximum synchronous rate under the worst load condition, if stepping errors are to be avoided. The step motor servo maximum speed is then always fixed at a value consistent with the worst load, which may be unacceptably low. The system shown in Figure 13 will automatically adjust the stepping rate to the highest value which the SM can tolerate without missing steps under the existing load conditions. This same system also gives automatic acceleration control such that the motor will always start at a speed which will insure errorless stepping. Under these conditions, the motor can run at high speeds under light load conditions, and will automatically slow down if the load increases. This automatic adaptability to the load is achieved by a continuous (step by step) comparison of the actual position of the motor shaft with the commanded position. The commanded position in binary form is already available at the step servo controller. The addition of a simple (typically 2 binary bit) encoder driven by the motor shaft will provide the actual motor position. Position command is by CW or CCW discrete (change in level) inputs, typically from tape program or computer outputs, as shown in Figure 13. Actual load position data is available in unweighted binary form (each pulse, CW or CCW, represents one step actually completed). Assuming that the SM shaft is initially at rest, and that the CW discrete has just switched from false to true, detailed operation is as follows: Initially the load position and commanded position are in agreement and the pulse generator is inhibited. As soon as the CW discrete is received the inhibit is removed and the pulse generator produces a single pulse. The CW gate is open since the CW command discrete is true, and the pulse is directed to the CW controller input. The controller then switches the motor coil voltages in a few microseconds. Since the motor shaft cannot move appreciably in this short time, the binary difference is no

LOAD ADAPTIVE STEP MOTOR SERVO SYSTEM *

* Patent Number 3,359,474

Figure 13

longer zero. Whenever the binary difference is not zero, the output signal from the binary difference detector inhibits the pulse generator from generating additional pulses. When the motor shaft, as detected by the simple encoder, completes the step; the inhibit is released and the pulse generator is allowed to generate one more pulse. This process is continued as long as a step command discrete exists. Each motor step is monitored and checked for completion before another step command pulse can be generated.

The unweighted binary output signal available to the computer or programmer provides a constantly updated knowledge of the correct load position. A visual load position display may also be included if desired. Shaft encoders (step detectors) of the type described are available and will attach directly to the rear of SM's as small as size 8, and not exceed the diameter of the SM.

REFERENCES

- I. "A Time Optimal Pulse Frequency Modulated Step Motor Servo System."

Proceedings of the National Electronics Conference
Vol. XXII, 1966.

BIBLIOGRAPHY

1. L. J. Dalton, Solid State Stepping Motor Controller Providing Constant Angular Motor Shaft Velocity, The Review of Scientific Inst. Vol. 43, No. 5, May 1975, pg 829.
2. J. Proctor, Stepping Motors Moving In, Product Engineering, February 4, 1963.
3. K. Hong, A Dynamic and Static Analysis of a Solenoid Actuated Stepping Motor, IEEE Transactions on Industrial Electronics and Control Instrumentation, Vol. IECI-18, No. 3, August 1971.
4. A. V. Bianculli, Stepper Motors: Application and Selection, IEEE Spectrum, December 1970.
5. W. Fenton, Some Aspects of the Design and Operation of a High-Torque Step Motor, IEEE Transactions on Industry Applications, Vol. 1A-10, No. 1, January/February 1974.
6. J. O'Gorman, The Harmonic Drive Electromechanical Actuator, Control Engineering, December 1964.
7. D. Herdeg, Electromagnetic Harmonic Drive Low Inertia Servo Actuator, ASD-TDR-63-466, December 1963.
8. T. Fredriksen, Roland Applications of Closed Loop Stepping Motor IEEE Transactions on Automatic Control, Vol. AC-13, No. 5, October 1968.
9. G. Baty, Control of Stepping Motor Positioning Systems, Electro-mechanical Design, December 1965.
10. J. Backler, H. Himmelfarb, Stepping Out, Electromechanical Design, January 1975.
11. B. Szabados, C. D. diCenzo and N. K. Sinha, "Dynamic Measurements of the Main Electrical Parameters of a DC Machine," IEEE Trans. Ind. Gen. Appl., Vol. IGA-7, pp. 109-115, January/February 1971.
12. B. Szabados, N. K. Sinha and C. P. diCenzo, "Practical Switching Characteristics for Minimum-Time Position Control Using a Permanent-Magnet Motor," IEEE Trans. Ind. Electron. Contr. Instrum., Vol. IECI-19, pp. 69-73, August 1972.

13. N.K. Sinha, C.D. diCenzo and B. Szabados, "Modelling of DC Motors for Control Applications," IEEE Trans. Ind. Electron. Contr. Instrum., Vol. IECI-21, pp. 84-88, May 1974.
14. C.D. diCenzo, N.K. Sinha and B. Szabados, "Steppers and Permanent-Magnet Motors Compete for Control Applications," Electronic Engineering, pp. 61-63, June 1973.
15. R.B. Kieburzt, "The Step Motor - The Next Advance in Control Systems," IEEE Trans. Automat. Contr., Vol. AC-9, pp. 98-104, January 1961.
16. M.A. Delgado, "Mathematical Model of a Stepping Motor Operating as a Finite Positioner Around a Given Step," IEEE Trans. Automat. Contr., Vol. AC-14, pp. 394-397, August 1969.
17. K. Venkatratnam, S.C. Sarkar and S. Palani, "Synchronizing Characteristics of a Step Motor," IEEE Trans. Automat. Contr., pp. 510-516, October 1969.
18. K. Venkatratnam and N.C. Mouli, "Stability of a Stepping Motor," Proc. IEE, Vol. 118, pp. 805-812, June 1971.
19. P.J. O'Donohue, "Transfer Function for a Stepper Motor," Control Engineering, pp. 103-104, November 1961.
20. D.J. Robinson and C.K. Taft, "A Dynamic Analysis of Magnetic Stepping Motors," IEEE Trans. Ind. Electron. Contr. Instrum., Vol. IECI-16, pp. 111-125, September 1969.
21. N. Sinha, A. Elliot, R. Wong, A Realistic Model for Permanent-Magnet Stepping Motors, IEEE Transactions on Industrial Electronics, Vol. IECI-21, No. 3, August 1974.

APPENDIX M
COMPUTER PROGRAM LISTING FOR STEPPER MOTOR
LOAD SIMULATION

*****SOLVER VERSION OF SFDIC*****

FIND SOURCE LANGUAGE PROGRAM

```

      PD=(1,0,0,0)
STEPPER WITH SPRT JC RATIO
      PAP(ERP,EA,TORNT,KONT,VHECH,PI)
      PAP(C,STOR,KBLAP,PC)
      PAP(M,KSL,JL,N,J,ZETA)
      PR=PI*JAY
      ERROSP=NSP(ERP,-KMP,KMP)
      ERROSP=ERROSP
      CS=ABS(RP*(ERR)
      SI=CS*(R*P*ERR)
      PULSC=FSW(PULSC,TRUE,FALSE,FALSE)
      PULSC=ABS(RATEST)-ATMAX
      RATECS=FSW(RATEST,FALSE,TRUE,TRUE)
      RATEER=FSW(RATEST,TRUE,TRUE,FALSE)
      POSPCS=FSW(ERP,FALSE,TRUE,TRUE)
      POSMES=FSW(ERP,TRUE,TRUE,FALSE)
      HLD=MIN(AND(PULS,POSPCS),.001)
      PULSPS=TOR(AND(RATECS,POSME),AND(POSPCS,RATEER))
      RATHAX=ZETA*ABS(ERP)*SQ(KF/JI)
      TORKMT=FSW(SINCH*X),SI,,CS)*FSW(SIN(.5**X),-1,,0,,1.)*SW
      C=FSW(0,TORKMT,KONT,TORMAX)
      X=INT(FSW(0,+1,,0,,1.)*0,,PUL,TRUE)
      TORKAP=TORKMT-AHECH*RATE-TORNT/JN
      RATE=INT(TORKAP/JI,0.)
      P=INT(RATE,0.)
      RM=FSW(ERP,SP,-1,,0,,1.)
      RS=0.
      SN=IAS(PB,FSW(RM,TRUE,FALSE,TRUE),1.)
      PN=0/1
      TKSPRG=KS*(PN-PI*JAY)
      TKMP=HS*(LORATE-RATE/.)
      TORKLD=TKSPRG-TKMP
      TRAPLN=TORKLD-PI*0*KF*2.*ZETA*SQ(JL*KF)*LORATE
      LORATE=INT(TRAPLN/JL,0.)
      PLOAD=INT(LORATE,0.)
      RATEST=TOR,*(ERR*INT(RATEST,PC))
      FIN(.2*PC,ABS(LORATE)*SQ(KF/JI)+ABS(ERP))
      FID(T,4.)
      TOR(T,ERR,RATEST,LORATE,TORKMT)
      OUT(T,ERR,RATEST,LORATE,TORKMT)
      PLO(T,P,PLOAD)
      END

```

SORT DIAGNOSTICS FOLLOW

NOTICE

"This report was prepared as an account of work sponsored by the United States Government. Neither the United States nor the United States Energy Research & Development Administration, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness or usefulness of any information, apparatus, product or process disclosed, or represents that its use would not infringe privately-owned rights."