ORNL/FEMA-92/1

**OAK RIDGE
NATIONAL
LABORATORY**

MARTIN MARIETTA

**Electromagnetic Pulse (EMP) Survey
of the Idaho State
Emergency Operating Center,
Boise, Idaho**

R. I. Crutcher
M. E. Buchanan
R. W. Jones

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

MANAGED BY
MARTIN MARIETTA ENERGY SYSTEMS, INC.
FOR THE UNITED STATES
DEPARTMENT OF ENERGY

OSTI
MAY 27 1992

This report has been reproduced directly from the best available copy.

Available to DOE and DOE contractors from the Office of Scientific and Technical Information, P.O. Box 62, Oak Ridge, TN 37831; prices available from (615) 576-8401, FTS 626-8401.

Available to the public from the National Technical Information Service, U.S. Department of Commerce, 5285 Port Royal Rd., Springfield, VA 22161.

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

**ELECTROMAGNETIC PULSE (EMP) SURVEY OF THE
IDAHO STATE EMERGENCY OPERATING CENTER,
BOISE, IDAHO**

R. I. Crutcher
M. E. Buchanan
R. W. Jones

Date Published—February 1992

Notice: This document contains information of a
preliminary nature. It is subject to
revision or correction and therefore does
not represent a final report.

Prepared for the
FEDERAL EMERGENCY MANAGEMENT AGENCY
Washington, DC 20472
under Interagency Agreement DOE 1459-1086-A1/FEMA EMW-84-E1459

Prepared by the
OAK RIDGE NATIONAL LABORATORY
Oak Ridge, Tennessee 37831-6285
managed by
MARTIN MARIETTA ENERGY SYSTEMS, INC.
for the
U.S. DEPARTMENT OF ENERGY
under contract DE-AC05-84OR21400

MASTER

TABLE OF CONTENTS

	Page
LIST OF FIGURES	v
LIST OF FEMA DRAWINGS	ix
I. GENERAL	1
II. BACKGROUND	2
III. POWER SYSTEM PROTECTION	2
A. Electrical Power Distribution System	2
1. Emergency Generator Protection	3
2. Main Panel Protection	3
3. Power Panel Protection	4
4. Additional Equipment Protection	5
B. Electrical Motors and Life-Support Systems	5
C. Fluorescent Lighting	6
D. Emergency Lighting	6
IV. ANTENNA AND RADIO SYSTEM	7
A. Antenna System	7
1. Roof-Level Antenna Grounding	7
2. Electrical Chase Coaxial Cable Grounding	9
3. Subbasement Coaxial Cable Grounding	9
4. Remote Antenna and Cable Grounding	11
B. Radios and Control Stations	11
1. Transceiver Protection	11
2. Control Station and Terminal Protection	13
V. FNARS SHIELDED ROOM	15
VI. TELEPHONE AND CONTROL LINES	16
A. Telephone Lines	16
B. Control Lines	17
1. Communications Room Grounding and Cable Protection	17
2. Granger Control Cable Protection	17
APPENDICES	47

LIST OF FIGURES

Figure	Page
1 Emergency generator and day tank	19
2 Starter solenoid for the emergency generator	19
3 Battery-charging generator for the emergency generator	20
4 Automatic transfer switch	20
5 Panel EM in the equipment room	21
6 Power panel BHB	21
7 Power panel BLC	22
8 Power panel HEM in the electrical and mechanical room	22
9 Step-down transformer TR6 in the subbasement	23
10 Power panel LR in Room 57	23
11 Input to one of two power filters for the shielded room	24
12 Power panel inside the shielded room	24
13 Circuit breaker box in the Harris transmitter cabinet	25
14 Motor controller for the emergency well pump	25
15 Overall front view of the motor control center	26
16 Control contactor for one of the pumping systems	26
17 Emergency lighting unit for the office area	27
18 Base of the Spira-cone antenna	27
19 Spira-cone antenna on the eastern end of the roof	28
20 Balun for the state high-frequency fan doublet antenna	28
21 State antennas on the roof of the building	29

LIST OF FIGURES (continued)

22	FM receive antenna mounted on the fire standpipe	29
23	Entry point for the state coaxial cables in the third-floor electrical room	30
24	Coaxial cables and conduits in the third-floor electrical room	30
25	Coaxial cables and conduits in the basement electrical room	31
26	Junction box in the air ventilation duct adjoining the subbasement	31
27	Three ground rods in the air duct adjacent to the subbasement	32
28	Penetration where coaxial cables enter the subbasement from the air duct . . .	32
29	Point in the subbasement where coaxial shields are grounded	33
30	Ground rod adjacent to transformer TR6	33
31	Penetration for state coaxial cables into the subbasement	34
32	Water and drain lines used as a ground for the shielded room	34
33	Remote receive antennas for the Harris system	35
34	Coaxial cables from the Harris remote receive antennas	35
35	Well water main supply line	36
36	National Guard radio in the communications room	36
37	State Emergency Operating Center high-frequency radio	37
38	VHF packet radio system	37
39	Emergency Broadcasting System remote pickup in the Hall of Mirrors Building	38
40	Rear of the Emergency Broadcasting System remote pickup in the Hall of Mirrors Building	38
41	Datapoint terminal on the Department of Transportation network	39
42	Modem for the Datapoint terminal	39

LIST OF FIGURES (continued)

43	Telephone connecting to the National Warning System network	40
44	Control station for the Civil Defense microwave network	40
45	Equipment for the Federal Emergency Management Agency National Teletype System and the Idaho Law Enforcement Teletype System	41
46	Motorola remote handset control for the Emergency Broadcasting System remote pickup station	41
47	Entrance door to the shielded enclosure	42
48	Honeycomb filter on the air intake for the shielded room	42
49	Fan and honeycomb filter for the air exhaust for the shielded room	43
50	Coaxial cable penetrations to the shielded room	43
51	Protection block for signal lines entering the shielded room	44
52	Telephone connection blocks for the EOC and the communications room . . .	44
53	Penetration at the rear of one console	45
54	Rear of the console with control line terminal blocks	45
55	Control box for the high/low switch on the Granger Spira-cone antenna	46

LIST OF FEMA DRAWINGS

FEMA No.		Page
0023-001	Idaho State Emergency Operating Center single line electrical power diagram	59
0023-002	Idaho State Emergency Operating Center partial basement and communications room equipment grounding system	60
0023-003	Idaho State Emergency Operating Center roof grounding system and antenna counterpoise system	61
0023-004	Idaho State Emergency Operating Center antenna counterpoise system hardware details	62
0023-005	Idaho State Emergency Operating Center sub-basement grounding system	63
0023-006	Idaho State Emergency Operating Center shielded room elevation, control wiring, and antenna penetrations	64
0023-007	Idaho State Emergency Operating Center communications room grounding system	65

I. GENERAL

The purpose of this report is to develop an engineering design package to protect the Federal Emergency Management Agency (FEMA) National Radio System (FNARS) facilities from the effects of high-altitude electromagnetic pulses (HEMPs). This report was developed specifically for the Idaho State Emergency Operating Center (EOC) in Boise, Idaho.

It is highly probable that there will be a heavy dependence upon high-frequency (hf) radio communications for long-haul communications following a nuclear attack on the continental United States, should one occur. To maintain the viability of the FEMA hf radio network during such a situation, steps must be taken to protect the FNARS facilities against the effects of HEMP that are likely to be created in a nuclear confrontation.

The FNARS equipment has already been designed, built, and installed so that little opportunity exists for equipment design changes that could raise the threshold levels at which malfunctions occur. The solution must then be to reduce HEMP-induced stresses on the system by means of tailored retrofit hardening measures using commercial protection devices when available.

It is the intent of this report to define the particular hardening measures that will minimize the susceptibility of system components to HEMP effects. To the extent economically viable, protective actions have been recommended for implementation, along with necessary changes or additions, during the period of the FNARS upgrade program.

This report addresses electromagnetic pulse (EMP) effects only and disregards any condition in which radiation effects may be a factor. It has been established that, except for the source region of a surface burst, EMP effects of high-altitude bursts are more severe than comparable detonations in either air or surface regions. Any system hardened to withstand the more extreme EMP environment will survive the less severe EMP conditions. The threatening environment will therefore be limited to HEMP situations. (In this report, HEMP will be referred to as EMP.)

This report identifies the systems in the facility that are considered critical for emergency operation and analyzes them for EMP coupling paths. Upon establishing these paths into the system, the system is then analyzed for its failure threshold. The protection of a system from an EMP is most easily accomplished by the elimination or restriction of the EMP coupling paths. EMP coupling paths are identified as directly connected, directly induced, and/or secondarily induced paths. Directly connected EMP paths are provided by power distribution systems, telephone lines, control cables, water pipes, etc. Directly induced EMP paths include doors, windows, ventilation systems, cooling systems, and any other physical opening into the facility. Secondarily induced EMP paths are associated with currents being induced into metal conductors in the vicinity of other conductors carrying EMPs. The elimination or restriction of these EMP coupling paths into the facility is of primary importance in protecting the FNARS facility.

To identify the critical systems in the facility and the EMP coupling paths affecting these systems, an EMP survey of the facility was conducted. Results of the survey and

of the survey and tests are presented along with recommendations for tailored retrofit hardening measures to be implemented to protect the facility from EMP.

II. BACKGROUND

An initial preliminary EMP survey of the Idaho State EOC in Boise was conducted July 25-27, 1989, by M. E. Buchanan, R. I. Crutcher, and R. W. Jones of Oak Ridge National Laboratory (ORNL) on behalf of FEMA. Fred Bretsch and Andrew Hendrickson of FEMA Region X assisted with the survey. Technical support was furnished by Pat Frischmuth of the Idaho Bureau of Disaster Services.

The initial site survey was performed to obtain firsthand information necessary to assess exposure potential, adequacy, and/or deficiencies in existing protection measures and to determine the amount of documentation and drawings available for use in the EMP protection engineering design package. Primary emphasis was placed on obtaining information about the protection of the FNARS radio room (communications shielded enclosure room). The original EMP protection and shielded communications room were installed in 1978. Because of the lapse of time since the installation of EMP protective devices and because new equipment has been added, it was determined that a comprehensive EMP survey was necessary.

III. POWER SYSTEM PROTECTION

A. Electrical Power Distribution System

The Idaho State EOC is in the basement of the Len B. Jordan (LBJ) Building, a multistory office structure, at 650 West State Street in Boise. The FNARS radio room/communications shielded enclosure room is in the basement, adjacent to the general communications center. Electrical power for the building is furnished from the commercial grid through underground lines and a transformer that provides 277/480-V three-phase grounded wye.

The electrical power system provides an excellent direct-connection EMP coupling path to critical communication equipment, and it must be considered in the development of the EMP engineering design protection plan. EMP protective measures for power connections are designed to protect principally against common-mode (phase-to-ground) transients. Localized protection distributed over the power system uses metal oxide varistors (MOVs) in the main breaker panel and critical power distribution panels. These devices are to be installed on the load side of any three adjacent breakers (phases) to metal case as a ground, with the device lead length as short as possible.

The materials list in Appendix A-1 will assist in identifying the specific protectors shown in various diagrams of the survey (see FEMA drawings). The basic protector number is shown inside the circle on the diagram, with the number of units required below and left of the circle. For example, the transfer switch shown in FEMA Dwg. 0023-001 indicates the symbol $3\textcircled{4}_o$. Checking the materials list, we see that this is an MOV transient suppressor (4), a V275HE250 (o), and that three each are required at this location (3).

All EMP transient arresters and jumpers recommended and shown in this report are to be located such that minimal lead lengths are required for their installation. Induced EMP transient currents have exceptionally fast leading-edge gradients, and protector lead inductance can result in significant inductive voltage drops, reducing a protector's effectiveness if it is not properly installed.

FEMA Dwg. 0023-001 is a single-line electrical power distribution diagram showing the locations for installation of recommended EMP protection devices for the electrical power system at the EOC. These EMP suppressors will reduce the direct EMP coupling paths through the electrical power system to critical areas in the facility. FEMA Dwg. 0023-001 through 0023-007, Figs. 1 through 55, and Appendix B describe the locations and methods for installing the protection devices.

1. Emergency Generator Protection

The emergency power generator for the EOC is in the basement electrical and mechanical room. FEMA Dwg. 0023-002 includes a placement drawing for the equipment room. An Onan 150-kW automatic-start generator supplies power for the EOC, the communications center, and the life-support equipment. The output of the generator is a 277/480-V three-phase grounded wye configuration.

Figure 1 shows the overall view of the generator and day tank. The conduit employed for the generator wiring does not contain a flexible section. The day tank pump, to the left of the generator, does have flexible conduit that has been paralleled by conductive jumpers. These jumpers are in good condition and should be left in place.

The starter solenoid for the emergency generator is shown in Fig. 2. This solenoid has V39ZA6 MOVs installed on the solenoid terminals. A bead of silicone rubber cement should be used to mount the body of the MOV to the solenoid housing to prevent vibration from breaking the MOV leads.

Figure 3 shows the dc generator used to charge the starting batteries for the emergency power generator. The dc generator has a V130LA10A MOV on the output terminal, and the voltage regulator has two V130LA10A MOVs installed. The body of each MOV should be fastened to the generator or voltage regulator structure with a bead of silicone rubber cement to prevent vibration from breaking the leads.

An external ac-powered battery charger is not installed on this generator. The batteries are kept charged by running the generator once every two weeks.

2. Main Panel Protection

The design philosophy of the power system calls for staged protection with MOVs installed in successive power panels. The single-line power diagram with the recommended protection is shown in FEMA Dwg. 0023-001. The 277/480-V power enters through a 2000-A main panel that can be opened by only the building electrical contractor. Therefore, the first stage of protection will be installed in the automatic transfer switch, shown in Fig. 4. The transfer switch had V480PA40 MOVs installed from each phase to ground on the commercial power terminals, the generator supply terminals,

and the load terminals. Existing protection practices do not place MOVs on the generator side of the transfer switch, and these devices should be removed. The V480PA40 MOVs on the commercial power terminals should be removed and replaced with V275HE250 MOVs installed from each phase to ground. The HE type MOVs require that the second terminal be connected to ground, as illustrated in Appendix B-1. It is important to keep lead lengths short when making these connections. The V480PA40 MOVs on the load side of the transfer switch should be removed and replaced by V275PA40A MOVs. The new MOVs can be mounted in place of the existing devices. The remote start line between the generator and the transfer switch has V39ZA6 MOVs installed at the terminals inside the transfer switch cabinet. These MOVs should be left in place.

From the transfer switch, the emergency power feeds to the EM section of the electrical switchgear. Several of the circuit breakers in the EM panel are shown in Fig. 5. V275PA40A MOVs should be installed on the load side of the breaker marked "Panel BHB." Install the MOVs on the metal wall to the right of the wires and attach the leads to the breaker terminals.

3. Power Panel Protection

The power panel BHB, shown in Fig. 6, had V480PA40 MOVs installed during the original EMP protection effort. The 480-V devices are installed from phase to ground on the 277-V line and do not provide the level of clipping protection that is required. These devices should be replaced by V275PA40A MOVs installed from each phase to ground on the output of three adjacent breakers. The 275-V MOVs can be installed in the physical position occupied by the existing 480-V devices.

Figure 7 shows the MOVs in power panel BLC, which supplies 120/208-V power to the EOC area. The panel has V130PA20 MOVs installed from each phase to ground and from the neutral to ground and requires no further protection. Panel LEB is adjacent to panel BLC and is fed from panel BLC. The proximity and wiring configuration are such that protection is not required for panel LEB.

Panel HEM in the electrical and mechanical room is shown in Fig. 8. This panel is wired for 277/480 V and has V480PA40 MOVs installed from each phase to ground. These MOVs should be replaced by V275PA40A MOVs installed with the same electrical and mechanical connections.

Step-down transformer TR6, in the subbasement below the EOC, is shown in Fig. 9. This transformer reduces the 277/480-V feed from panel EM to 120/208 V to supply panel LR in the communications room. The flexible conduits on TR6 should be shunted by No. 4 AWG copper conductors. The clamps on the flexible conduit have screws that can be used to attach lugs for the copper conductor.

Figure 10 shows panel LR in Room 57. The panel has V130PA20 MOVs installed from each phase to ground and is considered to be adequately protected.

The input to one of the power filters at the shielded room penetration is shown in Fig. 11. A V130PA20A MOV should be installed on the input of each filter, from the

line terminal to case ground. Use care when installing the MOV to avoid breaking the filter insulator.

Figure 12 shows the power panel inside the shielded room. The filter output terminals are in the bottom of the panel and feed into the panel main breaker. The circuits inside the shielded room should be protected by installing V130PA20A MOVs on the outputs of two adjacent breakers in this box.

4. Additional Equipment Protection

In addition to the MOVs installed for power protection at the panels or the equipment, plug-in MOVs will be installed at the receptacles feeding equipment at several locations. The plug-in devices are employed in those locations where a sensitive piece of electronic equipment is powered from a receptacle and the power conductor terminals are not accessible for installing protectors with leads.

A plug-in MOV should be installed in the receptacle that powers the National Guard radio and Datapoint terminal in the communications room. A plug-in MOV should also be installed on the receptacle that powers the Civil Defense microwave control station. The FEMA National Teletype System (FNATS) equipment and the Idaho Law Enforcement Teletype System equipment also require a plug-in protector unit.

The Emergency Broadcasting System (EBS) remote pickup (RPU) station in the Hall of Mirrors Building will require a plug-in MOV on the ac power receptacle feeding the station equipment. A plug-in MOV and grounded cube tap will be required for the power to the EBS RPU control head in the EOC office area.

The Harris FNARS radio equipment in the shielded room does not now have EMP protection past the filtering at the power panel. Although the filtering may be sufficient to protect the equipment, additional protection would be obtained by installing MOVs at the power box in the transmitter rack. The circuit breaker box, shown in Fig. 13, should have V130PA20A MOVs installed from the terminals on the load side of the breaker to ground.

B. Electrical Motors and Life-Support Systems

Electrical motors with essential loads (life-support equipment) should receive further EMP protection by placing MOVs as close to the motors as possible. The back electromotive force caused by the electrical breaking of inductive loads will cause premature failure of installed MOVs; therefore, EMP protection of this type should consist of MOVs installed on the electrical line side of the electrical motor starting/stopping contactors, rather than on the load side.

The main motor control distribution panel is a portion of the EM section of the switchgear. The switchgear will receive protection as described in Sect. II.A.2 of this report. Individual motor controllers will have the EMP protection upgraded as detailed below.

A detail of the controller and contactor for the emergency well pump is shown in Fig. 14. The incoming electrical line is now protected by V480PA40 MOVs installed from each phase to panel ground. These MOVs should be replaced by V275PA40A devices installed in the same location as the old units. The control coil has a V130LA10A MOV installed across the coil terminals. This MOV should be left in place.

Figure 15 shows an overall front view of the motor control center in the EM section of the switchgear. Other contactors in this panel besides the well water pump include the EOC air supply fan, the EOC air return fan, and the fire pump. Each of these is currently protected with V480PA40 MOVs, which should be replaced by V275PA40 devices as described for the well pump.

A control contactor for one of the pumps is shown in Fig. 16. The line side of this contactor is fed from the adjacent power panel HEM in the electrical and mechanical equipment room. Because panel HEM will receive protection, no devices will be installed in the pump control box.

The refrigeration equipment in the kitchen area is not connected to emergency power. The state EOC personnel should determine whether the emergency generator will handle the additional load from the refrigerators and, if feasible, connect the refrigeration circuits to emergency power. Transient protection should be added to the refrigeration circuits if these are placed onto an emergency power circuit.

C. Fluorescent Lighting

The fluorescent lights in the EOC should be EMP protected by installation of an MOV directly across the ballast transformer of the light fixture to be protected (see Appendix B-2). The fluorescent lamps in the EOC area operate from 277-V power. These fixtures should be protected by installing a V275LA20A MOV inside the fixture housing across the ac power leads to the ballast. Heat-shrinkable tubing should be used to insulate the bare leads of the MOV.

The EOC communications area, offices, hallways, operations room, cafeteria, and kitchen have a total of 289 fluorescent lighting fixtures. Half of these fixtures (145) should be protected in the manner described above. The fixtures receiving protection should be chosen such that the locations of the surviving lights will be distributed around the area of need.

D. Emergency Lighting

The emergency lighting unit for the office area is shown in Fig. 17. This type of lighting unit has a solid state charger circuit with EMP-susceptible diode rectifiers that should be EMP protected. EMP protection can be best accomplished by installing MOVs on the primary side of the step-down transformer, from the high (phase) side of the ac line to the low (neutral) side of the ac line, and from the high (phase) side of the ac line to ground. The input to this lighting unit is 120 V and should be protected with V130LA10A MOVs installed from the line to neutral and line to ground. The low-voltage secondary of the supply is contained within the localized area, and protectors are not required on the secondary side of the light.

Two additional emergency lighting units are installed in the hallway of the EOC area. These lights are identical to the one in Fig. 17 and should be protected in a similar manner with V130LA10A MOVs installed on the ac line from hot to neutral and from hot to ground.

IV. ANTENNA AND RADIO SYSTEM

A. Antenna System

The Granger Spira-cone antenna and the state hf and vhf antennas for the EOC are installed on the roof above the third floor of the building. Two receive antennas for the Harris equipment are installed on the roof of another building. The coaxial cables between the roof-mounted antennas and the EOC take two separate paths on opposite sides of the building. The coaxial cables from the remote antennas take a third route. Discussion of antenna protection will begin with grounding on the roof level. Grounding of the coaxial cables for the vertical runs through the electrical chases will be discussed next, followed by the grounding for the coaxial cables in the subbasement area. Finally, protection will be discussed for the remote receive antennas and their associated coaxial cables.

1. Roof-Level Antenna Grounding

Most antennas for the EOC are situated on the third-floor roof of the building. The grounding for these antennas and the associated roof-mounted equipment is not considered sufficient for the system to survive an EMP event. Recommendations are made in this section for installation of a counterpoise grounding network at roof level to equalize the voltage potential among the various pieces of equipment. Personnel from FEMA Region X have taken exception to the installation of a counterpoise on the basis that the Spira-cone and hf antennas are not designed to be operated in close proximity to a counterpoise. Although the theoretical patterns for these antennas are calculated for elevated operation, practical installations encounter steel reinforcing rods in the roof, sheet metal panels beneath the concrete, and metal structures above the roof. The Spira-cone at Boise is installed adjacent to a metal penthouse with one of the tubular booms of the antenna within 2 ft of the penthouse. The penthouse wall will affect the radiation pattern of the Spira-cone to a much greater extent than would a counterpoise at roof level, especially considering that the Andrew Corporation catalog confirms that the Model 3002 antenna can be either roof or ground mounted. Installation of a similar counterpoise under a Spira-cone at another state EOC did not appear to affect the pattern of the antenna. For these reasons, this report will recommend installation of the counterpoise, although Region X personnel may choose not to install it.

As mentioned in the preceding paragraph, the grounding of the roof-mounted antennas is not sufficient to protect the equipment in the event of an EMP occurrence. The Spira-cone antenna has one No. 8 AWG ground wire that runs from the tower base, shown in Fig. 18, to a ground rod in the subbasement. The balun for the state fan doublet antenna has a single ground wire that connects to an electrical conduit on the third floor. The lack of availability of a good earth ground dictates that a counterpoise be established at the roof level. This counterpoise will connect to the metal masts and towers of the antennas, the balun for the fan doublet, and the metal penthouse as building

structure. FEMA Dwg. 0023-003 gives the layout for the existing antennas and the recommended routing and placement of counterpoise grounding conductors. The counterpoise should attach to all metal components and assemblies on the roof to form a unified metal structure for the reflection and conduction of EMP currents.

Figure 19 shows the Spira-cone antenna on the east corner of the roof. The tower for the Spira-cone will serve as the hub for the eastern portion of the counterpoise, as illustrated in FEMA Dwg. 0023-003. The balun for the fan doublet on the state hf radio is shown in Fig. 20. The center of the fan doublet antenna will locate the hub of the western portion of the counterpoise. The ground connection for the balun should be attached to the center of the hub. The state antennas for the vhf packet radio and the National Guard radio, a support tower for the fan doublet, and the remote radiation monitor are shown in Fig. 21. These antenna mounts and the radiation detector should be attached to the counterpoise at the points illustrated in FEMA Dwg. 0023-003.

The details of the grounding counterpoise for the roof level are shown in FEMA Dwg. 0023-004. The counterpoise will be constructed from 1/4-in. copper tubing with fittings at the tubing connection points. A length of No. 4 AWG copper wire should be soldered into a tee at those points where physical connections will be made to towers, masts, the penthouse structure, and the two wires that will run to the grounds in the subbasement. Details of the connections to the structures are given in FEMA Dwg. 0023-004. The tubing for the counterpoise should be attached to the roof by plastic roofing cement applied at the cross points and periodically along the perimeter of the outer loops.

A manifold assembly will be designed, in accordance with FEMA Dwg. 0023-004, to fit around the pedestal of the Spira-cone and provide a tie point for the eight radials around the Spira-cone. The other ends of these radials will terminate in a ring that bounds the roof area on two sides and the penthouse on two sides. An intermediate connection ring will reduce the area of each enclosed loop. Reducing the enclosed area raises the resonant frequency of the loop and improves the loss mechanism of the counterpoise by creating intermediate circulating currents to shunt the EMP energy. A No. 4 AWG copper conductor will run from the base of the Spira-cone/hub assembly to ground points in the subbasement, following the route of the existing coaxial cables.

A hub assembly for the counterpoise under the state antennas will be fabricated as detailed in FEMA Dwg. 0023-004. This portion of the counterpoise consists of eight radials forming a circle under the fan doublet antenna. The balun will ground to the center of the counterpoise circle, and the other state antennas, the fan doublet support masts, and the radiation detector will ground to the counterpoise at connection points indicated in FEMA Dwg. 0023-003. The radials under the state antennas are bounded by an outer perimeter loop and divided by an inner loop to raise the resonant frequency and EMP loss mechanisms. The state counterpoise and the Spira-cone counterpoise are connected by three conductors: two around the penthouse and one diagonal. The state counterpoise has a No. 4 AWG copper conductor connected at the northwest end. This copper conductor will follow the path of the existing state coaxial cables, grounding to the electrical conduits in the electrical chase and to several pipes in the subbasement.

The FM antenna shown in Fig. 22 will not be connected to the counterpoise at this time. This antenna is mounted to a vertical fire standpipe that is not attached to either the building ground or the water system. The standpipe can act as an antenna for EMP with unwanted currents conducted onto the counterpoise if the standpipe and counterpoise are connected. The shield of the coaxial cable to the FM antenna will be grounded at the subbasement level, but it is recommended that the FM antenna be relocated from the standpipe to a smaller mast, if possible. The smaller mast can then be attached to the counterpoise without affecting operation of the counterpoise.

2. Electrical Chase Coaxial Cable Grounding

The coaxial cables for the state antennas are routed over the edge of the roof and through a wall penetration to the electrical chase. The entry point for the coaxial cables is shown in Fig. 23. The existing ground from the hf antenna balun is connected to the conduits in the top of the figure. This ground should be removed when the balun is grounded to the counterpoise.

A No. 4 AWG copper conductor should connect to the northwest end of the counterpoise and run with the coaxial cable bundle to grounding points in the subbasement. The inductance of the grounding connection can be reduced by paralleling the wire with an electrical conduit that extends from the basement to the third floor. Figure 24 shows the electrical conduit in the third floor electrical room. The No. 4 AWG conductor should be routed with the coaxial cable bundle to the right of the conduit. A 4-in. grounding clamp should be added a few inches above the floor to make electrical connection between the copper conductor and the electrical conduit.

Figure 25 shows the same conduit on the basement level. The No. 4 AWG grounding conductor that will be added to the coaxial bundle should be bonded to the conduit with a 4-in. grounding clamp a few inches above floor level. The conductor will continue into the subbasement where connections will be made to other grounding points. It should be noted that the vertical conduits shown in Fig. 25 are resting on polyvinylchloride (PVC) sweep cells at the floor level. As a matter of electrical safety, the building electrician should verify that an electrical ground exists between the building electrical system and the boxes attached to this conduit.

3. Subbasement Coaxial Cable Grounding

Coaxial cables are routed from the roof antennas through two separate vertical shafts to the subbasement before entering the communications room. Several grounding points are accessible on the subbasement level, and these will be utilized to drain transient currents from the coaxial cable shields. The No. 4 AWG copper conductors from the roof counterpoise will be attached to these grounds. Layouts of the cable routing and grounding attachments are shown in FEMA Dwg. 0023-005. As indicated in the drawing, the No. 4 AWG copper wire from the counterpoise under the state antennas will run with the state coaxial cables and attach to the water pipes that are a ground for the shielded room. Likewise, the No. 4 AWG ground from the Spira-cone antenna is routed with the coaxial cables from that antenna. This grounding wire will connect to a water line and to the grounding rod at transformer TR6.

Figure 26 shows a junction box in the air ventilation duct adjoining the subbasement. The vertical conduit contains the coaxial cables from the Spira-cone antenna and the horizontal conduit contains the cables that go to the shielded room. Additionally, the No. 8 AWG ground wire from the Spira-cone antenna exits the conduit at this point and attaches to a ground rod. A No. 4 AWG copper grounding wire should be routed through the junction box with these coaxial cables from the Spira-cone antenna to the shielded room ground. A branch from this grounding wire should be attached to the three ground rods shown in Fig. 27. The new No. 4 AWG grounding wire should connect to the three ground rods using clamps and should utilize the route of the existing No. 8 AWG wire to reach the junction box.

The penetration from the air duct to the subbasement is shown in Fig. 28. The No. 4 AWG grounding wire will be routed through this conduit. A black door connecting the subbasement to the air duct is to the right of the conduit penetration. Caution should be exercised when opening this door because the differential air pressure between the subbasement and the ventilation duct causes the door to open abruptly. It should also be noted that the floor is 3 ft lower on the back side of the door than on the front side.

Figure 29 shows a point in the subbasement where the shields of the coaxial cables to the Spira-cone are grounded to water and waste lines. The No. 4 AWG copper wire that will be installed with the coaxial cable bundle should ground to these pipes as it passes this location.

The ground rod adjacent to transformer TR6 is shown in Fig. 30. This rod will be the terminating point for the No. 4 AWG ground from the Spira-cone antenna. The existing No. 4/0 AWG wire that is attached to the rod is one of the grounds to the shielded room. The existing ground wire should be left in place when the No. 4 AWG is added.

Figure 31 shows the state antenna coaxial cables entering the subbasement. A No. 4 AWG copper grounding conductor will be added to this bundle, extending from the counterpoise on the roof to the water and drain lines shown in Fig. 32. These lines now serve as one ground for the shielded room, and attachment to this point will reduce the differential voltages among the building grounds.

Branches from the No. 4 AWG should be routed to penetrations in the ceiling that lead to the consoles in the basement. Routing for these lines is indicated on FEMA Dwg. 0023-005. The No. 4 AWG branches will be used to establish grounds for the console equipment, as discussed in Sect. VI.B.1.

The shields for the state coaxial cables should be grounded in the subbasement to the No. 4 AWG copper wire before penetrating to the communications room. This grounding can be accomplished by using tinned braid, a hose clamp, and a conductive epoxy mixture. The connection is made by removing a small ring of the outer jacket insulation from the cable, exposing the cable shield. The void is filled with the conductive epoxy and wrapped with the tinned braid for approximately one and one-half turns before clamping with a stainless steel hose clamp. Conductive cement is used to fill any voids at this connection. Because these cables are in a dry location inside the building, PVC electrical tape is sufficient to seal the connection after the epoxy dries. (Refer to

Appendix B-3 for a pictorial view of a typical coaxial grounding connection without silicone and PVC tape.) A split bolt can be used for making a connection to the No. 4 AWG ground wire that will be routed with the coaxial cable bundle.

4. Remote Antenna and Cable Grounding

Remote receive antennas for the Harris equipment are mounted on the roof of the Towers Building, approximately 2000 ft from the EOC. Figure 33 shows the vertical whip on the left and the B&W antenna on the right. Both antennas are mounted to the metal siding of the penthouse on the Towers Building. Because of the remoteness of these antennas, further grounding will not be added at this location.

The coaxial cables from the antennas on the Towers Building are routed through an underground tunnel to the LBJ Building. The first convenient grounding point in the LBJ Building is in the electrical and mechanical equipment room. Figure 34 shows a horizontal wire bundle that contains the coaxial cables for the remote receive lines. The two RG-213 cables in this bundle should have the shields grounded to a No. 4 AWG copper conductor that will connect to the well water main supply line.

The coaxial cable shields can be grounded by using tinned braid, a hose clamp, and a conductive epoxy mixture. The connection is made by removing a small ring of jacket insulation from the cable, exposing the cable shield conductor. The void is filled with the conductive epoxy and wrapped with the tinned braid for approximately one and one-half turns before clamping with a stainless steel hose clamp. Conductive cement is used to fill the voids at the connection. Because these cables are in a dry location inside the building, PVC electrical tape will be sufficient to seal the connection after the epoxy dries. The other end of the braid will be connected to a No. 4 AWG ground wire by using a split bolt clamp. A pictorial view of a typical coaxial grounding connection (without silicone and PVC tape) is shown in Appendix B-3.

The other end of the ground wire should attach to the water well main supply line, shown in Fig. 35. An additional grounding clamp should be added to the water pipe so that the existing ground wire and clamp are not disturbed.

B. Radios and Control Stations

The communications systems for the EOC include transceivers, control stations for remote links, and teletypes and terminals for text communications. This report will specify protection for the transceiver, but hardening of the remote links is beyond the scope of the current protection program. Likewise, the protection specified for the teletypes and terminals will limit the transients reaching the local equipment but will not safeguard the networks or the central computers.

1. Transceiver Protection

Most of the state radios that are to be protected are installed in the communications room. The locations and suggested protection devices for these radios are indicated in FEMA Dwg. 0023-002. Additionally, a summary of the protection devices recommended for the radio equipment is presented in Table 1.

Table 1. Electromagnetic pulse protection device recommendations for the radios at the Idaho State
Emergency Operating Center (EOC), Boise, Idaho

Designation	Frequency (MHz)	Transmit power (W)	Antenna connector	Transmitter protector	Receiver protector	Power protector	Control line protector
National Guard	453.275	60	UHF	FCC-250-230-UHF	FCC-450-3.3-L	Plug-in MOV	
State HF (RF-3200)	3-30	125	UHF	FCC-250-470-UHF	FCC-450-3.3-L	Plug-in MOV	
VHF packet radio	145	5	UHF	FCC-250-75-UHF		Plug-in MOV	
EBS RPU ^a	167	60	UHF	FCC-250-230-UHF	FCC-450-3.3-L	Plug-in MOV	1.5KE200C
District mobile radios ^b	3-30	125	UHF	FCC-250-470-UHF			

^a Emergency Broadcasting System remote pickup station in Hall of Mirrors Building.

^b Mobile radios to be used for District EOCs.

The National Guard radio is shown in Fig. 36. The radio in use at the time of the survey was a 60-W station operating on 46.95 MHz. This station is scheduled to be replaced by a system operating on 453.275 MHz with 60 W of transmit power. The transmitter on the new station should be protected by installing an FCC-250-230-UHF coaxial protector on the antenna line at the rear of the station. The receiver should be protected by installing an FCC-450-3.3-L diode bridge on the receive line inside the radio, after the transmit/receive (T/R) switch. Power to the radio will be protected by a plug-in MOV installed at the ac receptacle that powers the radio.

Figure 37 shows the state EOC hf radio. This radio is a Harris model RF-3200 SSB unit that can deliver 125 W of power over the 3- to 30-MHz band. The transmitter should be protected by installing an FCC-250-470-UHF coaxial protector on the antenna cable at the back of the radio. The receiver should be protected by installing an FCC-450-3.3-L diode bridge across the receive line after the T/R switch inside the radio. A plug-in MOV should be installed at the receptacle that powers the radio.

The packet radio system is shown in Fig. 38. The system consists of a 5-W Kenwood walkie-talkie operating on 145 MHz, a modem unit, a computer, and a printer. The antenna line should be protected by installing an FCC-250-75-UHF coaxial protector on the antenna lead at the UHF connector bulkhead in the rear of the cabinet. The walkie-talkie is powered by a dc supply on a shelf of the cabinet. The ac power for the system should be protected by a plug-in MOV at the receptacle.

The state has six hf mobile radios that will be carried to the district EOCs during an alert condition. These are 125-W radios that cover the 2- to 30-MHz range. FCC-250-470-UHF coaxial tees will be supplied to protect the antenna input to these radios.

Figure 39 shows the EBS RPU in the Hall of Mirrors Building. The station operates in the 167-MHz frequency range with a power of 60 W. The transmitter should be protected by installing an FCC-250-230-UHF coaxial protector on the antenna input. The receiver should be protected by installing an FCC-450-3.3-L diode bridge on the receive line after the T/R switch. This station is wired for use with a battery backup, but the battery is not currently installed. The state should consider either replacing the battery or relocating the station to an area with emergency power. In either case, a plug-in MOV should be installed on the ac power receptacle feeding this station. The terminals for the control line are shown in Fig. 40. The control lines use a dc current loop and should be protected by installing 1.5KE200C bipolar zener diodes from each conductor of the pair to chassis ground.

2. Control Station and Terminal Protection

Most of the control stations and terminals to be protected are in the communications room. FEMA Dwg. 0023-002 is a placement diagram for these stations and terminals, and the recommended protection devices for this equipment are shown in the drawing. A complete listing of recommended protection devices for all the control stations and terminals is given in Table 2.

Figure 41 shows the Datapoint 8200 terminal that is used for electronic mail on the Idaho Department of Transportation network. The terminal is connected to a thin-wire Ethernet-type network through the modem in Fig. 42. An FCC-450-3.3-BNC coaxial protector should be installed on the coaxial line at the modem. A plug-in MOV protector will be supplied for the receptacle that powers the terminal and modem.

Table 2. Electromagnetic pulse protection device recommendations for the terminals and control stations at the Idaho State Emergency Operating Center (EOC), Boise Idaho

Device	Function	Signal protector	Power protector
Datapoint 8200 terminal	Department of Transportation E-Mail	FCC-450-3.3-BNC	Plug-in MOV
National Warning Phone System	FEMA ^a Voice Network	CG-230-L ^b	
Civil Defence Microwave System	State Civil Defense Voice Control Station	CG-230-L ^b 1.5KE200C	Plug-in MOV
FEMA National Teletype System	FEMA Data Network	CG-230-L	Plug-in MOV
Idaho Law Enforcement Teletype System	Law Enforcement Data Network	CG-230-L	Plug-in MOV
Motorola Remote Handset Control ^c	EBS RPU ^d	1.5KE200C	Plug-in MOV

^a FEMA = Federal Emergency Management Agency.

^b Installed in U-channel strip on rear of console.

^c Located in office area of EOC.

^d EBS RPU = Emergency Broadcasting System remote pick-up.

The telephone shown in Fig. 43 is a part of the National Warning System (NAWAS) network. This telephone will be protected by installing CG-230-L communications gas gaps from each line to ground in a U-channel grounding strip that will be installed behind the console. The U-channel strip is described in Sect. VI.B.1.

Figure 44 shows the control station for the Civil Defense Microwave System, a part of the Department of Transportation microwave network. The control station uses a dc current loop to control a microwave transmitter on the Towers Building, approximately 2000 ft away. The line on the EOC end will be protected by installing CG-230-L communications gas gaps in a U-channel strip on the rear of the console.

Second-level protection will be provided by 1.5KE200C bipolar zener diodes installed from line to chassis ground inside the control station. The power for this station will be protected with a plug-in MOV. The microwave network itself will not be protected at this time.

The equipment for the FEMA National Teletype System (FNATS) and the Idaho Law Enforcement Teletype System is shown in Fig. 45. The incoming signal lines to these

devices should be protected by installing CG-230-L communications gas gaps from line to ground on each incoming pair of wires. The power should be protected by installing a plug-in MOV at the power receptacle that supplies this equipment.

Figure 46 shows the Motorola remote handset control used for the EES RPU station. The control line should be protected by installing 1.5KE200C bipolar zener diodes from each line to chassis ground in the control station. Additionally, the power should be protected by installing a plug-in MOV and a cube tap at the receptacle that powers the station.

V. FNARS SHIELDED ROOM

The primary thrust for updating the EMP hardening of this facility is the protection of the FNARS equipment. A principal component in the FNARS radio equipment protection plan is the shielded room. This room contains the Harris SSB HF transmitter and receivers that will link this facility with the other state and federal facilities. The importance of this equipment warrants that the integrity of the shielded room be inspected.

The shielded room, positioned in the corner of the communications center, is an 8 by 10 ft enclosure with sheet metal walls inside and out. A metal door has finger stock that forms a radio-frequency (rf) seal around the door. All lines into the enclosure are protected by filtering and transient arresters.

The physical integrity of the shielded room is considered excellent. Figure 47 illustrates the door into the shielded enclosure. The finger stock on this door is in good condition and does not require repair or upgrading. The honeycomb filter on the air intake vent, shown in Fig. 48, is intact and clean. Likewise, the honeycomb filter on the exhaust vent is intact, as shown in Fig. 49.

Details of the cable penetration area are given in FEMA Dwg. 0023-006. An elevation view of the penetration area shows the power filters near the top with the signal lines entering below to the left and the coaxial cable penetrations below to the right. Details of the cable layout and recommended protectors are given in the drawing.

The box containing the coaxial cable penetrations is shown in Fig. 50. The 1000-W transmitter lines are protected at the bulkhead by 1000-V gas discharge coaxial protectors, and the 100-W transmitter line is protected by a 230-V device. One of the receiver inputs is protected by an FCC-250-75-N protector, but the other receive antenna does not have protection installed. An FCC-250-75-UHF coaxial protector should be installed on the second receive line at the bulkhead of the shielded room. Second-stage protection for the Harris receivers should be implemented by installing FCC-450-6.8-BNC coaxial tees at the inputs to the receivers.

Figure 51 shows the protection block for the control and signal lines entering the shielded enclosure. The lines are identified in FEMA Dwg. 0023-006 along with the recommended protectors. The eight conductors on the upper right terminal block are the control lines for the Spira-cone pattern elevation adjustment. The terminal strip has V39ZA6 MOVs installed from the terminals to the copper grounding strip, but the

terminal blocks are split in the center and bridging clips are not installed. This condition leaves the conductors unprotected because the MOVs are not in the circuit. Either bridging clips or a soldered copper jumper wire should be installed on these eight lines to ensure that the protectors are connected to the wires entering the shielded room.

The three thermostat wires on terminals 6, 7, and 8 are protected with V130LA10A MOVs from line to ground. The MOVs on these lines should be changed to V39ZA6 devices to provide a clipping level that is closer to the 24-V control voltage used for the thermostat.

Telephone pairs on terminals 9/10 and 20/21 are now protected with V130LA10A MOVs. These MOVs should be changed to CG-230-L communications gas gap devices.

VI. TELEPHONE AND CONTROL LINES

Telephone and control lines establish a direct connection path by which EMP can reach the electronic equipment within a facility. Measures must be taken to limit the voltages on incoming lines to protect both the equipment that is directly connected to the line and the localized equipment that is subjected to secondarily induced currents.

A. Telephone Lines

The telephone company lines enter the building through underground ducts to a telephone terminal area in the Boise State University classroom. Currently, no gas gaps or carbon blocks are installed on these lines. The FEMA EMP program cannot place protective devices onto telephone company equipment, but it is recommended that the EOC personnel contact the telephone company concerning the installation of a gas discharge arrester block on these lines. Installation of these arresters will provide protection for all equipment in the building from both EMP and the threat of lightning.

The telephone lines that leave the main connection area are routed to localized connection blocks around the building. The connection blocks for the EOC and the communications room are shown in Fig. 52. The covered terminal block in the center of the figure connects a 25-pair cable that is used for the EOC lines. EOC personnel should contact the telephone company concerning the installation of a gas discharge arrester block for this group of lines.

The telephone system in the EOC has a local battery backup system that is charged from a power supply connected to the ac line. A plug-in MOV will be supplied to protect the receptacle that powers the battery charger.

During the survey, EOC personnel expressed interest in the possibility of protecting the internal telephone system. The existing EMP protection program does not extend protection to the full internal telephone system and electronic switchgear. The state does have an unused 8 by 10 ft shielded room however, and this room would make an excellent EMP protection enclosure for the state-owned telephone switching equipment. The conductors for the power can be filtered, and the penetrations for the telephone lines can have voltage-limiting devices installed. With proper installation of the equipment in the

shielded enclosure and with protection devices at the penetration, the internal telephone system could be expected to survive an EMP event.

B. Control Lines

1. Communications Room Grounding and Cable Protection

The control lines entering the EOC communications room from peripheral areas will be protected with communications gas gaps installed in a copper U-channel grounding strip. Protection in this manner will reduce the EMP damage threat to both directly connected equipment and to nearby equipment that may be inductively coupled to the lines. The lines to be protected in this manner include leased pairs and state-owned cables.

It is necessary that a grounding network be established in the communications room to provide for proper installation of the U-channel grounding strips. FEMA Dwg. 0023-002 shows a floor plan for the communications area. Grounds will be established on the rear of the two console clusters shown in the drawing.

The ground for the shielded radio room is established by connection to water pipes and a transformer grounding rod in the subbasement. This grounding network should be extended to the basement level to provide grounds for the equipment in the consoles. Figure 53 shows a penetration at the rear of the console with coaxial cables entering the room. A No. 4 AWG copper conductor should be routed through this penetration, extending from the back panel of the console to the grounding network that will be established in the subbasement. The No. 4 AWG conductor should connect to a 3-in. copper strap that will be attached to the rear of the console. Details of the layout and connection are given in FEMA Dwg. 0023-007. Ground connections should be made from the copper strap to the National Guard radio, the Harris hf radio, and the Department of Transportation electronic mail system.

A second copper strap should be installed on the rear of the console that is in the center of the room. The strap can be grounded by using a No. 4 AWG copper conductor that is routed through an existing penetration to the subbasement grounding system. The penetration is indicated as item 16 in FEMA Dwg. 0023-002. The copper strap should establish a ground for the packet radio system, the Civil Defense microwave control station, and the NAWAS station.

Figure 54 shows the rear of the console area with the control line terminal blocks. Fifteen pairs should be protected by U-channel grounding strips that are mounted to the 3-in. copper strap. CG-230-L communications gas gaps should be installed on the terminal blocks, from each conductor to the U-channel ground. Details are available in FEMA Dwg. 0023-007.

2. Granger Control Cable Protection

A multiconductor cable extends from the antenna controls in the FNARS shielded enclosure to the pattern control box on the Granger Spira-cone antenna at the roof. The control box used for high/low pattern switching is shown on the right in Fig. 55, with the

EMP protection boxes for rf on the left. The electronics on both ends of the cable are protected by 1.5KE36A zener diodes that were installed at the factory. The control cable has additional MOVs installed at the penetration to the shielded enclosure. Guidelines for protection of the Granger equipment are under evaluation, and an addendum to this report will be issued if further protection is determined to be necessary.

Fig. 1. Emergency generator and day tank. The flexible conduits on the fuel pump have copper jumpers that should remain in place. The generator does not have flexible conduits and requires no jumpers.

Fig. 2. Starter solenoid for the emergency generator. V39ZA6 MOVs are installed on the solenoid terminals. A bead of silicone rubber cement should be used to mount the body of the MOV to the solenoid housing.

Fig. 3. Battery-charging generator for the emergency generator. The generator and voltage regulator have V130LA10A MOVs installed. A bead of silicone rubber cement should be used to mount the body of the MOV to the generator or voltage regulator.

Fig. 4. Automatic transfer switch. The existing V480PA40 MOVs should be removed. V275HE250 MOVs should be installed from phase to ground on the commercial power side of the transfer switch. V275PA40A MOVs should be installed on the load side of the transfer switch, from phase to ground. Refer to Appendix B-1 for details of MOV installation.

Fig. 5. Panel EM in the equipment room. V275PA40A MOVs should be installed from each phase to ground on the load side of the breaker marked "Panel BHB." The metal plate to the right can be used as ground.

Fig. 6. Power panel BHB. Remove the existing V480PA40 MOVs. V275PA40A MOVs should be installed on the load side of three adjacent breakers, from line to phase ground.

Fig. 7. Power panel BLC. This panel has V130PA20 MOVs installed from each phase to ground and from neutral to ground. These MOVs should be left in place.

Fig. 8. Power panel HEM in the electrical and mechanical room. The existing V480PA40 MOVs should be removed and replaced by V275PA40A devices, installed from each phase to case ground.

Fig. 9. Step-down transformer TR6 in the subbasement. The flexible conduits should be shunted by No. 4 AWG copper conductors.

Fig. 10. Power panel LR in Room 57. The panel has V130PA20 MOVs installed from each phase to ground and is adequately protected.

Fig. 11. Input to one of two power filters for the shielded room. A V130PA20A MOV should be installed on the input for each filter, from the line to case ground.

Fig. 12. Power panel inside the shielded room. V130PA20A MOVs should be installed from the load side of two adjacent breakers to case ground.

Fig. 13. Circuit breaker box in the Harris transmitter cabinet. V130PA20A MOVs should be installed from the terminals on the load side of the breaker to case ground.

Fig. 14. Motor controller for the emergency well pump. The existing V480PA40 MOVs should be removed and replaced by V275PA40A devices. The control coil has a V130LA10 MOV installed across the coil.

Fig. 15. Overall front view of the motor control center. This center controls the well water pump, EOC air supply fan, EOC air return fan, and fire pump. The existing V480PA40 MOVs in each of these contactors should be replaced by V275PA40A devices.

Fig. 16. Control contactor for one of the pumping systems. This contactor is adjacent to power panel HEM and requires no protection.

Fig. 17. Emergency lighting unit for the office area. The light should be protected by installing V130LA10A MOVs on the ac line from hot to neutral and from hot to ground. This light is typical of three units.

Fig. 18. Base of the Spira-cone antenna. The single No. 8 AWG ground is considered insufficient. The Spira-cone base will serve as the center for the eastern portion of a counterpoise.

Fig. 19. Spira-cone antenna on the eastern end of the roof. The tower for the Spira-cone will serve as the hub for a counterpoise.

Fig. 20. Balun for the state high-frequency fan doublet antenna. The center of the fan doublet will locate the hub for the western portion of the counterpoise.

Fig. 21. State antennas on the roof of the building. The antennas for the VHF packet radio, the National Guard radio, a support tower for the fan doublet, and the radiation monitor should all be connected to the counterpoise.

Fig. 22. FM receive antenna mounted on the fire standpipe. This antenna should be relocated to a small mast mount if possible. The standpipe will act as an antenna and should not be attached to the counterpoise.

Fig. 23. Entry point for the state coaxial cables in the third-floor electrical room. The existing ground for the hf balun can be removed after the counterpoise is installed.

Fig. 24. Coaxial cables and conduits in the third-floor electrical room. A No. 4 AWG copper conductor will be routed with the coaxial cables and should be bonded to the 4-in. conduit with a grounding clamp.

Fig. 25. Coaxial cables and conduits in the basement electrical room. A grounding clamp should be used to bond the No. 4 AWG that is routed with the coaxial cables to the 4-in. conduit.

Fig. 26. Junction box in the air ventilation duct adjoining the subbasement. A No. 4 AWG copper conductor should be routed with these coaxial cables. A branch of the copper conductor will connect to three ground rods in the duct.

Fig. 27. Three ground rods in the air duct adjacent to the subbasement. A No. 4 AWG copper conductor should be attached to these grounds. The other end of the conductor should attach to the copper conductor that will run with the coaxial cables from the roof.

Fig. 28. Penetration where coaxial cables enter the subbasement from the air duct. A No. 4 AWG copper conductor will be routed with these cables. See the text for precautionary notes concerning the door to the right of this penetration.

Fig. 29. Point in the subbasement where coaxial shields are grounded. The No. 4 AWG conductor that will be added should ground to these pipes as it passes this point.

Fig. 30. Ground rod adjacent to transformer TR6. This rod will be the terminating point for the No. 4 AWG copper conductor that runs from the counterpoise to the subbasement on the eastern end.

Fig. 31. Penetration for state coaxial cables into the subbasement. A No. 4 AWG copper grounding wire will be added to this bundle, running from the counterpoise to grounds in the subbasement.

Fig. 32. Water and drain lines used as a ground for the shielded room. The No. 4 AWG copper conductor from the counterpoise under the state antennas should be attached to these pipes.

Fig. 33. Remote receive antennas for the Harris system. The vertical whip and the B&W antennas are mounted to the metal penthouse on the Towers Building. No additional protection will be installed at this location.

Fig. 34. Coaxial cables from the Harris remote receive antennas. The two RG-213 cables should have the shields grounded to a No. 4 AWG copper conductor that will attach to the well water pipe. Refer to the text and Appendix B-3 for details on coaxial shield grounding.

Fig. 35. Well water main supply line. The pipe will serve as a ground for the coaxial cable shields from the Harris remote receive antennas. A grounding clamp should be added beneath the existing clamp.

Fig. 36. National Guard radio in the communications room. An FCC-250-230-UHF coaxial protector should be installed on the antenna line at the rear of the radio. The receiver should be protected by installing an FCC-450-3.3-L diode bridge inside the radio, on the receive side of the transmit/receive switch. A plug-in MOV should be installed at the power receptacle.

Fig. 37. State Emergency Operating Center high-frequency radio. Protect the transmitter by installing an FCC-250-470-UHF coaxial protector on the antenna line. An FCC-450-3.3-L diode bridge should be installed across the receive line after the transmit/receive switch. The power will be protected by a plug-in MOV at the receptacle.

Fig. 38. VHF packet radio system. The radio should be protected by an FCC-250-75-UHF coaxial protector installed on the antenna line at the bulkhead connector in the rear of the cabinet. A plug-in MOV should be installed on the receptacle that supplies the power to the radio.

Fig. 39. Emergency Broadcasting System remote pickup in the Hall of Mirrors Building. The transmitter should be protected by installing an FCC-250-230-UHF coaxial protector on the antenna line at the rear of the chassis. The receiver should be protected by an FCC-450-3.3-L diode bridge installed on the receive side of the transmit/receive switch. Protect the control lines by installing 1.5KE200C bipolar zener diodes from each line to chassis ground. Install a plug-in MOV at the receptacle that supplies power to this transceiver.

Fig. 40. Rear of the Emergency Broadcasting System remote pickup in the Hall of Mirrors Building. The antenna line where the coaxial protector will be installed is to the left of the radio. The control lines that will receive the 1.5KE200C diodes are attached to the screw terminals.

Fig. 41. Datapoint terminal on the Department of Transportation network. Protection for this unit will consist of a plug-in MOV for the power and a coaxial protector for the cable connecting to the modem.

Fig. 42. Modem for the Datapoint terminal. An FCC-450-3.3-BNC coaxial protector should be installed on the network line at the rear of the modem.

Fig. 43. Telephone connecting to the National Warning System network. The telephone will be protected by installing CG-230-L communications gas gaps in a U-channel on the rear of the console.

Fig. 44. Control station for the Civil Defense microwave network. The control lines should be protected by installing 1.5KE200C bipolar zener diodes from each line to chassis ground inside the chassis. The control lines will also have CG-230-L communications gas gaps installed in the U-channel on the rear of the console. A plug-in protector will be added to the receptacle that powers this station.

Fig. 45. Equipment for the Federal Emergency Management Agency National Teletype System and the Idaho Law Enforcement Teletype System. The incoming lines should have CG-230-L communications gas gaps installed from each line to ground. A plug-in MOV will be supplied for the receptacle that powers this equipment.

Fig. 46. Motorola remote handset control for the Emergency Broadcasting System remote pickup station. Protect the control line by installing 1.5KE200C bipolar zener diodes from each line to chassis ground on the control lines. A plug-in MOV and grounded cube tap should be installed at the receptacle that supplies power to the station.

Fig. 47. Entrance door to the shielded enclosure. The finger stock on this door is in good condition and requires no repair or upgrading.

Fig. 48. Honeycomb filter on the air intake for the shielded room. The Honeycomb filter is clean and in good condition.

Fig. 49. Fan and honeycomb filter for the air exhaust for the shielded room. The honeycomb filter is intact and requires no attention at this time.

Fig. 50. Coaxial cable penetrations to the shielded room. Coaxial protectors are now installed on all but one receive-only line. This receive cable should be protected by installing an FCC-250-75-UHF coaxial protector at the bulkhead.

Fig. 51. Protection block for signal lines entering the shielded room. Bridging clips should be added to the terminals on the upper right side. Several of the MOVs on the left strip should be replaced. See the text and FEMA Dwg. 0023-006 to identify the correct protectors.

Fig. 52. Telephone connection blocks for the EOC and the communications room. The EOC personnel should contact the telephone company concerning the installation of a gas discharge arrester block.

Fig. 53. Penetration at the rear of one console. A No. 4 AWG copper conductor will be routed with these coaxial cables to provide a ground path for a 3-in. copper strip that will be mounted on the rear of the console.

Fig. 54. Rear of the console with control line terminal blocks. Fifteen pairs of wires should be protected by a U-channel with CG-230-L gas gaps installed. Refer to FEMA Dwg. 0023-007 for details of the installation.

Fig. 55. Control box for the high/low switch on the Granger Spira-conc antenna. The electronics in the control are protected by 1.5KE36A zener diodes.

APPENDIX A-1

Electromagnetic Pulse Materials List for Idaho State Emergency Operating Center, Boise, Idaho

Stock code	Description	Quantity	FEMA symbol
55000	FCC-250-75-UHF coaxial tee	2 ea	1 a
55001	FCC-250-230-UHF coaxial tee	3 ea	1 c
55003	FCC-250-470-UHF coaxial tee	7 ea	1 o
55008	FCC-450-3.3-UHF coaxial tee	1 ea	1 l
55016	FCC-450-3.3-BNC coaxial tee	1 ea	1 i
55017	FCC-450-6.8-BNC coaxial tee	2 ea	1 k
55019	FCC-450-3.3-L diode bridge	3 ea	3 a
55022	V-39-ZA-6 MOV	3 ea	4 ea
55025	V-130-LA-10A MOV	6 ea	4 a
55026	V-130-PA-20A MOV	6 ea	4 b
55030	V-275-HE-250 MOV	3 ea	4 o
55031	V-275-LA-20A MOV	145 ea	4 c
55032	V-275-PA-40A MOV	24 ea	4 d
55042	1.5-KE-200-C bipolar zener	6 ea	5 j
55047	Plug-in protector, req. 1 receptacle	8 ea	7 d
55048	Cube Tap, Grounded (pkg of 1)	2 pkg	12 m
55050	CG-230-L or J-2001-06, 230 VDC	52 ea	2 b
55061	Connector, female tab (pkg of 25)	2 pkg	10 e
55062	Connector, male tab (pkg of 10)	1 pkg	10 d

APPENDIX A-1 (continued)

Stock code	Description	Quantity	FEMA symbol
55063	Connector, spade tongue (pkg of 25)	1 pkg	10 b
55064	Connector, ring tongue (pkg of 25)	1 pkg	10 a
55065	Connector, butt splice (nkg of 10)	1 pkg	10 c
55066	Lug, for No. 4-14 AWG	20 ea	6 o
55067	Terminal block, 20 contacts	2 ea	12 h
55068	Grounding clamp, 1 in.	3 ea	6 j
55069	Grounding clamp, 2 in.	2 ea	6 k
55070	Grounding clamp, 4 in.	3 ea	6 l
55071	Clamp, hose, max 1-in. ID	8 ea	6 h
55072	Clamp, hose, max 2-in. ID	2 ea	6 i
55073	Grounding strip, U-channel	2 ea	12 i
55079	Sheet metal screw, No. 8 $\times$ 3/8 (20/pkg)	1 pkg	11 i
55084	Washer, lock, No. 8 (pkg of 50)	1 pkg	11 j
55086	Washer, flat, No. 8 (pkg of 25)	1 pkg	11 l
55087	Washer, star lock, 1/4 in.	20 ea	11 n
55088	Pop rivet, 1/8 $\times$ 3/8 in. (50/pkg)	2 pkg	11 m
55089	Tubing, Teflon, 0.034-in. ID	2 ea	12 g
55090	Shrink tubing, 1/4-in. OD (2 ft)	1 ea	12 f
55091	Shrink tubing, 3/8-in. OD (2 ft)	2 ea	12 n
55092	Shrink tubing, 1/2-in. OD (2 ft)	1 ea	12 o
55093	Wire, hook-up, Teflon	40 ft	12 l

APPENDIX A-1 (continued)

Stock code	Description	Quantity	FEMA symbol
55094	Braid, tinned copper	6 ft	6 a
55097	Wire, No. 4 AWG, stranded copper	540 ft	6 p
55098	Copper strip, 3 in. wide	16 ft	6 q
55099	Crimping tool	1 ea	12 b
55100	Riveting tool	1 ea	12 c
55101	Tap, thread cutting, No. 10-32	1 ea	12 e
55102	Drill bits, No. 21 and No. 29 (1 ea)	1 pkg	12 d
55104	Emery cloth, sheet	2 sheets	6 g
55105	Label, "EMP SUPPRESSOR" (pkg of 25)	1 pkg	12 a
55106	Wire ties, nylon, 7 in.	100 ea	12 j
55107	Tape, electrical, 3/4 in.	1 roll	6 d
55108	Adhesive, RTV (3-oz tube)	1 tube	6 c
55109	Conductive epoxy, (1/2-lb jar)	1 set	6 b
55177	Bolt, 1/4-20 × 1/2 in.	20 ea	11 g
TBP	Nut, 1/4-20, hex	20 ea	
TBP	Clamp, for 5/8-in. ground rod	3 ea	
TBP	Split bolt, for No. 4 AWG wire	20 ea	
TBP	Hub, grounding, per ORNL ^a design	1 ea	
TBP	Manifold, grounding, per ORNL ^a design	1 ea	
TBP	Copper tubing, 1/4 in. (50 ft)	36 rolls	
TBP	Ell, copper, 1/4 in.	10 ea	

APPENDIX A-1 (continued)

Stock code	Description	Quantity	FEMA symbol
TBP	Tee, copper, 1/4 in.	35 ea	
TBP	Cross, copper, 1/4 in.	25 ea	
TBP	Coupling, copper, 1/4 in.	35 ea	
TBP	Solder, rosin core	2 lb	
TBP	Cement, plastic roofing	5 gal	

^aORNL = Oak Ridge National Laboratory.

APPENDIX A-2

**Recommended Electromagnetic Pulse Materials Spare Parts List for
Idaho State Emergency Operating Center,
Boise, Idaho**

Stock code	Description	Quantity	FEMA symbol
55001	FCC-250-230-UHF coaxial tee	1 ca	1 c
55003	FCC-250-470-UHF coaxial tee	1 ca	1 o
55008	FCC-450-3.3-UHF coaxial tee	1 ca	1 l
55016	FCC-450-3.3-BNC coaxial tee	1 ca	1 i
55017	FCC-450-6.8-BNC coaxial tee	1 ca	1 k
55019	FCC-450-3.3-L diode bridge	1 ca	3 a
55022	V-39-ZA-6 MOV	3 ca	4 c
55025	V-130-LA-10A MOV	5 ca	4 a
55026	V-130-PA-20A MOV	3 ca	4 b
55030	V-275-HE-250 MOV	3 ca	4 o
55031	V-275-LA-20A MOV	10 ca	4 c
55032	V-275-PA-40A MOV	6 ca	4 d
55042	1.5-KE-200-C bipolar zener	2 ca	5 j
55050	CG-230-L or J-2001-06, 230 VDC	10 ca	2 b
55111	3-A pico-fuse (plug-in protector)	3 ca	7 b

APPENDIX A-3

**Electromagnetic Pulse Materials Cost Estimate to Harden
Idaho State Emergency Operating Center,
Boise, Idaho**

Stock code	Description	Quantity	Cost each (\$)	Total cost (\$)
55000	FCC-250-75-UHF coaxial tee	2 ea	80.00	160.00
55001	FCC-250-230-UHF coaxial tee	3 ea	80.00	240.00
55003	FCC-250-470-UHF coaxial tee	7 ea	80.00	560.00
55008	FCC-450-3.3-UHF coaxial tee	1 ea	80.00	80.00
55016	FCC-450-3.3-BNC coaxial tee	1 ea	80.00	80.00
55017	FCC-450-6.8-BNC coaxial tee	2 ea	80.00	160.00
55019	FCC-450-3.3-L diode bridge	3 ea	80.00	240.00
55022	V-39-ZA-6 MOV	3 ea	1.00	3.00
55025	V-130-LA-10A MOV	6 ea	1.00	6.00
55026V	V-130-PA-20A MOV	6 ea	12.60	75.60
55030	V-275-HE-250 MOV	3 ea	36.00	108.00
55031	V-275-LA-20A MOV	145 ea	0.83	120.35
55032	V-275-PA-40A MOV	24 ea	12.60	302.40
55042	1.5-KE-200-C bipolar zener	6 ea	2.00	12.00
55047	Plug-in protector, req. 1 receptacle	8 ea	19.95	159.60
55048	Cube tap, grounded (pkg of 1)	2 pkg	3.95	7.90
55050	CG-230-L or J-2001-06, 230 VDC	52 ea	3.00	156.00
55061	Connector, female tab (pkg of 25)	2 pkg	0.10	5.00
55062	Connector, male tab (pkg of 10)	1 pkg	0.10	1.00

APPENDIX A-3 (continued)

Stock code	Description	Quantity	Cost each (\$)	Total cost (\$)
55063	Connector, spade tongue (pkg of 25)	1 pkg	0.10	2.50
55064	Connector, ring tongue (pkg of 25)	1 pkg	0.10	2.50
55065	Connector, butt splice (pkg of 10)	1 pkg	0.10	1.00
55066	Lug, for No. 4-14 AWG	20 ea	0.86	17.20
55067	Terminal block, 20 contacts	2 ea	7.65	15.30
55068	Grounding clamp, 1 in.	3 ea	1.75	5.25
55069	Grounding clamp, 2 in.	2 ea	17.50	35.00
55070	Grounding clamp, 4 in.	3 ea	27.50	82.50
55071	Clamp, hose, max 1-in. ID	8 ea	0.34	2.72
55072	Clamp, hose, max 2-in. ID	2 ea	0.38	0.76
55073	Grounding strip, U-channel	2 ea	4.00	8.00
55079	Sheet metal screw, No. 8 $\times$ 3/8 (20/pkg)	1 pkg	0.02	0.40
55084	Washer, lock, No. 8 (pkg of 50)	1 pkg	0.01	0.50
55086	Washer, flat, No. 8 (pkg of 25)	1 pkg	0.01	0.25
55087	Washer, star lock, 1/4 in.	20 ea	0.01	0.20
55088	Pop rivet, 1/8 $\times$ 3/8 in. (50/pkg)	2 pkg	0.01	1.00
55089	Tubing, Teflon, 0.034-in. ID	2 ea	1.00	2.00
55090	Shrink tubing, 1/4-in. OD (2 ft)	1 ea	0.16	0.32
55091	Shrink tubing, 3/8-in. OD (2 ft)	2 ea	0.44	0.88
55092	Shrink tubing, 1/2-in. OD (2 ft)	1 ea	0.50	1.00

APPENDIX A-3 (continued)

Stock code	Description	Quantity		Cost each (\$)	Total cost (\$)
55093	Wire, hook-up, Teflon	40	ft	0.12	4.80
55094	Braid, tinned copper	6	ft	0.84	5.04
55097	Wire, No. 4 AWG, stranded copper	540	ft	0.25	135.00
55098	Copper strip, 3 in. wide	16	ft	0.98	15.68
55099	Crimping tool	1	ea	12.00	12.00
55100	Riveting tool	1	ea	10.00	10.00
55101	Tap, thread cutting, No. 10-32	1	ea	0.25	0.25
55102	Drill bits, No. 21 and No. 29 (1 ea)	1	pkg	0.25	0.50
55104	Emery cloth, sheet	2	sheets	0.50	1.00
55105	Label, "EMP SUPPRESSOR" (pkg of 25)	1	pkg	0.04	1.00
55106	Wire ties, nylon, 7 in.	100	ea	0.10	10.00
55107	Tape, electrical, 3/4 in.	1	roll	2.69	2.69
55108	Adhesive, RTV (3-oz tube)	1	tube	3.25	3.25
55109	Conductive epoxy, 1/2-lb jar	1	set	25.00	25.00
55117	Bolt, 1/4-20 × 1/2 in.	20	ea	0.10	2.00
TBP	Nut, 1/4-20, hex	20	ea	0.10	2.00
TBP	Clamp, for 5/8-in. ground rod	3	ea	8.00	24.00
TBP	Split bolt, for No. 4 AWG wire	20	ea	1.60	32.00
TBP	Hub, grounding, per ORNL ^a design	1	ea	200.00	200.00
TBP	Manifold, grounding, per ORNL ^a design	1	ea	700.00	700.00

APPENDIX A-3 (continued)

Stock code	Description	Quantity	Cost each (\$)	Total cost (\$)
TBP	Copper tubing, 1/4 in. (50 ft)	36 rolls	14.00	504.00
TBP	Ell, copper, 1/4 in.	10 ea	0.96	9.60
TBP	Tee, copper, 1/4 in.	35 ea	1.50	52.50
TBP	Cross, copper, 1/4 in.	25 ea	2.00	50.00
TBP	Coupling, copper, 1/4 in.	35 ea	0.50	17.50
TBP	Solder, rosin core	2 lb	9.00	18.00
TBP	Cement, plastic roofing	5 gal	6.00	30.00
TOTAL				\$4,523.94

*ORNL = Oak Ridge National Laboratory.

APPENDIX B

Fig. B.1. Installation of HE-Series MOVs in a panel. PA-Series MOVs are installed in a similar manner, with the mounting tab used for ground. Keep all lead lengths as short as possible to minimize inductive voltage drops.

Fig. B2 Typical schematic diagram of a dual 40-W rapid-start fluorescent lamp fixture with MOVs installed.

Fig. B.3 Typical installation of a grounding conductor to a coax cable shield.

277 / 480 V
3 Ø 4W
150 KW
GENERATOR

④
3 0

EL SECTION E.M

REVISION	FILE DATE	BY	CHKD	ENGR	APVD	APPROVALS	TOLERANCES UNLESS OTHERWISE SPECIFIED	DESIGNED BY R.W. JONES	DRAWN BY M.E. BUCHANAN	CHECKED BY R.I. CRUTCHER	DATE
1							FRACTIONS 1/16 XX DECIMALS 1 XX DECIMALS 1 ANGLES 1/2 BREAK SHARP EDGES				
ISSUE PURPOSE											

REFERENCE DRAWINGS		NUMBER	
FEDERAL EMERGENCY MANAGEMENT AGENCY		COORDINATOR Oak Ridge National Laboratory	
IDAHO STATE EMERGENCY OPERATING CENTER SINGLE LINE ELECTRICAL POWER DIAGRAM			
HIGH ALTITUDE ELECTROMAGNETIC PULSE PROTECTION FOR FNARS FACILITIES			
FILE DATE	FILE POINT	BLDG	WIT OF
HC	EC		
SCALE N.T.S.	TO 1/8"	FEMA 0023-001	
DRAWING APPROVALS	DATE	REV	00

ITEM	DESCRIPTION	CONNECTION
1	NWAS NATIONAL WARNING SYSTEM STATION	GROUND TO ITEM #15
2	CIVIL DEFENSE MICROWAVE (TRANSPORTATION) STATION	GROUND TO ITEM #15
3	VACANT	
4	IDAHO LAW ENFORCEMENT STATION (PRINTER)	
5	IDAHO LAW ENFORCEMENT STATION (TELETYPE) LEASED A.T.B.T.	
6	IDAHO LAW ENFORCEMENT STATION (MONITOR)	
7	SHIELDED ROOM (HARRIS EQUIPMENT)	
8	NATIONAL GUARD (GOWEN FIELD) RACES STATION	GROUND TO ITEM #17
9	HARRIS RF-3200 (STATE E.O.C. BASE) STATION	GROUND TO ITEM #17
10	E-MAIL DEPARTMENT OF TRANSPORTATION STATION	GROUND TO ITEM #17
11	P.C.	GROUND TO ITEM #17
12	PRINTER	GROUND TO ITEM #17
13	RACES CONTROLLER (P.C. MODEM, ETC.)	GROUND TO ITEM #15
14	TELEPHONE TERMINAL BOXES	GROUND TO ITEM #15
15	3" COPPER STRAP, ATTACH TO REAR OF CUBICLES	
16	EXIST. 3/4" CONDUIT TO DUCT BANK IN SUB-B5MT.	
17	3" COPPER STRAP, ATTACH TO REAR OF CUBICLES	
18	BATTERY BACKUP EMERGENCY LIGHT FIXTURES	
19	3" RIGID CONDUIT FROM PENTHOUSE TO SUB-B5MT.	
20	PML "BHB" 277/400 V	
21	TRANSFORMER #2	
22	PML "BLC"	
23	PML "LEB"	
24	AUTO. TRANSFER SW.	
25	EMERG. GEN. FLOAT TANK PUMP MOTOR	
26	M.C.C.	
27	PML "HEW" 277/400 V	
28	SUMP PUMP MOTOR	
29	TRANSFORMER #4	
30	PML "LEA"	
31	PML "BLB"	
32	PML "BLA"	
33	PML "BL1A"	
34	EMERGENCY GENERATOR	
35		
36		
37		
38		
39		
40

PARTIAL BASEMENT FLOOR PLAN
(EMERG. GEN. & ELECT. EQUIP. AREA)

REFERENCE DRAWINGS		NUMBER	
FEDERAL EMERGENCY MANAGEMENT AGENCY		COORDINATOR Oak Ridge National Laboratory	
IDAHO STATE EMERGENCY OPERATING CENTER PARTIAL BASEMENT & COM. ROOM EQUIPMENT GROUNDING SYSTEM			
HIGH ALTITUDE ELECTROMAGNETIC PULSE PROTECTION FOR FNARS FACILITIES			
FILE DATE	FILE POINT	BLDG	SHT. OF
	HC- EC-		14
SCALE 1/8" = 1'-0"	ID 1:50	REV 0023 002	

UNLESS TOLERANCES OTHERWISE SPECIFIED	APPROVED BY R.W. JONES
FRACTIONS 2	DESIGNED BY M.E. BUCHANAN
XX DECIMALS 4	APPROVED BY R.I. CRUTCHER
XXX DECIMALS 4	
ANGLES 4	
BREAK SHARP EDGES	
DRAWING APPROVALS	DATE

DESCRIPTION	FILE DATE	BY	CHKD	ENGR	APVD
REVISION OR ISSUE PURPOSE

DESCRIPTION OR ISSUE PURPOSE	FILE DATE	BY	CHKD	ENGR	APVD	APPROVALS

TOLERANCES
UNLESS OTHERWISE SPECIFIED
FRACTIONS 1/8"
XXI DECIMALS .001
XXII DECIMALS .0005
ANGLES 1/4°
BREAK SHARP EDGES

DESIGNED BY	R. W. JONES
CHECKED BY	M. E. BUCHANAN
APPROVED BY	R. I. CRUTCHER
DRAWING APPROVALS	DATE

REFERENCE DRAWINGS		NUMBER	
FEDERAL EMERGENCY MANAGEMENT AGENCY		COORDINATOR Oak Ridge National Laboratory	
IDAHO STATE EMERGENCY OPERATING CENTER ROOF GROUNDING SYSTEM AND ANTENNA COUNTERPOISE SYSTEM			
HIGH ALTITUDE ELECTROMAGNETIC PULSE PROTECTION FOR FNARS FACILITIES			
FILE DATE	FILE POINT	BLDG	INT. OF
	HC- EC-		
SCALE 1/8" = 1'-0"	TO 1&C	FEMA 0023-003	
REV			00

TYPICAL ANTENNA
MAST GROUND
CONNECTION DETAIL
N.T.S.

FAN DOUBLET COUNTERPOISE MANIFOLD
MAT'L: COPPER
1-REQ'D.
SCALE: 1/2"=1"

STRAIN RELIEF & COUNTERPOISE CONNECTION DETAIL
N.T.S.

TOLERANCES UNLESS OTHERWISE SPECIFIED	DESIGNED BY R.W. JONES
FRACTIONS *	DRAWN BY M.E. BUCHANAN
XX DECIMALS *	CHECKED BY R.L. CRUTCHER
XXX DECIMALS *	DATE
ANGLES *	DATE
BREAK SHARP EDGES	DATE

REFERENCE DRAWINGS		NUMBER	
FEDERAL EMERGENCY MANAGEMENT AGENCY		COORDINATOR Oak Ridge National Laboratory	
IDAHO STATE EMERGENCY OPERATING CENTER ANTENNA COUNTERPOISE SYSTEM HARDWARE DETAILS			
HIGH ALTITUDE ELECTROMAGNETIC PULSE PROTECTION FOR FNAHS FACILITIES			
FILE DATE	FILE POINT	BLDG	EXT. OF
HC- EC-			
SCALE AS NOTED	ID 1&C	FEMA 0023-004	REV 00

REVISION OR ISSUE PURPOSE	FILE DATE	BY	CHKD	ENGR	APVD

TOLERANCES UNLESS OTHERWISE SPECIFIED	DRAWN BY R.W. JONES	DATE
FRACTIONS 1/16"	CHECKED BY M.E. BUCHANAN	DATE
XX DECIMALS .01	DESIGNED BY R.I. CRUTCHER	DATE
XX DECIMALS .001		
ANGLES 1/4°		
BREAK SHARP EDGES		
	DRAWING APPROVALS	DATE

REFERENCE DRAWINGS		NUMBER	
FEDERAL EMERGENCY MANAGEMENT AGENCY		COORDINATOR Oak Ridge National Laboratory	
IDAHO STATE EMERGENCY OPERATING CENTER SUB-BASEMENT GROUNDING SYSTEM			
HIGH ALTITUDE ELECTROMAGNETIC PULSE PROTECTION FOR FNARS FACILITIES			
FILE DATE	FILE POINT	BUDG.	INT. OF
SCALE 1/8"=1'-0"	TO 1&C	FEMA 0023-005	REV 00

DESCRIPTION REVISION OR ISSUE PURPOSE	FILE DATE	BY	CHKD	ENGR	APVD

SHIELDED ROOM ELEVATION

ITEM	DESCRIPTION
1	SHIELDED ROOM ENCLOSURE
2	SIGNAL/CONTROL CABLE TERM. BOX
3	RF CABLE TERMINAL BOX
4	SIGNAL/CONTROL CABLE FEED THRU DUCT
5	POWER JUNCT. BOX
6	FILTER
7	FILTER
8	POWER DUCT
9	1/2" C. TELEPHONE LINES
10	2" RIGID C. (CONTROL WIRING OR ANTENNA)
11	2" RIGID CONDUIT ANT. COAX LEAD-IN
12	2" RIGID CONDUIT TO PWR. PNL. "LR"
13	# 4/0 AWG. TO WATER PIPES (EXISTING)

SIGNAL/CONTROL CABLE T

N.T.S.

- Ⓜ METAL OXIDE VARISTOR (V)
- Ⓟ METAL OXIDE VARISTOR (V)
- Ⓢ GAS GAP ARRESTOR (GAP)
- SOLID METAL JUMPER (C)
- SOLID METAL JUMPER CLIP

THIS DRAWING PRODUCED BY AEC INTERCOMPUTATION & CONTROL DIVISION AND SYSTEMS AND PLANT		REV.	MF	DESCRIPTION	FILE
		REVISION OR ISSUE PURPOSE

RF CABLE TERM. BOX

N.T.S.

COAXIAL FEED THRU PROTECTION SCHEDULE

ITEM	CONN. TYPE	EXISTING NAME	RECOMMENDED PROTECTION
1	TYPE "N"	1KW XHMT	FCC 250-1000-H
2	TYPE "N"	KWT-8	FCC 250-75-N
3	TYPE "N"	N.C.	N.C.
4	UHF	N.C.	FCC 600-3.3-UHF
5	UHF	REC. ONLY	FCC 250-75-UHF
6	TYPE "N"	515-1 (WB)	FCC 250-1000-H
7	UHF	100 W XHMT	FCC 250-230-UHF
8	UHF	REC. ONLY	FCC 400-3.3-UHF
9	TYPE "N"	N.C.	NONE
10	TYPE "N"	N.C.	NONE
11	TYPE "N"	REC. ONLY	NONE

SIGNAL/CONTROL CABLE TERM. BOX

N.T.S.

- (A) METAL OXIDE VARISTOR #V130LA10
(B) METAL OXIDE VARISTOR #V30CA6
(C) GAS GAP ARRESTOR #G0230
— SOLID METAL JUMPER CLIP (EXISTING)
--- SOLID METAL JUMPER CLIP (REQ'D.)

REFERENCE DRAWINGS			NUMBER		
FEDERAL EMERGENCY MANAGEMENT AGENCY			COORDINATOR Oak Ridge National Laboratory		
IDAHO STATE EMERGENCY OPERATING CENTER SHIELDED ROOM ELEVATION, CONTROL WIRING & ANTENNA PENETRATIONS					
HIGH ALTITUDE ELECTROMAGNETIC PULSE PROTECTION FOR FNAIS FACILITIES					TYPE
FILE DATE		FILE POINT	S/DG	SHT.	OF
		HC- EC-			
SCALE N.T.S.	ID 1/4"	FEMA 0023-006			REV 00

DESCRIPTION FILE DATE BY CHKD ENGR APVD					TOLERANCES UNLESS OTHERWISE SPECIFIED FRACTIONS Δ 10 DECIMALS Δ 100 DECIMALS Δ ANGLES Δ BREAK SHARP EDGES		DESIGNED BY R.W. JONES CHECKED BY M.E. BUCHANAN DRAWN BY R.I. CRUTCHER	
APPROVALS					APPROVALS		DRAWING APPROVALS

THIS DRAWING PRODUCED BY OMA INTERLAMBICATION & CONTROL'S DIVISION HAS DESIGN AND PURPOSE	REV.	MF	DESCRIPTION	FILE DATE	BY	CHK
			REVISION OR ISSUE PURPOSE			APP

GROUND CONNECTION DETAIL

REFERENCE DRAWINGS		NUMBER	
FEDERAL EMERGENCY MANAGEMENT AGENCY		COORDINATOR Oak Ridge National Laboratory	
IDAHO STATE EMERGENCY OPERATING CENTER COMMUNICATIONS ROOM GROUNDING SYSTEM			
HIGH ALTITUDE ELECTROMAGNETIC PULSE PROTECTION FOR FEMA'S FACILITIES			
FILE DATE	FILE POINT HC- EC-	BLDG	INT. OF
SCALE	NO I&C	FEMA 0023-007	

TOLERANCES UNLESS OTHERWISE SPECIFIED	DESIGN BY R.W. JONES
FRACTIONS 1/16	DESIGN CHECK M.E. BUCHANAN
XX DECIMALS .001	DRAWN BY R.L. CRUTCHER
XX DECIMALS .001	CHECKED BY
ANGLES 1/4	DATE
BREAK SHARP EDGES	

DESCRIPTION REVISION OR ISSUE PURPOSE	FILE DATE	BY	CHKD	ENGR	APVD

DRAWING APPROVALS DATE

INTERNAL DISTRIBUTION

1. H. R. Brashear	16. J. B. Ball, Advisor
2-5. M. E. Buchanan	17. B. Chexal, Advisor
6-7. R. I. Crutcher	18. T. B. Sheridan, Advisor
8. B. G. Eads	19. R. M. Taylor, Advisor
9. D. N. Fry	20-21. Central Research Library
10. R. W. Jones	22. Y-12 Technical Reference Section
11. D. W. McDonald	23-24. Laboratory Records
12. D. R. Miller	25. Laboratory Records ORNL-RC
13. C. H. Nowlin	26. ORNL Patent Section
14. R. E. Uhrig	27. I&C Publications Office
15. A. Zucker	

EXTERNAL DISTRIBUTION

- 28. Assistant Manager for Energy Research and Development, U.S. Department of Energy, Oak Ridge Field Office, P.O. Box 2001, Oak Ridge, TN 37831-8600.
- 29-39. R. P. Gates II, Federal Emergency Management Agency, Room 608, 500 C Street SW, Washington, DC 20472
- 40-41. Pat Frischmuth, State of Idaho, Bureau of Disaster Services, 650 West State Street, Boise, ID 83720
- 42-43. Andrew Hendrickson, Federal Emergency Management Agency, Region X, 130 228th Street SW, Bothell, WA 98021
- 44-45. Office of Scientific and Technical Information, U.S. Department of Energy, P.O. Box 62, Oak Ridge, TN 37831

**DATE
FILMED**

7/17/92