UCRL- 86890 (Revised)¹
PREPRINT

MASTER

STABILITY AND DISTURBANCE
OF LARGE DC SUPERCONDUCTING MAGNETS*

S. T. Wang

NOTICE - 'LEGIBLE'
~~PORTIONS OF THIS REPORT ARE ILLEGIBLE~~
~~It has been reproduced from the best~~
~~possible copy to permit the broadest~~
possible availability.

THIS IS AN INVITED PAPER FOR THE MEETINGS OF
THE SCIENTIFIC AND TECHNICAL
COMMISSIONS OF THE I.I.R.

UCRL--86890 Rev. 1

DE92 012388

Lawrence
Livermore
National
Laboratory

This is a preprint of a paper intended for publication in a journal or proceedings. Since changes may be made before publication, this preprint is made available with the understanding that it will not be cited or reproduced without the permission of the author.

STABILITY AND DISTURBANCE
OF LARGE DC SUPERCONDUCTING MAGNETS*

S. T. WANG

University of California, Lawrence Livermore National Laboratory
P. O. Box 5511 L-635
Livermore, California 94550 (U.S.A.)

SUMMARY

This paper addresses the stability aspects of several successful dc superconducting magnets such as large bubble chamber magnets, and magnets for the Mirror Fusion Test Facility and MHD Research Facility. Specifically, it will cover Argonne National Laboratory 12-Foot Bubble Chamber magnets, the 15-foot Bubble Chamber magnets at Fermi National Laboratory, the MFTF-B Magnet System at Lawrence Livermore National Laboratory, the U-238 Bypass MHD Magnet, and the CFF Superconducting MHD magnet built by Argonne National Laboratory. All of these magnets are cooled in pool-boiling mode. Magnet design is briefly reviewed. Discussed in detail are the adopted stability criteria, analyses of stability and disturbance, stability simulation, and the final results of magnet performance and the observed coil disturbances.

1. THE ARGONNE 12-FOOT BUBBLE CHAMBER MAGNET /1/

A. Magnet Design Review--The 12-Foot Bubble Chamber Magnet was designed to generate a 1.8 T central field in a field volume of approximately 4.8 m diameter by 3.1 m high. The overall coil assembly consists of two coil halves separated by 53 cm for beam access. Each coil half consists of fifteen pancakes clamped to a central stainless steel girder ring with seven pancakes on one side and eight on the other. The complete characteristics of the coils are given in Table I.

The pancake to pancake spacers are insulated aluminum spacers having a cross section of 5.08 cm x 1.27 cm thick.

The conductor is a composite with six untwisted strands of Nb-48% Ti metallurgically constructed into an OFHC copper strip of dimensions 5.08 cm x 0.508 cm. Only 4% of the overall cross section is superconductor. The remainder being OFHC copper with a resistivity ratio of 200. The actual measured characteristics are 4000 A at 2.5 T parallel field.

The turn-to-turn insulation is glass fiber-filled teflon, 0.254 mm thick by 50.0 mm wide, epoxy bonded to the conductor, allowing only edge cooling on the narrow face of the conductor.

TABLE I

Magnet characteristics of 12-foot and 15-foot bubble/chamber magnets

<u>Magnet characteristics</u>	<u>12-foot</u>	<u>15-foot</u>
Central field	1.8T	3.0T
Peak field	2.0T	5.15T
Operating current	2,200 A	5000 A
Stored energy	80 MJ	396 MJ
Inductance	40 H	31.7 H
Total ampere-turns	5.54×10^6	14.3×10^6
Winding i.d./o.d.	4.18 m/5.28 m	4.27 m/5.08 m
Separation between two coils	54 cm	99 cm
No. of coil pancakes	30	43
No. of turns per pancake	84	65
Average current density	775 A/cm ²	1885 A/cm ²
Current density in conductor	1700 A/cm ²	3700 A/cm ²
Total conductor weight	47,800 kg	50,000 kg
Heat transfer required for stabilization	0.1 W/cm ²	0.15-0.4 W/cm ²

*This work was performed under the auspices of the U.S. Department of Energy by Lawrence Livermore Laboratory under contract No. W-74050-Eng-46.

B. Coil Stabilization-Design Criteria and Simulation Tests--It was decided to use enough OFHC copper cross section to keep the hoop stress within the copper yield stresses. This results in a rather large copper/superconductor cross sectional ratio and a very conservative stabilization design. The resistance per cm length of conductor is 1.3×10^{-8} ohms at 4.2 K and 2 Tesla. Thus, even if the total 2200-A operating current flowed through the copper only, the maximum temperature rise is 0.1 K. This peak temperature is well below the transition temperature of the superconductor under the operating H-I conditions. It is therefore impossible for the superconductor to even go normal as long as it is maintained in a liquid helium bath.

The stability design for the conductor was checked by winding a six-pancake coil of 60-cm ID, 85-cm OD and 38-cm height. The total winding length was 650 m and the coil weight was 800 kg. The inter-turn insulation and the inter-pancake spacing are identical to that of the bubble chamber magnet. The test coil carried a superconducting current of 4650 A while developing a maximum parallel field of 3 T and a 1.9-T perpendicular field before the current sharing occurs. At 7200 A, the conductor thermal runaway and the transition of nucleate-to-film boiling occurred. In order to return to the superconducting state, the coil current was reduced to 3370 A to allow transition back to nucleate boiling.

C. Magnet Performance Tests and Observed Coil Disturbances--During the first two tests, it was impossible to maintain a horizontal surface of separation between liquid and gas because the cryostat had only one gas-exhaust line. Consequently, the liquid level in the opposite region of the exhaust pipe was several inches below the top pancakes. This resulted in quenches of the two top pancakes at 1300 amperes and 1000 amperes. After installation of four equally spaced exhaust pipes, the magnet was successfully energized to 1.84 T. During the charge and the discharge, both the unbalanced voltages between the two coil halves and the dB/dt pick-up coil were monitored to measure the increase or decrease of the inductance. Two types of signals were observed as shown in Fig. 1. The first type is a signal of short duration and large amplitude. The time duration is an order of 100 ms and

Fig. 1 - Unbalanced voltage and coil movement indications

the amplitude of (V_1-V_2) ranges from a few hundred millivolts to a few volts. These signals indicate the fast but small conductor motion. The second types are the signals of long duration. The dB/dt signals are, thus, of small amplitude; these signals probably represent the slow mechanical movements of the coil.

2. THE FERMI LABORATORY 15-FOOT BUBBLE CHAMBER MAGNET /2/

A. Coil Structure--The 15-Ft Bubble Chamber Magnet was designed, constructed, and delivered to Fermi National Laboratory by Argonne National Laboratory. The magnet was designed to generate a central field of 3 T in a field volume having a clear bore of 3.96 m diameter by about 3.42 m in height. There was no iron shield around the magnet. The complete characteristics of the coils are given in Table I

The coil assembly consists of two coil halves separated by a gap of 99 cm. The pancakes, which total 43, are series-connected, vertically stacked, and clamped directly to the bottom plate of the cryostat.

The conductor cross section is 3.76 cm in height by 0.38 cm in thickness. In each pancake, the conductor was wound with a 304 stainless steel strip of 0.19 cm thick by 3.8 cm high. The Nicarta spacers between pancakes, 6.35 cm thick by 2.54 cm wide, provide 50% coverage on the edge surface of the pancake coil.

For manufacturing reasons, the conductor was subdivided into four components as shown in Fig. 2. The superconducting strip is 1.27 cm X 0.254 cm with an aspect ratio of 5:1. The copper-to-superconductor (NbTi) ratio is 4:1. The number of filaments is 60 and the filament size is 0.38 mm diameter, which is small enough for sufficient heat transfer from superconducting filament to copper and yet large enough for easy and reliable manufacturing. These filaments are twisted at one twist per 30 cm. The backing strip of copper sets the overall width of the conductor at 3.76 cm. The two smaller copper pieces, 1.22 cm wide by 0.254 cm thick, have transverse grooves, 0.5 mm deep by 3.17 mm wide, giving a 50% surface for cooling. The assembly of the four components was done by soft-soldering (50-50 tin-lead).

B. Coil Stabilization-Design Criteria and Simulation Tests--Classical full stabilization criterion was used. Both the edge-cooling and the face-cooling are utilized to provide sufficient surface area exposed to liquid helium. For edge-cooling, the wetted area per cm length conductor is 0.572 cm². The heat exchange coefficient used is 0.4 W/cm². For face cooling, the surface is 2.5 cm /cm and the heat transfer coefficient for such shallow channels is 0.15 W/cm². Thus, the conductor exposed surface will remove 0.6 W/cm. On the other hand, the resistivity of copper including magnetoresistance is 3×10^{-8} ohm-cm. Thus, the I^2R power dissipation per cm length of conductor, when it is 100% normal, is 0.585 W/cm.

Fig. 2 - Conductor configuration for 15-Ft Bubble Chamber Magnet

In order to test the stability of the 15-Ft Bubble Chamber Magnet conductor, a 2-Ft model magnet of 8 pancakes stacking together was tested. A 3-Ft length heater was wound with the conductor. The magnet was charged to 4000 A, 4500 A and 5500 A. In each case, the conductor went normally with 100 Watt of heater power (1.08 W/cm). Even when the heater power was raised to as high as 300 W (3.24 W/cm), the normal region still would not propagate. Later, the model magnet was energized to 7100 A. No detectable normal zone were observed. At this current level, the magnet developed a 4-T axial field and 2.5-T peak radial field.

C. Magnet Performance Tests and Observed Coil Disturbances--Testing of the bubble chamber magnet went very well. The magnet current was increased in steps of 100 amperes each, and dumped frequently to monitor switch arcing. It was successfully charged to full design field (3 T at the center of the magnet) at 5000 A. During energization and dumping, the differences in voltage between the upper coil half and the lower coil half were recorded. A complete charge cycle only produced approximately 10 small voltage spikes of a few millivolts each. In comparison, Argonne's 12-Ft Bubble Chamber magnet gave disturbance signals several orders of magnitude in both the number and voltage excursion. The reason given was that the Fermi magnet used twisted superconducting filaments. Furthermore, the pancake coil structure is probably completely elastic during the energization. On the other hand, the ANL magnet used untwisted superconducting filaments which contributed to a large flux jump as well as the twisting force on the conductor resulting from the interaction of shielding current with the magnetic field.

3. THE UNITED STATES SUPERCONDUCTING MAGNET SYSTEM AT U-25 MHD FACILITY /3/

A. The Magnet Design Review--In May 1977, the Argonne National Laboratory successfully completed design and construction of the United States Superconducting Magnet System (U.S. SCMS) for use in the bypass loop of the U-25 MHD facility in Moscow, U.S.S.R.

The geometry of the magnet and the on-axis field intensity are shown in Fig. 3. The significant magnet characteristics are listed in Table II.

The selected coil configuration is a circular saddle shape. Each layer consists of two separate coil halves. The central portion of each coil half is the coil form, which is made of a slotted Micarta sheet of 0.9375 cm in thickness.

The conductor is cryostable with an overall Cu/NbTi ratio of approximately 15:1. It has a cross section of 0.2-cm by 1.0-cm and is a soldered assembly of a rectangular superconducting composite strip fit into a rectangular channel of 0.2 cm by 1.0 cm OFPC stabilizer. The number of filaments is 60. The filament diameter is 150 nm and the twist pitch is 15 cm. Two grades of conductors are used; one (Grade A) with a short sample of 1100 A at 6.5 T and the other (Grade B), 1100 A at 4.5 T.

The turn-to-turn insulation consists of three layers of Mylar tapes with an overall thickness approximately equal to 0.025 cm. The width of the tapes is 1.025 cm. The narrow faces of the conductor will be bare. Fifty percent of the conductor's narrow faces will be exposed to liquid helium. Fig. 4 shows the layer-to-layer structure at both the straight coil region and the coil end region.

Fig. 3 - US SCMS field and coil geometry vs. length

Fig. 4 - US SCMS layer-to-layer structure

B. Coil Stabilization-Design Criteria and Simulation Test--Because of shipping constraints, the coil size must be kept as small as possible, and, thus, a current density of about 5000 A/cm^2 was targeted for the design exercise. Therefore, a relatively high heat flux of about 0.7 W/cm^2 was designed for recovery at 900 A, the operational current at a 6-T peak field. This high-heat flux design was based in part on the belief that heat flux through interturn heat conduction and conduction along conductor cold ends would contribute to the recovery. Therefore, the magnet is only conditionally stable, and the stability and the coil disturbances must be carefully verified experimentally and analytically.

First we modeled the cooling channel geometry to determine the recovery current for several cooling channel heights for the banding width, and for several possible conductor turn-to-turn insulation schemes. For instance, when the banding width is equal to or greater than 20 mm, the recovery current begins to be affected. Next, we found that the proposed conductor recovery current is not affected even when several normal adjacent turns exist. Thirdly, we found that the recovery current is reduced by 10% if cooling channel height is reduced from 5 mm to 2.1 mm, and by 15% if it is reduced to 1.4 mm. Lastly, we found that if the conductor is covered by a film-type insulator, e.g. Kapton film, although it is as thin as 0.0025 mm (0.1 mils), the recovery current was cut in half. On the other hand, if the conductor is insulated with 0.005-mm varnish film such as Formva, the recovery current is reduced by only 5%.

Simple calculations on the conductor stability went as follows: The conductor in each coil pancake will have its 50% conductor edges cooled by liquid helium. The cooling channel between layers is 0.58 cm by 0.95 cm. The wetted area will remove about 0.925 Watt per cm length of conductor. Heat transfer through the turn-to-turn insulation to neighboring cold turns accounts for a minimum of 0.135 W/cm , and the heat generation (I^2R) per cm conductor length is 0.135 W/cm . Thus, the heat conduction along the conductor provides the stability margin if needed. In short, the magnet is stable against certain transient disturbance energy. Fig. 5 shows the computed minimum propagating current versus the perturbation energy. It is seen that at 900 A operating current, a perturbing energy equal or greater than 0.4 Joule will trigger a normal zone propagation. This is equivalent to the work done by the electromagnetic force on a section of conductor of about 10 cm that suddenly slips 2 mm at a magnetic field region of about 3.5 T. Also shown is the experimental data measured using a two-dimensional, 25-cm diam. sample coil and a simulated heater compound with the conductor to simulate the mechanical perturbation. The coil is noninductively wound and the experiment is carried out under a 3.5-T external field. The conductors used are grade B and about 30 meters long. The measured data are generally much better than the calculated ones. The experimental data definitely indicate that the magnet will be stable against a disturbance of about 2 J.

C. Performance Tests and Observed Coil Disturbances--The magnet was energized at incremental steps of current. The magnet energy was dumped at the end of each charging step. It was finally charged to full field without any problem.

The principal concern for the U.S. SCMS coil stability was the frictional heating associated with conductor motion. Two methods were used to detect the mechanical motion. One involved the use of accelerometers which are mounted on the magnet vessel. The other involved the use of many potentiometers connected across the magnet terminals. The inductive voltage of each coil could be bucked out by proper adjustment of the center tap of each potentiometer. It was found that the second method was very sensitive, and the information obtained proved exceedingly valuable in determining the charging rate.

Fig. 5 - Stability simulation test and comparison with the critical data

Fig. 6 - U-25B magnet mechanical perturbation amplitude

Fig. 7 - Mechanical perturbation amplitude varies as B^2

The typical frictional motion is the damped oscillations as shown in Fig. 6. It is seen that the details of a conductor motion could be very complex in nature. A typical time constant for conductor motion is on the order of 10 ms.

The perturbation amplitudes increase approximately as B^2 . This is shown in Fig. 7. In addition to the larger perturbation, one found that more numerous conductor motions per increment of magnet current occurs in the high field level. Since the perturbation amplitude consists of both the inductive voltage and the resistive voltage, it is not possible to derive the disturbance energy from this information.

4. THE COAL-FIRED FLOW MHD FACILITY SUPERCONDUCTING DIPOLE MAGNET /4,5/

A. Magnet Design Review--On August 30, 1981, the Argonne National Laboratory successfully tested a large-aperture superconducting MHD magnet for use in the Coal-Fired Flow Facility at Tullahoma, Tennessee. The CFF MHD magnet generates a peak on-axis field of 6 Tesla in a MHD warm bore having a 80-cm diameter at the inlet, a 100-cm diameter at the outlet, and a 312-cm effective length. The stored energy of the magnet is 210 MJ. The cold mass (4.2 K) is 131 metric tons and the ampere-turns 13.7×10^6 .

The magnet consists of fourteen concentric layers with a shorter coil (coil layer No. 1) close to the bore tube. The coil shape is a circular saddle which will support the hoop stress of the coil end itself. The significant magnet characteristics are listed in Table II. The magnet geometry is shown in Fig. 8. Coil layer structure is similar to that of U.S. SCMS except that the stainless steel banding is replaced by pultruded fiberglass banding.

As shown in Fig. 9, the conductor is a soldered assembly of a superconducting cable of Nb-48% Ti composite wires that fits into the longitudinal groove of the OFMC copper stabilizer. Three grades of conductors are used: Grade A with a 4.2 K short sample critical current of 4400 A at 7.5 T; Grade B, 4400 A at 6.5 T; and Grade C, 4400 A at 4.5 T. The operating point is 3620 A at 4.2 K with a field margin of 0.5 T for each grade of conductors. All conductors have a height of 3.1 cm with conductor thickness varying according to the field grades. The surface of superconducting cable is recessed below the stabilizer surface by 0.76 mm, thus forming a longitudinal cooling channel for the cable. Also shown in Fig. 9 is the turn-to-turn insulation which is a pultruded fiberglass strip with a keystone cross section. It is punched in a fishbone-like pattern for providing about 30% cooling on both conductor broad faces.

Each layer of coil consists of a pair of saddle coils. Pultruded-fiberglass banding, 18.5 cm wide X 7 mm thick, is banded over the coil layer leaving a 18.5 cm spacing between two bands in the straight conductor region and 6.2 cm in the coil end region.

Fig. 8 - Magnet geometry configuration

Fig. 9 - Soldered cable CFF SCMS conductor

B. Coil Stabilization - Design Criteria And Simulation Tests--The design for the stability of the CFFB MHD magnet was based on the classical steady state stability criterion, because the conditional stability required a good guess at the size of possible disturbance which is difficult to estimate. The copper cross sections are 1.303 cm^2 , 1.253 cm^2 and 1.212 cm^2 for grade A, B and C conductors, respectively. The current densities on the copper are 2800 A/cm^2 , 2900 A/cm^2 and 3000 A/cm^2 , respectively, for grade A, grade B and grade C conductors. Both the face-cooling and edge-cooling are employed. The I^2 per cm length of conductor are 0.392 W/cm , 0.359 W/cm and 0.278 W/cm , respectively, for grades A, B and C conductors. For comparison, the heat removal by the wetted area is estimated at about 0.40 W/cm , 0.375 W/cm and 0.35 W/cm , respectively, for grade A, B and C conductors. Thus, the heat conduction along the conductor and through the turn-to-turn insulation will provide additional margins for stability.

To obtain the heat-transfer data and the effect of helium vapor within the channel on the heat transfer, samples of copper conductor having configurations identical to the real conductor were assembled to form the simulated cooling channels. Heaters were embedded in the conductor. Vapor fraction was determined by measuring the change in the capacitance of the channel /6/. The measured steady state heat transfer characteristics shown in Fig. 10 indicate that the maximum nucleate heat flux is 0.4 W/cm^2 , while the recovery heat flux for the transition from film boiling to nucleate boiling is about $0.25 \text{ W/cm}^2/6/$. Once the heat flux exceeds 0.4 W/cm^2 , the temperature will rise suddenly from 4.4 K to about 11.2 K . During the recovery process, the temperature decreases suddenly from 5.2 K to 4.5 K when the nucleate boiling regime is attained.

Using the measured steady state heat transfer curve, one could compute the cold-end recovery current and the absolute stable current. This is shown in Fig. 10. It is seen that, for the CFFB SCMS grade A Conductor, the cold end recovery current is about 5700 A and the absolute stable current is 4800 A . Also shown in Fig. 10 are the heat generation curves for 3750 A , 5484 A and 5750 A .

Figure 11 shows the results of short sample tests for the three grades of conductors. Also shown in this figure are the conductor specifications, the operating points and the measured data for both the minimum propagating current and the recovery currents for each grade of conductor. It is seen that sufficient margins for conductor short sample capability and the conductor stability exist for the conductors employed.

To test further the conductor stability, a 24-cm long, grade A conductor was heated over the 7.5-cm middle region under an external magnetic field of 7.5 T at 3700 A . The conductor remained stable even after it was heated to a temperature of 37 K , absorbing a total power dissipation of more than 173 Watts . However, when the conductor was heated to about 54 K , thermal runaway occurred.

The effects of soldering voids on the recovery current of the superconductor were investigated. Recovery current vs. void length at different external fields is shown in Fig. 12. From these data, it is clear that in order for the CFFB SCMS grade A conductor to recover at 3675 A , the void length should be shorter than 3.8 cm . Note that the grade A conductor with 25.4-cm void length could only recover at a current of 1600 A !!

C. Magnet Performance Tests and Observed Coil Disturbances--The principal concern the very first time the large dipole magnet was energized were the mechanical perturbations from the conductor motion, the possible failure of the structural components, and the possible ground fault and integrity of the energization and magnet protection system. Three methods were used to detect mechanical motion in general and conductor motion in particular; the first one involved the use of unbalanced voltages across the various parts of the superconducting coils. The second involved the use of accelerometers with probes mounted on the outer faces of the end flanges of the helium vessel. The third employed the acoustic emission probes. It turns out that the first method was very

Fig. 10 - Graphical analysis of conductor stability

Fig. 11 - CFFF conductor stability limit and short-sample characteristics

Fig. 12 - The void effect on the recovery current

sensitive and provided very valuable information for us to determine the chirping rate. The results indicated that no significant conductor motion occurs at lower field regions (less than 3 T). Acoustic emission probes indicated that most of the motion occurred at high field coil ends. On the other hand, the higher the magnetic field, the more numerous and serious the conductor motion. Figure 13 shows the detailed time resolution of the unbalanced voltages. It was evident that some motions were simple damped oscillations while others were highly complicated, under-damped oscillations.

TABLE II

Magnet characteristics for US SCMS and CFF SCMS

	US SCMS	CFF SCMS
I. MHD related parameters		
On-axis field: inlet	4 T	4.5 T
peak	5 T	6.0 T
outlet	3.2 T	4.5 T
Effective magnetic length	2.55 m	3.12 m
Warm bore: inlet	0.4 m dia.	0.8 m dia.
outlet	0.6 m dia.	1.08 m dia.
II. Magnet characteristics		
Winding i.d.	34 cm	116 cm
Winding o.d.	70.4 cm	235.7 cm
Winding axial length	3.76 m	4.88 m
No. of layers	23	14
Stored energy	34.2 MJ	210 MJ
Inductance	84.5 H	32 H
Ampere-turns	6.3×10^5	13.7×10^6
Ampere-meters	52×10^6	145×10^5
Operational current	892 A	3622 A
Conductor peak field	6 T	7 T
Conductor current density	4460 A/cm ²	2890 A/cm ²
Cooling	Pool boiling	Pool boiling
Heat flux	0.7 W/cm ²	0.15 W/cm ²
Conductor weight	10,000 kg	48,000 kg
Magnet weight	37,000 kg	172,000 kg

Fig. 13 - Detail time resolution of conductor motion for CFF SCMS

5. MIRROR FUSION TEST FACILITY MAGNET SYSTEM /7/

A. Magnet Design Review—The WFF Magnet, is a Yin-Yang pair with an average major radius of 2.5 m and an average minor radius of 0.75 m. The geometrical centers of the pair are overlapped by 0.7 m, resulting in a net outside dimension of about 6 m and a plasma length between mirrors of 3.6 m. Other magnet parameters and conductor specifications are shown in Table III. The magnet load line, the measured stability, the operating point and the short sample are shown in Fig. 14.

A typical cross section of the coil is shown in Fig. 15. The coil pack is made up of 50 layers of winding of 24 turns each. Interturn insulation is composed of 1.14-mm thick NEVA G-11 buttons glued to a woven string. Interlayer insulation is 1.59-mm thick slotted NEVA G-10 sheets.

TABLE III

WFF magnet parameters and conductor specifications

I. Magnet parameters

Cooling	Pool boiling
Conductor peak field	7.68 T
Field at mirror	4.2 T
Field at center	2.0 T
Mirror-to-mirror length	3.6 m
Operating current	5775 A
No. of turns per coil	1392
Total stored energy	409 MJ
Conductor current density	3729 A/cm ²
Average current density	2325 A/cm ²
Conductor length per coil	20 km
Total cold mass weight	341,000 kg

II. Conductor specification

A. Superconducting core

Short sample	10 kA at 7.5 T and 4.2 K
Core size	6.5 mm X 6.5 mm
Cu/NbTi	1.7 : 1
Copper resistance ratio	150 : 1
No. of filament	480
Filament diameter	0.20 mm
Filament twist pitch	180 mm

B. Perforated sheath copper stabilizer

Resistivity at 7.68 T & 4.5 K	4.6×10^{-6} Ohm-cm
Stabilizer resistivity ratio	220 : 1

C. Overall conductor assembly

Copper to superconductor ratio	6.7 : 1
Overall size	12.4 cm X 12.4 cm
Soft solder	50-50 Pb-Sn

D. Conductor stability

Helium wetted area	Total 8.17 cm ² /cm
External open channel	2.54 cm ² /cm
Internal perforated channel	5.63 cm ² /cm
Average recovery heat flux	0.19 w/cm ²
Measured stability limit	1.55 w/cm
I ² R per cm length	1.28 w/cm

Fig. 14 - MFTF magnet load line

Fig. 15 - Coil assembly cross section

Fig. 16 - MFTF magnet conductor cryostability analysis data comparison with 1-a-bore test data

3. Coil Stabilization - Design Criteria and Simulation Tests--The MFTF conductor, is a result of a two-year conductor development effort (17). A solenoid coil, 103-cm inside and 167-cm outside diameter with axial coil length of 25.6 cm, was constructed to test the stability performance of the MFTF conductor. The insulation system between the pancakes and the turns is identical to that of the MFTF coil structure. Normal zones were created by pulsing heaters attached to the conductor. This study has established the stability limit (the onset of the positive normal front propagation) for the conductor at 1.55 W/cm length of the conductor. This corresponds to a heat flux, averaged over the 8.17-cm wetted area, of 0.19 W/cm^2 . This experimental observation can be explained by averaging heat fluxes of 0.4 W/cm^2 and 0.1 W/cm^2 over the open external and the restricted internal cooling surfaces, respectively. The magnet load line is shown in Fig. 14.

Stability analysis (19) employed a numerical thermal model of a representative length of the MFTF stabilized conductor. The disturbance condition was simulated by imposing a temperature of 30 K on a 40-cm section of the conductor. The disturbance condition corresponds to a disturbance energy input of 2.085 J/cm^2 , far exceeding the boiling heat extraction capacity of the single conductor local helium inventory. The analysis uses the conductor cooling characteristics derived from the above experimental data of the stability-coil tests. Fig. 16 shows the result of the analysis compared with the measured data from the stability coil. From this, one concludes that at a 7.95-T peak field, the magnet will quench in response to a disturbance of 2.085 J/cm^2 ; that is, a 40-cm section of conductor initially normal at a temperature of 30 K, will trigger the quench of the MFTF magnet. At a 7.83-T peak field, the magnet will have recovered from such a disturbance if cold end recovery is available. At 7.775 T, the MFTF magnet should recover even both ends of the normal zone are hot.

REFERENCES

1. J. PURCELL: The superconducting magnet system for the 12-foot bubble chamber. ANL/HEP 6813 (1968).
2. J. PURCELL, H. DESPORTES, and D. JONES: Superconducting magnet for the 15-foot BNL bubble chamber. ANL/HEP 7215 (1973).
3. S. T. WANG, et al.: The U.S. SCNS dipole magnet for the bypass loop of the U-25 XRD facility. Sixth Int. Conf. on Magnet Technology, Bratislava, Czechoslovakia, (1977) pp. 157-162.
4. S. T. WANG, et al.: Final design of a superconducting XRD magnet for the coal-fired flow facility at the University of Tennessee Space Institute. Advances in Cryogenic Engineering, Vol. 25 (1980) pp. 14-29.
5. S. T. WANG, et al.: Fabrication experiences and performance tests of the coal-fired flow facility superconducting dipole magnet. Submitted to Cryogenics (1981).
6. C. J. CHEN, S. T. WANG, J. W. DAWSON: Vapor locking and heat transfer of multiple layers. IEEE Transactions on Magnetics, MAG-17 (1981) pp. 1037-1039.
7. C. D. HENNING, et al.: Mirror Fusion Test Facility Magnet System - Final Design Report. UCRL-52955, (1980).
8. D. K. CORNISH, et al.: MFTF test coil construction and performance. IEEE Transactions on Magnetics, MAG-15 (1979) p. 530.
9. R. F. O'KELL and D. H. RIEMER: Thermodynamic analysis of the magnet system for Mirror Fusion Test Facility. General Dynamics Report No. CASD-LLL-78-002 (1978) Chapter 3.

DISCLAIMER

This document was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor the University of California nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial products, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or the University of California. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government thereof, and shall not be used for advertising or product endorsement purposes.