PORTIONS
OF THIS
DOCUMENT
ARE
ILLEGIBLE

LA-UR-82-340

NOTICE

PORTIONS OF THIS REPORT ARE ILLEGIBLE.

It has been reproduced from the best available copy to permit the broadest possible availability.

Copy - 8/14/83 - 1

Los Alamos National Laboratory is operated by the University of California for the United States Department of Energy under contract W-7405-ENG-36

DISCLAIMER

TITLE SPECTROMETER DETECTORS

AUTHOR(S) C. L. Morris

MASTER

SUBMITTED TO Workshop on High-Resolution, Large-Acceptance Spectrometers,
Argonne National Laboratory, Argonne, IL, Sept. 8-11, 1981

LA-UR-82-340

DISC-82-117

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

By acceptance of this article the publisher recognizes that the U.S. Government retains a nonexclusive, royalty-free license to publish or reproduce the published form of this contribution, or to allow others to do so, for U.S. Government purposes. The Los Alamos National Laboratory requests that the publisher identify this article as work performed under the auspices of the U.S. Department of Energy.

Los Alamos Los Alamos National Laboratory
Los Alamos, New Mexico 87545

SPECTROMETER DETECTORS

C. L. Morris

ABSTRACT

Comparisons of different techniques for position measurements in spectrometer focal plane detector systems are made. Capabilities and limits of gas proportional detectors are discussed.

Talk given at the Workshop on High-Resolution, Large-Acceptance Spectrometers, Argonne National Laboratory, September 8-11, 1981.

I. Introduction

Although the detectors used to readout positions from a large spectrometer system are a small fraction of the total spectrometer system, their performance can have a large impact on the total cost. The better the position resolution the less dispersion that is needed for a given momentum (or energy) resolution, and consequently the smaller the magnets necessary. Conversely, given a total size for a spectrometer system, its design should be optimized to make use of the position resolution available with current state of the art technology.

Most existing medium energy spectrometer systems use some version of the gaseous proportional chambers, either multiwire proportional chambers or drift chambers, to provide position information. First I will try to summarize the properties and capabilities of gas proportional chambers, and then I will describe the chambers used in some of the existing spectrometer systems, and finally I will present some recent ideas and developments.

II. Gas Proportional Chambers (General Properties)

A gas proportional chamber consists of an anode wire surrounded by some gas and cathode planes. The passage of a charged particle through the chamber creates a track of electron-ion pairs. The electrons drift toward the anode wire. If the field strength around the anode wire is sufficiently large an avalanche develops, resulting in an amplification of the original electron pulse by as much as a factor of 10^7 .

The quantities that can be measured are the time and pulse height of the anode pulses, as well as the distribution of the induced cathode pulses. Position information is commonly obtained for such a chamber by one or more of several methods. The first and crudest method is that used in a simple multiwire-proportional chamber (MWPC).¹ Such a chamber consists of a plane of anode wires. For particle trajectories at normal incidence pulse formation only occurs on a single anode wire. Determining which anode wire fired on the passage of a charged particle through the chamber determines its position with an accuracy given by the anode wire separation (the minimum practical separation is about 1mm). A second method involves

determining the particle coordinate along the anode wire. Two methods to accomplish this are to use the induced cathode pulses on a delay line² and measure the cathode distribution directly³ or to use a resistive anode wire and use a R-C⁴ or charge division type of readout.⁵ The third method is to measure the time it takes for an electron track to drift to the anode wire.⁶ Such a measurement provides the shortest distance from the particle track to the anode wire, thus improving on the position resolution obtainable for a given wire spacing over a simple MWPC. Several methods exist for determining on which side of the anode wire the track occurred.^{7,8}

The ultimate position resolution obtainable from such a detector is determined by the dynamics of the ion track formation and by the subsequent diffusion of the electrons in the time between the formation of the ion track and its detection. Since in 1 cm of Argon at atmospheric pressure (the typical thickness of a chamber) one out of 20 minimum ionizing particles will eject an electron whose range is greater than 100 μm , one can expect the ultimate position resolution from a gas proportional counter to be $\approx 100 \mu\text{m}/\sqrt{20}$ or approximately 20 μm (σ). Another contribution to the resolution is diffusion. In the direction parallel to the electric field, diffusion of the electrons in a drift chamber of lengths of 1 cm and with an Ar-Isobutane gas mixture contributes $\approx 50 \mu\text{m}$ to the chamber resolution.⁹ It is interesting to note that the diffusion in the direction perpendicular to the electric field is typically 2 to 5 times smaller¹⁰ than in the direction parallel to the electric field, and so the expected resolution is better in chambers which measure position along the direction of the anode wire.

Although induced cathode pulse readouts are expected to give better resolutions than drift chambers, such resolutions have only been recently observed, and then only for small chamber areas. In fig. 1 we show results obtained by Charpak, et al.³ using a small detector. The position for each event was found by independently reading out and digitizing the induced pulse heights on several cathode strips, and then computing the centroid of the induced charge. The best resolution obtained is $\approx 70 \mu\text{m}$ FWHM, about a factor of 2 better than can be obtained with a drift chamber. Similar results

have been obtained using a delay-line readout chamber with an active area of $5 \times 5 \text{ cm}^2$, fig. 2.¹¹

The counting rate of a MWPC is limited by space charge effects. This limits the rate in a typical chamber to $\approx 10^5/\text{sec/cm}$ of anode wire.⁹ In spectrometer applications, where events tend to be localized on a chamber, such a rate can be exceeded at reasonably low singles rates. Another consideration which is sometimes important is the thickness of a chamber and consequent multiple scattering and energy straggling of the incident particles.

III. Spectrometer Systems

Although as mentioned in the previous section, one can obtain the best position resolution from MWPC's by finding position along the anode wire (either directly, using a delay line, or with resistive anode wires), the best resolution of $< 100 \mu\text{m}$ has been obtained only recently. In chambers of reasonable length, $\approx 60 \text{ cm}$, position resolution has been dominated by contribution from the methods used to read out the cathode information. The accuracy available from charge division¹² or delay-line readouts^{13,14,15} has been limited to $\approx 500 \mu\text{m}$ (FWHM). Because of the complexity of the readout systems, chambers which directly digitize the induced charges on cathode pickup strips, a method which is not expected to degrade in long chambers, have not been implemented for large spectrometer systems. In fact, chambers in the focal planes of the highest resolution medium energy spectrometers (HRS, Bates, EPICS) have used drift time information to interpolate between anode wires and consequently provide position information with resolution $\approx 150 \mu\text{m}$ (FWHM).

A. Delay-line Readout Drift Chambers (DRDC)

The chambers used to readout the HRS and EPICS spectrometer focal planes, more thoroughly described elsewhere,¹⁶ are delay-line readout drift chambers. These systems use chambers with dimensions of up to $30 \times 90 \text{ cm}^2$. Four pairs of chamber planes, two orthogonal sets of four planes each, are used for each trajectory measurement. The planes are of an alternating gradient design¹⁰ with 8 mm wire spacings. Alternate field defining cathode wires are bussed together, providing two cathode outputs per plane, and the anode wires are coupled

directly into a fast (2.5 ns/cm) delay line¹⁵ which provides two anode outputs per plane. The anode planes, which are run at high positive voltage, are separated by grounded foil cathode planes.

An assembly view of such a chamber is presented in fig. 3. The O-ring seals between each plane provide a gas seal that is sufficiently tight to allow the chamber assembly to be used in a vacuum. All connections to the chamber are made through the front cover plate using either BNC connectors for the cathode signals or SHV connectors for the anode signals. Entrance and exit windows are constructed of mylar. This chamber assembly, consisting of eight wire planes used in the front of the EPICS spectrometer and operated in a vacuum with 51 μ m mylar entrance and exit windows, presents 30 mg/cm² of mass to the incident beam.

The anode signals are capacitively blocked and terminated into 100 Ω at the input to the Lecroy Systems Corp. LD604 amplifier-discriminator located approximately 1 meter from the chamber. The resultant NIM level fast logic pulses are transported to the counting house through up to 200 m of 50 Ω coaxial cable, and are then regenerated into a NIM leading edge discriminator and used as stops for CAMAC multichannel TDC's. The start signals for the TDC's are obtained from the trigger coincidence logic of the spectrometer system, which can include information from the chambers. Coarse position information is provided by the time difference between pulses from the ends of the delay lines whereas finer information is obtained from the time sum (drift time information)

The typical position resolution obtained from these chambers is 125 μ m (FWHM) and is independent of the chamber size. This resolution is not compromised by counting rates of up to 10⁶/sec.

B. Vertical Drift Chamber

A novel MWPC drift chamber called the vertical drift chamber (VDC) has been described by Bertozzi, et al.,¹⁷ and used to read out the MIT energy loss spectrometer at Bates. This device uses a single wire plane, rotated 45° with respect to the central ray leaving the spectrometer and lies approximately in the focal surface of the spectrometer. A detailed cross section view of this chamber is shown in fig. 4. Each of the active anode wires are alternately coupled

through an amplifier and discriminator into one of three delay lines. This readout scheme is shown in fig. 5. As in the chamber described above, the difference in pulse arrival times from the ends of the delay lines is used to decode the wire number, while the sum is used to provide the drift time.

As can easily be seen, with these chambers one plane provides both position and angle information. The accuracy of the reconstructed track position is 120 μm (FWHM) and the measured angle resolution is 12 mr .

IV. Recent Developments

A. Use of Induced Cathode Pulses

An alternative method of making the Left-Right decision recently applied to individual wire readout chambers^{7,8} is to use the current pulses induced on the cathode field defining wires. Using the present DRDC, Left-Right information was obtained by measuring the difference in the induced currents on the cathode wires on either side of the active anode wire. To minimize the electronics needed for these measurements, every other cathode wire in a plane is bussed together, providing two cathode outputs per plane. The difference of these two signals is generated using a voltage-sensitive differential amplifier. For odd (even) wires, a positive (negative) signal is observed for particles passing to one side of the anode wire, and a negative (positive) signal is observed for particles passing to the other side. The integration time constant of the amplifier, determined by the 80 pf capacitance of the chamber and a 500 Ω terminating resistor, is about 40 ns. The analog output from such a circuit, integrated for 100 ns, is shown in fig. 6 as a function of position. One can see a clear separation between the L-R signals. Initial tests of this method showed an erroneous left-right decision was made approximately 1% of the time.

This method reduces the number of chamber planes required to make a position measurement to one, and consequently results in a considerable simplification of the spectrometer system.

B. Reduction of Multiple Scattering

The present limit of the resolution of the EPICS spectrometer is determined by the accuracy of the angle measurements made in the front chambers (a schematic view of the spectrometer system is shown in fig. 7). The measured FWHM of this angle determination is 4 mrad, about what is expected from multiple scattering in the chamber gas. A reduction of a factor of ≈ 2 can be made in this multiple scattering by using a chamber gas mixture based on Neon rather than Argon. Initial tests of such a mixture showed it to be feasible, although some trouble was encountered with obtaining an efficiency greater than 98%/chamber plane. We hope to solve this problem with more experimentation.

A further reduction in the thickness and multiple scattering in these chambers can be obtained by replacing the existing windows with preformed Beryllium windows. Windows of 0.001" thickness can be made by sputtering Beryllium onto an aluminum mandrel. Forming the windows to a spherical shape reduces the stress, and allows thinner windows to be used over a given area.

V. Conclusion

Most present spectrometer readout systems use drift chambers to provide the needed positive resolution. With such chambers, it is possible to measure positions with accuracies of $\approx 120 \mu\text{m}$, and angles with accuracies limited by multiple scattering. The most cost effective spectrometer designs are likely to be ones which include the possibility of software corrections which can be made with such readout systems in the design phase.

REFERENCES

1. G. Charpak, R. Bouslier, T. Bessari, J. Favier and C. Zupansic, Nucl. Instr. and Meth. 62, (1968) 262.
2. R. Grove, I. Ko, B. Leskovar and V. Perez-Mendez, Nucl. Instr. and Meth. 99 (1970) 381.
3. G. Charpak, G. Petersen, A. Policarpo and F. Sauli, Nucl. Instr. and Meth. 148 (1978) 471.
4. C. J. Borkowski and M. K. Kopp, Rev. Sci. Instr. 39 (1968) 1515.
5. B. G. Harvey, J. Mahoney, F. C. Pühlhofer, F. S. Goulding, D. A. Landis, J. C. Faivre, D. G. Kovar, M. S. Zisman, J. R. Miriwether, S. W. Cospers and D. L. Hendrie, Nucl. Instr. and Meth. 104 (1972) 21.
6. A. H. Walenta, J. Heintz and B. Schürlein, Nucl. Instr. and Meth. 92 (1971) 373.
7. A. H. Walenta, Nucl. Instr. and Meth. 151 (1978) 461.
8. A. Breskin, G. Charpak and F. Sauli, Nucl. Instr. and Meth. 151 (1978) 473.
9. F. Sauli, CERN Report #77-09 (1977).
10. A. H. Walenta, Nucl. Instr. and Meth. 111 (1973) 467.
11. A. C. Thompson, J. M. Jaklevic, B. H. O'Connor, C. L. Morris, submitted to Nucl. Instr. and Meth.
12. V. Radeka and P. Rehak, IEEE Trans. Nucl. Sci., NS-25 (1978) 46.

13. D. M. Lee, S. E. Sobottka, and H. A. Thiessen, Nucl. Instr. and Meth. 109 (1973) 421.
14. J. L. Lacy and R. S. Lindsey, Nucl. Instr. and Meth. 119 (1974) 483.
15. C. L. Morris, H. A. Thiessen, and G. W. Hoffmann, IEEE Trans. Nucl. Sci. NS-25 (1978) 141.
16. L. G. Atencio, J. F. Amann, R. L. Boudrie and C. L. Morris, Nucl. Instr. and Meth. 187 (1981) 381.
17. W. Bertozzi, M. V. Hynes, C. P. Sargent, C. Creswell, P. C. Dunn, A. Hirsch, M. Leitch, B. Norman, F. N. Rad, and T. Sasanuma, Nucl. Instr. and Meth. 141 (1977) 457.

FIGURE CAPTIONS

Fig. 1: Position resolution obtained by Charpak et al.³ for X-rays in a chamber with independently readout cathode strips.

Fig. 2: Position resolution obtained by Thompson et al.¹¹ for X-rays in a short delay-line readout chamber.

Fig. 3: Assembly view of an EPICS front chamber.¹⁶

Fig. 4: Schematic drawing of a VDC¹⁷.

Fig. 5: Schematic drawing of the readout scheme for a VDC¹⁷.

Fig. 6: A scatter plot showing the difference in the induced cathode pulses for events on different sides of the anode wires. Anode wires are located every 8 mm from the center of the plot.

Fig. 7: Plan view of the EPICS spectrometer as modified for a recent double charge exchange experiment. Chambers are located in both the front chamber box, as well as at the rear of the spectrometer.

Figure 1

Figure 2

Figure 3

Figure 4

Figure 3

Figure 6

Figure 7