February 1992

**Vibration Study of the APS Storage Ring
Girder/Support Assembly Equipped with
Wedge-Type Alignment Jacks**

ANL/APS/IN/VIB--92/2

DE92 014023

by

J. A. Jendrzeczyk, M. W. Wambsganss, and R. K. Smith
Materials and Components Technology Division
Argonne National Laboratory

Background

As discussed in Ref. 1, the quadrupole magnets have a very stringent vibration criteria that must be satisfied if successful operation of the Advanced Photon Source (APS) facility is to be achieved. A feedback control system, using beam position monitors (BPMs), will compensate for magnet vibration at frequencies below 10 Hz. However, if the dynamic range of the feedback control system is exceeded, degraded performance will result, even in this frequency range. Therefore, frequency response of the magnet girder/support systems at frequencies below 10 Hz cannot be automatically disregarded. At frequencies above 10 Hz, the vibration amplitudes must satisfy the vibration criteria (see Ref. 1).

Several vibration studies of magnet girder/support systems that incorporate jackscrews as an alignment mechanism have been performed and reported [1,2]. Under certain conditions, a large 7.6-Hz vibration response was measured. This vibration was linked to the position (alignment) of the jackscrew within the jackscrew housing, which, in turn, was shown to be influenced by the horizontal alignment of the girder assembly. This girder/support assembly design with alignment jackscrews was considered unacceptable due to the potential for large magnification factors (>65, based on the measured damping factor) and the inherent uncertainty in mechanical fit-up of the jackscrew within its housing.

A new girder/support assembly design was developed with a sliding-wedge-type jack as the alignment mechanism and incorporating a significantly stiffer pedestal on which the jacks are mounted. The new design was fabricated and its vibration response was measured. The evaluation of the vibrational characteristics (natural frequencies, modes, and damping) and a comparison with the dynamic response characteristics of the earlier design (with jackscrews) are the subjects of this report.

MASTER

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

Objectives

The primary objective of this study is to evaluate and test the new girder/support assembly design from a vibration standpoint, and to determine what, if any, conditions could lead to unacceptable vibration response.

There are also two secondary objectives:

- Determine whether smaller sliding-wedge-type jacks are needed to anchor the large alignment jacks to the lower pedestal, or if standard bolts are acceptable.
- Determine whether modifications to the large alignment jacks are required in order to limit unwanted horizontal motion. The modifications involve restraining the horizontal motion of the sliding-wedge jacks by six setscrews.

Technical Approach

The girder/support assembly, shown schematically in Fig 1, was mounted to the Building 382 highbay floor. The pedestal-to-floor interface was not prototypical in that grout was not used and one anchor bolt in the single-jack end of the girder was missing due to misalignment problems in the test set-up. Floor thickness at the test location was estimated to be about 6 in., whereas the storage ring basemat on which the final design will be mounted is 24-in.-thick concrete. Also, to mount both pedestals on a single continuous section of concrete, it was necessary to place the girder near a corner of a slab that was isolated from adjoining slabs by expansion joints. This resulted in a floor that was much more flexible than the storage ring basemat, and therefore not prototypical.

The weights of the individual magnets were simulated by concrete shielding blocks, which were positioned axially to correspond to the center of mass of the actual magnets. To prevent damage to the surface of the girder by the rough surfaces of the shielding blocks, Mylar sheets were placed between the girder and the blocks. As discussed later, the uneven surface of the blocks and the relatively small "footprint" of the block on the girder resulted in a large dynamic response in the axial (beamline) direction, which is also nonprototypical.

Dynamic excitation was provided by two sources: (a) an electrodynamic exciter, which was used to provide either a 1-150 Hz random force or a single-frequency sine force, and (b) ambient floor motion.

Two triaxial accelerometer units (each consisting of an array of three accelerometers orthogonally positioned on a mounting block to measure acceleration in three axes) were used to measure floor motion and girder response. The measured accelerations were double-integrated to obtain displacements and were recorded on an FM magnetic tape recorder for subsequent analysis.

System resonant frequencies and vibration amplitudes were determined from power spectral density (PSD) plots generated with a Fast Fourier Transform analyzer. Mode shapes were obtained by exciting the girder sinusoidally at specific frequencies and using a portable (handheld) accelerometer to measure response amplitudes and phase at various locations.

Test Description

Test Article

The test article is a prototypical Section 5 storage ring girder/support assembly (shown schematically in Fig. 1, along with pertinent dimensions, including sizes and weights of the concrete shielding blocks). The girder surface was positioned at the required height by placing shims (nominally 1-1/2 in. in thickness) between the pedestal base and the floor. The pedestals were anchored to the floor with 3/4-in. diameter bolts that were securely fastened to the concrete floor. To facilitate removal, no grout was used between the pedestal base and floor. The accelerometer triplets were fastened to the girder surface and floor with epoxy. The exciter was fastened to the girder with C-clamps, and a piece of Mylar was sandwiched between the exciter base and girder to protect the machined girder surface.

Excitation Method

Two excitation methods were employed: (a) an electrodynamic exciter was attached to the girder and used to produce either random or sinusoidal force at three nominal levels (designated by input voltage levels of 0.1, 0.4, and 0.6), and (b) ambient ground motion. The three nominal force levels are particularly useful in determining system linearity and verifying sensitivity of the instrumentation. Ambient ground motion was transmitted to the girder via the two pedestals and the three alignment jacks and their associated mechanical components. Work activity in the area of the girder test was minimized whenever ambient-ground-motion excitation tests were conducted.

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

Measurement Method

Response was measured with accelerometers mounted in the two locations shown in Fig. 1. The location on the girder was chosen to avoid a vibration node and thereby to ensure measurable responses for all expected vibration modes. The floor location, near the pedestal, allows for calculation of a pseudo-transfer function (magnification factor) between the floor and girder response. Accelerations were double-integrated to obtain displacements in the range of 4-100 Hz, which were recorded on an FM analog tape recorder and analyzed with an HP 356 Fast Fourier Transform analyzer. The analysis frequency range is 0-100 Hz; however, no significant responses were observed above 70 Hz. Displacements were calculated from PSD measurements, which allow the use of digital filtering to study contributions at selected frequencies. Linear spectrum-frequency plots were used in calculating the system damping factor.

Test Matrix

A series of tests was planned and executed to accomplish the objectives of this study. The various tests are described below.

Test 1

Test conditions: Clamping bolts are used to attach the alignment jacks to the top surface of the pedestal. All bolts and lateral adjusters are tight.

Objective: Determine resonant response frequencies, displacements, and mode shapes. This is considered the reference test.

Excitation: Random or sinusoidal force excitation applied to the girder; ambient floor motion.

Measurement: Displacement response of the girder in three orthogonal directions (see Fig. 1).

Test 2

Test conditions: Basically the same as in Test 1, except that six small sliding-wedge-type jacks replace the bolts that fasten the alignment jacks to the pedestal. Girder alignment was disturbed during the installation of the small jacks.

Objective: Determine resonant frequencies and displacements; compare response with that of Test 1 to assess the need to use the more expensive small sliding-wedge jacks, rather than the less expensive bolts.

Excitation: Random or sinusoidal force excitation applied to the girder; ambient floor motion.

Measurement: Displacement response of the girder in three orthogonal directions (see Fig. 1).

Test 3

Test conditions: Six small setscrews, which were used to restrain horizontal motion of the wedge on each of the three alignment jacks, were removed. This allowed a potentially "looser" jack configuration. Six smaller sliding-wedge-type jacks fastened the alignment jacks to the pedestal as in Test 2.

Objective: Determine resonant frequencies and displacements; compare results with the results of Test 2 to evaluate the necessity of restraining horizontal motion of the alignment jack wedges.

Excitation: Random or sinusoidal force excitation applied to the girder; ambient floor motion.

Measurement: Displacement response of the girder in three orthogonal directions (see Fig. 1).

Test 4

Test conditions: Small sliding-wedge-type jacks are replaced with 3/8 in. diameter bolts; otherwise the same as Test 3 with the "loose" alignment jacks.

Objectives: Determine resonant frequencies and displacements; compare with the results from Test 3 to evaluate the effect of replacing the small sliding-wedge-type jacks with 3/8 in.-diameter bolts.

Excitation: Random or sinusoidal force excitation applied to the girder; ambient floor motion.

Measurement: Displacement response of the girder in three orthogonal directions (see Fig. 1).

Test 5

Test conditions: The concrete shielding blocks are anchored to the girder with bar clamps in an attempt to limit their large contribution to the axial (beamline) direction response. To accommodate the available clamps, the top block at the 109-in. position (Fig. 1) was repositioned with its 18-in. side resting on the lower block, resulting in a total height of 30 in. The test is otherwise identical to Test 4.

Objective: Determine resonant frequencies and displacements. This test attempts to anchor the concrete shielding blocks to the girder, thereby eliminating nonprototypical rocking.

Excitation: Random or sinusoidal force excitation applied to the girder; ambient floor motion.

Measurement: Displacement response of the girder in three orthogonal directions (see Fig. 1):

Test 6

Test conditions: The clamps used in Test 5 were removed and the concrete shielding block that had been repositioned was returned to the Test 4 position. Test conditions are identical to those of Test 4.

Objective: Determine resonant frequencies and displacements. If the exciter can provide sufficient input to the floor, calculate the magnification factor between floor and girder motion.

Excitation: Random or sinusoidal force excitation applied to the girder; ambient floor motion.

Measurement: Displacement response of the girder in three orthogonal directions (see Fig. 1).

Test 7

Test conditions: All concrete shielding blocks are removed; girder is unloaded, otherwise, conditions are the same as Test 4.

Objective: Determine resonant frequencies and displacements of unloaded girder.

Excitation: Random or sinusoidal force excitation applied to the girder; ambient floor motion.

Measurement: Displacement response of the girder in three orthogonal directions (see Fig. 1).

Test 8

Test conditions: Same as Test 7.

Objective: Determine the response of the unloaded girder to floor motion.

Excitation: Random force excitation applied to the floor.

Measurement: Displacement response of the girder in three orthogonal directions (see Fig. 1).

Test Results

The general identification scheme for the various tests is as follows: The first number (1-8) identifies the test, the letter (X, Y, or Z) designates the direction of the force excitation applied to the girder (see Fig. 1 for definition of coordinate scheme), and the double digits (01, 04, or 06) define the nominal force excitation level (low, medium, and high, respectively). For example, a test labeled 1X01 designates Test 1, with forced excitation in the X-direction, at a nominal force level of 01 (low force).

Test 1 is the reference test against which all other tests are compared. Therefore, more detailed information, such as mode shapes, were obtained and are presented for Test 1.

Power spectral densities from which the pertinent information was derived are plotted as a linear response spectrum (square root of PSD) versus frequency and are given in Appendix A.

Test 1

Resonant response frequencies for force excitation in three directions and at three nominal force levels are shown in Table 1a. Mode shapes were measured at the "two-jack" end of the girder with a handheld accelerometer; measurement locations used for the X- and Y-direction mode shape measurements are shown in Figs. 2 and 3, respectively. In the following, with the exception of the 8.5-Hz frequency, the various frequencies given in Table 1a are discussed relative to their

mode shapes. The 8.5-Hz frequency was attributed to the response in the vertical direction of the highbay floor and is not a resonant response frequency of the girder/support assembly.

The 9.6 Hz mode was identified as a Y-direction rigid body mode. It is also observed in the Z-direction, primarily due to translational response between the Y- and Z-directions as a result of the exciter position. The mode shape, measured for the 9.6-Hz component is given in Fig. 4; measurement points are identified by arrows. A large amount of flexibility is observed at the 19-in. elevation, corresponding to the top of the alignment jacks, at the location of a spherical washer.

The 22.6-Hz response, with its mode shape shown in Fig. 5, is a rigid-body response of the girder in the X-direction. This mode includes the concrete shielding blocks rocking on the girder surface, which is a direct result of the concrete shielding blocks not being anchored securely to the girder. If the blocks were securely anchored to the girder surface, some increase of response frequency could be expected.

Two additional X direction resonant frequencies, 40 and 48 Hz, are also the result of the shielding blocks rocking on the girder surface. This rocking motion is readily observed in the mode shapes shown in Figs. 6 and 7. Similar to the 9.6-Hz mode, a large amount of flexibility is observed at the top (19-in. level) of the alignment jacks at both frequencies. These frequencies are not considered prototypical; they would not be expected in a system in which the magnets are properly anchored to the surface of the girder. A small Y-direction response was observed at 60 Hz; its mode shape shown in Fig 8. This mode is also associated with the blocks rocking on the girder surface and therefore is not a prototypical response of a system in which the magnets are properly anchored to the girder.

In all the mode shapes measured, i.e., Figs. 4-8, rotation at the pedestal/shim/floor interface was observed, in addition to rotation at the girder/jack interface (spherical washer). Contributing to the flexibility at the pedestal/shim/floor interface is a combination of several nonprototypic conditions: (a) no grout was used between the pedestal base and floor surface, (b) due to alignment problems, only five bolts were used to anchor the "single jack" pedestal to the floor, and (c) the floor was relatively flexible as it was only approximately 6 in. thick and the pedestals were mounted near a corner of the concrete floor slab.

Wideband displacement-amplitude response for forced excitation is shown in Table 1b. The largest observed displacement of $0.407 \mu\text{m}$ RMS was for test condition 1Y06; for the girder/support design with jackscrews, the corresponding displacement was greater than $1 \mu\text{m}$ RMS. Displacement amplitude at 9.6 Hz

(Table 1c) is also the largest for test condition 1Y06, viz., $0.329 \mu\text{m}$ RMS. A comparable value for the girder/support assembly design with jackscrews in a 7.6-Hz mode is $0.785 \mu\text{m}$ RMS. Because the actual displacements are a function of excitation and measurement positions, the above comparisons should be considered accordingly.

Wideband displacement measurements of the girder to ambient floor motion are shown in Table 1d. Wideband magnification factors (pseudo-transfer functions), defined as the ratio of wideband girder response (output) to wideband floor motion (input), were computed and are also given in Table 1d. All magnification factor values are less than 2, which is considered acceptable.

Measured damping factors are shown in Table 1e. Only the 9.6-Hz mode is considered prototypical, because the other modes include nonprototypical rocking of the shielding blocks on the girder. Nevertheless, the damping characteristics of the other (nonprototypical) modes are of interest as indicators of the effect of design changes on system dynamic characteristics.

Test 2

The bolts that anchor the alignment jacks to the pedestals are replaced with small wedge jacks for this test. System resonant frequencies for forced excitation are shown in Table 2a. Because the objective of this test is to evaluate the effect of wedge-jack anchors on overall response, the 8.5-Hz floor response is neglected. Considering that it was necessary to realign the girder to facilitate installation of the wedge jacks, the frequencies of this test compare well with those of Test 1.

Wideband girder and floor response due to random excitation of the girder is shown in Table 2b. The measured displacements are about the same as those of Test 1 (see Table 1b). The 9.6-Hz displacement response, given in Table 2c, shows a similar trend when compared with results given in Table 1c; amplitudes in the Y-direction are approximately the same for the two tests.

RMS displacement response to ambient floor motion (wideband and 10-100 Hz) is given in Table 2d. Because the ambient floor vibration is random and is influenced by activity in the building, the magnification factor is a more valid parameter for comparison. A comparison of the magnification factors obtained in Tests 1 and 2 (Tables 1d and 2d, respectively) show that they are approximately equal, indicating little or no change in the dynamic response due to replacement of the bolts by small wedge jacks.

Damping factors for several modes are given in Table 2e. A comparison with corresponding damping factors from Test 1, given in Table 1e, reveals that

the modal damping factor for the 9.6-Hz mode is slightly smaller than that of Test 1. Further, the damping factor for the 22/23-Hz mode remains basically unchanged between tests. Because the girder was realigned between tests, it is important to note that no random variation of damping factor was observed as in the previous design with alignment jackscrews [2].

Test 3

For this test, the small setscrews, which prevent horizontal movement of the wedges in the alignment jacks, were removed, allowing a potentially "looser" jack. The objective of this test was to determine the necessity of providing horizontal restraint to the alignment jack wedge. Again, comparisons of test results from this configuration will be made with those from Test 1.

The resonant frequencies, determined from random-force excitation of the girder, are shown in Table 3a; the 8.5-Hz frequency is again omitted from the table. The 9.7-Hz mode is the same for both Tests 1 and 3. An additional frequency component, 20-Hz, is observed in this test, but appears to be a floor mode that is coupled to the girder; it is so determined, because, in the PSD plots, it is greater in proportion to the 9.7-Hz component measured on the floor than to that component measured on the girder. The 40- and 48-Hz modes, which are not typical girder response modes but can be used as an indication of a change in system dynamics, remain unchanged between tests.

Wideband dynamic-displacement response of the girder and floor due to random force excitation of the girder is shown in Table 3a. Displacement response in the X- and Z-directions is slightly lower than that of Test 1 (Table 1b), but the Y-direction amplitude is slightly higher. The differences are small and, considering the small amplitudes, can be considered approximately equal. Displacement response at 9.7-Hz mode (Table 3c) is approximately equal for both tests.

Dynamic response of the girder to ambient floor motion is shown in Table 3d. The wideband magnification factors are slightly higher in this test than in Test 1 (Table 1d). However, a considerable increase is observed in the 10-100-Hz magnification factors in the Y- and Z-directions. This increase can be attributed to the additional contribution from the 20-Hz mode, which was not seen in Test 1.

Damping factors for the observed modes are shown in Table 3e. There is a slight increase in the 9.7-Hz mode damping factor and a slight decrease in the 22/23-Hz mode damping factor. Importantly, no significant change in damping factor, which could indicate a dependence on mechanical fit-up of the components, could be observed.

Test 4

The small wedge jacks that anchor the alignment jacks to the pedestal are replaced with 3/8-in. bolts. Using bolts to anchor the horizontally unrestrained (unmodified) alignment jacks is the least expensive design condition.

The resonant frequencies determined from random excitation force of the girder are shown in Table 4a, again, the 8.5-Hz floor response is omitted. The lowest (9.6-Hz) mode is comparable to that measured in previous tests (Tests 1 and 2). The 15.5-Hz response is a low-level response that does not contribute significantly to the girder motion. The 20-Hz response is the same as that of Test 3. The 23-Hz mode is the rigid-body mode of the girder system in the X-direction and is approximately the same value as measured in previous tests. The 29-Hz response is coupled from the floor to the girder and corresponds to a rotational speed of 1750 rpm; it may be the result of an unbalanced condition in building equipment, such as a heating fan. The 40- and 48-Hz modes are measured as in previous tests and indicate no gross change in system dynamics.

Wideband dynamic-displacement response of the girder and floor to random force excitation of the girder is shown in Table 4a. A comparison of the measured displacements of this test to those from the reference test, Test 1, leads to the following observations: X-direction response amplitudes are approximately equal; Y-direction response is larger; and Z-direction response is smaller. The displacement response at 9.6 Hz (Table 4c) is slightly larger for this test.

Dynamic response of the girder to ambient floor motion is given in Table 4d. From the wideband measurements, the X-direction magnification factor remains unchanged, while the Y- and Z-direction magnification factors show some increase. All three directions show an increased magnification factor compared to that in reference Test 1. Considering the randomness of the excitation source, all magnification factor values are still well within acceptable values.

Damping values for the observed modes are shown in Table 4e. The damping factors associated with the 9.6- and 23-Hz modes are comparable to those of Test 1. No randomness was observed in the measurement of the damping factors.

Test 5

Bar clamps were used in an attempt to anchor the shielding blocks to the surface of the girder more securely. However, with this modification, the test is so nonprototypical that measurement results will are not reported.

Test 6

This test is identical to Test 4, but with the floor rather than the girder excited with the random-force generator. Table 5 shows the wideband displacement response of the girder and floor to both ambient and forced excitation. The magnification factors indicate that very little force is being input to the floor by the exciter. Most of the girder excitation results from ambient floor excitation, which was covered in sufficient detail in the preceding test discussions.

Test 7

This test consists of exciting the girder surface with random excitation. The shielding blocks are removed and the only items on the girder surface are the exciter and accelerometer triplet. For this test series, the X-direction girder accelerometer channel was inoperative; thus only the Y- and Z-direction resonant frequencies were considered. Only a 33-Hz resonant frequency, detected in both the Y- and Z-directions, was measured. The corresponding mode was determined to be a rigid-body mode in the Y-direction.

Test 8

This test is identical to Test 7 except that the exciter is located on the floor. Two system resonant frequencies were measured: a Y-direction rigid-body mode frequency at 34 Hz (this represents a slight increase from the 33-Hz value measured in Test 7 and may be the result of less mass on the surface of the girder with the exciter removed), and an X-direction rigid-body mode frequency at 51/52 Hz.

Discussion

In this section, comparisons will be made between the dynamic response of the girder/support assembly with wedge jacks to that of the girder/support assembly with jackscrews. Test 5 of this study will be used as the basis for comparison. Resonant frequencies, RMS displacement response to ambient floor motion, and modal damping factors will be considered.

The measured resonant frequencies for both girder/support assembly designs are given in Table 6. In the test of the girder/support assembly with alignment jackscrews [2], one 0.8-m quadrupole magnet was mounted to the girder surface, with concrete shielding blocks used to provide the additional mass required to simulate the remaining magnets. For those tests, however, the

shielding blocks used had a much larger "footprint" on the girder surface, which effectively served to minimize the rocking effect observed during these tests. From Table 8, it can be seen that five discrete resonant frequencies (modes) were measured; a very large amplitude ($0.5 \mu\text{m}$ RMS) was measured in the 7.62-Hz mode. Discounting the frequencies associated with the rocking of the shielding blocks, there were only two dominant modes for the girder/support assembly with alignment wedge jacks, and neither mode was associated with an unacceptably large dynamic response amplitude.

RMS response to ambient floor motion is given in Table 7. The girder/support assembly with alignment jackscrews was tested in Building 362, while the assembly with alignment wedge jacks was tested in Building 382. A smaller overall ambient floor motion was measured in Building 382, and this will have some influence on the values in Table 7. Nevertheless, trends can still be compared.

For the assembly with alignment jackscrews, the ambient displacement response level in the Y-direction was $0.526 \mu\text{m}$ RMS. Much of this response was controlled by the 7.6-Hz mode. Although the feedback control system will be able to control at frequencies below 10 Hz, the large floor/girder magnification factor is felt to be unacceptable. In contrast, no large response amplitudes were observed with the design using wedge jacks for alignment. For the two modal frequencies, the measured magnification factors were less than 3 for all test configurations. The RMS displacements in the frequency range of 10-100 Hz were also well within the APS vibration criteria.

Modal damping factors for both alignment jack designs are shown in Table 8. For the dominant 7.6-Hz mode, the measured damping factor for the assembly with alignment jack-screws varied between 0.0071 and 0.034. This variation was correlated to the mechanical fit-up of the jackscrew within its housing. This jackscrew housing clearance can be affected by horizontal alignment adjustments, allowing damping to take on values in an unpredictable manner. For the dominant 9.6- and 23-Hz modes of the girder/support assembly with wedge jacks for alignment, the measured modal damping factors were 0.024 and 0.017, respectively. The damping factors were predictable in that no variance was observed as the alignment was changed to implement the various test conditions.

Summary, Conclusions, and Recommendations

The girder/support assembly tested and reported here features stiffened I-beam pedestals and sliding-wedge-type alignment jacks (see Fig. 1). These represent the major changes from the previous jack-screw on pedestal design.

These represent the major changes from the previous jackscrew-on-pedestal design [1,2]. A series of vibration tests were performed with the objectives to (1) determine the dynamic characteristics (natural frequencies, modes, and damping) of the system and the system response to ambient floor motion, and (2) use this data to compare the design with wedge-type alignment jacks with the design based on jackscrews for alignment. The dynamic characteristics and RMS displacement response were determined for several different system configurations.

Several deviations from prototypicality were observed:

- The pedestal supports are not grouted at the pedestal/floor interface. Rather, the pedestal supports are bolted to the floor and shims are used between the support and floor to achieve the required height and alignment (see Fig. 1).
- The magnet masses are simulated by concrete shielding blocks that are axially positioned to correspond with the center of mass of the actual magnets (see Fig. 2). In the vertical direction, the actual center of mass will be a few inches higher than that simulated. It is significant that the blocks were simply placed on the girder surface and not fastened securely to the surface.
- The floor to which the pedestals are mounted is estimated to be only about 6 in. thick. This implies that the floor is more flexible than the APS storage ring basemat (24 in. thick). Further exacerbating the problem of increased flexibility is the fact that space limitations made it necessary to mount the girder close to a "corner" of the floor slab, in the sense that floor joints were close by.

All three of these deviations from prototypicality contributed substantially to the measured dynamics of the system, as will be discussed below.

Dominant frequencies in each of the three measurement directions (X, Y, Z) were identified from frequency-response plots:

- In the X-direction, with the magnet masses simulated, the dominant frequencies are 23, 41, and 48 Hz. On some tests, 15-, 33-, and 27-Hz frequencies were observed. With no load on the girder, the first dominant frequency is 52 Hz.
- In the Y-direction, with the magnet masses simulated, the dominant frequency is 9.6 Hz. On some tests, frequencies of 20, 33, and 60 Hz were

observed. With no load on the girder, the first dominant frequency is 33 Hz.

- In the Z-direction, with the magnet masses simulated, the dominant frequency observed is 9.6 Hz. On some tests, frequencies of 21, 29, and 62 Hz were observed. With no load on the girder, the first dominant frequency observed is 33 Hz. Both the 9.6- and 33-Hz frequencies can be associated with predominantly Y-direction modes. Here, it should be noted that many of the frequencies were very "weak," as represented on the frequency response plots.

Mode shapes were studied as an aid to understanding the dynamic response at each of the dominant frequencies; Y-direction modes of 9.6 and 60 Hz (see Figs. 4 and 7), and X-direction modes of 23, 40, and 48 Hz (see Figs. 5, 6, and 8), respectively, were evaluated. In the 9.6-Hz mode, as shown in Fig. 4, the blocks and girder move together as one rigid body; the block/girder interface does not come into play. However, all other studied modes showed the blocks to be moving relative to the girder. In the 40-, 48-, and 60-Hz modes, parts of the blocks are moving out of phase with the girder, i.e., rocking on the girder. This is not prototypical of the behavior to be expected with actual magnets installed on the girder. Therefore, these modes are not representative of the actual situation. Similarly in the 23-Hz mode, although the motion of the blocks is in phase with the girder, indications are that the modes are not representative of the actual situation, because the blocks are rotating relative to the girder and the magnet/girder interface is not properly simulated.

Study of the 9.6-Hz mode shape (Fig. 4) leads one to conclude that there is rotation at both the jack/girder interface and the pedestal/floor interface. The jack/girder interface, which includes a spherical washer, is prototypical. However, the pedestal/floor interface, which includes shims and bolts, is not prototypical. In the actual facility, the pedestal will be grouted and bolted to the floor.

Grouting the pedestals to the floor can be expected to increase the stiffness at that interface and therefore the frequency of that mode. One cannot estimate the percentage of increase with any degree of confidence. Also, it is reasonable to expect that the contribution to damping from that interface will be different with the grout.

Damping values were estimated with the half-power-bandwidth method. In general, the damping factor is relatively high, ranging from 1.7 to 2.6%.

Ambient floor motion and the response of the system to this motion were also measured. In the X- and Y-directions, RMS displacements over the frequency band 10-100 Hz averaged approximately 0.008 μm RMS; in the Z-direction, it averaged approximately 0.023 μm RMS. System response measurements yielded "overall (wideband) RMS magnification factors" of 1.3, 1.9, and 1.6 in the X-, Y-, and Z-directions, respectively. The measured RMS displacements were within the criteria of 0.11 and 0.04 μm RMS, for the horizontal and vertical directions, respectively.

The tests indicated that it is not necessary to use the small wedge jacks or the locking screws on the larger wedge jacks.

A comparison of the design with wedge-type alignment jacks with that using jackscrews for alignment leads to the conclusion that the design incorporating wedge jacks is a significant improvement over the design with jackscrews. The sliding-wedge jacks, in combination with the redesigned pedestal, provide a much stiffer and more predictable support. The girder and pedestal are very stiff and do not contribute to flexibilities in the system. In general, the girder, pedestal, and magnets behave dynamically as rigid bodies in the frequency range of interest (<100 Hz), as indicated by the mode shapes.

Discounting the frequencies dominated by the blocks, only one dominant frequency (9.6 Hz) was measured in the Y-direction; there were no dominant Z-direction frequencies. Of perhaps most importance is that the new design removes the variability associated with the jackscrews that can result in low damping and an uncertainty in system damping. In particular, it was shown that a magnification factor (based on the measured damping factor) greater than 65 could be realized with the jackscrew support design.

Ideally, one would prefer to model the system and to use the model as a guide in redesigning, e.g., to shift the lowest natural frequency. While a model consisting of a rigid body on three sets of translational and rotational spring supports can be developed, it would be extremely difficult to predict the spring constants with sufficient accuracy to use the model as a design tool; a very detailed analysis, integrated with feature testing of the support assembly, would be required.

The system is characterized by a large mass (12,000 to 14,000 lb), with a high center of mass (≈ 51 in. above the floor), mounted on a three-point support that must accommodate an alignment device. Within these design constraints, it appears that the lowest mode frequency will most likely be in the range <20 Hz; the configuration tested had a lowest mode resonant frequency of 9.6 Hz, while the earlier design with jackscrews had low rigid-body mode frequencies of

approximately 7, 11, and 12 Hz. When the pedestal is grouted at the interface with the floor, it can be expected that the frequency will increase; it is impossible to predict precisely how much.

In light of the fact that the "gray area" for the feedback control system seems to be in the range of 10 to 20 Hz, one must decide whether to move the lowest mode frequency into that range. To move it higher than 20 Hz would put it outside the range of the control system. While it would then be in a range that would be unlikely to experience large-amplitude motion because of the energy required to do so, the potential for coupling with other system frequencies, such as the vacuum chamber support structure, would exist. Regardless, within the design constraints, it is intuitively felt to be difficult to move the lowest frequency above 20 Hz. One can move the frequency below 10 Hz, e.g., approximately 9 Hz as in the tested configuration. However, one must then be concerned with the potential for resonance with a basemat frequency; on the linac slab, a well-defined 7.5-Hz response indicative of a resonant response was measured. At this time, we do not have measurements of the ambient motion of the storage ring basemat.

Conclusion and recommendations derived from the study are as follows:

- The new design with wedge jacks is a significant improvement over the previous design with jackscrews.
- Because of nonprototypicalities in the testing, the dynamic characteristics of the new design could not be firmly established.
- The development of a mathematical model as a design tool is not practical because of the complexities at the component interfaces that control the inherent flexibilities and because of the detail required of the model.
- Additional testing is recommended with the system as close to prototypical as possible, that is, pedestals grouted to floor, masses simulating magnets securely fastened to girder, and a floor slab closer to prototype.
- With regard to follow-on testing, it is recommended that the test be carefully planned, with adherence to prototypicality given the highest priority. A focus of the testing should be the identification of vibration modes. As an objective, the testing should include, where possible, a parameter study to (a) evaluate the effects of various components (including size and geometry) comprising the interfaces of interest and (b) optimize the design with respect to the lowest mode frequency.

Toward this end, consideration should be given to establishing a dedicated vibration test bed for the magnet/girder/support system.

- To maintain schedule, it is recommended that the girders, pedestals, and jacks be procured while final evaluation of the dynamics associated with the jack/girder and pedestal/floor interfaces, and the related effects on overall system behavior, is carried out.

References

1. Wambsganss, M. W., Jendrzejczyk, J. A., and Chen, S. S., "Vibration Study of the APS Magnet Support Assemblies," Argonne National Laboratory Report ANL/APS/IN/VIB-90/3 (November 1990).
2. Jendrzejczyk, J. A., Wambsganss, M. W., and Smith, R. K., "Vibration Study of the APS Storage Ring 0.8 Meter Quadrupole/Girder Assembly," Argonne National Laboratory Report ANL/APS/IN/VIB-91/2 (May 1991).

Table 1. Results from Test 1

(a) Resonant frequencies; force-excitation

Test	Natural Frequencies (Hz)			
	X	Y	Z	
1X01			22.8 40.8 48.4	
1X04			22.6 40.6 48.3	
1X06			22.6 40.4 48.1	
1Y01		9.8		60.5
1Y04		9.8		60.5
1Y06		9.6		60.4
1Z01	8.5	9.8		
1Z04	8.5	9.8		
1Z06		9.6		

(b) Wideband (4-100 Hz) RMS displacements (μm); force-excitation

Test	Girder			Floor		
	X	Y	Z	X	Y	Z
1X01	0.104	0.101	0.069	0.068	0.047	0.066
1X04	0.284	0.085	0.090	0.069	0.046	0.076
1X06	0.369	0.091	0.109	0.070	0.047	0.083
1Y01	0.065	0.094	0.077	0.068	0.047	0.065
1Y04	0.082	0.279	0.159	0.068	0.049	0.075
1Y06	0.096	0.407	0.226	0.068	0.048	0.085
1Z01	0.062	0.067	0.064	0.068	0.047	0.065
1Z04	0.068	0.107	0.089	0.068	0.048	0.069
1Z06	0.072	0.144	0.109	0.068	0.049	0.075

(c) RMS displacement (μm); 9.6-Hz mode; force-excitation

Test	Girder			Floor		
	X	Y	Z	X	Y	Z
1X01	0.007	0.031	0.018	0.007	0.029	0.016
1X04	0.007	0.036	0.020	0.005	0.005	0.007
1X06	0.085	0.026	0.015	0.005	0.006	0.007
1Y01	0.006	0.058	0.034	0.003	0.005	0.009
1Y04	0.008	0.219	0.124	0.007	0.007	0.021
1Y06	0.009	0.329	0.189	0.005	0.007	0.035
1Z01	0.006	0.025	0.015	0.005	0.005	0.006
1Z04	0.006	0.077	0.046	0.006	0.005	0.010
1Z06	0.006	0.113	0.065	0.006	0.005	0.014

Table 1. Results from Test 1 (Cont'd)

(d) RMS displacements (μm) and magnification factors; ambient floor excitation

Frequency Range (Hz)	Direction	Girder	Floor	Magnification Factor
4-100	X	0.030	0.028	1.07
	Y	0.037	0.027	1.34
	Z	0.033	0.018	1.81
10-100	X	0.009	0.0075	1.24
	Y	0.014	0.0070	1.97
	Z	0.014	0.0093	1.48

(e) Damping factor (% critical)

Test	Mode	Damping Factor
1Y01	9.6	0.026
1Y04	9.6	0.025
1Y06	9.6	0.025
1Z01	22.6	0.017
1Z04	22.6	0.015
1Z06	22.6	0.015
1X01	40.0	0.018
1X04	40.0	0.020
1X06	40.0	0.020
1X01	48.0	0.021
1X04	48.0	0.022
1X06	48.0	0.026
1Y01	60.0	0.025
1Y04	60.0	0.021
1Y06	60.0	0.021

Table 2. Results from Test 2

(a) Resonant frequencies; force-excitation

Test		Natural Frequencies (Hz)		
2X01		23.5	40.9	48.5
2X04		23.3	40.6	48.6
2X06		23.8	40.6	48.8
2Y01	9.6			
2Y04	9.6	32.9		
2Y06	9.6	32.5		
2Z01	9.6			
2Z04	9.6			
2Z06	9.6			

(b) Wideband (4-100 Hz) RMS displacements (μm); force-excitation

Test	Girder			Floor		
	X	Y	Z	X	Y	Z
2X01	0.083	0.061	0.066	0.064	0.047	0.063
2X04	0.224	0.089	0.094	0.068	0.047	0.073
2X06	0.329	0.119	0.125	0.069	0.047	0.083
2Y01	0.064	0.097	0.078	0.067	0.046	0.062
2Y04	0.119	0.278	0.172	0.068	0.048	0.074
2Y06	0.167	0.416	0.254	0.067	0.049	0.089
2Z01	0.034	0.076	0.055	0.031	0.029	0.033
2Z04	0.046	0.086	0.139	0.032	0.027	0.040
2Z06	0.063	0.145	0.163	0.028	0.027	0.051

(c) RMS displacement (μm); 9.6-Hz mode; force-excitation

Test	Girder			Floor		
	X	Y	Z	X	Y	Z
2X01	0.006	0.015	0.009	0.005	0.005	0.005
2X04	0.006	0.021	0.012	0.005	0.005	0.005
2X06	0.009	0.043	0.026	0.006	0.006	0.008
2Y01	0.006	0.069	0.041	0.005	0.006	0.009
2Y04	0.009	0.230	0.132	0.005	0.006	0.023
2Y06	0.013	0.348	0.020	0.006	0.007	0.034
2Z01	0.006	0.064	0.037	0.006	0.005	0.011
2Z04	0.006	0.062	0.038	0.014	0.005	0.013
2Z06	0.007	0.109	0.063	0.006	0.005	0.013

Table 2. Results from Test 2 (Cont'd)

(d) RMS displacements (μm) and magnification factors; ambient floor excitation

Frequency Range (Hz)	Direction	Girder	Floor	Magnification Factor
4-100	X	0.028	0.027	1.03
	Y	0.040	0.027	1.46
	Z	0.036	0.020	1.77
10-100	X	0.011	0.0082	1.35
	Y	0.014	0.0079	1.83
	Z	0.018	0.0122	1.46

(e) Damping factor (% critical)

Test	Mode	Damping Factor
2Y01	9.6	0.023
2Y04	9.6	0.023
2Y06	9.6	0.023
2X01	23	0.014
2X04	23	0.016
2X06	23	0.017
2X01	40	0.017
2X04	40	0.022
2X06	40	0.022
2X01	48	0.026
2X04	48	0.017
2X06	48	0.020

Table 3. Results from Test 3

(a) Resonant frequencies; force-excitation

Test	Natural Frequencies (Hz)		
3X01		23.4	40.6
3X04		23.4	40.4
3X06		23.3	40.3
3Y01	9.8	20.5	
3Y04	9.8	19.9	
3Y06	9.8	19.9	
3Z01	10.0		
3Z04	9.8	21.1	
3Z06	9.6	20.9	

(b) Wideband (4-100 Hz) RMS displacements (μm); force-excitation

Test	Girder			Floor		
	X	Y	Z	X	Y	Z
3X01	0.061	0.062	0.050	0.028	0.025	0.032
3X04	0.194	0.098	0.101	0.030	0.030	0.059
3X06	0.274	0.109	0.141	0.034	0.033	0.079
3Y01	0.037	0.082	0.057	0.028	0.026	0.026
3Y04	0.075	0.330	0.182	0.026	0.026	0.051
3Y06	0.096	0.463	0.259	0.028	0.026	0.062
3Z01	0.031	0.053	0.045	0.026	0.026	0.027
3Z04	0.042	0.098	0.070	0.027	0.027	0.034
3Z06	0.055	0.139	0.095	0.026	0.026	0.045

(c) RMS displacement (μm); 9.6-Hz mode; force-excitation

Test	Girder			Floor		
	X	Y	Z	X	Y	Z
3X01	0.005	0.036	0.022	0.005	0.005	0.008
3X04	0.007	0.056	0.038	0.005	0.005	0.016
3X06	0.008	0.047	0.032	0.006	0.007	0.013
3Y01	0.006	0.052	0.031	0.005	0.005	0.007
3Y04	0.008	0.220	0.125	0.005	0.005	0.021
3Y06	0.011	0.332	0.191	0.005	0.007	0.032
3Z01	0.005	0.028	0.018	0.005	0.005	0.007
3Z04	0.006	0.057	0.033	0.005	0.004	0.007
3Z06	0.005	0.081	0.048	0.005	0.005	0.010

Table 3. Results from Test 3 (Cont'd)

(d) RMS displacements (μm) and magnification factors; ambient floor excitation

Frequency Range (Hz)	Direction	Girder	Floor	Magnification Factor
4-100	X	0.026	0.027	0.99
	Y	0.038	0.024	1.59
	Z	0.038	0.020	1.92
10-100	X	0.010	0.0081	1.28
	Y	0.022	0.0076	2.88
	Z	0.022	0.0128	1.75

(e) Damping factor (% critical)

Test	Mode	Damping Factor
3Y01	9.6	0.031
3Y04	9.8	0.027
3Y06	9.8	0.027
3X01	20.5	0.025
3X04	19.9	0.023
3X06	19.9	0.030
3X01	23.4	0.015
3X04	23.4	0.015
3X06	23.4	0.013
3X01	40.8	0.018
3X04	40.5	0.019
3X06	40.4	0.017
3X01	48.8	0.024
3X04	48.9	0.019
3X06	48.9	0.020

Table 4. Results from Test 4

(a) Resonant frequencies; force-excitation

Test		Natural Frequencies (Hz)			
4X01			23.4	41.0	48.9
4X04			23.1	40.8	48.8
4X06		15.5	23.1	40.6	48.6
4Y01	9.6	20.5			
4Y04	9.6	19.9			
4Y06	9.6	19.6			
4Z01	9.6	21.0	23.3	29.3	
4Z04	9.6	20.5		29.1	
4Z06	9.6	20.1			

(b) Wideband (4-100 Hz) RMS displacements (μm); force-excitation

Test	Girder			Floor		
	X	Y	Z	X	Y	Z
4X01	0.078	0.052	0.045	0.027	0.027	0.027
4X04	0.279	0.076	0.085	0.031	0.026	0.052
4X06	0.375	0.102	0.117	0.033	0.027	0.070
4Y01	0.037	0.105	0.067	0.027	0.027	0.031
4Y04	0.087	0.356	0.195	0.027	0.028	0.054
4Y06	0.113	0.519	0.284	0.029	0.027	0.077
4Z01	0.030	0.048	0.043	0.027	0.002	0.028
4Z04	0.043	0.095	0.068	0.027	0.027	0.033
4Z06	0.057	0.151	0.073	0.027	0.026	0.031

(c) RMS displacement (μm); 9.6-Hz mode; force-excitation

Test	Girder			Floor		
	X	Y	Z	X	Y	Z
4X01	0.006	0.035	0.021	0.004	0.005	0.007
4X04	0.006	0.035	0.020	0.004	0.005	0.006
4X06	0.006	0.038	0.022	0.005	0.005	0.006
4Y01	0.006	0.079	0.046	0.005	0.005	0.010
4Y04	0.011	0.230	0.133	0.005	0.005	0.021
4Y06	0.015	0.349	0.201	0.005	0.006	0.033
4Z01	0.006	0.028	0.018	0.004	0.004	0.006
4Z04	0.005	0.053	0.032	0.005	0.005	0.006
4Z06	0.006	0.007	0.004	0.006	0.004	0.009

Table 4. Results from Test 4 (Cont'd)

(d) RMS displacements (μm) and magnification factors; ambient floor excitation

Frequency Range (Hz)	Direction	Girder	Floor	Magnification Factor
4-100	X	0.026	0.026	1.00
	Y	0.062	0.025	2.44
	Z	0.050	0.024	2.03
10-100	X	0.012	0.0083	1.46
	Y	0.019	0.0077	2.43
	Z	0.023	0.0141	1.67

(e) Damping factor (% critical)

Test	Mode	Damping Factor
4Y01	9.6	0.024
4Y04	9.6	0.026
4Y06	9.6	0.026
4Y01	21	0.026
4Y04	20	0.025
4Y06	20	0.025
4Z01	21	0.029
4Z04	21	0.023
4Z06	20	0.024
4X01	23	0.014
4X04	23	0.017
4X06	23	0.018
4Z01	29	0.008
4Z04	29	0.009
4Z06	29	0.011

Table 5. Wideband (4-100 Hz) RMS displacements (μm) and magnification factors

Excitation	Direction	Girder	Floor	Magnification Factor
Ambient	X	0.027	0.028	0.98
	Y	0.037	0.026	1.44
	Z	0.038	0.021	1.81
Force excited ^a	X	0.029	0.0265	1.11
	Y	0.040	0.0258	1.55
	Z	0.036	0.0228	1.59

^aTest 6X04 data.

Table 6. Vibration mode comparison of girder/support assembly designs

(a) Girder/support assembly with alignment jackscrews

Direction	Modal Frequency (Hz)	Mode Description
X	7.62	Magnet/girder response in the Y direction
	10.9	Magnet/girder response in the X direction
	11.7	Coupled response, strong in the X and Z directions
Y	7.6	Magnet/girder response in the Y direction
	23.6	Higher mode of magnet/girder in the Y direction
Z	11.7	Coupled response, strong in the X and Z directions
	32.4	Z direction response

(b) Girder/support assembly with alignment wedge jacks

Direction	Modal Frequency (Hz)	Mode Description
X	23	Girder /shielding block response in the X direction
	40.7	Girder/shielding block response in the X direction
	48.7	Girder/shielding block response in the X direction
Y	9.6	Girder response in the Y direction
Z	9.6	Girder response in the Y direction

Table 7. Displacement response ($\mu\text{m RMS}$) to ambient floor motion; a comparison between two designs

Frequency Range (Hz)	Direction	Position	Jackscrew ^a	Wedge Jacks ^b
4-100	X	Floor	0.071	0.026
	Y	Floor	0.053	0.025
	Z	Floor	0.032	0.024
	X	Girder	0.114 ^c	0.026
	Y	Girder	0.526 ^c	0.038
	Z	Girder	0.087 ^c	0.050
10-100	X	Floor		0.008
	Y	Floor		0.008
	Z	Floor		0.014
	X	Girder		0.013
	Y	Girder		0.019
	Z	Girder		0.023

^aDesign with jackscrews for alignment; data from Test 4 of Ref. 2.

^bDesign with wedge-jacks for alignment.

^cMeasured on shielding block simulating magnet.

Table 8. Modal damping factor; a comparison between two designs

(a) Girder/support assembly with alignment jack screws (Test 4 of Ref. 2)

Modal Frequency (Hz)	Damping Factor (% critical)
7.6	0.0071-0.034 ^a
10.9	0.0089

^aVariability associated with mechanical fit-up of jackscrew within its housing.

(b) Girder/support assembly with alignment wedge jacks

Modal Frequency (Hz)	Damping Factor (% critical)
9.6	0.024
23	0.017

Fig. 1. Test Article

Fig. 2. Mode shape measurement locations; X-direction
(all dimensions are in inches)

Fig. 3. Mode shape measurement locations; Y-direction
(all dimensions are in inches)

Fig. 4. 9.6-Hz, Y-direction mode shape (Test 1)

Fig. 5. 22.6-Hz, X-direction mode shape (Test 1)

Fig. 6. 40-Hz, X-direction mode shape (Test 1)

Fig. 7. 48-Hz, X-direction mode shape (Test 1)

Fig. 8. 60-Hz, Y-direction mode shape (Test 1)

Appendix
Power Spectral Density Plots

X, Girder

X, Floor

Y, Girder

Y, Floor

Z, Girder

Z, Floor

X,Floor

Y,Floor

Z,Floor

X,Girder

Y,Girder

Z,Girder

X, Floor

Y, Floor

Z, Floor

X, Girder

Y, Girder

Z, Girder

1X06

X,Floor

Y,Floor

Z,Floor

X,Girder

Y,Girder

Z,Girder

X, Floor

Y, Floor

Z, Floor

X, Girder

Y, Girder

Z, Girder

X,Floor

Y,Floor

Z,Floor

X,Girder

Y,Girder

Z,Girder

1Z01

X, Floor

Y, Floor

Z, Floor

X, Girder

Y, Girder

Z, Girder

X, Floor

Y, Floor

Z, Floor

X, Girder

Y, Girder

Z, Girder

X₁Floor

Y₁Floor

Z₁Floor

X₁Girder

Y₁Girder

Z₁Girder

X, Girder

X, Floor

Y, Girder

Y, Floor

Z, Girder

Z, Floor

X, Girder

X, Floor

Y, Girder

Y, Floor

Z, Girder

Z, Floor

X, Floor

Y, Floor

Z, Floor

X, Girder

Y, Girder

Z, Girder

X, Girder

X, Floor

Y, Girder

Y, Floor

Z, Girder

Z, Floor

X, Girder

X, Floor

Y, Girder

Y, Floor

Z, Girder

Z, Floor

X,Floor

Y,Floor

Z,Floor

X,Girder

Y,Girder

Z,Girder

2Z06

X, Girder

Y, Girder

Z, Girder

X, Floor

Y, Floor

Z, Floor

X, Girder

X, Floor

Y, Girder

Y, Floor

Z, Girder

Z, Floor

X, Floor

Y, Floor

Z, Floor

X, Girder

Y, Girder

Z, Girder

3Y01

X, Girder

Y, Girder

Z, Girder

X, Floor

Y, Floor

Z, Floor

X, Floor

Y, Floor

Z, Floor

X₁Floor Y₁Floor Z₁Floor X₁Girder Y₁Girder Z₁Girder

3Z01

X, Floor

Y, Floor

Z, Floor

3Z06

X, Floor

Y, Floor

Z, Floor

X,Girder

X,Floor

Y,Girder

Y,Floor

Z,Girder

Z,Floor

4Y04

X₁Girdler

Y₁Girdler

Z₁Girdler

X₁Floor

Y₁Floor

Z₁Floor

X, Floor

Y, Floor

Z, Floor

X, Girder

Y, Girder

Z, Girder

4Z04

X, Floor

Y, Floor

Z, Floor

X, Girder

Y, Girder

Z, Girder

4Z06

X,Floor

Y,Floor

Z,Floor

X,Girder

Y,Girder

Z,Girder

X,Girder

Y,Girder

Z,Girder

X,Floor

Y,Floor

Z,Floor

X, Floor

Y, Floor

Z, Floor

X, Girder

Y, Girder

Z, Girder

5X06

X, Girder

Y, Girder

Z, Girder

X, Floor

Y, Floor

Z, Floor

X, Floor

Y, Floor

Z, Floor

X, Floor

Y, Floor

Z, Floor

X, Girder

Y, Girder

Z, Girder

5Z06

X, Floor

Y, Floor

Z, Floor

X, Girder

Y, Girder

Z, Girder

X, Floor

Y, Floor

Z, Floor

X, Floor **Y, Floor** **Z, Floor**

X, Girder

Y, Girder

Z, Girder

X, Floor

Y, Floor

Z, Floor

X, Girder

Y, Girder

Z, Girder

X, Floor

Y, Floor

Z, Floor

X₁Floor

Y₁Floor

Z₁Floor

X₁Girder

Y₁Girder

Z₁Girder

6Z01

X, Floor

Y, Floor

Z, Floor

X, Girder

Y, Girder

Z, Girder

6Z06

X, Girder

Y, Girder

Z, Girder

X, Floor

Y, Floor

Z, Floor

X, Girder

Y, Girder

Z, Girder

X, Floor

Y, Floor

Z, Floor

X, Girder

Y, Girder

Z, Girder

X, Floor

Y, Floor

Z, Floor

X,Girder

Y,Girder

Z,Girder

X,Floor

Y,Floor

Z,Floor

X,Girder

Y,Girder

Z,Girder

X,Floor

Y,Floor

Z,Floor

X,Girder

Y,Girder

Z,Girder

X,Floor

Y,Floor

Z,Floor

X, Girder

Y, Girder

Z, Girder

K, Floor

Y, Floor

Z, Floor

X, Floor

Y, Floor

Z, Floor

X, Girder

Y, Girder

Z, Girder

X,Floor

Y,Floor

Z,Floor

X,Girder

Y,Girder

Z,Girder

X, Floor

Y, Floor

Z, Floor

X,Girder

Y,Girder

Z,Girder

X,Floor

Y,Floor

Z,Floor

8X04

X, Floor

Y, Floor

Z, Floor

X, Girder

Y, Girder

Z, Girder

8Y04

X, Floor

Y, Floor

Z, Floor

X, Girder

Y, Girder

Z, Girder

X₁Floor

Y₁Floor

Z₁Floor

X₁Girder

Y₁Girder

Z₁Girder

**DATE
FILMED**

7 / 6 / 92