DOE/ER/53250--5

DE92 012377

Annual Technical Report

Non-Local Kinetic Transport Studies
of a
Field Reversed Configuration*

for

July 1, 1989-June 30, 1990

by

Chan K. Choi
Principal Investigator

School of Nuclear Engineering
Purdue University
West Lafayette, IN 47907
(317) 494-6789

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

*Work supported by the U.S. Department of Energy under contract DE-FG02-87ER53250.A001.

MASTER

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

I. Introduction

During this past period a computer code was developed to determine the global kinetic linear stability for a 1-D Field-Reversed Configuration (FRC). This report will describe the physical assumptions used to model the plasma, the equations solved by the code, the numerical analysis for certain aspects of the code, and some preliminary results from the code.

An FRC consists of an axisymmetric, toroidal plasma confined by a magnetic field that is nearly poloidal. FRC's belong to a class of experiments known as compact toroids (CT's). A CT is distinguished from other toroidal devices by having no mechanical structure in the center of the torus. An FRC is attractive as a potential energy source not only because of its simple mechanical structure, but also because it has a relatively high value of β , defined as the ratio of plasma pressure to magnetic field pressure at the wall ($\beta = 8\pi p/B_w^2$). A schematic representation of an FRC is presented in Figure 1.

Figure 1. Schematic of an FRC

Currently, the physics of transport processes in an FRC are not well understood. In particular, the particle and energy loss times are greater than one would expect if cross-field diffusion were solely governed by Coulomb collisions. This stability code is the next step towards understanding the processes that govern FRC transport.

II. The Physical Assumptions

In this section the basic physical assumptions that are used to derive the equations that the code solves are discussed. This section presents both the strengths and shortcomings of our code.

Models that have been used to explain anomalous transport in an FRC range from the local approximation [1] to kinetic simulation techniques[2,3]. The simulations suffer from drawbacks in the physical parameters used. By using a 2-species simulation code with a realistic electron-ion mass ratio, but unrealistic large drift parameters, Brackbill, et al [2] found that Lower Hybrid Drift (LHD) turbulence developed but did not propagate to the interior of the plasma. A hybrid simulation using realistic drift parameters but unrealistic mass ratio was used to model the sheath region of an FRC and the LHD-like modes that were found were substantially different from those using the local approximation[3].

The local approximation requires that particle gyro-radii be much smaller than the gradient length scale. There are 2 regions in an FRC where this requirement fails. One is near the separatrix where the gradient scale lengths are typically 1 or 2 gyro-radii. The other is in the vicinity of the field null where the ion gyro-radius is ill-defined and particle excursions tend to be large, thus a particle sees a large part of the equilibrium.

The physical assumptions used in the code are strong enough to allow enough mathematical simplification to avoid the numerical difficulties of the kinetic simulations without losing important physics.

We specialize to the post-implosion phase of a hot FRC. Table 1 gives some physical quantities for a typical FRC plasma. First we assume that the plasma can be well described by a collisionless equilibrium. This is justified by comparing the cyclotron and

Table 1. Physical quantities characteristic of FRX-C

Useful reference values	5 mTorr	20mTorr
electron gyrofrequency (rad/sec)	1.4×10^{11}	1.2×10^{11}
ion gyrofrequency (rad/sec)	3.8×10^7	3.4×10^7
electron plasma frequency (rad/sec)	2.4×10^{12}	4.0×10^{12}
electron gyroradius (cm)	3.9×10^{-3}	3.4×10^{-3}
ion gyroradius (cm)	4.5×10^{-1}	2.5×10^{-1}
electron collision rate (s^{-1})	2.4×10^7	1.5×10^8
ion collision rate (s^{-1})	5.8×10^4	1.3×10^6

collision frequencies. In the 20 mTorr case the ratio of ion cyclotron to ion collision frequencies is not as large as in the 5 mTorr case, but clearly, the ion will undergo many oscillations before a collision. The assumption of a collisionless plasma greatly simplifies the problem mathematically. The collisionless equilibrium is computed by a code written by Bob Webster [4].

The next assumption is that the FRC can be modelled well by a one dimensional, cylindrically symmetric plasma. There are two motivations for making this assumption. First, the FRC is a long, thin plasma where the radial gradients are much greater than the axial gradients so that the mid-plane profile does not change very much over a significant portion of the configuration. The second reason for using a 1-D model is that in linear stability computations, the particle trajectories need to be computed. In a one dimensional plasma the particle orbits are bounded and periodic while in a general multi-dimensional plasma, the particle orbits can fill an entire region of phase space. What this means is that for a 1-D plasma the orbits only need to be computed over one period. (In a 2-D plasma the orbits would have to be computed over all phase space which is equivalent to integrating from $t=0$ to $t=\infty$.) This results in a tremendous mathematical and numerical simplification.

The final assumption is that the FRC is described well by linear stability. This means that the perturbations are small compared to equilibrium quantities. This code determines what instabilities are possible, but not their amplitudes.

The model used is that of a one-dimensional, cylindrically symmetric plasma, described by a collisionless distribution function [5]. The strengths of this model are the following:

- 1) The model is global so that the shortcomings of the local approximation will not mask the physics. The particle orbits are computed exactly.
- 2) The model allows enough mathematical simplification to be tractable numerically.

The shortcomings of this model are the following:

- 1) The model is one dimensional so effects due to magnetic field curvature and mirrors will not be seen.
- 2) The model does not determine any saturation mechanism for the instabilities and suffers from the limitations imposed by linear stability.

III. The Equations Solved

In this section the equations for the global kinetic stability are discussed. The basic goal is to characterize the solutions to the linearized Maxwell-Vlasov equations. First, there will be a short discussion about the equilibrium, then the linearized Maxwell-Vlasov system will be discussed in terms of an eigenvalue problem, and finally the equations the code is to solve will be presented.

III.1 The Collisionless Equilibrium

For a one dimensional, cylindrically symmetric equilibrium, we see that there exist three constants of the motion: H , the particle Hamiltonian; p_θ , the canonical angular

momentum; and p_z , the canonical axial momentum. If we assume that $T_{\parallel} = T_{\perp}$, we may eliminate one constant of the motion from the distribution function, i.e. we say that

$$f_{so} = f_{so}(H, p_{\theta}) \quad (1)$$

where f_{so} is the Vlasov distribution function for species s . A computer code exists [4] that can compute the equilibrium distribution for realistic FRC profiles. The code assumes a parametric representation of f_{so} given by

$$f_{so}(H, p_{\theta}) = \exp \left\{ \frac{(-H + \beta(p_{\theta}))}{\alpha(p_{\theta})} \right\} \quad (2)$$

The functions α and β have parametric forms that were chosen so that the pressure and temperature are well modelled. The precise functional dependence of α and β are determined by requiring the moments of the distribution to satisfy the low frequency Maxwell equations and quasi charge neutrality [5]. The code we have written assumes a form for the distribution given by equation (2). The user is required to provide subroutines for α and β (in addition to subroutines for the equilibrium potentials). The formats and non-dimensionalizations are described in the comments of the main program.

III.2 The Maxwell-Vlasov System

In this section the dispersion relation for the linear stability of the computed equilibria will be discussed. The basic methodology was developed by Lewis, Symon, Seyler, and Schwarzmeier [6-8]. We begin with the nonlinear, time-dependent, Maxwell-Vlasov equations given by

$$\frac{\partial f_s}{\partial t}(q, p, t) + \{f_s(q, p, t), H\} = 0 \quad (3)$$

$$\text{and} \quad \sum_{n=1}^4 \Lambda_{mn} \phi_{nm} = \int dp J_m f_s(q, p, t) \quad (4)$$

where $\{f, g\}$ is the classical Poisson bracket given by

$$\{f, g\} = \sum_{i=1}^3 \left(\frac{\partial f}{\partial q_i} \frac{\partial g}{\partial p_i} - \frac{\partial f}{\partial p_i} \frac{\partial g}{\partial q_i} \right) \quad (5)$$

f_s is the single particle distribution function for species s ; q and p are the canonical variables, Λ_{mn} is a field operator representing Maxwell's equations, ϕ_n is a component of an array containing the electric and magnetic potentials and J_m is a component of the charge-current kernel given by

$$J = q \left(1, \frac{\mathbf{v}}{c} \right) \quad (6)$$

We follow general procedures by assuming that $f_s(q, p, t)$ can be split into two parts: a time-independent equilibrium distribution, $f_{s0}(q, p)$ and a smaller time-dependent perturbation, $f_{s1}(q, p, t)$.

$$f_s(q, p, t) = f_{s0}(q, p) + f_{s1}(q, p, t) \quad (7)$$

Further, we assume that the Hamiltonian and potentials also split into two parts:

$$H(q, p, t) = H_0(q, p) + H_1(q, p, t) \quad (8)$$

$$\phi_n(q, t) = \phi_{n0}(q) + \phi_{n1}(q, t) \quad (9)$$

Making the substitution into equations (3) and (4) and ignoring all terms higher than first order, we get the following equations:

$$\frac{\partial f_{s1}}{\partial t} + L_0 f_{s1} = \{H_1, f_{s0}\} \quad (10)$$

$$\sum_n \Lambda_{mn} \phi_{n1} = \int dF j_m f_{s1} \quad (11)$$

Here, Λ_{mn} is the linearized field operator, and L_0 is the equilibrium Liouville operator defined by

$$L_0 g = \{g, H_0\} \quad (12)$$

$$j = q_s \left(1, \frac{v_0}{c} \right), \text{ where} \quad (13a)$$

$$v_0 = \left(p_i - \frac{q}{c} A_0 \right) \quad (13b)$$

and A_0 is the magnetic vector potential.

The problem is solved by expanding f_{s1} in terms of the eigenfunctions of the Liouville operator written as

$$L_0 w_r = i\mu_r w_r \quad (14)$$

The index r refers to a set of subscripts required to uniquely specify an eigenfunction. w_r is the eigenfunction and μ_r is the corresponding real eigenvalue. The expansion of f_1 is given by

$$f_1(q, p, t) = \sum_r \gamma_r(t) w_r(q, p) \quad (15)$$

Making this substitution into (10) and (11) and solving the resulting differential equation via the Laplace transform, we get the following system of equations (after some manipulation)

$$D(\omega) \hat{\phi}_1 = I(\omega) \quad (16)$$

$$\text{where } D(\omega) \hat{\phi}_1 = \hat{\Lambda} \cdot \hat{\phi}_1 - \sum_r \frac{\kappa_r (\hat{w}_r, \hat{\phi}_1) \int dp jw_r}{\mu_r - \omega} \quad (17)$$

$$\text{and } \kappa_r = \left[\mu_r \frac{\partial f_0}{\partial H_0} + m \frac{\partial f_0}{\partial p_\theta} + k \frac{\partial f_0}{\partial p_z} \right] \quad (18)$$

Where the array $I(\omega)$ contains the initial value information. A " ^ " over a previously defined symbol means the Laplace transform of that quantity. Instabilities occur whenever $I(\omega)$ or $D^{-1}(\omega)$ have a pole in the upper-half of the complex ω plane.

To solve equations (16) and (17), which a system of coupled, linear integro-differential equations, a Galerkin method was employed. The potentials are approximated in frequency space by a finite set of basis functions as follows

$$\hat{\phi}_{1i} = \sum_{n=1}^N \alpha(\omega) \eta_{ni} \quad (19)$$

By substituting (19) into (16) and (17), multiplying by η_n and integrating over coordinate space we get a finite dimensional analog of equation (16).

$$D_{nn}(\omega) \propto 0$$

$$D_{nn}(\omega) = \Lambda_{nn}(\omega) - \sum_r \frac{\kappa_r \Phi_{nr}^* \Phi_{nr}}{\mu_r - \omega}$$

$$\Lambda_{nn}(\omega) = \int dq \eta_n^* \Lambda \cdot \eta_n$$

$$\Phi_{nr}^* = \int dq dp w_r j \cdot \eta_n$$

$$\Phi_{nr}^* = \int dp dq w_r^* j \cdot \eta_n \quad (20a-e)$$

and where the vector a is an array of coefficients for the basis functions. The dispersion equation is found by requiring that

$$\det |D_{nn}(\omega)| = 0 \quad (21)$$

The matrix $D_{nn}(\omega)$ contains all the information about the linear stability properties of the equilibrium. In particular, it contains all the information about the particle motion as it affects the field perturbations. The eigenfunctions w_r have been found in one dimension and depend on the solution to the particle equations of motion, which are easily solved for a time-independent Hamiltonian with 2 ignorable coordinates.

III.3 Final Form Of The Dispersion Relation

Attempts have been made to compute $D_{nn'}(\omega)$ directly and have failed because of the enormous computation involved. For every ω considered, the particle motion must be solved and used to compute the orbit integrals over all the accessible phase space. An attempt to pose equation (20) in a more tractable form was made. In essence, the ω dependence in the sum over r was removed by a simple identity.

$$D_{nn'}(\omega) = \Lambda_{nn'}(\omega) - \int_{-\infty}^{\infty} d\mu \frac{S_{nn'}(\mu)}{\mu - \omega} \quad (22)$$

$$\text{where } S_{nn'}(\mu) = \sum_r \delta(\mu - \mu_r) \kappa_r \Phi_{nr}^* \Phi_{n'r} \quad (23)$$

The matrix S is called the dynamic spectral matrix. What makes it so useful is that much of the computation can be done analytically. In this section we will present the form of the dynamic spectral matrix computed by the computer code.

The label r hides much of what makes computing the dynamic spectral matrix difficult. If we call the integrand of equation (23) $G_{nn'}$, then writing the sum over r out completely

$$\sum_a \sum_{l=-\infty}^{\infty} \int_{-\infty}^{\infty} dp_\theta \int_{U_m(p_\theta)}^{\infty} dH \int_{-p_{z0}(H, p_\theta)}^{p_{z0}(H, p_\theta)} dp_z G_{nn'}(p_\theta, H, p_z; l, a) \quad (24)$$

The l is an integer used to label Liouville eigenfunctions and a is an index used to distinguish degenerate eigenfunctions (i.e when there are two possible orbits for the same H, p_θ and p_z). Using the dynamic spectral matrix allows the integration over p_z and the infinite summation to be done analytically.

The matrix S is defined by equations (22) and (23). To reduce the amount of calculation required, a change of variables is made:

$$H_{\perp} = H - \frac{p_z^2}{2m} \quad (25)$$

The matrix then becomes

$$S_{nn'} = \sum_a \sum_{l=-\infty}^{\infty} \int_{-\infty}^{\infty} dp_{\theta} \int_{U_m(p_{\theta})}^{\infty} dH_{\perp} \int_{-\infty}^{\infty} dp_z \delta(\mu - \mu_r) \kappa_r \Phi_{nr}^* \Phi_{n'r} \quad (26)$$

Where,

$$\Phi_{nr} = \int dp dq w_r j \cdot \eta_n \quad (27)$$

$$\eta_n = (\eta_{n1}, \eta_{n2}, \eta_{n3}, \eta_{n4}) \quad (28)$$

$$w_r = d_{sr} \delta(H - H') \delta(p_{\theta} - p'_{\theta}) \delta(p_z - p'_z) \exp(i [m\theta + kz]) u(\tau) \quad (29)$$

$$u(\tau) = \exp(i [l\Omega_r + m\Theta(\tau) + kZ(\tau)]) \quad (30)$$

$$\Theta(\tau) = \int_0^{\tau} \frac{\partial H_0}{\partial p_{\theta}} d\tau' - \Omega_{\theta} \tau \quad (31)$$

$$Z(\tau) = \int_0^{\tau} \frac{\partial H_0}{\partial p_z} d\tau' - p_z \tau = 0 \quad (\text{for 1-D}) \quad (32)$$

$$\Omega_r = \frac{2\pi}{T_{sr}}$$

$$T_{sr} = \int_{r1}^{r2} \frac{dr}{|v_r|}$$

$$v_r = \frac{p_r}{M} \quad (33a-c)$$

$r1$ and $r2$ are the inner and outer turning points defined by $p_r = 0$ and μ_r is the eigenvalue associated with the Liouville eigenfunction w_r

$$\mu_r = l\Omega_r + m\Omega_\theta + k\frac{p_z}{M} \quad (34)$$

The form of the Liouville eigenfunctions w_r is derived in Seyler and Lewis [8]. The η_{ni} are the basis functions (19) used in the discretization of equation (16). The quantity j is the charge-current kernel defined in equation (12). To finish defining the terms in the preceding equations we have

$$\begin{aligned} H_\perp &= \frac{p_r^2}{2M} + U(r; p_\theta) \\ U(r; p_\theta) &= \frac{\left[p_\theta - \frac{q}{c}\psi(r) \right]^2}{2Mr^2} + q\phi(r) \\ \psi(r) &= rA_\theta(r) \end{aligned} \quad (35a-c)$$

The p_z integration is performed via the delta-function using equation (34). After the integration, the terms in the integrand of the dynamic spectral matrix can be rearranged to so that it is in the following form

$$\sum_{l=-\infty}^{\infty} q \left(1 - \frac{1}{2}\right)^2 e^{i\pi(2l-1)v} [e^{i\pi v} P_{nn}^5(l)] \quad (36)$$

where P_{nn}^5 represents an expression whose l dependence is a fifth order polynomial. This summation would be nearly impossible to perform because the quantity q is very nearly 1. However, the summation is related to a transcendental function called the θ_2 function. θ_2 is defined by

$$\theta_2(v; q) = \sum_{l=-\infty}^{\infty} q \left(1 - \frac{1}{2}\right)^2 e^{i\pi(2l-1)v} \quad (37)$$

Using the properties of theta functions found in Floryan and Zernach [9], these sums can be computed to machine accuracy using only 3 or 4 terms. Figures 2 and 3 are plots of θ_2 for typical values of p_0 and H .

The final form of the dynamic spectral matrix is too cumbersome to present here but is presented in the Appendix. Currently this matrix has been verified for a uniform field with a Boltzmann equilibrium distribution. The rest of this report will concentrate on aspects of this computation.

IV. Numerical Analysis

In this section, certain numerical aspects of the code are discussed. In particular, potential sources of error ranging from regularity near the origin to convergence of integration are discussed.

IV.1 Regularity Conditions

Since Maxwell's equations are being applied to a cylindrical geometry, one must be concerned about the behavior of the computation near the origin. Lewis and Schwarzmeier (unpublished) approached this difficulty several years ago and developed two methods to attack this problem. The first was to determine the asymptotic form of the distribution function near $r=0$. The second was to find basic functions that guarantee that the computed potentials would be infinitely continuous near the origin.

The latter method is used in our code. The basic requirements differ for basis functions representing scalar and vector potentials. For the electric potential the requirement is

Figure 2. The Complex Part of the θ_2 vs. ν

Figure 3. The Real Part of θ_2 vs. ν

$$\phi(r) = r^m \psi(r^2) \quad (38)$$

where m is the poloidal mode number. For the magnetic vector potential the requirement is

$$A_\theta(r) = r^{m-1} \psi(r^2) \quad (39a)$$

$$A_z = r^m \psi(r^2) \quad (39b)$$

To test whether these conditions work, we used them to solve the wave-guide problem in a cylindrically symmetric geometry. In terms of our code this amounted to solving

$$\det |\Lambda_{nm}(\omega)| = 0 \quad (40)$$

The results are shown in Figure 4. Clearly the regularity conditions did not introduce any error.

IV.2 Boundary Conditions

The gauge choice made in determining the form of $\Lambda_{nm}(\omega)$ is that the radial component of the perturbed magnetic potential, $A_{1r} = 0$. While this simplifies the problem by reducing the number of functions that must be found, it results in frequency dependent boundary conditions. This required the redefinition of the basis functions representing the potentials near the boundary.

While frequency dependent boundary conditions would appear to defeat the purpose of using the dynamic spectral matrix, Schwarzmeier found that by determining $D_{nm}(\omega)$ without imposing boundary conditions, it is possible to redefine $D_{nm}(\omega)$ in such a way that the boundary conditions are satisfied. If we define $\Delta_{nm}(\omega)$ as the matrix computed without imposing the B.C.'s and $D_{nm}(\omega)$ the matrix obeying the B.C.'s, Schwarzmeier showed that

$$D_{nm}(\omega) = A \Delta_{nm}(\omega) \quad (41)$$

Where the matrix A does not involve the particle orbit information.

Figure 4. A Check on the Regularity Condition Imposed on the Basis Functions for waveguide modes $m=2, k=1$

IV.3 Integration Convergence

There are 4 integrations in the determination of the dynamic spectral matrix: a double integral as part of the orbit integral, the particle orbit computation, the p_θ integration and the H-perp integration. Of these, only the H-perp integration can have a significant error because all the other integrations use routines that estimate the error and adjust the computation accordingly. The H-perp integration uses a Gauss-Laguerre (or Gauss-Legendre for the cases when the Liouville eigenfunctions are degenerate) quadrature formula because of the special form of the integrand. Figure 5 shows the percent change from increasing the number of quadrature points in the computation. The integration converges adequately provided 7 or more quadrature points are used.

Figure 5. Convergence of the H_1 Integration

REFERENCES

- [1] R.C. Davidson and N.A. Krall. Anomalous Transport in High Temperature Plasmas with Applications to Solenoidal Fusion Systems, *Nucl Fusion*, 17 (6) (1977) 1313.
- [2] J. U. Brackbill, D. W. Forslund, K.B. Quest, and D. Winske. Nonlinear Evolution of the Lower Hybrid Drift Instability, *Phys. Fluids*, 27 (11) (1984) 2682.
- [3] N. T. Gladd, A. G. Sgro and D. W. Hewett, Microstability Properties of the Sheath Region of the Field-Reversed Configuration, *Phys. Fluids*, 28 (7) (1985) 2222.
- [4] Robert B. Webster, A Study of the Equilibrium Phase of the Field Reversed Configuration, PhD Thesis, Purdue University, 1988.
- [5] C. K. Choi. Non-local Kinetic Transport Studies of a Field-Reversed Configuration. Annual Report 1989. DOE-53250-003
- [6] H. R. Lewis and K.R. Symon, Stability of Inhomogeneous Vlasov Equilibria, *J. Math. Phys.*, 20 (1979) 413.
- [7] K.R. Symon, C. E. Seyler and H.R. Lewis, Stability of Vlasov Equilibria. Part 1 General Theory, *J. Plasma Phys.*, 27 (1) (1982) 13.
- [8] H.R. Lewis and C. E. Seyler, Stability of Vlasov Equilibria. Part 2 One non-ignorable coordinate, *J. Plasma Phys.*, 27 (1) (1982) 25.
- [9] J. M. Floryan and L. Zemach, Schwarz-Christoffel Mapping: A General Approach, *J. Comp. Phys.*, 72 (2) (1985) 347

APPENDIX

REDUCTION OF DYNAMIC SPECTRAL MATRIX

The dynamic spectral matrix is defined by equations (22) and (23). In this appendix, the infinite summation over l and the integration over p_z will be performed analytically, dramatically simplifying the computation involved in finding the roots of the dispersion relation. The precise form of the dynamic spectral matrix is given by

$$S_{nm}(\mu) = \sum_a \sum_{l=-\infty}^{\infty} \int_{-\infty}^{\infty} dp_{\theta} \int_{u_m(p_{\theta})}^{\infty} dH_{\perp} \int_{-\infty}^{\infty} dp_z \delta(\mu - \mu_r) K_r \Phi_{nr}^* \Phi_{nr} \quad (a1a)$$

$$\text{where } \Phi_{nr} = \int dp dq w_r^* j \cdot \eta_n \quad (a1b)$$

$$K_r = \left[\mu_r \frac{\partial f_0}{\partial H_0} + m \frac{\partial f_0}{\partial p_{\theta}} + k \frac{\partial f_0}{\partial p_z} \right] \quad (a1c)$$

$$\eta_n = (\eta_{n1}, \eta_{n2}, \eta_{n3}, \eta_{n4}) \quad (a1d)$$

$$w_r = d_{sr} \delta(H - H') \delta(p_{\theta} - p_{\theta}') \delta(p_z - p_z') \exp[i(m\theta + kz)] u(\tau) \quad (a1e)$$

$$u(\tau) = \exp[i (l\Omega_r - m \Theta(\tau) - kZ(\tau))] \quad (a1f)$$

$$\text{where } \Theta(\tau) = \int_0^{\tau} \frac{\partial f_0}{\partial p_{\theta}} d\tau' - \Omega_{\theta} \tau \quad (a1g)$$

$$Z(\tau) = \int_0^{\tau} \frac{\partial f_0}{\partial p_z} d\tau' - p_z \tau = 0 \quad (\text{for 1-D}) \quad (a1h)$$

$$\Omega_r = \frac{2\pi}{T_{sr}} \quad (a1i)$$

$$T_{sr} = 2 \int_{r1}^{r2} \frac{dr}{|v_r|} \quad (a1j)$$

$$v_r = \frac{p_r}{M} \quad (a1k)$$

where $r1, r2$ are the inner and outer turning points defined by $p_r = 0$ (a1l)

and μ_r is the eigenvalue associated with the Liouville eigenfunction w_r .

$$\mu_r = l \Omega_r + m \Omega_{\theta} + k p_z / M \quad (a1m)$$

The form of the Liouville eigenfunctions w_r is derived in the Appendix of Seyler and Lewis. The functions η_{nl} are the basis functions used in the discretization of equation

20. The quantity j is the charge-current kernel defined in equation 13a. To finish defining the terms in the preceding equations we have

$$H_{\perp} = \frac{p_r^2}{2M} + U(r, p_{\theta}) \quad (a2)$$

$$U(r, p_{\theta}) = \frac{\left[p_{\theta} - \frac{q}{c} \psi(r) \right]^2}{2Mr^2} + q\phi(r) \quad (a3)$$

$$\psi(r) = rA_{\theta}(r) \quad (a4)$$

To perform the p_z integration we note that μ_r and p_z are related by a constant. We can make a change of variable $p_z = M\mu_r / k$

$$\int_{-\infty}^{\infty} dp_{\theta} K_l \Phi_{nr}^* \Phi_{n'r} \delta(\mu - \mu_r) \quad (a5)$$

$$d\mu_r = \frac{k}{M} dp_z \quad (a6)$$

$$\int_{-\infty}^{\infty} dp_z \delta(\mu_r - \mu) K_l \Phi_{nr}^* \Phi_{n'r} = \int_{-\infty}^{\infty} d\mu_r \delta(\mu_r - \mu) K_l \Phi_{nr}^* \Phi_{n'r} \quad (a7a)$$

$$= \left[\frac{M}{k} K_l \Phi_{nr}^* \Phi_{n'r} \right]_{p_z = \frac{M}{k}(\mu - m\Omega_{\theta} - l\Omega_r)} \quad (a7b)$$

Next we turn to the infinite summation over l . To do this sum we will first simplify the terms in the orbit integrals, equation (a1b).

$$j \cdot \eta_n = Q_s \left[\eta_{n1} - \frac{v_{\theta} \eta_{n3} + \frac{p_z}{M} \eta_{n4}}{c} \right] \quad (a8)$$

where we have made a gauge choice of $A_{r1} = 0$ and hence $\eta_{n2} = 0$. Using the form of the Liouville eigenfunctions and the replacement of p_z in equations (a5-8)

$$\Phi_{nr} = \int_0^{T_r} \exp\{-i(\tau - m\Theta(t))\} [\alpha_n(\tau) + i\beta_n(\tau)] d\tau \quad (a9) \quad \text{where}$$

$$\alpha_n(\tau) = \frac{Q_s}{\sqrt{2\pi L T_{sr}}} \exp\{-im\Theta(\tau)\} \left[\eta_{n1} - \frac{v_\theta \eta_{n3}}{c} - \frac{\mu - m\Omega_\theta}{kc} \eta_{n4} \right] \quad (a10)$$

$$\beta_n(\tau) = \frac{Q_s}{\sqrt{2\pi L T_{sr}}} \exp\{-im\Theta(\tau)\} \left[\frac{\Omega_r}{kc} \eta_{n4} \right] \quad (a11)$$

$$\Phi_{nr}^* \Phi_{n'r} = \int_0^1 \int_0^1 \exp\{il(s-s')\} [a_{nn'}(\tau) + ib_{nn'}(\tau) + l^2 c_{nn'}(\tau)] \frac{ds ds'}{\Omega_r^2} \quad (a12)$$

$$\text{where, } a_{nn'}(\tau, \tau') = \alpha_n^*(\tau) \alpha_{n'}(\tau') \quad (a13)$$

$$b_{nn'}(\tau, \tau') = \alpha_n^*(\tau) \beta_{n'}(\tau') + \alpha_{n'}(\tau') \beta_n^*(\tau) \quad (a14)$$

$$c_{nn'}(\tau, \tau') = \beta_n^*(\tau) \beta_{n'}(\tau') \quad (a15)$$

$$s = \frac{\tau}{T_{sr}} \quad (a16)$$

We now turn to the K_r . If we take the form of the equilibrium distribution function to be

$$f_0 = \beta(p_\theta) \exp\left[\frac{-H}{\alpha(p_\theta)}\right] \quad (a17)$$

we see that after a bit of differentiation,

$$K_r = [A_1 + p_z A_2 + p_z^2 A_3] \quad (a18)$$

$$A_1 = \left\{ \frac{-\mu \beta(p_\theta)}{\alpha(p_\theta)} + m \left[\frac{d\beta}{dp_\theta} + \frac{\beta}{\alpha^2} H_\perp \frac{d\alpha}{dp_\theta} \right] \right\} \exp\left[\frac{-H_\perp}{\alpha(p_\theta)}\right] \quad (a19)$$

$$A_2 = \left\{ \frac{-k\beta}{2M\alpha} \right\} \exp\left[\frac{-H_\perp}{\alpha(p_\theta)}\right] \quad (a20)$$

$$A_3 = \left\{ \frac{m\beta}{2M\alpha} \frac{d\alpha}{dp_\theta} \right\} \exp\left[\frac{-H_\perp}{\alpha(p_\theta)}\right] \quad (a21)$$

Substituting for p_z , we see that

$$p_z^2 = \frac{M^2 \Omega_r^2}{k^2} [1-x]^2 \quad (a22)$$

$$x = \frac{\mu - m\Omega_\theta}{\Omega_r} \quad (a23)$$

so that we can write,

$$K_r = (X + lY + l^2Z) \exp\left[-\frac{M\Omega_r}{2\alpha k^2} (1-x)^2\right] \quad (a24)$$

$$X = A_1 + \frac{M\Omega_r}{k} x A_2 \quad (a24)$$

$$Y = -\left[\frac{M\Omega_r}{k} A_2 + 2 \frac{M^2 \Omega_r^2}{k^2} x A_3 \right] \quad (a25)$$

$$Z = \frac{M^2 \Omega_r^2}{k^2} A_3 \quad (a26)$$

we then have the orbit integrals

$$K_r \Phi_{nr}^* \Phi_{nr} = \int_0^1 ds \int_0^1 ds' q^{(1-x)^2} (X + lY + l^2Z) (a_{nr} + lb_{nr} + l^2c_{nr}) \frac{e^{il(s-s')}}{\Omega_r^2} \quad (a27)$$

$$\text{where, } q = \exp\left[-\frac{M\Omega_r^2}{2\alpha k^2}\right] \quad (a28)$$

Multiplying the two polynomials in (a27) and grouping the result in powers of l , we get that the integrand of (a27) is

$$q^{(1-x)^2} (A_{nr} + lB_{nr} + l^2C_{nr} + l^3D_{nr} + l^4E_{nr}) \Omega_r^2 e^{il(s-s')} \quad (a29)$$

where for the sake of readability, A-E will not be explicitly defined until the end of this appendix. Combining the exponential terms in (a29) we have

$$\exp[i l(s-s')] \exp\left[-\frac{M^2 \Omega_r^2}{2\alpha k^2} (1-x)^2\right] = \exp[f_1 (1-x)^2 + i l(s-s')] \quad (a30)$$

$$\text{where } f_1 = -\frac{M^2 \Omega_r^2}{2\alpha k^2} \quad (a31)$$

Completing the square in the argument of the exponential, we get

$$f_1(1-x)^2 + i l(s-s') = f_1 \left(1 - \frac{1}{2}\right)^2 + 2\pi v l i + \left(x^2 - \frac{1}{4}\right) f_1 \quad (a32)$$

$$\text{where } v = \frac{\left(\frac{1}{2} - 2x\right) f_1 + i(s-s')}{2\pi i} \quad (a33)$$

we see then, that the summation over l gives

$$K_r \Phi_{nr}^* \Phi_{nr} = e^{\left(x^2 - \frac{1}{4}\right) f_1} \int_0^1 ds \int_0^1 ds' q^{\left(1 - \frac{1}{2}\right)^2} e^{2i\pi l v} [P_{nn}^{(5)}(l)] \quad (a34)$$

$$\sum_{l=-\infty}^{\infty} K_r \Phi_{nr}^* \Phi_{nr} = e^{\left(x^2 - \frac{1}{4}\right) f_1} \int_0^1 ds \int_0^1 ds' \sum_{l=-\infty}^{\infty} q^{\left(1 - \frac{1}{2}\right)^2} e^{i\pi(2l-1)v} [e^{i\pi v} P_{nn}^{(5)}(l)] \quad (a35)$$

where $P_{nn}^{(5)}$ represents the polynomial in l in equation (a29). If we look at the term in (a36) that is lowest order in l

$$A_{nn} \sum_{l=-\infty}^{\infty} q^{\left(1 - \frac{1}{2}\right)^2} e^{i\pi(2l-1)v} = A_{nn} \theta_2(v; q) \quad (a36)$$

where θ_2 belongs to a class of transcendental functions called theta functions. Since the argument q is nearly one, a direct summation will converge extremely slowly. But using the properties of theta functions discussed in Floryan [9], the theta function in (a36) can be computed to machine accuracy using ten or fewer terms. The terms in equation (a35) containing powers of l can be found by differentiating with respect to v .

$$\sum_{l=-\infty}^{\infty} l q^{\left(1 - \frac{1}{2}\right)^2} e^{i\pi(2l-1)v} = \frac{e^{i\pi v}}{2\pi i} \frac{d}{dv} (e^{i\pi v} \theta_2(v; q)) \quad (a37)$$

The final form for the dynamic spectral matrix is then

$$S_{nn'}(\mu) = \int_{-\infty}^{\infty} dp_{\theta} \int_{u_m(p_{\theta})}^{\infty} dH_{\perp} \sum_a L_{nn'}(H_{\perp}, p_{\theta}, \mu) \quad (a38)$$

$$L_{nn'} = q \left(x^2 - \frac{1}{4} \right) \epsilon_1 \int_0^1 \int_0^1 ds ds' e^{i\pi v} G_{nn'} \quad (a39)$$

$$\begin{aligned} G_{nn'} &= A_{nn'} \theta_2(v) + B_{nn'} \left[\frac{e^{i\pi v}}{2\pi i} \frac{d}{dv} (e^{i\pi v} \theta_2(v)) \right] + \\ &C_{nn'} \left\{ \frac{e^{i\pi v}}{2\pi i} \frac{d}{dv} \left[\frac{e^{i\pi v}}{2\pi i} \frac{d}{dv} (e^{i\pi v} \theta_2(v)) \right] \right\} + \\ &D_{nn'} \left\{ \frac{e^{i\pi v}}{2\pi i} \frac{d}{dv} \left\{ \frac{e^{i\pi v}}{2\pi i} \frac{d}{dv} \left[\frac{e^{i\pi v}}{2\pi i} \frac{d}{dv} (e^{i\pi v} \theta_2(v)) \right] \right\} \right\} \end{aligned} \quad (a40)$$

where

$$A_{nn'} = \frac{x a_{nn'}}{\Omega_r^2}$$

$$B_{nn'} = \frac{1}{\Omega_r^2} [Y a_{nn'} + X b_{nn'}]$$

$$C_{nn'} = \frac{1}{\Omega_r^2} [X c_{nn'} + Y b_{nn'} + Z a_{nn'}]$$

$$D_{nn'} = \frac{1}{\Omega_r^2} [Y c_{nn'} + Z b_{nn'}]$$

$$E_{nn'} = \frac{1}{\Omega_r^2} Z c_{nn'}$$

END

**DATE
FILMED
6 102192**