DESIGN OF THE AGS BOOSTER IONIZATION PROFILE MONITOR*

A.N. Stillman, R.E. Thern, R.L. Witkover, W.H. Van Zwiennen
AGS Department, Brookhaven National Laboratory
Upton, NY 11973

BNL--45384

DE91 013804

Abstract

The AGS Booster Ionization Profile Monitor (IPM) must operate in a vacuum of about 3×10^{-11} Torr. The ultra-high vacuum imposes certain requirements on detector gain and restrictions on construction techniques. Each detector is a two-stage microchannel plate with an integral substrate containing sixty-four printed anodes. Formed electrodes provide uniform collection fields without the use of resistors, which would be unacceptable in these vacuum conditions. An ultra-violet light calibrates the detector in its permanent mounting. An extra set of electrodes performs a first order correction to the perturbations imposed by the horizontal and vertical collection electrodes. This paper will present details of the design of the profile monitor.

INTRODUCTION

The AGS Booster is a synchrotron whose purpose is three fold. It will increase the AGS proton intensity by allowing the injection of four 1.5 GeV pulses rather than one 200 MeV pulse. It will accumulate twenty pulses of polarized protons to boost their intensity as well. Lastly, it will accelerate heavy ions to a momentum suitable for injection into the AGS and RHIC, the Relativistic Heavy Ion Collider. It is an intensifier for AGS beams and a necessary pre-accelerator for RHIC.

The profile monitor in the AGS Booster is a residual gas ionization monitor. The Booster beam ionizes gas molecules in the volume over two sets of collecting wires, one vertical, the other horizontal. The ions would naturally drift radially outward for the space charge of the beam, but electrical fields that are strong enough to redirect their natural radial motion send them to the wires. For strong enough collection fields, the ions travel in rather straight trajectories from their point of generation to the collection wires. The pattern on the wires is thus either a horizontal or vertical projection of the intensity of ion production, which is directly proportional to the beam intensity. Standard, high sensitivity integrating electronics and a real time computer interface acquire the signals, display them, and allow control of the collecting fields and other variables. Figure 1 is a block diagram of the profile monitor and its electronics.

* Work performed under the auspices of the U.S. Department of Energy.

Fig. 1. A block diagram of the Ionization Profile Monitor and its readout electronics. AGS Booster timing signals control the integration and sampling times.

The most severe constraint on the ionization profile monitor design is the ultra-high vacuum of the AGS Booster, nominally 3×10^{-11} Torr. This pressure corresponds to a residual gas density of approximately 10^6 gas molecules per cm^3 . At these rarefactions, the beam produces ionization signals on the order of picoamps. Furthermore, there is an extremely limited range of construction materials and techniques that one can use in vacuum of this quality. Resistors, for instance, cannot grade potentials in the vacuum since they outgas too much. Aluminum softens at the bake out temperatures in use, so metal parts must be of stainless steel. An appropriate choice of detector, therefore, is a microchannel plate. The microchannel plate has high gain, operates only in a vacuum, and can tolerate bake out temperatures of 300°C .

MCP DETECTOR

A typical microchannel plate has a gain of 10^4 electrons per input electron. Cascaded plates provide higher gain, though not strictly the product of the gains of the individual plates, since saturation effects in the last plate dominate very quickly. In the AGS Booster IPM, the detector is a dual microchannel plate¹ with a specified gain of 10^7 electron per electron. Ionic inputs to microchannel plates cause slightly different gains from the electron inputs. In fact, the gain of a typical plate can vary with ion species and energy.² In order to generate beam

intensity profiles that are not merely qualitative, the profile monitor design must make these gain variations insignificant. Careful shaping of the electrical collecting fields minimizes these gain effects.

The heart of the profile monitor is the dual microchannel plate detector, which comprises the microchannel plates and their associated anode array. A small distance from the exit end of the plates is a ceramic substrate with sixty-four linear anodes. Each anode is a collecting wire, and runs the length of the plate. The whole detector assembly attaches to four supporting posts on the vacuum side of a flange. Ceramic insulation covers the wires from the detector to two thirty-five pin instrumentation feedthroughs. Ceramic also insulates the wires that provide the bias voltage to the front and back sides of the plates. The unity of the detector/anode assembly allows the anode spacing to be at a rather fine pitch. In fact, the anodes are 1.1 mm wide and are 1.47 mm apart. The length of the anodes is 75 mm, the length of the detector active area.

The gain of the detector is set by the voltage across the input and output faces of the dual plate. There is no electrical separation between the two plates. Generally, the voltage is about 1 kV per plate for the specified gain of 10^7 . However, the second plate can easily saturate in the presence of large input signals. This saturation is very deleterious, since microchannel plates have a finite life determined only by the charge extracted from them. Accordingly, the power supply that provides bias voltage also contains a protection circuit. This circuit reduces the bias voltage to half the full scale voltage, i.e. 500 V per plate. The circuit trips when the current flowing through the detector is 7% of the current that flows with no signal. This is the recommended value for the fraction of strip current at which to trip. This power supply circuit uses an optically isolated operational amplifier to compare the signal current to a set current. It also provides a small differential voltage between the exit side of the last microchannel plate and the collecting anodes.

FIELD SHAPING

The collecting fields in this profile monitor merit special consideration. There are constraints on them as well. The primary constraint is that they direct ions to the face of the detector in trajectories that accurately project the beam intensity distribution onto the anode wires. This voltage gradient, sufficient to overcome beam space charge effects, seems to be subject to a law of diminishing returns. There always seems to be a further reduction of beam profile width as the collection voltage increases.³ However, the ability to generate large fields in confined vacuum chambers falls off rapidly at the higher voltages. The historical value of the voltage gradient at the AGS is somewhere in the range of 1 kV/cm.

A second constraint on the collecting field value, not often noted in devices like these, is that the microchannel plate is an energy analyzer for ions below about 20 keV. Thus, to form accurate profiles, the minimum ionic energy must be above this threshold. The ions of minimum energy form in the tail of the beam closest to the face of the detector, so the collecting field at this distance must accelerate these ions to 20 keV. With careful electrode design, it is possible to maintain a potential of -20 kV at this distance.

The ultra-high vacuum conditions also cause problems in generating graded potentials. Since resistors are forbidden and external resistors would require prohibitively many feedthroughs, shaping of the collection field electrodes is the best way to shape the field itself. Figure 2 shows the final shape of the electrodes and a plot of the equipotential lines. The size of the walls of the box-shaped electrodes should be one quarter the length of the electrode.⁴ A close inspection of the equipotentials shows that they are certainly flat enough not to cause any distortion of the beam profile image. A four inch clear aperture being necessary for the beam, the electrodes must form part of the perimeter of an eight inch cube. They are of stainless steel, polished and with no sharp corners.

Each plane has a set of electrodes and the working voltage on each set is nominally 70 kV. To correct the kick on the beam from these fields, a third set of electrodes is between the two collection electrodes. These correction electrodes are at 45° to the horizontal and vertical collection electrodes. The corrector voltage, 99 kV, generates an electric field that cancels, to first order, the effect of the vector sum of the collector fields.

READOUT ELECTRONICS

Each detector plane has sixty-four channels. Each of these channels is input to a low leakage integrator. A commercial VME sample/hold multiplexer and A/D converter with an imbedded microprocessor stores the integrator outputs in a local memory. An IBM PC/AT then reads the memory locations via a commercial bus interface that connects the PC bus to the VME bus. The A/D can scan through all channels and load them into memory in about 1 msec. Timing for the data acquisition is by real time interrupts to the PC, which controls the scanner as if it were the VME host. The timing signals themselves are either standard AGS Booster time line codes or the Booster TO signal. Both are available for selection by the PC.

A simple calibration system is also available under PC control. An ultra-violet spectroscopy lamp of 180 nm wavelength illuminates the detector briefly in response to a

calibration pulse from the computer. The light shines on the detector face through a sapphire window in the vacuum chamber and then through the hole in the top of the collection electrode, since the lamp is physically outside the vacuum. The quantum efficiency of the micro-channel plates at this wavelength is about .5%. This calibration system can provide a roughly uniform input to the detector and will allow the monitoring of the inevitable decline of the detectors' gains.

SUMMARY

The AGS Booster Ionization Profile Monitor has the ability to generate beam profiles even in the tenuous residual gas of a 3×10^{-11} Torr vacuum. It uses a microchannel plate detector with an integral anode assembly to generate profiles with a 1.47 mm wire pitch. A computer based scanning ADC system allows for profile acquisition on AGS cycle time scales. Formed electrodes generate fields without the use of resistors and the high voltage design minimizes the distorting effects of beam space charge and differential detector response. A calibration system is integral to the design and may find use in generating quantitative information from the beam profiles as well as qualitative.

REFERENCES

1. Galileo Model 3810 with 64-element anode. Manufactured by Galileo Electro-Optics Corp., Galileo Park, P.O. Box 550, Sturbridge MA, 01566.
2. Hellsing, M., et al., "Performance of a Micro-channel Plate Ion Detector in the Energy Range 3-25 keV," *J. Phys. E: Sci. Instrum.*, **18**, 920 (1985).
3. Thern, R.E., "Space-Charge Distortion in the Brookhaven Ionization Profile Monitor," *Proc. 1987 IEEE Particle Accelerator Conference*, Washington, D.C.
4. Leal-Quiros, E., and Prelas, M.A., "New Tilted Poles Wien Filter with Enhanced Performance," *Rev. Sci. Instr.*, **60**, No. 3, 350 (1989).

Fig. 2. Poisson calculations of equipotential lines in the ionization profile monitor collection volume. These views are cross-sections of the collection volume and show the characteristic U-shape of the electrodes. Each electrode lip is one quarter the length of the electrode. In both views the -70 kV electrode is at the top and the ground electrode at the bottom; the voltage between potential lines is 3.5 kV. Scale is in cm. In (a), the input face of the microchannel plate detector is the upper dotted line. This face is held at -2 kV by the bias power supply. The characteristic dual plate capacitor potential lines have given way to flat potential lines due to the lips on the electrodes. In (b), a magnified view of the collecting volume shows that its electric field is essentially constant. Here the micro-channel plate detector is the rectangle above the lower electrode.