DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

Title:

The Dependence of the Anisoplanatic Strehl of a Compensated Beam on the Beacon Distribution

LA-UR--92-479

DE92 011272

Author(s):

Phillip Stroud
Strategic Systems Engineering Group

Submitted to:

Final Report
February 7, 1992

APR 0 3 1992

Los Alamos
NATIONAL LABORATORY

Los Alamos National Laboratory, an affirmative action/equal opportunity employer, is operated by the University of California for the U.S. Department of Energy under contract W-7401-ENG-36. By acceptance of this article, the publisher recognizes that the U.S. Government retains a nonexclusive, royalty-free license to publish or reproduce in any published form of this contribution, or to allow others to do so, for U.S. Government purposes. The Los Alamos National Laboratory requests that the publisher identify this article as work performed under the auspices of the U.S. Department of Energy.

REACTED

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

Form No. RM-115
ST 2020 10 81

The Dependence of the Anisoplanatic Strehl of a Compensated Beam on the Beacon Distribution

by

Phillip Stroud

Abstract

There are several applications for lasers where the effect of atmospheric turbulence is strong enough to require wavefront compensation, and the compensation can be made by an adaptive optics (AO) system which processes light returned from the target itself. The distribution of the target return light produces limitations to the performance of the AO system. The primary intent of this documentation is to present the new results of an analysis of the anisoplanatic effects arising from target return beacon geometries. It will also lay out the assumptions and steps in the analysis, so that the results can be validated or extended. The intent is to provide a self-consistent notation, simple physical interpretations of the mathematical formulations, and enough detail to reduce the investment of time required to become acquainted or reacquainted with the physics of laser propagation through turbulence, at a level needed to analyze anisoplanatic effects.

A general formulation has been developed to calculate the anisoplanatic Strehl of a compensated beam for any beacon distribution and turbulence profile. Numerical calculations are also shown for several beacon geometries and turbulence profiles. The key result is that the spread of the beacon distribution has a much less deleterious effect than does the offset of the beacon centroid from the aimpoint.

1. Introduction

When coherent light propagates through a vacuum from an aperture of diameter D (and radius R) to a focus at a range L , the peak intensity at the aimpoint is given by $(\pi/4) P (D/\lambda L)^2$, where P is the laser power and λ is the wavelength. In this diffraction limited case, the light from all parts of the aperture arrive in phase at the aimpoint. When there is a perturbation in the index of refraction in between the aperture and the target, the light from different parts of the aperture arrives at the target with different phases. The peak intensity will then be reduced from its diffraction limited value by a factor known as the Strehl ratio. If the phase of the light at the aperture is adjusted to cancel the effect of the index of refraction variations, then the intensity at the target returns to the diffraction limited value. The required phase correction is measured by detecting a beacon signal, which travels from the target back to the aperture. Because the beacon light does not exactly traverse the reverse path of the outgoing beam, there will be some error in the phase correction, and the intensity at the aimpoint will be less than the diffraction limited value. Anisoplanatic effects are those due to the beacon return signal not sampling the same optical path as the outgoing light.

The anisoplanatic effect of interest here is due to beacon sources which are distributed in the target plane. The beacon light source will be emitted with some distribution about the aimpoint, determined by the diffraction of the illuminator laser, the scattering of the

illuminator light by the turbulence, the illuminator pointing error, the motion of the target, and the reflectivity of the target.

The analysis presented here uses a geometric optics model and presumes that the amplitude perturbations are negligible. The interest is in the effect of the beacon distribution on AO system performance. There will be a displacement of the beacon centroid from the lead ahead point and a spread in the beacon distribution about the centroid. For a variety of beacon geometries, the effect of the spread of the beacon distribution is less severe than the effect of the displacement of the beacon centroid from the aimpoint.

Fried[1982] published a numerical analysis of the anisoplanatic effect for a point beacon displaced from the aimpoint, using a focused geometry. He gave graphical and tabular presentations of the Strehl as a function of two parameters: the ratio of the angular displacement to the isoplanatic patch angle, $(\theta/\theta_0)^{5/3}$, and the ratio of the aperture diameter to the atmospheric coherence length, $(D/\rho_0)^{5/3}$.

Sasiela[1988] published a grand methodology (utilizing and extending the classic work of Tatarski[1961]) for constructing and evaluating the integrals which give the Strehl or phase variance for a variety of anisoplanatic situations. In the limit of near unity Strehl, the log of the Strehl is given by the negative aperture averaged net phase variance. He included a calculation of the phase variance (including tilt and piston) for a uniform circular beacon distribution, with a collimated beam. His result can be interpreted as follows: the anisoplanatic phase variance with a collimated beam and an on axis uniform beacon of radius b is the same as the variance obtained with a beam focused at the beacon plane and a point beacon displaced from the lead ahead point by distance $0.2027 \cdot b$. This result is subject to the conditions that 1) the beacon spot size is much larger than the aperture, 2) the aperture averaged net phase (i.e. piston) goes to zero, which is equivalent to the condition that the aperture diameter is large, and 3) diffraction effects of the scattering off turbulence can be neglected.

Ellerbroek[1991] ran some numerical calculations with a simulated uniform circular distributed beacon (composed of a pattern of several weighted point source beacons). He concluded that the anisoplanatic effect for a uniform circular on axis beacon provides significantly less degradation than would be expected from a point beacon with angular offset on the same order as the circular beacon radius.

2. Formulation of Anisoplanatic Strehl

A. The Scaler Field Amplitude and Propagation Kernel

The electro-magnetic energy flux, or intensity, I , in units of W/m^2 , is given by the Poynting vector cross product of the electric and magnetic field vectors. The field amplitude, u , is defined as the complex scalar quantity which (like the E and B field components) satisfies Maxwell's equations, and whose magnitude squared is equal to the magnitude of the intensity:

$$I(\vec{r}, z) = u(\vec{r}, z) u^*(\vec{r}, z) \quad [1]$$

For monochromatic light, the temporal dependence can be separated from the spatial dependence, and described with a factor of $\exp(-i\omega t)$. As long as ω is real, this factor doesn't affect the uu^* product, and so can be removed from consideration. The phase of the field amplitude is defined by the following: the phase of u at position $\vec{s} + \Delta\vec{s}$ is greater than the phase at position $\vec{s}$, by an amount $\Delta\vec{s} \cdot \vec{k}_0 n$, where $\vec{k}_0$ is the vacuum wavenumber of the laser light (in radians per meter, with $k_0 = 2\pi/\lambda$), and n is the index of refraction.

For applications where a laser beam is propagated from a beam director to a target, the geometry can be described with a coordinate system having its origin at the center of the aperture, and the positive z axis directed to the aimpoint. A position in space is represented by the coordinates $(\vec{r}, z)$, with $\vec{r}$ being the location in the plane perpendicular to the z axis, at a distance z from the aperture plane. The aimpoint is located at $\vec{r}=0, z=L$, and the aperture plane is the $z=0$ plane. (For propagation through the atmosphere, the average index of refraction depends on the altitude, varying from around 1.000274 at sea level to 1 at the top of the atmosphere. Neglecting the effects of turbulence and diffraction, the atmosphere refracts light to a slightly curved path. A large body of work on atmospheric refraction, published primarily in Russian during the 1960's, was summarized by Zuev[1982]. For this analysis, the turbulence effects are treated as a perturbation on vacuum propagation. Gross refraction effects can be included by adding this perturbation to the refracted path.)

The field amplitude at any point in space is determined by the field amplitude and the direction of the field amplitude gradient on any surface which encloses that point. The surface element $d\vec{A}$ at $(\vec{r}', z')$ will provide a contribution to the field amplitude at $(\vec{r}, z)$ of

$$du(\vec{r}, z) = d\vec{A}' \cdot \vec{u}(\vec{r}', z') U(\vec{r}', z', \vec{r}, z). \quad [2]$$

$U(\vec{r}', z', \vec{r}, z)$ is a propagation kernel which depends on the entire index of refraction field. The total field amplitude at point $(\vec{r}, z)$ is obtained by integrating Eq[2] over any surface enclosing that point.

$$u(\vec{r}, z) = \int_{\text{surf}} d\vec{A}' \cdot \vec{u}(\vec{r}', z') U(\vec{r}', z', \vec{r}, z). \quad [3]$$

For propagation through vacuum, the propagation kernel is given by

$$U_{\text{VAC}}(\vec{r}', z', \vec{r}, z) = \frac{k_0}{2\pi i s} \exp(ik_0 s) \frac{1 + \cos(\chi)}{2} \quad [4]$$

where $s = \sqrt{(z-z')^2 + (\vec{r} - \vec{r}')^2}$ is the distance between the surface element at $(\vec{r}', z')$ and the point $(\vec{r}, z)$. χ is the angle between the normal to the wavefront (as determined by the gradient of the field amplitude) at the surface element, and the line connecting the surface element with the point $(\vec{r}, z)$. This propagation kernel is derived from the integrand of the Fresnel-Kirchoff integral, which comes from the Helmholtz-Kirchoff Integral Theorem solution of Maxwell's equations in vacuum [Born and Wolf, 1959].

The beam can be made to focus at distance L by applying an aperture field with a phase retardation as a function of radius that allows all rays to arrive at the focus in phase:

$$u_{\text{FOC}}(\vec{\rho}, 0) = u_0 \exp(-ik_0 \sqrt{L^2 + \vec{\rho}^2}), \quad [5]$$

where u_0 is the square root of the laser intensity on the aperture. The phase of u_0 is arbitrary, since it doesn't affect the resulting intensity anywhere. The time dependence merely affects the phase of u_0 .

For the laser beam geometry, the surface used to integrate the total field amplitude at the aimpoint will consist of the aperture plane and a hemisphere of infinite radius on the positive z direction. The only part of this surface which has non-zero field amplitude will be the aperture itself. Using such a surface, Eq[3] for the field amplitude at any position is given by

$$u(\vec{r}, z) = \int_{\text{aperture}} d\vec{\rho} u(\vec{\rho}, 0) U(\vec{\rho}, 0; \vec{r}, z). \quad [6]$$

The field amplitude at the aimpoint will be

$$u(0, L) = \int_{\text{aperture}} d\vec{\rho} u(\vec{\rho}, 0) U(\vec{\rho}, 0; 0, L). \quad [7]$$

B. Diffraction Limit Result

The intensity distribution produced by a circular aperture with uniform intensity will be used to demonstrate this formulation. The focal geometry aperture field amplitude (Eq[5]) and the vacuum propagation kernel (Eq[4]) are used to evaluate the field amplitude distribution at the target plane (Eq[6] with $z=L$). The value of s to use in Eq[4] is given by $[L^2 + (\vec{r} - \vec{\rho})^2]^{1/2}$. In the Fraunhofer approximation, $\cos(\chi)$ is set to 1, and the terms in the exponentials are expanded to second order in r/L and ρ/L . The propagation kernel is then

$$U_{\text{VAC, FRAU}}(\vec{\rho}, 0; \vec{r}, L) = \frac{k_0}{2\pi i L} \exp(i k_0 (L + \frac{(\vec{r} - \vec{\rho})^2}{2L})) \quad [8]$$

and the field amplitude on the aperture is

$$u_{\text{FOC, FRAU}}(\vec{\rho}, 0) = u_0 \exp(-i k_0 (L + \frac{\rho^2}{2L})) \quad [9]$$

The integral of Eq[6] is performed with the substitutions of Eqs[8]&[9] to obtain the field amplitude distribution in the focal plane:

$$u(\vec{r}, L) = \int d\vec{\rho} \frac{u_0}{i\lambda L} \exp(\frac{-i k_0}{2L} (2\vec{r} \cdot \vec{\rho} - r^2)) \quad [10]$$

$$= \frac{u_0}{i\lambda L} \exp(\frac{i k_0 r^2}{2L}) \int_0^R d\rho \rho \int_0^{2\pi} d\alpha \exp(\frac{-i k_0 r \rho \cos\alpha}{L}) \quad [11]$$

$$= \frac{u_0}{i\lambda L} \exp(\frac{i k_0 r^2}{2L}) \frac{2J_1(k_0 r R/L)}{k_0 r R/L} \pi R^2 \quad [12]$$

Since $I = uu^*$, the total power on the aperture is $P = u_0 u_0^* \pi R^2$, and the intensity distribution in the focal plane is

$$I(r) = P \pi R^2 \frac{1}{(\lambda L)^2} \left[\frac{2J_1(k_0 r R/L)}{k_0 r R/L} \right]^2. \quad [13]$$

This is of course the Airy distribution.

For propagation to the aimpoint, through a vacuum, in the Fraunhofer approximation, the propagation kernel is

$$U_{VAC,FRAU,FOC}(\vec{\rho},0;0,L) = \frac{1}{i\lambda L} e^{ik_0(L + \frac{\vec{\rho}^2}{2L})} \quad [14]$$

The field amplitude at the aimpoint is, from Eqs[7],[9],&[14],

$$u_{VAC,FRAU,FOC}(0,L) = \int d\vec{\rho} \frac{u_0}{i\lambda L} = \frac{u_0}{i\lambda L} \pi R^2. \quad [15]$$

This gives the laser intensity at the aimpoint of

$$I_{DL} = P \frac{\pi D^2}{4} \frac{1}{(\lambda L)^2} = 3.6705 \frac{P}{(\pi/4)(2.44\lambda L/D)^2}. \quad [16]$$

C. Intensity reduction due to phase and Amplitude Variations

Two effects combine to produce a modification in the integrand of Eq[6]. Turbulence will affect the propagation kernel, from that given by Eq[8] for propagation through vacuum. An adaptive optics system will affect the aperture plane field amplitude, from that given in Eq[9]. These effects can be described with a combined complex phase factor, which is a function of position in the aperture. This phase factor, when applied to the integrand of Eq[7], results in the aimpoint field amplitude which includes turbulence, and turbulence compensation. Anisoplanatic effects are obtained when the AO correction applied to the aperture field amplitude is based on beacon return signals from the target.

The effect of turbulence is to generate a field of index of refraction fluctuations in between the aperture and the target. This modifies the propagation kernel from the vacuum propagation value of Eq[8] by a factor of $\exp[\psi_T(\vec{\rho},0;\vec{r},L)]$ where the subscript T indicates "turbulence":

$$U(\vec{\rho},0;0,L) = U_{VAC}(\vec{\rho},0;0,L) \exp(\psi_T(\vec{\rho},0;0,L)) \quad [17]$$

It is a common notation to designate the real and imaginary parts of the log amplitude factor separately, using $\psi = \chi + i\phi$. With this notation, $e^\psi = e^\chi e^{i\phi}$. The imaginary part, $\phi_T(\vec{\rho},0;0,L)$, is the phase increment due to turbulence, on light emitted at position $\vec{\rho}$ in the aperture plane and received at the aimpoint in the target plane. The real part, $\chi_T(\vec{\rho},0;0,L)$, is the natural log of the amplitude variation of the propagation kernel, due to turbulence. In the absence of turbulence, $\psi_T(\vec{\rho},0;0,L)$ is zero and the diffraction limit propagation kernel obtains.

The phase of the applied field on the aperture can be varied by an adaptive optics (AO) system. The phase of the field amplitude on the aperture is modified from the case with no AO distortion, by application of the AO phase compensation $\phi_{AO}(\vec{\rho})$:

$$u_{FOC,FRAU,AO}(\vec{\rho},0) = u_{FOC,FRAU}(\vec{\rho},0) \exp(i\phi_{AO}(\vec{\rho})). \quad [18]$$

For AO systems which create the phase correction by varying the optical path length as a function of aperture plane position, the magnitude of the field amplitude on the aperture can not be adjusted. For the mechanical AO systems, then, $\chi_{AO}(\vec{\rho})$ is zero.

The total complex phase variation, including the AO system and the turbulence effect, is

$$\psi(\vec{\rho}, 0; 0, L) = \psi_T(\vec{\rho}, 0; 0, L) + i \phi_{AO}(\vec{\rho}). \quad [19]$$

The field amplitude at the aimpoint is obtained by applying this phase factor to Eq[15]:

$$u_{TURB,AO,FRAU,FOC}(0, L) = \int d\vec{\rho} \frac{u_0}{i\lambda L} \exp(\psi(\vec{\rho}, 0; 0, L)) \quad [20]$$

The intensity at the aimpoint is the magnitude squared of u , which is

$$I(0, L) = \frac{I_{DL}}{A^2} \int d\vec{\rho}_A \int d\vec{\rho}_B \exp(i(\phi_A - \phi_B)) \exp(\chi_A + \chi_B), \quad [21]$$

using the shorthand notation $\phi_A \equiv \phi(\vec{\rho}_A, 0; 0, L) + \phi_{AO}(\vec{\rho}_A)$, $\chi_A \equiv \chi(\vec{\rho}_A, 0; 0, L)$, and $A = \pi D^2/4 = \text{aperture area}$.

A common definition of the Strehl ratio, $\mathcal{S}$, is the expectation value of I/I_{DL} , i.e.

$$\begin{aligned} \mathcal{S} &= \frac{\langle I \rangle}{I_{DL}} \\ &= \frac{1}{A^2} \int d\vec{\rho}_A \int d\vec{\rho}_B \langle \exp(i\phi_A - i\phi_B) \exp(\chi_A + \chi_B) \rangle \\ &= \int_A \int_B \langle \exp(i\phi_A - i\phi_B) \exp(\chi_A + \chi_B) \rangle \end{aligned} \quad [22]$$

where $\int_A$ is shorthand for the aperture average $\frac{1}{A} \int d\vec{\rho}_A$. This Strehl is the ratio of the average laser intensity at the aimpoint when turbulence and the AO compensation are included, to the laser intensity at the aimpoint in the diffraction limit.

The expectation value is obtained by averaging over the ensemble of all realizations of the turbulence. Since the propagation path from the aperture to the aimpoint traverses a large number of independent turbules, each giving a small random phase increment, the ensemble distribution of $\phi_A - \phi_B$ will be Gaussian. The mean is 0, and variance around the mean is $\langle (\phi_A - \phi_B)^2 \rangle$. The ensemble distribution of $\chi_A + \chi_B$ will also be Gaussian, with mean of $\langle \chi_A + \chi_B \rangle$, and variance of $\langle (\chi_A + \chi_B - \langle \chi_A + \chi_B \rangle)^2 \rangle$. The following pair of integrals can be used to obtain the Gaussian averaged expectation values of the exponentials of Eq[22]:

$$\int_{-\infty}^{\infty} d\phi \frac{1}{\sqrt{2\pi}\sigma} \exp\left(-\frac{\phi^2}{2\sigma^2}\right) \exp(i\phi) = \exp\left(-\frac{\sigma^2}{2}\right) \quad [23]$$

$$\int_{-\infty}^{\infty} d\chi \frac{1}{\sqrt{2\pi}\sigma} \exp\left(-\frac{(\chi - m)^2}{2\sigma^2}\right) \exp(\chi) = \exp\left(\frac{\sigma^2}{2} + m\right) \quad [24]$$

Averaging over the Gaussian distributions in the ensemble gives the Strehl at the aimpoint:

$$\mathcal{S} = \int_A \int_B \exp\left(\frac{-\langle(\phi_A - \phi_B)^2\rangle}{2} + \frac{\langle(\chi_A + \chi_B - \langle\chi_A + \chi_B\rangle)^2\rangle}{2} + \langle\chi_A + \chi_B\rangle\right) \quad [25]$$

The condition of negligible amplitude perturbations leaves

$$\mathcal{S} = \int_A \int_B \exp\left(\frac{-\langle(\phi_A - \phi_B)^2\rangle}{2}\right) \quad [26]$$

When the variances are much smaller than 1 (the Marechal limit), the exponential can be expanded into a Taylor series, and the integrals can be performed term by term. To first order, the result can be recombined into an exponential:

$$S = \exp\left(-\int_A \int_B \frac{\langle(\phi_A - \phi_B)^2\rangle}{2}\right) \quad [27]$$

The two aperture integrals can now be separated, giving the result

$$S = \exp\left(-\int_A \langle\phi_A^2\rangle + \langle[\int_A \phi_A]^2\rangle\right) \quad [28].$$

The effective phase variance is defined by

$$\sigma_\phi^2 = \frac{1}{A} \int d\bar{\rho}_A \langle\phi_A^2\rangle - \langle[\frac{1}{A} \int d\bar{\rho}_A \phi_A]^2\rangle \quad [29]$$

so that the Strehl is

$$S = \exp(-\sigma_\phi^2) \quad [30]$$

The first term in Eq[29] is the aperture averaged value of the expected phase variance. This term is also called the piston included phase variance. The second term removes the piston component of the phase variance. The piston component of the phase variance rotates the total field amplitude in the complex plane without changing the magnitude, so it doesn't affect the intensity.

In the case that the expectation value of the phase variance between positions $\bar{\rho}_A$ and $\bar{\rho}_B$ in the aperture plane depends only on $\rho = |\bar{\rho}_A - \bar{\rho}_B|$, the double aperture integral of Eq[26] can be replaced by a single integral over ρ , with a weighting function which accounts for the fraction of pairs of aperture elements separated by distance in $d\rho$ about ρ :

$$S = \frac{16}{\pi D^2} \int_0^D d\rho \rho \left[\arccos\left(\frac{\rho}{D}\right) - \frac{\rho}{D} \sqrt{1 - \left(\frac{\rho}{D}\right)^2} \right] \exp\left(\frac{-\langle\phi_\rho^2\rangle}{2}\right) \quad [31]$$

This formulation has the advantage of not imposing the Marechal approximation (i.e. it is valid for small Strehl values), but the aperture integrals must be performed numerically.

The next step is to develop a formulation for the expectation values of phase variance terms of Eq[29] required in the evaluation of the Strehl.

3. Evaluation of the Phase Variance

A. Characterization of the Turbulence Field

The turbulence field is described as a perturbation in the index of refraction which is a function of position. In any limited region of space, this index variation can be decomposed into Fourier cosine wave components:

$$\delta n(\vec{r}, z) = \int d\vec{k} \tilde{n}(\vec{k}, z_0) \cos(\vec{k}_\perp \cdot \vec{r} + k_\parallel(z - z_0) + \phi(\vec{k}, z_0)) \quad [32]$$

$\delta n(\vec{r}, z)$ is the perturbation in the index of refraction due to atmospheric turbulence at the location $(\vec{r}, z)$. $\tilde{n}(\vec{k}, z_0) d\vec{k}$ is the amplitude of the "turbulence wave" component with wavenumber in $d\vec{k}$ about $\vec{k}$, in the region near the location $(\vec{r}=0, z=z_0)$. $\phi(\vec{k}, z_0)$ is a random variable, uniformly distributed over the interval 0 to 2π , which gives the phase of the turbulence wave at the location $(0, z_0)$. The phase of the wave components at different vector wavenumbers are uncorrelated. The utility of the trick of expanding the turbulence about an arbitrary point will become apparent when a double integration over z must be performed, and the dominant contribution to the integral occurs when the two integration variables are nearly identical.

For atmospheric turbulence, the amplitude of the Fourier component with wavenumber in $d\vec{k}$ about $\vec{k}$ is given by the Kolmogorov spectrum:

$$\tilde{n}^2(\vec{k}, z) d\vec{k} = \frac{0.0660108 C_n^2(z) d\vec{k}}{(k^2)^{11/6}} \quad [33]$$

This spectrum applies to the so called inertial regime, bounded in k space by the outer scale wavenumber and the inner scale wavenumber. For perturbations with wavenumber smaller than the outer scale wavenumber, there is nothing in the system large enough to generate such large scale perturbations. For perturbations with wavenumber larger than the inner scale wavenumber, the scale is so small that the perturbations dissipate into heat. The inner scale wavenumber is given by 5.48 divided by the inner scale [Tatarski, 1961, Eq. 3-27]. The inner scale for atmospheric turbulence is typically one or two millimeters at one atmosphere, with the value increasing at lower pressure. In cases where the inner and outer scales affect the results of the calculations, they can be included by using the Von Karman turbulence spectrum:

$$\tilde{n}^2(\vec{k}, z) d\vec{k} = \frac{0.0660108 C_n^2(z) d\vec{k}}{(k^2 + k_{outer}^2)^{11/6}} \exp(-k^2/k_{inner}^2) \quad [34]$$

B. The Compensated phase variation in the aperture plane

In the geometric approximation, the phase variation due to turbulence along the straight path (or the path with gross refraction separated out) connecting $(\bar{\rho}_A, 0)$ in the aperture plane, and $(\bar{r}, L)$ in the target plane, is

$$\phi_A = \phi(\bar{\rho}_A, 0; \bar{r}, L) = \int_0^L k_0 \delta n(\bar{q}(z), z) dz \quad [35]$$

where the integral over z is taken from the center of the aperture to the aimpoint, and $\bar{q}(z)$ is the position in the plane at z of the geometric ray. For the path from $\bar{\rho}_A$ in the aperture plane to the aimpoint, $\bar{q}(z) = \bar{\rho}_A (t/L)$, where $t=L-z$. The phase perturbation due to turbulence will be given by

$$\phi_{A,T} = \phi_T(\bar{\rho}_A, 0; \bar{r}, L) = \int_0^L k_0 \delta n(\bar{\rho}_A t/L, z) dz \quad [36]$$

This phase variation will be real, in the geometric approximation, so the amplitude variance will be zero.

For target return geometry, there will be a distribution of beacon source intensity in the target plane, with a distribution of $B(\bar{b})$, where $\bar{b}$ is the position in the target relative to the aimpoint. $B(\bar{b})$ is normalized so that $\int d\bar{b} B(\bar{b}) = 1$. The radial position of the geometric ray from $\bar{b}$ in the target plane to $\bar{\rho}_A$ in the aperture, is $\bar{q}(z) = \bar{\rho}_A t/L + \bar{b} z/L$. In the limiting case where the incoming beacon wavefront is perfectly sensed and reconstructed, the AO phase correction applied at $\bar{\rho}_A$ will be the negative average phase variation for the paths from $\bar{\rho}_A$ in the aperture plane to the target plane, weighted by the beacon intensity:

$$\phi_{A,AO} = - \int d\bar{b} B(\bar{b}) \int_0^L k_0 \delta n(\bar{\rho}_A t/L + \bar{b} z/L, z) dz. \quad [37]$$

Eqs[36] & [37] are used to find the compensated phase variation at position $\bar{\rho}_A$ in the aperture plane:

$$\phi_A = \int_0^L k_0 dz \left[\delta n(\bar{\rho}_A t/L, z) - \int d\bar{b} B(\bar{b}) \delta n(\bar{\rho}_A t/L + \bar{b} z/L, z) \right] \quad [38]$$

If the beacon distribution is a delta function at the aimpoint, this gives $\phi_A = 0$, from which the anisoplanatic Strehl is seen from Eq[28] to be 1.

C. Evaluation of the Phase Variance

The phase variance of Eq[29] can now be found. Substitution of Eq[32] into Eq[38] and moving the target plane integral outside gives

$$\phi_A = k_0 \int d\vec{b} B(\vec{b}) \int_0^L dz \sqrt{0.066 C_n^2(z_0)} \int \frac{d\vec{k}}{k^{11/6}} \quad [39]$$

$$[\cos(\vec{k}_\perp \cdot \vec{\rho}_A t/L + k_{||}(z-z_0) + \varphi(\vec{k}, z_0)) - \cos(\vec{k}_\perp \cdot \vec{\rho}_A t/L + \vec{k}_\perp \cdot \vec{b} z/L + k_{||}(z-z_0) + \varphi(\vec{k}, z_0))]$$

The value of z_0 is indeterminate, but constrained to be in the vicinity of z . The definition of "vicinity" will become apparent later in the analysis. The product $\phi_A \phi_B$ can then be formed:

$$\begin{aligned} \phi_A \phi_B = & 0.066 k_0^2 \int d\vec{b} B(\vec{b}) \int d\vec{b}' B(\vec{b}') \int_0^L dz \int_0^L dz' \sqrt{C_n^2(z) C_n^2(z')} \int \frac{d\vec{k}}{k^{11/6}} \int \frac{d\vec{k}'}{k'^{11/6}} \\ & [\cos(\vec{k}_\perp \cdot \vec{\rho}_A t/L + k_{||}(z-z_0) + \varphi) - \cos(\vec{k}_\perp \cdot \vec{\rho}_A t/L + \vec{k}_\perp \cdot \vec{b} z/L + k_{||}(z-z_0) + \varphi)] \\ & [\cos(\vec{k}'_\perp \cdot \vec{\rho}_B t'/L + k'_{||}(z'-z_0') + \varphi') - \cos(\vec{k}'_\perp \cdot \vec{\rho}_B t'/L + \vec{k}'_\perp \cdot \vec{b}' z'/L + k'_{||}(z'-z_0') + \varphi')] \quad [40] \end{aligned}$$

where the shorthand notation $\varphi' = \varphi(\vec{k}', z_0')$ is used. The integrand is expanded with trigonometric identities and collected into terms of $\cos\varphi \cos\varphi'$ and $\sin\varphi \sin\varphi'$.

$$\begin{aligned} \phi_A \phi_B = & 0.066 k_0^2 \int d\vec{b} B(\vec{b}) \int d\vec{b}' B(\vec{b}') \int_0^L dz \int_0^L dz' \sqrt{C_n^2(z) C_n^2(z')} \int \frac{d\vec{k}}{k^{11/6}} \int \frac{d\vec{k}'}{k'^{11/6}} \\ & (\cos\varphi \cos\varphi' [\cos(\vec{k}_\perp \cdot \vec{\rho}_A t/L + k_{||}(z-z_0)) - \cos(\vec{k}_\perp \cdot \vec{\rho}_A t/L + \vec{k}_\perp \cdot \vec{b} z/L + k_{||}(z-z_0))] \\ & [\cos(\vec{k}'_\perp \cdot \vec{\rho}_B t'/L + k'_{||}(z'-z_0')) - \cos(\vec{k}'_\perp \cdot \vec{\rho}_B t'/L + \vec{k}'_\perp \cdot \vec{b}' z'/L + k'_{||}(z'-z_0'))]) \\ & + \sin\varphi \sin\varphi' [\sin(\vec{k}_\perp \cdot \vec{\rho}_A t/L + k_{||}(z-z_0)) - \sin(\vec{k}_\perp \cdot \vec{\rho}_A t/L + \vec{k}_\perp \cdot \vec{b} z/L + k_{||}(z-z_0))] \\ & [\sin(\vec{k}'_\perp \cdot \vec{\rho}_B t'/L + k'_{||}(z'-z_0')) - \sin(\vec{k}'_\perp \cdot \vec{\rho}_B t'/L + \vec{k}'_\perp \cdot \vec{b}' z'/L + k'_{||}(z'-z_0'))]) \\ & \text{plus terms of } \sin\varphi \cos\varphi' \text{ and } \cos\varphi \sin\varphi' \quad [41] \end{aligned}$$

The expectation value of $\phi_A \phi_B$ can be found by averaging over the random phase variables, using the relations

$$\langle \cos\varphi \cos\varphi' \rangle = \int_0^{2\pi} \frac{d\varphi(\vec{k}, z_0)}{2\pi} \int_0^{2\pi} \frac{d\varphi(\vec{k}', z_0')}{2\pi} \cos(\varphi(\vec{k}, z_0)) \cos(\varphi(\vec{k}', z_0')) = \delta(\vec{k} - \vec{k}') \delta(z_0 - z_0')/2$$

$$\langle \sin\varphi \sin\varphi' \rangle = \delta(\vec{k} - \vec{k}') \delta(z_0 - z_0')/2$$

$$\langle \sin\varphi \cos\varphi' \rangle = \langle \cos\varphi \sin\varphi' \rangle = 0 \quad [42]$$

This gives

$$\begin{aligned} \langle \phi_A \phi_B \rangle = & 0.066 k_0^2 \int d\vec{b} B(\vec{b}) \int d\vec{b}' B(\vec{b}') \int_0^L dz \int_0^L dz' \sqrt{C_n^2(z) C_n^2(z')} \int \frac{d\vec{k}}{k^{11/6}} \\ & ((1/2) [\cos(\vec{k}_\perp \cdot \vec{\rho}_A t/L + k_{||}(z-z_0)) - \cos(\vec{k}_\perp \cdot \vec{\rho}_A t/L + \vec{k}_\perp \cdot \vec{b} z/L + k_{||}(z-z_0))] \\ & [\cos(\vec{k}'_\perp \cdot \vec{\rho}_B t'/L + k'_{||}(z'-z_0)) - \cos(\vec{k}'_\perp \cdot \vec{\rho}_B t'/L + \vec{k}'_\perp \cdot \vec{b}' z'/L + k'_{||}(z'-z_0))]) \end{aligned}$$

$$+ (1/2) \left[\sin(\vec{k}_\perp \cdot \vec{\rho}_A t/L + k_\parallel(z-z_0)) - \sin(\vec{k}_\perp \cdot \vec{\rho}_A t/L + \vec{k}_\perp \cdot \vec{b}z/L + k_\parallel(z-z_0)) \right] \\ \left[\sin(\vec{k}_\perp \cdot \vec{\rho}_B t/L + k_\parallel(z'-z_0)) - \sin(\vec{k}_\perp \cdot \vec{\rho}_B t/L + \vec{k}_\perp \cdot \vec{b}z'/L + k_\parallel(z'-z_0)) \right] \quad [43]$$

The indeterminate parameter z_0 can be set equal to z , while still meeting the constraints of being close to the value of z and z' , as long as the z' integration receives most of its contribution from the region where z' is close to z . Setting z_0 equal to z , and transforming the integral over z' to an integral over $\zeta = z' - z$, gives

$$\langle \phi_A \phi_B \rangle = 0.033 k_0^2 \int d\vec{b} B(\vec{b}) \int d\vec{b}' B(\vec{b}') \int_0^L dz \int_{-z}^{L-z} d\zeta \sqrt{C_n^2(z) C_n^2(z+\zeta)} \int \frac{d\vec{k}}{k^{11/3}} \\ \left(\begin{aligned} & [\cos(\vec{k}_\perp \cdot \vec{\rho}_A t/L) - \cos(\vec{k}_\perp \cdot \vec{\rho}_A t/L + \vec{k}_\perp \cdot \vec{b}z/L)] \\ & [\cos(\vec{k}_\perp \cdot \vec{\rho}_B t/L + k_\parallel \zeta) - \cos(\vec{k}_\perp \cdot \vec{\rho}_B t/L + \vec{k}_\perp \cdot \vec{b}z'/L + k_\parallel \zeta)] \\ + & [\sin(\vec{k}_\perp \cdot \vec{\rho}_A t/L) - \sin(\vec{k}_\perp \cdot \vec{\rho}_A t/L + \vec{k}_\perp \cdot \vec{b}z/L)] \\ & [\sin(\vec{k}_\perp \cdot \vec{\rho}_B t/L + k_\parallel \zeta) - \sin(\vec{k}_\perp \cdot \vec{\rho}_B t/L + \vec{k}_\perp \cdot \vec{b}z'/L + k_\parallel \zeta)] \end{aligned} \right) \quad [44]$$

The result is again expanded with trigonometric identities and collected into terms of $\cos(k_\parallel \zeta)$ and $\sin(k_\parallel \zeta)$.

$$\langle \phi_A \phi_B \rangle = 0.033 k_0^2 \int d\vec{b} B(\vec{b}) \int d\vec{b}' B(\vec{b}') \int_0^L dz \int_{-z}^{L-z} d\zeta \sqrt{C_n^2(z) C_n^2(z+\zeta)} \int \frac{d\vec{k}}{k^{11/3}} \\ \{ \cos(k_\parallel \zeta) \\ \{ [\cos(\vec{k}_\perp \cdot \vec{\rho}_A t/L) - \cos(\vec{k}_\perp \cdot \vec{\rho}_A t/L + \vec{k}_\perp \cdot \vec{b}z/L)] [\cos(\vec{k}_\perp \cdot \vec{\rho}_B t/L) - \cos(\vec{k}_\perp \cdot \vec{\rho}_B t/L + \vec{k}_\perp \cdot \vec{b}z'/L)] \\ + [\sin(\vec{k}_\perp \cdot \vec{\rho}_A t/L) - \sin(\vec{k}_\perp \cdot \vec{\rho}_A t/L + \vec{k}_\perp \cdot \vec{b}z/L)] [\sin(\vec{k}_\perp \cdot \vec{\rho}_B t/L) - \sin(\vec{k}_\perp \cdot \vec{\rho}_B t/L + \vec{k}_\perp \cdot \vec{b}z'/L)] \} \\ \text{plus a } \sin(k_\parallel \zeta) \text{ term} \} \quad [45]$$

The integrations over $k_\parallel$ and ζ can then be performed, using the relations

$$\int_{-\infty}^{\infty} d\zeta \int_{-\infty}^{\infty} dk_\parallel \cos(k_\parallel \zeta) G(k_\parallel, \zeta) = 2\pi G(0,0) \\ \int_{-\infty}^{\infty} d\zeta \int_{-\infty}^{\infty} dk_\parallel \sin(k_\parallel \zeta) G(k_\parallel, \zeta) = 0 \quad [46]$$

where $G(k_\parallel, \zeta)$ is any well behaved even function with no singularity or zero at $k_\parallel=0$ and $\zeta=0$. Applying this relation gives

$$\langle \phi_A \phi_B \rangle = 0.033 (2\pi) k_0^2 \int d\vec{b} B(\vec{b}) \int d\vec{b}' B(\vec{b}') \int_0^L dz C_n^2(z) \int \frac{d\vec{k}_\perp}{k_\perp^{11/3}} \\ \{ [\cos(\vec{k}_\perp \cdot \vec{\rho}_A t/L) - \cos(\vec{k}_\perp \cdot \vec{\rho}_A t/L + \vec{k}_\perp \cdot \vec{b}z/L)] [\cos(\vec{k}_\perp \cdot \vec{\rho}_B t/L) - \cos(\vec{k}_\perp \cdot \vec{\rho}_B t/L + \vec{k}_\perp \cdot \vec{b}z'/L)] \\ + [\sin(\vec{k}_\perp \cdot \vec{\rho}_A t/L) - \sin(\vec{k}_\perp \cdot \vec{\rho}_A t/L + \vec{k}_\perp \cdot \vec{b}z/L)] [\sin(\vec{k}_\perp \cdot \vec{\rho}_B t/L) - \sin(\vec{k}_\perp \cdot \vec{\rho}_B t/L + \vec{k}_\perp \cdot \vec{b}z'/L)] \} \quad [47]$$

Again expanding the trig functions gives

$$\begin{aligned} \langle \phi_A \phi_B \rangle = & 0.033(2\pi)k_0^2 \int d\vec{b} B(\vec{b}) \int d\vec{b}' B(\vec{b}') \int_0^L dz C_n^2(z) \int \frac{d\vec{k}_\perp}{k_\perp^{11/3}} \\ & \{ \cos(\vec{k}_\perp \cdot (\vec{\rho}_A - \vec{\rho}_B) \iota / L) [(1 - \cos(\vec{k}_\perp \cdot \vec{b} z / L)) (1 - \cos(\vec{k}_\perp \cdot \vec{b}' z / L)) + \sin(\vec{k}_\perp \cdot \vec{b} z / L) \sin(\vec{k}_\perp \cdot \vec{b}' z / L)] \\ & + \sin(\vec{k}_\perp \cdot (\vec{\rho}_A - \vec{\rho}_B) \iota / L) [\sin(\vec{k}_\perp \cdot \vec{b} z / L) (1 - \cos(\vec{k}_\perp \cdot \vec{b}' z / L)) - \sin(\vec{k}_\perp \cdot \vec{b}' z / L) (1 - \cos(\vec{k}_\perp \cdot \vec{b} z / L))] \} \end{aligned} \quad [48]$$

The double integration over b can now be separated out. The coefficient of the $\sin(\vec{k}_\perp \cdot (\vec{\rho}_A - \vec{\rho}_B) \iota / L)$ term integrates to zero. The $\cos(\vec{k}_\perp \cdot (\vec{\rho}_A - \vec{\rho}_B) \iota / L)$ term integration is incorporated into an "anisoplanatic filter function", leaving the result

$$\langle \phi_A \phi_B \rangle = 0.033(2\pi)k_0^2 \int_0^L dz C_n^2(z) \int \frac{d\vec{k}_\perp}{k_\perp^{11/3}} \cos(\vec{k}_\perp \cdot (\vec{\rho}_A - \vec{\rho}_B) \iota / L) F(\vec{k}_\perp) \quad [49]$$

$$\text{with } F(\vec{k}_\perp) = \left[\int d\vec{b} B(\vec{b}) (1 - \cos(\vec{k}_\perp \cdot \vec{b} z / L)) \right]^2 + \left[\int d\vec{b} B(\vec{b}) \sin(\vec{k}_\perp \cdot \vec{b} z / L) \right]^2 \quad [50]$$

This is equivalent to the filter function obtained by Sasiela [Sasiela, 1988].

The effects of diffraction by the turbulence can be included for the focal geometry by multiplying the integrand of Eq[49] by a factor of $\cos^2[\vec{k}_\perp^2 z t / 2k_0 L]$. The derivation is not presented here, but can be obtained with either a first order Rytov expansion, or with a first Born approximation using the second order power expansion in turbulence strength.

The expression in the exponential of the Strehl can now be evaluated:

$$\begin{aligned} \mathcal{S} &= \int_A \int_B \exp \left[- \frac{\langle (\phi_A - \phi_B)^2 \rangle}{2} \right] \\ &= \int_A \int_B \exp \left[- \frac{\langle \phi_A^2 - 2\phi_A \phi_B + \phi_B^2 \rangle}{2} \right] \\ &= \int_A \int_B \exp \left[- 0.033(2\pi)k_0^2 \int_0^L dz C_n^2(z) \int \frac{d\vec{k}_\perp}{k_\perp^{11/3}} [1 - \cos(\vec{k}_\perp \cdot (\vec{\rho}_A - \vec{\rho}_B) \iota / L)] F(\vec{k}_\perp) \right] \end{aligned} \quad [51]$$

In the Marechal Strehl approximation, this becomes $\mathcal{S} = \exp[-\sigma_\phi^2]$, where the phase variance is

$$\begin{aligned} \sigma_\phi^2 &= \int_A \int_B \frac{\langle (\phi_A - \phi_B)^2 \rangle}{2} \\ &= 0.033(2\pi)k_0^2 \int_0^L dz C_n^2(z) \int \frac{d\vec{k}_\perp}{k_\perp^{11/3}} F(\vec{k}_\perp) [1 - \int_A \int_B \cos(\vec{k}_\perp \cdot (\vec{\rho}_A - \vec{\rho}_B) \iota / L)] \end{aligned} \quad [52]$$

The double aperture integral can be performed in terms of Bessel functions to obtain

$$\sigma_\phi^2 = 0.033(2\pi)k_o^2 \int_0^L dz C_n^2(z) \int \frac{d\bar{k}_\perp}{k_\perp^{11/3}} F(\bar{k}_\perp) \left\{ 1 - \left[\frac{2 J_1(k_\perp R t/L)}{(k_\perp R t/L)} \right]^2 \right\} \quad [53]$$

Propagation through turbulence without wavefront compensation corresponds to $F(\bar{k}_\perp)=1$. This results when the turbulence phase perturbation of Eq[36] is used in place of the compensated phase perturbation of Eq[38] in the preceding derivation. The integral over $\bar{k}_\perp$ can be performed in that case, using $d\bar{k}_\perp=2\pi k_\perp dk_\perp$ and

$$\int_0^\infty d\mu \mu^{-8/3} \left[1 - \left(\frac{2J_1[\mu]}{\mu} \right)^2 \right] = 1.06498 \quad [54]$$

to give

$$\sigma_\phi^2 = 1.033 (D/r_o)^{5/3} \quad [55]$$

where r_o is Fried's atmospheric coherence length for the path from 0 to L, defined by

$$r_o = \left[\frac{2.91}{6.88} k_o^2 \int_0^L dz C_n^2(z) (L)^{5/3} \right]^{-3/5} \quad [56]$$

4. Evaluation of Anisoplanatic Strehl for Various Beacon Source Distributions

A. Phase Variance in the Large Aperture Limit

In the limit of large aperture, the Bessel function term of Eq[53] goes to zero. The phase variance is then

$$\sigma_\phi^2 = \frac{0.066(2\pi)k_o^2}{2} \int_0^L dz C_n^2(z) \int \frac{d\bar{k}_\perp}{k_\perp^{11/3}} F(\bar{k}_\perp) \quad [57]$$

This also describes the phase variance with piston included, so for finite apertures, it gives too much Strehl reduction. It can be used for a first comparison of anisoplanatic effects for various beacon geometries.

1. Point Beacon Off the Aimpoint

For a point beacon source, displaced from the aimpoint by $\bar{b}_o$, the beacon distribution, in terms of the Dirac delta function, is $B(\bar{b})=\delta(\bar{b} - \bar{b}_o)$, and the filter function obtained from Eq[50] is given by

$$F(\bar{k}_\perp) = 2 [1 - \cos(\bar{k}_\perp \cdot \bar{b}_o z/L)] \quad [58]$$

This is substituted into Eq[57] to get the phase variance including piston, and the integral over $\bar{k}_\perp$ is performed as follows, giving

$$\begin{aligned}
\sigma_\phi^2 &= 0.2073 k_o^2 \int_0^L dz C_n^2(z) \int \frac{d\mathbf{k}_\perp}{k_\perp^{11/3}} 2 [1 - \cos(\mathbf{k}_\perp \cdot \mathbf{b}_o z/L)] \\
&= 1.203 k_o^2 (b_o/L)^{5/3} \int_0^L dz z^{5/3} C_n^2(z) \int_0^\infty \frac{d\mu}{\mu^{8/3}} 2 (1 - J_0(\mu)) \\
&= 2.91 k_o^2 (b_o/L)^{5/3} \int_0^L dz z^{5/3} C_n^2(z) \\
&= \left(\frac{b_o/L}{\theta_o} \right)^{5/3}
\end{aligned} \tag{59}$$

where θ_o is the anisoplanatic patch angle, defined by

$$\theta_o^{-5/3} = 2.91 k_o^2 \int_0^L dz z^{5/3} C_n^2(z). \tag{60}$$

In the limit of aperture size large enough that expected square aperture averaged piston is negligible, the Strehl is then $S = \exp(-(\frac{b_o/L}{\theta_o})^{5/3})$. In the case that the displacement from the aimpoint is due to motion of the target during the round trip time of light (i.e. $b_o = 2 * \text{perpendicular target speed} * [\text{range to target} / \text{speed of light} + \text{sensor/processor lag time}]$), the quantity b_o/L is known as the lead ahead angle.

2. Uniform Circular Beacon Source

For a uniform circular beacon source distribution, of diameter b , centered at the aimpoint, the filter function of Eq[50] is found to be

$$F(\mathbf{k}_\perp) = \left[1 - \frac{2 J_1(k_\perp b z/L)}{k_\perp b z/L} \right]^2 \tag{61}$$

This is substituted into Eq[57] to get the aperture averaged phase variance including piston, and the integral over $\mathbf{k}_\perp$ can be performed, giving

$$\sigma_\phi^2 = \left(\frac{0.2017 b/L}{\theta_o} \right)^{5/3} \tag{62}$$

with θ_o given by Eq[60]. In this limit of large aperture, the anisoplanatic phase variance from a circular beacon of radius b will thus be equivalent to the phase variance that would be obtained by a point beacon offset from the aimpoint by $0.2017 b$.

In the case that the uniform circular beacon is offset from the aimpoint by a distance $\mathbf{d}$, the filter function is found to be

$$F(\mathbf{k}_\perp) = \left[1 - \frac{4 J_1(k_\perp b z/L)}{k_\perp b z/L} \cos(\mathbf{k}_\perp \cdot \mathbf{d} z/L) + \frac{2 J_1(k_\perp b z/L)}{k_\perp b z/L} \right]^2 \tag{63}$$

This result is similar to a result obtained by Sasiela for an offset uniform circular beacon with a collimated beam geometry, where an additional first Bessel function appears in the second term to account for the distance from the beacon to the aperture. When $b=0$, this result goes into the offset point beacon result. When $d=0$, this result goes into the on-axis uniform circular beacon result.

This is substituted into Eq[57] to get the phase variance including piston, and the integral over $\vec{k}_\perp$ is performed as follows, giving

$$\begin{aligned}\sigma_\phi^2 &= 0.2073 k_o^2 \int_0^L dz C_n^2(z) \int \frac{d\vec{k}_\perp}{k_\perp^{11/3}} \left[1 - \frac{4 J_1(k_\perp b z/L)}{k_\perp b z/L} \cos(\vec{k}_\perp \cdot \vec{d} z/L) + \left\{ \frac{2 J_1(k_\perp b z/L)}{k_\perp b z/L} \right\}^2 \right] \\ &= 1.303 k_o^2 \int_0^L dz C_n^2(z) \int \frac{dk_\perp}{k_\perp^{8/3}} \left[1 - \frac{4 J_1(k_\perp b z/L)}{k_\perp b z/L} J_0(k_\perp d z/L) + \left\{ \frac{2 J_1(k_\perp b z/L)}{k_\perp b z/L} \right\}^2 \right] \quad [64]\end{aligned}$$

The phase variance (including piston), normalized to the phase variance of a point beacon, offset at distance d , is then given by

$$\frac{\sigma_\phi^2}{(d/L\theta_o)^{5/3}} = 0.4477 (r/d)^{5/3} \int_0^\infty \frac{d\mu}{\mu^{8/3}} \left[1 - 2J_0(\mu d/r) \frac{2J_1[\mu]}{\mu} + \left(\frac{2J_1[\mu]}{\mu} \right)^2 \right] \quad [65]$$

This normalized phase variance (including piston) is shown, as a function of d/r , in Fig. 1. For a given offset to the center of a uniform circular beacon, the phase variance is minimized when the beacon radius is 1.59 times the offset, in which case, the phase variance is reduced by a factor of 0.8527 from the value obtained with an offset point beacon with offset of d .

3. Gaussian circular beacon source

For a Gaussian circular beacon source distribution, of rms radius Σ , centered at the aimpoint, the beacon distribution is

$$B(b) = \frac{1}{2\pi\Sigma^2} \exp\left(-\frac{b^2}{2\Sigma^2}\right). \quad [66]$$

The filter function of Eq[50] is found to be

$$F(\vec{k}_\perp) = \left[1 - \exp\left(-\frac{\Sigma^2 k_\perp^2}{2}\right) \right]^2 \quad [67]$$

This is substituted into Eq[57] to get the phase variance including piston, and the integral over $\vec{k}_\perp$ can be performed, giving

$$\sigma_\phi^2 = \left(\frac{0.3611 \Sigma/L}{\theta_o} \right)^{5/3} \quad [68]$$

with θ_0 given by Eq[60]. In this limit of large aperture, the anisoplanatic phase variance from a Gaussian circular beacon of rms radius Σ will thus be equivalent to the phase variance that would be obtained by a point beacon with a lead ahead of 0.3611Σ .

4. Two point straddle beacon

In this geometry, the beacon is composed of two point sources which straddle the aimpoint. The two points are located at positions $\bar{b}_0$ and $-\bar{b}_0$, in the target plane. The filter function is found to be

$$F(\bar{k}_\perp) = [1 - \cos(\bar{k}_\perp \cdot \bar{b}_0 z/L)]^2 \quad [69]$$

and the resulting phase variance, including piston, is

$$\sigma_\phi^2 = \left(\frac{0.388 b_0/L}{\theta_0} \right)^{5/3} \quad [70]$$

5. Circular Ring beacon source

In this geometry, the beacon is composed of a circular ring, centered on the aimpoint. The radius of the ring is b_0 in the target plane. The filter function is given by

$$F(\bar{k}_\perp) = [1 - J_0(k_\perp b_0 z/L)]^2 \quad [71]$$

and the resulting phase variance, including piston, is

$$\sigma_\phi^2 = \left(\frac{0.3201 b_0/L}{\theta_0} \right)^{5/3} \quad [72]$$

6. Uniform centered line beacon source

In this geometry, the beacon is represented by a uniform line segment source with half length b_0 in the target plane, centered at the aimpoint. This gives a filter function of

$$F(\bar{k}_\perp) = \left[1 - \frac{\sin(\bar{k}_\perp \cdot \bar{b}_0 z/L)}{\bar{k}_\perp \cdot \bar{b}_0 z/L} \right]^2 \quad [73]$$

and the resulting phase variance, including piston, is

$$\sigma_\phi^2 = \left(\frac{0.1663 b_0/L}{\theta_0} \right)^{5/3} \quad [74]$$

7. Offset Gaussian line beacon source

For a beacon source generated by reflection of an illuminator beam from a cylindrical target, the beacon distribution may be represented by a Gaussian line. The displacement of the Gaussian peak from the aimpoint is given by d , and is along the direction of the line, if the direction of motion of the target is along the cylinder axis. The 1-D rms beacon spread is given by r , so that the beacon distribution in the target plane is

$$B(\delta) = \frac{1}{\sqrt{2\pi r}} \exp\left(-\frac{(\delta-d)^2}{2r^2}\right) \quad [75]$$

with δ along the target cylinder axis. This gives a filter function of

$$F(\vec{k}_\perp) = 1 + \exp(-(\vec{r} \cdot \vec{k}_\perp)^2) - 2 \cos(\vec{d} \cdot \vec{k}_\perp) \exp\left(-\frac{(\vec{r} \cdot \vec{k}_\perp)^2}{2}\right) \quad [76]$$

The phase variance (including piston), normalized to the phase variance of a point beacon, offset at distance d , is then given by

$$\frac{\sigma_\phi^2}{(d/L\theta_0)^{5/3}} = 0.2398 (r/d)^{5/3} \int_0^\infty \frac{d\mu}{\mu^{8/3}} [1 - 2 \cos(\mu d/r) \exp(-\mu^2/2) + \exp(-\mu^2)] \quad [77]$$

This normalized phase variance (including piston) is shown, as a function of d/r , in Fig. 2. For a given offset to the beacon distribution peak, d , the minimum in the phase variance occurs at $r=1.15 d$, for which case the phase variance is $(0.8906 d/(L\theta_0))^{5/3}$.

In the limit where the offset to the Gaussian peak is much greater than the rms spread of the beacon distribution about the peak (i.e. where d/r is very large) this filter goes over to the point aniso result, with the aperture averaged phase variance, including piston, being $(d/L\theta_0)^{5/3}$. In the limit where the offset to the Gaussian peak is much smaller than the rms spread of the beacon distribution about the peak, where d/r is very small, the phase variance goes to the asymptote $(0.24825 r/L\theta_0)^{5/3}$. In this limit, the beacon spread can exceed the isoplanatic patch without deleterious effect.

8. Summary of piston included, or large aperture results

The following tabulation gives the beacon size for various geometries, which produce the same anisoplanatic Strehl in the large aperture limit:

- 1- a point beacon offset from the aimpoint by a distance b_0 ;
- 2- a uniform circular beacon, centered at the aimpoint, with radius $4.96 b_0$;
- 3- a uniform circular beacon distribution, with radius of $1.59 b_0$, with the center offset from the aimpoint by a distance $1.10 b_0$.
- 4- a circular Gaussian beacon distribution, centered at the aimpoint, with rms radius $2.77 b_0$;
- 5- a pair of point beacons straddling the aimpoint, each located a distance $2.58 b_0$ from the aimpoint;
- 6- a circular ring beacon, centered at the aimpoint, with radius $3.12 b_0$;
- 7- a uniform line beacon, centered at the aimpoint, with half length of $6.01 b_0$;
- 8- a Gaussian line beacon distribution, with rms spread of $1.29 b_0$, with the peak offset from the aimpoint by a distance $1.12 b_0$.
- 9- a Gaussian line beacon distribution, with rms spread of $4.03 b_0$, with the peak at the aimpoint.

B. Phase Variance for Finite Aperture Size

1. Point beacon off the Aimpoint

The phase variance with the piston component removed, for the displaced point beacon case, can be found by substituting Eq[66] into Eq[53]. This gives

$$\begin{aligned}
\sigma_\phi^2 &= 0.033 \, 2\pi \, k_o^2 \int_0^L dz \, C_n^2(z) \int \frac{d\vec{k}_\perp}{k_\perp^{11/3}} \left(1 - \left[\frac{2 J_1(k_\perp R t/L)}{(k_\perp R t/L)} \right]^2 \right)^2 [1 - \cos(\vec{k}_\perp \cdot \vec{b}_o z/L)] \\
&= 0.033 (2\pi)^2 k_o^2 R^{5/3} \int_0^L dz \, C_n^2(z) (v/L)^{5/3} \int_0^\infty \frac{d\mu}{\mu^{8/3}} \left(1 - \left[\frac{2 J_1(\mu)}{\mu} \right]^2 \right)^2 (1 - J_0(\frac{\mu b_o z}{R t})) \\
&= 1.303 \, k_o^2 R^{5/3} \int_0^L dz \, C_n^2(z) (v/L)^{5/3} KPA(\frac{b_o z}{R t}) \quad [78]
\end{aligned}$$

$$\text{where } KPA(\eta) = \int_0^\infty \frac{d\mu}{\mu^{8/3}} \left(1 - \left[\frac{2 J_1(\mu)}{\mu} \right]^2 \right)^2 (1 - J_0(\mu \eta)) \quad [79]$$

This phase variance (with piston removed) can be normalized to the phase variance (including piston) of a point beacon offset by b_o , i.e.

$$\frac{\sigma_\phi^2}{(b_o/L\theta_o)^{5/3}} = \frac{0.1410 (\frac{D}{b_o})^{5/3} \int_0^L dz \, (v/L)^{5/3} C_n^2(z) KPA(\frac{b_o z}{R t})}{\int_0^L dz \, (z/L)^{5/3} C_n^2(z)} \quad [80]$$

To proceed any further, the turbulence profile, $C_n^2(z)$, must be specified. Three cases have been treated: a uniform profile, a delta function at an arbitrary position along the path, and a fairly well behaved two parameter profile. With the uniform profile, $C_n^2(z)$ is constant along the path and can be taken outside the z integral. With the uniform profile,

$$\begin{aligned}
r_o^{-5/3} &= \frac{2.91 \, k_o^2}{6.88} \int_0^L dz \, (v/L)^{5/3} C_n^2(z) = 0.1586 k_o^2 L C_n^2, \text{ and} \\
(L\theta_o)^{-5/3} &= 2.91 \, k_o^2 \int_0^L dz \, z^{5/3} C_n^2(z) = 1.091 k_o^2 L C_n^2. \quad [81]
\end{aligned}$$

The normalized phase variance can then be written

$$\frac{\sigma_\phi^2}{(b_o/L\theta_o)^{5/3}} = 2.584 \left(\frac{DL\theta_o}{b_o r_o} \right)^{5/3} \int_0^L \frac{dz}{L} (v/L)^{5/3} KPA\left(\frac{0.6287 z b_o r_o}{DL\theta_o} \right). \quad [82]$$

A numeric evaluation of this normalized phase variance is shown as a function of $DL\theta_0/b_0r_0$, in Fig.3.

Another profile which leads to simplifications in the integrals, is that of a delta function, i.e. $C_n^2(z) = \delta(z-z_0) C_n^2$. In this case, the normalized phase variance is given by

$$\frac{\sigma_\phi^2}{(b_0/L\theta_0)^{5/3}} = 0.969 \left(\frac{DL\theta_0}{b_0r_0} \right)^{5/3} K^{PA} \left(\frac{0.6287 b_0r_0}{DL\theta_0} \right). \quad [83]$$

This result is independent of the location of the delta function turbulence. A numeric evaluation of this phase variance is also shown in Fig.3.

A third turbulence profile has been constructed which allows real profiles to be simulated. The profile is given by

$$C_n^2(z) = (t/L)^p (z/L)^q C_n^2. \quad [84]$$

where p and q are adjustable parameters which determine the profile. For $p=q=0$, this formulation gives a uniform profile. When the turbulence is localized near the aperture, with something like an exponential fall-off with distance, the profile can be simulated by setting $q=0$, and $p=L/(e\text{-folding length of the actual profile})$. For zenith propagation from the ground, p will typically have values of 200 to 4000. For near horizontal propagation from an airplane to a target at 25 to 50 km altitude, p will have values of 2 to 50. The best approximation of the atmosphere may involve non-zero q values. For the case of $q=0$, the normalized phase variance (i.e. the ratio of the phase variance with finite aperture to that with infinite aperture) for the offset point beacon anisoplanatic effect, is

$$\frac{\sigma_\phi^2}{(b_0/L\theta_0)^{5/3}} = 0.969(p+8/3) \left(\frac{DL\theta_0}{b_0r_0} \right)^{5/3} \int_0^L \frac{dz}{L} (t/L)^{(p+5/3)} K^{PA} \left(\frac{0.6287 z b_0r_0}{t DL\theta_0 (p+8/3) B(8/3, p+1)} \right). \quad [85]$$

where $B(x,y) = \Gamma(x)\Gamma(y)/\Gamma(x+y)$ is the Beta function. The formulation for non-zero q can also be expressed with a function of the parameter $DL\theta_0/b_0r_0$.

A numeric evaluation of this phase variance is also shown in Fig.3 for the case of $q=0$, $p=50$. It has been observed that the normalized phase variance is insensitive to the value of p over the range from a few tens to a few thousands. For example, at $DL\theta_0/b_0r_0=1$, the normalized phase variance for $p=50$ is 0.2370 while that for $p=1000$ is 0.2409, a difference of barely one percent. For the same $DL\theta_0/b_0r_0$, $p=0$ (uniform profile) gives 0.1658, while $p=1$ (linearly decreasing profile) gives 0.1943.

In the limit of large η , $K^{PA}(\eta)$ approaches the asymptotic value of 2.12996. This limit corresponds to the case where the lead angle divided by the anisoplanatic patch angle is much greater than the aperture divided by the coherence length. In this case, the phase variance (with all of the three turbulence profile formulations) approaches the asymptotic limit

$$\sigma_\phi^2 = 2.066 (D/r_0)^{5/3} \quad \text{for small } DL\theta_0/b_0r_0 \quad [86]$$

This phase variance is exactly twice the result obtained by Fried [Fried, 1982] for the phase variance of uncompensated turbulence. When the lead angle is sufficiently large, the phase error sensed by the beacon is uncorrelated to the required phase correction of the outgoing beam, so that the total variance is the sum of the beacon and outgoing beam variances, i.e. twice the uncompensated result.

In the limit of small η , $K^{PA}(\eta)$ approaches the asymptotic value of $2.23666 \eta^{5/3}$. In this case, the phase variance (with all of the three turbulence profile formulations) approaches the asymptotic limit

$$\sigma_{\phi}^2 = \left(\frac{b_0}{L\theta_0}\right)^{5/3} \text{ for large } DL\theta_0/b_0r_0. \quad [87]$$

In this limit, where the lead angle divided by the anisoplanatic patch angle is much smaller than the aperture divided by the coherence length, the phase variance with piston removed is identical to the phase variance with piston included or equivalently to the phase variance in the large aperture limit.

Fig.4 shows the Strehl as a function of $b_0/L\theta_0$, for the case where $D/r_0 = 10$. The tabularized results obtained by Fried [Fried,1982] with a uniform turbulence profile, are also shown for this case. For Strehl ratios over about 30%, the approximation by which Eq[27] was obtained from Eq[26] is seen to be valid. It can be concluded that the anisoplanatic Strehl obtained with a uniform turbulence profile, is non-negligibly larger than that obtained with a typical profile localized near the aperture, over much of the regime of interest. The anisoplanatic Strehl obtained with a delta function turbulence profile, is smaller than that obtained with a typical profile localized near the aperture.

2. Uniform Circular On-Axis Beacon

For a uniform circular beacon source distribution, of diameter b , centered at the aimpoint, the filter function of Eq[61] is substituted into Eq[53] to obtain the phase variance:

$$\begin{aligned} \sigma_{\phi}^2 &= 0.033 \, 2\pi \, k_0^2 \int_0^L dz \, C_n^2(z) \int \frac{d\mathbf{k}_{\perp}}{k_{\perp}^{11/3}} \left(1 - \left[\frac{2 J_1(k_{\perp} R/L)}{(k_{\perp} R/L)}\right]^2\right) \left[1 - \frac{2 J_1(k_{\perp} b z/L)}{k_{\perp} b z/L}\right]^2 \\ &= 0.033 (2\pi)^2 k_0^2 R^{5/3} \int_0^L dz \, C_n^2(z) (\nu/L)^{5/3} \int_0^{\infty} \frac{d\mu}{\mu^{8/3}} \left(1 - \left[\frac{2 J_1(\mu)}{\mu}\right]^2\right) \left[1 - \frac{2 J_1(\frac{\mu b_0 z}{R_L})}{\frac{\mu b_0 z}{R_L}}\right]^2 \\ &= 1.30278 \, k_0^2 R^{5/3} \int_0^L dz \, C_n^2(z) (\nu/L)^{5/3} K^{UC}\left(\frac{b_0 z}{R_L}\right) \end{aligned} \quad [88]$$

$$\text{where } K^{UC}(\eta) = \int_0^{\infty} \frac{d\mu}{\mu^{8/3}} \left(1 - \left[\frac{2 J_1(\mu)}{\mu}\right]^2\right) \left[1 - \frac{2 J_1(\mu \eta)}{\mu \eta}\right]^2 \quad [89]$$

Fig.5 shows a normalized phase variance as a function of a normalized aperture for the on-axis uniform circular beacon geometry, assuming a delta function turbulence profile. The phase variance is normalized by the factor $(0.2017r/L\theta_0)^{5/3}$, and the normalized aperture is given by $(D/r_0) (L\theta_0/0.2017r)$, where r is the radius of the uniform circular

beacon. There are two notable features when the uniform circular beacon is compared to the offset point beacon (the delta function case of Fig.3). First, when the beacon size is large relative to the normalized aperture, the phase variance approaches the uncompensated value, rather than twice the uncompensated value. This is because for a large uniform beacon, the sampled phase variance will average to zero. The second feature is that for the uniform circular beacon, the large aperture asymptotic value is reached at significantly smaller normalized aperture. This indicates that the piston component of the variance is much less for the uniform beacon than the offset beacon. For example, take the case where $D=10r_0$, and the beacons are constructed to give a phase variance including piston of one square radian (the offset of the offset point beacon is $b=L\theta_0$, while the radius of the uniform on-axis circular beacon is $r=4.96L\theta_0$). The normalized aperture is then 10 for both beacons. The effect of the finite aperture reduces the phase variance of the offset point beacon by a factor of 0.692, while the phase variance of the uniform on-axis circular beacon is reduced by only 0.986.

5. Summary

A methodology has been laid out by which the anisoplanatic effects of distributed beacon sources can be evaluated for focused beam geometries. Its application is in determining the performance limitations of an adaptive optics wavefront compensation system, where the wavefront sensor uses the return from an illuminated target. For any beacon source intensity distribution, Eq[50] can be used to find the appropriate anisoplanatic filter. This filter is then used as a weighting function for the integration over the turbulence spectrum. Eq[53] then gives the integral that must be performed over the turbulence profile to obtain the residual anisoplanatic phase variance. This phase variance is then used to obtain the Strehl ratio for the compensated beam. A number of simple beacon distributions have been treated analytically, and three analytic turbulence profile models have been employed, to illuminate trends.

The key result is that the spread of the beacon distribution has much less deleterious effect than does the offset of the beacon centroid from the aimpoint. Another useful development is the scaling, providing a formulation which is insensitive to the detailed turbulence profile.

References

- M.Born,E.Wolf, "Principles of Optics", Pergamon Press (1959).
- B.Ellerbroek, private communication. (1991).
- D.L.Fried,J.Opt.Soc.Am, 56, 52 (1982).
- R.J.Srniela,"A Unified Approach to Electromagnetic Wave Propagation in Turbulence and the Evaluation of Multiparameter Integrals", Lincoln Laboratory Technical Report 807 (July 1,1988).
- V.I.Tatarski,"Wave Propagation in a Turbulent Medium",McGraw-Hill Book Co (1961).
- V.E.Zuev,"Laser Beams in the Atmosphere", Consultants Bureau, New York (1982).

Figure 1. The normalized anisoplanatic phase variance (including piston) for an offset uniform circular beacon, as a function of d/r , the ratio of the offset of the center of the beacon from the aimpoint, to the radius of the beacon.

Figure 2. The normalized anisoplanatic phase variance (including piston) for an offset 1-D Gaussian line beacon, as a function of d/r , the ratio of the offset of the peak from the aimpoint, to the rms spread of the beacon.

Figure 3. The normalized anisoplanatic phase variance (piston removed) for an offset point beacon, as a function of the normalized aperture, for three turbulence profiles. The piston removed phase variance is normalized to the piston included phase variance. The aperture is normalized to the atmospheric coherence length times the offset angle divided by the isoplanatic patch angle.

Figure 4. Anisoplanatic Strehl for an offset point beacon, as a function of (offset angle / isoplanatic patch angle). The aperture diameter is 10 times the coherence length. The lines shows the result obtained by evaluating Eq.[85] numerically, for the uniform, localized near aperture ($p=50, q=0$), and delta function turbulence profiles. The data points show the results obtained by Fried [Fried, 1982] for a uniform profile, without resort to the Marechal approximation. Note the good agreement for Strehl ratios greater than 30%.

Figure 5. The normalized anisoplanatic phase variance (piston removed) for an on-axis uniform circular beacon, as a function of the normalized aperture, for the delta function turbulence profile. The piston removed phase variance is normalized to the piston included phase variance. The aperture is normalized to the atmospheric coherence length times 0.2017 times beacon radius, divided by the isoplanatic patch angle times the range.