NOTICE
This report was prepared as an account of work sponsored by the United States Government. Neither the United States nor the United States Department of Energy, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness or usefulness of any information, apparatus, product or process disclosed, or represents that its use would not infringe privately owned rights.

A PROPOSED ORBIT AND VERTICAL DISPERSION CORRECTION SYSTEM FOR PEP*

E. Close†, and M. Cornacchia, A. King, and M. J. Leett

Introduction

The scheme for minimization of the rms orbit errors in ISR1 and SPEAR2 will be used to correct the closed orbit errors in PEP. The effectiveness of this scheme has been studied for some alignment and field errors in the PEP magnets and position monitors. It has been found for orbit correction system in PEP consisting of 48 correctors and 96 monitors, both horizontal and vertical orbits can be kept below 0.5 mm rms values even allowing for a position monitor alignment error of 0.5 mm rms. This method of correction has also been found to be usable to reduce the rms value of the vertical dispersion without appreciably affecting the corrected orbits. The result of this study will be presented in this paper.

The Correction Scheme

Let vectors $\vec{y}$ and $\vec{n}_y$ be the vertical orbit and dispersion at the position monitors. Let $\vec{\delta}$ be the dipole kicks at the correctors. The values of the orbit and dispersion vectors after correction are given by the sum of the measured values and the values introduced by the correctors as:

$$\vec{y} = \vec{y}_m + \vec{y}_c \quad (1)$$

and

$$\vec{n}_y = \vec{n}_m + \vec{n}_c \quad (2)$$

If thin lens approximation is used for each magnet

$$\vec{y}_c = M\vec{\delta} \quad (3)$$

and

$$\vec{n}_c = N\vec{\delta} \quad (4)$$

where the matrix elements are

$$M_{ij} = \frac{\sqrt{\beta_{y1}\beta_{yj}}}{2 \sin(\pi\nu_y)} \cos(\pi\nu_y - |\phi_{y1} - \phi_{yj}|) \quad (5)$$

and

$$N_{ij} = \frac{\sqrt{\beta_{y1}\beta_{yj}}}{2 \sin(\pi\nu_y)} \left\{ \begin{array}{l} + \cos(\pi\nu_y - |\phi_{y1} - \phi_{yj}|), \text{ jth dipole} \\ + \sum_q \frac{\beta_{yq}}{2 \sin(\pi\nu_y)} \cos(\pi\nu_y - |\phi_{y1} - \phi_{yq}|) \\ - \cos(\pi\nu_y - |\phi_{y1} - \phi_{yj}|), \text{ q quadrupoles} \\ - \sum_s \frac{\eta_{ys}\beta_{ys}}{2 \sin(\pi\nu_y)} \cos(\pi\nu_y - |\phi_{y1} - \phi_{ys}|) \\ - \cos(\pi\nu_y - |\phi_{y1} - \phi_{yj}|), \text{ s sextupoles.} \end{array} \right. \quad (6)$$

*Work supported by the Department of Energy under contract no. EY-76-C-03-0515.

†Lawrence Berkeley Laboratory, Berkeley, CA 94720.
†Stanford Linear Accelerator Center, Stanford University, Stanford, California 94305.

Comp. 790327--85

SLAC-PUB-2265
February 1979
(A)

In these expressions the strengths of the quadrupole and sextupole magnets are given by $g = \partial B_y / \partial x$ and $2S = \partial^2 B_y / \partial x^2$; l = magnet length; B_0 = particle rigidity; ϕ_x , ϕ_y and ν_y are the betatron function, betatron phase and tune, respectively. The value of η_c results from the dipole corrector and the change in the orbit at the quadrupole and sextupole magnets caused by the correction.

It can be shown² easily that the corrector strengths corresponding to the minimum value of y_{rms} is given by

$$\vec{\delta} = -(\tilde{M}N)^{-1} \tilde{M}y_m \quad (7)$$

with $\tilde{M}$ denoting the transpose of M , and a similar result for minimum x_{rms} by interchanging y with x . For minimum η_y rms the solution is

$$\vec{\delta} = -(\tilde{N}N)^{-1} \tilde{N}n_m \quad (8)$$

Given a measured orbit vector we find the n most effective correctors up to 48 as follows: First we calculate y_{rms} using Eqs. (1), (3) and (7) for each of the 48 correctors and determine the corrector C_1 corresponding to the smallest y_{rms} values. We then calculate y_{rms} for all possible pair of correctors (C_1, C_2) and determine C_2 the second corrector which when paired with C_1 produces the smallest y_{rms} value. This procedure is repeated to find the third corrector which when coupled with C_1 and C_2 makes y_{rms} smallest. After n times, the best n correctors will be found. The strength of the corrector vector $\vec{\delta}$ for each n is given by Eq. (7).

The Corrected Orbit

The measured orbit and dispersion $\vec{y}_m$ and $\vec{n}_m$, were simulated by a computer code³ taking into account the surveying errors. The errors are assumed to be gaussian with the sigma values given below:

- vertical misalignment of quadrupoles 0.2 mm
- horizontal misalignment of quadrupoles 0.2 mm
- relative field error in the dipoles 0.01%
- misalignment of secondary monuments 0.3 mm
- angular misalignment of major monuments 20 μ rad.

The orbit and dispersion values produced by error values randomly selected with the above sigmas were calculated and displayed at the midpoint of every dipole, quadrupole, sextupole, position monitor and corrector around the ring (a total of 1044 points). A typical PEP configuration with $\nu_x = 21.23$, $\nu_y = 18.67$, $\beta_x^* = 0.11$ m, $\beta_y^* = 2.88$ m and $\eta_x^* = -0.468$ m was used for this study, where a * denotes the interaction point value.

In order to obtain a statistically significant result, we studied the orbit correction for 20 machines. For each machine, the measured orbit was simulated with a different set of random alignment and field errors. In all cases 48 correctors and 96 position monitors were used. Their layout is given in Fig. 6 for 1/12 of the lattice (see the appendix).

Table I gives the average of the rms values of the corrector strength, the orbit and dispersion before and after correction over the 20 cases considered.

END

Table 1

Monitor Position Error mm	Horizontal Corrector Strength μrad		Horizontal Orbit Values mm		Vertical Corrector Strength μrad		Vertical Orbit Values mm		Vertical Dispersion Values mm	
rms	rms	max	rms	max	rms	max	rms	max	rms	max
-	0	0	6.5	26	0	0	15	89	525	2640
0	63	148	0.4	1.8	49	123	0.4	1.4	105	635
0.5	76	181	0.6	2.2	53	133	0.5	1.7	136	806
1.0	107	248	0.9	3.4	64	158	0.7	2.4	199	1148

In addition, Table 1 also gives the rms value of the maximum corrector strength, the orbit and dispersion before and after orbit correction over the 20 cases. The values after correction are shown for three position monitor alignment errors with sigmas equal to 0.0, 0.5 and 1.0 mm.

In practice, it may be unnecessary to use all of the 48 correctors everytime we correct the orbit. The effectiveness of the correction as a function of the number of corrector for a typical case is shown in Fig. 1. In this case, 15 correctors should be sufficient.

Fig. 1. Vertical closed orbit and dispersion versus number of correctors (rms of one "machine").

The Corrected Dispersion

From the operating experience of SPEAR it may be necessary to reduce the vertical dispersion in PEP after the orbit is corrected. The effectiveness of the dispersion correction using the orbit correctors with the same minimization scheme as the orbit correction has been studied. Table 2 gives the results for a typical case. For this case it can be seen that both $n_{y \text{ max}}$ and $n_{y \text{ rms}}$ can be reduced by a factor of 5 with only 8 correctors. The effects upon the corrected orbit is relatively small since the strength of the correctors is less than 10% of those required for orbit correction. This method has been tried experimentally at SPEAR and obtained the predicted results.

The Harmonic Representation

Some of the results described in the previous sections could be explained in terms of the harmonics of the orbit and dispersion. For example, Fig. 2 shows the harmonics of the vertical orbit before orbit correction for the case described in Fig. 1. It can be seen that only those harmonics near 19 are dominant.

Table 2

Number of Correctors	Vertical Corrector Strengths μrad		Vertical Orbit Values mm		Vertical Dispersion Values mm	
	rms	max	rms	max	rms	max
0	0	0	0.4	1.1	64	304
1	15	15	0.6	2.1	33	114
2	9	11	0.6	2.1	32	106
3	7	11	0.5	2.0	31	108
4	10	12	0.5	1.3	23	62
5	9	14	0.5	1.3	21	60
6	8	13	0.5	1.4	17	58
7	8	13	0.5	1.5	16	63
8	9	14	0.5	1.5	15	61

Fig. 2. Harmonics of the normalized vertical closed orbit (before correction).

After orbit correction, all of the dominant harmonics were reduced as shown in Fig. 3. This residual orbit

Fig. 3. Harmonics of the normalized vertical closed orbit (after correction).

produces a dispersion having only a few predominant harmonics, as shown in Fig. 5, so that only a small number of correctors will be needed for dispersion correction. Note that the dispersion before orbit correction has dominant harmonics not just centered around 19 but also near 19 ± 6 as shown in Fig. 4; 6 is the machine superperiodicity.

Fig. 4. Harmonics of the normalized vertical dispersion (before correction).

Fig. 5. Harmonics of the normalized vertical dispersion (after correction).

Appendix

The effects of the orbit corrections have been examined for several systems with different position monitor and corrector locations. It has been found that the chosen system, which has correctors situated close to position monitors, gives the smallest residual orbit with the minimum corrector strength. A schematic layout of this system is given in Fig. 6 for $1/12$ of the lattice.

I.P. = Interaction Point Q = Quadrupole Magnet
S.P. = Symmetry Point H = Horizontally Correcting Dipole
B.P. = Beam Position Monitor V = Vertically Correcting Dipole

Fig. 6. A layout of a half-superperiod showing the relative position of the position monitors, dipole correctors, and the ring quadrupole magnets (48 correctors).

References

1. B. Autin and G. Marti, CERN-ISR-MA/73-17, 1973.
2. A. S. King, M. J. Lee and P. L. Morton, IEEE Trans. Nucl. Sci. NS-12, June 1973.
3. E. Close and R. Sah, ALIGN-The LBL/SLAC Alignment Program, PEP-Note-271.