DOE/ER/14064--T1

DOE/ER/14064--T1

DE93 013233

FINAL REPORT

**TWO AND THREE DIMENSIONAL
MAGNETOTELLURIC INVERSION**

Submitted by
Professor John Booker

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

MASTER
DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED *ds*

Abstract

Electrical conductivity depends on properties such as the presence of ionic fluids in interconnected pores that are difficult to sense with other remote sensing techniques. Thus improved imaging of underground electrical structure has wide practical importance in exploring for groundwater, mineral and geothermal resources, and in assessing the diffusion of fluids in oil fields and waste sites. Because the electromagnetic inverse problem is fundamentally multi-dimensional, most imaging algorithms saturate available computer power long before they can deal with the complete data set. We have developed an algorithm to directly invert large multi-dimensional data sets that is orders of magnitude faster than competing methods. We have proven that a two-dimensional (2D) version of the algorithm is highly effective for real data and have made substantial progress towards a three-dimensional (3D) version. We are proposing to cure identified shortcomings and substantially expand the utility of the existing 2D program, overcome identified difficulties with extending our method to three-dimensions (3D) and embark on an investigation of related EM imaging techniques which may have the potential for even further increasing resolution.

1. Introduction

Electrical conductivity depends on properties that are difficult to sense with other remote sensing techniques. These include temperature, lithology, metamorphic state, chemistry, metal and carbon content and perhaps most important, the presence of ionic fluids in interconnected pores. Improved imaging of underground electrical structure has wide practical importance. Surface electrical and electromagnetic measurements have been used for decades to explore for groundwater, mineral and geothermal resources, and borehole measurements are often the method of choice to distinguish the type of fluid in the formation and to estimate fluid permeability. Imaging the diffusion of fluids injected into producing oil fields and characterizing waste sites, which often involve contaminants whose conductivity contrasts strongly with the natural environment are obvious contexts in which electrical and electromagnetic techniques are likely to prove important. Even in hydrocarbon exploration, which is dominated by seismic methods in the United States, interest in electromagnetic techniques has increased as exploration has progressed to targets covered by basement overthrusts, high velocity carbonates or volcanics, all of which complicate seismic methods.

In a situation reminiscent of the advent of seismic reflection profiling, the last decade has seen vastly increased quality and quantity of magnetotelluric (MT) data. Parallel improvements have occurred in methods employing controlled artificial sources rather than the natural fields measured by MT. With this improved data has come understanding of the important distorting effect of shallow, small scale heterogeneities. Strategies to overcome these distortions universally involve sampling densely in space and over a wide bandwidth. Data sets which are an order of magnitude more accurate than 10 years ago, with more than 20 frequencies over at least 4 decades taken at 50 or more sites, are almost routine. Such data sets would have been considered enormous a few years ago and may represent only the beginning of the growth curve.

Because electromagnetic (EM) fields diffuse in the relatively high conductivity of earth materials, their power to resolve structure depends very strongly on the accuracy

of the measurements. Thus the new data have the potential for substantially improving the resolution of electrical structure in the earth, but only if the information can be extracted in a stable and numerically efficient manner. Most approaches to the MT imaging problem saturate existing computer power long before the algorithms can deal with the complete data set. This is true largely because the inverse problem is fundamentally multi-dimensional. We have developed an algorithm to directly invert large multi-dimensional MT data sets that is orders of magnitude faster than competing methods (e.g. Jupp and Vozoff [1977] or deGroot-Hedlin and Constable [1990]). We have proven that a two-dimensional (2D) version of the algorithm is highly effective for real data and believe that the resolution of MT imaging can often exceed that of seismic refraction or travel time tomography.

We are proposing to cure identified shortcomings and substantially expand the utility of the existing 2D program, overcome identified difficulties with extending our method to three-dimensions (3D) and embark on an investigation of related EM imaging techniques which may have the potential for even further increasing resolution. The next section reviews our progress in more detail. This is followed by technical background for the proposed work, an outline of specific tasks to be undertaken with our requested funding and a detailed justification of the budget.

2. Overview of past work

We have developed an algorithm to rapidly invert large multi-dimensional MT data sets. Our method is iterative and approximates lateral derivatives of the electric and magnetic fields inside the model by their values from the previous iteration. If these multi-dimensional fields are known, the derivatives of the data with respect to small changes in the model turn out to depend primarily on the vertical conductivity profile beneath each site. This leads to an inverse problem for improved conductivity beneath each site that is very similar to and can be solved as efficiently as the one-dimensional (1D) inverse problem. We call these inversions "pseudo-1D". The model is made unique by minimizing a function which measures the complexity of the model. Our philosophy is to find the model with the least structure for a given level of misfit to the data. The improved profiles under each site are interpolated to form an improved multi-dimensional model. Finally, the multi-dimensional forward problem is solved in the improved model, in order to improve the electric and magnetic fields inside the model. The solution of the forward problem is also iterative and takes advantage of the sparseness of the linear system generated by our Finite Difference Approximation (FDA) and the fact that the fields from the previous step are always a very good approximation to the new fields. This cycle is repeated until the measure of model complexity is minimized subject to a specified misfit to the data. If this process converges, we have a solution to the fully multi-dimensional inverse problem. Although Barashkov [1985] has had some success proving convergence for a philosophically similar inversion for weakly multi-dimensional models, we do not have a rigorous guarantee of convergence in general. However, convergence does occur in most practical examples that we have investigated.

A 2D version of our code is now fully operational. Figure 1 compares operation counts for our method (dubbed the Rapid Relaxation Inverse, or more simply RRI) to

Million floating point operations (MegaFLOP) per model iteration

Grid: 72 wide x 48 deep; 12 frequencies; 31 sites; 8 orthomin iterations

Storage (MB)

Figure 1. Operation counts and storage for one model iteration of 2D standard and rapid inversions. Typically 10-40 model iterations are required for a complete inversion in either the standard or rapid methods. LU corresponds to calculating the standard partial derivatives using full decomposition of the finite difference matrix. For 2D, this is slightly faster, but requires more storage than calculating the standard partial derivatives by solving the forward problem using an iterative method (ILU). In 3D, however, finding standard partial derivatives using the iterative forward solution is expected to be substantially faster than full decomposition.

those for an efficiently organized "standard" inversion in which one calculates fully 2D partial derivatives of the data with respect to the model. We use Incomplete Lower-Upper decomposition (ILU) to iteratively solve the 2D forward problem. The high relative efficiency of RRI extends to computer memory as well as time and our actual experience confirms the predictions of Figure 1. RRI can invert very large 2D magnetotelluric data sets with the modest computer power of a technical workstation. In fact, RRI is so efficient, that future large surveys will be able to do these inversions in the field and use them to guide data collection.

Our implementation also includes a variety of ways to stabilize the iterative process in the presence of noise. These include, for instance, robust re-weighting of the residuals to protect against non-Gaussian outliers. It also includes a variety of utilities for visualizing the results. Among these is color animation of the convergence process. The package has been installed at the USGS in Denver for a rigorous field test before making it generally available. Their experience has pointed out a number of non-portable features that are being dealt with.

RRI works quite well for noisy synthetic data, converging smoothly to fuzzy images of the truth, with the focus improving as the noise level decreases. Figure 2 is an example from Smith and Booker [1991]. Manuscripts in various states of completion, exist for studies which illustrate the power of RRI with very large real data sets. These include a 100 site, 37 frequency 25 km profile across the Wind River Thrust of Wyoming [Knickerbocker and Booker, 1991], a 51 site, 35 frequency, 135 km wideband MT profile across the Nevada-Utah border in the eastern Great Basin, and a 35 site, 40 frequency, 400 km wideband MT profile across the Williston Basin in Saskatchewan and Manitoba [Nong and Booker, 1991]. All of these data produce images of considerable interest. In the Wind river basin, for instance, we can see all the known structure including elements that require a combination of seismic reflection and refraction to image; in the Great Basin, we see conductive slivers beneath the major thrusts that are presumably sedimentary and are a surprise geologically [Johnston and Wannamaker, 1991].

Here we shall illustrate RRI on a large real data set with a 48 site, 23 frequency audio MT (AMT) profile over a gold prospect in the Carlin Trend of Nevada. "Transverse Magnetic" (TM) mode data were collected with dipoles approximately perpendicular to geologic strike placed end-to-end. The data are thus a spatially filtered, but otherwise complete picture of the variation of the response along the profile. These data are strictly TM only if the actual structure is 2D and the profile is perpendicular to strike. However, as noted by Wannamaker, *et al.* [1984], these data should be a good approximation to the TM response of a 2D structure which corresponds to a slice of the actual 3D structure.

The model grid is 70 nodes wide by 49 nodes deep and a total of 54 iterations were performed at an average of 170 seconds each on a Sun Sparc 1+. A convenient scaled misfit measure is the square root of the standard χ^2 misfit statistic. The goal for fitting the data was a scaled misfit of one for this and all other inversions to be discussed. The scaled misfit, which was 10 for the starting model (a 20 ohm-m halfspace) decreased to 2 in only 10 iterations and decreased only slightly in the remaining iterations. This means that, on the average, we were only able to fit the data to twice their claimed errors. This is not unreasonable for real data, which typically have claimed

Fig. 2 Inversion of synthetic TM mode data for the Prisms model with increasing added noise. There are 30 sites mostly spaced 3 km apart. Another inversion with 6-km site spacing produced a result with slightly less focus. The forward modeling grid has $44 \times 35 + 8$ nodes, is 400 km wide and extends to 100 km depth. The vertical node spacing is 500 m at the surface and 10 km at the bottom. The display uses boxes centered on the nodes.

errors that are too optimistic. We tried to take some account of this optimism by increasing the errors to 3% if they were claimed to be less. The model became progressively smoother after the initial rapid reduction in misfit, but changed very little after about the 35th iteration. The final model in Figure 3(a) shows several important structures: a resistive block on the right which is overlain at very shallow depth by a thin, very conducting layer; a very conductive unit centered at about 500 m depth near the left edge; and a shallow gently tilted thin layer in between. The choice of resistivity levels enhances the details of the structure within the conductive units, but obscures the fact that the resistive block actually exceeds 1000 ohm-m near its center. Note that the model is plotted versus the square root of depth, which facilitates visualizing deep and shallow structure in one plot. This scaling has the additional advantage that it roughly mimics the change with depth in the structure penalty and hence the resolution. Thus one can have roughly equal confidence in shallow and deep structure which have the same appearance in this figure.

Unlike ElectroMagnetic Profiling (EMAP) surveys, each site at Carlin also has a dipole perpendicular to the profile (i.e. approximately along strike) to collect "transverse electric" (TE) mode data. The ostensibly TE mode data are more difficult to invert with a 2D model assumption, because the current flows perpendicular to the profile and can be strongly affected by 3D variations off the profile about which we have no information. RRI inversion of the TE data (again starting from the halfspace) easily converges to a scaled misfit of 1.2 and produces the model in Figure 3(b). This model has rapid horizontal structural variations that correlate poorly with the TM structure in Figure 3(a) and that do not disappear if the misfit is allowed to increase substantially. If the dominant 3D effects are due to small scale, near-surface structure, they produce an effect called "static shift" in which phase is unaffected and apparent resistivity is multiplied by a frequency-independent constant. This constant can be estimated by including it as a parameter in the TE model and jointly inverting TE and TM starting from the TM model of Figure 3(a). The resulting model shown in Figure 3(c) is very similar to the original inversion of TM alone. The static shifts obtained correspond to electric fields which vary from about 30% too high to 70% too low and are quite robust to the choice of starting model.

One problem with this joint inversion is a systematic and substantial misfit to the lower frequency TE mode data near the left edge of the resistive block. This could be a non-static 3D effect, but could also be structure near the left boundary of the resistive block that has a TE response but little or no TM response. To investigate this possibility, we used the static shift coefficients determined in the joint inversion in a new inversion of the TE data alone. This "undistorted" TE model fits all the TE data very well, with a scaled misfit of 1.1 and is shown in Figure 3(d). It is much more like the original TM model than the "distorted" TE model of Figure 3(b). The one significant difference between the TM and undistorted TE models is a thin, nearly vertical conductor at the left edge of the resistive block. This is precisely the kind of structure we are looking for, since thin vertical conductors have very little TM response.

We generated the final model shown in Figure 3(e) by starting a joint inversion of TE and TM from the undistorted TE model, Figure 3(d). The TE resistivity data at the sites 300 and 800 meters from the left end of the profile consistently showed very large misfits at all stages of our analysis. It is probable that they involve some kind of

Figure 3

(a) TM inversion started from 20 ohm-m halfspace

(b) Distorted TE inversion started from 20 ohm-m half-space

(c) Joint TE and TM inversion started from (a)

Figure 3

(d) Undistorted TE inversion started from 20 ohm-m half-space

(e) Joint TE and TM inversion started from (d)

error that cannot be absorbed by a static shift. Their apparent resistivities (but not their phases) were excluded from this final inversion. The static distortion coefficients were re-determined during the final inversion, but changed very little. The ultimate scaled misfit of 1.9 is slightly better than the original joint inversion, primarily reflecting an improvement in the TE fit near the left edge of the resistive block. If the thin vertical feature really has no TM response, we might expect it to survive unscathed, since removing it would degrade the very good TE fit without improving the TM fit. This is essentially what we see, although the exact position and strength of the vertical conductor has changed somewhat. We conclude that the vertical structure is probably real and almost invisible to the TM mode. One has the distinct impression of the thin surface conductor on the right side of the model wrapping around the resistive block into the thin vertical structure. The gently tilted thin horizontal layer to the left of the thin vertical structure may also wrap around a somewhat less resistive block into another thin vertical structure further to the left. This second thin vertical structure terminates the right end of the deeper conductor at the very left edge of the model and appears to be more limited in vertical extent than its cousin further to the right. However, the actual depth extent of the second vertical feature is probably impossible to ascertain from this data because of the very high conductance of the deeper feature just to its left. Even if the structural units in this area have large acoustic contrasts, it is hard to imagine a single seismic experiment that could more effectively image this structure.

Unfortunately, further interpretation of the final model is hampered by the obvious proprietary sensitivity of the owner of the mineral rights, Newmont Mining. This has so far prevented us from obtaining other geological and geophysical data. Two alternatives suggest themselves. The first is that the resistive material is limestone and the thin vertical features are highly mineralized normal faults that have, in the past, fed hydrothermal fluids to the thin horizontal units. It should be noted that all the structure in this model is probably well above the water table in this very arid region and the high conductivities are not due to groundwater. The second is that the resistive material is intrusive and the thin vertical and horizontal units are probably graphitic boundaries produced when the intrusion invaded limestone. Gold in the Carlin Trend is often found in such carbonaceous structures.

Each data set that we have examined has provided additional insight into the problem of removing the distorting effects of shallow structure. Our Carlin inversion illustrates one of the techniques that we have found successful. The unaliased sampling of the Carlin data along the profile makes static shift corrections for the TM data unnecessary. Two other techniques, which have been quite useful when the TM mode is also potentially distorted are wavenumber filtering in the spatial domain and wide-band inversion of phase constrained by high frequency apparent resistivity.

In preparing for inclusion of surface topography in the 2D code, we have also made a significant advance in finite difference approximations (FDA) to the induction equations. We have found FDA's valid at boundaries at which the fields or their derivatives are discontinuous, which are accurate and do not require that the boundary be coincident with the nodal mesh. The ideas should work as well in 3D as 2D. The new FDA's are derived by integrating the original differential equation over a volume surrounding the node that extends half way to the adjacent nodes. The part of the equation that contains singularities can be converted to a surface integral involving

derivatives normal to the boundary of the volume that can be estimated with centered first differences that do not cross any discontinuity. For the 2D TE mode, the new FDA is extremely easy to implement, because all one has to do is replace the nodal conductivity with an "effective conductivity", which is the mean conductivity in the area of integration. The derivation demonstrates that a boundary that cuts diagonally across the mesh (or one that does not pass through any nodes) is as easily modeled as one coincident with a rectangular grid. Thus our FDA can easily mimic the triangular elements of finite element approximations. Test cases with identical triangular elements for our new FDA and a finite element code produce virtually identical results. Figure 4 shows an example from a paper submitted for publication [Aprea, *et al.*, 1991]. For discrete internal structure, the TM mode is more complicated and in 2D requires four "effective resistivities", but is otherwise similar and effective.

Our formulation of RRI can be most easily generalized to 3D by replacing the 2D interpolation and forward modeling steps by their 3D equivalents. The pseudo-1D inversions differ only in the implementation of the constraint to discriminate against lateral structure. We expect that RRI will turn an imaging problem that appears impossible with standard methods on any existing computer into one that can easily be done. We have written the code to do the 3D interpolation, so the only remaining step is to complete work on the 3D forward problem. Efficiently and accurately solving the 3D forward problem is eased by the fact that inversion for models with minimum structure produces models with no internal discontinuities. We have therefore developed an iterative solution to the problem of calculating the electric and magnetic fields in a smoothly varying, but otherwise arbitrary conductivity model that is numerically very efficient. The matrices generated are not as sparse as for 2D (12 as opposed to 5 non-zero diagonals) and a different iterative scheme (pre-conditioning by Incomplete Cholesky factorization of Conjugate Gradients, ICCG) has proven more efficient than ILU. We have, however, identified a problem that affects the accuracy of this algorithm that needs rectifying before we proceed to the 3D inversion. This is discussed in detail in section 4.

3. Background for proposed work

In this section we discuss the detailed justification of several avenues for continued research. the specific tasks to be addressed are outlined later.

3.1. Structural constraints

In dealing with specific geologic targets it is often desirable to incorporate *a priori* structural constraints. For instance Wannamaker, *et al.* [1989] demonstrate a very large increase in the power of MT to constrain the structure of the Juan de Fuca subduction zone if the known offshore conductance of the ocean is incorporated as a constraint. We will be exploiting a related effect in a search for the Alleghenian Suture along the eastern seaboard of the U.S. with funds granted by the National Science Foundation (NSF). This work will involve collecting about 100 new MT sites along a transect that also crosses an extensive overthrust. The eastern extent of sedimentary material beneath this overthrust is of considerable geologic interest. Since the depth of

GRID FOR VALLEY

Figure 4. Numerical results at 100 Hz for a valley in a 100 ohm-m halfspace. Triangles are our finite difference approximation and circles are for the finite element code of Wannamaker, *et al.* [1986]. The vertical bars are scaled to 1% in apparent resistivity. The valley is shown at a 1:1 scale below the results and the grid used for both methods is shown above. The sloping boundary at the edge of the valley is modeled with identical triangular elements in both cases. A slight bias between the two methods can be attributed to the fact that the finite element code works with perturbations to an analytical solution to the fields in the halfspace far from the valley, while the finite difference results work with the total fields.

the decollement is reasonably well known from seismic experiments, incorporating its geometry as a constraint may substantially improve our confidence in structure beneath. A final example is from a proposal that we have submitted to the United States Geological Survey (USGS) and NSF. The crustal seismicity in the Puget Sound region is confined sub-horizontally above and below. It appears to be overlain by the igneous Olympic Peripheral Rocks and is presumably terminated below by the brittle-ductile transition, which is hypothesized to coincide with the blueschist-greenschist metamorphic boundary. This geometry has lead us to predict that there will be sharp increases in conductivity at the top of the seismicity as one passes from the volcanic rocks into metamorphosed sediments of the Olympic Core and another increase at the base of the seismicity associated with trapped fluids below the metamorphic boundary. Allowing these boundaries to have discontinuities in conductivity, while searching for otherwise minimum structure models would be of considerable help in testing our hypothesis.

Structural constraints can be added in several ways. In fact, we already have the ability to freeze the model structure along any vertical profile through the starting model. This is simply done at the step where we interpolate the pseudo-1D inversions for the new multi-dimensional model. The frozen profiles are treated just like additional sites with conductivity profiles that never change. Extending this idea to profiles which are frozen for only part of their depth, as one might do to incorporate data from drill holes, appears to be straightforward. Adding more general structural constraints is not difficult in principle. In some cases one can reformulate the constraint as data, which can be included in the inversion. More commonly, one can modify the penalty function for model complexity so that the *a priori* structure is not discriminated against and modify the interpolation routine so as to preserve the *a priori* structure.

3.2. RRI of vertical magnetic fields

As already noted in our discussion of the Carlin data, there are important classes of structure (thin vertical conductors, for instance) that are almost invisible to the TM mode. Addition of TE mode MT data, which is sensitive to such structure, can be problematic, however. In a strictly 2D situation, TE data are not affected by non-inductive charge buildups that are so important in the TM mode, because the current flows in straight lines and crosses no boundaries. Real data, however, are rarely strictly 2D and the TE electric field is almost always perturbed by off-profile structure in a manner that is not compatible with a purely inductive response. However, another aspect of the TE mode is the vertical magnetic field, H_z . Off-profile structure affects H_z much less than the electric field, because the charge accumulations have no magnetic field. Thus incorporating the vertical magnetic field in an inversion offers a way to include TE mode information that is less sensitive to off-profile complications.

The key to RRI is that MT data are strongly affected by perturbations in the structure beneath each site. Vertical field data do not obviously have this property. Instead, the vertical field at the surface is zero above a line current and reaches its maximum magnitude off to the sides of the current. One must therefore find a way to transform measurements of H_z to a new datum that is primarily due to structure beneath each site. We propose to use a linear combination of H_z at adjacent sites. We

shall show that there is a pseudo-Frechet derivative which approximately relates a horizontally filtered version of perturbations in H_z to perturbations in the vertical structure beneath a site.

3.2.1. Pseudo-one-dimensional inversions of horizontally averaged data

Relating horizontally averaged data to structure beneath a site actually has much wider applications than inverting H_z , so we begin by considering a general 2D linear inverse problem where one has data at n_f frequencies at each of n_s sites. The extensions to a linearized non-linear problem, to measurements of more than one physical quantity and to 3D are straightforward. We take x and y parallel and perpendicular to the 2D strike and z positive downwards. The datum γ_{ij} at site y_i and frequency ω_j is assumed to be related to any 2D model $m(x)$ by

$$\gamma_{ij} = \int g_{ij}(x) m(x) dx + r_{ij} \quad (3.2.1)$$

where $g_{ij}(x)$ is a data kernel that contains the physics of the forward problem, r_{ij} is the residual between the measured datum and that predicted by the model, x is the 2D position vector and the domain of integration is the region over which the EM fields are significantly non-zero. One can improve an initial guess for the model using back-projection. One iteration of the back-projection method applied to the data for the j 'th frequency at all n_s sites gives a change to the 2D model

$$\Delta m_j(x) = \sum_{i=1}^{n_s} \frac{g_{ij}(x) r_{ij}}{\int [g_{ij}(y, z)]^2 dx} \quad (3.2.2)$$

Evaluating this below a site at $y=y_s$ gives

$$\Delta m_j(y_s, z) = \sum_{i=1}^{n_s} \frac{g_{ij}(y_s, z) r_{ij}}{\int [g_{ij}(y, z)]^2 dx} \equiv \sum_{i=1}^{n_s} w_{ij}(z) r_{ij}$$

Thus the back-projected change to the model below the site is simply a depth-dependent weighted average of the residuals at the different sites.

Since we actually want a single horizontal filter at each frequency, rather than a depth-dependent one, we define vertically averaged weights

$$\bar{w}_{ij} \equiv \frac{\int f_j(z) g_{ij}(y_s, z) dz}{\int [g_{ij}(x)]^2 dx + \lambda} \quad (3.2.3)$$

where $f_j(z)$ is a yet unspecified function and we have also introduced a damping factor λ . Then we define our horizontally averaged data, residual and data kernel for the j 'th frequency to be

$$\bar{\gamma}_j = \sum_{i=1}^{n_s} \bar{w}_{ij} \gamma_{ij} \quad \bar{r}_j = \sum_{i=1}^{n_s} \bar{w}_{ij} r_{ij} \quad \bar{g}_j = \sum_{i=1}^{n_s} \bar{w}_{ij} g_{ij}$$

and (3.2.2) becomes

$$\Delta m(x) = \frac{\bar{r}_j \bar{g}_j(x)}{\int [\bar{g}_j(x)]^2 dx} \quad (3.2.4)$$

The linearity of (3.2.1) immediately implies that the averaged residuals, data and any 2D model are related by

$$\bar{r}_j = \int \bar{g}_j(\mathbf{x}) m(\mathbf{x}) d\mathbf{x} - \bar{\gamma}_j$$

However, to be able to use RRI, we need a pseudo-1D inverse problem of the form

$$\bar{r}_j = \int \Gamma_j(z) \Delta m(y_s, z) dz \quad (3.2.5)$$

Substitution easily verifies that the 1D pseudo-Frechet kernel

$$\Gamma_j(z) = \frac{\int [\bar{g}_j(\mathbf{x})]^2 d\mathbf{x}}{\int [\bar{g}_j(y_s, z)]^2 dz} \bar{g}_j(y_s, z) \quad (3.2.6)$$

satisfies both (3.2.4) and (3.2.5).

These kernels are not unique. Any linear inversion can be used in place of equation (3.2.4). For example, the smallest perturbation in the mean square sense is

$$\Delta m(\mathbf{x}) = \bar{g}^t(\mathbf{x}) G^{-1} \mathbf{r} \quad \text{where} \quad G \equiv \int \bar{g}(\mathbf{x}) \bar{g}^t(\mathbf{x}) d\mathbf{x}$$

$\bar{\mathbf{r}}$ and $\bar{g}(\mathbf{x})$ are column vectors of the residuals and data kernels and the superscripted t denotes the matrix transpose. Then (3.2.5) is satisfied by

$$\Gamma(z) = G H^{-1} \bar{g}(y_s, z) \quad \text{where} \quad H \equiv \int \bar{g}(y_s, z) \bar{g}^t(y_s, z) dz$$

These kernels reduce to the back-projection kernels (3.2.6) when G and H are approximated by their diagonals.

3.2.2. Application to the vertical field

The magnetic field at y_i and $z=0$ due to a line current $J_x(y, z)$ is given by

$$H(y_i, 0) = \frac{J_x(y, z)}{2\pi} \frac{y_i - y}{(y_i - y)^2 + z^2}$$

where we have dropped a factor $\exp(-i\omega_j t)$. Typically, vertical magnetic field data at the i 'th site and j 'th frequency are given as the ratio of the vertical to horizontal magnetic fields. Thus

$$\gamma_{ij} \equiv \frac{H_z^{\text{total}}(y_i, 0, \omega_j)}{H_y^{\text{total}}(y_i, 0, \omega_j)}$$

These "total" horizontal surface fields at each site and frequency are composed of the external source field plus the field of the currents inside the earth. For the purposes of this discussion, we shall assume that the vertical field of external origin and the horizontal field of internal origin are negligible and that the horizontal source field is laterally uniform and of unit magnitude. Suitable modifications can be incorporated if these assumptions are unwarranted. Then

$$\frac{\partial \gamma_{ij}}{\partial J_x(y, z)} = \frac{1}{2\pi} \frac{y_i - y}{(y_i - y)^2 + z^2} \quad (3.2.7)$$

which depends on y only through $y_i - y$. These kernels are singular at $y=y_i$, $z=0$. An *ad*

hoc way to deal with this singularity is to add a small constant to the denominator of the right side of (3.2.7). The square of the median site spacing, Δ_s^2 seems reasonable, because the RRI algorithm cannot result in horizontal structure with scales smaller than the site spacing. We can then write

$$\delta\gamma_{ij} = \int g_{ij}(\mathbf{x}) \delta j_{x,j}(\mathbf{x}) d\mathbf{x} \approx \frac{1}{2\pi} \int \frac{y_i - y}{(y_i - y)^2 + z^2 + \Delta_s^2} \delta j_{x,j}(\mathbf{x}) d\mathbf{x}$$

Where $\delta j_{x,j}$ is any perturbation of current density with frequency ω_j .

To favor resolution of structure at depth, we can employ weights implicit in using back-projection to construct the change to the model at the average depth of induced current flow, $z = D(\omega_j) \equiv D_j$, i.e. we can choose $f_j(z) = \delta(D_j - z)$ for the weight function in equation (3.2.3). Recognizing that the maximum depth of integration should be limited, because current becomes negligible below some depth, the integrals involved in calculating the weights from (3.2.3) and the pseudo-1D kernels for current, $\Gamma_j(y_s, z)$, from (3.2.6) can be done in closed form.

Perturbing Ohm's Law, $\mathbf{j} = \sigma \mathbf{E}$, we obtain

$$\delta j_{x,j} = E_{x,j} \delta\sigma + \sigma \delta E_{x,j} \approx E_{x,j}^0 \delta\sigma$$

where, $E_{x,j}^0$ is the electric field along strike at the j 'th frequency in the initial guess for the model, σ^0 . This approximation neglects the secondary current induced by the magnetic field of $E_{x,j} \delta\sigma$. The pseudo-1D pseudo-Frechet derivatives for conductivity are finally

$$\tilde{\Gamma}_j(z) = \Gamma_j(z) E_{x,j}^0(y_s, z)$$

This derivation has involved a string of approximations which seem reasonable. We believe that the very simple back-projection kernels will perform well for H_z , but it remains to be proven. Clearly higher order approximations and more rigorous ways of dealing with the singularity of the current kernels can be used if necessary. Finally, it is worth noting that one can invert the anomalous horizontal magnetic field H_y , due to the internal current distribution in a similar way, although one has the difficulty of separating it from the stronger external source field.

3.3. Two-dimensional TM kernels

In the transverse magnetic (TM) induction mode, the electric field is polarized perpendicular to strike. The underlying philosophy of RRI requires that perturbations in data at a site be primarily due to perturbations in structure beneath the site. The fact that TM mode currents pass beneath all the measurement sites presents a difficulty, because data at a site can sometimes be quite sensitive to structure beneath adjacent sites. Thus the theoretical basis of RRI for the TM mode, which is based on a perturbation expansion, is less accurate than for the TE mode in which currents are polarized perpendicular to the measurement profile. This partially explains why we have observed better rates of convergence of RRI in the TE mode than in the TM mode.

The TM mode has an additional complication. Because the currents cross structural gradients, their paths are not necessarily straight. The currents can be thought of as being deflected by local charge concentrations, which do not disappear even when the frequency goes to zero. These DC effects are often called "galvanic". The simplest case of a galvanic effect is the charge responsible for the jump in normal electric field required by the continuity of electric current crossing an interface between materials of different conductivity. An extremely important galvanic effect is the so-called "static-shift" of the electric field due to small scale heterogeneities near the measurement site discussed in the context of the Carlin data. Our present TM mode pseudo-Frechet kernels do not explicitly involve the galvanic part of the response. It enters only indirectly through the forward modeling steps as lateral structure grows. This probably also helps explain slower convergence of the TM mode and perhaps the failure in some tests with synthetic data to recover model features whose TM response is more galvanic than inductive (e.g. Smith and Booker, 1991).

An *ad hoc* method that has improved TM convergence is to average the residuals and pseudo-1D Frechet kernels for each iteration from five adjacent sites using weights 1/16, 1/4, 1, 1/4, 1/16. We did this for two reasons. First, to damp an observed tendency of improving fit at one site to make the fit worse at an adjacent site and second, to fit large scale lateral structure in the data prior to small scale. As Torres-Verdin and Bostick [1991] point out, however, the galvanic part of the TM response can be reduced by spatially filtering the data. It is thus quite likely that our *ad hoc* filtering also improved TM convergence because it reduced the galvanic response in the early iterations.

Although the galvanic response extends to DC, it cuts off at a high frequency which is structurally dependent. Filtering to reduce the galvanic effects depends on what part of the model you are interested in and should ideally be frequency dependent. Electromagnetic Array Profiling (EMAP) collects data with a series of dipoles laid end-to-end. Its advantage is that continuous dipoles are an analog filter which reduces spatial aliasing of short wavelength structure. This facilitates further digital filtering. The EMAP processing of Torres-Verdin and Bostick is intended to effectively suppress the galvanic response at all depths. We have already discussed how to use RRI for any frequency dependent horizontal filter. Thus extension of RRI to TM data with EMAP style suppression of the galvanic response should be straightforward. We have had some success with preliminary efforts, but have by no means exhausted the potential for suppressing galvanic effects in an RRI inversion by adaptive, frequency-dependent filtering.

One should note, however, that the galvanic response contains structural information that ideally should not be discarded. We should therefore explicitly incorporate the partial derivative of the galvanic part of the response with respect to changes in the model. We propose to do this by solving for the full 2D partial derivatives on a very reduced grid. For example, we can envision using a site plus two or four of its adjacent sites. As long as the reduced grid is very narrow the required computations can be done quickly using an adjoint method for calculating the partial derivatives (e.g., as presented by Rodi [1976] and reviewed in an Appendix to Smith and Booker [1991]). The reduced 2D data kernels can then be combined to form 1D pseudo-Frechet kernels using the general methods developed in the section on "RRI of Vertical Magnetic

Fields'' or they can be inverted to form local 2D models, which can be combined in some yet to be determined manner to form the large scale 2D model. We have already written the code for calculating the full 2-D partials on a reduced grid and applied it to finding pseudo-1D kernels averaged with a 1:4:1 filter. Despite some crude approximations made to expedite initial development, we have already seen a modest improvement of convergence for the test case used in debugging the code. We propose to correct the initial gross approximations and extend the reduced 2D adjoint method calculating 1D pseudo-Frechet derivatives to handle arbitrary horizontal filtering of data (including EMAP).

3.4. Resolution

In a 1D linear inverse problem one can show that there exists a resolution (smoothing) operator that will turn any model that fits the data into the model which minimizes the chosen structural complexity function. The same result generalizes to non-linear inverse problems only for models that are linearly close to the minimum structure model. However, Smith and Booker [1988] demonstrate that the non-linearity of the suitably posed 1D MT inverse problem is actually quite weak. Egbert and Booker [1991] show for instance, that the resolution function appropriate to minimization of the mean square second derivative of $\log \sigma$ with respect to $\log z$ produces the smoothest model within its statistical uncertainty when applied to the "D⁺" model of Parker [1980], which consists of a series of infinite conductivity spikes. Since D⁺ is about as far away in model space as the "truth" is every likely to be from the smoothest model, it follows that it is quite reasonable to interpret the smoothest model as the truth viewed through the resolution operator. The spatial structure of the resolution operator should thus be of considerable help in determining what features in the inversion are likely to be required by the truth.

Generalizing the idea of a resolution operator to higher dimensions would clearly be desirable. We do not know whether the weak non-linearity of the 1D problem carries over into 2 or 3D, but this can be investigated using inversions of synthetic data generated from known structure. Calculating the resolution operator is straight forward if one has the fully 2 or 3D partial derivatives of the data with respect to the least structure model. Since RRI never generates these partial derivatives, it is necessary to calculate them after the RRI has converged. This could easily involve more computation than the entire RRI inversion and will certainly involve far greater computer memory. There is thus considerable incentive to find an approximate technique that gives essentially the same result.

The simplest strategy we can think of is to apply the 1D theory to the pseudo-1D inversions. This will give an estimate of the resolution in the vertical direction. It may then be possible to find a relation which predicts the horizontal resolution from the vertical resolution. One could simply assume that they are locally equal, but a more accurate approach would be to use the penalty function for horizontal structure (which in our algorithm depends only on the structure beneath the two adjacent sites) to estimate how the conductivity at each depth depends on the data at the adjacent sites. Another approach might be to calculate the fully multi-dimensional partial derivative matrix on a very reduced grid involving only a few adjacent sites at a time. One can then

calculate a local fully multi-dimensional resolution operator. Since we are already proposing to calculate such reduced partial derivatives to improve RRI for the 2D TM mode, this should involve little added computation.

3.5. Three-dimensional inversion

Our formulation of RRI can be generalized to 3D by simply replacing the 2D interpolation and forward modeling steps by their 3D equivalents. As discussed in the overview, the main problem separating us from a functioning 3D RRI inversion, is correcting the shortcomings of our 3D forward algorithm. Specifically, the expected jumps in the normal component of the electric field E at the surfaces of a tablet embedded in a uniform host are too small and occur spread out over several nodal points. Even more disturbing, there are regions of apparent charge accumulation in the host at substantial distances from the tablet, which simply should not be there. The problem is most evident as period becomes large and can be thought of as a failure to correctly calculate the galvanic part of the solution. To some extent, the tablet test is unfair, because our FDA was intended to be accurate only for σ which varies smoothly. It does not yet take advantage of the improved FDA's developed for use with topography. However, since the galvanic response is present in any sort of model, it is important to understand these errors and devise a strategy to ensure that they will be small.

The 3D electric field must satisfy

$$\nabla \times \nabla \times E = i\omega\mu_0\sigma E \quad (3.5.1)$$

This equation appears singular as $\omega \rightarrow 0$ because the dependence on σ apparently disappears. However, if we take the divergence of (3.5.1), we get

$$\nabla \cdot \sigma E = \nabla \cdot j = 0 \quad (3.5.2)$$

where j is the current density. As $\omega \rightarrow 0$, Lenz's Law becomes $\nabla \times E = 0$ and hence $E = \nabla\phi$. Thus the single equation (3.5.2), which appears inadequate to determine the vector E , reduces to an equation for a scalar potential that retains its dependence on σ . The actual singularity of (3.5.1) at low frequency is this reduction in the number of independent variables.

When (3.5.1) is solved using an FDA, however, an additional problem arises. Once the left side of (3.5.1) is approximated with an FDA, numerical inaccuracy prevents its divergence from being strictly zero and (3.5.2) becomes

$$\nabla \cdot \sigma E_0 = \nabla \cdot j = F_{\text{error}}(x) \quad (3.5.3)$$

where E_0 is the solution to the FDA approximation to (3.5.1) and x is the 3D position vector. This equation implies that current is not conserved. At the low frequencies of MT for which displacement currents are negligible, this is physically inaccurate.

It might appear that one could gain something by re-formulating the problem using the magnetic field, B , because it satisfies

$$\nabla \times \frac{1}{\sigma} \nabla \times B = i\omega\mu_0 B \quad (3.5.4)$$

which appears to behave better as $\omega \rightarrow 0$. However, the ill-conditioning remains as one can easily see by noting that (3.5.1) and (3.5.4) involve identical operators in the case where σ is constant. Also, at low frequency, the Biot-Savart Law requires that

$$\nabla \times \mathbf{B} = \mu_0 \mathbf{j} \quad (3.5.5)$$

and there is no guarantee that $\nabla \cdot \mathbf{j} = 0$ when an FDA solution is used to estimate the left hand side of (3.5.5). Furthermore, our ability to accurately calculate $\mathbf{B}$ is diminished by the necessity of approximating the gradients of σ^{-1} in (3.5.4).

The failure of current conservation in numerical approximations to Maxwell's equations has already been noted in studies of resonant cavities [e.g. Webb, 1985]. Webb identifies spurious modes by adding a term $S \nabla \nabla \cdot \sigma \mathbf{E}$ to the left side of (3.5.1). This added term should be zero for modes that conserve current, but will result in a change of frequency as S varies for resonant modes that do not conserve current. We plan to use a somewhat different approach inspired by Madden and Mackie [1989]. They have found that an iteration of an algorithm which involves a different numerical approximation (and hence different errors) can very effectively reduce problems associated with fields to which the FDA equations are relatively insensitive. We propose to insert occasional steps in our iterative algorithm that use an approximate Green's function method to enforce galvanic (low frequency) current conservation.

As already noted, at low frequency (3.5.3) reduces to

$$\nabla \cdot \sigma(\mathbf{x}) \nabla \phi = F_{\text{error}}(\mathbf{x}) \quad (3.5.6)$$

In principle, one could calculate $F_{\text{error}}(\mathbf{x})$ from the FDA solution to (3.5.1) and find the particular solution to (3.5.6) using a method such as a Green's function. The corrected field obtained by subtracting this $\mathbf{E}_{\text{error}} = \nabla \phi$ from the FDA solution of (3.5.1) should satisfy (3.5.2) and thus conserve current. If the potential field calculation also involves numerical error, one can improve the solution further by re-calculating $F_{\text{error}}(\mathbf{x})$ for the corrected field and iterating the process.

Calculating Green's functions for (3.5.6) with arbitrary non-uniform conductivity would be computationally intensive so alternative methods are needed. One possibility would be solve (3.5.6) using a separate FDA for ϕ . Since ϕ is a scalar, this should take a fraction of the time needed to solve (3.5.1). A second method can be deduced by re-writing the left side of (3.5.3) as

$$\nabla \cdot \sigma \mathbf{E} = \sigma [\nabla \cdot \mathbf{E} + \frac{\nabla \sigma}{\sigma} \cdot \mathbf{E}] \equiv 4\pi\epsilon_0 \sigma [\rho - \rho_{\text{galvanic}}] \equiv 4\pi\epsilon_0 \sigma \rho_{\text{error}} \quad (3.5.7)$$

where ρ is the physical charge density, ρ_{galvanic} is the effective charge density associated with gradients of σ and ρ_{error} is an apparent charge density due to the failure of current conservation. For σ constant and $\mathbf{E} = \nabla \phi$, (3.5.7) reduces to Poisson's equation for ϕ . Thus an estimate of $\mathbf{E}_{\text{error}}$ for $\omega \rightarrow 0$ can be almost trivially calculated from ρ_{error} using the Green's function for constant σ and homogeneous boundary conditions. Since this is only approximate in regions where σ varies spatially, iteration will be essential. Based on the experience of Mackie and Madden we expect that this iterative correction for failure of galvanic current conservation will be required only occasionally within the sequence of ICCG iterations used to solve the linear system of equations resulting from the FDA of (3.5.1). This supposes that $\mathbf{E}_{\text{error}}$ grows slowly with

each iteration and that E can be brought back on track with only an occasional correction, an assertion that must be verified.

3.6. Quasi-3D Inversion

Fully 3D inversion requires a distribution of data that adequately samples the 3D structure. Adequate sampling of the structure in 2D already involves data sets which strain the capabilities of existing data collection. It is unlikely that the third dimension will be routinely sampled without some further technological breakthrough. Wannamaker, *et al.* [1984] provide evidence that the TM response of a 2D slice through a 3D structure is often very similar to the 3D response with the same polarization. Thus 2D TM inversion can be expected to be quite useful even in 3D environments. However, we have already noted that the TM mode can be insensitive to important classes of structure and that incorporation of the TE mode, which is highly sensitive to structure in the cross-profile direction may be necessary. Often we will be able to make estimates of the 3D effects. For instance, we may have geologic constraints that allow us to assume reasonable along strike variations of the structure determined along a 2D profile. In our proposed USGS/NSF work in the Puget Sound region, there are good reasons to suppose that 3D effects associated with the deep sedimentary basins and complicated surface layer of salt water will be significant. To directly estimate them, we will deploy a magnetometer array that will permit inverting for lateral variations of integrated surface conductance. It is therefore of considerable interest to be able to do 2D inversions that permit direct incorporation of corrections for specified 3D effects.

The 3D electric field satisfies

$$\nabla \times \nabla \times \mathbf{E} = i\omega\mu_0\sigma\mathbf{E}$$

In rectangular Cartesian coordinates with the source electric field polarized in the x direction, this can be written

$$\frac{1}{E_x} \frac{\partial^2 E_x}{\partial z^2} + \frac{1}{E_x} \frac{\partial^2 E_x}{\partial y^2} + i\omega\mu_0\sigma(x,y,z) = \frac{1}{E_x} \left[\frac{\partial^2 E_y}{\partial x \partial y} + \frac{\partial^2 E_z}{\partial x \partial z} \right] \quad (3.6.1)$$

Evaluating this equation along a 2D slice in the y direction at x_0 gives

$$\frac{1}{E_x} \frac{\partial^2 E_x}{\partial z^2} + \left\{ \frac{1}{E_x} \frac{\partial^2 E_x}{\partial y^2} \right\} + i\omega\mu_0\sigma(x_0,y,z) = Q_{\text{source}}(x_0,y,z) \quad (3.6.2)$$

The iterative RRI method for 2D assumes that the apparent source $Q_{\text{source}} = 0$ and approximates the term in curly brackets on the left using the field from the previous iteration. To incorporate a correction for 3D effects in a 2D inversion, one needs to estimate the apparent source function and incorporate it in the 2D forward solution of (3.6.2). One can think of a series of progressively more complicated assumptions regarding Q_{source} . The simplest would be to estimate it for an initial starting model which incorporates the 3D variation one requires and then keep it constant. A somewhat more complicated assumption would involve updating a 3D model after a series of 2D RRI iterations, using the 2D slice conductivity and an assumption about how to extrapolate this 2D conductivity along strike. This would be followed by a 3D forward solution of (3.6.1) to improve Q_{source} . Obviously this could lead to an alternate

way to do the fully 3D inversion if the 3D variation is constrained by a series of parallel 2D slices rather than some assumption about the 3D variation.

3.7. Electromagnetic Migration

We think that electromagnetic "migration" or holography has a significant, but unrealized potential for electromagnetic imaging. The original references are mostly in Russian (see Zhdanov and Frenkel, 1983; and Zhdanov, 1988 for English treatments and references to the Russian literature) and not widely appreciated because of their mathematical formalism. However, the physical basis is actually very simple.

At the earth's surface, we measure the combination of the external electromagnetic source field, which is propagating downwards into the earth and fields that are propagating upwards and can be thought of as having been scattered back from internal structure. All the fields obey diffusion-like equations inside the earth. Their amplitudes decay and their phases are retarded in the direction of propagation (downward for the source fields and upward for the back-scattered fields). Given measurements of the electric and magnetic fields at the surface, it is theoretically possible to separate the fields of internal and external origin. Leaving aside the practicality of this separation, we can use the measured surface field of internal origin to reconstruct information about the field inside the earth in two different ways.

First, we could extrapolate the received signal back to reflectors or internal currents by undoing the upward diffusion of the original internal signal. This can be accomplished by thinking of the received signals as "pseudo-sources" and reversing the sign of time in the governing equations. This has been called "analytic continuation" by Berdichevsky and Zhdanov [1984], but we prefer to call it "back-propagation". Lee, *et al.* [1987] note the close parallel that can be drawn with seismic migration and use the electromagnetic equivalent of Claerbout's [1976] one-way wave equation algorithm to very efficiently solve the back-propagation problem for small conductivity contrasts and nearly horizontal internal structure. However, the encouraging results of Lee, *et al.* can be attributed to using accurate synthetic data. Unlike the wave equation, reversing the sign of time in the diffusion equation produces a new differential equation called the adjoint of the diffusion equation. The solution of the adjoint equation grows in amplitude in the direction of backward propagation and is therefore numerically unstable. Small scale noise in the surface boundary conditions will be rapidly amplified downwards and destroy the coherence of the back-propagated signal. This instability can, to some extent, be mitigated by a "regularization" or smoothing assumption which limits the growth of small scale perturbations (see Berdichevsky and Zhdanov [1984]).

Alternatively, we could allow the pseudo-source signals to propagate into the earth according to the diffusion equation rather than its adjoint. The *amplitude* of this "diffused" signal will decay downwards and will be very different from the internal signal which gave rise to the data in the first place. The utility of the diffused signal arises from two facts: (1) The *phase* evolution of the diffused signal is the same, except for a sign, as the phase evolution of the back-propagated signal. If desired, the sign of the phase evolution for the diffused and back-propagated fields can be made identical by reversing the time flow for the observed surface fields and having the

fields inside the earth obey the diffusion equation in reversed time (not its adjoint). Zhdanov and his coworkers call these diffused reversed time fields "migration fields". (2) Noise decays downwards. In the absence of noise, the phase of the migrated or back-propagated signals can be used interchangeably to image internal structure. In the presence of noise and/or small scale shallow structure, the phase of the diffused or migrated signals can be calculated more stably than the phase of the back-propagated signal.

Figures 5(a) and 5(b) show simple illustrative synthetic examples. In both cases, the downward (z) propagating electric source field $E_D(x,z)$ (polarized perpendicular to the profile) and its upgoing back-scattered response $E_U(x,z)$ were calculated in the model for plane wave illumination at ten frequencies between 1 and 5 Hz using a 2D finite difference algorithm.

Figure 5(a) involves a low angle slanted step in a single interface. (Note the large vertical exaggeration.) The migrated field $E_M(x,z)$ corresponding to the surface values $E_U(x,0)$, was calculated in a halfspace corresponding to the upper medium. The migration algorithm was very similar to the back-propagation of Lee, *et al.*, except that the sign of the propagation constant was reversed. A normalized complex reflection coefficient

$$\alpha(x,z,\omega) = \frac{E_M/E_D}{|E_M/E_D|}$$

was calculated for each position (x,z) and frequency, ω . Since the fields are dispersive, the phase of α will be significantly frequency dependent except at an interface (or other region of high conductivity gradient), where it will be approximately independent of frequency. Thus stacking α for a spectrum of frequencies results in positive reinforcement at interfaces and destructive interference elsewhere. The plot shows a normalized, stacked apparent reflection coefficient

$$\alpha^* = \epsilon \left| \sum_i \alpha(\omega_i) \right|$$

where ϵ is a constant chosen for plotting purposes. The local maximum in α^* almost coincident with the actual interface clearly demonstrates the phase coherence of the migrated field near the reflector.

The second case, Figure 5(b) involves local upward displacements in the interfaces of a three layer model. (Again, note the large vertical exaggeration.) The position of the upper interface was estimated in exactly the same way as for figure 5(a). The resistivity of the second layer was estimated from the data, assuming that the interface position corresponded to that predicted by the migration. The surface signal was then migrated downward through the estimated two-dimensional structure. The final stacked α^* is plotted. Both interface perturbations have been imaged (with finite resolution) and it is interesting to note that the structure of the upper interface appears to have produced negligible distortion of the image of the lower interface. This presumably is because diffusion in the migrated field has largely smoothed out the local wrinkle in the phase fronts due to the structure of the upper interface before they reach the second interface.

Figure 5. (a) to the left and (b) to the right. Note the large vertical exaggeration.

Part of the excellent success of these exercises is due to the ease with which the layer resistivities can be estimated from the accurate data. Although noise in the migrated field damps out as one descends into the model, noise in the data will definitely impact one's ability to determine the model in which to do the migration. We therefore envision using RRI or some other structure minimizing inversion to determine smooth, large scale structure and then migration to locally sharpen the focus of the image.

Practical application of electromagnetic migration involves several challenges. It is first necessary to obtain suitable data. This requires spatially dense measurements that preserve the inter-site phase relations. Fortunately, the almost universal use of remote references for magnetotellurics and the growing acceptance of multi-site acquisition strategies such as EMAP, mean that the required data can be obtained with relatively minor modifications to existing practice. The second problem is separation of the internal and external parts of the signal. This probably cannot be done with complete generality for natural sources, because it requires complete, accurate knowledge of the lateral variation of the surface fields. However, there are a variety of ways of separating the field into the external field plus the internal field for structure with scale larger than of interest and the anomalous field due to smaller scale structure to be imaged using migration. One of the oldest and simplest methods would be to subtract the signal at a "normal" site, but more optimal methods almost certainly exist.

Once appropriate data have been measured and transformed to pseudo-sources, it is necessary to calculate the migrated fields. This is easy for a half-space, not particularly difficult for one-dimensional structures or weakly laterally varying structures (using the method of Lee, *et al.*) and at least conceptually possible for general structures. However, it remains to be seen under what circumstances migration in simple or incorrect models is useful for imaging complex structure and whether numerically efficient algorithms can be found for computing the migration fields in complex structure.

Finally, one needs to understand how to deal with contamination by the galvanic response. The examples above used the TE mode, which eliminates the possibility of any galvanic component in the response. The galvanic response is essentially a potential field (see discussion in section 3.5) rather than a solution of the time-dependent diffusion equation and cannot be migrated (its phase is independent of frequency). Restricting the bandwidth to higher frequencies will help, but is not a totally satisfactory solution because it limits the practical depth of penetration. In addition, there are many kinds of structures that have galvanic effects even at high frequency (e.g. a vertical contact which reaches the surface). Spatial filtering of the TM response prior to migration in a manner related to the EMAP processing of Torres-Verdin and Bostick [1991] offers a possible approach because it suppresses the galvanic response. However, a method that retains the lateral resolution inherent in the galvanic response remains to be elucidated.

Despite the difficulty of migration in general, there are situations that can maximize probable success which are highly relevant to the goals of the Underground Imaging Program. For instance, controlled source measurements clearly have the advantage over natural field methods in that both the geometry and phase of the source are prescribed. Furthermore, there is no limitation on the geometry of the receivers and

hence the pseudo-sources. They can just as easily be located in wells as on the surface and migration appears to be an attractive image construction method for single hole (i.e. electromagnetic logging), hole-to-hole or hole-to-surface data. Finally, at the smaller scales relevant to waste site characterization, mining and geothermal prospect assessment and enhanced recovery of oil, an assumption that the background conductivity is known or at least not complicated, may either be very good or contribute usefully small errors to the image. This should greatly simplify computational problems.

4. Proposed Tasks

The following list of tasks probably constitutes a research program that will ultimately take more than the two years of support that we are requesting. However, we feel that we can make substantial progress on all of them.

I. Improving 2D RRI involves the following tasks:

- (1) Modifying the program to allow structural constraints including:
 - (a) Vertical profiles that are frozen in a limited depth range
 - (b) Layers with fixed conductance
 - (c) Vertical structure with a finite number of discontinuities that may be fixed or variable in position
- (2) Completing code to use data that are horizontal averages of measured data.
- (3) Completing code for calculating fully 2D partial derivatives
- (4) Applying (2) and (3) to:
 - (a) RRI of vertical magnetic fields
 - (b) Improved RRI of the TM mode
 - (c) RRI of EMAP filtered data
- (5) Developing numerically efficient resolution analyses and testing the limits of the linear assumption.
- (6) Modifying the 2D forward algorithm to incorporate source terms due to known 3D effects.
- (7) Incorporating surface topography in the inversion.

II. Bringing 3D RRI inversion to fruition requires the following specific steps:

- (1) Modifying the 3D FDA forward algorithm to enforce galvanic current conservation and verify its accuracy against computations with other numerical schemes.
- (2) Bringing all the pieces of the 3D code together.
- (3) Devising better display mechanisms for viewing 3D models and data misfits. We are presently using color slices.
- (4) Testing the algorithm on accurate and then noisy synthetic data.

III. Our proposed research on electromagnetic migration is aimed very specifically at determining whether it can be made a *practical* tool. This includes:

- (1) Devising optimum methods for constructing surface boundary conditions (pseudo-sources) from data that are noisy and spatially incomplete.
- (2) Investigating the effects of data noise on various imaging schemes that use the migrated field.
- (3) Examining the effects of migration in incorrect models.
- (4) Investigating the effects of substantial galvanic response in the fields to be migrated.
- (5) Developing algorithms for efficient migration in complicated 2 and 3D models. We expect that these will be related to our existing efficient solutions of the full governing equations.
- (6) Extension of the approximate back-propagation solution of *Lee, et al.* [1987] to the case where data is measured on boundaries surrounding the region of interest.

5. Budget Discussion

The 2D portion of the research will be done by the P.I. and three graduate students, Nong Wu, Jeff Knickerbocker and Claudia Aprea. Support for only one full student equivalent is requested because these students will also be partially supported by other grants involving collection and analysis of field data. Jeff Knickerbocker will receive most of the requested student support.

The completion of the 3D RRI algorithm is the primary responsibility of Post-Doctoral Research Associate Torquil Smith. His position will terminate when the requested support for his salary is exhausted. He is actively seeking a permanent position elsewhere. Should he accept a position in an academic institution, arrangements will be made to subcontract the unexpended portion of his salary so that he can complete the work in his new situation. If he takes a non-academic position and substantial salary remains, we will seek a person of similar experience and interests or support an advanced graduate student capable of undertaking the required tasks.

Instead of the part-time post-doctoral position, we are requesting salary support for Dr. Michael Zhdanov during the second year. He is perhaps the Soviet Union's leading scientist in the field of electromagnetic imaging and will visit the University of Washington during leave from his positions in Moscow. We are also requesting round-trip transportation for him from Moscow to Seattle. The amount requested is the full price round trip air fare for a passenger originating in Moscow. This is unfortunately substantially more expensive than the excursion fares available for a passenger originating in the U.S. and staying for a short time in the U.S.S.R. If we are successful in obtaining a less expensive fare, the difference will be used to support other travel by Dr. Zhdanov (for instance to professional meetings and institutions doing related imaging research). We will be requesting additional support from the University of Washington and industrial sources to enable him and his family to spend the full academic year in Seattle.

We have been informally cooperating with Dr. Zhdanov for some time regarding the theoretical basis for rapid inversion of MT data and he is, together with his student Frenkel, the inventor of electromagnetic migration. His skills as an applied mathematician complement ours in numerical techniques and data analysis and we believe that a period of more formal cooperation in an atmosphere that removes him from his considerable administrative burdens would be of great benefit to our research goals and to U.S. electromagnetic imaging research in general. Although he is widely known and respected in the U.S. geomagnetic induction community, we are including his resume for information. We note that since this resume was prepared, he has been elected to the newly formed Academy of Sciences of the Russian Republic.

Most of the computation associated with the proposed work will be carried out on the SUN SparcStations (there are presently seven) at our disposal. The departmental system support and policy of upgrading machines with time, coupled with recharge rates that are very favorable to numerically intensive users such as ourselves make our computing environment very cost effective. We also have use of a university owned IBM 3090 for tasks that exceed the reasonable capability of the workstations. CPU time on the 3090 is currently free. Should this situation change, we will probably request time on a DOE supported supercomputer at one of the National Labs. Since our research is closely related to NSF supported research, we also can request time on one of the NSF supported machines.

6. References

- Aprea, C., J.R. Booker and J.T. Smith, The forward problem of electromagnetic induction: accurate finite difference approximations for discrete boundaries with arbitrary geometry. *Geophys. J. Int.*, submitted.
- Barashkov, A.S., Interpretation of magnetotelluric sounding data in the class of quasi-one-dimensional models, *Izvestia, Earth Physics*, 21, 767-774, 1985.
- Berdichevsky, M.N., and M.S. Zhdanov, *Advanced Theory of Deep Geomagnetic Sounding*, Elsevier (Amsterdam), 408 pages, 1984.
- Claerbout, J.F., *Fundamentals of geophysical data processing*, McGraw-Hill (New York), 1976.
- deGroot-Hedlin, C. and S.C. Constable, Occam's inversion to generate smooth, two-dimensional models from magnetotelluric data, *Geophysics*, 55, 1613-1624, 1990.
- Egbert, G.D. and J.R. Booker, Very long period magnetotellurics at Tucson Observatory: Implications for mantle conductivity, *J. Geophys. Res.*, submitted, 1991.
- Johnston, J.M. and P.E. Wannamaker, Magnetotelluric transect of the Sevier overthrust belt in southwestern Utah and eastern Nevada, *Utah Geological Association*, in press, 1991.
- Jupp, D.L.B. and K. Vozoff, Two-dimensional magnetotelluric inversion, *Geophys. J. Roy. Astron. Soc.*, 50, 333-352, 1977.
- Knickerbocker, J. and J.R. Booker, Removing static shift from magnetotelluric data: Application to an EMAP across the Wind River Thrust, in preparation, 1991.

- Lee, S., G.A. McMechan, and L.V. Aiken, Phase-field imaging: The electromagnetic equivalent of seismic migration, *Geophysics*, 52, 678-693, 1987.
- Parker, R.L., The inverse problem of electromagnetic induction: Existence and construction of solutions based upon incomplete data, *J. Geophys. Res.*, 85, 4421-4428, 1980.
- Smith, J. T., and J. R. Booker, Magnetotelluric inversion for minimum structure, *Geophysics*, 53, 1565-1576, 1988.
- Smith, J. T., and J. R. Booker, Rapid Inversion of Two- and Three-Dimensional Magnetotelluric Data, *J. Geophys. Res.*, 96, 3905-3922, 1991.
- Torres-Verdin, C. and F.X. Bostick, Jr., Principles of spatial surface electric field filtering in magnetotellurics: Electromagnetic Array Profiling (EMAP), *Geophysics*, in press, 1991.
- Wannamaker, P.E., G.W. Hohman and S.H. Ward, Magnetotelluric responses of three-dimensional bodies in layered earths, *Geophysics*, 49, 1517-1534, 1984.
- Wannamaker, P.E., J.R. Booker, A.G. Jones, A.D. Chave, J.H. Filloux, H.S. Waff and L.K. Law, Resistivity cross-section through the Juan de Fuca subduction system and its tectonic implications, *J. Geophys. Res.*, 94, 14,127-14,145, 1989.
- Wannamaker, P.E., J.A. Stodt, and L. Rijo, Two-dimensional topographic responses in magnetotellurics modeled using finite elements, *Geophysics*, 51, 2131-2144, 1986.
- XP Webb, J.B., The finite element method for finding modes of dielectric loaded cavities, *IEEE Trans. Microwave Theory Tech.*, MTT33, 635-639, 1985
- Wu, N. and J.R. Booker, Conductivity structure across the Trans-Hudson Orogen, in preparation, 1991.
- Zhdanov, M.S., and M.A. Frenkel, Solution of inverse problems by analytical continuation of a transient electromagnetic field in reverse time, *J. Geomag. Geoelectr.*, 35, 747-765, 1983.
- Zhdanov, M.S., *Integral Transforms in Geophysics*, Elsevier (Amsterdam), 367 pages, 1988.

END

DATE
FILMED

6/9/93