LEGIBILITY NOTICE

A major purpose of the Technical Information Center is to provide the broadest dissemination possible of information contained in DOE's Research and Development Reports to business, industry, the academic community, and federal, state and local governments.

Although a small portion of this report is not reproducible, it is being made available to expedite the availability of information on the research discussed herein.

DE89 002241

 

SUBMITTED TO: 1988 American Nuclear Society Conference, Salt Lake City, UT
October 10-13, 1988

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

The Los Alamos National Laboratory requests that the publisher identify this article as work performed under the auspices of the U.S. Department of Energy.

MASTER

Los Alamos Los Alamos National Laboratory
Los Alamos, New Mexico 87545

A MEGAJOULE CLASS KRYPTON FLUORIDE AMPLIFIER FOR SINGLE SHOT, HIGH GAIN ICF APPLICATION

**Evan Rose, David Hanson, Burton Krohn, John McLeod, Michael Kang
Los Alamos National Laboratory**

ABSTRACT

A design study is underway to define the optimal architecture for a KrF laser system which will deliver 10 MJ of 248-nm light to an ICF target. We present one approach which incorporates final power amplifiers in the megajoule class, achieving 10 MJ with four final amplifiers. Each double-pass laser amplifier employs two-sided electron-beam pumping of the laser gas medium. Details of the design are based on a Monte-Carlo electron-beam deposition code, a one-dimensional, time-dependent kinetics code, and pulsed power circuit modeling. Linear dimensions of the amplifier's extracted gain volume are 6.25 m in height and length and 5.12 m in width. Each amplifier handles 160 angularly multiplexed laser channels. The one-amagat, krypton-rich laser medium is e-beam pumped at 60-kW cm^{-3} (4-MA @3.3-MV) over the 2-microsecond duration of the laser beam pulse train.

INTRODUCTION

Current KrF laser technology has produced a 10-kJ amplifier¹ at the Aurora facility at Los Alamos National Laboratory. One possible 10-MJ facility architecture would utilize 10-kJ-class amplifiers to meet mission requirements. Although individual amplifiers would be reliable, the facility would be required to manage on the order of one thousand units in a complicated,

three-dimensional layout. Simplification of the system architecture can be achieved with larger amplifier modules. An extreme amplifier size, the megajoule module, is considered in this paper and its companion "Optical Architecture for a Multi-megajoule ICF Driver Incorporating Megajoule Class XrF Amplifiers."

SCALING TO A MEGAJOULE CLASS AMPLIFIER

Several simple scaling laws dictate the design of a megajoule amplifier module:

1. Extracted laser energy per unit volume is roughly constant. Thus the number of amplifiers varies as the inverse of amplifier volume, or the cube ~~root~~ of amplifier linear dimension.

2. Gain-length product is optimized at a value of three (gain = 20). Lower gains underutilize the amplifier, and higher gains cause problems with parasitics. Thus pumping power per unit volume of laser medium varies inversely as length (linear dimension); and pumping duration varies linearly with length (as the cube root of volume).

3. For a given fluence at the amplifier window, the total number of beam channels varies inversely with amplifier area (varies as the inverse square of the linear dimension).

A short synopsis of the design logic follows:

Standard (inexpensive) optical elements in the facility's architecture are to be nominally meter-diameter, with a useful area of 4000 cm^2 and energy-handling capacity of 4 J cm^{-2} , for an energy of 16 kJ per beam channel. Output intensity of the amplifier is chosen to be 4 MW cm^{-2} (2.78 Isat), requiring a

32-m² window to produce a 16-kJ, 12.5-ns laser beam. Choosing an amplifier aperture of 6.25-m height and 5.12-m width satisfies this requirement. The length is chosen to be 6.25 m (same as height) to minimize unextracted volume for the angularly multiplexed scheme. Modeling indicates that 13 J/liter can be extracted from the KrF lasing medium at one amagat, giving an extracted total energy of approximately 2.6 MJ, or one fourth of the 10 MJ required for the facility. Thus only four final amplifiers will be required.

Each amplifier will be required to operate for two microseconds to extract 160 beams of 12.5-ns duration and 16-kJ energy each. The required electron-beam pump power is about 65 kW cm⁻³, assuming an intrinsic power efficiency of 10%.

KINETICS MODELING

Laser amplifier operation was modeled with a one-dimensional, time-dependent kinetics code². This code handles two- and three-body collisions and electron and photon interactions with a specified mix of krypton, argon, and fluorine. Amplifier geometry is treated in the direction of laser beam propagation. Temporal profiles are specified for the electron-beam pump power and the laser input pulse intensity to obtain the laser output pulse intensity profile.

For a 10% Kr / 0.22% F₂ / balance Ar mixture at 54 kW cm⁻³ pump power, 4 MW cm⁻² output intensity is obtained (Figure 1). A 30% increase in pump power or a 50% decrease in fluorine content results in severe loss in gain at the end of the pulse, caused by fluorine burn-up. On the other hand, a 50% increase in fluorine

content decreases the gain by increasing absorption losses. Thus the amplifier performance is sensitive to fluorine inventory. Risetime and spatial non-uniformities of electron-beam pumping should be minimized.

A second case was run for a 99.75% Kr / 0.25% F₂ mixture (Figure 2). To obtain 4 MW cm⁻² output intensity, 60 kW cm⁻³ pump power is required.

Electron-beam pumping of the KrF medium was modeled with a three-dimensional Monte Carlo electron-beam energy deposition code³. The code incorporates electron beam scattering and energy loss in the presence of magnetic fields and allows the beam to pass through a foil and interact with the walls of the laser chamber. The code as run for this study did not include collective effects from the electron beam current.

The energy deposition code is vital for design of the pulsed power, indicating the voltage and current levels necessary to achieve the laser operation predicted by the kinetics code.

Electron-beam energy deposition was modeled for a 10% Kr / 90% Ar case and for a 100% Kr case at one amagat with a 2-mil titanium diode foil in the presence of a 5-kG magnetic field (Figure 3). The figures show electron-beam energy deposition across the laser cavity, integrated over height and length. A titanium foil forms the boundary on the left and right edges of the figures. The deposition is given in units of kW cm⁻³ per Amp cm⁻², which is equivalent to kV/cm lost per electron.

For the 10%-Kr case, approximately 1.8 MV appears optimal for uniform pumping. At 3 MV uniformity is also good; at higher

voltages foil heating from electrons which pass through the full gas depth becomes a factor. For the 99+% krypton case, approximately 3.3 MV appears optimal for uniform pumping, with another region of uniform pumping expected above 5 MV.

ELECTRON BEAM DIODE

The laser driver consists of two opposing electron beam diodes in vacuum. Typical diodes utilize a field-emission cold cathode (a planar surface coated with carbon felt or velvet), which faces the anode across an anode-cathode (A-K) gap. The current density produced by this type of diode is determined by the A-K gap and the applied voltage. The Child-Langmuir law, $J = k V^{1.5} D^{-2}$ (current density J , electric potential V , A-K gap D) is used for the non-relativistic case. For the relativistic case⁴ current density is reduced, by 22% at 1.8 MV and 32% at 3.3 MV.

Operation of the diode is time-dependent, with a plasma layer forming on and expanding from the cathode and anode. The expansion of the plasma layer reduces the effective A-K gap and causes the current density to increase (diode impedance decrease) late in the pulse. The rate of effective A-K gap reduction is the closure velocity, which becomes larger with imposed magnetic field. A figure of $4 \times 10^8 \text{ m s}^{-1}$ is used in our study.

Propagation of the electron beam across the diode is complicated by the magnetic field induced by the beam. This self-field tends to pinch the electron beam and distort its shape and affect its propagation, most strongly at the edges where the field is highest. Standard practice is to provide a guide

magnetic field in the beam direction to reduce these effects. A figure of 1.5 times the self-field is used in our study.

At the interface between the vacuum of the diode and the gas of the laser chamber there is a foil and a support structure (hibachi), which consists of a series of metal ribs. Transmission through the foil and hibachi is critical for pumping efficiency. High transmission is achieved by reduction of the hibachi rib cross section to a minimum and the application of a magnetic field to modify electron trajectories to be more normal to the foil/hibachi structure. A figure of 50% hibachi transmission is used in this study.

There are problems associated with the operation of such a large electron diode which need further study. High self-fields may force cathode segmentation. Diode closure and the impedance reduction it causes increase requirements on the pulsed power system. Large cathodes require strong hibachi structures, which reduce transmission.

PULSED POWER

The implications of the energy deposition code results and hibachi transmission for pulsed power are straightforward. Operation at 1.8 MV requires a 0.3-ohm impedance diode (16.5-cm A-K gap, 3.5-kG self-field) and associated pulsed power driver, while operation at 3.3 MV requires a 0.85-ohm system (31-cm A-K gap, 2.2-kG self-field). The higher voltage, higher impedance system was chosen, since it reduces constraints on the pulsed power system, especially for system inductance and current-feed geometry.

A pulse compression scheme using water lines was considered for the 3.3-MV device. With four lines per side operating at a 1:1000 failure rate per side, each line would be 40 m long and 6.7 m diameter (larger than the diode). A system of eight lines would be 4.5-m diameter lines. Drawbacks to this system include the long time spent at high voltage (several times the 2-microsecond operation time) and the need to operate the lines at twice 3.3-MV into a matched load.

A second scheme uses a 3-section type-C Guillemin pulse-forming network (PFN). This system and waveforms are shown in Figure 4. The first harmonic section of the PFN uses Marx capacitor banks similar to the PBFA-II 6-MV banks⁵, the equivalent of 60 in parallel. Third and fifth harmonic PFN sections use the same Marx bank layout and are tied to the first harmonic at each switch and charging feed. The feed structure of this large PFN (tens of meters on a side) is not modeled.

One drawback of using a PFN with only three sections is the oscillation in delivered pump power. However, unlike the water lines, the PFN experiences a maximal voltage that is the same as the matched load (3-MV range) for the same time that the diode is run.

CONCLUSIONS

A preliminary study of a multi-megajoule amplifier for a 10-MJ system has been performed. The complexity of a system built with 10-kJ amplifiers is in number and three-dimensional architecture. For a system built with MJ amplifiers the

complexity is in the pulse-forming networks and the diode operation.

- 1 L. A. Rosocha et al., "Aurora Multikilojoule KrF Laser System Prototype for Inertial Confinement Fusion," Fusion Technology, **11**, 497 (1987).
- 2 S. J. Czuchlewski et al., "KrF Laser Optimization," Fusion Technology, **11**, 560 (1987).
- 3 J. C. Comly, Jr., et al., "Discharge and Kinetics Modeling in Electron-Beam Controlled CO₂ Laser Amplifiers," IEEE Journal of Quantum Electronics, **17**, 1786 (1981).
- 4 H. R. Jory and A. W. Trivelpiece, "Exact Relativistic Solution for the One-dimensional Diode," Journal of Applied Physics, **40**, 3924 (1969).
- 5 D. L. Johnson et al., "PBFA II Conceptual Design," 4th IEEE Pulsed Power Conference, 54 (1983).

FIGURE 1:

FIGURE 2

E-BEAM PUMPING -- LMF DESIGN

LMF Model Electron Energy Absorption

3 SECTION GUILLEMIN TYPE C NETWORK

3 SECTION GUILLEMIN TYPE C NETWORK

3 SECTION GUILLEMIN TYPE C NETWORK

FIGURE 4