Rockwell International
Rocketdyne Division

MASTER

CONTRACT E(04-3)1155

BIMONTHLY REPORT

NOVEMBER-DECEMBER 1976

ACD3-76DP01155

This report covers the bi-monthly period ending
1 January 1977. Progress made on the technical
effort to predict and generate the forces required
to move microspheres and microballoons on the surface
of surface acoustic wave line is presented in attached
Report C76-993.3/501 (Electronics Research Division).

APPROVED BY

S. V. Gunn for

S. V. Gunn
Program Manager
Special Programs

ROCKWELL INTERNATIONAL, ROCKETDYNE DIVISION
6633 Canoga Avenue
Canoga Park, Ca. 91304

see letter dtd Feb. 1, 1977 1155/8-1

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency Thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

Amended

Second Bimonthly Report

MICROSPHERE SEPARATION TECHNIQUES

During this period an analytical model was developed to predict the power density needed to move the microballoons across the surface of a surface acoustic wave line. This model predicted superior performance with a bismuth germanium oxide $\text{Bi}_{12}\text{GeO}_{20}$ substrate as compared with a quartz substrate. Transducers were placed on both materials but motion was observed on only the BGO substrate.

An aerodynamic model was developed to predict the size separation of microspheres, and experiments were carried out to test the theory. This process, referred to in the literature as elutriation, provided knowledge in the handling of the microballoons in closed, air blown systems. This led to the development of a controllable particle feed device.

Finally, microballoons were placed on the surface of a BGO line in an inverted geometry and were removed using surface acoustic waves. Removal occurred at a relatively low power for large microballoons indicating the presence of resonant behavior. In the normal geometry (particles on top of the substrate) the microballoons behaved as did the microspheres. That is, they were moved across the surface with a retrograde motion, and they agglomerated as the particles "bumped" into one another.

Discussion

In the first bimonthly report, an adhesion model for electrification was developed. Previously, this model postulates that the charge

DISCLAIMER

This book was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

of a particle is dependent on the radius of the particle and the Young's modulus of the material making up its composition. The charge is confined, in a good insulator such as glass, to the area of contact.

Using this model it is now possible to calculate the velocity the particle would have to acquire from a surface wave to escape the surface. Using Coulomb's law, and ignoring aerodynamic forces, the particle is held to the surface by a force

$$-F = \frac{-q^2}{4\pi\epsilon z^2}, \quad (1)$$

where q is the contact induced charge,
 z is the distance separating the contact areas, and
 ϵ is the dielectric constant.

A force applied to the particle opposed to the force of attraction could be written as

$$F = ma = m \frac{dv}{dt} = m \frac{dv}{dz} \cdot \frac{dz}{dt} = mv \frac{dv}{dz} \quad (2)$$

Setting equation (1) equal to this form of Newton's law allows a separation of variables into the integral expression

$$\int_{V_{\max}}^v mvdv = \int_{\delta}^z \frac{-q^2}{4\pi\epsilon z^2} dz \quad (3)$$

which yields

$$V^2 = V_{\max}^2 + \frac{q^2}{2\pi\epsilon m} \left(\frac{1}{z} - \frac{1}{\delta} \right), \quad (4)$$

where $V_{\max}$ is the maximum velocity and
 δ is the minimum contact distance of separation.

At large distances, V is real only if

$$V_{\max} \geq \sqrt{\frac{q^2}{2\pi\epsilon m\delta}} \quad (5)$$

which implies that the particle with a velocity equal to or exceeding $V_{\max}$ will never return to the surface due to electrostatic forces alone. In order to acquire this vertical velocity, a sufficient amount of rf power must be provided to drive the surface up and down, and in turn, this vertical displacement must be sufficiently transferred to the particle.

The efficiency with which the vertical momentum of the surface wave is transferred to the microsphere is poor since the area across which momentum must be transferred is a small fraction of the total area of the microsphere. Consider the vertical surface displacement velocity as given by the relation

$$V_z(t) = V_z \cos \omega t. \quad (6)$$

Through part of its cycle, this sinusoidal displacement will act as a net upward force on the particle.

Figure 1. Momentum Transfer Across the Substrate/Particle Boundary

In Figure 1 a surface acoustic wave is moving from left to right beneath a particle. The surface beneath the particle exerts a force given by

$$F(t) = m \frac{dV}{dt} = P \cdot S \quad (7)$$

where S is the substrate/particle contact area and P is the pressure of the surface wave displacement.

The pressure exerted by the surface wave is determined by the effective mass of the substrate in motion. If a layer Δz thick is assumed to be moving with velocity V_z the pressure is

$$P = \frac{\rho \Delta z S \frac{dV_z}{dt}}{S} = \rho \Delta z \frac{dV_z}{dt} \quad (8)$$

where ρ is the density of the substrate.

In the case of surface waves, the displacement of material in the substrate decays exponentially below the surface. Thus a reasonable estimate of Δz

is the Rayleigh wavelength λ_R . Differentiating equation (6) and using the Rayleigh wavelength in equation (8) yields

$$P = \rho \lambda_R \omega V_z \sin \omega t. \quad (9)$$

Substituting this expression into equation (7) yields

$$m \frac{dV}{dt} = \rho S \omega V_z \sin \omega t. \quad (10)$$

The velocity imparted to the particle can now be calculated by integration over the period of upward acceleration, which is a phase angle $\theta = \omega t$, of 270° to 0° . Hence

$$V = \int_{270^\circ}^{0^\circ} \frac{\rho S \lambda_R \omega V_z \sin \omega t}{m} dt, \quad (11)$$

which yields

$$V = \frac{\rho S \lambda_R}{m} V_z. \quad (12)$$

Auld¹ gives the vertical displacement velocity for quartz as

$$V_z = (4.8 \times 10^{-6}) \omega^{\frac{1}{2}} P_R^{\frac{1}{2}}, \quad (13)$$

where P_R is the power of the Rayleigh wave,

and for BGO the displacement velocity is

$$V_z = (4.2 \times 10^{-6}) \omega^{1/2} P_R^{1/2},$$

Using the identity $\omega = 2\pi f$, where f is the frequency, and the fact that surface waves are nondispersive so that $\lambda_R = V_R/f$; where V_R is the Rayleigh wave velocity, equation (12) can be solved for the power as

$$P_R = \frac{m^2 f}{2\pi \rho^2 S^2 V_R^2 (4.8 \times 10^{-6})^2} V^2, \quad [\text{watts/m}] \quad (14)$$

To escape the surface, the particle velocity must equal the escape velocity, $V = V_{\max}$, as given by equation (5).

Finally, the charge is given by the contact model discussed in the previous report. This is $q = \eta e$, where η is the number of elementary charges, and e is the charge on the electron. The number of elementary charges is given by

$$\eta = \frac{1}{4} \sqrt{\frac{S}{2\pi s}} \quad (15)$$

where s is the area of the lattice square, $\sim \delta^2$,

and

$$S = \pi \left[1.1 \left(\frac{\overline{RR}}{R+R} \right)^{1/3} \left(\frac{F}{Y} \right)^{1/3} \right]^2, \quad (16)$$

$$F = \frac{1}{16} \frac{e^2}{2\pi\epsilon s}, \quad (17)$$

where Y is the mean Young's modulus,
 $\bar{R}$ is the average particle radius,
and R is the radius of the particle.

Using equations (5), (14), and (15) through (17) it is possible to calculate the removal power for quartz. Figure 2 shows the removal power needed for microspheres at a surface wave frequency of 10 MHz. The charge of the microsphere is assumed to have been acquired as a member of a dust, whose average radius varied from 12.5 microns to 50 microns. To remove a 50 micron diameter microsphere would require an acoustic power density of about 1000 watts/cm. This is a very high power density, representing a technical challenge to rf source design and to materials capability (as will be discussed later).

Nevertheless, a 10 MHz quartz delay line was built and tested. Maximum power density was estimated to be 1 watt/cm, or three orders of magnitude below the estimate. No movement of particles was observed.

Inspection of equation (14) indicates the importance of the particle's mass. By reducing the mass, as happens in the case of the hollow microballoon, some reduction in the required power is obtained. Figure 3 indicates the expected power a 10 MHz quartz line would need to remove microballoons having a density of 300 Kg/m^3 . A 50 micron microballoon would be removed with a power density of 250 watts/cm.

Further improvement can be gained by increasing the density of the substrate. According to equation (14) the four-fold increase of density

of BGO over quartz would result in a 16-fold reduction in power requirements. However, the slower velocity of BGO somewhat offsets this improvement; nevertheless, Figure 4 shows a considerable improvement gained by BGO in microballoon removal.

The slower velocity can be considered an advantage if the problem is considered in terms of wavelength. For example, the velocity of BGO is half the velocity of quartz. Thus, for the same transducer size, a BGO line would work at half the frequency--a net advantage according to equation (14). Figure 5 is the final plot of a BGO line's effectiveness assuming the same transducer dimensions as the quartz line at 10 MHz. A 50 micron diameter microsphere is removed with a power density of about 50 watts/cm. This is a reduction in required power of almost 2 orders of magnitude from the case of Figure 2.

The transducer designed for the 10 MHz quartz line was placed on a BGO substrate and tested. Particle motion was observed even for microspheres.

The requirement for significant power densities must be considered in light of the practical output powers of real transducers. In particular, the maximum power that can be applied to a transducer is voltage limited. Hickernell, et al², measured the voltage breakdown between interdigital electrodes on various substrates. From his data it would appear that breakdown for a 10 MHz transducer on quartz would occur at 900v. The same transducer on lithium niobate would be about 1200v. The difference is due to the relative dielectric constant of the two materials. Quartz

with a dielectric of 4 would place far more voltage across the air gap than lithium niobate with a dielectric constant of 40. A BGO transducer would probably offer the same high breakdown, since the dielectric constant is similar to lithium niobate.

In general, a surface wave transducer can be represented as a combination of two circuit elements. These elements are a radiation resistance, R_a , represented by the loss of rf power to a surface acoustic wave; and a capacitor of reactance X_c , associated with the interdigital electrode capacitance.

Figure 6. Series Tuned Equipment Circuit

Figure 6 represents the equivalent circuit of an input transducer. Normally the impedance of the transducer is matched to the generator impedance Z_o in an effort to maximize the efficiency of power transfer.

In the present application, the goal is to maximize the power across R_a without concern for the efficiency. The only major concern is to keep the voltage across the transducer below breakdown. In the series tuned

circuit, the inductive reactance tunes out the capacitive reactance at center frequency making the transducer impedance $Z = R_a$. If the generator impresses a voltage of V across the circuit, the current will be

$$I = \frac{V}{R_a}, \quad (18)$$

and the voltage appearing across the transducer V_c is given by

$$V_c = IX_c = \frac{VX_c}{R_a} \quad (19)$$

but Smith³ has shown that the material parameter k or coupling coefficient is related to the circuit parameters by

$$\frac{1}{\omega_o C_s R_a} = \frac{V X_c}{N R_a} = \frac{\pi}{4} \frac{1}{k^2} \quad (20)$$

where C_s is the capacitance of a single finger pair,
 N^s is the number of fingers, and
 $\omega_o = 2\pi f_o$.

Therefore, the voltage across the transducer is minimized by choosing a high coupling coefficient material or by using a very large number of finger pairs (narrowing the bandwidth) or both.

A numerical example will demonstrate the effectiveness of this conclusion. Using an optimized transducer for quartz the following parameters

are obtained at 10 MHz

$$V_c = 1000 \text{ v}$$

$$R_a = 50 \text{ ohms}$$

$$X_c = 2.5 \times 10^3 \text{ ohms}$$

The power across R_a is

$$\begin{aligned} P &= \frac{V^2}{R_a} = \left(\frac{R_a}{X_c} \right)^2 \frac{V_c^2}{R_a} = \frac{R_a V_c^2}{X_c^2} \\ &= \frac{50 (10^3)^2}{(2.5 \times 10^3)^2} = 8 \text{ w} \end{aligned} \quad (21)$$

A transducer on quartz was measured at breakdown and found to have the ability to withstand a 30 v input pulse into a 50 ohm load, yielding an input power of 18 w in good agreement with the above argument.

The same transducer design placed on BGO would yield

$$V_c = 1200 \text{ volt}$$

$$R_a = 200 \text{ ohms}$$

$$X_c = 530 \text{ ohms ,}$$

yielding a power of over 1000 watts. The optimized cut of BGO outperforms quartz in terms of input power by a factor of over 100 times.

To conclude, in terms of driving a microsphere or microballoon a piezoelectric substrate which has high density and low velocity will result in the most efficient transfer of momentum from the surface wave

to the particle. Furthermore, the demand for high power requires the use of the highest coupling coefficient available. Of the surface wave materials currently available, BGO offers the best promise of satisfying these requirements.

Experimental Evidence of Particle Movement

A quartz 10 MHz transducer based on the usual impedance match approach was designed and tested. This transducer, when series tuned, arced at an input power of 25w with an estimated surface wave power of 1w. The transducer arced at the same power level when parallel tuned. In no case was particle movement observed.

The same transducer was placed on a BGO crystal. The crystallographic cut of the crystal was 4.5° off [112], propagating in the [111] direction. Because of its higher dielectric constant it could be series tuned with a minimum of stray capacitance. Figure 7 is an impedance plot of this transducer tuned to a center frequency of 5.95 MHz. The result is almost a perfect match, as illustrated by the experimental bandpass response of Figure 8. The minimum insertion loss is almost 8 dB, as compared with a measured loss of 30 dB for the quartz line. Breakdown into the input measured about 60 w, with an estimated surface wave power of about 15 w. Even though this crystal was not the optimum cut (it was the only crystal big enough to accept the mask), it still increased the available drive power by a factor of 15 over quartz.

Using the BGO delay line, particle movement was readily observed. Movement was retrograde, that is, the particles moved in a direction opposite to the propagation direction of the surface wave. Photograph 1

Supersedes G.R. Form 5301-7560-N

IMPEDANCE OR ADMITTANCE COORDINATES

[illegible]

is a microphoto of particles on the surface prior to the application of power. The particles were relatively uniformly distributed with few particles adhering to one another. Photograph 2 shows the particles after a few seconds of applied power. Under power, the particles glide across the surface until they collide with one or more particles. As time passes more and more individual particles collide with groups of particles and adhere; the result being an agglomeration of particles. The agglomerations also move along the surface, but at a slower rate. Photograph 3 shows the agglomerations entering the driving transducer and coming to rest in a final pile in the center of the transducer.

An attempt was made to quantify the observed phenomena. This was done by inverting the delay line and driving the particles off of the surface. By inverting the delay line in this way, agglomeration of the particles was avoided and the properties of the removed particles could be measured.

Consider the area immediately below the delay line. Into this area will fall all the removed particles present on the line. If this total number is N , then for any increment of rf voltage ΔV a portion of the total number $\Delta N/N$ will be removed. Thus we can define a removal rate as

$$R = \left(\frac{\Delta N}{N} \right) / \Delta V , \quad (22)$$

or a removal rate percentage as

$$R\% = \left(\frac{\Delta N}{N} \times 100\% \right) / \Delta V . \quad (23)$$

PHOTOGRAPH 1. Particles Prior to Application of RF Power

PHOTOGRAPH 2. Agglomeration After a Few Seconds of Applied Power

PHOTOGRAPH 3. The Pile Up of the Agglomerations in the Center of the Driving Transducer. (The Edge of the Transducer is Visible at the Left)

Data was then taken on the removal rate of the 3M-300-5005 microspheres. Figure 9 is a plot of the measured data in terms of the output rf voltage. The data points are fitted with a 7th degree least square curve which indicates a maximum removal rate at 3 v.

The experiment was then repeated with 3M-B-40B microballoons. A 7th degree least square fit shown in Figure 10 yields a double peak, with the maximum at 3v and the second smaller maximum at 12 v. A statistical analysis of the distribution of size at the 3v removal level in Figure 11 shows a hole in the middle of the distribution. This abnormal distribution can be fitted with two separate normal distributions, as shown. The lower distribution is the uninflated fraction of the microballoons (which are in fact, microspheres) and the upper fraction represents the large diameter microballoons, which would be resonant at the 5.95 MHz of the surface wave.

Elutriation Theory and Experiment

In the theory presented so far, little account is taken of the aerodynamic forces involved. Since processing can be done in a vacuum, this force can always be removed if it tends to complicate the problem. On the other hand, aerodynamic forces can be used constructively, as in a partical feeder or a partical pickup.

It has been felt that the easiest way to study the effect of aerodynamic forces on particles is through the use of elutriation. An elutriator consists of a hollow vertical column through which a constant rate of air flow is maintained. Particles are expelled when the aero-

Figure 9.

3 REMOVAL PER RF VOLT

Figure 10.

Figure 11.

dynamic force exceeds the force of gravity.

If the air flow is such that only streamlined motion is observed, then the force on a particle of radius R produced by an air velocity V_a and viscosity μ is given by Stoke's law as

$$F_a = 6\pi R V_a \mu \quad (24)$$

The force of gravity on the particle is

$$F_g = \frac{4}{3} \pi R^3 p g, \quad (25)$$

where g is the gravitational constant, and p is the particle density. setting these equations equal and solving for V_a yields the velocity needed to lift a particle, as

$$V_a = \frac{2}{9} \frac{R^2 p g}{\mu} \quad (26)$$

Figure 12. Elutriator Used for Microsphere Studies

Figure 12 is a diagram of the cross section of the elutriator used in this program. Gas was admitted to the column through an outlet below the cone section. The cone section provided a transition from turbulent to streamlined motion. Particles placed in this section swirled around this portion of the column, preventing smaller particles from being trapped under larger ones. Glass slides placed near the top of the tube caught the particles for further study.

A size distribution was plotted for a given velocity and a normal distribution was fitted as shown in Figure 13. The resultant size was then plotted against the flow rate and compared to the theoretical prediction of equation (26) as is shown in Figure 14. Agreement is poor when the microsphere density used is solid glass, however, the microspheres contain bubbles which reduce the observed density. Using the actual density measured, better agreement was obtained.

Of possibly more importance, is a qualitative observation based on relative humidity. When the laboratory humidity exceeds 50%, elutriation will not work when the tube is made of glass. Electrostatic voltmeters

indicated the generation of large amounts of charge in the region of the cone section, and the particles would coat the inside of the tube. When the material of the tube was replaced with Richmond RC-AS-1200 polyethylene, a conductive plastic used in semiconductor wafer processing, charge generation disappeared, and the data shown on Figure 14 was obtained.

When the relative humidity dropped to the 10 to 30% level, elutriation was again attempted. At the lower humidities the microspheres ceased coating the interior of the glass tube and results similar to the one presented in Figure 14 were obtained even in a glass tube.

A particle feeder with a small glass orifice was then built and driven by a small loudspeaker at about 200 cycles per second. At the same low relative humidity, the particles flowed through the orifice fairly continuously, without blockage.

ELUTRIATION OF 3M GLASS SPHERES 150-500S THRU 4 FT GLASS TUBE WITH N2 OVER PG-210

(FLOW RATE 90 MM)

MEAN= 0.03135
SIGMA= 0.00258

N= 90
FRACTION BELOW LCL = .001349
FRACTION ABOVE UCL = .001349

Figure 13.

ELUTRIATION OF 3M-390-5000
MACROSPHERES USING
RICHMOND RC-A5-1200
ANTISTATIC POLYETHYLENE

Figure 14.

BIBLIOGRAPHY

1. B. A. Auld, Acoustic Fields and Waves in Solids, Vol. II,
John Wiley & Sons, (1973), p. 385.
2. F. S. Hickernell, P. L. Clar, and I. R. Cook, "Pulsed DC Voltage
Breakdown Between Interdigital Electrodes", 1972 Ultrasonics
Symposium Proc., October 1972, pp. 388-391.
3. W. R. Smith, H. M. Gerard, J. H. Collins, T. M. Reeder, and
H. J. Shaw; "Analysis of Interdigital Surface Wave Transducers By
Use of an Equivalent Circuit Model", IEEE Tran. on MTT, Vol. MTT-17,
November 1969, pp. 856-864.