DOE/ER/53264-3

DOE/ER/53264--3

DE93 005130

ANNUAL PROGRESS REPORT
"LOW FREQUENCY RF CURRENT DRIVE"

Noah Hershkowitz
Principal Investigator

Department of Nuclear Engineering & Engineering Physics
University of Wisconsin-Madison

Work performed under
Department of Energy
Grant No. DE-FG02-88ER53264

MASTER

1a Antenna Development at Phaedrus-T

The Phaedrus-T rf program has produced the first tokamak operation of an unshielded antenna in the U.S., the first tokamak operation of an antenna with an insulating surround in the world, and the first tokamak operation of high power swept- and arbitrary- phase antennas in the world [Majeski 92]. Implementations of versions of the inductive decoupler, developed on Phaedrus-T to permit arbitrary phase operation of antenna straps, are now planned for TFTR and JET. A modification of the insulating surround technique will be implemented this year on one of the PBX IBW antennas. These innovations have also permitted significant design flexibility in the antennas installed on Phaedrus-T, and will eventually permit installation of a relatively simple phased four-strap high field-side antenna for Alfvén and ion Bernstein wave studies. Further experimental results obtained include measurements of the SOL potential modifications and impurity influx during rf experiments with a conducting Faraday shield. These experiments confirmed the importance of rf sheaths in impurity generation, the role of the radial antenna feeders in inductive sheath generation, and that impurity influx with 90° phasing was a potentially serious problem for fast wave current drive.

The original justification for these antenna studies was that high power rf operation and current drive experiments in a machine the size of Phaedrus-T are difficult. Impurities and plasma control are far more serious problems than in larger machines. Antenna phasing, especially in the Alfvén regime where the antenna loading is low, was an unsolved problem at the start of our experiments. The antenna development effort has proven to be a vital part of the Phaedrus-T program.

The present insulated, unshielded antenna design is the result of two recent advances in the understanding of the rf-edge plasma interaction. First, that rf generated sheaths are the source of modifications of the SOL potentials and the impurity influx observed during rf experiments [Perkins 89; Chodura 89; D'Ippolito 91]. Second, that Faraday shields are unnecessary for electrostatic shielding of antennas [Van Nieuwenhove 91].

The low field side antenna currently installed in the Phaedrus-T tokamak is a four-strap fast wave coupler (Version 3) designed primarily for 90° operation. No Faraday shield is employed on the antenna; it is the third design variant of an unshielded antenna to be installed in Phaedrus-T. All the antennas (since May 91) have used low-Z boron nitride, a refractory insulator, as the plasma-strap shield (the antenna surround). The two previous antennas were also unshielded, but were two-strap versions designed for completely arbitrary phase operation in order to determine the most promising $k_{\parallel}$ range for Alfvén wave experiments. These two antennas differed in strap-plasma separation. The second antenna (Version 2) introduced the use of insulating septa and heaters to outgas the boron nitride at temperatures of up to 350° C; design features which are incorporated into the present four-strap antenna. The most significant modification in the design for the present antenna is the use of a boron nitride "box" which is intended to further improve electrostatic isolation between the straps and the plasma, following measurements made with the Version 2 antenna which indicated that plasma-mitigated strap coupling produced difficulties in arbitrary phase operation at high frequencies (19 MHz). All three antennas are schematized in Fig. 1a-1a-c.

Experiments with an Unprotected Faraday Shield

The results of SOL measurements of the rf-induced plasma potentials are detailed in the papers included in the attached appendix. In brief, the Faraday shield, vacuum chamber wall, and limiters form part of a conducting loop which is then closed by plasma along the magnetic field. The antenna near fields induce a time varying magnetic flux through this loop, and by Faraday's law a voltage appears at the rf frequency. If the SOL plasma is sufficiently dense, which is virtually always the case, this rf voltage appears in thin sheaths at the termini of the plasma flux tube. A positive potential drop develops across the sheath which accelerates ions into the Faraday shield and limiter, resulting in an increase in sputtering and an impurity influx during rf injection. This process is robust; it occurs for the Alfvén range of frequencies as well as the ICRF, and is operative over a very wide range of SOL densities.

In Fig. 1a-2 we plot the quantity $V_f + 3.6 T_e \equiv \Phi_s^*$ as a function of the antenna strap current, for 0° phasing, as derived from triple probe measurements of the floating potential (V_f) and the electron temperature (T_e). If the local plasma potential is not time-varying, Φ_s^* represents the plasma potential. If the plasma potential is varying in time at the rf frequency, then Φ_s^* will be less than the time-average plasma potential $\langle \Phi_s \rangle$; we therefore take it as representative of the minimum time-average plasma potential. Data is given for three probes, labelled top, outboard, and bottom. The top probe lies along a magnetic field line which does not map to the Faraday shield, the outboard probe lies on a magnetic field line which maps to near the midline of the Faraday shield, and the bottom probe maps to the Faraday shield near the azimuthal location of the radial antenna feeders. It is clear that the SOL potentials are not significantly modified by rf injection in portions of the SOL that do not map to the Faraday shield. It is also clear that the sheaths generated by the feeders dominate in the Phaedruss-T geometry. In Fig. 1a-3 we plot the same quantity as a function of antenna current for three antenna phasings. Data were taken with the outboard probe. This data demonstrates that the rf-induced SOL potentials are phase dependent, that 180° phasing minimizes the SOL potential changes, and that 90° phasing generates significant SOL potential modifications. These SOL potentials, which exceed 200 V for modest rf power levels, can easily explain the observed influx of impurities, especially iron, during rf injection in Phaedruss-T. An indication of the impurity influx is given in Section 1e.

Experiments with Insulating Guard Limiters

Experiments with an unprotected Faraday shield indicated that rf generated sheaths were responsible for a significant impurity influx at the 90° antenna phasing which is required for a directional wave launch in current drive studies. Thick insulating guard limiters were therefore installed on the Faraday shield in April 1991. The geometry of the guard limiters is shown in Fig. 1a-4. The guard limiters provided a simultaneous verification of the rf-sheath scenario as the prime mechanism for impurity generation in the SOL, and a simple technique for alleviating the problem. If inductively generated rf voltages localized to the sheaths were the cause of the increased SOL potentials and the subsequent sputtering, then inserting a very high impedance (the insulator) into the conducting loop (discussed previously) in the SOL should localize the Faraday's law-induced voltages to the insulator, rather than the lower impedance plasma sheaths. In Fig. 1a-5 we again

Version 1

Fig. 1a-1a. First implementation of an unshielded antenna in Phaedrus-T.

Version 2

Fig. 1a-1b. Second unshielded antenna installation, with heated side limiters.

Fig. 1a-1c. Present four-strap antenna set. Straps are fully enclosed by insulating boxes; all insulating components are heated.

Fig. 1a-2. Φ_s^* as a function of antenna current, measured at three poloidal locations in Phaedrus-T. All probes are located at $r=27.4$ cm (behind the main limiter and Faraday shield).

Fig. 1a-3. Φ_s^* as a function of antenna current for three antenna phasings. Data are from the outboard probe at $r=27.4$ cm.

Insulating limiter geometry

Fig.1a-4.

Fig. 1a-5. Φ_s^* as a function of antenna current for the bottom probe at $r \sim 27-27.5$ cm. Data are shown for the bare Faraday shield (S.S.) and for the shield with insulating limiters (G.L.).

plot Φ_s^* as a function of the antenna current, for the bottom probe, with and without the insulating guard limiters. It is clear that, as expected, the guard limiters block the rf-generated increase in the SOL potentials. Fig. 1a-6 is a plot of the Fe XVI line intensity, normalized to the line density, vs. rf power for several antenna phases, with and without the guard limiters. Installation of the guard limiters clearly resulted in a reduction of the iron influx, although not in a total elimination of the problem.

Unshielded Antenna Experiments

It was suspected that cross-field transport of plasma onto the face of the Faraday shield was principally responsible for the residual influx of iron with the guard limiter/Faraday shield system. In light of this problem, and in the wake of the then-new TEXTOR results on operation without a Faraday shield, it was decided to eliminate the shield in favor of an insulating surround. The first version of the unshielded antenna was installed in September 1991. Iron influx measurements with this antenna are also shown in Fig. 1a-6, which demonstrates that removal of the Faraday shield largely eliminated the iron influx during rf injection. It should be noted however that operation in rf regimes which result in edge-weighted power deposition, especially at high power levels, can cause the iron influx to reappear. This is true in our Alfvén wave experiments. We also note that, as is detailed in [Majeski 92], the antenna loading, coupling to toroidal eigenmodes, etc. was largely unaffected by the removal of the Faraday shield and the installation of the insulating surround. However, experimental measurements of the strap-plasma impedance and the strap-strap coupling in the presence of plasma indicated that electrostatic coupling between the straps, and to the plasma, was sufficient to impede phase-swept antenna operation. The new four-strap antenna provides a factor of ten increase in the electrostatic isolation between the straps and the SOL plasma, which should certainly be sufficient for our experiments in the sub-15 MHz frequency regime. For very high frequency experiments which are more sensitive to electrostatic coupling, however, a simplified form of Faraday shield in combination with an insulating cover may be preferable to a purely insulating strap cover. This is the arrangement planned in a collaborative effort between the PBX-M group and the Phaedrus-T group to install an insulating cover on one of the PBX-M IBW antennas.

Fig. 1a-6. Intensity of the FE XVI line, normalized to the line density, as a function of rf power, for several antenna structures. Phasing is indicated. S.S. refers to the bare Faraday shield, G.L. to the shield with insulating guard limiters, and U. to data taken with the unshielded antenna.

1b Method of Detecting Small RF Driven Currents

The predicted current drive efficiency in the low frequency fast wave regime (LFFW) and in the Alfvén wave regime, when scaled to Phaedrus-T parameters, is small enough that special methods must be used to detect the effects. For example, the predicted LFFW current drive, for 100 kW of RF power, was roughly 2.5 kA out of a total plasma current of 90 kA. The shot to shot variation in plasma current in Phaedrus-T is of this order due to the finite gain of the feedback system, which regulates the current, and the shot to shot variation in impurity content. To look for current drive by taking a sequence of shots with the RF on and off, or with the phase at $+90^\circ$ and -90° would take many shots.

The response time of the plasma to a current driving force must be considered. If there is a step change in the loop voltage, the plasma current will respond in an L/R time of about 70 ms for Phaedrus-T. Since this is about the length of the RF pulse, we cannot hope to study the steady-state. Furthermore, any application of high power RF in Phaedrus-T results in changes in impurity influx and gas recycling sufficient to cause changes in the plasma current and loop voltage comparable to the small predicted current drive effects.

Fortunately, we can do much better for two basic reasons:

- The Phaedrus-T transmitter system consists of two completely independent amplifier chains driven by programmable synthesizers, so that the phase and amplitude of the transmitter output can be varied almost arbitrarily.
- The use of the decoupling network in the antenna, together with our vector analysis and tuning system, allows us, under most circumstances, to abruptly (in a few tens of microseconds) alter the phase of the antenna currents and to do so many times within a shot.

Thus, our method is to take shots in which the phase is modulated by a square wave of about a 20 millisecond period, giving three or four transitions between a positive phase (waves co-propagating with the plasma electrons) and a negative phase (counter-propagating). This approach has the advantages that:

- The power can be held almost constant while varying the phase, minimizing the effects on loop voltage due to impurities (we will show later that such effects were a dominant source of noise in the search for LFFW current drive).
- The shot to shot variation of the current can be eliminated by allowing a new baseline to be generated at each transition.

The disadvantage of this method is that, by constraining the effects to short time scales (10 ms in each phase), we are forced to look not at the total changes in the plasma current but at the inflections of the current. There is a trade-off involving signal and noise. The longer one holds a given phase, the more time the current is allowed to change due to the current drive effects.

However, the plasma current changes randomly even during a single shot by an amount roughly proportional to the time (the system has roughly a $1/f$ noise spectrum). The 20 ms period thus represents the best compromise, allowing a large number of transitions to improve our statistics while still allowing the inflections to be measurable above the short term fluctuations.

An example of this analysis, taken from the LFFW effort, is shown in Figs. 1b-1 to 1b-4. First, the data from a single shot is shown in Fig. 1b-1. Then, in Fig. 1b-2, the current traces from all the transitions in 30 shots are shown, first as raw data and then with the baselines subtracted. The histogram showing the deviations of the values of this data from the mean is shown in Fig. 1b-3. This allows us to estimate the standard deviation of the raw data. Finally, the mean data and the straight-line fits to measure the inflections are shown in Fig. 1b-4. The error bars in these figures reflect the aforementioned standard deviations in the raw data divided by the square root of the number of transitions in the average, as in the usual statistics of normally distributed variables. In this case the errors were much less than the predicted current drive effects. The above error analysis does not, however, take into account systematic effects such as the effects of a phase-dependent impurity release which turned out to be mimicking current drive in this case. This is discussed in the section on LFFW results.

Fig. 1b-1. Data from a single current drive shot, showing the phase chopping technique used to search for small current drive effects. The spiky behavior of the RF power and the phase is due to the strong eigenmodes.

Fig. 1b-2. The top graph shows the raw current data from each transition in strap current phase from about 30 shots. The bottom is the same data but with the baseline subtracted from each transition. The time scale is such that the center of the plot is where the phase jumps.

Fig. 1b-3. The histogram showing the deviation of current values from the mean for the data in the previous figure. We can see that the data is fairly well represented by the normal distribution (dotted line).

Fig. 1b-4. The means of the data, showing the inflections of the current in the case of two different types of transitions.

1c Low Frequency Fast Wave Current Drive Experiments

Increasing world interest in LFFW current drive and the fact that the Phaedrus-T survey antenna and transmitter systems were readily configurable to such a mode led to the decision to conduct LFFW current drive experiments. This was done by retuning the transmitters to 19 MHz, the upper end of their usable range. We could then operate at a frequency of $3\omega_{CD}$ on axis. The survey antenna has a strap spacing of .17 m, such that at 19 MHz and with 90° phasing the peak in the $k_{||}$ spectrum resonates with about 400 eV electrons. At first the power was limited by the transmitter to about 60 kW at this frequency. Later we improved the transmitter so that about 300 kW was available.

We found that the loading resistance was several ohms for these conditions. Strong eigenmodes were observed, indicating weak single pass absorption as theory predicts. At first the experiments were performed using the stainless steel Faraday shield with insulating bumper limiters, which allowed operation with lower RF generated impurities but still large density rises. Later we implemented the practice of helium glow discharge cleaning between shots, which allowed us to control the density better during the RF pulse.

The initial search for current drive gave the results shown in Figs. 1b-1 through 1b-4 as discussed in the section Method of Detecting Small RF Driven Currents. The technique of rapidly switching the phase between co and counter injection showed that the plasma current inflected by an amount corresponding to a steady-state drive of about 2 kA. This conclusion, that current drive was actually taking place, was invalidated when an experiment was performed in which the phase was fixed at $+90^\circ$ (corresponding to co-injection) and the power was repeatedly pulsed on and off, as shown in Fig. 1c-1. The plasma current was found to inflect as before, but in such a way that the current decreased when the power was on. The density was also found to be inflecting, oppositely to the current. Apparently the RF was causing the release of gas or impurities, and the resulting power load on the plasma was forcing the current down. If we call the plasma current inflection ΔI_p and the density inflection Δn , and the ratio of the two $\alpha \equiv \Delta I_p / \Delta n$, then we find that in this power pulsing experiment that $\alpha \equiv 3 \times 10^{-16} \text{ Am}^3$, and re-examination of the current drive data showed that there $\alpha \equiv 5 \times 10^{-16} \text{ Am}^3$. These values are sufficiently close to invalidate the current drive hypothesis. There was either enough imbalance in power between the two phases, or some asymmetry allowing more gas to be injected in one phase (-90°) than the other, to result in density modulations, which then caused the current inflections. Further, the power we estimate necessary to create the observed amount of extra plasma, on the order of 5 kW, is comparable to the observed loss of poloidal magnetic energy $\Delta(L_p I_p \dot{I}_p)$, where L_p is the plasma inductance. This makes the explanation feasible from the point of view of power balance. We note further that in all LFFW experiments there was never any indications of plasma heating, such as a drop in loop voltage. We therefore cannot account for the RF power coupled to the plasma. If current drive were taking place, there should be some observed coupling to the electrons in the form of heating as well.

Fig. 1c-1. Plots showing the results of a power pulsing experiment in which the phase was fixed at $+90^\circ$ while the power was square-wave modulated. The marked effects on the current, mimicking a strong anti-drive, support the theory that all our LFFW current drive effects were due to density modulations as shown, caused by small variations in the RF induced fuelling. The ratio of the current inflection to the voltage inflection is approximately the same as in the LFFW current drive results shown in Figs. 1b-1 to 1b-4.

The possibility remained that there was still some residual current drive, and so a series of experiments were performed in which the power balance between $+90^\circ$ and -90° was purposely varied, so that the density modulation could be varied. The results of this scan are shown in Fig. 1c-2.

We can see that the current inflection varies linearly with the density inflection, and that it goes to zero in approximately the same place. The scatter in this data (current inflection versus density inflection) is now the dominant source of noise and sets a lower limit on the detectable current drive of about 1000 A (projected to steady-state). That is, we do not know within this limit if the current inflection goes to zero at zero density inflection. This is only about half of the predicted LFFW current drive. To test the theory of LFFW more thoroughly will require further reductions in RF related fuelling and impurity generation.

Fig. 1c-2. Results of a scan in which the RF power was purposely made different in the $+90^\circ$ phase than in the -90° so that the density inflections could be varied. In this way we could investigate whether the observed current drive vanished for small density modulations, which it appears to do as shown in the top graph. The dotted line is a least squares fit.

1d Alfvén Wave Interactions with Electrons - Experimental Results

During Alfvén wave experiments we have observed that rf injection results in electron heating. A ~ 30% drop in plasma loop voltage, with a corresponding ~ 15% increase in the electron temperature is measured by Thomson scattering, for 100 kW of coupled rf power. For comparison, ohmic power input was approximately 150 kW. These experiments, which were primarily designed for electron heating, were performed as a first step towards a demonstration of Alfvén wave current drive. There are two main reasons to pursue electron heating experiments prior to current drive work in Phaedrus-T. First of all, no prior evidence of Alfvén wave heating in tokamaks has been obtained [Vaclavik 91]. This includes the ten-year effort on the TCA tokamak at Lausanne, which was largely dedicated to Alfvén wave experiments. It should be noted, however, that the wave physics of the processes involved in Alfvén wave heating was successfully established by the TCA effort [Collins 86; Behn 87; Weisen 89], including transient indications of Alfvén wave - electron interactions [Moret 88]. A successful heating experiment was needed to demonstrate Alfvén wave modification of the electron distribution function and to establish the physics basis of the Alfvén wave - electron interaction. Secondly, the present two-strap antenna set was designed as a "survey set", which was intended to indicate the most promising $k_{||}$ and frequency regimes for current drive experiment. With a two strap antenna it is impossible to avoid edge power deposition in the Alfvén regime at phasings other than 180° , which is suitable for heating but not current drive. The results of the heating experiments led to significant design changes in the four-strap antenna set which has now been installed in Phaedrus-T.

Experiments were performed at 7 and 9.2 MHz. A summary plot for a 7 MHz experiment is shown in Fig. 1d-1. The primary diagnostic indicating rf-electron interaction is the loop voltage, which shows a ~ 30% drop with ~ 150 kW of rf power. An increase in soft x-ray emission is associated with the loop voltage drop - a further indication of electron heating. Line density is constant or drops slightly, with no change in the gas puffing rate. Under these conditions Thomson scattering also indicates a slight increase in the electron temperature during the rf pulse (see Fig. 1d-2). The values of the loop voltage observed during Alfvén wave heating (~ 1 V) were the lowest ever obtained in Phaedrus-T (except for very low density/runaway electron discharges). In general, the loop voltage drop could not be sustained for much longer than 20 msec, which is a period longer than τ_E at this low (0.7 T) magnetic field but less than the L/R time of the plasma.

The strongest Alfvén wave-electron interactions were observed when the Alfvén resonance for the bulk of the antenna spectrum was located in the edge plasma, very near the limiter. The Alfvén resonance condition (corrected for finite frequency effects) is $v_\phi = v_A(1 - \omega^2/\Omega_i^2)^{1/2}$, where v_ϕ is the wave phase velocity and v_A is the local Alfvén speed. The radial location of the resonance can therefore be changed by adjusting the toroidal field. We find that the antenna loading increases as the Alfvén resonance is moved out in radius into the edge of the plasma; a decrease in loading ensues as the resonance is moved further, past the limiter into the SOL. This result is shown in Fig. 1d-3. Note that the "resonance location" is rather broad due to the width of the antenna $k_{||}$ spectrum.

Fig. 1d-1. Alfvén wave heating experiment at 7 MHz.

Fig. 1d-2. Electron temperature, derived from Thomson scattering, as a function of rf power for the 7 MHz Alfvén wave heating experiment.

Fig. 1d-3. Antenna loading resistance as a function of toroidal magnetic field.

There are two possible wave mechanisms which could be responsible for the observed electron interaction. The first is direct excitation of the Alfvén resonance and generation of kinetic Alfvén waves (KAW) by the evanescent fast wave fields generated by the antenna. Although this mode is a kinetic wave which suffers electron Landau damping, the KAW does propagate cross-field, unlike the cold shear Alfvén wave, and could be responsible for core or near-core electron interactions. An alternative explanation involves excitation of a global Alfvén wave (GAW) or global eigenmode of the Alfvén wave (the GEAW, in the terminology of Vaclavik and Appert [Vaclavik 91]), which heats electrons in the core plasma. At present we are unable to conclusively identify the wave channel responsible for the wave - electron interaction, although a resolution is expected in the round of experiments which have just begun by comparisons of experiments in deuterium and hydrogen plasmas. Operation in deuterium was not possible with the original two-strap antenna due to frequency limitations. In comparing operation at 7 and 9.2 MHz, we find that larger magnitude and longer duration loop voltage drops were obtained at 7 MHz. Thus lower phase velocity operation is preferential. This observation tends to support the importance of mode conversion to the KAW, since mode conversion to the KAW is optimized when the condition $v_\phi < v_{Te}$ is met at the resonance surface. For a resonance in the edge plasma this implies very low v_ϕ is desirable. At the least it is clear that excitation of the cold shear Alfvén wave is not desirable.

The heating effect appears to terminate in 10 - 20 msec, as can be seen in Fig. 1d-2. The Alfvén velocity is proportional to the inverse square root of the mass density, and so the resonance location is sensitive to heavy impurities. An increase in the edge impurity content will shift the resonance to lower density (larger radius). Since we are forced to locate the Alfvén resonance in the evanescent antenna fields, which decrease exponentially away from the limiter, edge power deposition, heating, and impurity influx is inevitable with the present antenna geometry. For the conditions under which we obtain changes in the loop voltage an increase in the edge oxygen content to 2-3% will shift the resonance location outwards several cm, into or near the SOL where the mode conversion criterion is no longer met over most of the antenna spectrum. Heavier impurities will obviously have a larger effect. 2-3% oxygen in the edge plasma during rf is consistent with observations of the peak intensity of the OV line during rf injection made with a XUV imaging system recently installed on Phaedrus-T in a collaboration with Johns Hopkins University. A plausible explanation for the termination of the loop voltage drop is, therefore, impurity influx, which shifts the resonance location into the cold edge plasma. Note that there is a clear possibility of a cascade effect here, where the increased edge power deposition leads to increased impurity influx and further localizes power deposition in the edge. A further issue is dilution of the hydrogen plasma by residual helium from the helium glow between shots, which is performed to condition the walls and reduce hydrogen recycling during a discharge. Any significant helium content in the plasma will move the Alfvén resonance to lower magnetic field, further into the edge or SOL.

These observations have largely determined the design of the next antenna set.

1. A four-strap antenna is required in order to avoid a $k_{||} = 0$ component in the antenna spectrum for 90° operation. A four-strap antenna operated at 90° will also have a longer evanescence length than an antenna operated at π phasing, so that the resonance can be located further from the edge, minimizing edge power deposition and impurity influx.
2. Low frequency operation, with a close-spaced antenna set, is required to minimize the rf phase velocity. This goal is primarily a result of the empirically differences in electron interactions at 7 and 9.2 MHz.
3. Deuterium operation is desirable both for the above reason and because the higher mass of deuterium minimizes the effect of a heavy impurity influx on the resonance location. However, a comparison of results with H and D operation should clarify the electron interaction mechanism.

For these reasons the new antenna recently installed in Phaedrus-T has four 60° straps spaced 14.5 cm apart in a single port box. The antenna is optimized for 90° operation; 180° is possible but only in $(0, \pi, \pi, 0)$ phasing rather than the usual $(0, \pi, 0, \pi)$ phasing. The antenna is thus specialized to current drive experiments. Additional capacitors, and the higher strap inductance of the antenna design, extend the operating frequency downward to 4-4.5 MHz so that deuterium can be the standard working gas.

1e Machine Conditioning, Impurity Generation and Density Control

Impurity generation and density control are important operational requirements for successful experiments that involve rf in tokamaks. Phaedrus-T, as a mid-sized tokamak with reasonable rf power density (300 W/cm^2 at the antenna), has successfully operated with low impurity generation ($P_{\text{rad}} \leq 0.5 (P_{\text{ohmic}} + P_{\text{rf}})$) and adequate density control ($\delta n/n \leq 0.1$) for rf pulse lengths of 30-70 ms as shown in Fig. 1e-1. To achieve these results, required substantial work in three areas: antenna design, first wall material selection and machine conditioning. An insulator antenna surround was designed that significantly reduces the direct power input to the scrape-off layer (SOL) plasma (as measured by probes). A thin layer of carbon and boron is deposited weekly using a DC discharge with He and trimethylboron as the feed gases and has come to be known as boronization. Phaedrus-T was the first US tokamak to use trimethylboron and the second US tokamak to try boronization. Machine conditioning has evolved into pure He DC glow discharging and boronization after an up to air. Density control is obtained by using one hour He glows each morning and short 5 minute He glows between each tokamak discharge. DIII-D and Phaedrus-T are the only tokamaks in the world to condition with He between shots.

The Phaedrus-T antenna, Faraday shield design had to be stringently designed to reduce impurity generation. The machine is relatively small (volume = 1 m^3) with low toroidal field and low toroidal plasma current so impurities can penetrate easily and the SOL is physically broad. Moreover, current drive requires antenna phasing that normally generates enhanced impurities. JET [JET 91] has shown that 180 degree phasing between adjacent antenna straps generates the least impurities but this phasing is not effective for the present Phaedrus-T current drive experiments- the waves are not unidirectional. Our data gives very similar results [Hershkovitz 92]: 180 degree phasing is generally the "cleanliest" rf scenario while 0 degree phasing is the worst. The rf power density at the antenna in Phaedrus-T is comparable to JET's but not as large as TFTR [Phillips 91]. In Phaedrus-T, we now use no Faraday shield. The insulator antenna surround is made of boron nitride, a low Z material.

Machine conditioning on Phaedrus-T has evolved into depositing the carbon/boron layer weekly and using pure He glow discharges between each shot. The plasma facing surfaces, the graphite limiters and the boron nitride antenna shield, are baked to reduce occluded gas including volatile water vapor and hydrogen especially after an up to air. Hydrogen pulse discharge cleaning is not used since it was found to be ineffective and time consuming in comparison to the boronization-He glow scenario. Density control is maintained by He glow discharge cleaning between each shot. This maintains a constant low reflux rate of hydrogen during the tokamak pulse, although a residue of Helium is present in the discharge.

Initially, Phaedrus-T had a bakeable graphite limiter and a non-bakeable stainless steel Faraday shield. We relied on pulse discharge cleaning and hydrogen DC glow discharge cleaning for machine conditioning. The methods we used were copied from procedures that were in place or evolving in other devices. DIII-D [Jackson 89] had found that He glow between shots produced their best plasmas. We first used this procedure on a limited basis during the summer of 1990.

Fig. 1e-1. Total Input Power (ohmic and coupled rf power), P_{in} ; the radiated power, P_{rad} , using the single fast platinum resistance bolometer normalized by the copper/thinister bolometer array; the line average density, n_p ; and the coupled rf power for a discharge with $B_T \sim 0.7$ kG, $I_p \sim 70$ kA, and constant hydrogen fueling 70-150 ms. Alfvén wave excitation at 180° phasing.

TEXTOR [Winter 90] had found that TMB ($\text{B}(\text{CH}_3)_3$) introduced into a He DC glow discharge produced amorphous carbon/boron layers and gave results similar to those discharges using a combination of methane and diborane (B_2H_6). TMB is 1,000 time less toxic than diborane. At first, we tried carbonization with a Helium/methane glow discharge gas mixture (Dec. 90 and Jan. 91). This lowered metal impurity influx with ohmic pulses and with rf (similar to earlier TEXTOR results). The boronization (Mar. 91) with Helium/TMB lowered the Z_{eff} and impurity radiation more significantly and so was retained on a more continuous basis. The carbon/boron layer reduced both the oxygen and carbon impurity levels. A summary of the results over this period are illustrated in Fig. 1e-2 for ohmic discharges. To obtain reliable low reflux with this amorphous layer, pure He discharges were needed before each run of 100 discharges. We speculate that the amorphous carbon/boron layer acts as a sponge and can change from a "pump" to a source depending on the amount of hydrogen in the outer layer. Reports from both TFTR [Dylla 90] and Compass [Morris 91] confirmed the reports from DIII-D that He glows deplete this hydrogen. It was the Compass report on TMB generated films at the IAEA meeting on small tokamaks (1990) that convinced us that boronization with TMB was worth trying.

The persistent problem of uncontrolled density increase with rf was alleviated by running a He glow discharge between shots. In Fig. 1e-3 we show that the density increase with rf is almost eliminated immediately after a He glow cycle.

Fig. 1e-2. Soft X-Ray, Loop Voltage, Z_{eff} (From Mar. 11, 1991), C, Fe XVI, and O, signals normalized to $2 \times 10^{13} \text{ cm}^{-3}$ line averaged density and ohmic shots only. Jan. 30 is the baseline; early Feb., carbonization; Mar. 11, first boronization; Apr. 22 after an up to air and one boronization; April 27, second boronization reduced the O line emission; May 2, 200 shots later the boronization effect is reduced; May 20, up to air and boronize; May 22, second boronization duplicates results of Mar. 11 only 4 days after pump down.

Fig. 1e-3. Density variation caused by rf a) immediately after a He glow cycle and b) many shots after one. The density decreases even though the gas feed rate is maintained at 25 A for case a). For case b) the density increases dramatically but the gas feed rate has been reduced to 8 A.

END

**DATE
FILMED**

2 / 1 / 93