SUMMARY

The Accelerator Research Studies program at the University of Maryland, sponsored by the Department of Energy under grant number DE-FG05-91ER40642, is currently in the second year of a three-year funding cycle.

The program consists of the following three tasks: TASK A, "Study of Transport and Longitudinal Compression of Intense, High-Brightness Beams," (P.I., M. Reiser); TASK B, "Study of Collective Ion Acceleration by Intense Electron Beams and Pseudospark Produced High Brightness Electron Beams," (Co-P.I.'s, W.W. Destler, M. Reiser, M.J. Rhee, and C.D. Striffler); TASK C, "Study of a Gyroklystron High-Power Microwave Source for Linear Colliders," (Co-P.I.'s, V.L. Granatstein, W. Lawson, M. Reiser, and C.D. Striffler).

In this report we document the progress that has been made during the past year for each of the three tasks. The highlights of our research accomplishments during the year 1992 can be summarized as follows:

TASK A: The multiple-beam experiment was brought to a successful conclusion by the summer (D. Kehne, Ph.D. dissertation, 1992). Our major activity since then has been the longitudinal beam physics studies (D. Wang, Ph.D. dissertation in progress) where we demonstrated experimentally for the first time that a parabolic bunch profile has the linear behavior expected from theory. We also measured the dramatic change of an initially rectangular bunch profile in drift space due to the nonlinear space charge forces in this case. The results will be checked by computer simulation by Irving Haber, NRL in the near future. Additional milestones were achieved with the controlled excitation and experimental observation of space-charge waves and the start-up of a new research project for studies of the sources of energy spread including collisions in beam transport (N. Brown, Ph.D. student). Progress was also made in the theory of the longitudinal instability in space-charge dominated beams (J.G. Wang and M. Reiser). The resistive-wall instability experiment, which had been delayed due to an accident that broke the resistive glass tube, will be resumed in 1993 with the arrival of a new tube from China.

TASK B: The laser-controlled collective ion acceleration experiment has been concluded for the time being, as planned, since further progress would require a machine with higher voltage and longer pulse duration. Our research activities have therefore concentrated al-

MASTER

ED

most entirely on the studies of the hollow-cathode pseudospark discharges as a source of high-brightness electron beams. New diagnostic results of the low-energy (~ 20 keV) pseudospark device including successful inductive post-acceleration by 25 kV demonstrate the great potential for achieving very high brightness in the range of 10^{12} - 10^{13} Amp/(m-rad)². A very exciting new development is the pulse-line driven pseudospark experiment at energies in the 150 keV to 300 keV range where the initial results are very encouraging and a new experiment is being planned for 1993.

TASK C: After the successful demonstration of 27 MW peak power in L-band, our gyrokystron project has now moved into a new phase where we operate at the second harmonic at 19.7 GHz. Several megawatts have already been demonstrated with the new configuration. A new electron gun has been designed which would be capable of generating as much as 150 MW of rf power in X-band (first harmonic operation) and about 100 MW at 19.7 GHz (second-harmonic operation). We will go out for bids and hope to award a contract for this gun in the spring of 1993.

Table of Contents

Summary

i

TASK A: Study of Transport and Longitudinal Compression of Intense, High-Brightness Beams

1	Introduction and Synopsis	A1
2	Research Progress	A3
2.1	Multiple Beam Experiments	A3
2.2	Longitudinal Pulse Compression Experiments	A5
2.2.1	Completion of the compression experimental setup	A5
2.2.2	Measurement of longitudinal energy spread	A6
2.2.3	Study of longitudinal dynamics of parabolic beams	A7
2.2.4	Study of longitudinal dynamics of rectangular beams	A8
2.3	Longitudinal Instability Experiments	A10
2.3.1	Theoretical studies	A10
2.3.2	Generation and propagation of space-charge waves	A10
2.3.3	Status of resistive-wall instability experiment	A11
2.4	Experiment to Measure the Boersch Effect	A13
2.4.1	New energy analyzers	A13
2.4.2	Modification of the long-pulse injector	A13
2.4.3	Energy spread from focusing	A13
3	Proposed Research	A15
3.1	Longitudinal Pulse Compression Experiments	A15
3.2	Longitudinal Instability Experiments	A15
3.3	Experiment to Measure the Boersch Effect	A16
4	Papers and Presentations Resulting from this Research	A17
	Appendix	A19

Task B: Study of Collective Ion Acceleration by Intense Electron Beams and Pseudospark-Produced High Brightness Electron Beams

1	Introduction and Synopsis	B1
2	Research Progress	B1
2.1	Research on Collective Field Accelerators - Laser Controlled Beamfront Accelerator Experiments	B1
2.2	Research on Pseudospark-Produced Electron Beams	B2
2.2.1	Time-Resolved Energy Spectrum of a Pseudospark-Produced Electron Beam	B2

2.2.2	Post-Acceleration Experiment	B3
2.2.3	Beam Quality and Other Accelerator Studies	B3
2.3	Pulse-Line Driven Pseudospark Experiments	B4
2.4	Pseudospark Modeling	B5
2.4.1	Parallel-Plate Model — Parameter Space	B5
2.4.2	Results	B6
3	Proposed Research on High Brightness Beams Generated in Pseudospark Discharges	B9
3.1	Post-Acceleration Experiment	B9
3.2	Beam Transport Study	B9
3.3	Experimental Study of Hollow Cathode Phenomena	B9
3.4	Pulse-Line Driven Pseudospark Experiments	B9
3.5	Pseudospark Modeling	B10
4	Papers and Presentations Resulting from this Research	B12
	Appendix	B15

TASK C: Study of a Gyroklystron High-Power Microwave Source for Linear Colliders

1	Synopsis and Introduction	C1
2	Experimental Research Progress	C5
2.1	Three-Cavity Experiments	C6
2.2	Second Harmonic Amplifiers	C7
2.2.1	Hardware for 19.7 GHz Operation	C7
2.2.2	Tube H1 (First Harmonic Experiment)	C8
2.2.3	Tube H2 (Second Harmonic Experiment)	C20
2.2.4	Tubes H3 and H4	C32
2.3	Modulator Upgrade	C36
2.4	Electron Gun Design	C38
2.5	Cavity Design/Cold Test	C41
3	Theoretical Research Progress	C42
3.1	Theory of the Relativistic Gyrotwistrons	C42
3.2	Efficiency of Frequency Upshifted Gyrodevices: Cyclotron Harmonics versus CARMs	C42
3.3	Improved Gyrotron Modeling	C43
3.4	Codes for Coaxial Circuits	C44
4	References	C46

5	Proposed Research	C48
5.1	Experiment	C48
5.2	Theory	C49
5.2.1	Optimization of microwave phase velocity and axial distribution of external magnetic field for extraction of maximum energy from electron beams with realistic velocity spread	C49
5.2.2	Analysis of excitation of spurious waves in relativistic gyroamplifiers .	C50
6	Papers and Presentations Resulting from this Research	C51
	Appendices	C53

Reprints + Preprints removed

TASK A
Study of Transport and Longitudinal Compression of
Intense, High-Brightness Beams

Contents

1	Introduction and Synopsis	A1
2	Research Progress	A3
2.1	Multiple Beam Experiments	A3
2.2	Longitudinal Pulse Compression Experiments	A5
2.2.1	Completion of the compression experimental setup	A5
2.2.2	Measurement of longitudinal energy spread	A6
2.2.3	Study of longitudinal dynamics of parabolic beams	A7
2.2.4	Study of longitudinal dynamics of rectangular beams	A8
2.3	Longitudinal Instability Experiments	A10
2.3.1	Theoretical studies	A10
2.3.2	Generation and propagation of space-charge waves	A10
2.3.3	Status of resistive-wall instability experiment	A11
2.4	Experiment to Measure the Boersch Effect	A13
2.4.1	New energy analyzers	A13
2.4.2	Modification of the long-pulse injector	A13
2.4.3	Energy spread from focusing	A13
3	Proposed Research	A15
3.1	Longitudinal Pulse Compression Experiments	A15
3.2	Longitudinal Instability Experiments	A15
3.3	Experiment to Measure the Boersch Effect	A16
4	Papers and Presentations Resulting from this Research	A17
	Appendix	A19

1 Introduction and Synopsis

Our research in TASK A during the past year has been in four areas, namely multiple-beam studies (subsection 2.1), longitudinal pulse compression (2.2), longitudinal instability (2.3), and initiation of a new experiment to measure the energy spread caused by Coulomb collisions, generally known as the Boersch effect (2.4).

The multiple beam experiments formed the research topic for David Kehne's doctoral dissertation which was completed in the spring of 1992. David has stayed on with us as a post doc and will join CEBAF on February 1, 1992. Part of his work during this time involves further analysis of the experimental and simulation results for the mismatched beam case. Of particular interest here is the observed halo formation where we are trying to obtain a better understanding by tracing back the halo particles to the origin in the computer simulation. This work is still in progress, and we hope to have the desired results early in 1993 to be reported in a paper submitted to the Particle Accelerator Conference.

Experimentally, our major activity during the past year has been the longitudinal beam physics experiments. Dunxiong Wang, who is performing his Ph.D. dissertation with this work, has made excellent progress. The short-pulse electron beam from the new injector has been injected into our 5-m long solenoid channel, and the experimental observations have been very impressive. Thus it was shown experimentally – to the best of our knowledge, for the first time – that a parabolic longitudinal distribution remains parabolic during the compression or expansion process in the channel. Energy measurements show the linear behavior expected from theory (the longitudinal space-charge forces is linear in a parabolic line-charge distribution). Likewise, it was observed that a rectangular pulse displays the expected nonlinear behavior where the two sharp ends rapidly change and the kinetic energy of the particles at the front increases while that of the particles at the rear decreases.

Another milestone was the generation of space-charge waves on the rectangular beam pulse. The slow wave, which propagates towards the rear of the pulse, is responsible for the longitudinal instability in particle accelerators and high-current transport systems. We can see both waves, the slow wave propagating towards the rear and the fast wave propagating towards the front of the pulse as the beam passes through the solenoid channel. In future

work we hope to find out what happens to these space-waves when they hit the end of the pulse. This is a very important theoretical question that our work could shed some light on.

In the resistive-wall instability experiment we suffered a temporary setback when the resistive tube from China broke during assembly. A new tube has been ordered and should arrive here in January 1993. Since a graduate student has now been hired for this project, we expect to make good progress in the coming year. We have carried out further theoretical work on this topic by expanding the existing theory into the regime of a space-charge dominated beam. Our model includes both a purely resistive wall, as will be used in our electron beam experiment, as well as a series of induction gaps with resonant interaction between beam and cavity fields.

Finally, we have initiated a new research project that deals with the problem of Coulomb collisions and the resulting energy spread. Nathan Brown, a new graduate student who would like to pursue his Ph.D. thesis on this topic, has already made significant progress in the theoretical analysis. Thus it appears the some of the energy spread observed by Dunxiong Wang in the longitudinal pulse propagation can be attributed to Coulomb collisions rather than focusing in the lenses. Work is now in progress to design a special experiment for studying this effect by injecting the beam from the Hughes gun into a long solenoid similar to the resistive-wall solenoid and compress it down to a small diameter of a few millimeters. The effects of Coulomb collisions depend on the particle density and increases when the beam is compressed transversely. An important tool in these planned experiments will be a high-resolution (< 1 eV) energy detector that has been built during the past months. (See paper 14 on the list in Section 4.)

2 Research Progress

2.1 Multiple Beam Experiments

Research previously performed at the University of Maryland Electron Beam Transport Experiment involving the merging and transport of a multiple beamlet distribution revealed several interesting phenomena that are currently being investigated. The distribution is created by masking out a 240 mA round electron beam with energy of 5 keV into a 5-beamlet configuration with total current of 44 mA. This distribution first enters a 2-solenoid matching section and then is injected into the 36-solenoid periodic channel.

The first stage of the research studied the merging and transport where the distribution was rms-matched to the channel. In agreement with theory and simulation, the experiment showed the beamlets rapidly merging into a nearly uniform solid beam in a quarter of a plasma wavelength, $\lambda_p/4$. Theory and simulation predicted approximately 50% increase in rms-emittance as the free energy associated with the nonstationary initial distribution is converted to random kinetic energy. At the half betatron wavelength, an image of the initial distribution appeared. In the image, the space between the beamlets is filled with electrons of relatively low density. Using smooth approximation to calculate the emittance of the particles forming the image suggests that this low-density distribution has in fact undergone no further emittance growth beyond the 50% at the $\lambda_p/4$ position. If this is true, then the low density regions are responsible for the 50% growth in emittance to start with. At the end of the channel, however, all residual structure has disappeared and the beam seems to have thermalized to a great extent.

The second stage of the research involved rms-mismatching the distribution so that the rms-radius at the beginning of the channel was half that of the matched beam at the same location. Theory and simulation predicted a factor four of growth in rms-emittance occurring as the free energy associated with the mismatched beam was converted to random kinetic energy. However, both experiment and simulation revealed an extensive halo of particles existing in configuration (x-y) space forming between the seventh and twelfth channel lens and the formation of an inner core of particles. Emittance measurements of the beam core at the end of the channel resulted in a value nearly identical to that of the matched beam. The

simulation revealed that there was a halo in velocity (x' - y') space as well and that the halo particles in both phase spaces make up nearly 20% of the total beam current. Simulation also revealed that these particles were found to be the cause of all of the predicted emittance growth that occurs over and above the 50% due to the homogenization of the initial multiple-beam configuration. Thus, at the end of the channel, the 80% of the current comprising the beam core has the same general characteristics as the rms-matched beam.

In both of these situations, the emittance growth is associated with the conversion of free energy. However, the resulting beams are quite different. In the rms-matched case, the final distribution is well behaved and has the characteristics of a stationary beam with the excess energy for the homogenization process seemingly spread among the particles. On the other hand, the rms-mismatched beam exhibits a large halo that contains nearly all of the excess energy derived from the mismatch.

It is still not clear from what portion of the initial beam these halo particles come. It is suspected that the halo particles initially lie on the fringe of phase space, generally characterized by high rms velocity or position. On the other hand, the inherently nonlinear processes involved in emittance growth could affect particles randomly. In order to determine whether there is some correlation between a particle in the halo and its initial position in phase space, the existing simulation data will be analyzed. The simulations were performed using $32,768 = 2^{15}$ particles. With this number of particles, a statistically accurate view of the particle dynamics can be generated.

The multiple-beam experiments have been discontinued as the transport channel is now being used for longitudinal beam physics experiments. For these new experiments our new in-house-built injector with a short-pulse gridded electron gun is being used. For the long-pulse Hughes gun we have built a new injector with a vacuum valve that allows us to disconnect the gun from an experiment without exposing the cathode to air. This will be a major improvement over the past situation where we needed to recondition the cathode after each change that involved breaking the vacuum.

David Kehne, who has carried out his Ph.D. dissertation with the multiple-beam experiments and who has held a postdoctoral appointment with us since July 1 of this year, has accepted an offer from CEBAF and will leave us by the end of January 1993.

2.2 Longitudinal Pulse Compression Experiments

2.2.1 Completion of the compression experimental setup

The longitudinal compression experimental setup consisting of the newly developed electron beam injector and the 5-m long periodic channel was completed during the summer. It has been commissioned to run the longitudinal compression and other experiments ever since.

The electron beam injector was completed last year. A paper entitled “Electron Beam Injector for Longitudinal Beam Physics Experiments” was published in NIM A316, pp. 112-122, 1992. This paper summarizes the design, operation principle, and test results of the injector.

The 5-m long periodic channel has undergone substantial modification since last year. The notable points are:

- Five fast wall-current monitors have been installed in the channel to measure the beam current profile at different locations along the channel. The monitors have a wide bandwidth above 2 GHz.
- Three retarding field energy analyzers and one deflecting energy analyzer have been installed in the channel. With the aide of a DSA602A oscilloscope, the time-resolved energy spectrum of the beam can be obtained along the channel. Unfortunately, one retarding field energy analyzer had to be taken out of the system due to a leak in the vacuum feedthrough bellow.
- The metal pipes of the channel have been thoroughly and carefully cleaned. More ion pumps have been added to the channel. Therefore, the vacuum of the system has been improved by more than an order of magnitude. This is very critical to the gun operation.
- The system has been carefully aligned. The error of the alignment is believed to be less than 1 mm through the channel.

Figure 1: Beam energy distribution at two different magnetic focusing fields: $s_0 = 53^\circ$ on the left and $s_0 = 90^\circ$ on the right.

4.2.2 Measurement of longitudinal energy spread

The time-resolved beam energy measurement was done with the injector last year. The results were presented at the 9th International Conference on High-Power Particle Beams, Washington, DC, May 25-29, 1992. It was found that the resolution of the energy measurement by the retarding field energy analyzer was mainly limited by the longitudinal beam energy spread due to the focusing of the magnetic lenses.

This phenomena has been studied further with the long periodic channel. Figure 1 shows the measured beam energy distribution at two different focusing magnetic field strengths. This energy spread is mainly due to the coupling between the longitudinal and transverse motion of the particles, and is reversible. When the beam is over-focused, not only the beam energy spread increases, but also the distribution shape of the energy spread changes. This may be due to collision at the crossover, and is irreversible. Further theoretical and computational investigation on this phenomena is underway.

The experimental study of this problem and some computer simulation results are summarized in a paper entitled "Time-Resolved Energy Measurement of Short Electron Beam Bunches by Both Retarding and Deflecting Field Energy Analyzers", which is to be submitted for publication. An abstract entitled "Longitudinal Kinetic Energy Spread from Focusing

Figure 2: Linear space-charge force along the parabolic bunch, where $t = 0$ corresponds to the center of the bunch with an energy of 2.5 keV.

in Charged Particle Beams" has been submitted to the 1993 Particle Accelerator Conference, Washington, DC, May 17-20, 1993.

2.2.3 Study of longitudinal dynamics of parabolic beams

The longitudinal dynamics, including drifting expansion and compression, of parabolic beams has been studied extensively since last year. With the injector only, we have, for the first time, experimentally demonstrated the linear space-charge force along such a beam. This result is shown in Fig. 2. A paper entitled "Longitudinal Expansion of Space-Charge Dominated Drifting Beam Bunches with a Parabolic Line Charge Density Distribution" summarizes the measurement and analysis of this study. The paper will be published in Applied Physics Letters.

After completion of the compression channel, we have experimentally verified the longitudinal envelope equation through the measurement of the beam drifting expansion and compression. The beam bunch length as a function of the drifting distance is shown in Fig. 3, where a good agreement between the experiment and theory is found. A paper entitled

Figure 3: Beam bunch length vs. drifting distance during expansion and compression, where the circles are the experimental data points while the solid lines are from the longitudinal envelope equation.

“Experimental Investigation of Longitudinal Beam-Envelope Changes of a Drifting Space-Charge Dominated Parabolic Beam” describes the details of this study. The paper is to be submitted for publication to Applied Physics Letters.

2.2.4 Study of longitudinal dynamics of rectangular beams

The longitudinal expansion and compression of rectangular beams have been studied experimentally on the long periodic focusing channel. Due to the strong nonlinear longitudinal force on the edges of the beam, the beam ends erode rapidly during the drifting expansion. A scenario of such a process is illustrated in Fig. 4. When a linear tilt of velocity is added to the beam by the induction module, the beam performs longitudinal compression while it propagates down the channel. This can be seen in Fig. 5. A paper entitled “Longitudinal Drift Expansion and Compression of Electron Bunches in a Periodic Solenoid Focusing Transport Channel” was presented in the 16th International Linac Conference, Ottawa, Ontario, Canada, August 23-28, 1992, and describes this experiment in more detail.

Figure 4: Longitudinal expansion of a rectangular beam, where the five signals are from the five wall-current monitors.

Figure 5: Longitudinal compression of a rectangular beam as measured by the five wall-current monitors.

The simulation of the expansion and compression of both parabolic and rectangular beams is underway in collaboration with Dr. I. Haber of NRL. A comparison between the experiments and simulation is to be made in the near future.

2.3 Longitudinal Instability Experiments

2.3.1 Theoretical studies

The longitudinal instability has been studied theoretically for space-charge dominated beams in transport channels with complex impedances. Departing from previous studies in this area, we have taken all the relevant parameters including the space-charge force, the complex wall-impedances, and the beam energy spread into account. The growth rate of the instability for monoenergetic beams are discussed in different parameter ranges. The stable regions for hot beams are analyzed with examples.

In February, we presented a talk entitled "Studies of the Longitudinal Instability with an Electron Beam" at the Workshop on Longitudinal Instability in Induction Linacs for Heavy Ion Driven Inertial Confinement Fusion, Lawrence Berkeley Laboratory, Berkeley, CA. The talk appears in the workshop proceedings. Some results of this study were presented at the 19th IEEE International Conference on Plasma Science, Tampa, FL, June 1-3, 1992, and at the 16th International Linac Conference, Ottawa, Ontario, Canada, August 23-28, 1992. A paper entitled "Longitudinal Instability of Space-Charge Dominated Beams in Transport Channels with Complex Wall Impedances" summarizes this study and has been submitted for publication to *Physics of Fluids B*.

2.3.2 Generation and propagation of space-charge waves

In the first phase of the longitudinal instability experiment, we have been studying the generation of space-charge waves from local perturbations and their propagation along the periodic solenoid channel. The local perturbation is introduced to the beam through the grid-cathode pulse on the electron gun. The beam and the perturbation are diagnosed by the five fast current monitors and three energy analyzers. Figure 6 shows the current waveforms with the perturbation, measured by the current monitors. On the left of the

Figure 6: Current waveforms with perturbation from the first current monitor (left) and the fourth current monitor (right), showing propagation of two space charge waves.

figure the current waveform is from the first current monitor which is 0.624 m away from the electron gun. On the right, the current waveform is measured by the fourth current monitor at a distance of 4.3 m from the gun, illustrating the further apart of the two space charge waves. The energy measurement by the second retarding field energy analyzer is shown in Fig. 7 where the excess energy of the two waves above the beam average energy is plotted. Figure 8 shows the separation of the two waves as a function of the propagation distance. A comparison with the theory is also made in the figure.

2.3.3 Status of resistive-wall instability experiment

An effort was made last spring to run the resistive-wall instability experiment. Unfortunately, the glass tube was broken during installation. After the tube was rejoined with a short length of 0.7 m and much lower resistance of about 1.5 kW/m, it was believed that a meaningful experiment could not probably be performed with such a component. Besides, the electron beam injector was going to be engaged in the compression experiment soon. Therefore, we decided to postpone the resistive-wall experiment.

Figure 7: Excess energy carried by two space charge waves, measured by the second retarding field energy analyzer.

Figure 8: Time interval between two space-charge waves vs. drifting distance. The stars represent measurements from the wall-current monitors, the crosses are data points from the energy analyzers, and the solid line is from the theory. The rather larger deviation of the last two points from the theory is not yet understood.

A new resistive tube has been received (January 1993) from the Chinese Vacuum Institute in Beijing.

2.4 Experiment to Measure the Boersch Effect

Energy spread is an important factor in determining the quality of a charged particle beam. It has several sources, including exchanges between potential, longitudinal and transverse kinetic energy in expansion and focusing; temperature relaxation due to collisions; and temperature increase from collisions in a crossover. The latter two are known as the Boersch effect. We are developing an experiment to measure the energy distribution resulting from all of these sources in various combinations, culminating with a comparison between experimental and theoretical results for the energy distribution from all sources combined. Previous experiments have only measured the energy spreads due to beam expansion and particle collisions, each separately. Achievements during the past six months are as follows.

2.4.1 New energy analyzers

Three new parallel-plate energy analyzers have been built. Energy spread due to space-charge expansion and focusing is predicted to depend on radius within the beam. Each of the new energy analyzers masks out a different portion of the beam in order to test the dependence of energy spread on radius.

2.4.2 Modification of the long-pulse injector

The long-pulse injector as shown in Fig. 9 has been mounted on a platform which will allow more accurate alignment of the beam for focusing and matching into the solenoid. It will also allow us to make changes in the beam channel while maintaining the vacuum on the cathode.

2.4.3 Energy spread from focusing

Theoretical work has been completed on the energy distribution due to focusing by a series of magnetic solenoid lenses (paper to be given at the 1993 Particle Accelerator Conference).

Schematic of Long-Pulse Injector

Figure 9: Configuration of the long pulse injector.

The results compare well with measurements made after the three matching lenses of the periodic channel. Measurements have also been made after 24 lenses in the periodic channel, showing a full-Maxwellian distribution due to interparticle collisions.

3 Proposed Research

3.1 Longitudinal Pulse Compression Experiments

The longitudinal compression experiment so far has mainly been studied by measuring the current waveform at five different locations along the channel. Due to a rather large jitter from the pseudospark switch, it is difficult to perform good energy measurement. Improvement of the pseudospark switch is underway. We will continue to run the longitudinal compression experiment next year. The energy measurement during the compression process will be enhanced in the future.

For rectangular pulses we will study the reformation of the pulse shape. Theory shows that a rectangular pulse will become a cusp shape at some point during drifting expansion. The velocity tilt is linear at this point. If an opposite velocity tilt is added to the pulse at this moment, the pulse will become rectangular again with a higher energy at a later time. We call this process reformation of the rectangular pulse. This could be a new acceleration mechanism for high current bunches. The experimental verification of the process will be conducted next year.

We will also run computer simulation for the compression process and compare with the experimental results.

3.2 Longitudinal Instability Experiments

Following this year's experiment of the propagation of local perturbations on the beam in the periodic channel, the study of the space-charge waves will focus on the end reflection effect of the perturbation. The difficulty in performing this experiment is to hold the beam edge from drifting expansion. The induction module originally designed for the compression experiment has a slow response and cannot achieve this goal. A new modulator needs to be developed to fulfill this task. In addition, theoretical analysis and computer simulation will be conducted in order to compare with the experiments. We expect to run the resistive-wall instability experiment next year. The new tube is expected to arrive in a couple of months. Most of the components for the experiment are ready to be installed in the system. After

the new injector is disassembled from the compression experiment, we can start to assemble the system and to run the experiment. The goal for the first step of the experiment is to measure the growth rate of the slow wave and verify the theory which we have been working on in the past.

3.3 Experiment to Measure the Boersch Effect

The beam from the long-pulse injector will be focused into the solenoid which has already been built for the resistive wall instability experiment. Matching and mismatching the beam within the solenoid will enable us to separate the energy spread resulting from two sources: temperature relaxation and crossover collisions. Work is now in progress using the KV code to focus and match the beam to a small radius in the solenoid. Measurements will then be made of the energy distribution at three locations: immediately after emission, after the focusing and matching lenses, and after transport through the solenoid, followed by a final focusing lens. The goal is to find the energy distribution from each source, and from all sources in combination, making comparisons with theoretical results for each case.

4 Papers and Presentations Resulting from this Research

1. J. G. Wang, M. Reiser, W. M. Guo, and D. X. Wang, "Theoretical Study of the Longitudinal Instability and Proposed Experiment", *Particle Accelerators*, vol. 37-38, pp. 181-189 (1992).
- *2. J. G. Wang, D. X. Wang, and M. Reiser, "Electron Beam Injector for Longitudinal Beam Physics Experiments", *Nucl. Instr. & Meth. in Phys. Res.* **A316** (1992) 112-122.
3. M. Reiser and J. G. Wang, "Studies of the Longitudinal Instability with an Electron Beam", *Proceedings of the Workshop on Longitudinal Instability in Induction Linacs for Heavy Ion Driven Inertial Confinement Fusion*, Lawrence Berkeley Laboratory, Berkeley, CA, February 26 and 27, 1992, Edited by Edward P. Lee, HIFAN-540.
4. D. X. Wang, J. G. Wang, and M. Reiser, "Longitudinal pulse compression experiments at the University of Maryland", presented at the 1992 Spring Meeting of the American Physical Society, Washington, DC, April 20-24, 1992.
5. J. G. Wang, M. Reiser, W. M. Guo, and D. X. Wang, "Longitudinal instability experiment at the University of Maryland", presented at the 1992 Spring Meeting of the American Physical Society, Washington, DC, April 20-24, 1992.
6. D. X. Wang, J. G. Wang, and M. Reiser, "Time-Resolved Beam Energy Measurement of Short Electron Beam Bunches with a Longitudinal Velocity Tilt", to be published in the *Proceedings of the 9th International Conference on High-Power Particle Beams*, Washington, DC, May 25-29, 1992.
7. J. G. Wang and M. Reiser, "Longitudinal Instabilities of Intense Beams in a Transport Channel with Complex Impedances", presented at the 19th IEEE International Conference on Plasma Science, Tampa, FL, June 1-3, 1992.
8. J. G. Wang and M. Reiser, "Analysis of the Longitudinal Instability of Intense Beams in a Transport Channel with Complex Wall Impedances", in the *Proceedings of the*

9. D. X. Wang, J. G. Wang, and M. Reiser, "Longitudinal Drift Expansion and Compression of Electron Bunches in a Periodic Solenoid Focusing Transport Channel", in the Proceedings of the 16th International Linac Conference, Ottawa, Ontario, Canada, August 23-28, 1992, Vol. 2, pp. 489-491.
- *10. J. G. Wang, D. X. Wang, D. Kehne, and M. Reiser, "Longitudinal Expansion of Space-Charge Dominated Drifting Beam Bunches with a Parabolic Line Charge Density Distribution", accepted for publication in Applied Physics Letters.
- *11. J. G. Wang and M. Reiser, "Longitudinal Instability of Space-Charge Dominated Beams in Transport Channels with Complex Wall Impedances", submitted for publication to Physics Fluids B.
12. D. X. Wang, J. G. Wang, D. Kehne, and M. Reiser, "Experimental Studies of Longitudinal Beam Dynamics of Space-Charge Dominated Beams", submitted to the 1993 Particle Accelerator Conference, Washington, DC, May 17-20, 1993.
13. J. G. Wang, D. X. Wang, D. Kehne, and M. Reiser, "Propagation of Local Perturbation in Space-Charge Dominated Electron Beams", submitted to the 1993 Particle Accelerator Conference, Washington, DC, May 17-20, 1993.
14. N. Brown, M. Reiser, D. Kehne, D. X. Wang, and J. G. Wang, "Longitudinal Kinetic Energy Spread from Focusing in Charged Particle Beams", submitted to the 1993 Particle Accelerator Conference, Washington, DC, May 17-20, 1993.
- *15. D. X. Wang, J. G. Wang, D. Kehne, and M. Reiser, "Experimental Investigation of Longitudinal Beam-Envelope Changes of a Drifting Space-Charge Dominated Parabolic Beam", to be submitted for publication.
16. D. X. Wang, J. G. Wang, and M. Reiser, "Measurement of Electron Beam Energy Spread due to Longitudinal Space-Charge Forces", to be submitted for publication to Scientific Instruments.

*Copies of these papers are enclosed in Appendix A.

TASK B

**Study of Collective Ion Acceleration by Intense Electron Beams
and Pseudospark-Produced High Brightness Electron Beams**

Contents

1	Introduction and Synopsis	B1
2	Research Progress	B1
2.1	Research on Collective Field Accelerators - Laser Controlled Beamfront Accelerator Experiments	B1
2.2	Research on Pseudospark-Produced Electron Beams	B2
2.2.1	Time-Resolved Energy Spectrum of a Pseudospark-Produced Electron Beam	B2
2.2.2	Post-Acceleration Experiment	B3
2.2.3	Beam Quality and Other Accelerator Studies	B3
2.3	Pulse-Line Driven Pseudospark Experiments	B4
2.4	Pseudospark Modeling	B5
2.4.1	Parallel-Plate Model — Parameter Space	B5
2.4.2	Results	B6
3	Proposed Research on High Brightness Beams Generated in Pseudospark Discharges	B9
3.1	Post-Acceleration Experiment	B9
3.2	Beam Transport Study	B9
3.3	Experimental Study of Hollow Cathode Phenomena	B9
3.4	Pulse-Line Driven Pseudospark Experiments	B9
3.5	Pseudospark Modeling	B10
4	Papers and Presentations Resulting from this Research	B12
	Appendix	B15

1 Introduction and Synopsis

Task B of this contract is concerned with experimental and theoretical studies of intense pulsed-power electron beam systems and their applications to advanced accelerator concepts. In particular, work supported under Task B has been focused around two experimental projects; the laser-controlled collective ion accelerator and studies of high brightness electron beams produced in pseudospark discharges. Although progress on the laser-controlled collective accelerator has been steady and the basic concept has been validated, our quest for even higher accelerated ion energies has been hampered by the voltage and pulse duration limitations of our existing intense beam sources. As a result almost all of our research activity over the past year has been concentrated on the studies of hollow cathode pseudospark discharges as high-brightness electron beam sources. Based on experiments conducted in our laboratory over the past three years, we believe that this new class of high-brightness electron beam source may have important applications in such diverse areas as linear colliders, free electron lasers, rf sources, high power switching systems, and materials processing. In fact, our experiments indicate that beams can be generated in pseudospark discharges with brightness values in the range $10^{12} - 10^{13}$ Amp /m²-rad². These values are greater than those achieved even in photocathode beam sources at substantially greater system cost and complexity. This work is summarized in Section II.B

2 Research Progress

2.1 Research on Collective Field Accelerators - Laser Controlled Beamfront Accelerator Experiments

During the past year, the second-generation Laser-Controlled Beamfront Accelerator has been tested and ion acceleration experiments have been undertaken at a number of accelerating gradients. The experiment was designed to accelerate protons over a 100 cm distance at gradients up to 60 MeV/m using electron beams with energies in the range 1.2-1.5 MeV. Although effective controlled acceleration over 50 cm at a gradient of 40 MeV/m has been previously demonstrated, the latest experiments have failed to produce higher energy ions than have previously been observed. This negative result is attributed to the voltage and pulse duration limitations of our existing intense beam sources. In particular, although our

largest pulsed electron beam source can produce appropriate electron beams with energies in the range 1.2 - 1.5 MeV, the pulse shape and duration allow for the production of such beams for only about 15 ns. The experimental laser beamfront control system requires pulse durations of at least 25 ns for beamfront control over the full 100 cm accelerating distance. Since funds are not available to upgrade the pulsed electron beam source for longer pulse duration, these experiments have been terminated as discussed in the original Task B proposal.

2.2 Research on Pseudospark-Produced Electron Beams

We are conducting the first comprehensive study of the generation of high-power, high brightness electron beams for advanced accelerator applications using pseudospark discharges. Unlike previous studies in this area, we are studying not only low voltage devices, but the scaling of such devices to voltages and currents comparable to those achieved in pulse line accelerators. In this manner, the high brightness beams generated may be more easily controlled and extracted for injection into advanced accelerators, free electron lasers, or for other possible applications. Thus a primary goal of this research is the production of kiloampere high-brightness electron beams from such discharges with electron energies in the range 0.2 - 1 MeV.

2.2.1 Time-Resolved Energy Spectrum of a Pseudospark-Produced Electron Beam

A time-resolved energy spectrum of a pseudospark-produced electron beam has been obtained by using a simple device developed recently. A small portion of the electron beam is sampled on axis and injected into a vacuum. The electrons passing through a negatively biased electrode are measured by a Faraday cup. The time-resolved energy spectrum is determined by analyzing the Faraday-cup current waveforms measured at various bias voltages. The resultant spectrum reveals that the instantaneous beam energy is nearly monoenergetic. The energy decreases monotonically in time in a manner resembling the anode-cathode voltage waveform. Results of this experimental study are detailed in the paper, "Time-resolved energy spectrum of a pseudospark-produced electron beam", submitted to the Rev. Sci. Instrum and enclosed in the Appendix.

2.2.2 Post-Acceleration Experiment

A simple induction linac system of 25 kV, 1 kA, 50 ns pulse has been used to post-accelerate the electron beam produced by the pseudospark. The pseudospark-generated electron beam that is propagating in a low pressure gas is accelerated by the induction linac. The time-resolved energy spectra before and after the post-acceleration were measured using the technique described above. The resultant spectra reveal that the instantaneous beam energy is approximately equal to the sum of the cathode voltage and the induction-linac accelerating voltage. Results of this study are detailed in the paper, "Post Acceleration of a Pseudospark-produced High-brightness Electron Beam" to be published in the proceedings of Beams '92 and enclosed in the Appendix.

2.2.3 Beam Quality and Other Accelerator Studies

2.2.3.1 Analyses of beam brightness

The beam brightness is a figure of merit for beam quality useful for high-current low-emittance beams. The lack of preciseness in the original definition (van Steenberg) $B = I/V_4$, or alternative expression in terms of emittance (J. D. Lawson) $B = \eta I / (\pi^2 \epsilon_x \epsilon_y)$ has been an important concern in the high-brightness beam community. As an attempt to remove ambiguity in the definitions, the definition has been redefined as the arithmetic mean of the distribution. Using this definition, brightnesses of a few commonly used beam distributions have been determined and the form factor η have been shown to be nearly equal to unity. Results of this study are published in the paper, "Refined Definition of the Beam Brightness," Phys. Fluids B 4, 1674 (1992) enclosed in the Appendix.

In order to see to what extent the unity form factor is valid, we also examined cases of a few double-humped distributions. The double-humped distribution is comprised of two identical beams displaced by a variable separation distance. It is found that the form factor remains relatively constant and close to unity for a wide range of the separation. Results of this study are detailed in the paper, "Refined Definition of the beam brightness as the arithmetic mean of the distribution function," to be published in the Proceedings of Beams '92 and enclosed in the Appendix.

2.2.3.2 Square pulse generation by inductive pulse forming lines

An important merit of the inductive energy pulsed power system is its compactness of

size. We proposed use of two inductive pulse forming line systems, the current charged transmission line and the dual of the Blumlein line, as inductive energy storage. These systems are of particular interest, because of their capability of square pulse generation. Efficient power multiplication can be achieved in these systems by simply narrowing the duration of the square output pulse for a given stored energy. Using an n-channel MOSFET as an opening switch, we demonstrated that efficient square pulse generation can be achieved. Results of this study are detailed in the paper "Simple Methods of Square Pulse Generation by Inductive Pulse Forming Lines and a Field Effect Transistor as an Opening Switch," to be published in the Proceedings of Beams '92 and enclosed in the Appendix.

2.3 Pulse-Line Driven Pseudospark Experiments

One goal of this research program is to determine if the very high brightness electron beams generated in pseudospark devices can be scaled to the energies and currents usually associated with high power pulse-line accelerators. If high brightness electron beams can be generated with electron energies in the range 100-1000 keV and currents in excess of 1 kA, then such devices could find immediate application in such diverse areas as coherent radiation sources, free electron lasers, and advanced accelerators. For this reason, we embarked upon an ambitious project to mate a pseudospark device to the DRAGON pulse line accelerator (100-1000 kV, 1-130 kA, 100ns) at the University of Maryland.

Initial results from this experimental program are detailed in the paper "High Power, High-Brightness Electron Beam Generation in a Pulse-Line Driven Pseudospark Discharge", submitted for publication to Applied Physics Letters and enclosed in the Appendix to this report. In these studies, high brightness ($\sim 10^{10}$ Amp²/m²-rad²), high power density ($\sim 10^{10}$ W/cm²) electron beams have been generated with energies in the range 150-300 keV and currents in the range 500-1000 A. Beam diameter is estimated to be only about 1 mm with effective emittances at or below 170 mm-mrad. Beam pulse duration at high electron energy is about 20 ns.

These results, although very preliminary in nature, clearly indicate the potential of hollow cathode discharges to produce high quality electron beams at the energies and currents usually associated only with those produced in field emission diodes where beam brightness is typically orders of magnitude lower and effective beam emittance is almost always much larger. Further experimentation is currently underway with the goal of increasing beam

energy, brightness, and pulse duration.

2.4 Pseudospark Modeling

In last year's annual report we presented initial results obtained from our hollow-cathode model. The geometry of the hollow cathode model is two-dimensional (r, z) with an applied anode-cathode voltage, V_0 . The background gas is helium at a pressure p . The physics included in the model is electron emission from the cathode surfaces due to ion bombardment (a single emission rate of 0.5 was used) and ionization of the gas by the electrons and ions. The charged particle (macroparticle) motion is determined by Newton's equation of motion and Poisson's equation plus the effects of collisions with the background neutral gas via a "local-field" approximation. This model is similar to that in the article by J.-P. Boeuf and L.C. Pitchford[1] with the addition of ionization of the gas by the charged particles. At $t = 0$ an initial neutral plasma background density n_{p0} is assumed and the system evolves per the above described physics and particle motion. We were unable to obtain a picture of "gas breakdown" and subsequent electron beam production. This was due to the fact that to obtain results for one set of parameters – V_0 , geometry, p , n_{p0} – it took days. The plasma production process takes hundreds of nanoseconds and space/time scales have to be small because of enhanced electric fields near the cathode hole, plasma frequencies, etc. At this point we set aside the hollow cathode model and developed a simple parallel-plate model. We have systematically added physics to this system and are able to study a relatively large parameter space in order to provide guidance for future hollow-cathode studies. The results reported below are from this new model.

2.4.1 Parallel-Plate Model — Parameter Space

The geometry of the model used to study "gas breakdown" and electron beam production is composed of parallel plates separated by a distance d with an applied voltage V_0 . A uniform gas density of helium, pressure p , fills the space between the plates. The initial condition is a low density charge neutral, uniform plasma of density n_{p0} of electrons and helium ions. The physics included in the model is impact ionization of the helium gas by electrons and helium ions[2] and cathode wall electron emission rate due to helium ion impact[3]. The electron emission rate is ion energy dependent, an important improvement from our constant value of

0.5 used in our initial simulations. The coefficient exceeds 1.0 for helium ions above about 1 keV. It should be noted that we use helium versus argon gas because of the available cross-section data for many processes. The helium ionization cross-sections are about a factor of 10 lower than the argon ionization cross-sections, thus requiring pressures about a factor of 10 higher. The electron and helium ion macroparticle motion is determined by Newton's equation of motion and Poisson's equation. At this point we have not included collision effects. The parameter regimes being studied are $0 < V_0 < 50$ kV and $1 < d < 50$ cm, and the helium gas pressure p is varied.

2.4.2 Results

For a nominal set of parameters the simulation evolves as follows. As the initial charged particles n_{p0} are accelerated from rest by the applied field V_0/d , they ionize the background gas before they leave through the anode (electrons) or cathode (helium ions). If the pressure is too low the system becomes void of charged particles and nothing further happens. Above a critical pressure $p = p_c$ the plasma density increases and ultimately a steady state is achieved between charged particles leaving the system and those being produced via ionization or electron emission from the cathode. A typical plot of potential V versus z and charged particle densities $n_{He} = n_i$ and n_e versus z is shown in Figure 1a and b after the system has achieved steady state. This usually takes 100 nsecs or so. For the case shown, a large region of the space between the plates is occupied by a charge neutral plasma. The width of the space increases as the pressure p increases above the critical value p_c . Note that the electric field at the cathode increases rapidly for $p > p_c$. (We have incorporated field enhanced electron emission[4] at the cathode but to date in the parameter regimes examined this process is not important.) In Fig. 1c we have plotted electron current passing through the anode versus time. In this pressure regime, the current is very low until steady-state has been achieved. For the case shown, the rapid current increase starts at about 100 nsec and steady-state conditions are achieved in about 20-40 nsec, at which time about 1 A/cm² is passing through the anode.

In Tables 1-3 we summarize the results for the parameter spaces examined to date. In Table 1 we have tabulated the critical pressure p_c for a plate spacing of 1 cm for voltages from 100 V to 50 kV. In Table 2, for a plate spacing of 1 cm and a pressure $p = 2$ torr ($> p_c$), the steady-state electron current I_e is tabulated versus the applied voltage. Note the rapid

Figure 1: Nominal results from parallel plate model of gas breakdown. System parameters: $V_0 = 5$ kV, $d = 1$ cm, $p = 2$ torr Helium. (a) V vs. z at $t=0.148$ μsec ; (b) n_i and n_e vs z at $t = 0.148 \mu\text{sec}$; (c) I_e passing through the anode vs. time.

Table 1: Critical pressure p_c above which steady-state current flow can occur as a function of anode-cathode voltage V_0 and spacing d .

V_0 (kV)	0.1	0.2	0.5	1.0	2.0	5.0	10.0	20.0	50.0	20.0
d (cm)	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	1.0	5.0
p_c (torr)	2.3	1.4	0.9	0.8	0.8	1.0	1.0	1.1	1.3	0.25

Table 2: Steady-state electron current through the anode as a function of anode-cathode voltage V_0 for spacing $d = 1$ cm and pressure $p = 2$ torr of helium.

V_0 (kV)	1	5	10	20
I_e (A/cm ²)	0.035	0.94	3.78	11.54

increase in I_e , becoming greater than 10 A/cm² for $V_0 \geq 20$ kV. In Table 3 we tabulate the components that contribute to I_e versus applied voltage V_0 for $d = 1$ cm, $p = 1$ torr. Note from Table 1 that $p = 1$ torr is greater than p_c only in the voltage region $\sim 0.3 < V_0$ (kV) < 5.0 . Also note that the electron current contribution from electron ionization of the helium gas dominates from 0.4 kV to ~ 1.2 kV and then the electron current resulting from cathode wall emission becomes dominant for $V_0 > 1.5$ kV.

In summary we are encouraged by the results from this simple model. We have obtained electron currents greater than 10 A/cm² in the limited parameter space studied to date. In the proposed research section we will delineate some concerns with the present model as well as the direction of our studies in the near future.

Table 3: Steady-state electron current through the anode as a function of the anode-cathode voltage V_0 for spacing $d = 1$ cm and pressure $p = 1$ torr of helium. Total current and contribution of each process; due to ion ionization $I_{e,i}$, due to electron ionization, $I_{e,e}$, and due to ion impact on the cathode surface, $I_{e,wall}$.

V_0 (kV)	0.4	0.6	0.8	1.0	1.2	1.5	2.0	2.5	3.0	4.0	5.0
I_e (mA/cm ²)	0.94	2.91	6.10	11.15	14.16	22.93	38.27	55.53	82.41	121.9	181.3
$I_{e,i}$ (mA/cm ²)	0.20	0.53	1.01	1.67	2.11	3.18	4.92	6.88	9.55	13.9	19.6
$I_{e,e}$ (mA/cm ²)	0.52	1.59	3.12	5.27	6.22	9.34	13.74	17.49	24.32	29.7	32.6
$I_{e,wall}$ (mA/cm ²)	0.21	0.79	1.96	4.21	5.83	10.41	19.62	31.17	48.54	78.3	123.4

3 Proposed Research on High Brightness Beams Generated in Pseudospark Discharges

3.1 Post-Acceleration Experiment

Preliminary results of post-acceleration experiment are very encouraging and these studies will be continued. Presence of the background gas which is necessary for self-focusing the beam appears to have no effect on the acceleration of main beam. However, it is expected to observe some unfavorable effect such as acceleration of low-energy plasma electrons and shorting the accelerating gap.

3.2 Beam Transport Study

We observed that while the beam is propagating through the drift space in the induction linac, the beam current is reduced by a good fraction compared to the current measured at the anode. Despite the fact that the ion channel created neutralizes the space-charge field of the beam and produces focusing force, we observe that the beam is diverging as it propagates downstream. However, it is not clear whether this beam diverging is the main cause of beam loss or other mechanisms such as beam-neutral gas scattering are responsible. We will study beam transport in more detail to address these questions.

3.3 Experimental Study of Hollow Cathode Phenomena

To date the exact mechanism of the pseudospark discharge is not completely understood. The hollow cavity in the cathode is responsible for interesting phenomena such as the fast discharge and the production of the charged particle beams. In addition to our previous experimental studies, systematic measurements of the electric field and the emission of electrons and ions in the hollow cavity will be performed.

3.4 Pulse-Line Driven Pseudospark Experiments

Over the next year, it is proposed to continue our very promising high-voltage pseudospark experiments with the goal of increasing beam brightness, energy, and pulse duration. In addition to basic scientific studies that are aimed at exploring the basic operational limitations

of pulse-line driven pseudospark devices, we plan additional studies in the following areas:

a) In our initial experiments the DRAGON pulse-line accelerator was modified to produce a 1 μ sec pulse, since our experience with low voltage pseudospark devices indicated that longer pulse durations were required to establish the hollow-cathode discharge. We are presently preparing an experiment to directly connect a pseudospark device to the 100 ns pulse line output of DRAGON to determine if effective operation can still be obtained with the shorter charging time. If successful, then operation at higher beam current levels and greater overall efficiency may be possible.

b) Since the observed high-brightness electron beams are generated in an ion background associated with the pseudospark discharge, experiments are planned to investigate the extraction of the high-brightness electron beams out of the plasma into vacuum in the presence of a confining magnetic field. These experiments are important to possible future applications of such beams.

c) Improved measurements of the beam emittance are essential if we are to obtain a more accurate estimate of beam brightness (previous estimates are actually lower bounds to what may have been achieved). For this reason we are constructing an emittance measurement system capable of measuring beam emittance on a single shot. This system will be constructed and tested during the next grant period.

3.5 Pseudospark Modeling

In the parameter regimes where electron ionization is dominating the contribution to total electron current, we will improve our model on the motion of the electron macroparticle. This is necessary since electron ionization is most important when electron energies are 100-300 V where the loss of energy due to ionization could be a reasonable fraction of the initial electron energy.

In the next few months we will complete our planned parameter space studies with our parallel plate model. Using the "best" results, we will perform simulations with our hollow-cathode model. These results will be presented at the 1993 PAC in Washington, DC (abstract attached).

Our goal in all these studies is to determine the dominant physical processes in the parameter space of "gas breakdown" and electron beam production. The parallel plate model will aid in identifying the dominant processes. The hollow cathode model will be used to

compare directly to the experimental results and it will evolve (geometry and physics) as we become more confident in the results.

References

- [1] J.-P. Boeuf and L.C. Pitchford, *IEEE Plasma Science* **19**, 286 (1991).
- [2] R.K. Janev, et al. *Elementary Processes in Hydrogen-Helium Plasmas*, Springer-Verlag, 1987.
- [3] B. Chapman, *Glow Discharge Processes*, Wiley & Sons, 1980, p. 87.
- [4] W.P. DYKE and W.W. Dolen, *Advances in Electronics and Electron Phys.*, L. Marbon, editor (1956), p. 89.

4 Papers and Presentation Resulting from this Research

1. K. K. Jain, B. N. Ding, and M. J. Rhee, "Scaling Study of Pseudospark Produced Electron Beam," in Proceedings of 1991 IEEE Particle Accelerator Conference, .
2. M. J. Rhee and B. N. Ding, "Beam Loading in a High Current Accelerating Gap," To be published in Proceedings of 1991 IEEE Particle Accelerator Conference p. 2999.
3. K. A. Boulais and M. J. Rhee, "Root-Mean-Square Emittance Analysis of a Multiple Beam System," To be published in Proceedings of 1991 IEEE Particle Accelerator Conference.
4. M. J. Rhee and R. F. Schneider, "Phase-Space Measurement of a Beam with a Maxwellian Transverse Velocity Distribution by a Finite-Width Slit," Rev. Sci. Instrum. 62, 1468 (1991).
5. M. J. Rhee and K. A. Boulais, "Root-Mean-Square Emittance of Multiple Beam Systems," Phys. Fluids B 3, 1781 (1991).
6. M. J. Rhee and B. N. Ding, "Breakdown Voltage Characteristic of a Pseudospark Device," To be published in Phys. Fluids B 4, xxx (1992).
7. K. A. Boulais AND M. J. Rhee, "Root-Mean-Square Emittance Analysis of a Multiple Beam System," Bull. Am. Phys. Soc. 36, 1509 (1991).
8. K. K. Jain and M. J. Rhee, "Scaling Study of Pseudospark Produced Electron Beam," Bull. Am. Phys. Soc. 36, 1590 (1991).
9. M. J. Rhee, "Beam Loading in a High Current Accelerating Gap," Bull. Am. Phys. Soc. 36, 1647 (1991).
10. K. A. Boulais and M. J. Rhee, "Analysis of RMS Emittance for Multiple Beam Systems," IEEE Conference Record-Abstracts, 1991 IEEE International Conference on Plasma Science, p. 214 (1991).

11. B. N. Ding, K. K. Jain, and M. J. Rhee, "Scaling Study of Pseudospark Discharge," IEEE Conference Record-Abstracts, 1991 IEEE International Conference on Plasma Science, p. 217 (1991).
12. M. J. Rhee and B. N. Ding, "Transmission Line Model of Beam Loading in a High-Current Accelerating Gap," IEEE Conference Record-Abstracts, 1991 IEEE International Conference on Plasma Science, p. 214 (1991).
13. B. N. Ding, S. W. Chang, and M. J. Rhee, "Current and Emittance Scaling of Electron Beam Produced in a Multigap Pseudospark Device," Bull. Am. Phys. Soc. 36, xxx (1991).
14. M. J. Rhee and B. N. Ding, "Beam Loading in a Multigap High Current Accelerator," Bull. Am. Phys. Soc. 36, xxx (1991).
15. S. H. Cho, B. N. Ding, and M. J. Rhee, "Capacitor Shunted Opening Switch," Bull. Am. Phys. Soc. 36, xxx (1991).
16. B. N. Ding, T. J. Myers, and M. J. Rhee, "Post-Acceleration of a Pseudospark-Produced Electron Beam by an Induction Linac," IEEE Conference Record-Abstracts, 1992 IEEE International Conference on Plasma Science, p. 104, (1992).
17. T. J. Myers, B. N. Ding, and M. J. Rhee, "Time-Resolved Energy Spectrum of a Pseudospark-Produced High-Brightness Electron Beam," IEEE Conference Record-Abstracts, 1992 IEEE International Conference on Plasma Science, p. 120, (1992).
18. T. J. Myers, K. A. Boulais, and M. J. Rhee, "Beam Brightness Calculation for Analytical and Empirical Distribution Functions," IEEE Conference Record-Abstracts, 1992 IEEE International Conference on Plasma Science, p. 140, (1992).
19. B. N. Ding, T. J. Myers, and M. J. Rhee, "Simple Methods of Square Pulse Generation by Inductive Pulse Forming Lines and a Field Effect Transistor as an Opening Switch," IEEE Conference Record-Abstracts, 1992 IEEE International Conference on Plasma Science, p. 163, (1992).
20. M. J. Rhee and K. A. Boulais, "Analysis of Beam Brightness for Multiple Beam Systems," Bull. Am. Phys. Soc. 37, 1455, (1992).

21. B. N. Ding, B. K. Classon, and M. J. Rhee, "Study of Post-Acceleration and Transport of the Electron Beam Produced by a Triggered Pseudospark," *Bull. Am. Phys. Soc.* 37, 1462, (1992).
22. M. J. Rhee and B. N. Ding, "Breakdown Voltage Characteristic of a Pseudospark Device," *Phys. Fluids B* 4, 764 (1992).
23. M. J. Rhee, "Refined Definition of the Beam Brightness," *Phys. Fluids B*, 4, 1674 (1992).
24. W. W. Destler and S. Guharay, Eds., *High Brightness Beams for Advanced Accelerator Applications* (AIP Press, New York, 1992).
25. W. W. Destler and M. J. Rhee, "Pulse-Power Driven Pseudospark Devices for High-Brightness Beam Generation," invited paper, Proc. 5th SDIO/ONR Pulse Power Meeting, August 17-19, 1992, Conference Record, p. 39.
26. W. W. Destler, Z. Segalov, J. Rodgers, K. Ramaswamy, and M. Reiser, "High Power, High Brightness Electron Beam Generation in a Pulse-Line Driven Pseudospark Discharge," submitted to *Applied Physics Letters*, October, 1992.

TASK C

Study of a Gyroklystron High-Power Microwave Source for Linear Colliders

Synopsis

Building on the successful demonstration of a 27 MW, X-band gyrokystron amplifier, efforts are underway to study the feasibility of developing a gyrokystron which would have performance adequate for driving a future TeV linear collider. Target parameters for the gyrokystron include output power of 100 MW, pulse duration near 1 μ sec, and frequency of 17 GHz. At present the most promising configuration appears to be a coaxial gyrokystron circuit with the output cavity operating in the TE₀₂ mode at the second harmonic of the electron cyclotron frequency. A feasibility study of the second harmonic output cavity concept is underway using available equipment. Preliminary experimental results are promising with 7.5 MW output power being produced by a 2nd harmonic cavity operating at 19.7 GHz; experimental improvements are expected to increase output power to ~ 10 MW. Designs of a 100 MW gyrokystron circuit and the associated electron gun are well advanced; a modulator is being upgraded to accommodate such a large power level. Theoretical studies indicate the second harmonic gyrokystron is superior in performance to alternative configurations (viz., gyrotwistron or CARM). Efforts to optimize the design are proceeding, and procurement of a 400 MW electron gun is expected in the coming year.

1 Introduction

The gyroklystron amplifier is a leading alternate concept to conventional klystron amplifiers for driving future TeV-class linear colliders. It has recently been suggested¹ that three criteria be used to evaluate and compare the various amplifier options. These are as follows:

- (1) η_A amplifier efficiency (which will need to be modified by the efficiency of any pulse compression circuit);
- (2) V , voltage required to operate the microwave amplifier; and,
- (3) ℓ_1 , the length of accelerator structure which may be driven by a single amplifier tube at a chosen value of accelerator gradient.

Clearly one would like to have efficiency as close to 100% as possible to minimize both average power consumption and cost of power supplies. Amplifier voltage should be $\lesssim 800$ kV so that conventional soft-tube modulator technology can be used, and preferably V should be as small as possible to minimize the cost of such items as electron gun insulators. The parameter ℓ_1 , determines the total number of amplifiers which will be required; for example, a 1 TeV accelerator with a gradient $E_a = 100$ MV/m will have an overall length of $L = 10^4$ m and the number of amplifiers required will be $N_t = L/\ell_1$. To keep N_t reasonable (1000-2000), one would like to have $5 \text{ m} \lesssim \ell_1 \lesssim 10 \text{ m}$ for a 1 TeV collider.

The expression which we have derived¹ for ℓ_1 is in mks units

$$\ell_1 = 3.6 \times 10^{11} \frac{P_p \tau_p \eta_c}{E_a^2 \lambda^2}, \quad (1)$$

where P_p is the peak amplifier output power, τ_p is the pulse duration of the microwave pulse, and η_c is the efficiency of any pulse compression circuit used and is estimated as

$$\eta_c = 0.9^{\log_2(\tau_p/t_f)}, \quad (2)$$

where the structure fill-time t_f is

$$t_f \approx 2.3 \times 10^{-5} \lambda^{3/2}. \quad (3)$$

Table 1: Demonstrated microwave amplifier performance. (ℓ_1 is the length of accelerator which could be driven by the amplifier at $E_a = 100$ MV/m.)

Type of Amplifier	Research Institution	f (GHz)	λ (cm)	P_p (MW)	τ_p (μ s)	ℓ_1 (m)	V (kV)	amplif. effcy. η (%)	overall effcy. $\eta\eta_c$ (%)
klystron	SLAC	2.856	10.5	65	3.5	.59	350	45	36
klystron	SLAC	11.4	2.63	50	1.0	1.8	447	22	15
gyroklystron	U.Md.	9.85	3.05	27	1.4	1.0	425	32	22
FEL	MIT	33	0.91	61	0.02	.53	750	27	27
TWT	Cornell	8.76	3.42	200	0.1	.60	800	24	24
TW-klystron	Haimson	11.4	2.73	100	0.05	.24	440	43	43

(* $\tau_p < t_f$; took $\eta_c = 1$ in calculating ℓ_1)

In Table 1,^{1a} the demonstrated performance of various candidate amplifiers is tabulated for the purpose of comparison. The performance characteristics of the S-band SLC klystron is also tabulated.

It is seen that with both the X-band klystron under development at SLAC and the gyrokystron being developed by our group at the University of Maryland progress has been made in extending the ℓ_1 parameter over what is possible with the SLC production klystrons. However, values of ℓ_1 in the range between 1 and 2 are not sufficient for the needs of a TeV collider. Our present gyrokystron studies are aimed at extending ℓ_1 ; we are pursuing studies to evaluate the feasibility of developing a gyrokystron with the parameter ℓ_1 in the range 5 m to 10 m. For example, target parameters might be $P_p = 100$ MW, $f = 17$ GHz, $\tau_p = 0.86$ μ sec. These parameters correspond to $\ell_1 = 6.6$ m. Operation would be with the output cavity operating at the second harmonic of the electron cyclotron frequency in the TE₀₂ mode; aside from the output cavity, the rest of the circuit and the input signal would be near the fundamental cyclotron frequency (~ 8.5 GHz). Such an arrangement would keep magnetic field requirements reasonably low and would make circuit dimensions large enough

to handle the large power.

Among the most important of the feasibility studies being presently pursued is the demonstration of stable operation of a gyroklystron with a TE_{02} output cavity at the second harmonic of the electron cyclotron frequency. We have used the same electron gun, input signal and input cavity as in our fundamental mode 9.85 GHz gyroklystron whose operation is summarized in Table 1. Predicted efficiency for this feasibility demonstration experiment is 24%, and good initial progress has been made as described in Section 2 below. Also described in Section 2 is the modulator upgrade in preparation for the 100 MW output power experiment, and designs of 100 MW co-axial gyroklystron circuits.

In Section 3, alternative gyrotron configurations are considered theoretically. Specifically, a circuit using a travelling wave output section in place of a cavity (gyro-twistron), and a circuit operating far from cutoff (CARM) are both evaluated and compared with the second harmonic gyroklystron. Finally, proposed research is described Section 4.

Figure 1: A summary of the peak power performance for the fundamental mode gyrokystrons.

2 Experimental Research Progress

During the past year, we have made considerable progress in all areas of experimental effort. We completed the final two fundamental mode experiments. Those tubes performed well, but not better than earlier tubes, and added some insight into the mechanism for extracting power from the electron beam. A summary of the peak power performance for the ten fundamental mode tubes is shown in Fig. 1. The gain at each point is also indicated. The maximum power level of 27 MW closely approached the original design goal and showed the viability of the gyrokystron as a potential source for collider applications.

Two second harmonic designs have been tested. The first tube design was described in last year's progress report. The tube was plagued by many instabilities so that amplification studies could not be performed. The second tube had a shorter output cavity and modified drift sections. The threshold for oscillations was pushed back considerably, but were still more troublesome than in the fundamental system. Initial studies have yielded harmonic amplified powers up to 3.8 MW with modest efficiency ($\sim 8\%$) and gain (~ 16 dB). Two more tubes have been designed with shorter output cavities in an attempt to further improve stability. Both will be tested in the near future.

The effort on 100 MW systems has produced 400 MW Magnetron Injection Gun designs

for both 11.4 GHz and 17.0 GHz. It was found that single-anode designs performed better than their double-anode counterparts. Both designs have axial velocity spreads less than 10% throughout the current range of 0-800 A. Simulations also indicate that the guns can operate over a wide range of circuit magnetic fields. Furthermore, large-signal simulations have indicated that coaxial second harmonic circuits can produce efficient amplification. Initial cold tests of coaxial input cavities have produced the required resonant frequency and quality factor. Finally, construction of the modulator upgrade is well underway. The critical elements have been ordered and the PFN tank is almost complete.

We have continued to make progress in supporting areas as well. We have completed construction of our circuit breaks and designs of our new capacitive probes. Neither has been installed yet due to time constraints. We have also been working on tunable input cavities, coaxial supports, and new microwave absorber configurations. Details of the main efforts are detailed in the paragraphs below.

2.1 Three-Cavity Experiments

Over the course of the last few years there have been four different three-cavity circuits designed, constructed, and tested. Last year's annual report presented the experimental results of the first two circuits and the designs of the last two circuits. The first two circuits [see Reference 2] resulted in a peak power of 27 MW at 32% efficiency and 36 dB gain. The highest efficiency achieved was 37% at 16 MW and the highest gain achieved was 50 dB at 20 MW. These first two three-cavity circuits achieved power levels and efficiencies comparable to the two cavity circuits with the expected higher gain due to the penultimate [third] cavity. However, comparison of the experimental results with the predictions of our nonlinear code was not satisfactory. In the region of the operating parameters, the code predicted power levels about a factor of two lower. This led to the hypothesis that beam energy was also being extracted and coupled to the TE_{01} operating mode in the region after the output cavity; that is, a traveling-wave interaction was occurring. The nonlinear code did not include such effects. Thus the third and fourth three-cavity circuits were designed with the hope of taking advantage of this post-output cavity interaction.

These last two three-cavity circuits were tested and their results appear in references 3-6;

reference 5 includes a complete comparison of all two- and three-cavity circuits. These two circuits were nominally longer in length and operated with cavity Q's such that they were closer (some parameter regimes above) to start oscillation. In summary, these two circuits achieved maximum power levels of 22 MW, at efficiencies $\sim 27\%$ and gains $\lesssim 44$ dB. These circuits were able to operate with higher alphas than the first two circuits, however, their power levels were lower. The conclusion at this stage is that the longer cavities resulted in less post-output cavity interaction which appears to be stronger than the cavity interaction. More theoretical work and experimental testing needs to be done to clear up this issue and the discrepancies between theory and experiment.

2.2 Second Harmonic Amplifiers

2.2.1 Hardware for 19.7 GHz Operation

Before the second harmonic experiments could begin, several components had to be designed and constructed for three basic tasks. For cold-testing, mode converters were required for conversion from rectangular TE_{10} to circular TE_{01} and from circular TE_{01} to circular TE_{02} . The first converters were of the Marie type and were designed and constructed by an outside vendor. The latter converter was designed in house. Two nonlinear tapers that adapt the cold-test hardware to the circuit components were also designed in house and built by an outside vendor. All components performed well. When connected together, mode conversion from rectangular TE_{10} to circular TE_{02} was nearly 99% efficient.

The second task was to reconfigure the vacuum jacket/output waveguide. The beam dump and resonant output window were suitable for second harmonic operation but the two nonlinear tapers were not (due to excessive mode conversion). New taper designs were described in last year's progress report. They were fabricated by an outside vendor and have performed well in initial tests.

Finally, the microwave diagnostics had to be modified. A 19.7 GHz, mode selective directional coupler was designed and built on the same hardware that houses the original 9.85 GHz coupler. A new horn/waveguide system was added to the anechoic chamber.

2.2.2 Tube H1 (First Harmonic Experiment)

2.1.2.1. Design and cold test

The microwave circuit for tube H1 is shown in Fig. 2. It was constructed from the final fundamental two-cavity circuit by making three changes. First, the downtaper from the final three cavity tube was used because of its increased transmission loss near the lower end of X-Band. Second, a resonant trap was added to the drift tube to absorb TE_{01} energy at 19.7 GHz. It was constructed with two ceramic rings (99% MgO – 1% SiC) separated by copper spacers. Also, the orientation of some of the beryllium rings was altered to increase K-Band loss. The optimum results were determined empirically. Attenuation for X-Band (TE_{11}) and K-Band (TE_{01}) are shown in Fig. 3.

The final change was to replace the output cavity with a TE_{02} , 19.7 GHz circuit. The design of this cavity was described in the previous progress report. One design requirement was to minimize mode conversion from the TE_{02} to the TE_{01} at 19.7 GHz. This was achieved by minimizing the cavity radius and by using smooth (sinusoidal) transitions to define the cavity rather than the step transition of the fundamental circuits. The resulting cavity is quite long (~ 8 cm). The second requirement is to avoid oscillations near the fundamental cyclotron frequency. Since this usually entails short cavities, some compromise must be reached. The start oscillation curves for some troublesome modes are shown in Fig. 4. The curves correspond to the nominal beam parameters of the fundamental system and include a beam voltage of 425 kV and a velocity ratio of $\alpha = 1.0$. Many modes exist below the current threshold of 160 A, so it was no surprise that oscillations were pervasive in the first system.

Cold testing was performed by drilling two holes in the sides of the cavity at the center of the main section. A signal from a network analyzer was injected into one hole and then picked up by the other hole and by a horn pointing at the axial diffractive lip. The cold-test resonant frequency was $19.56 \text{ GHz} \pm .04 \text{ GHz}$ and the quality factor was 680 ± 50 .

2.1.2.2. Hot Test Results for Tube H1

Tube H1 was assembled in the LPR Vacuum Tube Processing Facility and installed into

Figure 2: A schematic of harmonic gyrokystron tube H1.

the existing beam transport system. After a 150-200 °C bakeout for several days, a base pressure near 8×10^{-9} torr was obtained. The microwave input and diagnostic system used for the initial survey is illustrated in Figure 5. The output signal from the gyrokystron is launched into an anechoic chamber. A WR-90 waveguide stub antenna located on the far wall of the anechoic chamber intercepts a small fraction of the radiated power. This signal is directed into a series of directional couplers, waveguide transitions, and filters which provide three different signal channels: 6.56-13.5 GHz, 9.49 GHz and higher, and 14.05 GHz and higher. These channels provide an initial estimate of frequency. An exact value for the frequency is obtained with an HP spectrum analyzer that can be connected to the chamber. The pickup antenna is situated on a movable, remotely controlled mounting inside the anechoic chamber. Radiation patterns obtained with this system are used to identify the mode of amplification or oscillation. A small (1.5 cm diameter) fixed position loop antenna is also located inside the anechoic chamber. This loop allows observation of instabilities without waveguide cutoff effects, which is particularly useful when studying low frequency instabilities below 6.5 GHz. Finally, an additional microwave horn is located behind the electron gun inside the modulator. This allows observation of any performance limiting gun downtaper modes or backward radiating drift tube modes.

Figure 3: Drift tube attenuation for Tube H1: (a) X-band and (b) K-band.

Figure 4: Start oscillation curves for the output cavity of Tube H1. The nominal beam parameters from the fundamental experiments are assumed.

The performance of Tube H1 was limited by numerous instabilities associated with fundamental cyclotron interactions in the output cavity. Weak harmonic amplifier operation (gain only slightly better than 0 dB) was achieved at a much reduced operating point of 390 kV, 92 A, $\alpha \approx 0.5$. Attempts to increase either α or the beam current triggered instabilities which completely suppressed the amplified signal. The study of these instabilities constituted the majority of the Tube H1 experimental program, and the results will be described in this section. The knowledge gained from these investigations (i.e., mode identification, frequency, starting current, etc.) simplified the design of a more stable second tube. The results from this improved tube, including preliminary amplification studies, will be presented later in the report.

In our earlier 24 MW, 9.85 GHz, TE₀₁ gyrokystron work, we found it useful to classify instabilities according to their location within the microwave circuit. In addition to allowing a simplified discussion of the various instabilities, it provides insight into the strategies used to eliminate them. In the two-cavity, 9.85 GHz Tubes I-V, we found four classes of instabilities: class 1, weak interactions occurring in the output beam tunnel aided by window reflections; class 2, gyrotron interactions associated with modes near cutoff in the output beam tunnel;

Figure 5. Schematic diagram of the microwave input and diagnostic system used for the initial stability and amplifier survey.

class 3, whole tube modes concentrated in the drift tube; and class 4, oscillations in the gun downtaper. Two-cavity Tube VI exhibited an oscillation in the input cavity under certain circumstances; these modes were called class 5. In the present 2nd harmonic system, several of the instabilities occur only in the output cavity. This new type of instability will be referred to as class 6. A pictorial representation of the various classes of instabilities appears in Figure 6.

Since Tube H1 used the same electron gun and downtaper employed in the 9.85 GHz experiments, no change in the stability to class 4 modes was expected or observed. The onset of the gun downtaper instabilities still limits α to about 1.1. The Q of the input cavity in Tube H1 was about 400, which was considerably lower than the Q of 600 used in 9.85 GHz Tube VI. Indeed, the stability of the input cavity was enhanced in Tube H1, with class 5 TE_{011} oscillations observed only at the highest values of α . Finally, the attenuation per unit length in the Tube H1 drift tube over the 7-12.4 GHz frequency range was comparable to that of Tube VI. Only minor changes in stability of the previously observed class 3 oscillations were noted in Tube H1.

However, the long, relatively flat 2nd harmonic output cavity exhibited numerous new oscillations which required further study to identify. The first instability to occur as the operating parameters were increased was generally the TE_{011} mode associated with the fundamental cyclotron harmonic. Oscilloscope traces for this instability are shown in Figure 7. The X-Band crystal trace exhibits a broad, fairly flat maximum lasting for nearly 1 μsec . The frequency spectrum of this instability appears in Figure 8. In this particular case, the oscillation frequency was 10.903 GHz, which is in excellent agreement with the theoretical TE_{011} resonant frequency. The center frequency was observed to vary from 10.85 to 10.95 GHz depending on the operating parameters. Power levels, obtained from the crystal voltage using a cold-test calibration of both the crystal response and the anechoic chamber attenuation, were estimated to be as high as 15 MW at an efficiency of 25%. This power level and efficiency are surprisingly large for an unintended and unoptimized oscillation, although magnetic field tapering was being employed in an attempt to enhance amplification. The high power and relatively low starting current of the instability presumably occurred as a result of the long interaction length in the cavity, extended interactions in the straight beam

Figure 6. Schematic of a gyrokystron showing the classes of instabilities.

tunnel located just after the output cavity, and a 10% power reflection from the output window at 10.9 GHz (it is a $\lambda/2$ resonant window designed for 9.85 and 19.7 GHz).

A second group of instabilities observed over a wide range of operating parameters were TE_{11p} modes in the output cavity. Significant leakage of the cavity fields into the drift tube was probable, since these modes were capable of suppressing all other instabilities. In addition, beam scraping and gas production were observed, which in the past has been associated with RF-induced electron orbit disruption in the drift tube (where the beam has only a 1 mm radial clearance to the wall). These instabilities occupy a range of frequencies between 5.5 and 7.2 GHz, and result from backward wave interactions. Scope traces of the cathode voltage and a crystal detector connected to the loop antenna are shown in Figure 9. The various bursts are associated with slightly different frequencies of oscillation. As the beam voltage, current, and α vary during the pulse, the various instabilities grow and decline as they compete with each other. The spectrum of this family of instabilities is shown in Figure 10. The spectrum was obtained with a modest beam voltage of 340 kV. As the voltage was increased towards 400 kV, the frequency of the instabilities decreased as a result of the decrease in the relativistic cyclotron frequency. Like the 10.9 GHz TE_{011} mode, these instabilities are all fundamental cyclotron interactions.

The third group of output cavity instabilities were associated with TE_{21p} modes in the output cavity. They generally occurred in the 8.8-9.2 GHz range, near cutoff frequency in the long output cavity. Like the TE_{11p} modes, these caused gas production from the drift tube, indicating some upstream leakage of the cavity fields into the drift tube. They could suppress all instabilities except the TE_{11p} family, and once again amplifier operation was impossible in the presence of these oscillations.

Finally, harmonic oscillation of the output cavity in the TE_{021} mode at 19.6 GHz was observed occasionally. These oscillations can occur only at the rare operating points where the TE_{11p} and TE_{21p} instabilities have not started and the TE_{011} mode is comparatively weak. A group of such operating points was located at high currents (>150 A) at 350-430 kV, in a flat 0.565 T magnetic field. Values of α were generally about 0.5-0.7 at these points. A complete set of scope traces at an operating point of 390 kV, 206 A is shown in Figure 11. The corresponding spectrum appears in Figure 12. The TE_{021} mode appears to partially

Figure 7. Scope traces associated with the TE_{011} instability at 340 kV, 180 A. Shown are an X-Band crystal detector voltage mV (solid) and the cathode voltage in kV (dashed).

Figure 8. Spectrum of the TE_{011} instability.

Figure 9. Scope traces associated with the TE_{11p} instabilities at 340 kV, 180 A. Shown are the loop crystal detector voltage in $mV \times 3$ (solid) and the cathode voltage in kV (dashed).

Figure 10. Spectrum of the TE_{11p} instabilities.

Figure 11. Scope traces associated with the TE₀₂₁ instability at 390 kV, 206 A. The frequency ranges for each of the crystal detector signals and associated hardware are: X-Band 6.56-13.5 GHz, Ku-Band >9.49 GHz, and K-Band >14.05 GHz.

Figure 12. Spectrum of the TE₀₂₁ instability.

suppress the TE_{011} mode late in the pulse, as evidenced by the decrease in the X-Band crystal signal coincident with the K-Band signal. This point on the voltage pulse is also the point of highest α [7]. As the α is further increased by an increase in magnetic compression, the strength of the harmonic K-Band signal increases. This is expected since a higher α beam tends to favor the harmonic over the fundamental. However, further increases in α are strongly limited by the onset of the 5.5-7.2 GHz TE_{11p} instabilities. Attempts to mode lock the TE_{021} oscillation by injecting an input signal at 9.80 GHz (1/2 of 19.6 GHz) appeared to be unsuccessful, since no changes in the strength or frequency spectrum of the 19.6 GHz instability or on the onset of the TE_{11p} family were observed.

2.2.3 Tube H2 (Second Harmonic Experiment)

2.1.3.1. Design and cold test

The microwave circuit for tube H2 is shown in Fig. 13. It is distinguished from H1 by three changes. First, the downtaper was replaced with the one from the final two-cavity fundamental system. This replacement was made to eliminate suspected ceramic contamination which hampered beam production. It should be noted that while this taper had reduced cold-test performance, its hot-test performance was comparable to the first taper. The second change was to replace the 19.7 GHz trap with a more sophisticated system. This system used a reflection cavity and two thin alumino-silicate cavities. Furthermore, three additional Beryllia pieces were inserted between the trap and the output cavity. Both X-Band (TE_{11}) and K-Band (TE_{01}) transmission curves are shown in Fig. 14.

Four basic changes were made to the output cavity design. First, its main section radius was increased and its length decreased. Second, two of the transitions had Dolph-Chebyshev profiles. Third, the design quality factor was cut in half (to 350). Finally, the output waveguide radius was made dramatically different from the main cavity radius. All changes were made to help stabilize the cavity. The start oscillation curve is shown in Fig. 15 for the same parameters of Fig. 4. The only modes that could potentially oscillate in the output cavity are the TE_{011} and TE_{012} modes. Mode conversion to the TE_{01} mode travelling back to the gun is down by over 40 dB. This is comparable to the mode conversion in the first

2nd Harmonic Gyroklystron Tube #2

Figure 13: A schematic of harmonic gyrokystron tube H2.

system. A new small uptaper had to be constructed due to the final change.

Cold testing was improved by using the two mode converters to inject power into the cavity. Holes were again drilled into the side walls to measure transmitted power. The resonant frequency was $19.68 \text{ GHz} \pm 10 \text{ MHz}$. The quality factor was 450 ± 50 . The measurement was hindered by the presence of the TM_{121} mode. The origin of the quality factor discrepancy (design vs. measured) is unknown and was not explored because of time constraints. The cavity walls had fairly large slopes which may have resulted in machining problems. This question will be explored further when the hot tests are complete.

2.1.3.2. Hot Test Results for Tube H2

Prior to operation of Tube H2, a variety of modifications to our vacuum system and bake-out procedures were carried out. The goals were to improve the stability of cathode emission during the course of the experiments, and to prolong the life of the cathode. A Residual Gas Analyzer (RGA) was added to our vacuum system to identify any harmful impurities in the tube atmosphere during bakeout (prior to opening the gate valve between the electron gun

Figure 14: Drift tube attenuation for tube H2: (a) X-band and (b) K-band.

Figure 15: Start oscillation curves for the output cavity of tube H2. The nominal beam parameters from the fundamental experiments are assumed.

and the microwave circuit). Furthermore, the RGA system provides information on when to terminate the bakeout procedure. Formerly, the system was baked until pressures reached the mid 10^{-7} torr level at 150-200 °C. Upon cooling, base pressures in the high 10^{-9} to low 10^{-8} torr level were obtained. With the RGA diagnostic, the bakeout is continued for a longer time, until the partial pressures of undesirable gasses, such as H_2O , CH_4 , CO , and CO_2 , are very low compared to the hydrogen partial pressure. Furthermore, the ion pumps are now started midway through the nominally turbopump-based bakeout (formerly they were started only near the end of the bakeout), in order to improve the diffusion of pumped gasses into the bulk of the ion pump plates. The new procedures resulted in a base pressure below 2×10^{-9} torr and a partial pressure of H_2O below 1×10^{-10} torr in Tube H2. The cathode performance was significantly improved by these modifications.

Tube H2 exhibited a significantly enlarged region of stability compared to Tube H1. The powerful 10.9 GHz TE_{011} mode was completely eliminated by the modified output cavity structure. The TE_{21p} family of instabilities were similarly eliminated. In addition, the very troublesome 5.5-7.2 GHz TE_{11p} backward wave instabilities were partially stabilized, allowing operation up to 450 kV. When these instabilities did occur, they were much weaker than

in Tube H1 and did not cause beam scraping and gas production. The new output cavity also exhibited improved stability to the TE_{021} mode, with oscillation occurring only at high magnetic fields and producing comparatively low output power (≈ 50 kW).

The stable operating parameter range present in this tube was large enough to permit preliminary harmonic amplification studies. To prepare for these investigations, the WR-90 waveguide stub antenna in the anechoic chamber was replaced by a K-Band, WR-42 version. Similarly, the X-, Ku-, and K-Band power splitting arrangement of Figure 5 was replaced by an all K-Band system, to guarantee single mode propagation in the diagnostic hardware at 19.7 GHz. The attenuation figures for the various components were measured with a network analyzer. Finally, the anechoic chamber was re-calibrated. This was accomplished by injecting a 19.7 GHz TE_{02} signal from a mode converter through the nonlinear uptapers and window into the chamber and measuring the power intercepted by the K-Band waveguide stub at a variety of positions.

The reduction in fundamental cyclotron instabilities allowed not only harmonic amplification to occur, but also several new harmonic oscillations in Ku-Band. An example of such an instability is shown in Figure 16, and the spectrum is pictured in Figure 17. Although the 15.0-15.7 GHz frequency range is below the official designation of K-Band, the frequencies are above the 14.05 GHz cutoff of WR-42 waveguide. These and other similar instabilities therefore register on the K-Band detector, making it difficult to determine the amount of power due to harmonic amplification. To solve this problem, a microwave filter with a center frequency of 19.74 GHz, a half power bandwidth of 9%, and greater than 30 dB of attenuation in the 14-17.5 GHz range was designed and constructed. The frequency response of this filter is shown in Figure 18. The filter was inserted into the signal path before the K-Band detector; thus the detector registers only the power in the second harmonic. An additional crystal detector was added to the signal path prior to the filter to provide information on both the amplified signal and any instabilities above 14.05 GHz. Comparison of the filtered and unfiltered signals allows the purity of the output signal to be quickly estimated, with the spectrum analyzer providing greater detail as needed.

Harmonic amplification was identified at several operating points with the aid of the filter during a preliminary survey. An example of low power amplification is shown in Figure

Figure 16. Scope traces associated with the Ku-Band harmonic instability at 445 kV, 154 A. Shown are the crystal response in mV (solid) and the cathode voltage in kV (dash).

Figure 17. Spectrum of the Ku-Band instability.

Figure 18. Frequency response of the 19.74 GHz microwave filter.

Figure 19. Scope traces associated with 19.74 GHz, 800 kW peak power output harmonic amplification in Tube H2 at 430 kV, 132 A. Shown are the filtered K-Band crystal voltage in mV (solid) and the cathode voltage in kV (dash).

19. The peak output power level was computed to be about 800 kW, based on the crystal, anechoic chamber, and waveguide component calibrations. This result was obtained at 430 kV beam voltage and 132 A beam current, with an estimated α of about 0.8. The gain at the maximum power point was about 13 dB at an efficiency of 1.4%. When examining this efficiency one must remember that the output power was not saturated; it was limited by the combination of the low gain and a 40 kW input source. Considerably more power was obtained at 416 kV and 152 A with a slightly higher α . With careful adjustment of beam voltage, current, magnetic compression, and circuit magnetic field profile, a peak power of 1.8 MW was obtained. Scope traces associated with this operating point are pictured in Figure 20. The narrow pulse shape results from the extreme sensitivity of the amplifier gain to operating parameters. As the pulse progresses, there are slight changes in voltage, current, and α . As these parameters drift in and out of their optimum values, the gain, and thus the output power, vary accordingly. The power reaches a maximum near the end of the flat-top region of the pulse, which was shown in previous work[7] to correspond to the point of maximum α . Presumably the sensitivity to operating parameters will decrease when saturated operation is achieved, either at an improved operating point in this tube or more probably in the next tube (Tube H3). The gain associated with the 1.8 MW output power is 16.5 dB, and the unsaturated efficiency is about 3%.

The spectrum of the 1.8 MW harmonic amplified signal is shown in Figure 21. The output frequency, 19.742 GHz, is twice the drive frequency measured to within the resolution of the spectrum analyzer. The smaller signal at 19.69 GHz is very close to the TE₀₂₁ cavity resonant frequency measured during cold testing, and probably corresponds to self oscillation. However, since the level of this oscillation is over 35 dB lower than the amplified signal, the instability is very weak and of little consequence.

In order to prove the presence of amplification, as opposed to free-running or mode-locked oscillation, the effects of input power level and input frequency on the output power and output frequency must be investigated. The effect of input frequency on output power, obtained at the same voltage and current as with the 1.8 MW result, is shown in Figure 22. The magnetic compression was slightly decreased (lower α) for this sweep to reduce the sensitivity of the output power to beam parameters. The drawback to this adjustment was a

Figure 20. Scope traces associated with 19.74 GHz, 1.8 MW peak power output harmonic amplification in Tube H2 at 416 kV, 152 A. Shown are the cathode voltage, the input and reflected (dotted) power crystal signals, and the filtered output K-Band crystal signal.

lower (1.2 MW) maximum power level. The double lobed structure is similar to early results obtained with the TE_{01} 9.85 GHz gyrokystron and probably results from an offset between the optimum frequencies for bunching in the input cavity and energy extraction (at twice the frequency) in the output cavity. Improved frequency alignment between the cavities and higher efficiency operation in the next tube will reduce this effect. During this sweep the output frequency remained at twice the input frequency to within the spectrum analyzer resolution.

The effect of input power on the output power at the same operating point and 9.872 GHz input frequency is shown in Figure 23. The gain is about 15.5 dB at the highest power level (1.4 MW) measured during this sweep. There do not appear to be any significant saturation effects at the limit of the input source power. It is noteworthy that the curve would not pass through the origin if extrapolated backwards. We believe that this effect is due to low level instabilities (the weakened TE_{11p} family) which are present when the drive signal is weak. These instabilities compete with and/or suppress the harmonic amplifier at low input powers. When the input signal reaches a certain point, probably about 10 kW, the beam becomes sufficiently bunched to excite harmonic amplification. The harmonic signal presumably suppresses the instability at this and all higher input power points. Further work, including measurements of instability power vs. input power, are required to confirm this explanation. In any case, the ability to control the output power with the input signal in a continuous fashion, the existence of a well behaved frequency response, and a factor of two relationship between the output and input frequencies over the entire measurement range confirms harmonic amplification.

The E_ϕ radiation pattern of the 1.8 MW harmonic signal was obtained as a final step in these preliminary amplifier studies. The results are displayed in Figure 24, along with the TE_{02} cold-test calibration pattern. The agreement in structure is quite good, considering that the sensitivity to beam parameters discussed previously will cause a drift in output power as the measurement proceeds over the course of several minutes. The maxima and minima of the amplifier output closely match the calibration curve, and the orthogonal (E_θ) signal (not shown) is at least 30 dB lower than the E_ϕ signal. Thus, the harmonic amplifier signal at this operating point is largely in the TE_{02} mode, as expected.

Figure 21. Spectrum of the 1.8 MW, 19.74 GHz harmonic amplifier signal.

Figure 22. A representative plot of harmonic output power vs. input frequency.

Figure 23. A representative plot of harmonic output power vs input power. The input frequency was fixed at 9.872 GHz.

Figure 24. E_ϕ radiation pattern measured in the anechoic chamber during harmonic amplification (circles). Also shown in the figure is the E_ϕ pattern produced by a TE_{02} mode launcher measured during cold-testing (solid line).

Encouraging initial results from an expanded search of the operating parameter space have recently been obtained. An amplifier output power of 3.8 MW at an efficiency of 8%, a gain of 16 dB, and a frequency of 19.74 GHz was produced at a reduced-voltage operating point of 350 kV at a beam current of 140 A. A strongly uptapered magnetic field with a lower than normal average value was required to achieve this level of performance. Similar results (3.6 MW, 7% efficiency, 16 dB gain) were obtained at 407 kV and 160 A with a moderately downtapered field. An operating point that produced a somewhat lower output power of 2.8 MW but with a higher 18.5 dB gain was also located during the search. Careful adjustment of the magnetic field profile was required to optimize the output power and/or gain at these various operating points. Finally, with an 8% uptaper in magnetic field over the length of the circuit, an output power of 7.5 MW at an efficiency of 11% and a gain of 20 dB was obtained. The performance in all cases was limited by the onset of TE_{11p} whole-tube modes.

Future work with Tube H2 will begin with a much expanded search for improved output power and efficiency. In addition to a systematic search of the effects of current, voltage, and magnetic field taper, operating points with reduced voltages and correspondingly lower magnetic fields will be investigated. These may further reduce the backward-wave TE_{11p} family of instabilities, allowing improved amplifier operation and higher efficiency. Finally, the increased understanding of instabilities in harmonic gyrokystrons resulting from the survey should help in the design of an improved tube. Careful measurements of frequency response, output vs. input power, radiation pattern, and mode competition will be performed at the most interesting operating points.

2.2.4 Tubes H3 and H4

A schematic for the output cavity of Tube H3 is shown in Fig. 25. The effective cavity length is shorter than the length in H2, primarily because the transitions that define the cavity are shorter. All the transitions are of the Dolph-Chebyshev type with the parameter constant increased to decrease the slope in the wall. The quality factor is still 350 but the resonant frequency has been raised 50 MHz to coincide with twice the optimal input cavity frequency. The left-to-right power ratio has decreased slightly (to 38 dB) but the mode purity has increased. The start oscillation curves are slightly better than for the previous

2ND HARMONIC OUTPUT CAVITY #3

Figure 25: A schematic of the output cavity of tube H3.

tube as shown in Fig. 26. The drift tube will be shortened by about 2 cm and we will continue to search empirically for optimal drift tube attenuation.

The simulated large-signal performance for this tube is promising. Figure 27 shows the predicted efficiency at the nominal beam parameters over a range of output cavity magnetic fields. Powers over 17 MW should be obtainable over a wide parameter range if the tube is stabilized. The theoretical drive curve for tube H3 is shown in Fig. 28. Again, substantial powers are indicated.

Tube H4 will use an output cavity with abrupt radial transitions similar to those employed in the 9.85 GHz work. Such a cavity operating at 19.7 GHz will contain a mixture of the TE_{011} and TE_{021} modes. Since the TE_{01} mode is not cutoff in the drift tube at the operating frequency, the cavity fields would leak backwards into the drift tube. This would greatly increase the effective interaction length of the cavity and would lead to instability. A modified cavity structure containing an additional abrupt radial transition roughly midway along the length will be used to cancel the backward propagating TE_{01} wave. Such a cavity is pictured in Figure 29.

The main advantage offered by this type of cavity is improved stability to the 5.5-7.2

Figure 26: Start oscillation curves for the output cavity of tube H3.

Figure 27: Theoretical efficiency of tube H3 as a function of output cavity magnetic field. The input cavity magnetic field is near 5.15 kG and the drive power is 42 kW.

Figure 28: Theoretical efficiency of tube H3 as a function of drive power at the optimal field taper.

Figure 29: Diagram of the complex, abrupt radial transition output cavity for Tube H4.

GHz TE_{11p} family of oscillations. This results from the relatively short length of the cavity (about 2 cm) compared to the smooth transition cavities of Tubes H1-H3 (greater than 3.5 cm). Since competition from the TE_{11p} family appears to be the primary factor limiting performance in Tube H2, there is a good chance of improved results with this type of cavity. The output cavity is directly compatible with the input cavity, drift tube, vacuum jacket, and post-output cavity beam tunnel used in 9.85 GHz two-cavity Tube VI, so very little fabrication will be required to test this concept.

This scheme has several drawbacks which will need to be explored. First, the 19.7 GHz output signal is a mixture of the TE_{01} and TE_{02} waveguide modes. A mode converter would be required to convert this mixed mode output into a single mode for most practical applications. Such a mode converter should not be particularly hard to fabricate, provided that the mode content of the signal remains relatively fixed over the desired range of operation. Furthermore, in a linear collider application the source tubes are generally operated at some fixed level of beam voltage and current, while only the input power is adjusted to control the output power. Studies of mode purity as a function of output power will therefore be performed in Tube H4. The stability of the backward-radiating wave cancellation effect with beam parameters and modulation level is another related concern. Should beam-induced detuning cause significant TE_{01} radiation into the drift tube, the cavity could break into oscillation over some range of input power or operating points. Ascertaining whether or not this phenomenon occurs and determining its importance will be an additional goal of the Tube H4 experiments. Finally, the theoretical efficiency of the abrupt-transition output cavity design appears to be somewhat lower than the efficiencies predicted for the longer, smooth-walled cavities. Further investigation of this prediction is underway.

2.3 Modulator Upgrade

We are currently upgrading our 500 kV, 200 MW modulator in preparation for the upcoming 100 MW gyrokystron experiments. Three different goals are associated with this upgrade. First, the output current of the modulator will be doubled from the present level of 400 A to 800 A. This will be accomplished by increasing the number of paralleled pulse forming networks (PFNs) from four to eight, and switching them into the pulse transformer with new

thyratrons. Each thyatron will discharge four PFNs instead of two. Since we do not plan on purchasing a new dc power supply, the repetition rate of the modulator will drop from 5 to 2.5 Hz. This is not a problem since the majority of our 9.85 GHz work was performed at 1-2 Hz without any trouble. The present system employs a resistive divider that consumes 50% of the output current to power the modulation anode of the double anode magnetron injection gun (MIG). Therefore, only 200 A is available for cathode current in the present system. In the upgraded system, which is designed to power a single-anode MIG, the entire 800 A output current can be directed into the cathode. This effectively increases the beam power by a factor of four over the present system.

The second goal involves a reduction in the stray capacitance associated with the 500 kV connections between the pulse transformer and the gun. In the present system, the 500 kV components are spread out between two different oil tanks, with a large distance between the transformer and the electron gun terminals. In the new system, all of the 500 kV components, including the pulse transformer, filament transformer, capacitive voltage dividers, rogowski coils, and load resistors (for operation at lower cathode currents), will be placed in a single tank with the electron gun terminals as close as possible to the pulse transformer. The stray capacitance should drop from 400 to 170 pF as a result of these modifications. Furthermore, the lower stray output capacitance will reduce the magnitude of the thyatron reverse voltage, which causes problems in the present system. The new modulator should produce an output pulse with nearly a 2 μ sec flat-top and 1.3 μ sec rise and fall times, compared to the 1 μ sec flat-top and 2 μ sec rise and fall times of the current system. A simulation of the output pulse expected from the upgraded modulator is shown in Figure 30.

As a final change, some arcing problems in the 500 kV components will be corrected. These arcs, in conjunction with the thyatron reverse conduction caused by the excess stray output capacitance, have limited reliable modulator operation to voltages below about 450 kV. An improved design of the metal components and supporting insulators subjected to high electric fields, a better oil filtration system, and the lower capacitance arrangement of the components should allow operation at the full 500 kV level.

Significant progress on the modulator upgrade has been achieved. A new oil tank to

Figure 30: Simulated voltage pulse of the modulator upgrade.

hold the additional four PFNs has been designed and is currently under construction. The capacitors for the PFNs have been procured and individually tested for both voltage holdoff and current production capability. The PFN inductors have also been constructed. Two new inverse diode, metal oxide varistor, and auxiliary load assemblies used for short protection have been constructed for use with the additional PFNs. In addition, two new ITT F-187, 75 kV, 20 kA hydrogen thyratrons for the upgraded modulator have been ordered and are due to arrive in February 1993. Completion of additional PFN system is expected by April 1993. The new 500 kV component tank and its contents are currently in the design phase, with construction scheduled to begin immediately after the completion of the PFN system. We anticipate completion and resistive load testing of the entire modulator upgrade by early November 1993.

2.4 Electron Gun Design

We have been investigating the design of electron guns that would be required to produce at least 100 MW of microwave power at a frequency dictated by the supercollider application. To this end we have designed several Magnetron Injection Guns (MIGs). These designs have focussed on providing beam parameters suitable for driving a coaxial gyrokystron but could

Figure 31: A schematic of the 17 GHz MIG design.

be used for other applications as well. Our study has indicated that single-anode designs are superior to double-anode designs for the specified parameters due to their enhanced current range, magnetic field range, simpler design, and (predicted) cheaper cost. A detailed comparison of 400 MW MIGs for an 11.424 GHz system is given in a paper in the Appendices.

The most recent effort has been to design a 400 MW, single anode MIG for 17 GHz. The resultant electrode shapes and simulated beam trajectories are shown in Fig. 31. The peak electric field, cathode loading, and magnetic compression are all similar to those in the existing 100 MW MIG. The dependence of velocity spread on beam current is given in Fig. 32. The velocity ratio is kept at $\alpha = 1.5$ by varying the cathode magnetic field. The ability to go from 0 A to 800 A with a spread below 10% is due to the laminar nature of the single-anode system and will greatly enhance the experimental process. The gun also maintains a low velocity spread over a wide range of circuit magnetic fields. This is indicated in Fig. 33, where velocity spread is plotted as a function of output frequency. This curve is generated by assuming second harmonic operation and a fixed percentage difference between operating frequency and cyclotron frequency.

Figure 32: The dependence of velocity spread on beam current for a fixed velocity ratio of $\alpha = 1.5$.

Figure 33: The dependence of velocity spread on magnetic field in the circuit region. The beam current is 600 A and the velocity ratio is $\alpha = 1.5$.

2.5 Cavity Design/Cold Test

Preliminary designs for two cavity, coaxial gyrokystron circuits were examined for both 11.424 GHz and 17 GHz. The cavities are defined by transitions in either the inner or outer conductor. For the output cavities, both step and smooth transitions were considered. The input cavity is defined by step transitions. It operates at half the output frequency and achieves its quality factor with the help of thin lossy ceramic rings. A simple prototype was constructed and successfully tested; details are given in a student paper in the Appendices. Preliminary large-signal simulations have yielded efficiencies of 32% as discussed in Section 3.

3 Theoretical Research Progress

3.1 Theory of the Relativistic Gyrotwistrons

Gyrotwistrons are devices combining advantages of gyroklystrons and gyro-traveling-wave-tubes (gyro-TWTs). The gyrotwistron consists of an input cavity and drift section (like gyroklystrons) and an output waveguide section (like gyro-TWTs). The first cavity and drift section provide good prebunching of electrons. This prebunched electron beam excites traveling waves in the output waveguide where the amplitude of the wave is smaller than that in a high-Q output cavity of a GKL at the same level of output power. Thus, the problem of microwave breakdown occurring at high levels of output radiation is alleviated. Also, the output waveguide has the potential benefit of a larger frequency bandwidth.

Two versions of the theory of relativistic gyrotwistrons were developed. The first one is valid for gyrotwistrons with a constant or slightly tapered external magnetic field. The second describes a model of relativistic gyrotwistrons with a strongly tapered magnetic field in which effects of magnetic compression/decompression of the beam and transverse drift of electron guiding centers are important. In this theory, the concept of synchronous deceleration of electrons was used. This concept implies that the tapering of the magnetic field provides exact cyclotron resonance for one macroparticle in the process of interaction with the electromagnetic wave. Therefore, if such a particle is chosen properly, a large number of other particles with similar energies and gyrophases will also be decelerated effectively. The results obtained in consideration of these models were used as guidelines in further designs based on much more complicated numerical codes.

3.2 Efficiency of Frequency Upshifted Gyrodevices: Cyclotron Harmonics versus CARMs

The interest in this study was motivated by the program of planned experiments aimed at increasing the operating frequency in GKLs. The comparison of efficiencies of two kinds of operation, operation at cyclotron harmonics at frequencies near cut-off and operation at the fundamental resonance far from cut-off, has been done for the case when the operating

frequency and the external magnetic field are the same for both schemes. It was found that for an ideal electron beam the CARM operation is much more efficient, however, when the velocity spread grows the CARM efficiency degrades much faster than that of the harmonic operation. In particular, for the velocity spread typical for the present GKL experiments, operation at cyclotron harmonic can be more efficient. The results were obtained for a constant external magnetic field distribution. In future work we will optimize efficiency with a tapered magnetic field.

3.3 Improved Gyrotron Modeling

Gyrotron modeling fell into two categories: gyroklystron amplifier code enhancement and gyrotwistron code development.

The enhancements to the gyroklystron amplifier codes primarily involved the addition of automatic optimization of routines. We are now able to rapidly optimize efficiency with respect to a number of parameters, including magnetic field profile. This capability greatly decreases the time it takes to achieve a particular design. In addition, we have developed a gyroklystron amplifier code which computes the field profiles self-consistently. However, it is of somewhat limited use because of its slow convergence. Improved search algorithms are planned.

We have used these codes to design a second harmonic, co-axial gyrotron operating at 17 GHz. Because the radiation is not cut off in the drift section, we use a complex output cavity which combines TE_{01} and TE_{02} modes to eliminate the backward wave, as shown in Fig. 34. The quality factor of this cavity is approximately 1000 and the cold-cavity backward wave power is down by about 40 dB. Because of the high Q we do not expect the electron beam to have a large effect on the electromagnetic field profile, although we are planning to check this expectation using our self-consistent gyroklystron amplifier code. With a flat magnetic field we have achieved an efficiency of 32% at 500 kV, 600 A and pitch ratio of 1.5. Optimization with a tapered field continues. In addition, we will be looking at a simple output cavity with a pure TE_{02} mode and a gyrotwistron.

A similar approach has been used to design a second harmonic gyroklystron amplifier at 19.7 GHz using our present electron gun. The calculated efficiency of this device is now

Figure 34: Complex output cavity for 17 GHz operation.

approximately 24%; we are continuing our optimization.

To model gyrotwistrons, we have to develop a new set of codes. These include:

- gyrotwistron with forward wave only
- gyrotwistron with forward and backward waves
- linear mode competition
- nonlinear mode competition (in progress)

We have been using these codes to study the possibility of operating in the gyrotwistron mode. A preliminary design at 9.85 GHz has been completed and is shown in Fig. 35. Simulations predict an efficiency near 40% with a pitch angle near one and an axial velocity spread of 6%. However, linear mode competition studies indicate that there are a number of unstable modes, the worst of which is the TE_{21} mode with a start current near 50 A. When the operating mode is included and modifications are made to the magnetic field profile, the start current should increase; these studies are under way.

3.4 Codes for Coaxial Circuits

Three codes have been modified to facilitate the design of coaxial gyrokystrons. First, an all metal version of CASCADE was rewritten for systems with variable inner radii. A paper which details the results is included in the Appendices.

Figure 35: Schematic of the 9.85 GHz gyrotwistron. All dimensions are in cm.

A variable inner conductor was also added to the code which computes transmission and reflection in smooth tapers. This code is required to design the output waveguide. A paper which describes this code is also included in the Appendices.

Finally, a code was written to compute attenuation per unit length in modes that travel in coaxial waveguides that are lined with lossy dielectrics. This code will be used in preliminary design of the drift tubes.

4 References

1. V.L. Granatstein and C.D. Striffler, "Summary Report: High Intensity EM Waves," Proc. of the 3rd International Workshop on Advanced Accelerator Concepts, June 14-20, 1992, Port Jefferson, Long Island, NY; to be published.
2. S.G. Tantawi, W.T. Main, P.E. Latham, G.S. Nusinovich, W.G. Lawson, C.D. Striffler, and V.L. Granatstein, "High Power X-Band Amplification from an Overmoded Three-Cavity Gyroklystron with a Tunable Penultimate Cavity," IEEE Trans Plasma Science **20**, 3, 205-215 (1992).
3. W. Main, S. Tantawi, P.E. Latham, B. Hogan, W. Lawson, C.D. Striffler, and V.L. Granatstein, "Optimization of the Output Cavity for a Three Cavity X-Band Gyroklystron Amplifier," to appear in the Proc. of the Beams '92 Conference, Washington, DC, May 1992.
4. P.E. Latham, U.-V. Koc, W. Main, S.G. Tantawi, "Theoretical Investigation of Anomalous High Efficiency in a Three Cavity Gyroklystron Amplifier," to appear in the Proc. of the Beams '92 Conference, Washington, DC, May 1992.
5. W. Lawson, V.L. Granatstein, B. Hogan, U.-V. Koc, P.E. Latham, W. Main, H.W. Matthews, G.S. Nusinovich, M. Reiser, C.D. Striffler, and S.G. Tantawi, "Experimental Gyroklystron Research at the University of Maryland for Application to TeV Linear Colliders," to appear in the Proc. of the 1992 Advanced Accelerator Workshop, Port Jefferson, New York, June 1992.
6. C.D. Striffler, S. Tantawi, W. Main, B. Hogan, P.E. Latham, W. Lawson, U.-V. Koc, H.W. Matthews, G.S. Nusinovich, and V.L. Granatstein, "Three-Cavity Circuit Studies of the Maryland Gyroklystron," to appear in the Proc. of the 1992 Linac Conference, Ottawa, Canada, August 1992.
7. J.P. Calame, W. Lawson, V.L. Granatstein, P.E. Latham, B. Hogan, C.D. Striffler, M.E. Read, M. Reiser, and W. Main, "Experimental studies of stability and amplifi-

cation in four overmoded, two-cavity gyrokystrons operating at 9.87 GHz," J. Appl. Phys. **70**, 2423 (1991).

5 Proposed Research

5.1 Experiment

The experimental effort for the upcoming year will continue to focus on several areas. The first area will lead to completion of the amplifier experiments with the existing electron gun. A related area involves the implementation of the improved beam diagnostic. The third area is the modulator upgrade. The fourth area is the design and cold testing of the high power tube components and the final area is the design and procurement of a new electron gun and associated magnet system.

The final sequence of amplifier experiments on the current test bed is predicated on our ability to suppress instabilities in the drift tube/output cavity. If all goes well, we expect to test four different configurations. The first two are the tubes H3 and H4 which were described briefly in the previous sections. We also expect to install a tube with improved current breaks, and capacitance probe in the beam down taper, and coaxial insert. The final experimental configuration would be a gyrotwistron based on the theoretical efforts described earlier.

The modulator upgrade will be completed in the upcoming year. The PFN tank will be assembled, the new thyratrons will be installed, the new high voltage tank will be installed, constructed, and several minor components (transformer, resistors, etc.) will be procured. We will also install a new oil transfer system as mandated by our laboratory. The new system will be benchmarked using a resistive load.

Once we have converged on the design parameters for the 100 MW gyrokystron experiments, we must finalize the designs of a large number of components. The electron gun parameters will be summarized in an RFP which will be sent to industry for bids. Modification to the magnet system will be designed and constructed (possibly in-house). New microwave diagnostics will also be designed and constructed. The three main diagnostics will be an anechoic chamber, a liquid calorimeter, and a directional coupler.

The cold-test work on coaxial circuits will be expanded to include 17 GHz. We will design and test lossy coaxial drift tubes. Output cavities for fundamental mode and second harmonic operation will be designed, constructed and tested. Finally, a new output waveg-

uide (vacuum jacket assembly) will be designed and constructed. Novel components of this system will be the inner conductor support and the transition from coaxial to right-circular waveguide.

The longest lead-time item is the electron gun, which will be delivered approximately one year ARO. The goal of the other efforts is to assemble a system which is ready to be tested by the time the new gun arrives.

5.2 Theory

5.2.1 Optimization of microwave phase velocity and axial distribution of external magnetic field for extraction of maximum energy from electron beams with realistic velocity spread

It is known that for an ideal electron beam (zero velocity spread) the optimal kind of gyrodevice is the CARM, in which the phase velocity of the wave is close to the speed of light, c , and therefore, it is possible to transform into microwave radiation a significant portion of the kinetic energy of both the axial and transverse motion of the gyrating electrons. It is also known that for a poor quality electron beam the optimal gyrodevices are those in which the wave phase velocity, v_{ph} , is much larger than c (like gyromonotrons or gyroklystrons). In such devices the inhomogeneous broadening of the cyclotron resonance band caused by the effect of axial velocity spread on the Doppler term $k_z v_z = (\omega/v_{ph})v_z$ is not very important because v_{ph} is large. Therefore, these devices are not so sensitive to spread in electron axial velocities.

It seems obvious that for any given value of the electron velocity spread one can find the optimal phase velocity that will be between these two limits: $v_{ph} \approx c$ (CARM) and $v_{ph} \gg c$ (gyrotron). Our study will be aimed at finding this optimum and its dependence on velocity spread. For relativistic electron beams the interaction with electromagnetic waves causes significant changes in the relativistic gyrofrequency (which modifies the cyclotron resonance) so we will also optimize the axial distribution of the external magnetic field.

5.2.2 Analysis of excitation of spurious waves in relativistic gyroamplifiers

Another problem which is especially important for gyroamplifiers with waveguide sections is the excitation of spurious electromagnetic waves. Among these the most dangerous are waves propagating towards the cathode. We will analyze the optimized models mentioned above as well as more realistic designs that take into account existing requirements and restrictions.

6 Papers and Presentations Resulting from this Research

1. J. Calame, W. Lawson, V. L. Granatstein, P. E. Latham, B. Hogan, C. D. Striffler, M. E. Read, M. Reiser, and W. Main, "Experimental Studies of Stability and Amplification in Four Overmoded, Two-Cavity Gyroklystrons Operating at 9.87 GHz," *J. Appl. Phys.* **70** (1991) 2423.
2. W. Lawson, J. Calame, B. Hogan, P. E. Latham, M. E. Read, V. L. Granatstein, M. Reiser, and C. D. Striffler, "Efficient Operation of a High Power X-Band Gyroklystron," *Phys. Rev. Lett.* **67** (1991) 520.
3. W. Lawson, M. E. Read, W. Wang, and M. Naiman, "An Evaluation of Directional Couplers for High Power Gyrotrons," *Int. J. Electronics* **72** (1992) 1135.
4. W. Lawson, J. Calame, B. Hogan, M. Skopec, C. D. Striffler, and V. L. Granatstein, "Performance Characteristics of a High Power, X-Band, Two-Cavity Gyroklystron," *IEEE Trans. Plasma Sci.* **20** (1992) 216.
- * 5. S. Tantawi, W. Main, P. E. Latham, G. Nusinovich, W. Lawson, C. D. Striffler, and V. L. Granatstein, "High Power X-Band Amplification from an Overmoded Three-Cavity Gyroklystron with a Tunable Penultimate Cavity," *IEEE Trans. Plasma Sci.* **20** (1992) 205.
- * 6. W. Lawson and P. E. Latham, "The Scattering Matrix Formulation for Overmoded Coaxial Cavities," *IEEE Trans. Microwave Theory Tech.* **40** (1992) 1973.
- * 7. W. Lawson and V. Specht, "Design Comparison of Single-Anode and Double-Anode 300 MW Magnetron Injection Guns," Submitted May 1992 to *IEEE Trans. Electron Dev.*
8. W. Lawson, J. Cheng, V. L. Granatstein, B. Hogan, P. E. Latham, W. Main, H. W. Matthews, G. Nusinovich, M. Reiser, V. Specht, C. D. Striffler, and S. Tantawi, "Gyroklystron Research for Application to TeV Linear Colliders," *Beams '92*, Washington DC, May 26, 1992. Book of Abstracts, p. 151.
9. P. E. Latham, W. Lawson, and G. S. Nusinovich, "Design of a High-Power, Second Harmonic Gyroklystron Amplifier," *Bull. Am. Phys. Soc.* **37** (1992) 950.
10. P. E. Latham, U.-V. Koc, W. Main, S. Tantawi, B. Hogan, and W. Lawson, "Theoretical and Experimental Studies of Anomalously High Efficiency in a Three Cavity Gyroklystron Amplifier," 1992 *IEEE Int. Conf. Plasma Science*. June 1992, p. 162.
11. W. Lawson, P. E. Latham, H. Matthews, B. Hogan, V. Specht, M. K. E. Lee, C. D. Striffler, and V. L. Granatstein, "Design Studies of High-Power, Two-Cavity, Second-Harmonic Gyroklystrons," 1992 *IEEE Int. Conf. Plasma Science*. June 1992, p. 184.
- * 12. W. Main, S. Tantawi, P. E. Latham, B. Hogan, W. Lawson, C. D. Striffler, and V. L. Granatstein, "Optimization of the Output Cavity for an X-Band Gyroklystron Amplifier," *Beams '92*, Washington DC, May 26, 1992. Book of Abstracts, p. 217.
13. W. Lawson, H. W. Matthews, J. Cheng, J. P. Calame, B. Hogan, P. E. Latham, C. D. Striffler, and V. L. Granatstein, "Performance Comparison of Output Systems for a High Power Gyro-Amplifier Experiment," *Bull. Am. Phys. Soc.* **37**(1992)1536.

14. W. Lawson, H. W. Matthews, V. Specht, J. P. Calame, B. Hogan, M. K. E. Lee, C. D. Striffler, and V. L. Granatstein, "High Power X-Band and K-Band Second Harmonic Gyroklystron Experiments," Submitted to *1992 Int. Conf. Infrared Millimeter Waves*.
15. J. Calame, H. W. Matthews, W. Lawson, B. Hogan, M. K. E. Lee, J. Cheng, C. D. Striffler, M. Reiser, and V. L. Granatstein, "Initial Operation of a High Power, K-Band, Harmonic Gyroklystron for Accelerator Applications," Submitted to 1993 *Particle Accelerator Conference*.
16. W. Lawson, P. E. Latham, J. Calame, V. Specht, Q. Qian, M. K. E. Lee, M. Rimlinger, B. Hogan, C. D. Striffler, M. Reiser, and V. L. Granatstein, "Design of a 100 MW, 17 GHz Second Harmonic Gyroklystron Experiment," Submitted to 1993 *Particle Accelerator Conference*.
- * 17. W. Lawson, B. Hogan, H. W. Matthews, V. Specht, J. Cheng, P. E. Latham, C. D. Striffler, and V. L. Granatstein, "Experimental Gyroklystron Studies for TeV Linear Colliders," *LINAC '92 Conference Proceedings*, p. 383.
- * 18. C. D. Striffler, S. Tantawi, W. Main, B. Hogan, P. E. Latham, W. Lawson, U.-V. Koc, H. W. Matthews, G. S. Nusinovich, and V. L. Granatstein, "Three-Cavity Circuit Studies of the Maryland Gyroklystron," *LINAC '92 Conference Proceedings*, p. 386.
- * 19. V.L. Granatstein and C.D. Striffler, "Summary Report: High Intensity EM Waves," Proc. of the 3rd International Workshop on Advanced Accelerator Concepts, June 14-20, 1992, Port Jefferson, Long Island, NY; to be published.
- * 22. P.E. Latham, U.-V. Koc, W. Main, S.G. Tantawi, "Theoretical Investigation of Anomalous High Efficiency in a Three Cavity Gyroklystron Amplifier," to appear in the Proc. of the Beams '92 Conference, Washington, DC, May 1992.
- * 23. W. Lawson, V.L. Granatstein, B. Hogan, U.-V. Koc, P.E. Latham, W. Main, H.W. Matthews, G.S. Nusinovich, M. Reiser, C.D. Striffler, and S.G. Tantawi, "Experimental Gyroklystron Research at the University of Maryland for Application to TeV Linear Colliders," to appear in the Proc. of the 1992 Advanced Accelerator Workshop, Port Jefferson, New York, June 1992.
- * 24. W. Lawson, "Theoretical Mode Conversion in Overmoded Nonlinear Coaxial Waveguide Tapers," submitted to IEEE Trans. Microwave Theory Tech., January 1993.
- * 25. M. K. Lee, "Coaxial Gyroklystron Circuits for Linear Colliders," undergraduate honors thesis, December, 1992.

*Copies are included in the Appendix.

END

**DATE
FILMED**

5 / 12 / 93