DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

Technical Progress Report

DOE/ER/54141--1

DE93 010400

For Project

Electron Cyclotron Heating and Current Drive in Toroidal Geometry

Identification Number
DE-FG02-92-ER5-4141

Principal Investigator
Arnold H. Kritz

Department of Physics
Lehigh University
Bethlehem, PA 18015

Submitted To: Vickie L. Vickers, Contract Specialist
U. S. Department of Energy
Chicago Operations Office
9800 South Cass Avenue
Argonne, IL 60439

March 1993

RECEIVED
APR 01 1993
OSTI

MASTER
dk

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

1. Introduction

The Principal Investigator has continued to work on problems associated both with the deposition and with the emission of electron cyclotron heating power electron cyclotron heating in toroidal plasmas. In particular, the work has focused on the use of electron cyclotron heating to stabilize $q = 1$ and $q = 2$ instabilities in tokamaks and on the use of electron cyclotron emission as a plasma diagnostic. The research described in this report has been carried out in collaboration with scientists at Princeton, MIT and Livermore. The Principal Investigator is now employed at Lehigh University, and a small group effort on electron cyclotron heating in plasmas has begun to evolve at Lehigh involving undergraduate and graduate students. Work has also been done in support of the electron cyclotron heating and current drive program at the Center for Research in Plasma Physics in Lausanne, Switzerland.

Our work requires that we continue to refine the modeling capability of the TORCH code¹ (which evolved from the earlier TORAY code²). Some of our studies also requires that our electron cyclotron heating codes be linked with transport codes such as the BALDUR 1 1/2 D code.³ To facilitate code development and take advantage of the efficient environment provided by workstations, we have developed script files for taking the sources that are used on the CRAY under the BASIS interface and converting them to run under a namelist fortran format on IBM and SUN workstations. For most applications of the TORCH code, this conversion is now complete. The workstation version of the code is now being used at the University of Texas and at the Center for Plasma Physics Research in Lausanne.

An electron cyclotron driven current near the $q = 2$ surface may contribute to the stabilization of $m = 2$ instabilities. However, density fluctuations (near the edge of the tokamak plasma) effect our ability to drive the current required for stabilization. This issue has been examined in the past year and results of these studies have been presented at the Sherwood Meeting last Spring and at the Europhysics Topical Conference on RF Heating and Current Drive in Fusion Devices held in Brussels last summer. Also some of this work is included in a paper now submitted for publication.⁴ In particular, we explored scenarios for injection of electron-cyclotron heating power (electron cyclotron heating) in order to drive current locally near the $q = 2$ surface in order to suppress

tearing modes and thereby control disruptions in the Tokamak Physics Experiment (TPX). This work is summarized below in Section 2 below.

A number of computational modules have been developed for describing the deposition of electron cyclotron waves in plasmas. These include calculations based on warm plasma, weakly-relativistic and fully-relativistic descriptions of the plasma. In the past year, the applicability of these approaches for various parameter ranges has been examined. Limits on the range of applicability of each computational module has been established. Also, by refining some of the modules, the applicability was extended into domains that we have not been able to consider in previous studies. This work is described in Section 3.

We have also continued our analysis related to stabilization of the $m = 1$ instability at the $q = 1$ surface near the center of the plasma. We have examined current drive associated with electron cyclotron heating considering effects of both direct current drive and indirect current drive. The indirect current drive results from the enhanced conductivity associated with the temperature change due to electron cyclotron heating. We found in our analysis that the indirect current drive may be of the same order as the direct current drive. This work is summarized in Section 4.

2. Electron Cyclotron Current Drive in TPX

As noted above, suppression of $m = 2$ tearing modes by local current-profile modification is a possible scheme for disruption control in tokamaks. In our work, we have considered the characteristics of an electron cyclotron heating system capable of suppressing tearing modes in an early design of the Tokamak Physics Experiment (TPX).

In previous work where tearing-mode suppression by electron cyclotron heating in various tokamaks was examined, it was found that very good localization of the driven current is required. A handy expression for the required magnitude and localization of the current is introduced in Ref. 5 and refined in Ref. 6. We use an equivalent expression found by converting from r/a to poloidal flux ψ (normalized to $\psi = 1$ at the plasma edge) and denoting by ψ_{10} and ψ_{90} the flux surfaces that contain, respectively, 10% and 90% of the driven current. The required magnitude I_d of the driven current is given as

a fraction of the total plasma current I_p by

$$\frac{I_d}{I_p} = 0.4 \frac{(\psi_{90} - \psi_{10})^2}{\psi_{q=2}}.$$

This expression is applicable when the flux $\psi_{q=2}$ at the $q = 2$ surface satisfies the condition $\psi_{10} < \psi_{q=2} < \psi_{90}$. We found that the required current is seen to increase rapidly as localization deteriorates ($|\psi_{90} - \psi_{10}|$ increases). Minimization of the required electron cyclotron heating power depends on deposition and, consequently current drive in a narrow range of the poloidal flux. It is therefore important to include effects of finite width of the microwave beam and of scattering of the beam power by the drift-wave density fluctuations observed in all tokamaks. It was precisely these two items that were a major focus of our work.

Electron-cyclotron current-drive efficiency can be seriously degraded if absorption occurs at a position where velocity space contains a large trapped-electron region.⁷ The large- R part of the $q = 2$ surface is at such a position, especially in a low-aspect-ratio tokamak. Absorption on that part of $q = 2$ after injection from the low-field side of the plasma, while most attractive technologically, is often very problematic due to the physics of current drive. The high aspect ratio of TPX results in larger $\nabla\psi$ on low field side and greater sensitivity of deposition to wave and plasma parameters.

Absorption on the small- R (larger toroidal field) part of $q = 2$ avoids trapped-electron effects. Another advantage of that scenario is the relatively small $|\nabla\psi|$, which leads to better localization of the driven current. Two possible disadvantages of absorption at small R are that (a) a higher-frequency microwave source must be available and (b) unwanted second-harmonic absorption may occur.⁸ For TPX we found these disadvantages are relatively unimportant, so absorption at small R is promising. In hotter, higher-field tokamaks like ITER these disadvantages are significant.

In the results presented below, the TPX parameters used are obtained using the GA MHD code. the magnetic field, $B = 3.1$ T at the magnetic axis; the plasma current, $I_p = 1.7$ MA; the $q = 2$ surface is near $\psi = 0.79$. The density and electron temperature at $q = 2$ are about $0.35 \times 10^{20} \text{ m}^{-3}$ and 2 keV. (We also considered scattering from TPX with central temperatures of 5 keV with the temperature at the $q = 2$ surface of the order of 1 keV). The TPX equilibrium information is illustrated in Figures 1 and 2. Below we describe our study of the scattering of the electron cyclotron heating beam by density

fluctuations followed by our calculations of the power required for the suppression of the $m = 2$ tearing modes. Below we describe our study of the scattering of the electron cyclotron heating beam by density fluctuations followed by our calculations of the power required for the suppression of the $m = 2$ tearing modes.

Fig 1. TPX equilibrium used in our study of the effect of fluctuations on deposition. Plot of constant flux surfaces and plot of the q factor as a function of the normalized flux.

Fig 2. TPX equilibrium. Plots of normalized density and electron temperature as a function of the normalized flux. The plot of δn shows the amplitude and location of the fluctuations.

In our study of scattering of electron cyclotron heating beam by density fluctuations, we used a bundle of 45 rays to model a circular Gaussian beam with a waist radius of 4 cm. The rays are launched from the concave wave front 135 cm upstream from the waist and therefore represent a weakly converging beam. Rays are launched with the ordinary-mode polarization from just outside the plasma at either of two vertical positions. The first position is in the horizontal plane that contains the magnetic axis, and the beam center is parallel to that plane; this case is called “on-axis.” The second position is 70 cm below that plane, and the beam center is launched at an angle of 45° from horizontal; this case is called “off-axis.”

Scattering of rays by drift-wave density fluctuations is treated by essentially the same Monte Carlo algorithm as utilized in Ref. 9.

In this treatment the density-fluctuation wave number spectrum is taken to be Gaussian with the probability distribution for the scattering angle, β , given by

$$g(\beta) = \exp[-\gamma \sin^2(\beta/2)]$$

where

$$\gamma = 2 \left(\frac{k_0}{\zeta} \right)^2.$$

k_0 is the wavevector of the incident microwave field and ζ = typical wave number of the scattering fluctuation. The distribution of scattering angles depends on the width ζ of the wave vector spectrum of the fluctuations. We take $\zeta = 1.4 \text{ cm}^{-1}$, based on scaling (as 1/gyroradius) of experimental results.¹⁰ The probability of scattering is proportional to the density fluctuation level $\langle (\delta n)^2 \rangle^{1/2}$, which we assumed to be non-zero (parabolic) only for $0.6 < \psi < 1$ and to have a maximum value of $0.1 \times 10^{20} \text{ m}^{-3}$ at $\psi = 0.8$ (see Figure 2).

The Monte Carlo calculation is used for each step with the the probability, dp of scattering through an angle is calculated using

$$dp = ds \left(\frac{2\pi e^2}{mc^2} \right) \frac{\langle (\delta n)^2 \rangle}{k_0 \zeta^2} \int_{-\pi}^{\pi} d\beta g(\beta)$$

Each value of dp is compared with random number between 0 and 1. If $dp < \text{random number}$, then it is assumed that no scattering occurs; otherwise, a scattering angle is randomly chosen using $g(\beta)$.

Note that scattering occurs in our calculations within the absorption region but is of little quantitative importance. Scattering is important in large- R regions for beams with frequency $f \approx 120$ GHz that suffer significant spreading before reaching the small- R absorption region. Next we consider the power required for suppression of $m = 2$ tearing modes.

Even though TPX has a high aspect ratio of 4.5, we found current drive on the large- R part of the $q = 2$ surface to be problematic, because efficiency and localization were very sensitive to wave and plasma parameters. This sensitivity arises from competition between current-drive mechanisms with opposite signs.⁷ (For example, the interplay of the Ohkawa current and the Fisch-Boozer current can result in a cancellation and/or a reversal of the driven current.) Our results suggest that 1 MW of electron cyclotron heating power at 82 GHz, launched on-axis with a toroidal injection angle of 10° , would be 99% absorbed and would suppress tearing modes. Nevertheless, because of sensitivity we have reservations about the reliability of such a system. We consider the high-frequency option to be a better choice. Only if the plasma and wave parameters are well known, it might be possible to stabilize $m = 2$ modes by current drive on the low field (large R) side.

For absorption at small R we first omit scattering and show the poloidal cross section of the ray trajectories in Figure 3. Only 150 kW of incident power is required to suppress tearing modes in this on-axis case; 89% of the power is absorbed and 11% shines through. With scattering, the trajectories spread dramatically in the vertical direction (Figure 4) but little in the horizontal direction. The required power increases to 670 kW, and only 68% is absorbed. In Figure 5 integrals of the ECH power deposited and the current driven between the magnetic axis and the flux surface ψ are shown. These results indicate that an acceptable scenario exists near the chosen frequency of 116.5 GHz and injection angle of 6° , even with the rather high turbulence level assumed.

Absorption at small R can also be achieved by the off-axis launch scenario illustrated in Figure 6. This scenario has a potential advantage over on-axis launch because rays have longer paths within the absorption region and thus less shine through and better localization. Scattering lessens the localization advantage slightly. Our results are that 78% of the power is absorbed (compared to 68% on-axis), and the power requirement is 780 kW, somewhat higher than the on-axis case.

Fig. 3. Ray trajectories, projected onto a poloidal plane, for the on-axis launch scenario, without scattering.

Fig. 4. Ray trajectories for the same scenario as in Fig. 3, but with scattering.

Fig. 5. For the scenario shown in Fig. 4, integrals of power deposited (solid curve) and current driven (dashed curve). The right-hand scale, which applies to the current and ranges from 0 to -0.005, has units of amps per incident watt.

Fig. 6. Ray trajectories for the off-axis launch scenario, with scattering.

A brief study of the effects of varying T_e at the $q = 2$ surface indicates that the power requirement is fairly insensitive to T_e .

In summary, for a variety launch scenarios that were considered, suppression of $m = 2$ tearing modes would occur with 1 MW or less of electron cyclotron heating power even in the presence of a rather high turbulence level. If radial electron transport causes significant spreading of the driven-current profile, then it may be necessary to use somewhat higher, but probably still acceptable, amounts of electron cyclotron heating power to suppress tearing modes.

3. ECH Absorption Calculations

In studies of electron cyclotron heating and current drive in tokamaks, a variety of approximations and assumptions enter the calculation of the power deposition. For example depending on the temperature and cyclotron harmonic, the computation of power deposition may be based on non-relativistic, weakly relativistic, or fully relativistic considerations. In our studies of the propagation and deposition of electron cyclotron heating power in toroidal plasmas, we have utilized the TORCH code. In the TORCH code, the ray paths have been calculated using the dispersion relation for a cold plasma and a Maxwellian electron velocity distribution. The deposition of electron cyclotron heating power near the fundamental resonance has been based on either cold plasma¹¹ or weakly-relativistic theory¹² with a fully relativistic module only available for calculating the deposition at higher harmonics.¹³ (Previously, we included a damping module for relativistic absorption at the fundamental following the approach used by E. Mazzucato *et al.*,¹⁴ but unfortunately this module was not robust for the ranges of plasma parameters considered.) While the weakly relativistic limit may be appropriate for some parameter regimes, we have found that with the increasing temperatures now encountered in tokamaks, a fully relativistic treatment is often required.

Evaluation of the elements of the dielectric tensor (ϵ), or equivalently, the conductivity tensor (σ) is of upmost importance in the calculation of electron cyclotron wave absorption. These tensors are simply related by

$$\epsilon_{ij} = \delta_{ij} + i \frac{4\pi}{\omega} \sigma_{ij}$$

There are two formulations developed by Trubnikov¹⁵ that are generally used as the basis for calculating the elements of the tensor.

In the past year, we developed a robust fully relativistic absorption module for computing the absorption near the fundamental. This module is based on a general relativistic expression for the dielectric tensor, namely Trubnikov's second formula given below.¹⁵ With the assumption of a Maxwellian electron distribution, the conductivity tensor can be rewritten in terms of an integral over K-Bessel functions with complex arguments. This approach avoids the summation over harmonics so that contributions from all harmonics are included. Carrying out the integration over momentum space, one obtains the Trubnikov result (Eq. 2.11 in Ref. 15) known as Trubnikov's second formula. (Trubnikov's first formula will be discussed below.)

$$\sigma_{ij} = \frac{\alpha}{4\pi\sqrt{\beta}K_2(\rho)} \int_0^\infty \left(\frac{K_2(\sqrt{R})}{R} II - \frac{K_3(\sqrt{R})}{R^{3/2}} III \right) d\tau$$

where

$$\alpha = \omega_{pe}^2/\omega^2, \quad \beta = \omega_{ce}^2/\omega^2, \quad \rho = mc^2/T_e$$

and

$$R = \left(\rho - i\frac{\tau}{\sqrt{\beta}} \right)^2 + \frac{1}{\beta} (n_{\parallel}^2 \tau^2 + 2n_{\perp}^2 (1 - \cos \tau))$$

$$II = \begin{pmatrix} \cos \tau & -\sin \tau & 0 \\ \sin \tau & \cos \tau & 0 \\ 0 & 0 & 1 \end{pmatrix}$$

$$III = \begin{pmatrix} n_{\perp}^2 \sin \tau^2 & -n_{\perp}^2 \sin \tau (1 - \cos \tau) & n_{\perp} n_{\parallel} \tau \sin \tau \\ n_{\perp}^2 \sin \tau (1 - \cos \tau) & -n_{\perp}^2 (1 - \cos \tau)^2 & n_{\perp} n_{\parallel} \tau (1 - \cos \tau) \\ n_{\perp} n_{\parallel} \tau \sin \tau & -n_{\perp} n_{\parallel} \tau (1 - \cos \tau) & n_{\perp}^2 \tau^2 \end{pmatrix}$$

Computation of the elements of the dielectric tensor with sufficient accuracy requires care in setting the upper limit of the integration in the expression above for σ_{ij} . For each element, the oscillatory nature of the integrand, along with the relatively slow decay of the integrand, requires that when the damping is small the integration not be improperly truncated.

Once the elements of the dielectric tensor are known, there are two approaches that have been employed to compute the imaginary wave number that then yields information about the local deposition of the electron cyclotron heating power. One involves a Taylor expansion of the dielectric tensor¹¹ and the other involves an energy balance approach.¹⁶ In our studies we have found that the Taylor expansion approach is flawed and that energy balance approach must be used to obtain reliable results.

It has been shown,¹⁵ that for an arbitrary distribution function, $f(p_\perp, p_\parallel)$ where $p_\perp$ and $p_\parallel$ are the perpendicular and parallel momenta, the conductivity tensor can be written

$$\sigma = 4\pi\alpha \int \int dp_\perp dp_\parallel \left[\frac{\partial f}{\partial p_\perp} - \frac{n_\parallel}{\gamma} \left(p_\parallel \frac{\partial f}{\partial p_\perp} - p_\perp \frac{\partial f}{\partial p_\parallel} \right) \right] \sum_l \frac{M_l}{\gamma - n_\parallel p_\parallel - l\sqrt{\beta}} \\ + 4\pi\alpha \hat{z}\hat{z} \int \int dp_\perp dp_\parallel \frac{p_\parallel}{\gamma} \left(p_\parallel \frac{\partial f}{\partial p_\perp} - p_\perp \frac{\partial f}{\partial p_\parallel} \right)$$

$$M_l(p_\perp, p_\parallel) = \begin{pmatrix} -i(l\sqrt{\beta}/n_\perp)^2 J_l^2 & p_\perp(l\sqrt{\beta}/n_\perp) J_l J_l' & -ip_\parallel(l\sqrt{\beta}/n_\perp) J_l^2 \\ -M_{xy} & -ip_\perp^2 (J_l')^2 & -p_\parallel p_\perp J_l J_l' \\ M_{xz} & -M_{yz} & -ip_\parallel^2 J_l^2 \end{pmatrix}$$

where

$$\alpha = \omega_{pe}^2/\omega^2, \quad \beta = \omega_{ce}^2/\omega^2, \quad \gamma = \sqrt{1 + p_\parallel^2 + p_\perp^2}$$

All the parameters are non-dimensional, that is, $p = p/mc$.

With the assumption that the electron distribution is Maxwellian, that is

$$F(p) = \rho/(4\pi K_2(\rho)) \exp \left[-\rho(1 + p_\perp^2 + p_\parallel^2)^2 \right] \quad \text{where} \quad \rho = mc^2/T_e$$

the result for the dielectric tensor, in the equation above, reduces to

$$\sigma = \frac{\alpha \rho^2 \omega}{8K_2(\rho)} \sum_l \int_0^\infty dp \frac{p^2}{\gamma} e^{-\rho\gamma} \int_{-1}^1 d\mu \frac{M_l(p, \mu)}{(\gamma - n_{||} p \mu - l\sqrt{\beta})}$$

$$M_l(p_\perp, p_{||}) = \begin{pmatrix} (l\sqrt{\beta}/n_\perp)^2 J_l^2 & ip_\perp(l\sqrt{\beta}/n_\perp) J_l J_l' & p_{||}(l\sqrt{\beta}/n_\perp) J_l^2 \\ -M_{xy} & p_\perp^2 (J_l')^2 & -ip_{||} p_\perp J_l J_l' \\ M_{xz} & -M_{yz} & p_{||}^2 J_l^2 \end{pmatrix}$$

The J_l 's are Bessel functions of order l with argument $n_\perp p_\perp / \sqrt{\beta}$ and

$$p_\perp = p \sqrt{1 - \mu^2}, \quad p_{||} = p \mu$$

$$\alpha = \omega_{pe}^2 / \omega^2, \quad \beta = \omega_{ce}^2 / \omega^2.$$

The expression for the dielectric constant, in the equation above, is known as Trubnikov's first formula and is the form used in Ref. 13. This formulation is convenient if only a few harmonics are required. However, as the temperature increases and harmonics begin to overlap, more harmonics are required and Trubnikov's second formula described above is preferable for the absorption calculation.

Results of our studies of the validity of the various approximations used in the calculation of electron cyclotron deposition is being prepared for publication.

4. Sawtooth Stabilization Near the $q = 1$ Surface

Work on the examination of sawtooth stabilization by localized electron cyclotron heating near the $q = 1$ surface was carried out in collaboration with J. Manickam and M. Yamada of Princeton University and with P. T. Bonoli, R. C. Engade and M. Porkolab of MIT. In part this work was motivated by the fact that sawtooth oscillations in a number of tokamaks have been observed to be suppressed with deposition of electron

cyclotron power. For example, the suppression of sawteeth in the WT-3 tokamak has been interpreted in terms of reduction of shear at the $q = 1$ surface.^{21,22} The contribution to change in shear resulting from the ECH wave induced current was examined using the TORCH ray-tracing code. In our work, we determined the effect on shear associated with the change in local temperature that results from electron cyclotron heating by simulating the evolution of discharges using the combined BALDUR-TORCH transport-ray tracing codes. Changes in shear that are a consequence of the local change in temperature in WT-3 were compared with the changes in shear that result from the wave induced current drive.

In the WT-3 experiment, the stabilization depended on the electron cyclotron heating power and beam focusing. Also differences in stabilization were found when the electron cyclotron heating power was deposited at $q = 1$ on the high field side as opposed to $q = 1$ on the low field side. This is indicated in Figure 7. In Figure 7a a schematic of the wave trajectory and the electron cyclotron resonance layers are shown as vertical lines for the cases plotted in Figures 7b, 7c and 7d. The $q = 1$ surface is shown as a dotted circle. The evolution of the the soft X-ray signal is shown in Figures 7b, 7c and 7d where for Figure 7b the electron cyclotron heating at $q = 1$ is on the high field side ($B_t = 0.93$ T); for Figure 7c, the heating is on axis ($B_t = 1.02$ T; and for Figure 7d the heating is at $q = 1$ on the low field. For the examples shown $q_L = 3.4$, I_P ranges from 83 to 100 KA and the electron cyclotron power is 213 kW.

Fig 7.

Fig. 8

Stability analysis carried out using the PEST code shows that reduction of shear leads to stabilization of the $m/n = 1/1$ mode in WT-3. This is indicated in Figure 8 where as shear is reduced, the plasma moves from the unstable point A to the marginally stable point B and finally to the stable point C. Since

$$q = \frac{r B_t}{R B_p} = \frac{2\pi r^2 B_t}{R I}$$

it follows that

$$\frac{dq}{dr} = \frac{4\pi r B_t}{R I} - \frac{4\pi^2 r^3 B_t J}{R I^2}$$

so that increased current density at the $q = 1$ surface results in lower shear (dq/dr). Thus by examining plasma equilibrium generated by the PEST code, the effects of current profile modification can be assessed for the effects on stability.

In order to examine the relative effects of direct and indirect current, we used the combined BALDUR-TORCH code. BALDUR provides the evolving equilibrium for TORCH, and TORCH provides the power deposition and current-drive input for BALDUR. By omitting the current-drive input, we can study the effect of the indirect current drive. In particular, the indirect current results from the change in conductivity, σ , with temperature. That is since $\sigma = \sigma(T_e(r))$, the local current density

$$J = \sigma(T_e(r)) E(r)$$

changes with changing local temperature. The direct current drive produced by electron

cyclotron heating is the the wave induced current given by

$$\frac{J_{\parallel}}{B} = \left\langle \int d^3p \Gamma_w \cdot \frac{\partial}{\partial \mathbf{p}} G \right\rangle$$

where $\langle \rangle$ denotes a flux surface average; Γ_w is the wave-induced velocity space flux; and G is modified to include mirror-trapped particles.

Thus the current density modification by electron cyclotron heating is

$$\Delta J = \pm \Delta J_{\text{Direct}} + \Delta J_{\text{Indirect}}$$

As noted above we input to BALDUR either P_d or both P_d and ΔJ_{Direct} . With only P_d input we examined current profile (and shear) effects due to change in resistivity. In this way we determined the relative roles of $\Delta J_{\text{Direct}} + \Delta J_{\text{Indirect}}$.

In general, we found that ECH also can directly drive significant current near $q = 1$ surface. The direct and the indirect current are both significant with regard to the reduction of shear. However, in our BALDUR-TORAY simulations of the evolution of the WT-3 plasma, we found that the direct driven electron cyclotron heating current was more effective than indirect current resulting from the thermal effect on σ producing the enhanced indirect driven current. Our simulations also showed more effective reduction of shear on high field side than on low field side of the plasma.

References

- ¹R. C. Myer, M. Porkolab, G. R. Smith and A. H. Kritz, *Electron Cyclotron Wave Propagation and Absorption in the CIT Nuclear Fusion* **29**, 2155 (1989) – a brief description of TORCH appears in the Appendix of this paper.
- ²A. H. Kritz, H. Hsuan, R. C. Goldfinger and D. B. Batchelor, *Ray Tracing Study of Electron Cyclotron Heating in Toroidal Geometry*, Proceedings of the 3rd Joint Varenna-Grenoble International Symposium on Heating in Toroidal Plasmas, Commission of the European Communities, Vol. II, 707 (1982).
- ³G. Bateman, Spring College on Plasma Physics, Trieste (1985).
- ⁴Gary R. Smith, Daniel R. Cook, Allan N. Kaufman, A. H. Kritz and Steven W. McDonald, *Scattering of Ordinary-Mode Electromagnetic Waves by Density Fluctuations in Tokamaks*, submitted to Phys. Fluids (1993).
- ⁵E. Westerhof, Nucl. Fusion **27**, 1929 (1987).
- ⁶E. Westerhof, Nucl. Fusion **30**, 1143 (1990).
- ⁷R. H. Cohen, Phys. Fluids **30**, 2442 (1987) and **31**, 421 (1988).
- ⁸G. R. Smith, R. H. Cohen, and T. K. Mau, Phys. Fluids **30**, 3633 (1987).
- ⁹B. Hui, E. Ott, P. T. Bonoli, and P. N. Guzdar, Nucl. Fusion **21**, 339 (1981).
- ¹⁰R. L. Watterson, R. E. Slusher, and C. M. Surko, *Phys. Fluids* **28**, 2857 (1985).
- ¹¹D. B. Batchelor and R. C. Goldfinger, *RAYS: A Geometrical Optics code for EBT*, ORNL/TM-6844 (1980).
- ¹²I. P. Shkarofsky, Phys. Fluids **9**, 561 and 570, 1966; J. Plasma Phys. **35**, 319 (1986); I. P. Shkarofsky and A. K. Ghosh, Technical Report 232-1, MPB Technologies Inc. (1984).
- ¹³D. B. Batchelor, R. C. Goldfinger and H. Weitzner, Phys. Fluids **27**, 2835 (1984).
- ¹⁴E. Mazzucato, I. Fidone, and G. Granata, Phys. Fluids, **30**, 3745 (1987).

- ¹⁵B. A. Trubnikov, *Electromagnetic Waves in a Relativistic Plasma in a Magnetic Field in Plasma Physics and the Problems of Thermonuclear Reactions*, Ed. by M. A. Leontovich, trans. J. B. Sykes, Pergamon Press, London, Vol. 3, 122 (1959).
- ¹⁶M. Bornatici, R. Cano, O. DeBarbieri and F. Engelmann, Nucl. Fusion **23**, 1153 (1983), Sec. 2.2.2.
- ¹⁷P. A. Robinson, Plasma Physics and Controlled Fusion, **27**, 1037, 1985.
- ¹⁸I. Fidone *et al.*, Nucl. Fusion **26**, 1537 (1986).
- ¹⁹M. Bornatici and U. Ruffina, Plasma Physics and Controlled Fusion, **30**, 113, 1988.
- ²⁰Y. Matsuda and Gary R. Smith, *A Microinstability Code for a Uniform Magnetized Plasma with an Arbitrary Distribution Function*, J. Comput. Phys., **100**, 229, 1992.
- ²¹R. T. Snider *et al.*, Phys. Fluids **1B**, 404 (1989).
- ²²K. Hanada *et al.*, Phys. Rev. Lett. **66**, 1974 (1991).

END

**DATE
FILMED**

4 / 28 / 93