Lh. 2667

Review

CL

198
5-26-81
gph
R4590

(1)
LH. 2667

Prepared for **DOE** under contract
No. W-7405-Eng-48

About the cover

Modern nuclear weapons design involves an immense amount of computer simulation to predict the behavior of rapidly imploding objects. At some point, it becomes necessary to verify the computational models experimentally. One way to do this is to take a flash x-ray picture, i.e., to record the imploding geometry radiographically at a given moment. Shown on the cover is a six-module electron source that will be used in the LLNL flash x-ray (FXR) machine. A four-module assembly similar to the one shown has been used to validate the design of a full 54-module machine (currently under construction), which will be capable of delivering an x-ray dose of 500 R within 60 ns. This dose is five times greater than that available from our existing flash x-ray machine, and the exposure time is two to three times shorter. Thus, FXR will permit us to look deeper into the implosion with less motion smear than before. For more information on FXR and the design problems it has posed, see the article on p. 1.

About the journal

The Lawrence Livermore National Laboratory is operated by the University of California for the United States Department of Energy. The Laboratory is one of two nuclear weapons design laboratories in the United States. Today more than half of our effort is devoted to programs in magnetic and laser fusion energy, basic physics and chemistry, biomedical and environmental research, applied energy technology, and other research activities.

The *Energy and Technology Review* is published monthly to report on accomplishments in these research and applied technology efforts and on unclassified portions of the weapons program. A companion journal, the *Research Monthly*, reports on weapons research and other classified programs. Selected titles from past issues of the *Energy and Technology Review* are listed opposite the inside back cover.

Scientific editor

Stein Weissenberger

General editors

Jay C. Cherniak
Richard B. Crawford
Patricia L. Lien
Kent Madsen
Palmer T. Van Dyke
Barbara S. Strack

Graphics designer

John Schuster

Energy and Technology Review

May 1981 Lawrence Livermore
National Laboratory

Implosion Experiments

We have built and tested a prototype of the basic power module and accelerating cell of the new LLNL flash x-ray machine (FXR). The new machine will permit us to verify computer simulations of the behavior of rapidly imploding objects.

LLNL engineers have developed an inexpensive substitute for the Faraday isolators that now protect our large lasers from back-reflected light.

A huge superconducting magnet for the LLNL Mirror Fusion Test Facility (MFTF) will be capable of generating powerful fields at modest energy costs thanks to a liquid-helium cooling system and extensive thermal protection.

Researchers can now measure soft, pulsed x rays, even against an intense and mixed radiation background.

Using the techniques by which tiny integrated circuits are made, we can fabricate instrument parts smaller than any that could be machined by conventional methods.

A new minicomputer-based, interactive graphics system makes it easy for electronics engineers to translate their design ideas into fully documented schematics and high-quality circuit-board drawings.

Using a hair-thin laser beam and a brazing alloy, we can join tiny, heat sensitive instrument parts without damage or distortion.

DISCLAIMER

UCRL 52000-81-5
Distribution Category UC-2
May 1981

Engineering at LLNL

This issue of Energy and Technology Review focuses on recent engineering achievements at LLNL. From the refinement of plasma diagnostics to the development of a nonmechanical shutter for our giant lasers, from the validation of a new flash x-ray (FXR) design to the development of techniques for machining tiny Fresnel zone plates, engineering plays a vital role. Research in fields as diverse as nuclear weapons design, laser- and magnetic-fusion energy, and biomedical and environmental sciences is enhanced by the efforts of engineers who find innovative solutions to problems, increase productivity, and help to meet established goals and commitments.

The three engineering departments—electronics engineering, mechanical engineering, and plant engineering—employ about 3500 people, almost half of the total Laboratory staff. In matrix fashion, they supply the engineering technology, personnel, management, and goods and services necessary to achieve program goals. In addition, they anticipate future needs by maintaining and renewing the current engineering technology base, preserving useful engineering capabilities, and retaining a highly competent technical staff.

Each of the three departments contributes engineering expertise strongly flavored by the technical requirements of the Laboratory's diverse programs. Often, technologies beyond the current state of the art must be developed.

- *Electronics engineering provides the full spectrum of capabilities necessary to develop anything from a new transducer, a microcomputer controller, or a multimewatt pulsed power supply, to hardware and software for a complete research system (including control, diagnostics, data-acquisition, data-reduction, and display systems).*

- *Mechanical engineering designs, builds, and tests prototype hardware, makes precision measurements, and performs theoretical analyses. Among its many recent accomplishments are the invention of a laser brazing process by which hair-thin metal parts can be joined securely without damage or distortion and the design of a two-story coil-winding machine used in fabricating large superconducting magnets for our mirror fusion test facility (MFTF).*

- *Plant engineering conceives, plans, designs, constructs, and maintains a number of facilities and utility systems, including office buildings, exotic research laboratories, and a very large "clean room" housing the Shiva laser.*

Together, the three engineering departments strive to provide any engineering capabilities that are needed in our programs. For further information on engineering at LLNL contact Henry C. McDonald (415/422-8351).

Validation of the pulsed-power design for FXR

For further information contact
Bernhard Kulke (415/422-8625).

LLNL's new flash x-ray machine (FXR) is a linear-induction accelerator scheduled for completion in late 1981. It will use a pulsed electron beam (20-MeV, 4-kA, 60-ns) to generate 500 R of bremsstrahlung x rays 1 m from a target. FXR will consist of 54 modules: 6 injector modules plus 12 duplicates of the basic 4-module accelerator block. To deal with design uncertainties, we have built and tested prototypes of the basic power module, including the four-module accelerator block itself. Our measurements validate important design features such as high-voltage hold-off margins, pulse shapes, and switchgap performance.

Modern nuclear weapons design involves an immense amount of computer simulation to predict the behavior of rapidly imploding objects. At some point it becomes necessary to verify the computational model experimentally. One way to do this is to take a flash x-ray picture (i.e., to record the imploding geometry radiographically at a given instant) and compare the result with the prediction. However, it takes a very large x-ray dose delivered in a small fraction of a microsecond to penetrate the objects involved and to form an image quickly enough to stop the rapid inward motion of the boundary surfaces.

The FXR linear-induction accelerator is designed to deliver an x-ray dose of 500 R at a distance of 1 m from the beam target within 60 ns. This dose will be five times greater than that available from our existing flash x-ray machine, and the exposure time will be two to three times shorter. Thus, FXR will permit us to look deeper into the implosion with less motion smear than before. Moreover, FXR will be modular, making possible later expansion to increase the x-ray intensity by a factor of 10.

For convenience in tuning the machine before firing a radiography pulse, we have designed FXR to be pulsed at 3-s intervals. Because explosives experiments are expensive, the machine must also be highly reliable: we aim to have no more than one failure in 1000 experiments. Both requirements are unusually severe in a high-voltage, pulsed-power environment.

To validate the design of our high-voltage, high-current electrodes, switches, and insulators, we have assembled a four-module test version of the FXR. We have fired this test version about 100 000 times at nominal voltage levels (400 kV per module) and tens of times at elevated voltages, identifying statistical properties and optimum operating ranges for the two most important types of high-voltage switch.

The large number of shots, in addition to confirming the basic pulsed-power design, revealed weaknesses or excessive wear rates

in certain components in time to improve the design. The test exercise was also a valuable training experience for personnel who will build and operate the FXR machine.

A full discussion of FXR—including descriptions of the injector system, the Marx generators, the switching system, beam transport, monitoring and control, and the mechanical systems necessary to manage water, oil, gas, and

vacuum—has been published elsewhere.¹ This article concentrates on the design features and test results.

Overview of the FXR design

The FXR machine applies a local electric field to a cluster of traveling electrons, accelerating them to very high energies and directing them at a bremsstrahlung target. The target responds by emitting an intense, forward-

directed cone of x rays, which is aimed through an armored "bullnose" at a test object on the firing table. A film cassette behind the object records an x-ray shadowgraph of the object as it is detonated.

As shown in Fig. 1, FXR consists of 54 identical accelerator modules, 6 of which are used in the electron source. A 4-kA beam is accelerated through the remaining 48 modules (grouped in 4-module

Fig. 1 Plan view of the LLNL flash x-ray (FXR) facility. The FXR machine is a linear-induction accelerator used to produce an x-ray pulse intense enough and short enough to penetrate an imploding object and to capture on film its shape at a given instant. The accelerator consists of 54 identical accelerator modules, 6 of which are used to power the cold-cathode electron source. The 4-kA electron beam is accelerated as it travels from the source to the target area through the remaining 48 modules (grouped in blocks of 4), each of which adds some 400 keV to the beam energy. The final energy is near 20 MeV. The accelerated beam travels through a diagnostic area and is focused onto a bremsstrahlung target. The target emits an

intense, forward-directed cone of x rays, which is aimed through an armored "bullnose" at a test object on the firing table. The pulse of x rays is timed so that a film cassette behind the object will record an x-ray shadowgraph of the object as it is detonated. A massive concrete bunker protects both the machine and the operators from the blast of the test shot on the firing table. Internal concrete shielding acts as radiation protection for people working in the electronics corridor while the machine is running. A large underground optics room contains high-speed cameras that will be synchronized with the FXR radiography pulse to permit simultaneous optical observation of the test object.

blocks). The final beam energy is approximately 20 MeV. The FXR design extends the parameters of a

similar machine that was built and operated at the Lawrence Berkeley Laboratory some 10 years ago. A

53-m-long blast-resistant building will house the new machine.

Shown in Fig. 2 is a simplified cross section of one of the four-module accelerator blocks together with information on the pulsed-power conditioning needed to create the potential difference that accelerates the electrons. A high-voltage dc power supply first energizes a conventional, parallel-charged, series-discharged (Marx) capacitor bank at the 35-kV level over a 3-s time period. Through internal spark-gap switches, the Marx bank is then connected to four Blumlein pulse-forming lines (capacitive energy storage elements that are capable of producing a flat-topped output pulse). The Blumleins are charged from the Marx bank for 1.8 μ s, and then each Blumlein is fired through its own spark-gap switch. This transfers 800 J of stored energy in 90 ns into each accelerating cavity, or cell. (In effect, the 35-kV initial dc charging voltage has been amplified to the 400-kV level as the pulse length has gone from 3 s to 90 ns.) A large fraction of the Blumlein energy is dumped into ballast loads to stabilize the pulse that provides the accelerating voltage.

The cavity geometry would short out the applied Blumlein pulse almost immediately, were it not for the toroidal ferrite cores shown in Fig. 2; the change in magnetic flux

Fig. 2 Shown here is a simplified cross section of the four-module accelerator block used to validate the FXR design. Information is also provided on the pulsed-power conditioning needed to create the time-varying electric field that accelerates the electrons. A high-voltage dc power supply energizes a conventional, parallel-charged, series-discharged (Marx) capacitor bank at the 35-kV level over a 3-s time period. Through internal spark-gap switches, the Marx bank is then connected to four Blumlein pulse-forming lines (capacitive energy storage elements that are capable of producing a flat-topped output pulse). The Blumleins are charged from the Marx bank for 1.8 μ s, and then each Blumlein is fired through its own spark-gap switch, transferring 800 J of stored energy in 90 ns into each accelerating cavity, or cell. (In effect, the 35-kV initial dc charging voltage has been amplified to the 400-kV level as the pulse length has gone from 3 s to 90 ns.) A large fraction of the Blumlein energy is dumped into ballast loads to stabilize the pulse that provides the accelerating potential. The cavity geometry would short out the applied Blumlein pulse almost immediately, were it not for the toroidal ferrite cores; the change in magnetic flux induced in the ferrite by the pulse corresponds exactly to the applied voltage pulse height and duration. During a 90-ns interval, a 400-kV axial potential difference thus appears across each vacuum gap, accelerating the electron beam as it passes through.

induced in the ferrite by the pulse corresponds exactly to the applied voltage pulse height and duration. During a 90-ns interval, a 400 kV axial potential difference thus appears across each vacuum gap, ac-

celerating the electron beam as it passes through.

The designs of a single accelerator cavity and its driver module are shown in Fig. 3. Early tests with a single module led to

design improvements that were incorporated into the final hardware that made up our four-module prototype system; the major part of the testing took place on the latter, shown in Fig. 4.

In the actual machine, the accelerator cavities must be turned on (switched) in synchronism with the passage of the electron beam. Accurately cut lengths of charged cables will distribute and amplify the command pulse using the inherent voltage reversal that results from shorting the cable ends (with a spark-gap switch). For the prototype tests, we mocked up enough of this switching system to activate the four test cavities. This allowed us to characterize extensively the two key types of spark-gap switch.

High-voltage hold-off design

In FXR, insulators and electrode spacings must withstand voltage stress for various periods of time. Several different media (oil, water, vacuum, and pressurized gases) are involved. After some initial problems had been solved, our prototype reached a peak cavity voltage of 530 kV without breakdown in a series of 20 shots. This established a comfortable margin over the nominal peak operating voltage of 400 kV. We will now discuss, in turn, some key components of the basic FXR module (shown in Figs. 3a and 3b) and the voltage hold-off considerations that apply to each of them.

Blumleins and feed lines.

Standard design formulas exist for estimating the field stress in regions bounded by simple, coaxial cylinders, but these formulas do not apply for doubly curved surfaces. For surfaces of revolution, such as the bottom of the concentric Blumlein conductors or the tapered insulators, a computer code maps equipotential lines and thus, in effect, calculates the field stress at these surfaces.

The criterion used to determine the permissible level of field stress generally depends on the medium,

the polarity, and the electrode geometry. In vacuum, the field stress on negative-polarity metal

Fig. 4 (a) Four accelerator modules in the FXR. Each module is driven from two horizontally opposed feedline ports, with two vertically opposed CuSO_4 ballast loads mounted in quadrature with the feedlines. (b) Four Blumlein pulse-forming lines in the FXR. The Marx generator tank is partially hidden behind the Blumleins.

surfaces was maintained below 200 kV/cm, which is below the field emission threshold. For insulating oil, a commonly used design value for voltage hold-off under short-pulse conditions is 400 kV/cm. However, to date, most high-voltage, pulsed-power devices have been designed to operate in a single-pulse mode. Under these conditions there is ample time between pulses for possible corona products (such as gas bubbles or carbon particles) to diffuse away from the breakdown region. Because this might not be the case for FXR (firing at 3-s intervals), the nominal field stress under oil was generally kept below 200 kV/cm. In water, the breakdown stress depends on polarity. Other workers have invested a great deal of effort in developing a useful set of empirical design formulas.²

Table 1 lists the design stresses for the simple coaxial regions of the (more highly stressed) inner half of the Blumlein and for the feed line, and the calculated breakdown stress for each case. With the relatively large safety factors evident in Table 1, it is hardly surprising that breakdown was not a problem in these areas.

A major concern throughout the four-module test has been the proper filtering and degassing of the insulating liquid (water or oil) and the development of transfer procedures that avoid inadvertent aeration of the previously degassed liquid. Grooves and channels in insulators and along metal surfaces allowed rising bubbles to escape or migrate away from stressed surfaces. In addition, both the oil and the water volumes were routinely evacuated before filling with the degassed liquid at atmospheric pressure, and the dielectric fluid (water) in the Blumleins and feed lines was recirculated and degassed continuously.

Accelerator cavities. Critical high-voltage stress points occur at the epoxy insulator separating the oil from the vacuum side, at the accelerating gap, and at the inner and outer diameters of the oil-immersed ferrite toroids (Fig. 3b).

The epoxy insulator has a calculated peak surface stress of 60 kV/cm near the upper edge on the vacuum side. The highest stress at the accelerating gap occurs on the negatively charged inner rim. Because the rim is rounded to a radius of 19 mm, the field here is 90 kV/cm, safely below the nominal 200-kV/cm field-emission threshold.

Machined polyethylene shims support and space the 25-mm-thick ferrite toroids to ensure some oil circulation (free convection) both around and between them. With a resistivity of $10^7 \Omega \cdot \text{cm}$, the ferrite acts as an insulator. However, the inherent uncertainty in the ferrite permittivity translates into unknown and potentially large field stresses in the oil layer and, worse, in the polyethylene spacers.

We obtained encouraging information on this uncertainty when we disassembled a single cavity that

Table 1 Coaxial design stresses at 400 kV and calculated breakdown stresses for Blumleins and feed lines.

Component	Design stress, kV/cm	Calculated breakdown voltage, kV/cm
Inner half of Blumlein, inner conductor (-)	149	238
Inner half of Blumlein, outer conductor (+)	67	113
Feed line, inner conductor (-)	314	562
Feed line, outer conductor (+)	13	233

had been tested to some 20 000 shots at 360 kV. The polyethylene shims showed no signs of corona damage or of volume breakdown.

A typical overlay of 10 successive pulse traces at a 400-kV gap voltage is shown in Fig. 5; these traces are representative of the 100 000-shot test series on the four-module system, and they illustrate the low time and amplitude jitter obtained with this system.

Electrode design for large currents

In addition to designing for high-voltage hold-off, we had to be concerned with currents in the tens of kiloamperes as the high-voltage sources discharge into relatively low-impedance loads. FXR has a shorter firing interval than most commercial pulsed-power equipment, and faster erosion may be expected because of the resultant thermal and mechanical environ-

ment. The FXR prototype tests did, in fact, uncover erosion problems both in water and in sulfur hexafluoride (used to pressurize some switchgaps), making it necessary, for example, to replace an electron-beam-welded, tantalum-stainless steel switchgap electrode with a one-piece stainless steel design.

Similarly, after 60 000 shots, we found severe erosion on the flat contact surfaces joining two of the Blumlein conductors to their switchgaps. The joints had loosened, allowing a thin film of water to intrude. To remedy this problem, we made these end surfaces concave, leaving the raised edges to make the actual contact and greatly increasing the contact pressure there. In a nanosecond pulse circuit, almost all the current flows on the surface of the conductors, making good contact at the joint edges of paramount importance. We have also applied this

type of edge-to-plane contact successfully elsewhere in the FXR design.

Switchgap characteristics

While the four-module test permitted the mock-up of only a small part of the overall FXR switching system, this was adequate to characterize the Blumlein switch (which handles 300 to 400 kV) and the switch that triggers the Blumlein. These switches are spark gaps (not unlike ordinary automobile spark plugs) that operate in a pressurized-gas environment. Normally open, they are triggered to spark (i.e., to close a circuit) from a third auxiliary electrode. Variations in the time it takes for the switch to close are referred to as "jitter." Both switches turned out to have comfortable operating ranges, extending over some 70 to 150 kPa of gas pressure, where the probabilities of the gap firing either prematurely or too late are negligible. The trigger switch jitter, with $\sigma = 1.5$ ns, dominated system performance. However, a few nanoseconds of jitter should not affect

the beam quality because the 60-ns beam pulse will be timed to coincide with the flat top of the 90-ns accelerating pulse, thus leaving a wide window for relative shifts of the two pulses. This means that reasonable care in assembling trigger cable lengths (to an accuracy of a few centimetres) should produce practically perfect synchronism with a very low probability of beam degradation.

Conclusions

Tests performed on the prototype tandem block of four FXR modules have demonstrated comfortable margins for high-voltage hold-off and for switchgap

jitter and prefire/late-fire probabilities, with an almost ripple-free and highly repeatable accelerating-voltage pulse shape. In pulsing the system some 100 000 times, we learned how to improve significantly both high-current electrode design and system operational procedures. Thus, as we build and operate the complete FXR machine, we will have the benefit of a fair amount of hands-on experience.

Key words: electron accelerators, flash x-ray sources, FXR, particle accelerators, x-ray sources

Notes and references

- 1 B. Kuike et al., *Design of a 20-MeV, 4 kA Linear Induction Accelerator*, Lawrence Livermore National Laboratory, UCID 18939 (January 1981)
- 2 *Pulsed Electrical Power Dielectric Strength Notes*, PEP 5-1, AFWL TR 73-167, Air Force Weapons Laboratory, Kirtland AFB, New Mexico (April 1973)

The Nova plasma shutter

For further information contact
Irving F. Stowers (415/422-0407)
or Laird P. Bradley (415/422-6154)

We have developed a relatively inexpensive way to protect the Nova laser system against damaging back-reflected light. Our new plasma shutter shoots a reflective plasma across the beam path in the 400-ns interval between the passage of the main beam pulse and the return of the reflected light. Testing shows that this plasma is more than adequate to stop light of the intensity expected from Nova. Faraday rotator-polarizer isolators of the kind we are now using to protect the Shiva laser system from back-reflected light would cost \$500 000 apiece if designed for the Nova system. Each plasma shutter will cost only \$80 000.

The Nova laser system will consist of 20 separate lasers in parallel, in each of which a relatively narrow beam of 1.05- μ m light grows progressively larger in diameter and more intense as it passes through a long series of neodymium-glass amplifiers (Fig. 1). All 20 beams will be finally focused on a tiny deuterium-tritium target so as to produce a fusion reaction. However, not all of the laser light will be absorbed by the target capsule; some will be reflected; and if this reflected light were to get back into the amplifiers it would travel back down the chain in the wrong direction wreaking havoc on our equipment.

To protect the existing Shiva laser system from back-reflected light, we use optical "diodes" known as Faraday rotator-polarizer isolators. These devices contain a pair of polarizing plates separated by a paramagnetic material that rotates the plane of polarization of light passing through it by 45°. Light going toward the target can get through, but light coming back is stopped because the second 45° rotation puts the plane of polarization at 90° with respect to the original polarizer.

Faraday isolators are expensive. Furthermore, they introduce unnecessary losses, thus making added amplification a necessity. Units scaled for the Nova laser system would cost about \$500 000 apiece, plus the cost of the additional amplification.

One alternative way of protecting the laser would be to close a shutter across each of the beam paths after the main pulse passes by and before the reflected light gets back. However, the forward and return beam pulses are only 400 ns apart. Thus, such a shutter would have to be extremely fast. To cross the full beam aperture (46 cm) in 400 ns, a shutter would have to move at an impossible speed of more than 1000 km/s.

There are places in the laser chain (the spatial-filter pinholes) where the beam is focused to a diameter of 6 mm or smaller. However, a shutter placed at one of these points would still need to move at an extravagant 15 km/s to

bridge the gap in time. Furthermore, where the beam diameter is small, the beam energy is very concentrated, and thus, any conventional shutter placed directly in a pinhole would be instantly vaporized. What we need, then, is a renewable shutter-like device that can be placed in the beam path

reliably at a speed of more than 15 km/s.

Operating principles

Above a certain critical density, a plasma (a cloud of electrons and ionized atoms) will totally reflect light. Because it is vaporized plasma is relatively easy to ac-

celerate to high velocities. Since it consists of charged particles, we can use a magnetic field (generated by a pulser circuit) to fire it across the beam. With these basic principles in mind, we have developed a plasma shutter that meets all our requirements for the Nova laser system.

In our plasma shutter (Figs. 2 and 3) a fast electronic switch dumps a current of 500 kA from four large capacitors charged to 35 kV through a thin (50 μm) aluminum ribbon. The ribbon explodes, forming a dense plasma (1.5×10^{21} ions/ cm^3). Magnetic fields, generated by the heavy

currents flowing through the connecting leads and the plasma, accelerate the plasma to 20 km/s as it moves across the laser beam path.

Two plasma-shutter modules have been built to date, and both of them are undergoing testing and refinement. We are using one to study the plasma generated, to

characterize the high-voltage electronics of the pulser circuit, and to investigate the reliability and life expectancy of the device. With the other module, we are evaluating the control system, investigating ways of minimizing electromagnetic interference, testing the ribbon-changing mechanism, and

performing high-power tests on the Shiva laser system.

The pulser

The basic design requirement of the pulser circuit is that it have a current in excess of 300 kA when the ribbon explodes, and hence a fast current rise-time (implying a very low inductance). Furthermore, since we want magnetic propulsion after the burst, the current must continue and even increase. The circuitry must be extremely reliable because a single misfire could ruin one of the laser's arms.

There must be a mechanism for replacing the ribbon after each shot, and this equipment must operate inside the evacuated spatial filter. Each ribbon changer must hold a large supply of fresh ribbon to facilitate reloading. Furthermore, the design must prevent vaporized aluminum from depositing on the nearby spatial-filter optics.

Figure 3 is a simplified equivalent pulser circuit. To make the rail-gap switches fire reliably, we trigger them with a 100-kV, 8-ns

spark that pre-illuminates their surfaces with ultraviolet light. By initiating electron avalanches and streamers, the ultraviolet light predisposes the railgaps to fire simultaneously when the trigger pulse arrives, reducing the jitter (the variability between firing times) to about 1 ns. This pre-illumination is especially important as the triggering blades become rounded with age.

One of the major innovations built into the design is a special silicone elastomer insulator for the coaxial connector. Coaxial design

minimizes the number of exposed edges at high voltage, and the silicone minimizes arcing across insulator surfaces. Its elasticity enables it to bounce back after a magnetically induced impulse and to maintain contact with the conductors.

Experimental results

We have investigated the operation of the plasma shutter experimentally and with a two-dimensional computer model. The model has been particularly useful to us in selecting an operating

Fig. 3 Schematic drawing of the discharge and triggering circuits of the plasma shutter. A thyatron dumps a 100-kV pulse through each of the eight pre-illumination gaps (one shown) and into the rail-gap triggering blade, which in turn discharges to the lower rail. This discharge provides multiple paths for a fast-rising 500-kA arc in the rail gap, which explodes an aluminum ribbon to produce a dense plasma of electrons and aluminum ions.

point, interpreting the experimental data, and scaling up from initial experiments. In our experiments, we have monitored the charge voltage of the capacitors and the current and voltage near the ribbon (with electrical instruments) and shutter closure with a probe laser. We have measured the angular distribution and density of the emitted plasma with glass witness plates and the plasma-front velocity with a Faraday cup and with a streak camera. Recently we installed an LLNL-developed, 5-keV, pulsed x-ray backlight source with which we

radiographed the plasma as it emerged from the nozzle.

Figure 4 combines the results of Faraday-cup and streak-camera measurements with SHUT-code predictions for the plasma-front velocity. We also combined the divergence measurement, the nozzle geometry, the initial ribbon size, and the Faraday-cup arrival time to estimate the peak plasma density at 1.5×10^{21} ions/cm³. (These data have now been verified with the x-ray backlight diagnostic.) This is 50% more than the critical density for 1.05- μ m light.

At the location planned for the plasma shutter in the Nova laser, we expect a reflected beam intensity of 1 TW/mm². Calculations with LASNEX (a code for simulating the interactions of laser light with plasma) indicate that a beam of this intensity will burn through only 2% of the plasma thickness. We recently tested the second prototype plasma shutter on the Shiva system and successfully blocked a 5-ns, 400-J pulse focused to 10 TW/mm².

Despite its mechanical complexity and its technical sophistication, the plasma shutter is an economical replacement for the Faraday isolator. Whereas isolators suitable for use in the Nova laser system would cost \$500,000 each, we can build a plasma shutter for \$80,000.

Key words: critical density, Faraday isolator, SHUT, Nova laser system, plasma shutter, Shiva laser system

Fig. 4 Comparison showing the excellent agreement between SHUT-code-calculated plasma velocity and streak-camera and extrapolated Faraday-cup measurements. (The experimental data were not used in developing the code.) This close agreement increases our confidence in other calculations involving the beam fluence of the full Nova system.

Thermal control of the MFTF superconducting magnet

For further information contact
James H. Van Sant (415/422-9890).

The 300-tonne superconducting magnet for the LLNL Mirror Fusion Test Facility (scheduled for testing this year) should produce strong magnetic fields at modest energy costs. This happy result has been achieved through extensive analysis and testing of unique design features, including liquid-helium cooling (to produce the low temperatures required to make superconductors of the windings), insulation from heat sources, and protection in the event of a magnet quench. Experiments conducted with this magnet will give us the information we need to design a 22-coil magnet system for the MFTF-B machine, a tandem mirror fusion experiment scheduled for operation in 1985.

When engineering experiments with the Mirror Fusion Test Facility (MFTF)¹ begin at LLNL this year, the world's largest superconducting magnet, weighing nearly 300 tonnes and storing up to 440 MJ of energy, will go into operation. The economic feasibility of large magnetic-fusion experiments depends on the use of such magnets, cooled to the point at which the electrical resistivity of the windings vanishes. If a conventional magnet were used in MFTF, a 1000-MW power supply and a large water cooling system would be required. As it is, the MFTF superconducting magnet will require only two 1800-W power supplies.

A similar design will be used in the giant magnet system for the Tandem Mirror Fusion Test Facility (MFTF-B),² scheduled for operation at LLNL in 1985. MFTF-B,

which will contain two MFTF-type magnets along with 18 other large superconducting magnet coils, will be used for experiments crucial to our efforts to harness thermonuclear fusion.

Superconductivity is a low-temperature phenomenon. Thus, the basic thermal engineering problem in designing the MFTF magnet was to cool and insulate it properly. Cooling will be achieved by flooding the coils with liquid helium at a temperature of 4.5 K. However, since this temperature is only 0.5 K below the transition temperature of the winding materials (i.e., that at which they become stable superconductors), the magnet must also be protected from external heat. Otherwise, it will simply cease to function. To avoid this problem, we maintain good circulation of liquid helium throughout the coils and insulate it from external heat sources. The magnet is so well protected thermally that it should require extraction of only 460 W of heat energy.

Magnet cooling

The MFTF magnet will be cooled by natural circulation of liquid helium from an elevated supply Dewar (Fig. 1a). Since the magnet is in the riser leg of the flow

Fig. The MFTF magnet, vacuum vessel, and liquid-helium flow system. (a) The magnet coils are oriented at a 45° angle with respect to the horizontal and positioned below the helium Dewar so that heat loads on the magnet will induce natural flow. If a magnet quench should occur, the return and supply valves close, and the vent valves open to vent gaseous helium into a recovery bag. (b) Seven struts (not all shown) support the magnet in the vacuum vessel. Heat flow in the struts from the warm vessel wall is intercepted by liquid-nitrogen-cooled heat barriers. Gaseous helium flowing out the current leads intercepts heat flowing in through them.

circuit, the heat absorbed there induces thermosiphon flow. This useful phenomenon eliminates the need for pumps and ensures that the helium flow rate will increase with heat load. To handle the estimated heat load, 6 l/s of liquid helium, with an average vapor quality of less than 1%, will flow through the coils.

The geometry of the MFTF magnet is shown in Fig. 1b. Two large, folded solenoid coils are joined together in what is known as a yin-yang configuration. To assure

proper helium flow and eliminate vapor trapping, the symmetry planes of the coils are oriented at a 45° angle with respect to the horizontal.

Helium enters at the lowest point and exits at the highest point in each coil. Flow divides internally so that a portion goes through each half of the coil. The coils each have a dedicated piping circuit so that during cool-down and warm-up cycles, flow can be controlled to keep temperatures relatively even and thus limit thermal stresses.

A plenum constructed of porous electrical insulation (not shown in Fig. 1) is included at the top and bottom of each coil near the supply and outlet ports. The plenums distribute the flow entering and leaving the coils and allow vapor to separate from the coil bundle so that the conductor itself is always in liquid.

The superconductor is cryostable under MFTF magnet conditions.⁴ (That is, it will tend to recover to below the transition temperature if its temperature rises momentarily as a result of a transient heat pulse.) Each coil contains over 25 km of multifilament Nb-Ti in a 6-mm X 6-mm copper matrix encased in a 12-mm X 12-mm copper stabilizer (Fig. 2). Cooling passages in the stabilizer allow transverse and axial flow, which more than doubles the effective heat-transfer surface area. Slotted sheets of electrical insulation between coil layers and insulator buttons between coil turns permit two-dimensional cross-flow on the outside of the conductor. This design results in an effective porosity of 0.32 and a hydraulic diameter of 3.2 mm. This allows adequate helium flow throughout the coil bundle.

Thermal protection

Because it is essential to limit the flow of heat to the magnet, we had to take into account all possible heat sources, conductive and radiative. Heat can be conducted to the magnet through supports, current leads, and instrumentation wires, and it radiates to the magnet from warm surfaces nearby. (The MFTF-B magnets, scheduled for operation in 1985, will also be heated by plasma radiation and fusion neutrons. These are not a

factor in MFTF technology demonstration tests.¹) We have eliminated thermal convection heating by placing the magnets in a vacuum environment. However, heat conduction cannot be eliminated entirely. The magnet must be supported by something ultimately in contact with a warmer structure, and it must be connected electrically to a warm power supply. However, by using low-thermal-conductivity materials in these areas and by intercepting the heat inflow, we can minimize the problem.

Protecting against heat conduction. The seven magnet support struts have been designed to conduct as little heat as possible. They consist of stainless steel rods with optimally located annuli filled with liquid nitrogen (LN). The annuli serve as thermal barriers (Fig. 1). Even though the supports are large (27 cm in diameter, with a

wall thickness of 29 mm), less than 8 W are conducted into the magnet through each one, primarily because of the low thermal conductivity of stainless steel at cryogenic temperatures. At 5 K stainless steel has a thermal conductivity less than 1% of that at room temperature. Cheaper carbon steel was not used because it has a much higher thermal conductivity at 5 K.

Our design of the electrical connections also limits the amount of heat conducted to the magnet. Each lead is constructed of sixty 1.5-m-long copper tubes in a stainless steel tube (Fig. 3). Helium vapor flows inside the copper tubes, which carry up to 6000 A. The helium-vapor flow rate and tube dimensions are selected so that nearly all Joule heating and conduction inflow in the lead is transferred to the helium vapor. Heat inflow is intercepted by helium-vapor outflow through a

section of the leads where a temperature transition from 5 K to 300 K takes place.

We have designed the leads for high reliability because if one should fail, the magnet could be irreparably damaged. Thus, they are rugged, even though we could have reduced heat conduction by using lighter materials. The leads are assembled with a high-temperature braze, which gives good joint strength. This will permit them to operate for more than 10 min after an accidental loss of helium vapor flow before a magnet dump must be initiated. Lead temperatures are monitored by our control systems, so that in the event of overheating the system will automatically initiate a "magnet dump," a controlled draining of the magnet's stored energy through an external electrical resistor.

Protecting against radiant heat. LN-cooled panels, attached by special brackets to the magnet surfaces, completely cover the superconducting magnet and shield it from thermal radiation. The panels are made of stainless steel with a high electrical resistivity, so that in the event of a fast dump,

Fig. 3 Vapor-cooled current lead for the MFTF magnet. Helium vapor flows through the 60 copper tubes, entering the bottom end at 5 K and leaving the top end at 30 K while the lead is carrying 6000 A. The helium flow intercepts heat conduction in the lead from the warm end and is heated also by Joule heating.

the currents induced in them will be small. Even though the total magnet surface area is greater than 320 m², the total radiation heat transfer will initially be less than 50 W. We have allowed for 160 W of heating in our design because the electropolished surfaces of the panels may degrade during their lifetime as a result of corrosion or contamination.

More than 1000 brackets will be used to support the LN panels, and space limitations require that most of them be no more than 3 cm high. The brackets are made of a high-density fiberglass-epoxy composite, which satisfies our requirements for heat-transfer characteristics and mechanical strength (Fig. 4). Each bracket will conduct less than 0.1 W from the LN panels to the magnet. Thus, the total heat load from the brackets is under 90 W. Each bracket is capable of supporting a compressive load of 4500 N.

Thermal radiation heating of the magnet could be further reduced by placing a shield (e.g., aluminum foil) between the LN-cooled panels and the magnet surface. However, we do not intend to do this because such shields would severely inhibit heat transfer when we wish to warm the magnet surface by flowing warm nitrogen in the panels.

(Gases condense onto the cryogenically cooled surface of the magnet, and it must be periodically "cleansed" by warming to at least 15 K.) Also, it would be very difficult to prevent radiation shields from bridging the gap between the panels and the magnet and thus creating thermal shorts.

Some parts of the MFTF-B magnets will be protected from plasma and neutral-beam heating by water-cooled panels, or warm liners placed over the LN panels.

Quench protection

If the cooling system fails, allowing the temperature to rise and the magnet to begin to quench (i.e., to lose its superconducting capability),

the 440 MJ of stored electrical energy (equivalent to approximately 95 kg of high explosive) must be dumped or the magnet could be severely damaged. When a transition to normal conduction occurs, there is Joule heating in the magnet conductor, and its temperature increases. Unless the current is turned off quickly, the conductor will overheat.

The temperature rise is enhanced by the fact that at cryogenic temperatures the specific heat of copper is very low. Thus, small amounts of heat will greatly increase its temperature. Furthermore, heating rapidly increases the resistivity of copper. Consequently, the conductor temperature

Fig. 4 Bracket for supporting liquid-nitrogen-cooled thermal shields on the magnet. This LLNL-designed bracket will conduct less than 0.1 W from the shield to the magnet and can support more than a 4500-N compressive load or a 4300-N transverse load.

increases almost exponentially with time if current is not decreased, but if it decreases too rapidly, unacceptably high voltages will develop in the magnet. Hence, one of our design problems was to select a dump resistor and dump delay time that would produce an acceptable conductor temperature and voltage.

We selected a maximum permissible conductor temperature of 200 K and a maximum voltage of 1000 V. To ensure that these parameters were not exceeded, we placed a 0.17- Ω resistor across each coil, and stipulated that no more than a 10-s delay would be permitted before initiation of a fast dump. A quench-detection system, receiving voltage signals from 14 locations in each coil, commands a control system that shunts the current into the dump resistors after a normal zone (i.e., a non-superconducting zone) has been allowed to propagate in the magnet for 10 s. If the magnet recovers to a superconducting state during the 10-s delay period, a fast dump is aborted.

In the event of a quench, the control system also closes the liquid helium supply and return valves and opens the vent line valves to a recovery system (Fig. 1). Helium vapor generated in the magnet is collected in a large gas bag for reuse.

Component testing

Tests of component parts and extensive computer analyses show that the magnet will perform well when it is assembled. To ensure that thermal stresses will be held to

a minimum during cool-down and warm-up, we have used computer codes to evaluate this aspect of the design. Critical parts, such as the magnet supports (Fig. 1), will undergo laboratory testing at our Nevada Test Site before being installed.

We have tested and analyzed the magnet case to ensure that the 89 000 000-N force tending to spread it open during operation will be effectively resisted. Excessive spreading could damage the superconductor or the basic structure. Since conventional stainless steel is brittle at low temperatures, we had to make the case out of a special stainless steel (304 LN), and to ensure that this material will not break, we have tested it extensively. We have also analyzed the design of the case with computer codes and have checked the actual case for hidden flaws using a new LLNL-developed ultrasonic inspection technique. As a result of all of these efforts, we are confident that the magnet will perform well in experiments this year.

Summary

In our design of the MFTF magnet, we have taken into account all the principal aspects of thermal control. Our design ensures good circulation of liquid helium throughout the magnet coils, adequate insulation from external heat sources, and protection

in the event of a quench. Successful operation this year will represent a major advance in the engineering technology of large superconducting magnets. The design and test results are expected to provide information that we need in order to design the larger 22-coil system for MFTF B, which is to be operational in 1985.

Key words: magnetic fusion energy; MFTF mirror machines; design; superconducting magnets; thermonuclear reactors

Notes and references

1. The Mirror Fusion Test Facility is described in the October 1977 *Energy and Technology Review* (UCRL 52000-77-10), p. 1. The scope of the MFTF project was changed in 1980 as plans were made to convert it into a very large tandem mirror experiment (MFTF-B). Thus, MFTF will be used solely for engineering technology demonstration experiments this year, and not for fusion experiments.
2. For an expanded discussion of MFTF-B, see the July 1980 *Energy and Technology Review* (UCRL 52000-80-7), p. 1.
3. J. H. Van Sant and R. M. Russ, "Thermal Control for the MFTF Magnet," in *Advances in Cryogenic Engineering*, Vol. 25, K. D. Timmerhaus and H. A. Snyder (eds.), Plenum Press, New York, 1980, pp. 808-810.
4. D. N. Gorash, V. P. Zbasnik, R. L. Leber, D. G. Hirzel, J. E. Johnson, and A. R. Rosdahl, "MFTF Test Coil Construction and Performance," *IEEE Trans. on Magnetics*, Mag-15, No. 2, 530-544 (1979).

A low-energy x-ray spectrometer for pulsed- source diagnostics

For further information contact
Richard Crabb (415 422 1281)

As electron temperatures in magnetic-confinement fusion devices increase, a greater fraction of the emitted radiation takes the form of low-energy x rays. Accurate measurements in this region are thus becoming increasingly important in determining energy loss and in providing diagnostic data. However, the presence of intense background radiation has often frustrated attempts to carry out such measurements. A new x-ray spectrometer developed at LLNL now makes it possible to obtain medium spectral and temporal resolution in measurements of soft x rays, even against an intense and mixed particle and radiation background. We believe that the design of this spectrometer will lend itself to numerous other applications, permitting the analysis of previously undiagnosed sources of soft x rays.

Magnetic-confinement fusion devices typically generate a broad spectrum of electromagnetic and particle radiation of varying intensities. As the electron temperatures in such devices continue to increase, a greater proportion of the radiation is emitted in the x-ray region, much of it below 1 keV. It is thus important to be able to identify this low-energy radiation, to determine its role in energy loss, and to make accurate diagnostic measurements.

Until recently, however, efforts at LLNL's Tandem Mirror Experiment to obtain appropriate spectral and temporal resolution of x rays in this region were frustrated by the presence of an accompanying background of intense ultraviolet, charged particle, neutron, and gamma radiation. The problem was therefore to isolate and measure the low-energy x rays in the presence of this background.

A design, development, and testing effort led to a solution last year: the double-reflection x-ray spectrometer (DREXS), a unique and highly versatile device that represents a significant advance in the measurement of pulsed radiation sources.

Our conceptual approach to the problem was based on the fact that the index of refraction for x rays in certain mirror materials is less than unity, and hence grazing-incidence x rays of a particular energy are almost totally reflected for angles less than the critical angle.¹ At the critical angle, the reflectivity drops to almost zero (quite abruptly, if the absorption by the reflecting medium is small). Conversely, at a particular mirror angle, there will be a corresponding abrupt dropoff in reflectivity at some critical energy. Thus certain types of mirrors can resolve x-ray spectra by serving as low-pass filters. Use of this so called mirror technique to filter continuous x-ray spectra is not new. Our innovation was in the observation that refraction as well as reflection could be used to isolate and resolve x-ray spectra because reflection and refraction cutoffs are equally sharp and occur at the same mirror angle.

We designed DREXS to provide a unique combination of useful operational features. No prior knowledge of the spectrum to be measured is necessary. DREXS decisively identifies x rays and measures them in the spectral range from approximately 0.5 to 8.0 keV. Other features are high efficiency (about 80%), an x-ray response determined by mirror angles, a highly directional measurement capability (convenient for spatial resolution studies), and an ability to discriminate against, isolate, and measure the various radiation backgrounds present. Finally, DREXS is designed for maximum versatility, compactness, and portability.

Design and operation

Because DREXS is intended for use at many different facilities we designed it to provide maximum versatility. The unit is packaged to be as small and as light as possible for easy handling and shipping, yet sturdy enough to maintain extremely precise alignment of internal components. The lightweight housing has an external strong arm to stabilize alignment between the front end and the rail assembly. The complete instrument package measures approximately 25 cm $\times$ 46 cm $\times$ 1.5 m and weighs 68 kg.

DREXS has three functional parts (Fig. 1). The front end conditions the incoming beam; the rail assembly measures the conditioned x-ray beam; and the hous-

ing ties the front end and rail assembly together and provides a vacuum environment.

Figure 2 is a schematic of the DREXS configuration. Incident radiation from a pulsed source is accepted by a collimator-slit system consisting of a neutron and gamma ray collimator between two defining slits, which restrict x rays to the desired plane. The beam then passes through a selected wheel mounted filter and a vacuum light barrier. The eight position rotary wheel enables the operator to select an appropriate thin filter to reduce any contribution from the residual x ray tail below the spectral region of interest; the vacuum light barrier stops light and radio frequency noise. The conditioned

beam then impinges on the surface of a highly polished vitreous-carbon mirror at a grazing-incidence angle. Incident x rays below a particular energy corresponding to the critical mirror angle are specularly reflected out of the beam; the reflectivity for x rays above this energy drops abruptly to nearly zero.

The x rays reflected by the carbon mirror are then re-reflected at the flat, polished surface of a plastic scintillator. Adjusting the scintillator mirror at an angle slightly greater than that of the carbon mirror refracts x rays within a narrow band into the scintillator. A photomultiplier tube converts light pro-

duced in the scintillator into an electrical current that is proportional to the time-dependent intensity of the x rays. The bandwidth to be measured is controlled by appropriate angular adjustments of the carbon mirror (upper energy cut) and the scintillator mirror (lower energy cut). The

relationship between critical cutoff energy and mirror angle is shown for both mirrors in Fig. 3. The resolution limit—about 0.25 keV—is determined by the sharpness of the mirror reflectivity cutoff.

High-flux permanent magnets are mounted immediately behind the carbon mirror to prevent charged particles, particularly electrons, from reaching the scintillator detector.

For ease of adjustment, each of the two mirrors is mounted on its own independent rotation stage; each rotation stage can be set to within $\pm 0.01^\circ$ of a desired angle. In addition, the scintillator mirror-photomultiplier tube is affixed to a translation stage that enables it to be adjusted to a precise location for intercepting x rays reflected from the vitreous carbon mirror. The translation stage also moves the detector out of the x-ray beam, enabling the operator to determine the ambient radiation level. At present, the two rotation stages, the translation stage, and the filter wheel are remotely controlled and manually operated; eventually, we plan to control the system automatically with microprocessors.

The two four-position x-ray slits in the front end are spaced 61 cm apart to provide adequate x-ray and neutron-gamma collimation. The neutron-gamma opening in the collimator is slightly larger than the largest x-ray slit. The carbon mirror and the detector (scintillator mirror) are also separated by a 61-cm space to minimize the effects of scattering from the carbon mirror. This space also enables the scintillator mirror to be positioned outside the direct beam of gamma

and neutron radiation, even with the carbon mirror set at highly grazing angles.

Applications

We used DREXS to measure the x-ray spectrum at the LLNL Tandem Mirror Experiment facility in July 1980.² On the basis of its test performance, we believe that it has numerous uses as an exploratory tool at many facilities where soft x rays have never been measured. DREXS's accuracy and portability promise significant contributions to investigations of low-energy pulsed x-ray sources. A facility using DREXS can obtain data to provide a basis for the design of a multi-channel spectrometer specifically tailored to the facility's special needs.

An important potential application is to the Nuclear Test Program, where soft x-ray emissions may be measured at the several pulsed-source facilities routinely used for calibrating Nevada Test Site field detectors.

Key words: double reflection x-ray spectrometer, DREXS, low energy, x-ray spectrometer, x-rays, x-ray measurements, x-ray spectrum, x-ray sources, magnetic fusion

Notes and references

1. G. A. Burgin, J. P. Stoening, R. W. Hill, and L. V. Singman, "A Low Energy, High Fluence Reflection Refraction X-Ray Spectrometer," *J. Appl. Phys.* **49**, 513 (1978).
2. J. P. Stoening, H. D. Snyder, G. A. Burgin, A. Toor, C. Anderson, R. Crabb, M. E. McGee, and P. Poulsen, "Spectrometer X-Ray Measurements at TMX," *Bull. APS* **25** (8), 881 (1980).

For further information contact
Dino Carlo 415 422 8872

Many LLNL experimental programs need ultra-small components (diffraction gratings, pinhole arrays, micro-Fresnel zone plates, etc.) to achieve their goals. Some of these components are so small that they cannot be machined by conventional methods. For this reason, we are exploring the use of integrated-circuit fabrication techniques—photolithography, etching, and microelectroplating—as the basis for a new “micromachining” technology. Using such techniques, we have been able to make components with dimensions on the order of 1 to 2 μm .

In physics experiments at LLNL, there is often a need for extremely small parts (diffraction gratings, pinhole arrays, membranes, micro-Fresnel zone plates, etc.) to meet particular resolution, sensitivity, or performance requirements. It is very difficult to fabricate such parts using conventional lathes, drill presses, and milling machines because of constraints on the size and strength of cutting tools and on our ability to hold and precisely

position small parts. Furthermore, conventional machining is expensive and time-consuming.

Advances over the last 10 years in the mass-production of integrated circuits hold out the promise of a new micromachining technology capable of fabricating parts with dimensions of a few micrometres and smaller. Shown in Fig 1 is one such part, a 12- μm -thick Fresnel zone plate used in examining laser-induced plasmas.

Also shown (for comparison) is a human hair with a diameter of roughly $100\text{ }\mu\text{m}$.

The techniques involved in micromachining include:

- Photolithography, a process by which selected areas of a surface are covered with an organic film that is not attacked by etchants.

- Orientation- and concentration-dependent etching, the exploitation of differential etch rates to produce a desired pattern.

- Microelectroplating, which involves depositing material in a mold via an electrochemical process.

- Reactive-ion etching, i.e., etching conducted in the glow dis-

charge of a gas.

In what follows, we will discuss these techniques and show examples of our work.

Photolithography

Very small images—etching patterns with dimensions of $1\text{ }\mu\text{m}$ or less—can be transferred to a surface via photolithography. In this process, the desired substrate is coated with an organic substance, called a photoresist film, that is sensitive to ultraviolet light but is not attacked by etchants. A special printing system with high-resolution optics is used to expose the photoresist film; the higher the resolution of the optics, the smaller

the image that can be formed. After the film is exposed, it is processed in a developer solution. Depending on the exact photoresist used, exposure to ultraviolet light will make it either soluble or insoluble in the developer solution. Thus, the same printing template can be used to obtain both positive and negative images.

When the substrate is a silicon wafer, it is quite common to grow a quartz film thermally on the wafer and then to pattern an image in this film using photoresist. This allows the quartz film to be used as the mask for the etching of the silicon. Quartz withstands the silicon etchants far better than photoresist.

Fig. 2 The orientation-dependent etchant potassium hydroxide etches the (110) and (100) crystal planes many times faster than the (111) planes. Since the (110) planes of single-crystal silicon are perpendicular to the (111) planes, we can etch deep, straight-walled grooves (a); and since the (111) planes form a 54° angle with the (100) planes, we can etch steep-sided V-shaped grooves (b). Ethylenediamine pyrocatechol, a concentration-dependent etchant, can be used to form a membrane on the (100) crystalline surface of single-crystal silicon; etching stops abruptly at the boron-doped region, leaving a thin membrane of silicon supported by thicker sections of the silicon wafer (c). To micromachine single-crystal silicon into mandrels for vacuum-evaporated metal films, an isotropic etchant (one that etches silicon at a constant rate) can be used (d).

Orientation-dependent etching

Once a pattern is formed on a quartz-coated single-crystal silicon wafer and the quartz is etched with hydrofluoric acid, we can etch the underlying silicon material in a number of different ways (Fig. 2). One etchant used is potassium hydroxide, which etches the (110) crystal plane several hundred times faster than the (111) plane. Because the (110) crystal planes of single-crystal silicon are perpendicular to the (111) planes, we can use potassium hydroxide to etch deep grooves with straight walls into the substrate (Fig. 2a).

If we need to produce V-grooves (Fig. 2b), we can pattern a quartz mask on the (100) silicon wafer

plane and again use potassium hydroxide, which etches the (100) crystal plane much faster than the (111) plane. Since the (111) planes form a 54° angle with the (100) planes, grooves with sloping sides (54° from the horizontal) can be etched. The etching will continue to the point where the two sloping sidewalls meet. We use this V-groove technique to make diffraction gratings for surface diffusion studies and microchannels that conduct fluid along a surface in miniature ink-jet printers.

Concentration-dependent etching

To fabricate thin membranes in single-crystal silicon (Fig. 2c), we can pattern the quartz film on a silicon wafer and use a concentration-dependent etchant such as ethylenediamine pyrocatecol. This etchant will etch single-crystal silicon unless the silicon has been impregnated by a heavy concentration of boron atoms. We allow boron to diffuse into one surface of the single-crystal silicon wafer to a depth corresponding to the desired membrane thickness, and then we etch

the silicon (with ethylenediamine pyrocatecol) from the other side. The etching stops abruptly at the boron-doped region. One notable advantage of this particular process is that, because of the way the boron atoms fit into the silicon crystal lattice, the resulting membrane is taut and does not sag. Thus, it can be positioned very accurately with respect to another part. Portions of the silicon wafer that are protected from the etchant by the quartz mask provide thick support for the membrane. Shown

in Fig. 3 is a thin membrane fabricated via concentration-dependent etching. It is used as an x-ray transmission window.

Single-crystal silicon can also be micromachined into mandrels for vacuum-evaporated metal films (Fig. 2d). A quartz mask is patterned on the silicon wafer (to protect those places that are not to be etched), and an isotropic etchant (one that etches the silicon at a constant rate regardless of crystal orientation) is used. This produces an undercut at the edges

Fig. 3 Scanning electron photomicrograph of a 25- μ m-thick membrane in the (100) crystalline surface of silicon, which was fabricated using a concentration-dependent etchant. A 260- μ m-diameter pinhole was etched into the membrane using an orientation-dependent etchant.

of the quartz mask. After the silicon crystal is etched, a metal film can be evaporated over the entire surface to a thickness slightly less than the depth of the etch. When the entire film is peeled off, the flat metal parts on top of the quartz mask separate easily from the metal film on the bare silicon. Thus, many flat metal parts (those on the quartz mask) can be made simultaneously.

The silicon mandrel shown in Fig. 4 was fabricated by means of isotropic etching. It in turn was

used to manufacture hundreds of gold disks (up to $25\text{ }\mu\text{m}$ thick) used in laser targets.¹

Microelectroplating

The micromachining techniques described above are used to produce shapes consistent with the etching characteristics of single-crystal silicon. To make parts with more arbitrary shapes, we use microelectroplating. However, this technique requires a suitable mold around which to electroplate. One way of creating such an electro-

plating mold is to expose an image of the desired shape in a layer of photoresist film of the desired thickness, develop it, and use the resulting image as the mold.

The $1\text{-}\mu\text{m}$ -diam pinhole in the gold foil shown in Fig. 5a was fabricated by electroplating gold through a mold of photoresist film. The gold membrane surrounding the pinhole is $2\text{ }\mu\text{m}$ thick and is itself supported by a $10\text{-}\mu\text{m}$ -thick gold foil. This pinhole is but one of an array of 400 identical pinholes, spaced $50\text{ }\mu\text{m}$ apart, and used in calibrating an x-ray microscope.

Figure 5b shows a scanning electron photomicrograph of a micro-Fresnel zone plate that was fabricated using photoresist as an electroplating mold. These zone plates are used to examine laser-produced plasmas.²

The use of photoresist as an electroplating mold is practical for molds that are about as thick as they are wide. However, the process does not work well for molds that are much thicker than they are wide. Long exposure times are required for thicker layers of photoresist, and the exposing light gets diffracted within the film, causing the image to blur.³

Fig. 4 Scanning electron photomicrograph of a silicon mandrel fabricated using an isotropic etchant. The inner and outer diameters are, respectively, 200 and $500\text{ }\mu\text{m}$; the annular ring is $12\text{ }\mu\text{m}$ above the background surface. This mandrel was used for manufacturing hundreds of gold disks (about $25\text{ }\mu\text{m}$ thick) simultaneously.

Reactive-ion etching

Molds that are much thicker than they are wide are best fabricated by means of a combination of photolithography and reactive-ion etching (Fig. 6).⁴ In this technique, a glass substrate coated with a 100- to 500-nm-thick gold film is covered with a layer of polymer material. The polymer is then covered with an evaporated aluminum film, and the aluminum mask is patterned using photoresist film and an aluminum etch. The sample is then placed in a vacuum system, and a small amount of oxygen is admitted. A radio-frequency voltage is used to generate the reactive oxygen ions, which etch the polymer. The polymer is etched approximately 500 times faster

than the aluminum mask material. Because reactive-ion etching is an anisotropic procedure, it does not undercut the aluminum mask, and straight sidewalls are produced. After the aluminum is removed, the remaining polymer pattern is used as an electroplating mold. Figure 7 shows a scanning electron photomicrograph of a pattern that was reactively ion-etched into an 80- μ m-thick polymer film.

Summary

In many instances, integrated-circuit fabrication techniques can be used to micromachine extremely small parts that are almost impossible to manufacture using conventional machining techniques. We have successfully micromachined

ultra-small diagnostic devices, components for laser targets, and instrument calibration parts. As new methods are developed to micromachine three-dimensional parts (as opposed to the basically two-dimensional features found on integrated circuits), more and more applications for this procedure will be found. We are working on new methods and at the same time applying those already discovered to meet the needs of LLNL experimental programs.

Key words: chemical machining, electrical discharge machining, etching, microelectroplating, micromachining, photolithography

Notes and references

1. W. E. Tindall, *Fabrication of Laser Components by Semiconductor Technology*, Lawrence Livermore National Laboratory, UCRL 82 444 (1979).
2. Zone plate coded imaging was discussed in the January 1978 *Energy and Technology Review*, Lawrence Livermore National Laboratory, UCRL 52000 78 1, p. 1.
3. D. R. Carlo and N. M. Ceglio, "Ultrathick Photoresist Processing," in *Proc. SPIE Semiconductor Microfabrication*, U. March 17-18, 1980, San Jose, California, Vol. 221, p. 64.
4. N. M. Ceglio and G. F. Stone, "Microstructures for High Energy X-ray and Particle Imaging Applications," to be published.

Fig. 7

An 80- μ m-thick polymer mold for a zone plate. The mold was fabricated by reactive-ion etching.

Electronics Engineer's Design Station

For further information contact
Robert M. Shectman (415 422-8187).

We have developed a minicomputer-based interactive graphics system that automates the process of designing and producing new electronic circuits. Our system, known as the electronics engineer's design station (EEDS), allows the engineer to create a schematic diagram directly on the machine and then to modify and improve it with a minimum of duplicated effort. The EEDS generates documentation that will enable the shop to produce a prototype without additional input. Thus, it eliminates many routine, mechanical tasks and minimizes the introduction of human error as design ideas are translated into drawings and working prototypes.

The process of designing and producing an electronic circuit traditionally begins with a designer's rough sketch. The sketch goes to the drafting department, and the finished drawing then goes to the shops, where a

prototype circuit is made and tested. If modifications are required, another round of sketching, drawing, and testing follows. Finally, an acceptable design is converted into one or more printed circuit boards.

Fig. 1 The electronics engineer's design station (EEDS) showing the console and the vector display monitor. Input is primarily by means of the light pen, with which the user selects items from the display for inclusion in the schematic drawing of an electronic circuit. The menu at the bottom of the display lists all the commands the program can execute at the moment, any one of which can also be selected by means of the light pen. This equipment helps a designer to translate his ideas into working schematic drawings and circuit layouts. It also generates the inputs for other computer programs that produce actual printed circuit boards.

Over the years, it has become easier to design and produce electronic circuits because computer-aided drafting systems, circuit simulators, and automated printed-circuit layout programs have made the various operations more efficient. However, when an engineer sits down to convert a design idea into a circuit drawing, he still typically has nothing more sophisticated to work with than pencil, paper, and eraser. Furthermore, the automated systems in the drafting and production departments are not linked. Thus, each department has to enter new designs manually into its system. This takes time and increases the probability of error.

We have developed an electronics engineer's design station (EEDS) that unifies the entire process and eliminates duplication of effort.¹ Our system, shown in Fig. 1, directly links the designer and the production facilities, speeding the transfer of information and eliminating transmittal errors. It allows the engineer to create a schematic directly on the machine (see Fig. 2) and then to modify and improve it easily. The system then generates the documentation that will enable the shop to produce a prototype without additional input.

System design

An engineer is not likely to use EEDS for more than a month at a time, and then several months may pass before he returns to it. Thus, the major design criterion is that each operation required of the user be simple to learn and perform. We have designed the system so that it takes less than four hours initially to learn, and no more than a few

minutes to relearn. Users of comparable systems developed elsewhere (for drafters) often must devote several weeks to training

and several months to intensive practice before they can claim real proficiency. The simplicity of operation that characterizes the EEDS

has greatly increased the complexity of the software upon which it is based, but the initial expenditure in software development time will ultimately produce great benefits in making the system accessible to more people.

Figure 2 shows a representative display on the EEDS system. At the top is a repertoire of components; in the center is an incomplete schematic drawing; and below is a menu of legal commands. These commands enable the user to add components to the drawing from the repertoire, call up a different repertoire, label any component or connection, delete any portion of the drawing, move any section of the drawing to a new location, rearrange the interconnections, and enlarge or reduce the area of the drawing covered by the display. Because it is far easier to point than to type, the various commands and components are selected by means of a light pen.

At each step in the process, the menu is updated to show only those operations that can be performed at that moment. The menu shown at the bottom of the screen in Fig. 2 allows access to four main areas: component selection, schematic manipulation, connections between components, and display parameters such as magnification and window position.

After constructing the schematic drawing the designer can make a layout drawing (Fig. 3), specifying the placement of the physical components.

Outputs

Upon completion of these two constructive phases, the computer

has in its memory a complete representation of the circuit and the board layout. The computer

can then manipulate these data to produce a great variety of outputs in two major categories: design documentation and input to other computer-aided design systems. The great value of the EEDS lies in the wide variety of these outputs and the ease with which they can be produced.

This computer-generated documentation includes (in addition to schematics and layout drawings) tables listing title blocks, component locations, connection locations, parts, and a "from-to" list detailing the component interconnections. This additional documentation has three major advantages over previous documentation:

- It is inexpensive to generate, since it involves almost no human effort.
- It is as accurate as the engineer's input.
- It is easily updated if design changes are necessary.

The EEDS also gives our designers improved access to a broad range of existing and developing computer-aided design facilities. These include SCEPTRE or NET-2 (two logic simulators), SLIPINS (an in-house code that programs automated wire-wrap equipment),² REDAC (a commercial system that automates the production of printed circuit-board artwork), and AUTOTROL (a commercial automated drafting system). Interfaces to other commercial or in-house services will be easy to produce as needed. This translation of data bases, which provides the links to other services,

offers the same advantages as the computer-generated documentation: economy of production, accuracy, and ease of updating.

Status

We have assembled a prototype EEDS, using a PDP-11/34 minicomputer and commercially available components. The engineers and technicians who use it find it to be a powerful design tool, providing high-quality working drawings early in the design phase and several output listings that are too lengthy and expensive to produce by conventional methods. In addition, the EEDS is invaluable in reducing the number of errors that can creep in at various stages. Because of this, weeks are subtracted from the time required to produce a prototype or a finished product.

We are now upgrading the hardware and software capabilities of the current system and are investigating the possibility of replicating the EEDS on PDP-11 systems already in place. We are also looking into the possibility of substituting a newer, less expensive, raster monitor for the present vector device.

Future development may make it possible to move the EEDS software to a VAX-11/780 minicomputer. This move should make the software more portable and provide significant new capabilities and improved performance.

Key words: automated documentation, computer-aided design, computer-aided graphics, interactive graphics

Notes and references

1. D. E. Benning, "The Electronics Engineer's Design Station," *Proc. 17th Design Automation Conf.*, Minneapolis, Minn. (1980).
2. W. Magnuson, Jr., "Octopus Guide for Running the SLIPINS and SLIWIREFLIST Programs," Lawrence Livermore National Laboratory, internal report LER-7-410-8402 (1974).

For further information contact
Charles Witherell (415 422 8341)

Welding can distort or degrade the properties of small metal parts and adjacent plastic or glass fittings. Such effects have limited its use in joining heat-sensitive microelectronic components and other tiny instrument parts. To overcome this problem, we have developed a laser-brazing technique that focuses a carefully controlled amount of heat on the joint area itself, leaving the surrounding metal cool and solid. We have been successful in joining metal sections with diameters as small as 0.025 mm. The technique has potential applications in biomedical engineering, instrument manufacturing, and electronics fabrication.

When heat is applied during welding and brazing, it can distort or weaken the metal and destroy nonmetallic (e.g., plastic) components adjacent to the joint. This is a critical problem whenever very thin metal parts must be securely joined, as in precision instruments and microelectronic circuits. (See the box on p. 36) Laser brazing, a new technique developed at LLNL, makes it possible to create strong, reliable joints between hair-thin metal parts without weakening or distorting the parts.

To explore the feasibility of the concept, we tested a variety of metal and alloy sheets with thicknesses ranging from 0.025 mm to 0.318 mm and several common, commercially available brazing fillers in the form of powders and strips. (The fillers were mostly alloys of silver and copper; the one used to braze aluminum was an alloy of aluminum and silicon.) The materials selected represent those

most commonly encountered in the fabrication of small metal parts. Four metalworking lasers representing different wavelengths and operational modes were available, and all were used at one time or another.

In a series of experiments over several months, we found that it was possible to join thin pieces of metal using laser energy fired in short pulses (Fig. 1). The most reproducible results and lowest heat input were obtained by firing the laser beam directly onto a measured volume of brazing alloy preplaced at the joint. (The beam diameter was as small as 0.3 mm.) We found that each *properly controlled* laser pulse melts a circular spot of brazing alloy and heats the metals to the brazing temperature—all within about 10 ms. The molten spot of brazing alloy, with a diameter equal to that of the beam, wets to the surfaces of the pieces being joined, and when the beam is switched off, the brazing alloy solidifies, forming a metal bridge across the joint.

The laser is aimed with the aid of a microscope, and the metal sections are mounted on a computer-driven table. As the table advances

(c)

Fig. A laser-brazed joint between a capillary tube and a fitting where the tube enters the fitting wall. Photographs were made with a scanning electron microscope. The outside diameter of the tube is 0.18 mm. Laser brazing enables us to join miniature parts such as these without any heat damage. (a) Surface appearance of the joint. (b) Longitudinal section through the joint. (c) Diagram of the laser-brazing process. We use a microscope to aim the laser beam and fire it directly onto a measured volume of powdered brazing alloy

preplaced at the joint. The laser pulse lasts about 10 ms and melts a circular spot of brazing alloy, which then wets to the hot surfaces. When the beam is switched off, the brazing alloy solidifies, forming a metal bridge across the joint at that point. A continuous bridge along the entire joint is made by rotating the assembly slightly between pulses. Although the laser beam delivers $100\,000\text{ W cm}^{-2}$ to the target, its narrow diameter and short pulse time confine the heat to the area of the joint, leaving the surrounding metal cool and undamaged.

Welding and brazing

Welding and brazing are two different ways of joining metal. In welding, the metals are melted together to form a bond, and sometimes additional metal, called filler, is added to strengthen the metal bridge. In brazing, only the filler is melted; the metals themselves are heated just to the flow temperature of the filler. The filler distributes itself along the joint by capillary action (much as butter wets the surface of a frying pan).

Generally, the objective in welding is to provide a metallic bridge that has the same mechanical, metallurgical and chemical properties as the metals being welded. However, this goal is seldom achieved. Heating, melting, solidification, and cooling can distort and weaken the metal, and furthermore, adjacent materials and components can be damaged in the process. To minimize these side-effects, the specialist frequently opts for brazing. The relatively low temperatures involved and the small volume of braze deposit result in less distortion.

Brazing has some drawbacks. It often requires heating the entire part to the brazing temperature (above 800°F) and keeping it there for several minutes. This can produce distortion and undesirable interactions between the filler and the metals being joined, particularly if the metals are thin. Thus, conventional brazing of thin metals and dimensionally critical parts and assemblies is sometimes impossible.

At LLNL we have pioneered electron-beam welding (EBW), which permits us to join materials with minimal side-effects by relying upon a concentrated heat source (and thus restricting the heat to the joint). However, in spite of the advantages offered by EBW, it is still unsuitable for some applications.

Metalworking lasers, developed during the past decade for welding, have provided an even more precise and intense heat source. However, even laser welding is too crude a method for joining sections less than 0.025 mm thick. Our new laser-brazing technique makes it possible to join these ultra-thin parts and components too small to be welded even with the most sophisticated laser tools and techniques.

the joint between laser pulses, a continuous joint, consisting of a series of overlapping brazed spots (Fig. 2), is formed. Although the laser beam is intense, with energy levels of over 1000 J/cm² and power densities of 100 000 W/cm², the narrow beam and short time pulse effectively confine the heat to the area of the joint. Thus, the surrounding part is unaffected.

Our tests have shown that almost all metals can be joined via laser brazing in a wide range of dissimilar combinations. One has only to provide the right set of laser conditions, the appropriate filler, and a protective atmosphere around the joint during the operation. We used an argon atmosphere in our experiments.

Laser-produced joints cool at a very high rate (over 1 000 000°C/s). While this can be detrimental to some hardenable alloys, it actually increases the hardness of certain braze deposits to 1.2 to 1.9 times that of deposits made with an oxygen-fuel gas torch. In alloys not ordinarily regarded as hardenable, the increase in hardness occurs when the number of quenched-in lattice defects rises, when super-saturated solid solutions form, or when trace impurities cause dispersion-strengthening. The increase in hardness can significantly improve joint strength over that normally achieved in conventional torch or furnace brazing.

FIGURE 1 A laser-brazed joint between a 0.127-mm-thick stainless-steel sheet and 0.254-mm-thick titanium, with copper filler metal. Laser brazing causes no heat damage to metal surrounding the joint, and this makes it possible to create miniature (1-mm-wide) joints like this one. The metal assembly is advanced a short distance between pulses (under computer control), and this produces the rippling shown in the figure. Fast cooling (at rates of 1 000 000°C/s) produces an extremely strong joint in certain metals.

It is unlikely that laser brazing will replace conventional methods when these are adequate.

However, it could become important in the fabrication of joints in miniature parts with small dimensional tolerances, and in applications that require highly reliable joints. Laser-brazed joints in most metal-filler combinations are corrosion-resistant and extremely reliable. Thus, they have potential applications in the fabrication of biomedical implants, which are

continuously exposed to the body's fluids, and of sensors that monitor corrosive environments. Laser brazing also has promise as a cost-effective competitor in the commercial production brazing of large numbers of identical small parts where heat input must be minimized.

Key words: brazing, laser brazing, laser welding, welding

Past titles

Listed below are articles published over the last several months in the Energy and Technology Review. They are grouped generally in subject categories corresponding to the areas of responsibility of Assistant Secretaries in the U.S. Department of Energy. However, a few additional categories have been created for research funded by other agencies.

DEFENSE PROGRAMS

Inertial fusion

The Nova laser fusion facility (December 1980)

Military application

Electrical aspects of ramjet (January 1981)

Light propagation in optical fibers (March 1981)

Shock wave studies modeling the giant planets (April 1981)

ENERGY RESEARCH

Computer modeling of magnetic mirror experiments (December 1980)

MFTF supervisory control system (December 1980)

Channeling radiation (January 1981)

Computer simulations of ion surface interactions (February 1981)

Improving the performance of high speed computer networks (February 1981)

Making better scientific use of drill holes (February 1981)

Microearthquakes in the Livermore Valley (February 1981)

Physically reasonable interpolation methods (February 1981)

Underground imaging pictures of the world below (February 1981)

Flame quenching in internal combustion engines (April 1981)

Modeling of solid state materials for solar cells (April 1981)

LABORATORY TRENDS

Using new technology to increase engineering productivity (January 1981)

NUCLEAR ENERGY

The chemistry of uranium vapor (March 1981)

WORK FOR OTHERS

Defense Advanced Research Projects Agency

Brief Advanced Test Accelerator dedicated (January 1981)

U.S. Army Research Office

Mechanisms influencing gun barrel erosion (March 1981)