11-93 JSC

PNL-8450
UC-359
920

Characteristics of Identifying Linear Dynamic Models from Impulse Response Data Using Prony Analysis

D. J. Trudnowski

December 1992

**Prepared for
the Bonneville Power Administration
under a Related Services Agreement
with the U.S. Department of Energy
Contract DE-AC06-76RLO 1830**

**Pacific Northwest Laboratory
Operated for the U.S. Department of Energy
by Battelle Memorial Institute**

PNL-8450

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor Battelle Memorial Institute, nor any of their employees, makes **any warranty, expressed or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights.** Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof, or Battelle Memorial Institute. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

PACIFIC NORTHWEST LABORATORY
operated by
BATTELLE MEMORIAL INSTITUTE
for the
UNITED STATES DEPARTMENT OF ENERGY
under Contract DE-AC06-76RLO 1830

Printed in the United States of America

Available to DOE and DOE contractors from the
Office of Scientific and Technical Information, P.O. Box 62, Oak Ridge, TN 37831;
prices available from (615) 576-8401. FTS 626-8401.

Available to the public from the National Technical Information Service,
U.S. Department of Commerce, 5285 Port Royal Rd., Springfield, VA 22161.

**Characteristics of
Identifying Linear Dynamic Models
from Impulse Response Data
Using Prony Analysis**

D. J. Trudnowski

December 1992

**Prepared for
the Bonneville Power Administration
under a Related Services Agreement
with the U.S. Department of Energy
Contract DE-AC06-76RLO 1830**

**Pacific Northwest Laboratory
Richland, Washington 99352**

MASTER

Summary

Pacific Northwest Laboratory (PNL) conducted this study for the Bonneville Power Administration (BPA). The purpose of the study was to investigate the characteristics of fitting linear dynamic models to the impulse response of oscillatory dynamic systems using Prony analysis.

Many dynamic systems exhibit oscillatory responses with multiple modes of oscillations. Although the underlying dynamics of such systems are often nonlinear, it is frequently possible and very useful to represent the system operating about some set point with a linear model. Derivation of such linear models can be done using two basic approaches: model the system using theoretical derivations and some linearization method such as a Taylor series expansion; or use a curve-fitting technique to optimally fit a linear model to specified system response data. Prony analysis belongs to the second class of system modeling because it is a method of fitting a linear model to the impulse response of a dynamic system. Its parallel formulation inherently makes it well suited for fitting models to oscillatory system data.

Such oscillatory dynamic effects occur in large synchronous-generator-based power systems in the form of electromechanical oscillations. To study and characterize these oscillatory dynamics, BPA has developed computer codes to analyze system data using Prony analysis. The objective of this study was to develop a highly detailed understanding of the properties of using Prony analysis to fit models to systems with characteristics often encountered in power systems. This understanding was then extended to develop general "rules-of-thumb" for using Prony analysis.

The general characteristics were investigated by performing fits to data from known linear models under controlled conditions. The conditions studied include various mathematical solution techniques; different parent system configurations; and a large variety of underlying noise characteristics. Some of the general guidelines for intelligent use of Prony analysis include the following:

- In sampling the system data, use a sample period at least double the Nyquist rate but not more than 10 times the Nyquist rate.
- In choosing the length of the data record, several factors must be considered: 1) at least one full cycle of the minimum-frequency oscillatory mode should be included (more data is preferred); 2) if data is collected in a noisy environment, an excessively long data record should be avoided (this is somewhat a judgment, but the record should be short enough to keep the signal-to-noise ratio (SNR) above 20 db); 3) if a double-precision root finder is employed in solving the Prony analysis problem, the number of data points should not exceed 250 (a safer limit is 100); and 4) for a quad-precision root finder, the limits are 500 and 200.
- In most cases, one should not expect to accurately identify stable real poles with a magnitude greater than $1/(3T)$, where T is the sample period.
- Use the covariance method in the forward direction to formulate the linear prediction (LP) problem for the Prony analysis solution. Also, if possible, use a quad-precision root finder

to factor the LP polynomial.

- In choosing the order of the LP fit, use $N/3$ to $N/2$ (where N is the number of data points), as long as it does not exceed 50 for a double-precision root finder or 100 for a quad.
- Accurate fits are likely if the SNR is 20 db or greater. If the noise is highly colored, poor fits are likely for poles and residues in the bandwidth of the colored noise.
- If closely-spaced poles are identified, especially with similar imaginary terms, the error bounds for these terms are likely to be large even if the fit is graphically accurate.

Contents

Summary	iii
1.0 Introduction	1.1
2.0 Prony Analysis	2.1
2.1 Derivation	2.1
2.2 Literature Review	2.3
3.0 Prony Analysis Codes	3.1
3.1 SIGPAKZ and IPRONY	3.1
3.2 IPRONYID	3.1
3.3 PRSPAK (Core Prony Subroutine)	3.2
3.4 TRANSIENTS	3.3
3.5 Computer Platforms	3.4
4.0 Example Systems and MATLAB Interfaces	4.1
4.1 Interfacing with MATLAB	4.1
4.2 Test Systems	4.2
4.2.1 Test System 1	4.2
4.2.2 Test System 2	4.4
4.2.3 Test System 3	4.6
4.3 Noise Models	4.8
5.0 Properties of Prony Analysis	5.1
5.1 Alternative Solution Techniques	5.1
5.1.1 The Linear Prediction Method	5.2
5.1.2 Linear Prediction Algorithm	5.2

5.1.3	Forward/Backward Formulation	5.3
5.1.4	Vandermonde System-Solving Algorithms	5.3
5.2	Effects of Linear Prediction Model Order	5.3
5.3	Effects of Sampling Frequency	5.4
5.4	Effects of Record Length	5.8
5.5	Effects of Noise Level and Coloration	5.9
5.6	Effects of Closely-Spaced Poles	5.13
5.7	Effects of Closely-Spaced Pole-Zero Pairs	5.15
6.0	Conclusions and Recommendations	6.1
6.1	Conclusions	6.1
6.2	Recommended Future Work	6.2
6.2.1	Overhaul PSRPAK	6.2
6.2.2	Implement Revision Control System	6.4
6.2.3	Incorporate Transfer Function Identification into SIGPAKZ	6.4
6.2.4	Develop "Local Intelligence" in SIGPAKZ and IPRONYID	6.4
6.2.5	Investigate New Options	6.4
7.0	References	7.1
Appendix A - PRSPAK2 Version 1.1.2.1		A.1
Appendix B - Section 5 SIGPAKZ Input Files		B.1
Appendix C - TRANFUN and ORDER Subroutines		C.1

Figures

4.1	Impulse response of test system 1	4.3
4.2	Frequency response of test system 1	4.3
4.3	Frequency response of test system 1	4.4
4.4	Impulse response of test system 2	4.5
4.5	Frequency response of test system 2	4.5
4.6	Frequency response of test system 2	4.6
4.7	Impulse response of test system 3	4.7
4.8	Frequency response of test system 3	4.7
4.9	Frequency response of test system 3	4.8
4.10	Frequency response of $1/f$ and $1/f^2$ filters	4.9
4.11	Frequency response of coloring filter	4.10
4.12	Frequency response of white and $1/f$ noise	4.10
4.13	Frequency response of white and $1/f^2$ noise	4.11
4.14	Frequency response of colored noise	4.11
5.1	Impulse response of 3rd-order fit to 9th-order system with white noise at 27-db SNR, Example 5.3	5.5
5.2	Frequency response of 3rd-order fit to 9th-order system with white noise at 27-db SNR, Example 5.3	5.5
5.3	Impulse response of 15th-order fit to 9th-order system with white noise at 27-db SNR, Example 5.3	5.6
5.4	Frequency response of 15th-order fit to 9th-order system with white noise at 27-db SNR, Example 5.3	5.6
5.5	Impulse response of 30th-order fit to 9th-order system with white noise at 27-db SNR, Example 5.3	5.7

5.6	Frequency response of 30th-order fit to 9th-order system with white noise at 27-db SNR, Example 5.3	5.7
5.7	Different data record fits impulse response, Example 5.4	5.8
5.8	Different record length fits frequency response, Example 5.4	5.9
5.9	Impulse response of different record length fits, Example 5.5	5.10
5.10	Frequency response of different record length fits, Example 5.5	5.10
5.11	Impulse response of fit to system with 40-db SNR, Example 5.6	5.11
5.12	Impulse response of fit to system with 15-db SNR, Example 5.6	5.12
5.13	Frequency response of different noise level fits, Example 5.6	5.12
5.14	Impulse response of system (5.5), Example 5.8	5.16
5.15	Frequency response of system (5.5), Example 5.8	5.17
5.16	Impulse response of the $p = 0.9$ fit, Example 5.8	5.17
5.17	Frequency response of the $p = 0.9$ fit, Example 5.8	5.18
5.18	Impulse response of system (5.6), Example 5.9	5.19
5.19	Frequency response of system (5.6), Example 5.9	5.19

Tables

4.1	Test system 1	4.2
4.2	Test system 2	4.4
4.3	Test system 3	4.6
5.1	Identified poles for given LP methods, Example 5.1	5.2
5.2	Identified 0.35-hz terms for forward/backward formulations, Example 5.2	5.3
5.3	Identified poles and residues for given colored noise, Example 5.7	5.13
5.4	Identified poles, Example 5.8	5.15
5.5	Identified residues, Example 5.8	5.16
5.6	Identified poles for closely-spaced pole-zero pairs, Example 5.9	5.20
5.7	Identified residues for closely-space pole-zero pairs, Example 5.9	5.20

1.0 Introduction

Many dynamic systems exhibit oscillatory responses with multiple modes of oscillations. Examples include electromechanical oscillations in large synchronous-generator-based power systems and flexible mechanical structures and manipulators. Although the underlying dynamics of such systems are often nonlinear, it is often possible and very useful to represent the system operating about some set point with a linear model. Derivation of such linear models can be done using two basic approaches: model the system using theoretical derivations and some linearization method such as a Taylor series expansion; or use a curve-fitting technique to optimally fit a linear model to specified system response data. Prony analysis belongs to the second class of system modeling because it is a method of fitting a linear model to the impulse response of a dynamic system. Its parallel formulation inherently makes it well suited for fitting models to oscillatory system data.

Such oscillatory dynamic effects occur in large synchronous-generator-based power systems in the form of electromechanical oscillations. These oscillations arise when energy is exchanged between generators, or sets of generators, through transmission lines. In theory, a power system has $m - 1$ modes of oscillation, where m is the number of generators; modern systems have hundreds of generators. In reality, any one signal will be dominated by a few modes. To study and characterize these oscillatory dynamics, the Bonneville Power Administration (BPA) has developed computer codes to analyze system data using Prony analysis. To make full integrated use of the Prony analysis codes, as well as other analysis techniques, BPA has commissioned Pacific Northwest Laboratory (PNL)^(a) to further develop the codes and techniques into a software tool termed the Power System Identification (PSI) Toolbox.

The first phase of the PSI Toolbox development involves investigating the characteristics of the analysis techniques by evaluating existing software and developing guidelines for best use. Subsequent phases include extending current software; developing new analysis algorithms; and reorganizing the software into a modular collection of computer programs.

The primary focus of this report falls under the first phase. The characteristics of using Prony analysis to fit a linear model to the impulse response of an oscillatory system are investigated. The investigation is conducted by performing fits to the impulse response of known linear models under controlled conditions. The conditions studied include fitting algorithms, parent system configurations, and underlying noise characteristics. Many general "rules of thumb" for fitting under these conditions are drawn from the testing results. Special effort is made to investigate the effects that might be encountered in studying electromechanical oscillations in power systems. These oscillations typically occur in the 0.1-hz to 2.0-hz range; therefore, examples systems used in the investigations consist of multiple modes in this frequency range. Although the intended focus of this work is power system oscillations, the studies are generic enough that the results are applicable to many types of oscillatory systems with closely-spaced modes (including flexible mechanical structures and manipulators).

The following section focuses on introducing Prony analysis and presenting a literature review on associated numerical fitting algorithms. The different Prony analysis computer codes used to conduct

(a) Pacific Northwest Laboratory is operated by Battelle Memorial Institute for the U.S. Department of Energy under Contract DE-AC06-76RLO 1830.

tests are discussed in Section 3. In Section 4, test systems and noise models are presented. The main results on testing Prony analysis under different conditions are presented in Section 5, and conclusions and recommendations are discussed in Section 6.

2.0 Prony Analysis

Prony analysis is a numerical technique that fits a weighted summation of exponential terms to a general signal. It provides modal, damping, phase, and magnitude information contained in the signal. A complete and up-to-date review of Prony analysis is contained in Scharf (1991). The technique originated nearly 200 years ago (Prony 1795), but only with the advancement of the modern digital computer has its full implementation become feasible. In this section, Prony analysis is first introduced, followed by a review of literature focussed on numerical algorithms for solving the Prony analysis problem.

2.1 Derivation

Prony analysis provides a method of fitting a signal to a weighted linear combination of exponential terms. Consider a general signal $y(t)$ that is to be modeled by

$$\hat{y}(t) = \sum_{i=1}^n B_i e^{\lambda_i t} \quad (2.1)$$

where $B_i \in \mathbb{C}$ is termed the output residue for the continuous-time pole $\lambda_i \in \mathbb{C}$. The objective is to identify the residues, poles, and n that force the signal of (2.1) to be the least-squares error fit to $y(t)$.

The signal $y(t)$ is sampled at a constant sample period (T) smaller than the Nyquist period, and (2.1) is rewritten in discrete-time form as

$$\hat{y}_k = \sum_{i=1}^n B_i z_i^k, \quad k=0,1,\dots,N-1 \quad (2.2)$$

where

$$z_i = e^{\lambda_i T} \quad (2.3)$$

$z_i \in \mathbb{C}$ is termed the discrete-time pole. It is not required that the original signal be a continuous set. One can just as easily start with evenly-spaced discrete data and formulate the starting model as (2.2).

It is well known that the output of (2.2) satisfies its own characteristic equation. Let the characteristic equation of (2.2) be written as

$$p(z) = z^n - (a_1 z^{n-1} + a_2 z^{n-2} + \dots + a_n) \quad (2.4)$$

Then the output of (2.2) satisfies

$$\hat{y}_k = a_1 \hat{y}_{k-1} + a_2 \hat{y}_{k-2} + \dots + a_n \hat{y}_{k-n} \quad (2.5)$$

for $k=0,1,\dots,N-1$. Equation (2.5) is known as an auto-regressive (AR) sequence written in the forward

direction. Assuming $\hat{y}$ is a real function, it is also well known that it satisfies

$$\hat{y}_k = \bar{a}_1 \hat{y}_{k+1} + \bar{a}_2 \hat{y}_{k+2} + \dots + \bar{a}_n \hat{y}_{k+n} \quad (2.6)$$

for $k=0,1,\dots,N-1$, and where the roots of the polynomial

$$\bar{p}(z) = 1 - (\bar{a}_1 z + \bar{a}_2 z^2 + \dots + \bar{a}_n z^n) \quad (2.7)$$

are reflections about the unit circle of the roots of the polynomial in (2.4). Equation (2.6) is the AR sequence written in the backward direction.

Generally, the process of solving for the unknowns is conducted in three steps:

1. y is substituted for $\hat{y}$ in (2.5) and/or (2.6), and the linear equations are solved for the unknown a_i 's. This step is termed the **Linear Prediction (LP)** problem.
2. Polynomials (2.4) and/or (2.7) are factored for the discrete-time poles (i.e., the z_i 's). This, in turn, yields the continuous-time poles.
3. Again, substituting y for $\hat{y}$, (2.2) is solved for the output residues. Because (2.2) involves a Vandermonde matrix, this is termed the **Vandermonde** problem.

Solving step 1 has received the most attention in the literature. The problem can be formulated many different ways. For example, consider only the forward direction problem. If initial (i.e., $k < 0$) and post (i.e., $k > N$) conditions are assumed zero, then the equations (2.5) are written as

$$\begin{array}{cccc} \uparrow & & \uparrow & \\ | & & | & \\ | & & | & \\ | & \uparrow & | & \uparrow \\ X_4 & | & X_2 & | \\ | & X_3 & | & X_1 \\ | & | & \downarrow & \downarrow \\ | & | & & \\ | & | & & \\ \downarrow & \downarrow & & \end{array} \begin{bmatrix} y_0 & 0 & & \\ y_1 & y_0 & & 0 \\ \vdots & \vdots & \ddots & \\ y_n & y_{n-1} & \dots & y_0 \\ y_{n+1} & y_n & \dots & y_1 \\ \vdots & \vdots & & \vdots \\ y_{N-1} & y_{N-2} & \dots & y_{N-n-1} \\ 0 & y_{N-1} & \dots & y_{N-1} \\ & & \ddots & \vdots \\ & 0 & & y_{N-1} \end{bmatrix} \begin{bmatrix} -1 \\ a_1 \\ a_2 \\ \vdots \\ a_n \end{bmatrix} = \begin{bmatrix} 0 \\ \vdots \\ 0 \end{bmatrix} \quad (2.8)$$

The matrix in (2.8) is the Toeplitz data matrix. One could just as easily write the analogous matrix equation using (2.6), or a combination of (2.5) and (2.6). In the majority of practical cases the Toeplitz matrix is non-square with more rows than columns. Then a least-squares solution can be calculated by minimizing the right-hand side of (2.8).

Four different formulations are indicated in (2.8); these are X_1 through X_4 . X_1 is termed the covariance problem. Because initial and post conditions are not used, no assumption is required on their value. X_4 is the correlation problem; it incorporates both initial and post conditions. The last two problems, X_2 and X_3 , are termed the pre-windowed and post-windowed methods.

The solution to step 2 can be done in one of two ways: eigenanalysis or polynomial factoring. With eigenanalysis, a companion matrix is constructed for polynomials (2.4) and/or (2.7) and the eigenvalues which are equal to the z_i 's are calculated. In using polynomial factoring, the roots of (2.4) and/or (2.7) are calculated using a root-finding algorithm.

Step 3 is also a linear algebra problem. Once the z_i 's are obtained from step 2, they are substituted into (2.2) and written in matrix form as

$$\begin{bmatrix} 1 & 1 & \dots & 1 \\ z_1 & z_2 & \dots & z_n \\ z_1^2 & z_2^2 & \dots & z_n^2 \\ \vdots & \vdots & \vdots & \vdots \\ z_1^{N-1} & z_2^{N-1} & \dots & z_n^{N-1} \end{bmatrix} \begin{bmatrix} B_1 \\ B_2 \\ \vdots \\ B_n \end{bmatrix} = \begin{bmatrix} y_0 \\ y_1 \\ \vdots \\ y_{N-1} \end{bmatrix} \quad (2.9)$$

The $N \times n$ matrix in (2.9) is a Vandermonde matrix.

Up to now, it has been assumed that the order of the signal n is known and that this is the order used in the LP and Vandermonde problems. This is not always the case. In many cases n is unknown, and even when it is known, one often chooses a larger order for the LP and Vandermonde problems for numerical robustness. To simplify explanation in the remainder of this document, we define n_{LP} to be the order used in the LP problem, n_v to be the order used in the Vandermonde problem, and n will continue to be the order of the final model.

2.2 Literature Review

Prony analysis was first introduced by Baron de Prony (1795) 200 years ago. Because of lack of modern computing capability, significant applications were not explored until Hildebrand (1956) proposed least-squares solutions. Since the proposition by Hildebrand, several papers have been published on solving Prony analysis types of problems. Probably the most complete and modern discussion of Prony analysis is contained in Scharf (1991). The literature review here is focussed on solution techniques and extensions of Prony analysis. Papers discussing the application of Prony analysis are not reviewed here.

The original Prony method proposed that $N = 2n$, $n_v = n_{LP} = n$, and the LP forward-direction covariance formulation be used. The LP and Vandermonde systems are then directly solved using matrix inversion; the Vandermonde system is made square by using only the first n data points. Even with modern computers, this formulation is extremely numerically sensitive (Scharf 1991). To avoid these numerical problems, Hildebrand (1956) proposed to allow $N > 2n$ and employ least-squares solution techniques. Much of the modern literature on Prony analysis focuses on robustly solving the

least-squares problem.

Many researchers have contributed to developing modern least-squares Prony analysis. Some have termed the least-squares solution approach "extended Prony analysis" (Marple 1989). The work by Kumaresan and Tufts (Kumaresan and Tufts 1982; Tufts and Kumaresan 1982a, 1982b) is probably best known for pioneering modern development of Prony analysis by applying advanced numerical techniques to solve the least-squares problems. Its main thrust is solving the LP problem.

In Tufts and Kumaresan (1982a, 1982b) methods are presented based on singular value decomposition (SVD) for estimating closely spaced frequencies of sinusoidal signals in noise. Although they do not explicitly call this a Prony method, it is equivalent to assuming that all the poles are on the unit circle. Under this constraint, the forward and backward direction LP polynomials are the same. Significant attention is given to the algorithm described in Tufts and Kumaresan (1982b) where the LP problem is written in a combined forward-backward manner and n_{LP} is maximally chosen. Discussions of the properties of this method are contained in Rao (1986a, 1986b).

Kumaresan and Tufts (1982) expand their methods to estimate parameters of damped sinusoids in a least-squares sense as proposed by Hildebrand (1956). Again they address the problem of solving for the LP coefficients. The LP problem is written in the backward direction, as opposed to the forward proposed in Hildebrand (1956), using the covariance form, and the SVD of the LP matrix is computed. The smaller singular values are "ignored" (their inverse are identically set to zero) in computing the least-squares solution with the SVD matrices. As discussed in Tufts and Kumaresan (1982a), this is the best lower rank approximation to a given matrix (in the Frobenius norm sense). The order of the prediction (i.e., n_{LP}) is assumed to be a fraction of the number of data samples (approximately $N/3$ to $N/2$), which facilitates the robustness of the SVD. By using the backward direction of the LP method, the true signal modes occur outside the unit disk while noise terms are inside the disk.

Using the SVD method to solve over-determined systems of equations has become a highly recommended method (Press et al. 1990). This is due primarily to its robust numerical properties and ease of implementation.

A modification to the procedure used in Kumaresan and Tufts (1982) for estimating the LP coefficients is proposed by Porat and Friedlander (1986). The LP problem is solved both in the forward and backward directions. When the backward direction terms are reflected about the unit circle, the signal poles will reflect onto those from the forward direction analysis while the noise terms will move away from each other. The identified terms are then averaged. The authors claim this algorithm can be used to identify both damped and undamped modes.

Although the methods in Steiglitz and McBride (1965) and Steiglitz (1977) are not strictly Prony analysis methods, they are used to identify impulse response models. Three methods are compared in Steiglitz (1977). The LP problem is solved similar to that proposed by Hildebrand (1956), and an iterative correction algorithm is used to improve on the LP estimation.

Barone et al. (1987) propose using the Burg algorithm to solve the LP problem in covariance form. They term this the Prony-Burg method. The Burg analysis is an iterative one where $2n_{LP}$ LP polynomials are calculated. It has proven successful with Maximum Entropy Spectral Estimation (MESA) (Kay and Marple 1981). The Akaike method (1969) is used to determine the actual LP

model order (n) and thus the proper LP polynomial. Applying the Akaike method to this problem results in the final prediction error (FPE) being minimized at the proper model order (n), where

$$FPE = \frac{N+n+1}{N-n-1} \sigma^2 \quad (2.10)$$

with σ^2 being the squared error between model and data. Barone et al. (1987) recommend that eigenanalysis be used for calculating the roots of the LP polynomial and SVD be used for solving the Vandermonde system.

Four different methods for solving the over-determined covariance LP system are compared in Barone (1988); these methods are: 1) a least-squares covariance algorithm using an orthogonalization method based on Givens rotations (Kay and Marple 1981); 2) the covariance SVD method proposed in Tufts and Kumaresan (1982a); 3) the Burg algorithm (Kay and Marple 1981); and 4) the Marple algorithm (Marple 1980). The methods are compared by applying the four to an example problem consisting of sinusoids in noise. It is concluded that for this example, the Marple and Burg algorithms perform best.

Additional methods for solving the LP problem are proposed (Minami et al. 1986; Cruz 1986). In Minami et al. (1986) the LP problem is solved using eigenvalue decomposition of the covariance matrix. By discarding eigenvalue and eigenvector terms that are too "small," the optimal model order (n) is determined during the fit. Cruz (1986) proposes that the quotient-difference (QD) algorithm of Rutishouser (1957) be used to solve the LP problem. Using this algorithm allows the system poles to be directly identified, removing the need for root finding or eigenanalysis. No comparisons are made in Minami et al. (1986) or Cruz (1986) with more established methods such as SVD.

Demeure and Scharf (1990) describe a "fast" recursive orthogonalizing (QR) method for decomposing the Toeplitz matrix in the LP problem. Once the decomposition is complete, the LP problem is easily solved. For high-order problems, the algorithm offers significant speed-up when compared to standard Cholesky methods. The technique is also described in Scharf (1991).

The problem of choosing the model order (n) and the signal components is addressed by Kumaresan, Tufts, and Scharf (1984). A least-squares solver (such as SVD) is used to estimate the LP parameters with n_{LP} being near $N/3$ to $N/2$. Then n_v is varied from 1 to n_{LP} , and the best model for each n_v is calculated by searching all the z_i 's for the n_v subset that best represents the signal. Two search methods are possible: 1) try every possible combination of mode terms; or 2) search for the terms one at a time using the search technique described in Hocking and Leslie (1967). The second is less accurate than the first, but it requires much less calculation time. The true model is selected as the one that maintains a minimum error between the signal data and model output with minimum model order. The optimal order is subjective and difficult to algorithmize.

A similar model-order selection technique that employs a model reduction method has been

developed at PNL.^(a) With this method, $n_{LP} = n_V$ are assumed large ($N/3$ to $N/2$), and the LP and Vandermonde problems are solved for order n_{LP} . The model order is then reduced by selecting the subset of residue and pole terms that minimize an Akaike information criterion with the associated error calculated in both the time and frequency domains. The method is much less time consuming than that in Kumaresan, Tufts, and Scharf (1984), as only one Vandermonde problem must be solved.

In the previously mentioned literature, little attention is given to factoring the LP polynomial to obtain signal poles. Basically, two methods are possible: eigenanalysis and polynomial factoring. Only a few papers address polynomial factoring, and no published papers were obtained that discussed different eigenanalysis routines.

Three methods of calculating the roots of a real-coefficient polynomial are compared in Rautenberg et al. (1988). Special attention is devoted to polynomials such as those found within Prony analysis. The three algorithms compared are: 1) the Madsen (1973) method; 2) the Muller (1956) iterative algorithm; and 3) the three-stage method by Jenkins and Traub (1970). Comparisons are based on accuracy, convergence rate, and stability. The Jenkins and Traub method performs best in most cases. For example, using double-precision arithmetic, the Jenkins and Traub method can accurately calculate the roots of a 60th order polynomial compared to 20 and 30 for the other two.

An algorithm for concurrently calculating the roots of a polynomial is proposed in Hoxha, Lambert, and Noailles (1988). Such an algorithm could be implemented on a parallel processing computer to accelerate computation time of Prony analysis. Examples are given for various versions of the algorithm, but no comparison is made with more conventional algorithms.

Demeure (1989) uses a fast QR factorization of the Vandermonde matrix to solve for the residues. Versions described include algorithms for complex conjugate poles and for poles with multiplicity greater than or equal to one.

Data pre-conditioning is proposed in Friddell et al. (1989) for improving the performance of Prony analysis under low signal-to-noise ratio (SNR). First, pre-filtering is examined with only limited success. Then a method that utilizes the fast Fourier transform (FFT) in conjunction with filtering to "zoom-in" on a portion of the signal spectrum is proposed. Basically, an FFT is performed on the signal, then all parts outside the regions of interest in the frequency domain are removed. An inverse Fourier transformation (IFT) is then used to obtain a clean time-domain signal.

A recursive form of Prony analysis is proposed in Lambert and Castanie (1988). With this algorithm pole and residue estimates are updated with each sample. Simulations demonstrate that the algorithm is able to track step and drift changes in the parameters of a sinusoid in noise.

McWhorter and Scharf (1991) examine the error bounds of Prony analysis (and other general modal analysis methods). They compute and examine the Cramer-Rao (CR) bounds for many of the parametric descriptions of a mode including AR and MA coefficients, poles and residues, and poles and zeros. All are related through transformations. The CR bounds provide a theoretical lower limit

(a) D. J. Trudnowski. 1993. "Order Reduction of Large Scale Linear Oscillatory System Models." To be presented at the 1993 IEEE Power Engineering Society Winter Meeting, Columbus, Ohio, February 1993.

for estimated parameters. An interesting point made in McWhorter and Scharf (1991) is that the CR bound is valid for any unbiased estimator. That is, the theoretical lower limit of an estimator's error is not dependent on that estimator algorithm, but is dependent on the information contained in the sampled data. The Fisher Information Matrix used in determining the CR bounds is also used to generate the smallest achievable "concentration ellipse" for a parameter set. These concentration ellipses define the smallest possible confidence ellipse within which the true parameters may lie with a given probability. Many examples are used to demonstrate the usefulness and properties of these error bounds.

In order to use the forms of Prony analysis discussed up to this point for system identification, the excitation to the system must be an impulse function. In reality, it is often extremely difficult to apply such an excitation to an actual system. Using Prony type analysis for system identification has been investigated for many different input forms.

Basically, the system identification problem is addressed from two perspectives. With the first, an input is applied to the system and Prony analysis is used to analyze the output after the input is turned off. Then the transfer function terms are obtained through algebraic functions involving the Prony fit terms. The second perspective involves modifying the Vandermonde problem to directly identify system transfer function terms. The advantage of this case is that all of the output data is used to calculate transfer function residues as opposed to just the data when the input is off. Using all the data in the LP problem is more difficult and can be done only if the input stays on for a significant number of samples (at least double the assumed system order).

The results in Poggio et al. (1978) show the equations required for identifying a strictly proper transfer function using Prony analysis when the input is

$$u(t) = e^{\tau_1 t} - e^{\tau_2 t} \quad (2.11)$$

where τ_1 and τ_2 are real time-constants. With this formulation, it is assumed that the system does not have poles at $-\tau_1$ or $-\tau_2$. In Hauer (1991) the input is allowed to be a square wave pulse, but the system is assumed not to have a pole at zero. The allowed input is expanded in Trudnowski et al. (1991) to be a finite duration of pulses with the same time constant, which includes a pulse train. But again, the system must be strictly proper and cannot have a pole corresponding to the input's time constant.

The work in Pierre, Trudnowski, and Hauer (1992) and Pierre et al. (1992) as well as recent work at PNL^(a) allow the system to be proper and to have non-zero initial conditions. Also, the system is allowed to have poles corresponding to the input's time constants. The input is expanded to be a finite-dimensioned Laplace-transformable function, which includes pulse trains, step functions, sinusoids, and a linear combination of these. The general versions proposed in Pierre et al. (1992) and in the recent PNL work^(a) uses all the system data to calculate transfer function residues and feedforward terms.

(a) D. J. Trudnowski, M. K. Donnelly, and J. F. Hauer. 1993. "Advances in the Identification of Transfer Function Models Using Prony Analysis." Submitted for presentation to the 1993 American Control Conference, San Francisco, California, June 1993.

3.0 Prony Analysis Codes

Primarily through BPA, several related Prony analysis computer codes have been developed. All are FORTRAN-based. In this section the content, differences, and status of these codes are summarized. Attention is paid primarily to the options in the core mathematical routines.

It is somewhat difficult to compare these codes in detail, as no previous effort has been given to formally track code updates and modifications. PNL has informally begun to track the versions of the routines that make up these codes by using the Revision Control System (RCS) described in Tichy (1985). The versions discussed here are the latest versions obtained by PNL and are likely the most recent.

The programs described here include SIGPAKZ, IPRONY, IPRONYID, and TRANSIENTS. The first three codes use primarily double-precision arithmetic and are built around the subroutine PRSPAK which performs the actual calculations of the Prony analysis fit. TRANSIENTS is a Prony analysis program developed at the University of Colorado at Boulder (UC) and uses primarily single-precision arithmetic. An early double-precision version of TRANSIENTS called DTRANSIENTS was used as the basis for PRSPAK. The current version of TRANSIENTS has several new options and modifications not included in PRSPAK.

3.1 SIGPAKZ and IPRONY

SIGPAKZ was developed at BPA and is a noninteractive program that uses the PRSPAK routine to perform the Prony analysis fit. No formal documentation or manual has been published for SIGPAKZ, but some detailed explanations are contained in Hauer et al. (1990) and Hauer and Taylor (1990) and in examples available with the program. It has several very distinct advantages, including the following: reads many data file formats for the system response data, including many power-industry-specific formats; allows "sliding window" fits; permits transfer function identification for a single pulse or step input and a proper system with no poles at zero; has several data-conditioning options (e.g., detrending and scaling); and has several output options including files for direct analysis using other BPA programs.

IPRONY is a stripped interactive version of SIGPAKZ. It calls the routine PRSPAK without the many options available in SIGPAKZ. It is very similar to an earlier version of DTRANSIENTS.

3.2 IPRONYID

IPRONYID is an interactive transfer function identification program that also uses PRSPAK as the core Prony fitting routine along with other routines developed at PNL.^(a) The system input is allowed to be an impulse function or a finite number of square-wave pulses (including step functions). The transfer function model is allowed to be proper and can have a pole at zero (in the s-plane). IPRONYID also performs model reduction to separate true system terms from those representing noise

(a) D. J. Trudnowski. 1992. "IPRONYID Version 1.1b: A Computer Program for the Identification of Transfer Functions Using Prony Analysis." Pending PNL report.

effects.

The version of PRSPAK used in IPRONYID is a variation of that called by SIGPAKZ. Modifications were made so that PRSPAK does not necessarily have to write to a data file during execution in batch mode. Changes were made so that this new version can easily be used with SIGPAKZ and IPRONY. Several tests were conducted to compare the results from SIGPAKZ and IPRONYID. As expected, under the same input conditions, they both give the same results.

3.3 PRSPAK (Core Prony Subroutine)

SIGPAKZ, IPRONY, and IPRONYID all use versions of the subroutine PRSPAK which performs the actual Prony analysis. The version of PRSPAK used in SIGPAKZ and IPRONY is PRSPAK2 version 1.1 (the version number has been adopted at PNL for convenience). This version was obtained from BPA in a send-out tape (dated June 1991). Version 1.1.2.1 of PRSPAK2 is contained in Appendix A and is the version used in IPRONYID. Three main functions are performed in PRSPAK: 1) solution of the LP problem; 2) rooting of the LP polynomial; and 3) solving the Vandermonde problem. There are 12 different ways of formulating the LP problem, and 4 possible solution methods for each formulation. Also, there are 2 solution options for the root finding problem, and 3 different solution methods for the Vandermonde problem. This means that there are 288 possible solution paths available in PRSPAK for solving the Prony analysis problem. As can be seen, PRSPAK calls many other subroutines.

With the LP problem, the user must first choose the linear prediction method from one of the following: correlation; pre-windowed; covariance; and post-windowed options. This determines the form of the Toeplitz matrix as described by Equation (2.8). Then the forward/backward logic must be determined. PRSPAK allows the LP equation to be written in the forward direction as in (2.5), or the backward direction as in (2.6), or a combination of these. In the forward direction, the a_i 's are identified; in the backward, the $\bar{a}_i$'s are identified; and in the combination case, both polynomial coefficient sets are identified.

There are four choices for solving the over-determined set of equations representing the LP problem: 1) singular-value decomposition (SVD); 2) standard QR; 3) total least-squares (TLS); and 4) fast QR;. The SVD is performed on the Toeplitz matrix using a standard double-precision LINPACK (Dongarra 1979) routine, and the solution is obtained using the standard SVD method (Press et al. 1990). Also, the QR factorization routine in double-precision LINPACK is used to solve the LP problem using the standard QR (again, see Press et al. [1990] for details). The fast QR method is described in Demeure and Scharf (1990).

The TLS method is slightly different than solving (2.8) in a least-squares sense. Let (2.8) be re-written in matrix form as

$$YA=0 \tag{3.1}$$

In solving (3.1) using TLS, we assume that an error matrix is associated with Y . Let's call this error

matrix δY . Now Equation (3.1) is written as

$$(Y + \delta Y)A = 0 \quad (3.2)$$

TLS consist of minimizing the Frobenius norm of δY , under the constraint that the (3.2) is satisfied. The TLS problem in PRSPAK is solved using singular-value decomposition. The Toeplitz matrix is factored into its singular-value components as

$$Y = U \Sigma V^T \quad (3.3)$$

where U and V are the left and right singular-value unitary matrices and Σ is a diagonal matrix of singular values (see Dongarra et al. [1979] for details). The solution vector A is then

$$A = -v_m \quad (3.4)$$

where v_m is the appropriately normalized m th column of matrix V , and m corresponds to the location of the minimum singular value in Σ . Again, the double-precision LINPACK SVD routine is used in PRSPAK to perform the SVD on the Toeplitz matrix.

Only one root finder option is available in PRSPAK, although it can be performed in either a double (DPOLYRT) or quad-precision (QPOLYRT) subroutine. The root finding routine was taken from the "SAMSAN" codes by Dr. John Hauer of BPA. From the notes in the subroutines, it is a version of RPOLY described in Jenkins (1975). But, it is not clear from the code that this is the actual algorithm used in DPOLYRT and QPOLYRT.

The third calculation performed in PRSPAK is determining the signal residues through the solution of the Vandermonde problem. There are three possible solution methods: 1) standard QR; 2) fast real; and 3) fast complex. As with the LP problem, double precision LINPACK routines are used to solve the standard QR problem. The two fast routines are taken from Demeure (1989).

PRSPAK allows the user to choose the order of the Vandermonde system (n_v) to be less than the order of the LP (n_{LP}). If n_v is less than n_{LP} , PRSPAK solves all the possible Vandermonde problems that represent all combinations of z_i 's taken n_v times. The one solution combination that best fits the data in a squared-error sense is taken as the final solution.

Other functions performed in PRSPAK fall into one of the following categories: interactive input/output; batch output; default parameter selection; miscellaneous calculations; and plotting. The plotting routines compile only under specific platforms and are activated only when PRSPAK is operated in the interactive mode.

3.4 TRANSIENTS

TRANSIENTS is an interactive Prony analysis program being developed at UC. The version currently at PNL was the latest version available from UC in spring 1992. As previously mentioned, the current versions of PRSPAK were developed by modifying an older version of TRANSIENTS. Since that time, several modifications have been made to TRANSIENTS and to the several supporting subroutines.

TRANSIENTS has the same solution options as PRSPAK, although many minor changes have been made to nearly all the subroutines as compared to those employed in PRSPAK. A new major addition to TRANSIENTS includes the solution of composite mode problems. That is, it allows the assumed model to have repeated poles.

3.5 Computer Platforms

Because all the Prony analysis codes are FORTRAN-based, it is possible to port them to different computer platforms if an adequate FORTRAN compiler is available. In this section, PNL's experience with different platforms is summarized.

SIGPAKZ and IPRONY, as delivered from BPA, execute under a VAX-VMS operating system. At PNL this code was ported to a SUN Sparc 2 workstation operating under the UNIX system. The SUN version 1.4 FORTRAN compiler was used to compile and link the programs on the Sparc 2. This porting required a number of modifications. Summaries of these modifications are described here.

Modifications to SIGPAKZ include the following:

1. Changing file names in INCLUDE statements to lower case because UNIX differentiates between capital and lower-case letters.
2. Adding parentheses to the arguments of PARAMETER statements as required by the SUN compiler.
3. Changing the default I/O unit numbers from 5 and 6 to 2 and 3. SUN reserves 5 and 6.
4. Modifying common files LUNITS.CMN and PLOT.CMN to remove redundancies in COMMON and DATA statements.
5. Modifying OPEN statements in LUNET.FOR to use SUN I/O options.
6. Using the SUN version of the random number generator in functions DALEAT and ALEAT in file MATH.FOR.
7. Adding a new FORMAT statement in RDSIG for reading character data. With the SUN compiler the FORMAT must match the declared dimension of a character string. As more read options are used with the SUN version of SIGPAKZ, more changes of this type will likely have to be made.
8. Routines and functions in files NEWGRAPH.FOR, PLOT.FOR, VERSA2.FOR, and VPLOT.FOR that make calls to PLOT10/LIB and VTRANOP.OBJ were disabled with comment markers. This was done because PLOT10/LIB and VTRAN.OBJ are not available for porting; therefore, they are not included in the link list. Also, the routine CPUTIME.FOR was disabled because it makes specific VMS calls; if so desired, these calls could be replaced with SUN-specific calls.

With these changes SIGPAKZ successfully compiles and links under the SUN system. Several test cases were run both on the VMS version and the SUN version of SIGPAKZ. Results matched between the two versions out to the 9th or 10th decimal place with all the tests. The slight difference between the two is likely due to the different interpretations of double precision between VAX and SUN platforms. SUN uses the IEEE Standard for Binary Floating-Point arithmetic. For a 64 bit number, 11 bits are devoted to the exponent which leaves 53 significant bits. VAX in D_floating format reserves 8 bits for the exponent leaving 56 significant bits.

With similar differences, IPRONYID also compiles under both the VAX-VMS and SUN platforms. Also, IPRONYID was compiled under a DOS operating system using a Lahey^(a) compiler. With this DOS version, the double precision root finder must be used as the Lahey compiler does not support quad-precision. Only a very few other minor changes were made to the SUN version of IPRONYID to make it compile under DOS.

TRANSIENTS is being developed under a Hewlett Packard (HP) platform using several HP specific plotting options. These plotting options are scattered throughout most the subroutines. Therefore, the majority of modifications required to port TRANSIENTS to a SUN platform involved disabling the appropriate plotting options. The only other required modification involved changing the calling to a HP specific random number generator.

(a) Developed by Lahey, Inc.

4.0 Example Systems and MATLAB Interfaces

To effectively evaluate the characteristics of Prony analysis, response data from linear systems under controlled conditions were required (including noisy conditions). The purpose of this section is to describe the test systems, synthetic noise characteristics, and interfacing with the commercial software package MATLAB, which was developed by the Mathworks, Inc.

4.1 Interfacing with MATLAB

Much of the data processing for conducting SIGPAKZ and IPRONYID runs was done using the software package MATLAB and its associated Control System Toolbox. This includes the development of test systems. Details on interfacing SIGPAKZ and IPRONYID files with MATLAB are described here as are several MATLAB m-files for performing specific tasks.

MATLAB (standing for matrix laboratory) is a multi-purpose interactive program that allows a user to easily access several advanced numerical and matrix analysis methods. When used with the Control System Toolbox, it can solve many advanced analysis problems related to linear systems. A few of the functions include time-domain simulation, frequency domain analysis, conversion between model formulations (e.g., state-space to ratio of zeros and poles), and root locus analysis. MATLAB allows the user to write custom functions using m-files.

Interfacing MATLAB with SIGPAKZ and IPRONYID is done using a combination of FORTRAN programs and m-files. To save a data set for processing by SIGPAKZ, the data are saved in MATLAB as a straight ASCII file; this ASCII file is then converted to a readable SIGPAKZ file using the FORTRAN program CONVERT2SWX. To import the results from a SIGPAKZ execution, the output model is extracted from the SIGPAKZ output file and then loaded into MATLAB using the load command. The m-file SIGZ2MAT.M is then used to convert the data to residue/pole model in MATLAB. IPRONYID outputs are extracted by running the FORTRAN program IPR2MAT and then loading the appropriate file into MATLAB and running the m-file IPR2MAT.M.

Several other m-files have been developed for the work presented in this report. Some of the less trivial m-files include

- **PAR2SS.M:** Convert a model in parallel form to block-diagonal state-space form. **SS2PAR.M** performs the vise-versa.
- **ODEABCD.M** and **ODEABCD2.M:** Perform a time simulation of a linear model in state-space form (errors have been encountered with the similar MATLAB function LSIM).
- **ORDER.M:** Performs model reduction.
- **PARRID.M:** Given a system input, output, and Prony fit to the output, calculate the transfer function residues.
- **THRUPUT.M:** Given the results from PARRID.M, calculate a least-squares fit to the throughput term (or feed-forward term).

- REFLECT.M: Reflect system poles and zeros about the $j\omega$ axis.
- IMPULSEPAR.M and BODEPAR.M: Calculates impulse and frequency responses for systems in parallel form (similar to MATLAB functions IMPULSE and BODE for state-space forms).

4.2 Test Systems

Characteristics of Prony analysis were investigated using variations of three linear systems. The first system is a 9th-order, 4-oscillator system; the second is a 12th-order, 5-oscillator system; and the third is a 28th-order, 14-oscillator system. The second and third systems were obtained from BPA.

4.2.1 Test System 1

Test system 1 is represented by the parameters in Table 4.1, where " $\pm$ " is used to represent complex conjugate pairs. Using the notation in Table 4.1, the transfer function for this test system can be written as

$$G(s) = \sum_{i=1}^n \frac{\text{Residue}(i)}{s - \text{Pole}(i)} \quad (4.1)$$

or as

$$G(s) = \frac{\text{Gain} \prod_{i=1}^m (s - \text{Zero}(i))}{\prod_{i=1}^n (s - \text{Pole}(i))} \quad (4.2)$$

where n is the number of poles and m is the number of zeros. Figure 4.1 shows the impulse response of test system 1, and Figures 4.2 and 4.3 show the frequency response. This system is characterized by two dominant modes at 0.35 and 0.45 hz, and two weaker, more lightly damped modes at 0.8 and 1.0 hz. After 1.6 hz, the frequency response of the system tends to roll off because of the real pole.

Table 4.1. Test system 1.

Poles	Residues	Zeros	Gain
-1.60(2 π)	44.062	-0.80+j0.55(2 π)	9.6 π
-0.50+j0.35(2 π)	57.46 $\angle \mp 74.47^\circ$	-0.15+j0.65(2 π)	
-0.25+j0.45(2 π)	25.07 $\angle \pm 137.87^\circ$	-0.30+j0.90(2 π)	
-0.10+j0.80(2 π)	3.00 $\angle \mp 109.55^\circ$	-0.60+j1.50(2 π)	
-0.05+j1.0(2 π)	3.425 $\angle \mp 143.10^\circ$

Figure 4.1. Impulse response of test system 1.

Figure 4.2. Frequency response of test system 1.

Figure 4.3. Frequency response of test system 1.

4.2.2 Test System 2

Test system 2 is shown in Table 4.2 and Figures 4.4 through 4.6. The 0.38-hz mode primarily dominates the response.

Table 4.2. Test system 2.

Poles	Residues($\times 10^{-3}$)	Zeros	Gain
-0.7166(2π)	-0.003929	0	-6.964
-2.644(2π)	0.02893	-0.4547(2π)	
-0.08182+j0.1087(2π)	4.0013 $\angle \mp 163.0^\circ$	-0.7083(2π)	
-0.04014+j0.3802(2π)	3.398 $\angle \pm 29.26^\circ$	-2.653(2π)	
-3.879+j1.178(2π)	5.262 $\angle \pm 128.67^\circ$	-0.1074+j0.5825(2π)	
-0.2187+j1.398(2π)	4.381 $\angle \mp 26.61^\circ$	-0.1691+j2.008(2π)	
-0.2591+j2.160(2π)	0.3872 $\angle \mp 56.48^\circ$

Figure 4.4. Impulse response of test system 2.

Figure 4.5. Frequency response of test system 2.

Figure 4.6. Frequency response of test system 2.

4.2.3 Test System 3

Test system 3 is represented in Table 4.3 and Figures 4.7 through 4.9.

Table 4.3. Test system 3.

Poles	Residues($\times 10^{-3}$)	Zeros	Gain
$-0.9088 \pm j1.606(2\pi)$	$12.21 \angle \mp 61.03^\circ$	-0.03157	0.003876
$-0.2414 \pm j1.502(2\pi)$	$3.370 \angle \pm 167.1^\circ$	-2.664	
$-0.1669 \pm j1.292(2\pi)$	$2.035 \angle \mp 28.9^\circ$	$-2.475 \pm j1.364(2\pi)$	
$-0.1112 \pm j1.240(2\pi)$	$2.110 \angle \mp 86.2^\circ$	$-2.475 \pm j1.364(2\pi)$	
$-0.3525 \pm j1.151(2\pi)$	$4.579 \angle \mp 21.8^\circ$	$-0.1809 \pm j1.270(2\pi)$	
$-0.3978 \pm j1.043(2\pi)$	$3.806 \angle \mp 84.7^\circ$	$-0.2882 \pm j1.245(2\pi)$	
$-0.1615 \pm j0.7427(2\pi)$	$17.66 \angle \pm 175.0^\circ$	$-0.35144 \pm j1.092(2\pi)$	
$-0.5387 \pm j0.7275(2\pi)$	$26.86 \angle \mp 53.60^\circ$	$-1.555 \pm j0.9946(2\pi)$	
$-0.1429 \pm j0.5975(2\pi)$	$13.97 \angle \pm 76.96^\circ$	$-3.722 \pm j0.6327(2\pi)$	
$-0.2756 \pm j0.5358(2\pi)$	$14.36 \angle \pm 0.05293^\circ$	$-0.03767 \pm j0.7804(2\pi)$	
$-0.3198 \pm j0.4609(2\pi)$	$8.825 \angle \mp 119.2^\circ$	$-2.186 \pm j0.3209(2\pi)$	
$-0.3746 \pm j0.3045(2\pi)$	$12.08 \angle \mp 4.998^\circ$	$-1.356 \pm j0.4281(2\pi)$	
$-0.2001 \pm j0.0913(2\pi)$	$5.010 \angle \pm 116.6^\circ$	$-0.04561 \pm j0.5726(2\pi)$	
$-0.1507 \pm j0.0367(2\pi)$	$7.226 \angle \pm 30.12^\circ$	$-0.08628 \pm j0.4820(2\pi)$	
		$-0.07624 \pm j0.08101(2\pi)$

Figure 4.7. Impulse response of test system 3.

Figure 4.8. Frequency response of test system 3.

Figure 4.9. Frequency response of test system 3.

4.3 Noise Models

To study the ability of Prony analysis to identify accurate models under noisy conditions, several synthetic noise files were constructed. Four noise models, each with its own coloration, are discussed here: 1) white noise; 2) $1/f$ noise; 3) $1/f^2$ noise; and 4) sharply colored noise. White noise has a flat power spectrum over the frequency range of interest. The synthetic white noise signals were generated using the stationary Gaussian noise generator in MATLAB.

The power spectrum for $1/f$ noise rolls off a rate of $1/f$ where f is the frequency in the range of interest. For the models investigated here, the frequency range of interest is 0.1 to 2.0 hz. For this range, $1/f$ noise is obtained by passing white noise through the nonlinear filter

$$G_{1/f}(s) = \frac{(2\pi 0.1)^{1/2}}{s^{1/2} + (2\pi 0.1)^{1/2}} \quad (4.3)$$

Because (4.3) is not a linear filter, data are passed through it in the frequency domain. The frequency response of Equation (4.3) is calculated and multiplied by the discrete fourier transform of the input time-domain signal. The inverse fourier transformation is then used to obtain the output signal.

Likewise, $1/f^2$ noise has a power spectrum that rolls off at a rate of $1/f^2$ for the range of interest. This noise is generated by passing white noise through the filter described by Equation (4.4). Figure 4.10 shows the frequency response of Equations (4.3) and (4.4). Note that the $1/f$ noise rolls off at 10 db/decade and the $1/f^2$ rolls off at 20 db/decade over the frequency range of interest.

$$G_{1/f}(s) = \frac{2\pi 0.1}{s + 2\pi 0.1} \quad (4.4)$$

White and $1/f$ noise have very unique characteristics in that their power spectrum decreases linearly with frequency. If audible noise with this characteristic is recorded and played back at a different speed, it will sound the same. These types of noises are called "scaling noises" West (1990). For this reason, and others discussed in (West 1990), $1/f$ noise is often called fractal noise.

Colored noise is generated by passing white noise through a sharply tuned filter. For the examples discussed later in this report, the coloring filter consists of a 10th-order Chebyshev band-pass filter with corners at 0.4 and 0.7 hz. Figure 4.11 shows the frequency response of this filter.

Figures 4.12 through 4.14 show the discrete fourier transformations of the noise sequences used in the examples in Section 5. Two methods of measuring the noise level are employed in later examples. One is the covariance of the noise sequence, and the other is the signal-to-noise ratio (SNR). The covariance is absolute measurement that is a function of the noise only. The SNR is defined here as

$$SNR = 10 \log_{10} \left(\frac{cov(y(t))}{cov(n(t))} \right) \quad (4.5)$$

where cov is the covariance, $y(t)$ is the deterministic signal, and $n(t)$ is the noise.

Figure 4.10. Frequency response of $1/f$ and $1/f^2$ filters.

Figure 4.11. Frequency response of coloring filter.

Figure 4.12. Frequency response of white and $1/f$ noise.

Figure 4.13. Frequency response of white and $1/f^2$ noise.

Figure 4.14. Frequency response of colored noise.

5.0 Properties of Prony Analysis

To optimally use an advanced analysis technique such as Prony analysis, one must fully understand its characteristics. These characteristics can then be used to formulate general "rules of thumb" for the technique. In this section, the properties of using Prony analysis to fit linear models to data with known controlled characteristics are discussed.

The properties discussed here were investigated by fitting models to the impulse response of known linear systems with specific characteristics. Special attention is paid to the following effects:

1. alternative solution techniques
2. assumed model order
3. sampling frequency
4. data record length
5. additive noise level and coloration
6. closely-spaced poles
7. closely-spaced pole-zero pairs.

Many tests were conducted using SIGPAKZ and IPRONYID to investigate these properties. Some of the tests are discussed here as examples to demonstrate certain points. The SIGPAKZ input files for the examples are contained in Appendix B.

5.1 Alternative Solution Techniques

As discussed in Section 3, PRSPAK offers 288 different solution paths for solving the Prony analysis fitting problem. The options include

1. four methods of formulating the Toeplitz data matrix (termed the LP method)
2. three methods of formulating the LP polynomial (termed the FB method)
3. four choices of LP solution algorithms (termed the LP algorithm)
4. three options for solving the Vandermonde problem.

The only other option available in PRSPAK involves the root finding option. This can be done using either double or quad precision arithmetic. For all the results presented here, the quad-precision routine is used. Other tests not discussed in this report show, that in general, the double-precision routine performs nearly as accurately except for very high-order models (i.e., when n_{LP} is large). It is recommended that one use the quad routine if the respective platform allows; if not, use the double. It seems that in many cases, the double-precision root finder gives warning errors if the polynomial is of

the order of 50 or more, while the quad typically does not give warnings until order 120.

5.1.1 The Linear Prediction Method

The possible linear prediction methods are correlation, pre-window, covariance, and post-window. Consider a signal y sampled to be y_k , $k = 0, 1, \dots, N-1$. With the correlation, pre-windowed, and post-windowed options, assumptions must be made concerning the value of y_k for $k < 0$ and/or $k > N - 1$. In PRSPAK the assumption is that $y_k = 0$ in this range. When analyzing the impulse response of a linear system, the $y_k = 0$ assumption is the incorrect one because such a system cannot have distinct discontinuities. Therefore, one should expect the covariance method to give more accurate fits than the others for system impulse responses.

Several tests were conducted using the four different LP methods under various system and noise conditions. With all the tests, even the noise-free ones, the covariance fits were considerably better.

Example 5.1

Consider the test system 1. Fits are conducted on the first 15 seconds of the noise-free impulse response of the system. Table 5.1 compares the pole fits for the different LP methods. Note that the covariance method identifies the parameters much more accurately. The post-window method gives a relatively accurate estimate, likely because the end of the ring-down signal is close to zero because system damping.

Table 5.1. Identified poles for given LP methods, Example 5.1.

Actual	Cov.	Corr.	Pre.	Post.
-1.6(2 π)	-1.6(2 π)	Not identified	Not identified	-1.45(2 π)
-0.50 $\pm$ j0.35(2 π)	-0.50 $\pm$ j0.35(2 π)	-0.24 $\pm$ j0.39(2 π)	-0.23 $\pm$ j0.39(2 π)	-0.51 $\pm$ j0.34(2 π)
-0.25 $\pm$ j0.45(2 π)	-0.25 $\pm$ j0.45(2 π)	-0.15 $\pm$ j0.46(2 π)	-0.14 $\pm$ j0.46(2 π)	-0.27 $\pm$ j0.45(2 π)
-0.10 $\pm$ j0.80(2 π)	-0.10 $\pm$ j0.80(2 π)	-0.067 $\pm$ j0.79(2 π)	-0.050 $\pm$ j0.79(2 π)	-0.16 $\pm$ j0.79(2 π)
-0.05 $\pm$ j1.00(2 π)	-0.05 $\pm$ j1.00(2 π)	-0.078 $\pm$ j1.00(2 π)	-0.029 $\pm$ j1.00(2 π)	-0.13 $\pm$ j1.00(2 π)

5.1.2 Linear Prediction Algorithm

Once the linear prediction method is determined, a linear prediction algorithm is selected. As described in Section 3, there are four linear prediction algorithms: 1) singular-value decomposition (SVD); 2) standard QR; 3) total least-squares (TLS); and 4) fast QR. All the algorithms provide relatively accurate mode estimates in low-level noise cases. With high-level noise, one algorithm might work slightly better than the others, but the "best" algorithm seems to be highly variable, although SVD is consistently one of the better.

The advantage of the fast QR algorithm is that it is much faster computationally. As described in Demeure and Scharf (1990), the complexity of the standard Cholesky QR factorization method is on the order of $(N+n_{LP})n_{LP}$ while the fast QR is on the order of $N(n_{LP})$, where N is the number of data points. If one uses the recommended assumption that $N/3 < n_{LP} < N/2$, then the fast QR can represent significant speed-up. Although no specific timing tests were conducted, in most cases tested for this

report, the fast QR computed LP terms more than twice as fast as the other algorithms.

5.1.3 Forward/Backward Formulation

In formulating the linear prediction equations, one can write the auto-regressive equations in either forward or backward time. PRSPAK allows the use of forward, backward, and a combination of both. The roots of the backward AR polynomial are reflected about the unit circle when compared to the roots of the forward AR polynomial.

Several cases were investigated to compare the three possible formulations. In the noiseless case, all three perform equally well. But as noise is added to the data, the forward option results in significantly more accurate pole estimates.

Example 5.2

Fits are performed to the impulse of test system 1 with added white noise at a variance of 10 (SNR = 17 db). Table 5.2 compares the identified 0.35 hz modes for the three cases. The other identified modes have similar characteristics. Note that the forward option results in a much more accurate identified pole. The backward option identifies the 0.35-hz pole in the right half of the s-plane which is a reflection about the unit circle.

Table 5.2. Identified 0.35-hz terms for forward/backward formulations, Example 5.2.

	Actual	Forward	Backward	For./Back.
Pole	-0.50 $\pm j0.35(2\pi)$	-0.52 $\pm j0.36(2\pi)$	0.73 $\pm j0.36(2\pi)$	-0.30 $\pm j0.37(2\pi)$

5.1.4 Vandermonde-System Solving Algorithms

Once the mode estimates have been obtained by solving the linear prediction problem, the signal residues must be calculated. As described in Section 3, PRSPAK offers three options in solving the Vandermonde system: 1) standard QR; 2) fast real; and 3) fast complex. Under the conditions studied, all three give the same results. This includes the analysis of both noiseless and noisy data.

5.2 Effects of Linear Prediction Model Order

The literature recommends that one assume the model order to be large to allow extra terms for fitting the "noise" effects; doing so frees the other terms to fit actual system modes. Then the user must determine which identified terms represent noise and which represent actual system modes. For example, it is suggested in Kumaresan and Tufts (1982) that the assumed model order be $N/3$ to $N/2$ where N is the number of data points. The results obtained with the tests conducted with SIGPAKZ tend to support this recommendation.

In the noise-free case, model order is not very critical. If the model order is assumed too small, Prony analysis tends to produce a model that "averages through" small response details. In this case

none of the identified terms is accurate. If the model order is greater than or equal to the true system order, an accurate model is identified with the extraneous terms having very small residues.

As noise is added to the system output, model order becomes more critical. Even for very low-level noise, a model order equal to the system order results in a poor fit. As the model order is progressively increased, the fit improves. For low-level noise, a model order near $N/5$ or greater seems to provide good fits (assuming $N/5$ is greater than the true model order).

Separating the system model terms from the noise model terms is a difficult problem. No separation algorithm is currently employed in SIGPAKZ. IPRONYID uses a method recently developed at PNL, and mentioned in Section 2. This subject is discussed further in Section 6.

Example 5.3

In this example, several fits with various values for n are conducted to the impulse response of the 9th-order test system 1 with added white noise at a variance of 1.0 (SNR = 27 db). Each fit includes 150 data points. Figures 5.1 through 5.6 show the time and frequency response of identified models for $n = 3, 15$, and 30. Each time-domain plot compares the model with the actual system noisy data, and the frequency-response plots show the "clean" response of the actual system. For $n = 3$, the 0.35-hz mode is nearly identified. This is somewhat expected as this is the dominant mode. For $n = 15$, the identified model is not very accurate because of the noise effects. Not until $n = 30$ does the Prony analysis identify an accurate model. With the 30th-order model, 9 of the identified modes very closely match that of the actual system; these are used as the identified model. As n is increased past 30, the identified model parameters continue to improve in accuracy.

5.3 Effects of Sampling Frequency

It is well known that in sampling continuous-time data for analysis, one must sample at least the Nyquist rate. But, one also must not sample at too high a rate as the Z-transform poles converge to 1 on the unit circle. The natural question is, Given these restrictions, what is the best sample rate to use for optimum parameter identification?

Prony analysis is relatively robust to variations in the sample frequency. A general rule for choosing the sample rate is to make the highest frequency pole occur near the imaginary axis in the Z-plane. That is, the sample frequency should be double the Nyquist rate. If the sample frequency is on the order of four times greater than this, one is likely to still obtain accurate results. But, if the rate is two orders of magnitude greater than the general rule, errors are likely to occur because of Z-plane poles converging to 1.

Figure 5.1. Impulse response of 3rd-order fit to 9th-order system with white noise at 27-db SNR, Example 5.3.

Figure 5.2. Frequency response of 3rd-order fit to 9th-order system with white noise at 27-db SNR, Example 5.3.

Figure 5.3. Impulse response of 15th-order fit to 9th-order system with white noise at 27-db SNR, Example 5.3.

Figure 5.4. Frequency response of 15th-order fit to 9th-order system with white noise at 27-db SNR, Example 5.3.

Figure 5.5. Impulse response of 30th-order fit to 9th-order system with white noise at 27-db SNR, Example 5.3.

Figure 5.6. Frequency response of 30th-order fit to 9th-order system with white noise at 27-db SNR, Example 5.3.

5.4 Effects of Record Length

Naturally, one should provide as much information as possible to a fitting routine. But, for ring-down signals, at some point the noise will tend to dominate the data. At this point, additional data will likely make the fitting more difficult.

Based on many tests with Prony analysis, it seems that a general rule of thumb is that one should provide enough data to cover at least one full cycle of the low-frequency dominant modes of oscillation. This limit seems to be a corner; a safer rule might be to use two full cycles. Somewhat surprisingly, this rule is fairly independent of the sampling frequency.

Example 5.4

Fits are performed on varying lengths of the impulse response of test system 2. Figures 5.7 and 5.8 show the impulse and frequency responses of fits performed on 5 seconds of data and 2.5 seconds. The 5-second fit exactly matches the actual system data, but the 2.5-second fit is very poor.

Figure 5.7. Different data record fits impulse response, Example 5.4.

Figure 5.8. Different record length fits frequency response, Example 5.4.

Example 5.5

Now fits are performed to the noisy (variance = 10) response of test system 1. Figures 5.9 and 5.10 show the model and system responses for 10-second and 50-second fits. The 10-second fit is much more accurate (the identified parameters are also much more accurate). This is because, after 10 seconds, the ringdown is dominated by the noise.

5.5 Effects of Noise Level and Coloration

To investigate the effects of additive noise on Prony analysis, the different noise signals described in Section 4 were added to the impulse responses of the test systems. Several noise levels and colorations were tested.

Noise coloration has less effect on the performance of the Prony analysis than the noise level. As expected, poor identification occurs in the bandwidth of the noise. However, in most cases, accurate identification occurs outside the bandwidth of the noise. White and $1/f$ seem to equally affect all parameters, as these noise types have a wide bandwidth. $1/f^2$ noise tends to cause errors at the lower frequency end, and colored noise causes errors on terms within its bandwidth.

In general, accurate parameter identification is achieved for signal-to-noise ratios of 30-dB SNR or more, and in most cases, relatively accurate fits are obtained with a SNR of 20 dB. Noise levels greater than 10-dB SNR cause significant parameter errors. Under high noise conditions, use of a shorter data record can improve the fit (this is demonstrated in Example 5.5). This is because the lower end of the ringdown is dominated by the noise.

Figure 5.9. Impulse response of different record length fits, Example 5.5.

Figure 5.10. Frequency response, different record length fits, Example 5.5.

Example 5.6

In this example, progressively higher-level white noise is added to the impulse response of test system 1. Figures 5.11 through 5.13 show the fits for noise levels of variance 0.05 (40-db SNR) and 15 (15-db SNR); 15 seconds of data are used with each fit. The model parameters used to create the plot responses in these figures consist of only the parameters that closely match actual system parameters. The 40-db SNR case results in a very good fit, both graphically and in the parameters. The 15-db SNR fits poorly at the lower frequency gain areas, but appears to fit well at the higher gains (e.g., near 0.35 hz).

Figures 5.12 and 5.13 suggest that the 15-db SNR fit is accurate near 0.35 hz, but the identified parameters are not accurate. The actual system has a pole at $-0.50 \pm j 0.35(2\pi)$. The Prony analysis identifies two poles in this area; they are at $-41 \pm j 0.33(2\pi)$ and $-0.28 \pm j 0.38(2\pi)$. Both modes have large residues. This demonstrates that in high noise conditions one can obtain an accurate time and frequency domain fit, but the actual identified parameters may be in error.

Figure 5.11. Impulse response of fit to system with 40-db SNR, Example 5.6.

Figure 5.12. Impulse response of fit to system with 15-db SNR, Example 5.6.

Figure 5.13. Frequency response of different noise level fits, Example 5.6.

Example 5.7

In this example, different noise colorations are compared. Four different colorations are added to the impulse response of test system 1 each at a SNR of 20 db (based on a 15 second ringdown). The four colorations are white, $1/f$, $1/f^2$, and sharply colored between 0.4 hz and 0.7 hz (see Section 4). Table 5.3 shows the identified parameters for each case. Note that the $1/f^2$ noise causes relatively larger errors at the lower frequencies. This is because the energy of such noise is concentrated at the low end. Errors caused by the white and $1/f$ noise are spread over all the frequencies due to the wide-band effect of the noise. The colored noise caused only slight error for the 0.45-hz mode. In this case, Prony identified other modes in this area to adapt to the colored noise. Parameters outside the bandwidth of the colored noise are accurately identified.

Table 5.3. Identified poles and residues for given colored noise, Example 5.7.

Actual Pole Residue	White	$1/f$	$1/f^2$	Colored
-1.6(2 π) 44.1	-1.57(2 π) 65.8	-2.18(2 π) 58.0	Not identified	-1.60(2 π) 44.2
-0.50+j0.35(2 π) 57.5 $\angle \mp 74.5^\circ$	-0.46+j0.34(2 π) 46.6 $\angle \mp 80.6^\circ$	-0.51+j0.36(2 π) 70.0 $\angle \mp 90.8^\circ$	-0.48+j0.37(2 π) 62.1 $\angle \mp 101.0^\circ$	-0.50+j0.35(2 π) 57.5 $\angle \mp 73.7^\circ$
-0.25+j0.45(2 π) 25.1 $\angle \pm 139.0^\circ$	-0.23+j0.45(2 π) 21.5 $\angle \pm 142.0^\circ$	-0.24+j0.46(2 π) 20.5 $\angle \pm 111.0^\circ$	-0.20+j0.46(2 π) 16.8 $\angle \pm 117.0^\circ$	-0.29+j0.44(2 π) 23.3 $\angle \pm 146.0^\circ$
-0.10+j0.80(2 π) 3.00 $\angle \mp 110.0^\circ$	-0.11+j0.80(2 π) 3.49 $\angle \mp 116.0^\circ$	-0.12+j0.80(2 π) 3.68 $\angle \mp 117.0^\circ$	-0.12+j0.80(2 π) 3.42 $\angle \mp 112.0^\circ$	-0.10+j0.80(2 π) 3.04 $\angle \mp 110.0^\circ$
-0.05+j1.00(2 π) 3.42 $\angle \mp 143.0^\circ$	-0.085+j1.00(2 π) 3.78 $\angle \mp 145.0^\circ$	-0.078+j1.00(2 π) 3.53 $\angle \mp 146.0^\circ$	-0.05+j1.00(2 π) 3.39 $\angle \mp 143.0^\circ$	-0.05+j1.00(2 π) 3.43 $\angle \mp 143.0^\circ$

5.6 Effects of Closely-Spaced Poles

The standard assumed model for Prony analysis does not allow repeated poles. Given this, a natural question is, What is the effect of nearly repeated poles on the fitting algorithms? To investigate these effects, poles were incrementally moved closer together. Two cases were investigated. With one case, the poles were moved closer with equal imaginary terms. In the other, case they were moved closer with equal real terms.

In a linear system as the poles converge, the residues have large, nearly-equal magnitudes but opposite phase. Consider a strictly proper system written in the Laplace domain as

$$G(s) = \sum_{i=1}^n \frac{R_i}{s - \lambda_i} = \frac{b_0(s - z_1)(s - z_2) \dots (s - z_m)}{(s - \lambda_1)(s - \lambda_2) \dots (s - \lambda_n)} \quad (5.1)$$

where $m < n$, and

$$\lambda_2 = \lambda_1 + \delta \quad (5.2)$$

Using partial fraction expansion, solve for R_1 and R_2 :

$$R_1 = \frac{1}{\delta} \frac{\prod_{i=1}^m (\lambda_1 - z_i)}{\prod_{i=3}^n (\lambda_1 - \lambda_i)} \quad (5.3)$$

$$R_2 = -\frac{1}{\delta} \frac{\prod_{i=1}^m (\lambda_2 - z_i)}{\prod_{i=3}^n (\lambda_2 - \lambda_i)} \quad (5.4)$$

Poles λ_1 and λ_2 are moved close together by making δ small. From (5.3) and (5.4), we see that R_1 and R_2 become large in magnitude and opposite in phase. These effects make closely-spaced pole identification relatively difficult.

As one might expect, closely-spaced poles can cause significant problems with Prony analysis fitting. In noise-free cases, Prony analysis performs very well. The closely-spaced terms are identified with less than 1.0% errors. But, as noise is added to the impulse response, the results quickly change. Even for low-level noise (e.g., 30-db SNR), the errors on the closely-spaced terms significantly increase. The errors are especially large for the identified residues. These results correspond with the sensitivity results presented in McWhorter and Scharf (1991). In many cases, the errors are largest when the poles have similar frequencies but different damping. This is likely because such a configuration can often nearly be represented as a single mode with a compromised damping.

Example 5.8

Consider the system in Equation (5.5), which is a variation of test system 1.

$$G(s) = \left(\frac{s^2 + 0.2s + 0.1^2 + (3\pi)^2}{s^2 + 0.1s + 0.05^2 + (2\pi)^2} \right) \left(\frac{s^2 + 1.2s + 0.6^2 + (1.8\pi)^2}{s^2 + 0.2s + 0.1^2 + (1.6\pi)^2} \right) \left(\frac{s^2 + 0.3s + 0.15^2 + (1.3\pi)^2}{s^2 + 0.5s + 0.25^2 + (0.9\pi)^2} \right) \left(\frac{9.6\pi}{s + 3.2\pi} \right) \left(\frac{s^2 + 1.6s + 0.8^2 + (1.1\pi)^2}{s^2 + 2(0.5 - p0.25)s + (0.5 - p0.25)^2 + (0.9\pi)^2} \right) \quad (5.5)$$

As p is varied from 0 to 1, the poles at 0.45 hz converge. Figures 5.14 and 5.15 show the impulse and frequency response of Equation (5.5) for $p = 0, 0.75$, and 1.0. White noise at a variance of 0.005 (30 db SNR) is added to the impulse of (5.5) for various p 's, and Prony analysis fits are conducted. Tables 5.4 and 5.5 show the identified parameters for $p = 0, 0.75$, and 0.9; the closely spaced terms are in bold.

The errors on the identified poles are largest for those that are closely spaced; but, errors are less than 20% in most cases. Note that the damping on one of the closely-spaced poles is too small, while the damping on the other is too large. The residue errors for the closely-spaced poles are very large, especially as p increases. For $p = 0.9$, the identified residues are approximately one-sixth of the actual residues. From the large residue errors, one might expect the time and frequency domain fits to be poor. This is not the case. Figures 5.16 and 5.17 compare the response of the identified model with the actual system for $p = 0.9$. The actual time domain data includes the added noise, while the actual frequency response data does not include the noise. The time-domain fit is very close. The frequency-domain fit is very close at the response peaks. In the frequency range of the closely-spaced poles, the identified model's frequency response very closely matches the actual system response.

Table 5.4. Identified poles, Example 5.8.

Actual $p = 0.0$	Identified $p = 0.0$	Actual $p = 0.75$	Identified $p = 0.75$	Actual $p = 0.9$	Identified $p = 0.9$
-1.6(2 π)	-2.280(2 π)	-1.6(2 π)	-2.09(2 π)	-1.6(2 π)	-2.06(2 π)
-0.25 $\pm j0.45(2\pi)$	-0.242 $\pm j0.445(2\pi)$	-0.25 $\pm j0.45(2\pi)$	-0.220 $\pm j0.444(2\pi)$	-0.25 $\pm j0.45(2\pi)$	-0.209 $\pm j0.443(2\pi)$
-0.5 $\pm j0.45(2\pi)$	-0.566 $\pm j0.464(2\pi)$	-0.3125 $\pm j0.45(2\pi)$	-0.364 $\pm j0.461(2\pi)$	-0.275 $\pm j0.45(2\pi)$	-0.333 $\pm j0.460(2\pi)$
-0.10 $\pm j0.80(2\pi)$	-0.105 $\pm j0.798(2\pi)$	-0.10 $\pm j0.80(2\pi)$	-0.105 $\pm j0.798(2\pi)$	-0.10 $\pm j0.80(2\pi)$	-0.105 $\pm j0.798(2\pi)$
-0.05 $\pm j1.00(2\pi)$	-0.0521 $\pm j1.00(2\pi)$	-0.05 $\pm j1.00(2\pi)$	-0.0527 $\pm j1.00(2\pi)$	-0.05 $\pm j1.00(2\pi)$	-0.0528 $\pm j1.00(2\pi)$

5.7 Effects of Closely-Spaced Pole-Zero Pairs

This effect was tested by incrementally moving a pole-zero pair together. As with closely-spaced poles, the terms were converged in two cases: equal real terms and equal imaginary terms. In the noise-free case, Prony analysis performs very well. But as low-level noise is added, the results change significantly. Much more accurate identification is obtained in the case where the closely-spaced pole-zeros have equal real terms and different imaginary terms. With the other case, the zero appears to provide "false damping" to the close pole. That is, a pole is identified with increased damping to compensate for the zero with the same frequency.

Table 5.5. Identified residues, Example 5.8.

Actual $p = 0.0$	Identified $p = 0.0$	Actual $p = 0.75$	Identified $p = 0.75$	Actual $p = 0.9$	Identified $p = 0.9$
4.27	4.43	4.12	4.04	4.09	3.98
6.04 $\angle \mp 152^\circ$	5.29 $\angle \mp 135^\circ$	24.2 $\angle \mp 154^\circ$	9.81 $\angle \mp 118^\circ$	60.4 $\angle \mp 154^\circ$	10.9 $\angle \mp 114^\circ$
5.18 $\angle \pm 2.84^\circ$	3.84 $\angle \pm 16.7^\circ$	23.1 $\angle \pm 20.2^\circ$	7.6 $\angle \pm 52.6^\circ$	59.3 $\angle \pm 23.3^\circ$	8.60 $\angle \pm 58.7^\circ$
0.425 $\angle \mp 92.8^\circ$	0.42 $6\angle \mp 89.8^\circ$	0.43 $0\angle \mp 99.0^\circ$	0.432 $\angle \mp 96.3^\circ$	0.431 $\angle \mp 100^\circ$	0.433 $\angle \mp 97.6^\circ$
0.455 $\angle \mp 170^\circ$	0.461 $\angle \pm 171^\circ$	0.458 $\angle \mp 175^\circ$	0.466 $\angle \mp 176^\circ$	0.458 $\angle \mp 175^\circ$	0.467 $\angle \mp 177^\circ$

Figure 5.14. Impulse response of system (5.5), Example 5.8

Figure 5.15. Frequency response of system (5.5), Example 5.8.

Figure 5.16. Impulse response of the $p = 0.9$ fit, Example 5.8.

Figure 5.17. Frequency response of the $p = 0.9$ fit, Example 5.8.

Example 5.9

Consider the system

$$G(s) = \left(\frac{s^2 + 0.2s + 0.1^2 + (3\pi)^2}{s^2 + 0.1s + 0.05^2 + (2\pi)^2} \right) \left(\frac{s^2 + 1.2s + 0.6^2 + (1.8\pi)^2}{s^2 + 0.2s + 0.1^2 + (1.6\pi)^2} \right) \left(\frac{s^2 + 1.3s + 0.65^2 + (1.3\pi)^2}{s^2 + s + 0.5^2 + (0.7\pi)^2} \right) \left(\frac{9.6\pi}{s + 3.2\pi} \right) \left(\frac{s^2 + (1.4 - p0.9)s + (0.7 - p0.45)^2 + (0.9\pi)^2}{s^2 + 0.5s + 0.25^2 + (0.9\pi)^2} \right) \quad (5.6)$$

which is a modified version of test system 1. As p moves from 0 to 1, the pole-zero pair near 0.45 hz converge. Figures 5.18 and 5.19 show the response of system (5.6) for $p = 0, 0.75$, and 0.9. White noise at 30 db SNR is added to the impulse response of, (5.6) and fits are performed for $p = 0, 0.75$, and 0.9. Tables 5.6 and 5.7 summarize the identified parameters; closely-spaced terms are highlighted. As the pole-zero pair converge, the identified damping on the pole becomes too large and the estimated residue becomes too large. At $p = 0.9$, the estimated damping is nearly double the actual, and the identified residue is nearly three times the actual. Although not shown here, the estimated model very closely matches the time and frequency responses of the actual system despite the error for the closely-spaced terms.

Figure 5.18. Impulse response of system (5.6), Example 5.9.

Figure 5.19. Frequency response of system (5.6), Example 5.9.

Figure 5.18. Impulse response of system (5.6), Example 5.9.

Figure 5.19. Frequency response of system (5.6), Example 5.9.

Table 5.6. Identified poles for closely-spaced pole-zero pairs, Example 5.9.

Actual	Identified $p = 0.0$	Actual $p = 0.75$	Identified $p = 0.9$
$-1.6(2\pi)$	Not identified	Not Identified	Not Identified
$-0.5 \pm j0.35(2\pi)$	$-0.521 \pm j0.346(2\pi)$	$-0.509 \pm j0.346(2\pi)$	$-0.516 \pm j0.346(2\pi)$
$-0.25 \pm j0.45(2\pi)$	$-0.273 \pm j0.449(2\pi)$	$-0.325 \pm j0.449(2\pi)$	$-0.475 \pm j0.461(2\pi)$
$-0.10 \pm j0.80(2\pi)$	$-0.0997 \pm j0.799(2\pi)$	$-0.101 \pm j0.799(2\pi)$	$-0.101 \pm j0.799(2\pi)$
$-0.05 \pm j1.00(2\pi)$	$-0.0525 \pm j1.00(2\pi)$	$-0.0516 \pm j1.00(2\pi)$	$-0.0514 \pm j1.00(2\pi)$

Table 5.7. Identified residues for closely-spaced pole-zero pairs, Example 5.9.

Actual $p = 0.0$	Identified $p = 0.0$	Actual $p = 0.75$	Identified $p = 0.75$	Actual $p = 0.9$	Identified $p = 0.9$
4.95	Not Ident.	4.22	Not Ident.	4.28	Not Ident.
2.55 $\angle \mp 57.7^\circ$	2.54 $\angle \mp 51.5^\circ$	2.49 $\angle \mp 83.8^\circ$	2.39 $\angle \mp 79.0^\circ$	2.56 $\angle \mp 88.8^\circ$	2.47 $\angle \mp 81.7^\circ$
1.28 $\angle \mp 153^\circ$	1.45 $\angle \mp 155^\circ$	0.318 $\angle \mp 149^\circ$	0.466 $\angle \mp 157^\circ$	0.127 $\angle \mp 149^\circ$	0.367 $\angle \mp 175^\circ$
0.513 $\angle \mp 116^\circ$	0.506 $\angle \mp 115^\circ$	0.498 $\angle \mp 105^\circ$	0.493 $\angle \mp 104^\circ$	0.496 $\angle \mp 103^\circ$	0.491 $\angle \mp 102^\circ$
0.483 $\angle \pm 178^\circ$	0.491 $\angle \pm 177^\circ$	0.476 $\angle \mp 175^\circ$	0.481 $\angle \mp 176^\circ$	0.475 $\angle \mp 173^\circ$	0.480 $\angle \mp 174^\circ$

6.0 Conclusions and Recommendations

This report demonstrates the characteristics of using Prony analysis to identify linear dynamic models from system impulse response data. Special attention is paid to systems with several closely-spaced damped modes. For the most part, the characteristics are established by conducting a number of fits under controlled conditions and studying the results of these fits. Proposed future work centers around using the results in this report to further advance the Prony analysis software.

6.1 Conclusions

The main thrust of the work presented here has centered around investigating the characteristics of Prony analysis for fitting to the impulse response data of oscillatory systems. From this investigation, several "rules of thumb" can be developed for making Prony analysis an effective analysis tool.

The following is a list of general guidelines that can be used in fitting linear systems to damped impulse response data using Prony analysis. It is important to note that these are only guidelines based on experience, not hard rules.

- In sampling the system data, use a sample period at least double the Nyquist rate but not more than 10 times the Nyquist rate.
- In choosing the length of the data record, several factors must be considered: 1) at least one full cycle of the minimum-frequency oscillatory mode should be included (more data is preferred); 2) if data is collected in a noisy environment, an excessively long data record should be avoided (this is somewhat a judgment, but the record should be short enough to keep the SNR above 20 db); 3) if a double-precision root finder is employed, the number of data points should not exceed 250 (a safer limit is 100); and 4) for a quad-precision root finder, the limits are 500 and 200.
- In most cases, one should not expect to accurately identify stable real poles with a magnitude greater than $1/(3T)$, where T is the sample period.
- In fitting to the data, the following algorithm choices are likely to give the best results: 1) use the covariance method in the forward direction to formulate the LP problem; 2) there are presently no obvious differences between the LP solution algorithms available in PRSPAK, but SVD currently seems to be a safe first choice; 3) if possible, use the quad-precision root finder; and 4) make the order of the Vandermonde problem the same as the LP problem.
- In choosing the order of the LP fit, use $N/3$ to $N/2$, as long as it does not exceed 50 for the double-precision root finder or 100 for the quad.
- Accurate fits are likely if the SNR is 20 db or greater. If the noise is highly colored, poor fits are likely for poles and residues in the bandwidth of the colored noise.
- If closely-spaced poles are identified, especially with similar imaginary terms, the error

bounds for these terms are likely to be large, even if the fit is accurate graphically. This may be an indication to combine the modes as one composite term.

6.2 Recommended Future Work

The work presented here was conducted as part of a first phase in the development of a Power System Identification (PSI) Toolbox. Several extensions of this work are proposed with the objective being the further development of Prony analysis programs and methods for eventual inclusion in the toolbox.

A practical vision of the analysis programs in the Toolbox is that they exist at two levels. The first level would be similar to the commonly used LINPACK (Dongarra et al. 1979) or Numerical Recipes (Press et al. 1990) subroutines. Each routine would consist of standard FORTRAN coding with non-platform-dependent input options and no graphical options. The second level would consist of a few "highly intelligent" programs developed for specific platforms with appropriate graphical and user-friendly interfaces. The core analysis routines for the second level would consist of the routines from the first.

Using the first level of routines, analysis programs could be incorporated into other analysis programs (for example, data collection software). For Prony analysis, the subroutine PRSPAK would be the primary analysis routine. Other possible routines would be ORDER and TRANSFUN employed in IPRONYID (see Appendix C for current versions of these subroutines), and many of the routines called by subroutine PRGEN in SIGPAKZ.

Proposed future work for the next phase focuses on forming the level one routines for the Toolbox and further developing the Prony analysis codes. Future proposed work includes 1) updating and overhauling the current version of subroutine PRSPAK; 2) implementing a formal revision system for all routines in SIGPAKZ and IPRONYID for developing modifications; 3) incorporating the transfer function identification routine TRANSFUN into SIGPAKZ; 3) incorporating "local intelligence" into SIGPAKZ and IPRONYID based on results presented in this report; 4) further investigating new options for solving the Prony analysis problem and processing results; and 5) investigating the use of combined time-domain (Prony analysis) and frequency-domain methods to identify transfer functions.

6.2.1 Overhaul PRSPAK

As discussed in Section 3, the current version of PRSPAK is a subroutine developed from the program DTRANSIENTS. In its current form, it contains coding developed at the University of Colorado at Boulder and the Bonneville Power Administration. As it is used in IPRONYID and SIGPAKZ, several options are not used and a few errors exist in the routine. The proposed overhaul primarily involves making PRSPAK a clean level-one subroutine. The objective is make PRSPAK an efficient routine that is as close to standard FORTRAN as possible. Modifications will be made to 1) correct errors; 2) remove all platform-dependent graphing options; 3) remove all timing calculations; 4) incorporate new interactive and batch options; and 5) do a general variable clean up. The goals are to make PRSPAK a flexible subroutine that can easily be incorporated into many different standalone programs, both custom and commercial, and to make implementation of new algorithms as simple as possible.

To date, the following errors have been encountered in the version of PRSPAK obtained from BPA:

- There is no check to make sure NSIZE is not exceeded.
- In solving the LP problem using standard QR or TLS, PRSPAK jumps to statement 390, an IF block checking for an error in the fast QR algorithm. In some circumstances it is possible that PRSPAK could use the fast QR algorithm when the TLS or standard QR is desired. To fix this change, the GOTO 390 statements after the TLS and standard QR to GOTO 400.
- Fix comments in the code (e.g., the comment for the section of code that searches for the strongest mode inside the interval [FTRIML,FTRIMH] states that the interval outside [FTRIML,FTRIMH] is searched). Also, the comment on line 812 should read NNHAT in place of NNFIT, and several main header comments are outdated.
- There is no return statement in PRSPAK (it should be after the section of code starting at statement 8800).

The current version of PRSPAK has interactive graphing options that are supported on only specific platforms. Also, some of the routines called by PRSPAK (such as LSTQR) have plotting options. These plotting options are memory- and time-consuming; also, because the plotting options are platform-dependent, porting the code to different platforms is very difficult. For example, when PRSPAK was ported to a SUN workstation at PNL, the plotting options had to be disabled. Therefore, it is proposed that all plotting options be removed from PRSPAK. Using the interactive and batching options proposed below, all plotting options could still be performed, but outside PRSPAK.

The current BPA version of PRSPAK has an interactive option and a batch option. With the batch option, key variables are output to a data file. With PRSPAK2 version 1.1.2.1 described in Section 3, a second batch option is added to PRSPAK. This option is the same as the first batch option, but no variables are written to an output file. This allows PRSPAK to be a standalone subroutine with all inputting and outputting performed in the subroutine call.

To make PRSPAK as generic as possible, it is proposed that new interactive and batching options be developed. Basically the same interactive option currently used in PRSPAK will be employed. All inputting is performed in subroutines INENTER and LGENTER. Plotting and special read/write options can be incorporated into subroutines INENTER and LGENTER. Future versions of INENTER and LGENTER could range from platform-independent generic read routines to user-friendly platform dependent routines. The proposed batching option is similar to the current form, but with all outputting to data files removed. In place of the outputting, extensive use will be made of the array MRETR (flags for Prony return mode) to indicate the status of the different Prony analysis steps. Then all outputting to data files can be done outside PRSPAK.

The current version of PRSPAK uses the array MSEC to track the CPU timing of different calculations. Because CPU time calculation is platform-dependent, this option is not directly portable. Also, with the speed of modern platforms, the computation time of the algorithms employed in PRSPAK is relatively trivial. For these reasons, it is proposed that the CPU time calculation options

be removed from PRSPAK. If one desires to track computation time, many of the modern compilers and debugging programs allow one to do so.

The final steps in overhauling PRSPAK will be to develop a document that describes the routine in detail. This will later become a chapter in an extensive manual discussing all the level one subroutines.

6.2.2 Implement Revision Control System

Currently, no revision control system is employed with the BPA-based Prony analysis programs. In the work conducted for this report, an initial revision system was implemented using the public domain Revision Control System (RCS) (Tichy 1985). With this system, modifications and version numbers are automatically tracked. Several options are possible with RCS for customizing to the users' needs.

Because UC is currently developing new Prony-related algorithms that may be implemented into the current version of SIGPAKZ and IPRONYID, it is proposed that a set coding standard be adopted for developing new routines. These standards are to be developed in conjunction with UC and BPA and based on an industry standard (such as IEEE). Such a system will ensure timely, efficient, and accurate incorporation of new algorithms into the analysis software.

It is proposed that PNL be responsible for assigning and tracking version numbers. Modifications to PRSPAK will be conducted in conjunction with UC to ensure that fitting algorithms are properly incorporated. The general idea is to have the routine PRSPAK and the main calling routine of the UC program TRANSIENTS be parallel routines in that new options incorporated into TRANSIENTS can easily be implemented into PRSPAK, or vice versa.

6.2.3 Incorporate Transfer Function Identification in SIGPAKZ

The current version of SIGPAKZ allows transfer function terms to be calculated only from a single pulse input. Several extensions have been developed that allow much more general inputs to be used. A subroutine called TRANFUN has been developed at PNL for use with IPRONYID that allows the identification of transfer function terms for a general input involving a series of square-wave pulses. It is proposed that this subroutine be incorporated into SIGPAKZ and be called from the subroutine PRSGEN. One possible way to do this is to incorporate the calculations in TRANFUN into the subroutines PRSMOD1 and 2.

6.2.4 Develop "Local intelligence" in SIGPAKZ and IPRONYID

The results from the tests discussed in this report will be used to develop "intelligent" decision and calculation options into PRSGEN and PRSPAK. This includes data-dependent defaulting and possibly iterative calculation options.

6.2.5 Investigate New Options

Areas that merit further investigation before being implemented into SIGPAKZ include model ordering and reduction methods; composite modes; error bounds on parameters; eigenanalysis for LP

polynomial rooting, as well as other rooting algorithms; use of LAPACK (Anderson et al. 1992) routines in place of LINPACK ones; and investigation of alternative LP solution methods discussed in the literature review. Investigation of many of these new options will be coordinated with or conducted at CU based on BPA and PNL discretion.

The current version of SIGPAKZ outputs models in the order of lowest frequency to highest frequency. No effort is given to re-order the terms from most important to least important, and it is often impossible to distinguish between terms that are true system modes and modes due to noise effects. The model order reduction method recently developed at PNL has proven to be very valuable in solving this problem (a modified version of the ordering algorithm is contained in IPRONYID). Only one case seems to cause sensitivities, that is the one of very closely-spaced poles. It is proposed that this algorithm be tested and, if feasible, implemented in SIGPAKZ.

The composite mode method developed at UC is used to identify models with repeated roots. The method primarily involves combining modes that are closely spaced. Error bound algorithms for identified parameters are also being developed at UC using Cramer-Rao bound theory (McWhorter and Scharf 1991). It is proposed that these methods be tested for use in PRSPAK. This testing will be conducted in close association with UC.

Currently, PRSPAK has only one algorithm for rooting the LP polynomial. Although this algorithm has proven to give good results in many cases, other options are available. These include eigenanalysis. It is proposed that other rooting methods, including eigenanalysis, be compared and tested.

LAPACK (Anderson et al. 1992) is the next generation of LINPACK developed by the National Science Foundation. It represents significant improvements in computational efficiency and numerical robustness. It is proposed (and highly recommended) that LAPACK QR and SVD routines be implemented in place of the current LINPACK ones used in PRSPAK.

The last new option that merits investigation involves solution methods for the LP problems contained in Kay and Marple (1987); Marple (1980); Minami (1986); and Cruz (1986). Currently, these methods are not contained in PRSPAK, but show merit based on the literature.

7.0 References

- Akiake, H. 1969. "Fitting Autoregressive Models for Prediction." *Mathematical Review* 21:243-247.
- Anderson, E., Z. Bai, C. Bischof, J. Demmel, J. Dongarra, J. Du Croz, A. Greenbaum, S. Hammarling, A. Mckenney, S. Ostrouchov, and D. Sorensen. 1992. *LAPACK User's Guide*. Society for Industrial and Applied Mathematics, Philadelphia.
- Barone, P. 1988. "Some Practical Remarks on the Extended Prony's Method of Spectrum Analysis." *Proceedings of the IEEE* 76(3):284-285.
- Barone, P., L. Guidoni, E. Massaro, and V. Viti. 1987. "Prony-Burg Method for NMR Spectral Analysis." *Journal of Magnetic Resonance* 73:23-33.
- Cruz, J. R. 1986. "Spectral Analysis Using the QD Algorithm." In *Proceedings of the IEEE International Conference on Acoustics, Speech, and Signal Processing*, vol. 2, pp. 1345-1348. April 1986, Tokyo, Japan. Institute of Electrical and Electronics Engineers, Piscataway, New Jersey.
- Demeure, C. J. 1989. "Fast QR Factorization of Vandermonde Matrices." *Journal of Linear Algebra and Its Applications* 124:165-194.
- Demeure, C. J., and L. L. Scharf. 1990. "Sliding Windows and Lattice Algorithms for Computing QR Factors in the Least Squares Theory of Linear Prediction." *IEEE Transactions on Acoustics, Speech, and Signal Processing* ASSP-38(4):721-725.
- Friddell, T. H., J. A. Ritcey, and D. Haynor. 1989. "Data Pre-conditioning for Improved Performance of the Prony Method." In *Proceedings of the 23rd Asilomar Conference on Signals, Systems, and Computers*, pp. 360-364. October 1989, Pacific Grove, California. Institute of Electrical and Electronics Engineers, Piscataway, New Jersey.
- Hauer, J. F., C. J. Demeure, and L. L. Scharf. 1990. "Initial Results in Prony Analysis of Power System Response Signals." *IEEE Transactions on Power Systems*. 5(1):80-89.
- Hauer, J. F. 1991. "The Use of Prony Analysis to Determine Modal Content and Equivalent Models for Measured Power System Response." In *IEEE Symposium on Eigenanalysis and Frequency Domain Methods for System Dynamic Performance*, pp. 105-115. Publication 90TH0292-3-PWR, Institute of Electrical and Electronics Engineers, Piscataway, New Jersey.
- Hauer, J. F., and C. W. Taylor. 1990. *Feedback Control and Frequency Domain analysis of Large Electric Power Systems, Vol. 1: Seminar Workbook*. Carson Taylor Seminars, Portland, Oregon.
- Dongarra, J. J., C. B. Moler, J. R. Bunch, and G. W. Stewart. 1979. *LINPACK User's Guide*. Society for Industrial and Applied Mathematics, Philadelphia.
- Hildebrand, F. B. 1956. *Introduction to Numerical Analysis*. McGraw Hill, New York.

- Hocking, R. R., and R. N. Leslie. 1967. "Selection of the Best Subset in Regression Analysis." *Technometrics* 9(4):531-540.
- Hoxha, F., C. Lambert, and J. Noailles. 1988. "Experiments in Concurrently Computing Polynomial Roots." In *Proceedings of the 4th European Signal Processing Conference*, pp. 659-662. September 1988, Grenoble, France. Elsevier Science Publishers B. V., North-Holland.
- Jenkins, M. A. 1975. "Algorithm 493, Zeros of a Real Polynomial." *ACM Transactions on Mathematical Software* 1(2):178-189.
- Jenkins, M. A., and J. F. Traub. 1970. "A Three Stage Algorithm for Real Polynomials Using Quadratic Iteration." *SIAM Journal on Numerical Analysis* 7(4):545-566.
- Kay, S. M., and S. L. Marple. 1981. "Spectrum Analysis -- A Modern Perspective." *Proceedings of the IEEE* 69:1380-1419.
- Kumaresan, R., and D. W. Tufts. 1982. "Estimating the Parameters of Exponentially Damped Sinusoids and Pole-Zero Modeling in Noise." *IEEE Trans. on Acoustics, Speech, and Signal Processing* ASSP-30(6):833-840.
- Kumaresan, R., D. W. Tufts, and L. L. Scharf. 1984. "A Prony Method for Noisy Data: Choosing the Signal Components and Selecting the Order in Exponential Signal Models." *Proceedings of the IEEE* 72(2):230-233.
- Lambert, C., and F. Castanie. 1988. "An Adaptive Prony Algorithm." In *Proceedings of the 4th European Signal Processing Conference*, pp. 571-574. September 1988, Grenoble, France. Elsevier Science Publishers B. V., North-Holland.
- Lancaster, P., and M. Tismenetsky. 1985. *The Theory of Matrices*. Academic Press, New York.
- Madsen, K. 1973. "A Root-Finding Algorithm Based on Newton's Method." *BIT* 13:71-75.
- Marple, S. L. 1989. "A Tutorial Overview of Modern Spectral Estimation." In *Proceedings of the International Conference on Acoustics, Speech, and Signal Processing*, pp. 2152-2157. Glasgow, Scotland. Institute of Electrical and Electronics Engineers, Piscataway, New Jersey.
- Marple, L. 1980. "A New Autoregressive Spectrum Analysis Algorithm." *IEEE Trans. on Acoustics, Speech, and Signal Processing* ASSP-28(4):441-454.
- McWhorter, T., and L. L. Scharf. 1991. *Cramer-Rao Bounds for Modal Analysis*. Technical Report DSP-504, Department of Electrical Engineering, University of Colorado, Boulder.
- Minami, K., N. Schlumberger, and S. Kawata. 1986. "Prony's Method Based on Eigenanalysis and Overdetermined System Approach." In *Proceedings of the IEEE International Conference on Acoustics, Speech, and Signal Processing (ICASSP)*, vol. 2, pp.1393-1396. April 1986, Tokyo, Japan. Institute of Electrical and Electronics Engineers, Piscataway, New Jersey.

Mueller, D. E. 1956. "A Method for Solving Algebraic Equations Using an Automatic Computer." *Mathematical Tables Aids Computation* 10:208-215.

Pierre, D. A., J. R. Smith, D. J. Trudnowski, and J. W. Pierre. 1992. "General Formulation of a Prony Based Method for Simultaneous Identification of Transfer Functions and Initial Conditions." In *Proceedings of the 31st IEEE Conference on Decision and Control*, (To be published in December 1992). Institute of Electrical and Electronics Engineers, Piscataway, New Jersey.

Pierre, D. A., D. J. Trudnowski, and J. F. Hauer. 1992. "Identifying Linear Reduced-Order Models for Systems with Arbitrary Initial Conditions Using Prony Signal Analysis." *IEEE Transactions on Automatic Control* 37(6):831-835.

Poggio, A. J., M. L. Van Blaricum, E. K. Miller, and R. Mittra. 1978. "Evaluation of a Processing Technique for Transient Data." *IEEE Trans. on Antennas and Propagation* AP-26(1):165-173.

Porat, B., and B. Friedlander. 1986. "A Modification of the Kumaresan-Tufts Method for Estimating Rational Impulse Responses." *IEEE Trans. on Acoustics, Speech, and Signal Processing* ASSP-34(5):1336-1338.

Press, W. H., B. P. Flannery, S. A. Teukolsky, and W. T. Vetterling. 1990. *Numerical Recipes, The Art of Scientific Computing*. Cambridge University Press, New York.

Prony, B. de. 1795. "Essai Expérimental et Analytique: sur les Lois de la Dilatabilité de Fluides Élastiques et Sur Celles de la Force Expansive de la Vapeur de l'Eau et de la Vapeur de l'Alcool, à Différentes Températures." *Journal de l'École Polytechnique* 1(2):24-76.

Rao, D.V.B. 1986a. "An Explanation of the Limitation Observed in the Kumaresan-Prony Algorithm." *IEEE Trans. on Acoustics, Speech, and Signal Processing* ASSP-34(5):1338-1340.

Rao, D.V.B. 1986b. "An Analysis of the Kumaresan-Prony Method." In *Proceedings of the 20th Asilomar Conference on Signals, Systems, and Computers*, pp. 467-471. November 1986, Pacific Grove, California. Institute of Electrical and Electronics Engineers, Piscataway, New Jersey.

Rautenberg, T., D. J. Gingras, and J. F. Bohme. 1988. "Comparison of Some Real Coefficients Polynomial Zero-Finder Methods with Respect to Applications in Spectrum Estimation." In *Proceedings of the 4th European Signal Processing Conference*, pp. 187-190. September 1988, Grenoble, France. Elsevier Science Publishers B. V., North-Holland.

Rutishauser, H. 1957. *Der Q-D Algorithmus*. Birkhauser, Basel.

Scharf, L. L. 1991. *Statistical Signal Processing: Detection, Estimation, and Time Series Analysis*. Addison-Wesley Publishing Company, New York.

Steiglitz, K., and L. E. McBride. 1965. "A Technique for the Identification of Linear Systems." *IEEE Trans. on Automatic Control* AC-10:461-464.

Steiglitz, K. 1977. "On the Simultaneous Estimation of Poles and Zeros in Speech Analysis." *IEEE Trans. on Acoustics, Speech, and Signal Processing* ASSP-25(3):229-234.

Tichy, W. F. 1985. "RCS -- A System for Version Control." *Software -- Practice & Experience* 15(7):637-654.

Trudnowski, D. J., J. R. Smith, T. A. Short, and D. A. Pierre. 1991. "An Application of Prony Methods in PSS Design for Multimachine Systems." *IEEE Transactions on Power Systems* 6(2):118-126.

Tufts, D. W., and R. Kumaresan. 1982a. "Singular Value Decomposition and Improved Frequency Estimation Using Linear Prediction." *IEEE Trans. on Acoustics, Speech, and Signal Processing* ASSP-30(4):671-675.

Tufts, D. W., and R. Kumaresan. 1982b. "Estimation of Frequencies of Multiple Sinusoids: Making Linear Prediction Perform Like Maximum Likelihood." *Proceedings of the IEEE* 70(9):975-989.

Van Blaricum, M. L., and R. Mittra. 1975. "A Technique for Extracting the Poles and Residues of a System Directly from Its Transient Response." *IEEE Trans. on Antennas and Propagation* AP-23(6):777-781.

Van Blaricum, M. L., and R. Mittra. 1978. "Problems and Solutions Associated with Prony's Method for Processing Transient Data." *IEEE Trans. on Antennas and Propagation* AP-26(1):174-182.

West, B. J. 1990. "The Noise in Natural Phenomena." *American Scientist* 7:40-45.

Appendix A

PRSPAK2 Version 1.1.2.1

Appendix A

PRSPAK2 Version 1.1.2.1

```

C *** PRONY SUBROUTINE II [JFH VERSION 08/02/90]
C
C $Id: prspak2.f,v 1.1.2.1 1992/09/09 21:21:12 d3f011 Exp d3f011 $
C
C It consists of :
C   - Data acquisition (values and parameters)
C   - Model specification
C   - Linear prediction modelling with rank reduction
C   - Root the annihilator polynomial for the modes
C   - Subset selection with amplitude and initial phase computation
C   - Signal reconstruction
C   - ARMA model computation
C
C With the possible following graphic plots :
C   - Eigenvalues plot
C   - Linear Prediction coefficients plot
C   - Roots plot (or in tabular mode)
C   - Modes tabular plot
C   - ARMA coefficients plot
C   - Signal plots
C
C*****C
C Signal description variables :
C   XSIG   : Data sequence (0,...,NNHAT-1)
C   NNFIT   : NUMBER OF DATA VALUES FOR FITTING (NOT TO EXCEED NTAILLE)
C   NINIT   : Initial data sample number.
C   TSTEP   : Sampling frequency (in seconds)
C
C Model description variables :
C   LPOCON  : Linear prediction order (must be less than NSIZE-1)
C   LPMCON  : Linear prediction method control
C             = 1 CORRELATION
C             = 2 PRE-WINDOWED
C             = 3 COVARIANCE
C             = 4 POST-WINDOWED
C   FBCON   : Forward-backward control
C             = 1 => Forward
C             = 2 => " -Backward
C             = 3 => Backward
C   LPACON  : Linear prediction algorithm control
C             = 1 Rank reduction via SVD
C             = 2 Rank reduction via QR
C             = 3 Total least squares
C             = 4 Fast algorithm
C   VDMCON  : Vandermonde system solver method
C             = 1 Linpack SVD (this is actually QR)
C             = 2 Fast algorithm using real arithmetic
C             = 3 Fast algorithm using complex arithmetic
C   PIRCON  : Forced limit on retained model order
C             (not to exceed LPOCON)
C   QCON    : Number of desired modes
C             (not to exceed DMODES)
C
C Resulting variables :
C   DMATSV  : Vector of singular values
C             [1,...,LPOCON]
C   A       : Linear prediction polynomial coefficients
C             [1,...,LPOCON]
C             A(0)=1.0
C   DMODES  : Total number of modes (usually around LPOCON/2)
C   ROOTR   : Vector of real part of the roots of A(z)
C             [1,...,DMODES]
C   ROOTI   : Vector of imaginary part of the roots of A(z)
C             [1,...,DMODES]

```

```

C      MAG      : Vector of magnitude of the roots of A(z)
C                [1,...,DMODES]
C      PHA      : Vector of phase of the roots of A(z)
C                [1,...,DMODES]
C
C Description of the selected modes :
C      MAGOPT   : Vector of damping factors
C                [1,...,QCON]
C      PHAOPT   : Vector of frequencies
C                [1,...,QCON]
C      AMPOPT   : Vector of amplitudes
C                [1,...,QCON]
C      PHIOPT   : Vector of initial phases
C                [1,...,QCON]
C
C DESCRIPTION OF THE INPUT/OUTPUT VARIABLES
C      NNHAT    : NUMBER OF DATA SAMPLES FOR COMPARISON OF MODEL RESULTS
C                AGAINST STORED SIGNAL (MAY EXCEED NNFIT)
C
C      FTRIMH   :
C      FTRIML   :
C      TRIMLPM  : (MOVE)
C      LUIN     : LOGICAL UNIT FOR INPUT DATA
C      LUOUT    : LOGICAL UNIT FOR STANDARD OUTPUT
C      LURES    : LOGICAL UNIT FOR ACCESSORY RESULTS
C      BATCH    : FLAG FOR BATCH PROCESSING CASE
C      STORE    : FLAG FOR SAVING ACCESSORY RESULTS ON LURES
C      TRACK    : FLAG FOR PROCESS TRACKING
C      MRETR    : INTEGER FLAG FOR PRONY RETURN MODE
C
C      SUBROUTINE PRSPAK3 (DNAME,RNAME,XSIG,TSTEP,NFSAVE,NSTART
C      *,QCON,SNR,SHAT,DAMP,FRQHZ,RELMAG,PHASE,AMPOPT,PHIOPT
C      *,LPOSAVE,LPMSAVE,FBSAVE,LPASAVE,VDMSAVE,PIRSAVE,QSAVE,NHSAVE
C      *,TRIMLPM,FTRIMH,FTRIML
C      *,LUIN,LUOUT,LURES,BATCH,STORE,TRACK,MRETR)
C      IMPLICIT NONE
C      INCLUDE 'dimpars.cmn'
C      CHARACTER*20 DNAME,RNAME
C      REAL*8 XSIG(0:*),SHAT(0:*),SNR,SIGEN
C      REAL*4 TSTEP
C      REAL*8 DAMP(1:*),FRQHZ(1:*),RELMAG(1:*),PHASE(1:*),AMPREF,FAC
C      REAL*8 DAMPBB(1:NSIZE),FRQHZBB(1:NSIZE)
C      REAL*8 FTRIMH,FTRIML,TRIMLPM,ZTRIMH,ZTRIML,ZZTRIM
C      INTEGER*4 NNHAT,MRETR
C      INTEGER MRETC,MRETF
C      INTEGER*4 NFSAVE,NSTART,NHSAVE
C      INTEGER*4 LPOSAVE,LPMSAVE,FBSAVE,LPASAVE,PIRSAVE,QSAVE,DQPSET
C      INTEGER*4 LPOMAX
C      INTEGER*4 BATCH
C      LOGICAL STORE,TRACK,TRACKO,DONUM
C      LOGICAL PIRADJ
C      INTEGER ILAST,QTRIM,SRULE
C      INTEGER LUIN,LUOUT,LURES,PIRCON,I,ISEL,NNFIT,FBCON
C      INTEGER LPOCON,QCON,DMODES,DMREAL,DMCMPX,N1,J,LPMCON,K,NINIT,INFO
C      INTEGER LPACON,VDMCON,VDMSAVE
C      INTEGER IC(1:NSIZE),AADEG,BBDEG,NRMODES
C      INTEGER*4 ICOUNT,IQ,IFAIL
C      LOGICAL FAIL,DOPLLOT
C      REAL*8 SIGDIF(0:NTAIL-1)
C      REAL*8 MAT(1:NTAIL,1:NSIZE),WORK(1:NTAIL),SUM
C      REAL*8 DENERGY,ALPHA,PI,DEG,DEGI,EPS1,HZFAC
C      REAL*8 U(1:NTAIL,1:NSIZE),V(1:NSIZE,1:NSIZE)
C      REAL*8 A(0:NSIZE-1),B(1:NSIZE),C(1:NTAIL),DMATSV(1:NSIZE)
C      REAL*8 OPR(1:NSIZE),ZEROR(1:NSIZE),ZEROI(1:NSIZE)
C      REAL*8 ROOTR(1:NSIZE),ROOTI(1:NSIZE),MAG(1:NSIZE),PHA(1:NSIZE)
C      REAL*8 AMP(1:NSIZE),PHI(1:NSIZE),DERR,DMINERR
C      REAL*8 AMPOPT(1:NSIZE),PHIOPT(1:NSIZE)
C      REAL*8 MAGOPT(1:NSIZE),PHAOPT(1:NSIZE)
C      REAL*8 AA(0:NSIZE-1),BB(0:NSIZE-1)
C      REAL*8 ROOTAAR(1:NSIZE),ROOTAAI(1:NSIZE),MAGBB(1:NSIZE)
C      REAL*8 ROOTBBR(1:NSIZE),ROOTBBI(1:NSIZE),PHABB(1:NSIZE)
C      CHARACTER*20 LPMTEXT(10),FBTEXT(10),LPATEXT(10),VDMTEXT(10)
C
C      *** NOTE: THIS VERSION OF PRSPAK2 AND ITS SUBORDINATE ROUTINES USES
C      A MIXTURE OF I*2 AND I*4 VARIABLES. LATER VERSIONS SHOULD
C      USE I*4 EXCLUSIVELY, OR AS FAR AS POSSIBLE. LOGICAL
C      VARIABLES HAVE A SIMILAR PROBLEM. [JFH]

```

```

C *** TIMING VARIABLES
REAL*8 RZERO, TOPAK, T1PAK, TOSUB, T1SUB
INTEGER*4 MSEC(20)
C
C *** MATHEMATICAL CONSTANTS
INTEGER*4 IZERO, IONE
C
C ** SET BATCH CASE: IF BATCH=0, NO BATCH; IF BATCH=1, BATCH WITH
C *** NO OUTPUT; IF BATCH=2, BATCH FULL OUTPUT
IF (BATCH.EQ.1) TRACK=.FALSE.
C
IF (BATCH.NE.1) WRITE (*,9900)
IF (BATCH.GT.1) WRITE (LUOUT,9900)
C
C *** SET PRECISION CONTROLS
[LATER VERSIONS WILL ENTER THESE AS SPECIAL PROCESSING CONTROLS]
DQPSET=0 ! ROOTING VIA 'QPOLY'
C *** DQPSET=1 ! ROOTING VIA 'DPOLY'
C
C *** CLEAR CLOCK TIMES
DO I=1,20
MSEC(I)=0
END DO
RZERO=0.0
CALL CPUTIME (TOPAK, IZERO)
C
C *** SET MATHEMATICAL CONSTANTS
IZERO=0
IONE=1
PI=4.DO*DATAN(1.DO)
DEG=180.DO/PI
DEGI=1.DO/DEG
HZFAC=1./(360.*TSTEP)
EPS1=1.D-8
C
C *** CHECK STORAGE AND DISPLAY CONTROLS
[LATER VERSIONS WILL ENTER THESE AS SPECIAL PROCESSING CONTROLS]
C
STORE=LURES.GT.0
DONUM=.FALSE.
IF (BATCH.EQ.0) DONUM=.TRUE.
TRACK0=TRACK
C *** TRACK=.TRUE.
C
C *** SET INTEGER CONTROLS
NNFIT=NFSAVE
IF (NNFIT.LE.0) THEN
IF (BATCH.GT.1) WRITE (LUOUT,9940) NNFIT
IF (BATCH.NE.1) WRITE (LUOUT,9940) NNFIT
GO TO 8000
END IF
NINIT=NSTART
LPOCON=LPOSAVE
LPOMAX=NNFIT/2
LPACON=LPASAVE
VDMCON=VDMSAVE
C
C *** RESTART POINT FOR NEW CHOICE OF ALGORITHM
100 IF (LPOCON.LT.1) THEN
LPOCON=11*LPOMAX/12
IF (BATCH.GT.0) THEN
IF (STORE) WRITE (LURES,9060) LPOCON
IF (BATCH.GT.1) WRITE (LUOUT,9060) LPOCON
END IF
END IF
IF (LPOCON.GT.LPOMAX) THEN
LPOCON=11*LPOMAX/12
IF (BATCH.GT.0) THEN
IF (STORE) WRITE (LURES,9062) LPOMAX, LPOCON
IF (BATCH.GT.1) WRITE (LUOUT,9062) LPOMAX, LPOCON
END IF
END IF
IF (LPOCON.GT.NSIZE) THEN
LPOCON=NSIZE
IF (BATCH.GT.0) THEN
IF (STORE) WRITE (LURES,9064) NSIZE, LPOCON
IF (BATCH.GT.1) WRITE (LUOUT,9064) NSIZE, LPOCON
END IF

```

```

END IF
IF (LPOMAX.GT.NSIZE) LPOMAX=NSIZE
LPMCON=LPMSAVE
IF (LPMCON.LT.1.OR.LPMCON.GT.4) LPMCON=3
FBCON=FBSAVE
IF (FBCON.LT.1.OR.FBCON.GT.3) FBCON=3
PIRCON=PIRSAVE
IF (PIRCON.LT.1.OR.PIRCON.GT.LPOCON) PIRCON=15*LPOCON/16
QCON=QSAVE
NNHAT=NNHSAVE
IF (NNHAT.LT.NNFIT) NNHAT=NNFIT
QTRIM=0
C
C *** DIAGNOSTICS
IF (BATCH.GT.1) THEN
  WRITE (LUOUT,9910) NNFIT,NINIT,QCON,LPOCON,LPMCON
  * ,FBCON,LPACON,VDMCON,PIRCON,MRETR
  WRITE (LUOUT,9912) TSTEP
END IF
IF (STORE) THEN
  WRITE (LURES,9910) NNFIT,NINIT,QCON,LPOCON,LPMCON
  * ,FBCON,LPACON,VDMCON,PIRCON,MRETR
  WRITE (LURES,9912) TSTEP
END IF
C
C *** TEST FOR NULL SIGNAL
SIGEN=DENERGY(XSIG,NNFIT)
IF (BATCH.NE.1) WRITE (*,9914) SIGEN
IF (BATCH.GT.1) WRITE (LUOUT,9914) SIGEN
IF (STORE) WRITE (LURES,9914) SIGEN
IF (SIGEN.LT.1.D-12) THEN
  IF (BATCH.NE.1) WRITE (*,9920) SIGEN
  IF (BATCH.GT.1) WRITE (LUOUT,9920) SIGEN
  DMODES=0
  GO TO 8000
END IF
C
C *** SIGNAL DISPLAY
IF (TRACK.AND.STORE) THEN
  WRITE (LURES,9100)
  DO K=0,NNFIT-1
    WRITE (LURES,9622) K,XSIG(K)
  END DO
END IF
C
C *** SET TEXT STRINGS
LPMTEXT(1)='CORRELATION'
LPMTEXT(2)='PRE-WINDOWED'
LPMTEXT(3)='COVARIANCE'
LPMTEXT(4)='POST-WINDOWED'
FBTEXT(1)='FORWARD'
FBTEXT(2)='FORWARD-BACKWARD'
FBTEXT(3)='BACKWARD'
LPATEXT(1)='SVD'
LPATEXT(2)='QR'
LPATEXT(3)='TLS'
LPATEXT(4)='FAST'
VDMTEXT(1)='QR'
VDMTEXT(2)='FAST REAL'
VDMTEXT(3)='FAST COMPLEX'
C
IF (BATCH.GT.0) THEN
  IF (BATCH.GT.1) WRITE (*,9120) LPOCON
  IF (BATCH.GT.1) WRITE (*,9130) LPMCON,LPMTEXT(LPMCON)
  IF (BATCH.GT.1) WRITE (LUOUT,9120) LPOCON
  IF (BATCH.GT.1) WRITE (LUOUT,9130) LPMCON,LPMTEXT(LPMCON)
  IF (STORE) THEN
    WRITE (LURES,9120) LPOCON
    WRITE (LURES,9130) LPMCON,LPMTEXT(LPMCON)
  END IF
  GO TO 280
END IF
C
C *** ASK FOR THE LINEAR PREDICTION ORDER
240 CALL INENTER (LUOUT,LUIN,'Linear prediction order '
  * ,LPOCON,LPOCON)
IF (LPOCON.LE.0.OR.LPOCON.GE.LPOMAX) THEN

```

```

        WRITE (LUOUT,9180) LPOMAX
        GO TO 240
    END IF
    LPOSAVE=LPOCON
C
C *** ASK FOR LINEAR PREDICTION METHOD
    WRITE (LUOUT,*) 'LINEAR PREDICTION METHOD:'
    DO I=1,4
        WRITE (LUOUT,9110) LPMTEXT(I),I
    END DO
    WRITE(LUOUT,*) '
    WRITE(LUOUT,*) '
        RESTART = 98'
        TERMINATE = 99'
260 CALL INENTER (LUOUT,LUIN,'Your choice ',LPMCON,LPMCON)
    IF (LPMCON.EQ.98) GO TO 7000
    IF (LPMCON.EQ.99) GO TO 8000
    IF (LPMCON.LT.1.OR.LPMCON.GT.4) GO TO 260
    LPMSAVE=LPMCON
    WRITE (LUOUT,9110) LPMTEXT(LPMCON),LPMCON
    IF (STORE) THEN
        WRITE (LURES,9110) LPMTEXT(LPMCON),LPMCON
    END IF
C
280 IF (BATCH.GT.0) THEN
    IF (BATCH.GT.1) WRITE (*,9140) FBCON,FBTEXT(FBCON)
    IF (BATCH.GT.1) WRITE (LUOUT,9140) FBCON,FBTEXT(FBCON)
    IF (STORE) WRITE (LURES,9140) FBCON,FBTEXT(FBCON)
    GO TO 305
END IF
C
C *** ASK FOR PREDICTION TYPE
    WRITE (LUOUT,*) ' FORWARD/BACKWARD LOGIC : '
    DO I=1,3
        WRITE (LUOUT,9110) FBTEXT(I), I
    END DO
    WRITE(LUOUT,*) '
    WRITE(LUOUT,*) '
        RESTART = 98'
        TERMINATE = 99'
300 CALL INENTER (LUOUT,LUIN,'Your choice ',FBCON,FBCON)
    IF (FBCON.EQ.98) GO TO 7000
    IF (FBCON.EQ.99) GO TO 8000
    IF (FBCON.LT.1.OR.FBCON.GT.3) GO TO 300
    FBSAVE=FBCON
    WRITE (LUOUT,9110) FBTEXT(FBCON),FBCON
    IF (STORE) THEN
        WRITE (LURES,9110) FBTEXT(FBCON),FBCON
    END IF
C
305 IF (BATCH.GT.0) THEN
    IF (BATCH.GT.1) WRITE (*,9150) LPACON,LPATEXT(LPACON)
    IF (BATCH.GT.1) WRITE (LUOUT,9150) LPACON,LPATEXT(LPACON)
    IF (STORE) WRITE (LURES,9150) LPACON,LPATEXT(LPACON)
    GO TO 320
END IF
C
C *** ASK FOR LINEAR PREDICTION ALGORITHM
    WRITE (LUOUT,*) 'LINEAR PREDICTION ALGORITHM:'
    DO I=1,4
        WRITE (LUOUT,9110) LPATEXT(I),I
    END DO
    WRITE(LUOUT,*) '
    WRITE(LUOUT,*) '
        RESTART = 98'
        TERMINATE = 99'
310 CALL INENTER (LUOUT,LUIN,'Your choice ',LPACON,LPACON)
    IF (LPACON.EQ.98) GO TO 7000
    IF (LPACON.EQ.99) GO TO 8000
    IF (LPACON.LT.1.OR.LPACON.GT.4) GO TO 310
    LPASAVE=LPACON
    WRITE (LUOUT,9110) LPATEXT(LPACON),LPACON
    IF (STORE) THEN
        WRITE (LURES,9110) LPATEXT(LPACON),LPACON
    END IF
C
C *** FORM LEAST SQUARES TOEPLITZ SYSTEM FOR DENOMINATOR COEFFICIENTS
C *** (EXCEPT FOR FAST ALGORITHM)
320 MRETC=0
    CALL CPUTIME (TOSUB,IONE)
    IF (LPACON.NE.4) THEN
        CALL SETTP (XSIG,MAT,C,NNFIT,LPOCON,N1,FBCON,LPMCON,LUOUT
1 ,BATCH,MRETC)

```

```

      END IF
      CALL CPUTIME (T1SUB, IONE)
      MSEC(2)=MSEC(2)+(T1SUB-T0SUB)*1000
      IF (MRETC.GT.0) GO TO 8000
C
C *** CLEAR POLYNOMIAL COEFFICIENTS (TO SIMPLIFY DIAGNOSTICS)
      DO I=0, NSIZE-1
        A(I)=0.0
      END DO
C
C *** SVD BASED ALGORITHM
      IF (LPACON.EQ.1) THEN
        CALL CPUTIME (T0SUB, IONE)
        CALL DSVDC (MAT, NTAILL, N1, LPOCON, DMATSV, B, U, NTAILL, V
          , NSIZE, WORK, 21, INFO)
        CALL CPUTIME (T1SUB, IONE)
        MSEC(3)=MSEC(3)+(T1SUB-T0SUB)*1000
        IF (BATCH.GT.1) WRITE (LUOUT, 9330) DMATSV(1), DMATSV(LPOCON)
        IF (BATCH.NE.1) WRITE (LUOUT, 9330) DMATSV(1), DMATSV(LPOCON)
        IF (STORE) THEN
          WRITE (LURES, 9330) DMATSV(1), DMATSV(LPOCON)
          WRITE (LURES, 9200)
          DO I=1, LPOCON
            WRITE (LURES, 9622) I, DMATSV(I)
          END DO
        END IF
C
      IF (BATCH.GT.0) THEN
        IF (BATCH.GT.1) WRITE (LUOUT, 9320) LPOCON
        IF (BATCH.GT.1) WRITE (LUOUT, 9322) PIRCON
        IF (STORE) THEN
          WRITE (LURES, 9320) LPOCON
          WRITE (LURES, 9322) PIRCON
        END IF
        GO TO 380
      END IF
C
C *** PLOT AND EXAMINE THE SINGULAR VALUES, IF REQUESTED
      CALL LGENTER (LUOUT, LUIN, 'Plot the singular values ', 1, I)
      IF (I.EQ.0) THEN
        CALL GRPHTRM (LUOUT, LUIN)
        CALL PLTEIGN (DMATSV, LPOCON, LPMCON, FBCON, DNAME, NNFIT, NINIT, 1)
        CALL GFINAL (LUIN)
      END IF
      CALL LGENTER (LUOUT, LUIN, 'Examine the singular values ', 1, I)
      IF (I.EQ.0) THEN
        WRITE (LUOUT, 9330) DMATSV(1), DMATSV(LPOCON)
        WRITE (LUOUT, 9200)
        DO I=1, LPOCON
          WRITE (LUOUT, 9622) I, DMATSV(I)
        END DO
      END IF
C
C *** ENTER THE DESIRED RANK OF THE DATA MATRIX
360  WRITE (LUOUT, 9320) LPOCON
      CALL INENTER (LUOUT, LUIN, ' SET DATA RANK LIMIT TO ', PIRCON
        , PIRCON)
      IF (PIRCON.LT.1.OR.PIRCON.GT.LPOCON) THEN
        WRITE (LUOUT, 9180) LPOCON
        GO TO 360
      END IF
      PIRSAVE=PIRCON
C
C *** SOLVE LEAST SQUARE SYSTEM TO GET THE VECTOR A(0:LPOCON), A(0)=1.
380  CALL CPUTIME (T0SUB, IONE)
      CALL LSTSVD (A, U, V, DMATSV, C, PIRCON, N1, LPOCON, LUOUT, BATCH)
      CALL CPUTIME (T1SUB, IONE)
      MSEC(4)=MSEC(4)+(T1SUB-T0SUB)*1000
      IF (TRACK) THEN
        WRITE (LUOUT, 9450) LPOCON, PIRCON
        IF (STORE) WRITE (LURES, 9450) LPOCON, PIRCON
      END IF
      GO TO 400
    END IF
C
C *** QR BASED ALGORITHM
      IF (LPACON.EQ.2) THEN

```



```

      CALL CPUTIME (TOSUB, IONE)
      CALL LSTQR (MAT, C, A, N1, LPOCON, LPMCON, FBCON, DNAME, NNFIT
1      , NINIT, PIRCON, LUOUT, LUIN, BATCH)
      CALL CPUTIME (T1SUB, IONE)
      MSEC(4)=MSEC(4)+(T1SUB-TOSUB)*1000
      GO TO 400
    END IF
  C
  C *** Total Least Squares solution
  IF (LPACON.EQ.3) THEN
    CALL CPUTIME (TOSUB, IONE)
    CALL TLS(MAT, C, A, N1, LPOCON)
    CALL CPUTIME (T1SUB, IONE)
    MSEC(4)=MSEC(4)+(T1SUB-TOSUB)*1000
    GO TO 400
  END IF
  C
  C *** FAST LEAST SQUARES ALGORITHM
  IF (LPACON.EQ.4) THEN
    CALL CPUTIME (TOSUB, IONE)
    IF (FBCON.EQ.1) THEN
      IF (LPMCON.EQ.1) CALL LSCOR(XSIG, NNFIT, A, LPOCON, MRETF)
      IF (LPMCON.EQ.2) CALL LSPRE(XSIG, NNFIT, A, LPOCON, 0, MRETF)
      IF (LPMCON.EQ.3) CALL LSCOV(XSIG, NNFIT, A, LPOCON, IZERO
1      , TRIMLPM, MRETF)
      IF (LPMCON.EQ.4) CALL LSPST(XSIG, NNFIT, A, LPOCON, 0, MRETF)
    ELSE IF (FBCON.EQ.3) THEN
      IF (LPMCON.EQ.1) CALL LSCOR(XSIG, NNFIT, A, LPOCON, MRETF)
      IF (LPMCON.EQ.2) CALL LSPRE(XSIG, NNFIT, A, LPOCON, 1, MRETF)
      IF (LPMCON.EQ.3) CALL LSCOV(XSIG, NNFIT, A, LPOCON, IONE
1      , TRIMLPM, MRETF)
      IF (LPMCON.EQ.4) CALL LSPST(XSIG, NNFIT, A, LPOCON, 1, MRETF)
    ELSE IF (FBCON.EQ.2) THEN
      IF (LPMCON.EQ.1) CALL LSCOR(XSIG, NNFIT, A, LPOCON, MRETF)
      IF (LPMCON.EQ.2) CALL LSPREFB(XSIG, NNFIT, A, LPOCON, MRETF)
      IF (LPMCON.EQ.3) CALL LSCOVFB(XSIG, NNFIT, A, LPOCON, MRETF)
      IF (LPMCON.EQ.4) CALL LSPSTFB(XSIG, NNFIT, A, LPOCON, MRETF)
    END IF
    CALL CPUTIME (T1SUB, IONE)
    MSEC(4)=MSEC(4)+(T1SUB-TOSUB)*1000
    GO TO 390
  END IF
  IF (BATCH.NE.1) WRITE (*,*) 'LPACON TYPE NOT RECOGNIZED'
  IF (BATCH.GT.1) WRITE (LUOUT,*) 'LPACON TYPE NOT RECOGNIZED'
  STOP
  C
  C *** TEST FAST SOLUTION
  390 IF (MRETF.LT.0) THEN
    LPACON=1
    IF (BATCH.NE.1) WRITE (*,9960) MRETF, LPACON
    IF (BATCH.GT.1) WRITE (LUOUT,9960) MRETF, LPACON
    GO TO 100
  END IF
  C
  C *** DIAGNOSTIC DISPLAY OF DENOMINATOR Z-COEFFICIENTS
  400 IF (TRACK.OR.STORE) THEN
    IF (TRACK) WRITE (LUOUT,9451)
    IF (STORE) WRITE (LURES,9451)
    DO I=0, LPOCON
      IF (TRACK) WRITE (LUOUT,9622) I, A(I)
      IF (STORE) WRITE (LURES,9622) I, A(I)
    END DO
  END IF
  C
  C *** ROOT DENOMINATOR POLYNOMIAL FOR FREQUENCIES AND DAMPING FACTORS
  DO I=0, LPOCON
    OPR(I+1)=A(LPOCON-I) ! NOTE REVERSAL
  END DO
  IF (DQPSET.EQ.0) THEN
    CALL CPUTIME (TOSUB, IONE)
    CALL QPOLYRT (OPR, LPOCON, ZEROR, ZEROI, IFAIL)
    CALL CPUTIME (T1SUB, IONE)
    MSEC(5)=MSEC(5)+(T1SUB-TOSUB)*1000
    IF (IFAIL.NE.0) THEN
      IF (BATCH.GT.1) WRITE (LUOUT,*) 'QPOLY FAILURE =' , IFAIL
1, ' FOR DENOMINATOR'
      IF (STORE) WRITE (LUOUT,*) 'QPOLY FAILURE =' , IFAIL
    
```

```

1, ' FOR DENOMINATOR'
END IF
END IF
IF (DQPSET.GE.1) THEN
CALL CPUTIME (TOSUB, IONE)
CALL DPOLYRT (OPR, LPOCON, ZEROR, ZEROI, IFAIL)
CALL CPUTIME (T1SUB, IONE)
MSEC(5)=MSEC(5)+(T1SUB-TOSUB)*1000
IF (IFAIL.NE.0) THEN
IF (BATCH.GT.1) WRITE (*,*) 'DPOLY FAILURE =', IFAIL
1, ' FOR DENOMINATOR'
IF (STORE) WRITE (LUOUT,*) 'DPOLY FAILURE =', IFAIL
1, ' FOR DENOMINATOR'
END IF
END IF
C
C *** DIAGNOSTIC DISPLAY OF DONOMINATOR Z-ROOTS
IF (TRACK.OR.STORE) THEN
IF (TRACK) WRITE (LUOUT,9210)
IF (STORE) WRITE (LURES,9210)
DO I=1,LPOCON
IF (TRACK) WRITE (LUOUT,9622) I,ZEROR(I),ZEROI(I)
IF (STORE) WRITE (LURES,9622) I,ZEROR(I),ZEROI(I)
END DO
END IF
C
C *** SIFT OUT COMPLEX DENOMINATOR ROOTS IN LOWER HALF OF Z-PLANE
C *** SIFT OUT OVERLY LARGE ROOTS, RESTARTING IF APPROPRIATE
C *** COMPUTE MAGNITUDE AND PHASE OF RETAINED Z-ROOTS AND ORDER
C BY DECREASING MAGNITUDE
ZZTRIM=10.** (30.DO/NNFIT)
PIRADJ=.FALSE.
DMODES=0
DMREAL=0
DMCMPX=0
DO 420 I=1,LPOCON
IF (ZEROI(I).LT.0.DO) GO TO 420
DMODES=DMODES+1
ROOTR(DMODES) = ZEROR(I)
ROOTI(DMODES) = ZEROI(I)
IF (DABS(ROOTI(DMODES)).LT.EPS1) ROOTI(DMODES) = 0.DO
MAG(DMODES) = DSQRT(ZEROR(I)**2 + ZEROI(I)**2)
PHA(DMODES) = DABS(DATAN2(ZEROI(I),ZEROR(I)))*DEG
IF (PHA(DMODES).LT.EPS1) THEN
ZEROI(DMODES)=0.DO
PHA(DMODES)=0.DO
END IF
IF (MAG(DMODES).LT.1.DO) GO TO 410
IF (TRACK) THEN
IF (BATCH.GT.0) WRITE (LUOUT,9212) MAG(DMODES),PHA(DMODES)
WRITE (LUOUT,9212) MAG(DMODES),PHA(DMODES)
END IF
IF (MAG(DMODES).GT.ZZTRIM) THEN
IF (BATCH.GT.1) WRITE (LUOUT,9214)
IF (STORE) WRITE (LURES,9214)
IF (PIRADJ.AND.PIRCON.GE.LPOCON-6) THEN
PIRCON=PIRCON-2
IF (BATCH.GT.1) WRITE (LUOUT,9220) PIRCON
IF (STORE) WRITE (LUOUT,9220) PIRCON
GO TO 380
ELSE
IF (BATCH.GT.1) WRITE (LUOUT,9222)
IF (STORE) WRITE (LUOUT,9222)
DMODES=DMODES-1
GO TO 420
END IF
END IF
410 IF (ZEROI(DMODES).EQ.0.DO) DMREAL=DMREAL+1
IF (ZEROI(DMODES).NE.0.DO) DMCMPX=DMCMPX+1
420 CONTINUE
SRULE=-1
CALL CPUTIME (TOSUB, IONE)
CALL HEAPSRT (MAG,PHA,ROOTR,ROOTI,DMODES,SRULE)
CALL CPUTIME (T1SUB, IONE)
MSEC(6)=MSEC(6)+(T1SUB-TOSUB)*1000
IF (BATCH.GT.1) WRITE (*,9452) LPOCON,DMODES,DMREAL,DMCMPX
IF (STORE) WRITE (LURES,9452) LPOCON,DMODES,DMREAL,DMCMPX

```

```

      QCON=DMODES
C
C *** DIAGNOSTIC DISPLAY OF SIFTED ROOTS
      IF (TRACK.OR.STORE) THEN
        IF (TRACK) WRITE (LUOUT,9210)
        IF (STORE) WRITE (LURES,9210)
        DO I=1,QCON
          IF (TRACK) WRITE (LUOUT,9622) I,ROOTR(I),ROOTI(I)
          IF (STORE) WRITE (LURES,9622) I,ROOTR(I),ROOTI(I)
        END DO
      END IF
      IF (BATCH.GT.0) GO TO 480
C
C *** INTERMEDIATE DISPLAY OF ROOTS AND RELATED PARAMETERS
460 WRITE (LUOUT,*) 'Intermediate menu'
      WRITE (LUOUT,*) '      Tabulated solution polynomial = 1'
      WRITE (LUOUT,*) '      Tabulated roots = 2'
      WRITE (LUOUT,*) '      Plot the roots = 3'
      WRITE (LUOUT,*) '      Continue = 4'
      WRITE (LUOUT,*) '      RESTART = 98'
      WRITE (LUOUT,*) '      TERMINATE = 99'
462 CALL INENTER (LUOUT,LUIN,'Your choice ',4,I)
      IF (I.EQ.98) GO TO 7000
      IF (I.EQ.99) GO TO 8000
      IF (I.LE.0.OR.I.GT.4) GO TO 462
C
C *** IF A GRAPHIC PLOT WAS REQUESTED, EXECUTE IT
      IF (I.LE.3.AND.I.GE.1) THEN
        CALL GRPHTRM (LUOUT,LUIN)
        IF (I.EQ.1) CALL TABCFAR (A,LPOCON,LUIN)
        IF (I.EQ.2) CALL TABROOT (DMODES,ROOTR,ROOTI,MAG,PHA,LUIN)
        IF (I.EQ.3) CALL PLTROOT (DMODES,LPOCON,ROOTR,ROOTI
1      ,350.,250.,150.,LPMCON,FBCON,NNFIT,NINIT,DNAME)
        CALL GFINAL (LUIN)
        GO TO 460
      END IF
C
C *** SELECT THE VANDERMONDE SYSTEM SOLVER
C
480 IF (BATCH.GT.0) THEN
      IF (BATCH.GT.1) WRITE (*,9160) VDMCON,VDMTEXT(VDMCON)
      IF (BATCH.GT.1) WRITE (LUOUT,9160) VDMCON,VDMTEXT(VDMCON)
      IF (STORE) WRITE (LURES,9110) VDMCON,VDMTEXT(VDMCON)
      GO TO 600
    END IF
C
C *** ASK FOR THE VANDERMONDE SYSTEM SOLVER
      WRITE (LUOUT,*) 'VANDERMONDE SYSTEM SOLVER:'
      DO I=1,3
        WRITE (LUOUT,9110) VDMTEXT(I),I
      END DO
      WRITE (LUOUT,*) '      RESTART = 98'
      WRITE (LUOUT,*) '      TERMINATE = 99'
490 CALL INENTER (LUOUT,LUIN,'Your choice ',VDMCON,VDMCON)
      IF (VDMCON.EQ.98) GO TO 7000
      IF (VDMCON.EQ.99) GO TO 8000
      IF (VDMCON.LT.1.OR.VDMCON.GT.3) GO TO 490
      VDMSAVE=VDMCON
      WRITE (LUOUT,9110) VDMTEXT(VDMCON),VDMCON
      IF (STORE) THEN
        WRITE (LURES,9110) VDMTEXT(VDMCON),VDMCON
      END IF
C
C *** SUBSET SELECT THE POLES :
C Enter the number of desired modes
520 WRITE (LUOUT,9440) DMODES
      CALL INENTER (LUOUT,LUIN,'DESIRED NUMBER ',QCON,QCON)
      IF (QCON.GT.DMODES.OR.QCON.LE.0) GO TO 520
      QSAVE=QCON
C
C *** COMPUTE THE NUMBER OF SETS OF SIZE QCON OUT OF DMODES, WITH A
C TRICK TO AVOID INTEGER OVERFLOW
600 ICOUNT=1
      IQ=QCON
      IF (IQ.GT.(DMODES/2)) IQ=DMODES-QCON
      DO I=0,IQ-1
        ICOUNT=ICOUNT*(DMODES-I)/(I+1)
      END DO

```

```

END DO
IF (BATCH.GT.1) WRITE(LUOUT,*) 'ICOUNT =',ICOUNT
IF (BATCH.NE.1) WRITE (LUOUT,*) 'ICOUNT =',ICOUNT
DO I=1,QCON
  IC(I)=1
END DO
DO I=QCON+1,DMODES
  IC(I)=0
END DO
DMINERR=DENERGY(XSIG,NNFIT)*DFLOAT(NNFIT)
DO I=1,ICOUNT
  CALL CPUTIME (TOSUB,IONE)
  IF (VDMCON.EQ.1) THEN
    CALL LSTVDM (XSIG,MAG,PHA,AMP,PHI,NNFIT,QCON
    ,DMODES,IC,DERR)
  *
  ELSE IF (VDMCON.EQ.2) THEN
    CALL LSFVDM (XSIG,MAG,PHA,AMP,PHI,NNFIT,QCON
    ,DMODES,IC,DERR)
  *
  ELSE
    CALL CLSFVDM (XSIG,MAG,PHA,AMP,PHI,NNFIT,QCON
    ,DMODES,IC,DERR)
  *
  END IF
  CALL CPUTIME (T1SUB,IONE)
  MSEC(7)=MSEC(7)+(T1SUB-TOSUB)*1000
  IF (DERR.LT.DMINERR) THEN
    DMINERR=DERR
    J=1
    DO K=1,DMODES
      IF (IC(K).EQ.1) THEN
        MAGOPT(J)=MAG(K)
        PHAOPT(J)=PHA(K)
        AMPOPT(J)=AMP(K)
        PHIOPT(J)=PHI(K)
        ROOTAAR(J)=ROOTR(K)
        ROOTAAI(J)=ROOTI(K)
        J=J+1
      END IF
    END DO
  END IF
  CALL CPUTIME (TOSUB,IONE)
  CALL COMBIN (DMODES,QCON,IC)
  CALL CPUTIME (T1SUB,IONE)
  MSEC(8)=MSEC(8)+(T1SUB-TOSUB)*1000
END DO

C
C *** FORCE ALL MODE AMPLITUDES POSITIVE
DO I=1,QCON
  IF (AMPOPT(I).LT.0.0) THEN
    AMPOPT(I)=-AMPOPT(I)
    PHIOPT(I)=PHIOPT(I)+180.0
  END IF
END DO

C
C *** ORDER MODES BY DECREASING AMPLITUDE
SRULE=-1
CALL CPUTIME (TOSUB,IONE)
CALL HEAPSRT (AMPOPT,PHIOPT,MAGOPT,PHAOPT,QCON,SRULE)
CALL CPUTIME (T1SUB,IONE)
MSEC(9)=MSEC(9)+(T1SUB-TOSUB)*1000

C
C *** FIND STRONGEST MODE NOT AT SAMPLING FREQUENCY,
C AND INSIDE INTERVAL [FTRIML,FTRIMH]
ZTRIMH=FTRIMH/HZFAC
IF (ZTRIMH.LE.0.0) ZTRIMH=360.0
ZTRIML=FTRIML/HZFAC
AMPREF=AMPOPT(1)
DO 640 I=1,QCON
  IF (PHAOPT(I).LT.ZTRIML.OR.PHAOPT(I).GT.ZTRIMH) GO TO 640
  IF (DABS(PHAOPT(I)-180.0).GT.1.D-6) THEN
    AMPREF=AMPOPT(I)
    GO TO 642
  END IF
640 CONTINUE
642 CONTINUE

C
C *** TEST FOR NULL SOLUTION
IF (AMPOPT(1).LT.1.D-8.OR.AMPREF.LT.1.D-8) THEN

```

```

      IF (BATCH.NE.1) WRITE (*,9950) AMPOPT(1),AMPREF
      IF (BATCH.GT.1) WRITE (LUOUT,9950) AMPOPT(1),AMPREF
      IF (LPACON.NE.1) THEN
        MRETF=-200
        GO TO 390
      END IF
    END IF
  END IF
C
C *** TEMPORARY DIAGNOSTIC
  IF (TRACK.OR.STORE) THEN
    WRITE (LURES,9170) QCON
    WRITE (LURES,9618)
    DO I=1,QCON
      WRITE (LURES,9622) I,AMPOPT(I)
    END DO
  END IF
C
  IF (BATCH.GT.0) THEN
    IF (BATCH.GT.1) WRITE (LUOUT,*) 'QCON = ',QCON
    IF (STORE) WRITE (LURES,*) 'QCON = ',QCON
    IF (TRIMLPM.GT.0.0) THEN
      IF (BATCH.GT.1) WRITE (LUOUT,9460) TRIMLPM
      IF (STORE) WRITE (LURES,9460) TRIMLPM
    END IF
    IF (STORE) WRITE (LURES,9620)
    FAC=1.0
    IF (AMPREF.GT.0.0) FAC=1./AMPREF
    DO I=1,QCON
      RELMAG(I)=AMPOPT(I)*FAC
      IF (RELMAG(I).LE.TRIMLPM) GO TO 680
      ILAST=I
    END DO
    IF (STORE) WRITE (LURES,9622) I,RELMAG(I)
  END IF
680  IF (BATCH.GT.1) WRITE (LUOUT,9470) ILAST
      IF (BATCH.NE.1) WRITE (LUOUT,9470) ILAST
      IF (STORE) WRITE (LURES,9470) ILAST
      QCON=ILAST
      QTRIM=QCON
      GO TO 740
    END IF
C
C *** ENTER MODE TRIMMING CONTROLS
  CALL LGENTER (LUOUT,LUIN,'TRIM WEAK MODES? ',0,ISEL)
C
  TRIMLPM=1.E-6
  IF (ISEL.EQ.0) THEN
    WRITE (LUOUT,*) 'QCON = ',QCON
    IF (STORE) WRITE (LURES,*) 'QCON = ',QCON
    WRITE (LUOUT,9620)
    IF (STORE) WRITE (LURES,9620)
    DO I=1,QCON
      RELMAG(I)=AMPOPT(I)/AMPREF
      WRITE (LUOUT,9622) I,RELMAG(I)
      IF (STORE) WRITE (LURES,9622) I,RELMAG(I)
      IF (RELMAG(I).GT.TRIMLPM) ILAST=I
    END DO
  700  CALL INENTER (LUOUT,LUIN,'TRIM ALL PAST MODE ',ILAST,ISEL)
      TRIMLPM=0.0
      IF (ISEL.LE.0.OR.ISEL.GT.QCON) GO TO 700
      TRIMLPM=RELMAG(ISEL)
      QCON=ISEL
    END IF
    QTRIM=QCON
C
C *** COMPUTE THE RECONSTRUCTED AND PREDICTED SIGNAL SEGMENTS FROM THE
C QCON SELECTED MODES
C *** COMPUTE THE FITTING ERROR AND SNR (OVER NNHAT SAMPLES ONLY)
740  DO I=0,NNHAT-1
    SUM=0.0
    DO K=1,QCON
      ALPHA=(PHAOPT(K)*I+PHIOPT(K))*DEGI
      SUM=SUM+AMPOPT(K)*DCOS(ALPHA)*MAGOPT(K)**I
    END DO
    SHAT(I)=SUM
    SIGDIF(I)=XSIG(I)-SHAT(I)
  END DO
  SNR=10.*DLOG10(DENERGY(SHAT,NNFIT)/DENERGY(SIGDIF,NNFIT))
  IF (BATCH.NE.1) WRITE (LUOUT,9600) SNR,QCON

```

```

C
C *** CONVERT Z-DOMAIN MODES TO S-DOMAIN
DO I=1,QCON
  DAMP(I)=-1.0/TSTEP*DLOG(MAGOPT(I))/(2.*PI)
  FRQHZ(I)=PHAOPT(I)*HZFAC
  PHASE(I)=PHIOPT(I)
END DO
C
  IF (.NOT.DONUM) GO TO 820
C
C *** COMPUTE THE RECONSTRUCTION ARMA POLYNOMIAL BB(Z)/AA(Z)
C [AA(Z) IS THE ANNIHILATOR (TAKEN AS AN MA FILTER)]
C [THE SIGNAL IS MODELED AS THE IMPULSE REPOSE OF BB(Z)/AA(Z)]
CALL CPUTIME (TOSUB,IONE)
CALL POLYFM (MAGOPT,PHAOPT,AMPOPT,PHIOPT,QCON,AA,BB
1,AADEG,BBDEG)
CALL CPUTIME (T1SUB,IONE)
MSEC(10)=MSEC(10)+(T1SUB-TOSUB)*1000
C
C *** ROOT THE NUMERATOR POLYNOMIAL
DO I=0,BBDEG
  OPR(I+1)=BB(BBDEG-I) ! NOTE REVERSAL
END DO
IF (DQPSET.EQ.0) THEN
  CALL CPUTIME (TOSUB,IONE)
  CALL QPOLYRT (OPR,BBDEG,ZEROR,ZEROI,IFAIL)
  CALL CPUTIME (T1SUB,IONE)
  MSEC(11)=MSEC(11)+(T1SUB-TOSUB)*1000
  IF (IFAIL.NE.0) THEN
    IF (BATCH.GT.1) WRITE(LUOUT,*) 'QPOLY FAILURE =',IFAIL
1, ' FOR NUMERATOR'
    IF (STORE) WRITE (LURES,*) 'QPOLY FAILURE =',IFAIL
1, ' FOR NUMERATOR'
  END IF
END IF
IF (DQPSET.GE.1) THEN
  CALL CPUTIME (TOSUB,IONE)
  CALL DPOLYRT (OPR,BBDEG,ZEROR,ZEROI,IFAIL)
  CALL CPUTIME (T1SUB,IONE)
  MSEC(11)=MSEC(11)+(T1SUB-TOSUB)*1000
  IF (IFAIL.NE.0) THEN
    IF (BATCH.GT.1) WRITE(LUOUT,*) 'DPOLY FAILURE =',IFAIL
1, ' FOR NUMERATOR'
    IF (STORE) WRITE (LURES,*) 'DPOLY FAILURE =',IFAIL
1, ' FOR NUMERATOR'
  END IF
END IF
C
C *** COMPUTE MAGNITUDE AND PHASE OF THE NUMERATOR Z-ROOTS AND ORDER
C BY DECREASING MAGNITUDE
C [EACH COMPLEX CONJUGATE PAIR IS ONLY MEMORIZED ONCE, WITH POSITIVE
C [IMAGINARY PART.
NRMODES=0
DO 780 I=1,BBDEG
  IF (ZEROI(I).LT.0.D0) GO TO 780
  NRMODES=NRMODES+1
  ROOTBBR(NRMODES) = ZEROR(I)
  ROOTBBI(NRMODES) = ZEROI(I)
  IF (DABS(ROOTBBI(NRMODES)).LT.EPS1) ROOTBBI(NRMODES) = 0.D0
  MAGBB(NRMODES) = DSQRT(ZEROR(I)**2 + ZEROI(I)**2)
  PHABB(NRMODES) = DABS(DATAN2(ZEROI(I),ZEROR(I)))*DEG
  IF (DABS(PHABB(NRMODES)).LT.EPS1) PHABB(NRMODES) = 0.D0
  IF (MAGBB(NRMODES).GE.1) THEN
    IF (BATCH.GT.1) WRITE(LUOUT,*) 'ROOT ON OR',
* ' OUTSIDE THE UNIT CIRCLE'
  END IF
780 CONTINUE
SRULE=-1
CALL HEAPSRT (MAGBB,PHABB,ROOTBBR,ROOTBBI,NRMODES,SRULE)
C
C *** CONVERT Z-DOMAIN NUMERATOR ZEROS TO S-DOMAIN
DO I=1,NRMODES
  IF (MAGBB(I).GT.1.E-6) THEN
    DAMPBB(I)=-1.0/TSTEP*DLOG(MAGBB(I))/(2.*PI)
  ELSE
    DAMPBB(I)=1.E20
  END IF

```

```

      FRQHZBB(I)=PHABB(I)*HZFAC
    END DO
C
C *** FINAL RESULTS PROCESSING
820 DO PLOT=.FALSE.
    CALL PLTSIG (XSIG, SHAT, NNHAT, 2, NINIT, DNAME, TSTEP, SIGDIF, SNR
    *, DO PLOT)
    CALL TABMDC (QCON, MAGOPT, PHAOPT, AMPOPT, PHIOPT, LUIN, TSTEP
    1, DAMP, FRQHZ, RELMAG, PHASE, DO PLOT)
C
C *** ORDER MODES BY INCREASING NATURAL FREQUENCY
    SRULE=1
    CALL HEAPSRT (FRQHZ, DAMP, AMPOPT, PHASE, QCON, SRULE)
C
C *** ORDER NUMERATOR ROOTS BY INCREASING NATURAL FREQUENCY
    IF (DONUM) THEN
      SRULE=1
      CALL HEAPSRT (FRQHZBB, DAMPBB, MAGBB, PHABB, QCON, SRULE)
    END IF
C
C *** RECALCULATE RELATIVE MAGNITUDES
    DO 860 I=1, QCON
860   RELMAG(I)=AMPOPT(I)/AMPREF
C
C *** DISPLAY NUMERATOR RESULTS
    IF (DONUM) THEN
      IF (BATCH.GT.1) WRITE(LUOUT,*)
1     'NUMERATOR RESULTS: BBDEG =', BBDEG
      IF (STORE) WRITE(LURES,*) 'NUMERATOR RESULTS: BBDEG =', BBDEG
      DO I=1, NRMODES
        IF (BATCH.GT.1) WRITE(LUOUT,9622) I, DAMPBB(I)
1      , FRQHZBB(I), MAGBB(I), PHABB(I)
        IF (STORE) WRITE(LURES,9622) I, ROOTBBR(I), ROOTBBI(I), MAGBB(I)
1      , PHABB(I)
      END DO
    END IF
C
    I=6
    IF (BATCH.GT.0) GO TO 6000
C
5000 WRITE(LUOUT,*) 'Final results menu'
    WRITE(LUOUT,*) '      Plot the discrete time modes = 1'
    WRITE(LUOUT,*) '      Plot the continuous time modes = 2'
    WRITE(LUOUT,*) '      Plot the data vectors = 3'
    WRITE(LUOUT,*) '      Plot the arma filter = 4'
    WRITE(LUOUT,*) '      Plot the poles/zeros = 5'
    WRITE(LUOUT,*) '      NEW SOLUTION = 6'
    WRITE(LUOUT,*) '      RESTART = 98'
    WRITE(LUOUT,*) '      TERMINATE = 99'
5020 CALL INENTER (LUOUT, LUIN, 'Your choice ', 6, I)
    IF (I.EQ.98) GO TO 7000
    IF (I.EQ.99) GO TO 8000
    IF ((I.LE.0).OR.(I.GT.6)) GO TO 5020
    DO PLOT=.TRUE.
    IF (I.LE.5) THEN
      CALL GRPHTRM (LUOUT, LUIN)
      IF (I.EQ.1) CALL TABMDD (QCON, MAGOPT, PHAOPT, AMPOPT
      *, PHIOPT, LUIN)
      IF (I.EQ.2) CALL TABMDC (QCON, MAGOPT, PHAOPT, AMPOPT
      *, PHIOPT, LUIN, TSTEP, DAMP, FRQHZ, RELMAG, PHASE, DO PLOT)
      IF (I.EQ.3) CALL PLTSIG (XSIG, SHAT, NNFIT, 2, NINIT, DNAME
      *, TSTEP, SIGDIF, SNR, DO PLOT)
      IF (I.EQ.4) CALL TABCF (AA, AADEG, BB, BBDEG, LUIN)
      IF (I.EQ.5) CALL PLTPOLE (QCON, NRMODES, ROOTAAR, ROOTAAI
      *, ROOTBBR, ROOTBBI, 350., 250., 150.)
      CALL GFINAL (LUIN)
      IF (I.LT.6) GO TO 5000
    END IF
C
C *** CASE TERMINATION LOGIC
C [NOTE: ROUTINE "DSTORERES" IS NO LONGER USED]
6000 CONTINUE
    IF (BATCH.GT.0.OR.I.EQ.6) THEN
      MRETR=0
      QCON=QTRIM
      TRACK=TRACKO
      GO TO 8800
    
```

```

      END IF
      GO TO 8000
C
C *** RESTART LOGIC
7000 MRETR=98
      QCON=QTRIM
      TRACK=TRACK0
      GO TO 8800
C
C *** GLOBAL TERMINATION LOGIC
8000 MRETR=99
      QCON=QTRIM
      TRACK0=TRACK
C
C *** FINAL TIME CALCULATIONS AND DISPLAY
8800 CALL CPUTIME (T1PAK, IONE)
      MSEC(1)=MSEC(1)+(T1PAK-TOPAK)*1000
      IF (BATCH.GT.1) THEN
        WRITE (*,9990)
        WRITE (*,9991)
        WRITE (*,9993) (MSEC(I), I=1,10)
        WRITE (*,9992)
        WRITE (*,9993) (MSEC(I), I=11,20)
      ENDIF
      IF (BATCH.GT.1) WRITE (LUOUT,9990)
      IF (STORE) WRITE (LURES,9990)
      IF (BATCH.GT.1) THEN
        WRITE (LUOUT,9991)
        WRITE (LUOUT,9993) (MSEC(I), I=1,10)
        WRITE (LUOUT,9992)
        WRITE (LUOUT,9993) (MSEC(I), I=11,20)
      END IF
      IF (STORE) THEN
        WRITE (LURES,9991)
        WRITE (LURES,9993) (MSEC(I), I=1,10)
        WRITE (LURES,9992)
        WRITE (LURES,9993) (MSEC(I), I=11,20)
      END IF
C
      IF (BATCH.NE.1) WRITE (*,9998)
      IF (BATCH.GT.1) WRITE (LUOUT,9998)
      IF (STORE) WRITE (LURES,9998)
C
      RETURN
C
9042 FORMAT (' ')
9044 FORMAT ('0')
9060 FORMAT (1X,'##LINEAR PREDICTION ORDER LESS THAN 1:')
1, ' SETTING LPOCON =', I4)
9062 FORMAT (1X,'##LINEAR PREDICTION ORDER EXCEEDS NNFIT/2 =', I4, ':')
2, ' SETTING LPOCON =', I4)
9064 FORMAT (1X,'##LINEAR PREDICTION ORDER EXCEEDS NSIZE =', I4, ':')
1, ' SETTING LPOCON =', I4)
9100 FORMAT (4X,'K',12X,'XSIG(K)')
9110 FORMAT (14X,A20,' =', I2)
9120 FORMAT (1X,'##LINEAR PREDICTION ORDER = LPOCON =', I4)
9130 FORMAT (1X,'##LINEAR PREDICTION METHOD = LPMCON =', I4
*,2X,A20)
9140 FORMAT (1X,'##FORWARD/BACKWARD CONTROL = FBCON =', I4
*,2X,A20)
9150 FORMAT (1X,'##LINEAR PREDICTION ALGORITHM = LPACON =', I4
*,2X,A20)
9160 FORMAT (1X,'##VANDERMODE ALGORITHM = VDMCON =', I4
*,2X,A20)
9170 FORMAT (1X,'##QCON =', I4)
9180 FORMAT (3X,'LIMITS ARE 1,', I4, ': TRY AGAIN')
9200 FORMAT (1X,'##DATA MATRIX SINGULAR VALUES:'
*,2X,'NUMBER',10X,'VALUE')
9210 FORMAT (1X,'##DENOMINATOR Z-ROOTS:'
*,3X,'MODE',8X,'REAL PART',3X,'IMAGINARY')
9212 FORMAT (3X,'Z-ROOT ON OR OUTSIDE UNIT CIRCLE:'
,F6.2,' @ ',F8.4,' DEGREES')
9214 FORMAT (39X,'WARNING: VERY LARGE ROOT')
9220 FORMAT (1X,'##RESTART WITH PIRCON REDUCED TO', I4//)
9222 FORMAT (39X,'(DELETED)')
9320 FORMAT (1X,'##MAXIMUM RANK OF THE DATA MATRIX = LPOCON =', I4)

```



```

9322 FORMAT (1X,'##SETTING DATA RANK LIMIT           = PIRCON =',I4)
9330 FORMAT (1X,'##SINGULAR-VALUE RANGE:   SIGMA MAX   = ',E12.4)
      */27X,'SIGMA MIN = ',E12.4)
9440 FORMAT (1X,'##NUMBER OF AVAILABLE REAL MODES     =',I4)
9450 FORMAT (1X,'##AFTER DLEASTSVD:   LPOCON,PIRCON    =',2I4)
9451 FORMAT (1X,'##DONOMINATOR Z-COEFFICIENTS:')
9452 FORMAT (1X,'##AFTER ROOTSIFT :   LPOCON,DMODES    =',2I4)
      1/22X,'DMREAL,DMCMPX      =',2I4)
9460 FORMAT (1X,'##LPM MODE TRIMMING: TRIM LEVEL      = ',D12.6)
9470 FORMAT (1X,'##NUMBER OF RETAINED MODES           =',I4)
9600 FORMAT ('0','##SIGNAL-TO-NOISE RATIO (SNR)        = ',F10.4)
      1,6X,'FOR QCON = ',I4)
9618 FORMAT (1X,'##MODAL AMPLITUDES:'
      */3X,'MODE',8X,'AMPLITUDE')
9620 FORMAT (1X,'##MODAL WEIGHTS (RELATIVE):'
      */3X,'MODE',8X,'REL. AMP.')
9622 FORMAT (1X,I5,5X,6D17.8)
9900 FORMAT ('0','##IN PRSPAK2:')
9910 FORMAT (1X,'##IN PRSPAK2: NNFIT,NINIT,QCON,LPOCON,LPMCON = '
      *,5I4/15X,'FBCON,LPACON,VDMCON,PIRCON,MRETR = ',5I4)
9912 FORMAT (4X,'TSTEP = ',F8.6)
9914 FORMAT (4X,'SIGNAL ENERGY = ',E12.6)
C
9920 FORMAT ('0','##IN PRSPAK: NULL SIGNAL:   ENERGY = ',E12.4)
9940 FORMAT ('0','##IN PRSPAK: NO DATA       NNFIT = ',I5)
9950 FORMAT ('0','##IN PRSPAK: NULL SOLUTION; AMPOPT(1),AMPREF = '
      1,2E12.4)
9960 FORMAT ('0','##IN PRSPAK: FAST ALGORITHM FAILURE; MRETF = ',I5)
      1/14X,'RESTARTING WITH LPACON =',I3)
9990 FORMAT ('0','##IN PRSPAK: TIMING ANALYSIS (MSEC)')
9991 FORMAT ('0',3X,'TOTAL',3X,'SETTP',4X,'SVDC',5X,'LPA',2X,'ROOT#1'
      *,2X,'SORT#1',5X,'VDM',2X,'COMBIN',2X,'SORT#2',2X,'POLYFM')
9992 FORMAT ('0',2X,'ROOT#2')
9993 FORMAT (1X,10I8)
9998 FORMAT (1X,'##PRSPAK DONE'//)
C
      END

```

Appendix B

Section 5 SIGPAKZ Input Files

Appendix B

Section 5 SIGPAKZ Input Files

Example 4.1

```
C
C exsigz920512a.sgz
C data file is exsysm920512.swx
C Fitting to noiseless data.
C LPM=correlation, LPA=SVD, FB=forward, VM=QR
C
C 00000001111111112222222223333333334444444445555555556666666667777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   15.0   1.00000E-8   1 01  4 00 000  0  1 150
5.0    0.0    1.0    0.0        0 000  1  1 000  0 13  00
SET LPASAVE=1
END

C
C exsigz920512b.sgz
C data file is exsysm920512.swx
C Fitting to noiseless data.
C LPM=prewindowed, LPA=SVD, FB=forward, VM=QR
C
C 00000001111111112222222223333333334444444445555555556666666667777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   15.0   1.00000E-8   1 01  4 00 000  0  1 150
5.0    0.0    1.0    0.0        0 000  2  1 000  0 13  00
SET LPASAVE=1
END

C
C exsigz920512c.sgz
C data file is exsysm920512.swx
C Fitting to noiseless data.
C LPM=covariance, LPA=SVD, FB=forward, VM=QR
C
C 00000001111111112222222223333333334444444445555555556666666667777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   15.0   1.00000E-8   1 01  4 00 000  0  1 150
5.0    0.0    1.0    0.0        0 000  3  1 000  0 13  00
SET LPASAVE=1
END
```

```

C
C exsigz920512d.sgz
C data file is exsysm920512.swx
C Fitting to noiseless data.
C LPM=post windowed, LPA=SVD, FB=forward, VM=QR
C
C 00000001111111112222222223333333334444444445555555556666666667777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   15.0   1.00000E-8  1 01  4 00 000  0  1 150
5.0    0.0    1.0    0.0      0 000  4  1 000  0 13  00
SET LPASAVE=1
END

```

Example 4.2

```

C
C exsigz920513_f.sgz
C data file is exsysm920512.swx
C Fitting to noisy data (var=10)
C LPM=covariance, LPA=SVD, FB=backward, VM=QR
C
C 00000001111111112222222223333333334444444445555555556666666667777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   15.0   0.00000E-8  1 03  4 00 000  0  1 150
5.0    0.0    1.0    0.0      0 000  3  3 000  0 13  00
SET LPASAVE=1
END
C
C data file is exsysm920512.swx
C Fitting to noisy data (var=10)
C LPM=covariance, LPA=SVD, FB=forward-backward, VM=QR
C
C 00000001111111112222222223333333334444444445555555556666666667777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   15.0   0.00000E-8  1 03  4 00 000  0  1 150
5.0    0.0    1.0    0.0      0 000  3  2 000  0 13  00
SET LPASAVE=1
END
C
C data file is exsysm920512.swx
C Fitting to noisy data (var=10).
C LPM=covariance, LPA=SVD, FB=forward, VM=QR
C
C 00000001111111112222222223333333334444444445555555556666666667777777778
C 34567890123456789012345678901234567890123456789012345678901234567890

```

```

C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   15.0   1.00000E-8  1 03  4 00 000  0  1 150
5.0    0.0    1.0    0.0        0 000  3  1 000  0 13  00
SET LPASAVE=1
END

```

Example 4.3

```

C
C data file is exsysm920512.swx
C Fitting to noisy data (var=1)
C Fitting to different model orders.
C
C 00000001111111112222222222333333333344444444445555555555666666666677777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   15.0   0.00000E-8  1 02  4 00 000  0  1 150
5.0    0.0    1.0    0.0        0 003  3  1 003  0 13  00
SET LPASAVE=1
END

```

```

C
C data file is exsysm920512.swx
C Fitting to noisy data (var=1)
C Fitting to different model orders.
C
C 00000001111111112222222222333333333344444444445555555555666666666677777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   15.0   0.00000E-8  1 02  4 00 000  0  1 150
5.0    0.0    1.0    0.0        0 015  3  1 015  0 13  00
SET LPASAVE=1
END

```

```

C
C data file is exsysm920512.swx
C Fitting to noisy data (var=1)
C Fitting to different model orders.
C
C 00000001111111112222222222333333333344444444445555555555666666666677777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   15.0   0.00000E-8  1 02  4 00 000  0  1 150
5.0    0.0    1.0    0.0        0 030  3  1 030  0 13  00
SET LPASAVE=1
END

```

Example 4.4

```
C
C 5 seconds, 100 data points.
C
C 0000000111111111222222222233333333334444444444555555555566666666667777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   5.0   1.00000E-8  1 01 4 00 000 0 1 100
5.0    0.0   1.0   0.0       0 000 3 1 000 0 13 00
SET LPASAVE=1
END

C
C 2.5 seconds, 50 data points.
C
C 0000000111111111222222222233333333334444444444555555555566666666667777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   2.5   1.00000E-8  1 01 4 00 000 0 1 50
5.0    0.0   1.0   0.0       0 000 3 1 000 0 13 00
SET LPASAVE=1
END
```

Example 4.5

```
C
C exsigz920528f.sgz
C data file is exsysm920512d.swx
C Fitting to different data record lengths of noisy data.
C noise is wtnois1 (var=10)
C LPM=covariance, LPA=SVD, FB=forward, VM=QR
C 50 seconds, 500 data points.
C
C 0000000111111111222222222233333333334444444444555555555566666666667777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   50.0   0.00000E-8  1 03 4 00 000 0 2 500
5.0    0.0   1.0   0.0       0 000 3 1 124 0 13 00
SET LPASAVE=4
SET VDMSAVE=2
END

C
C 10 seconds, 100 data points.
C
C 0000000111111111222222222233333333334444444444555555555566666666667777777778
```

```

C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   10.0   1.00000E-8  1 03  4 00 000  0  2 100
5.0    0.0    1.0    0.0      0 000  3  1 000  0 13  00
SET LPASAVE=4
SET VDMSAVE=2
END

C
C 2.5 seconds, 25 data points.
C
C 00000001111111112222222222333333333344444444445555555555666666666677777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0    2.5    1.00000E-8  1 03  4 00 000  0  2  25
5.0    0.0    1.0    0.0      0 000  3  1 000  0 13  00
SET LPASAVE=4
SET VDMSAVE=2
END

```

Example 4.6

```

C
C exsigz920610a.sgz
C data file is exsysm920610a.swx
C Fitting to noisy data (wtnois1)
C LPM=covariance, LPA=SVD, FB=forward, VM=QR
C var=0.05, 40 db snr
C
C 00000001111111112222222222333333333344444444445555555555666666666677777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   15.0   0.00000E-8  1 01  4 00 000  0  2 150
5.0    0.0    1.0    0.0      0 000  3  1 000  0 13  00
SET LPASAVE=1
END

C
C var=15, 15 db snr
C
C 00000001111111112222222222333333333344444444445555555555666666666677777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   15.0   0.00000E-8  1 04  4 00 000  0  2 150
5.0    0.0    1.0    0.0      0 000  3  1 000  0 13  00
SET LPASAVE=1

```

END

Example 4.7

```
C
C exsigz920610a.sgz
C data file is exsysm920610a.swx
C Fitting to noisy data (wtnoise1)
C LPM=covariance, LPA=SVD, FB=forward, VM=QR
C var=5, 20 db snr
C
C 00000001111111112222222222333333333344444444445555555555666666666677777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   15.0   0.00000E-8  1 03  4 00 000  0  2 150
5.0    0.0    1.0    0.0        0 000  3  1 000  0 13 00
SET LPASAVE=1
END
```

```
C
C exsigz920610b.sgz
C data file is exsysm920610b.swx
C Fitting to noisy data (db10noise1)
C LPM=covariance, LPA=SVD, FB=forward, VM=QR
C var=5, 20 db snr
C
C 00000001111111112222222222333333333344444444445555555555666666666677777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   15.0   0.00000E-8  1 03  4 00 000  0  2 150
5.0    0.0    1.0    0.0        0 000  3  1 000  0 13 00
SET LPASAVE=1
END
```

```
C
C exsigz920610c.sgz
C data file is exsysm920610c.swx
C Fitting to noisy data (20dbnoise1)
C LPM=covariance, LPA=SVD, FB=forward, VM=QR
C var=5, 20 db snr
C
C 00000001111111112222222222333333333344444444445555555555666666666677777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   15.0   0.00000E-8  1 03  4 00 000  0  2 150
5.0    0.0    1.0    0.0        0 000  3  1 000  0 13 00
SET LPASAVE=1
END
```



```

C
C exsigz920610d.sgz
C data file is exsysm920610d.swx
C Fitting to noisy data (wtnoise1)
C LPM=covariance, LPA=SVD, FB=forward, VM=QR
C var=5, 20 db snr
C
C 00000001111111112222222222333333333344444444445555555555666666666677777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   15.0   0.00000E-8  1 03  4 00 000  0  2 150
5.0    0.0    1.0    0.0      0 000  3  1 000  0 13  00
SET LPASAVE=1
END

```

Example 4.8

```

C
C exsigz920603c.sgz
C data file is exsysm920603b.swx
C Poles moving close together
C LPM=covariance, LPA=SVD, FB=forward, VM=QR
C p=0.75
C
C 00000001111111112222222222333333333344444444445555555555666666666677777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   10.0   0.00000E-8  1 01  4 00 000  0  2 100
5.0    0.0    1.0    0.0      0 000  3  1 000  0 13  00
SET LPASAVE=1
END

C
C p=0.9
C
C 00000001111111112222222222333333333344444444445555555555666666666677777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
  0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys  0.0   10.0   0.00000E-8  1 02  4 00 000  0  2 100
5.0    0.0    1.0    0.0      0 000  3  1 000  0 13  00
SET LPASAVE=1
END

C
C p=0.0
C
C 00000001111111112222222222333333333344444444445555555555666666666677777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):

```

```

0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys 0.0 10.0 0.00000E-8 1 04 4 00 000 0 2 100
5.0 0.0 1.0 0.0 0 000 3 1 000 0 13 00
SET LPASAVE=1
END

```

Example 4.9

```

C
C exsigz920608c.sgz
C data file is exsysm920212b_2.swx
C Pole/zero pair moving close together with same frequency and noise.
C LPM=covariance, LPA=SVD, FB=forward, VM=QR
C p=0.0
C
C 00000001111111112222222223333333334444444445555555556666666667777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys 0.0 10.0 0.00000E-8 1 01 4 00 000 0 2 100
5.0 0.0 1.0 0.0 0 000 3 1 000 0 13 00
SET LPASAVE=1
END

C
C p=0.75
C
C 00000001111111112222222223333333334444444445555555556666666667777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys 0.0 10.0 0.00000E-8 1 02 4 00 000 0 2 100
5.0 0.0 1.0 0.0 0 000 3 1 000 0 13 00
SET LPASAVE=1
END

C
C p=0.9
C
C 00000001111111112222222223333333334444444445555555556666666667777777778
C 34567890123456789012345678901234567890123456789012345678901234567890
C ** LOGICAL UNIT ASSIGNMENTS (- INDICATES FILES ALREADY OPEN):
0 0 0 0 -2 3 0 8 -14 10 00 00 13 00 15 16 00 18 00 20
C
C ** DATA LINES 1 AND 2, SEE PG. 7.3.2 OF RED BOOK:
exsys 0.0 10.0 0.00000E-8 1 03 4 00 000 0 2 100
5.0 0.0 1.0 0.0 0 000 3 1 000 0 13 00
SET LPASAVE=1
END

```

Appendix C

TRANFUN and ORDER Subroutines

Appendix C

TRANFUN and ORDER Subroutines

```

C*****
C**
C** $Id: trans.f,v 1.1.1.1 1992/09/09 20:54:52 d3f011 Exp d3f011 $
C** SUBROUTINE TRANFUN
C**
C** by: Dan Trudnowski, Pacific NW Labs, April 1992.
C**
C** References: D. Trudnowski, "IPRONYID version 1.1b: A Computer Program
C**             for the Identification of Transfer Functions using Prony
C**             Analysis," PNL pending report.
C**
C** Consider the following Laplace transform system:
C**
C**
C**      U(s)  ----->|  G(s)  |--Y(s)-->sampld at TSTEP----->
C**      -----
C**
C** A system model (G(s)) is identified by this routine where
C**
C**      G(s) = [THRUPUT + sum_{i=1}^{QCON} [ \frac{RES(i)}{s-\lambda(i)} + \frac{Conjugate(RES(i))}{s-Conjugat(\lambda(i))} ] ]
C**
C** where the eigenvalues (\lambda(i)'s) are assumed distinct and may be
C** real and/or zero. This program identifies the RES(i) terms. U(s)
C** is a known input of the form
C**
C**      U(s) = sum_{j=1}^{NINPUTS} INAMP(j) \frac{\exp(-s*DELAY(j-1)) - \exp(-s*DELAY(j))}{s}
C**
C** A model of the output is assumed known after the input is turned off
C** or on the last pulse of the input. The output model is a sum of
C** exponentials with eigenvalues EIG. The output model starts at sample
C** SHIFT:
C**      y(t) = sum_{j=1}^{QCON} AMPOPT(j)*exp(-DAMP(j)*2*pi)*cos(FRQHZ(j)*2*pi+PHASE(j))
C**
C** For t=SHIFT*TSTEP, (SHIFT+1)*TSTEP, ..., (SHIFT+NNFIT-1)*TSTEP
C**
C** System eigenvalues (\lambda(i)'s) are:
C**      Real(\lambda(i))=-DAMP(i)*2*pi
C**      Imag(\lambda(i))=FRQHZ(i)*2*pi
C**
C*****
C**
C** INPUT:
C**      NINPUTS = Number of input pulses.
C**      DELAY   = Input switching times (sec.)
C**              (1...NINPUTS). DELAY(0) assumed 0.
C**      INAMP   = Input pulse amplitudes. (1...NINPUTS).
C**      OUTPUT  = Output samples with sample period TSTEP. (0...)
C**      TSTEP   = Sample period.
C**      QCON    = Number of output conjugate pair terms.
C**      QTHRU   = Number of terms used to calculate THRUPUT.
C**      DAMP    = Damping of output eigenvalues (divided by
C**              2*pi). (1...QCON)
C**      FRQHZ   = Frequency of output eigenvalues (hz). (1...QCON).
C**      AMPOPT  = Amplitude of output terms. (1...QCON)
C**      SHIFT   = See Above.
C**      NNFIT   = See Above.
C**

```

```

C** OUTPUT:
C**      RESR   = Real part of trans. func. residues. (1...QCON).
C**      RESI   = Imag. part of trans. func. residues. (1...QCON).
C**      THRUPUT = Feed forward term.
C**
C*****
      SUBROUTINE TRANFUN(NINPUTS,DELAY,INAMP,TSTEP,QCON,QTHRU,DAMP,
& FRQHZ,AMPOPT,PHASE,SHIFT,OUTPUT,RESR,RESI,THRUPUT)
      IMPLICIT NONE
      INCLUDE 'dimpar.cmn'
      INTEGER NINPUTS,QCON,QTHRU,SHIFT,NNFIT
      INTEGER INTOT,INSTEP,IRESO
      INTEGER I,J,K,L,M,N
      REAL*8 DELAY,INAMP,OUTPUT,DAMP,FRQHZ,AMPOPT,PHASE
      REAL*8 LASTAMP,RESO,RESR,RESI,BRESR,BRESI,EIGR,EIGI,
& THRUPUT,BRESO
      REAL*8 X,Y,Z,XR,XI,YR,YI,ZR,ZI,THRUK,VIKI,VIKR,VOK,
& XR2,XI2,YR2,YI2,ZR2,ZI2,T,PIE,PIE2
      REAL*4 TSTEP
      DIMENSION DELAY(0:INPMAX),INAMP(INPMAX),OUTPUT(0:),DAMP(NSIZE),
& FRQHZ(NSIZE),AMPOPT(NSIZE),PHASE(NSIZE)
      DIMENSION RESR(NSIZE),RESI(NSIZE),BRESR(NSIZE),BRESI(NSIZE)

C
      DELAY(0)=0.0D0
      PIE=DABS(DACOS(-1.0D0))
      PIE2=2.0D0*PIE

C
C CALCULATE OUTPUT RESIDUES AND FIND TERM AT ZERO:
C FIND TERM AT ZERO IN THE S-PLANE:
      L=0
      X=1.0D12
      DO I=1,QCON
        IF (FRQHZ(I).EQ.0.0D0) THEN
          IF (DABS(DAMP(I)).LT.X) THEN
            X=DABS(DAMP(I))
            L=I
          ENDIF
        ENDIF
      ENDDO
      IRESO=0
      BRESO=0.0D0
      IF (X.LT.1.0D-4) THEN
        IRESO=L
        BRESO=AMPOPT(IRESO)*DCOS(PHASE(IRESO)*PIE/180.0D0)
      ENDIF
      DO I=1,QCON
        IF (I.EQ.IRESO) GOTO 100
        BRESR(I)=AMPOPT(I)*DCOS(PHASE(I)*PIE/180.0D0)/2.0D0
        BRESI(I)=AMPOPT(I)*DSIN(PHASE(I)*PIE/180.0D0)/2.0D0
      100 ENDDO

C
C SHIFT OUTPUT RESIDUES:
      INSTEP=0
      INTOT=NINPUTS
      IF ((SHIFT*TSTEP).LT.DELAY(NINPUTS)-1.0D-8) THEN
        INSTEP=1
        INTOT=NINPUTS-1
      ENDIF
      T=TSTEP*SHIFT-DELAY(INTOT)
      IF ((SHIFT*TSTEP).GT.DELAY(INTOT)) THEN
        DO I=1,QCON
          IF (I.EQ.IRESO) GOTO 110
          XR=T*DAMP(I)*PIE2
          XI=-T*FRQHZ(I)*PIE2
          CALL CEXPRZ(YR,YI,XR,XI)
          CALL CMULTZ(XR,XI,BRESR(I),BRESI(I),YR,YI,1)
          BRESR(I)=XR
          BRESI(I)=XI
        110 ENDDO
      ENDIF

C
C CALCULATE RESIDUE FOR ZERO EIGENVALUE AND RESIDUE IF INPUT IS STEP:
      IF (INSTEP.EQ.0) THEN
        LASTAMP=0.0D0
        X=0.0D0
        DO I=1,INTOT

```

```

      X=X+INAMP(I)*(DELAY(I)-DELAY(I-1))
      ENDDO
      RESO=0.0D0
      IF (DABS(X).GT.1.0D-12) RESO=BRESO/X
      ELSE
      RESO=0.0D0
      LASTAMP=INAMP(NINPUTS)
C
C----IF A STEP FUNCTION CALCULATE RESIDUES:
      IF (INTOT.EQ.0) THEN
      DO I=1,QCON
      IF (I.EQ.IRESO) GOTO 120
      EIGR=-DAMP(I)*PIE2
      EIGI=FRQHZ(I)*PIE2
      CALL CMULTZ(RESR(I),RESI(I),EIGR,EIGI,BRESR(I),
      &      BRESI(I),1)
      RESR(I)=RESR(I)/INAMP(1)
      RESI(I)=RESI(I)/INAMP(1)
120      ENDDO
      GOTO 200
      ENDIF
      ENDIF
C
C CALCULATE RESIDUES:
      DO I=1,QCON
      IF (I.EQ.IRESO) GOTO 130
      XR=LASTAMP
      XI=0.0D0
      EIGR=-DAMP(I)*PIE2
      EIGI=FRQHZ(I)*PIE2
      DO J=1,INTOT
      YR=EIGR*(DELAY(INTOT)-DELAY(J-1))
      YI=EIGI*(DELAY(INTOT)-DELAY(J-1))
      YR2=EIGR*(DELAY(INTOT)-DELAY(J))
      YI2=EIGI*(DELAY(INTOT)-DELAY(J))
      CALL CEXPRZ(ZR,ZI,YR,YI)
      CALL CEXPRZ(ZR2,ZI2,YR2,YI2)
      XR=XR+INAMP(J)*(ZR-ZR2)
      XI=XI+INAMP(J)*(ZI-ZI2)
      ENDDO
      CALL CMULTZ(XR2,XI2,EIGR,EIGI,BRESR(I),
      &      BRESI(I),1)
      CALL CDIVZ(RESR(I),RESI(I),XR2,XI2,XR,XI,1)
130      ENDDO
      GOTO 200
C
C CALCULATE THRU-PUT TERM:
200      THRUPUT = 0.0D0
      M = 0
      L=IDNINT(DELAY(NINPUTS)/TSTEP+0.5D0)
      IF (L.GE.(SHIFT+NNFIT-1)) L=SHIFT+NNFIT-1
      DO K=0,L
      T=K*TSTEP
      THRUK = 0.0D0
      X = 0.0D0
      VOK = 0.0D0
      DO J=1,NINPUTS
      Y = 0.0D0
      Z = 0.0D0
      IF (T.GE.DELAY(J-1)) Y=1.0D0
      IF (T.GE.DELAY(J)) Z=1.0D0
      X=X+INAMP(J)*((T-DELAY(J-1))*Y-(T-DELAY(J))*Z)
      VOK=VOK+INAMP(J)*(Y-Z)
      ENDDO
      IF (DABS(VOK).LT.1.0D-12) GOTO 210
      M = M+1
      THRUK=OUTPUT(K)-RESO*X
      DO I=1,QTHRU
      IF (I.EQ.IRESO) GOTO 205
      EIGR=-DAMP(I)*PIE2
      EIGI=FRQHZ(I)*PIE2
      VIKR=0.0D0
      VIKI=0.0D0
      DO J=1,NINPUTS
      Y = 0.0D0
      Z = 0.0D0

```

```

        IF (T.GE.DELAY(J-1)) Y=1.0D0
        IF (T.GE.DELAY(J)) Z=1.0D0
        ZR=EIGR*(T-DELAY(J-1))
        ZI=EIGI*(T-DELAY(J-1))
        CALL CEXPRZ(XR,XI,ZR,ZI)
        ZR=EIGR*(T-DELAY(J))
        ZI=EIGI*(T-DELAY(J))
        CALL CEXPRZ(YR,YI,ZR,ZI)
        VIKR=VIKR+INAMP(J)*(XR*Y-YR*Z)
        VIKI=VIKI+INAMP(J)*(XI*Y-YI*Z)
        ENDDO
        CALL CDIVZ(XR,XI,RESR(I),RESI(I),EIGR,EIGI,1)
        VIKR=VIKR-VOK
        CALL CMULTZ(YR,YI,XR,XI,VIKR,VIKI,-1)
        THRUK=THRUK+2.0D0*YR
205  ENDDO
        THRUPUT=THRUPUT+THRUK/VOK
210  ENDDO
        IF (M.NE.0) THRUPUT = THRUPUT/M
C
C ADD RESIDUE AT ZERO TO LIST:
        IF (IRES0.GT.0) THEN
            RESR(IRES0)=RES0/2.0D0
            RESI(IRES0)=0.0D0
        ENDIF
C
        RETURN
        END
C*****
C** SUBROUTINE TRANSIM
C**
C** This subroutine calculates the output of the system
C**
C**

$$G(s) = [\text{THRUPUT} + \sum_{i=1}^{\text{QCON}} \frac{\text{RES}(i)}{s - \text{lambda}(i)} + \frac{\text{Conjugate}(\text{RES}(i))}{s - \text{Conjugat}(\text{lambda}(i))}]$$

C**
C** with
C**      Real(lambda(i))=-DAMP(i)*2*pi
C**      Imag(lambda(i))=FRQHZ(i)*2*pi
C**
C** where the eigenvalues (lambda(i)'s) are assumed distinct and allowed
C** to be real and/or zero. The system input is of the form
C**

$$U(s) = \sum_{j=1}^{\text{NINPUTS}} \text{INAMP}(j) \frac{\exp(-s*\text{DELAY}(j-1)) - \exp(-s*\text{DELAY}(j))}{s}$$

C**
C** Initial conditions are assumed zero, and DELAY(0) is assumed zero.
C** The system output (YOUT) is calculated at a sample period of TSTEP.
C**
C** INPUT:
C**      QCON      = Number of complex conjugate pairs.
C**      THRUPUT   = Feedforward term.
C**      DAMP      = Damping of eigenvalues. (1...QCON).
C**      FRQHZ     = Frequency of eigenvalues. (1...QCON).
C**      RESR      = Real part of residues. (1...QCON).
C**      RESI      = Imag. part of residues. (1...QCON).
C**      NINPUTS   = Number of input pulses
C**      INAMP      = Input amplitudes. (1...NINPUTS).
C**      DELAY     = Input switch times. (0...NINPUTS).
C**                  DELAY(0) assumed 0.
C**      NTOTAL    = Total number of output samples desired.
C**      TSTEP     = Output sample period.
C**
C** OUTPUT:
C**      YOUT      = System output. (0...NTOTAL-1).
C**
C*****
        SUBROUTINE TRANSIM(QCON,RESR,RESI,DAMP,FRQHZ,THRUPUT,NINPUTS,
& INAMP,DELAY,NTOTAL,TSTEP,YOUT)
        IMPLICIT NONE
        INCLUDE 'dimpars.cmn'
        INTEGER QCON,NINPUTS,NTOTAL
        INTEGER IRES0

```

```

      INTEGER I,J,K,L,M,N
      REAL*8 RESR,RESI,DAMP,FRQHZ,INAMP,DELAY,YOUT,THRUPUT
      REAL*8 VOKP,VOK,VIKI,VIKR,TERM3,RESO,EIGR,EIGI,PIE2,T
      REAL*8 X,Y,Z,XR,XI,YR,YI,ZR,ZI
      REAL*4 TSTEP
      DIMENSION RESR(*),RESI(*),DAMP(*),FRQHZ(*),INAMP(*),
& DELAY(0:*),YOUT(0:*)
C
      PIE2=2.0D0*DABS(DACOS(-1.0D0))
      DELAY(0)=0.0D0
C
C FIND TERM AT ZERO IN THE S-PLANE:
      L=0
      X=1.0D12
      DO I=1,QCON
        IF (FRQHZ(I).EQ.0.0D0) THEN
          IF (DABS(DAMP(I)).LT.X) THEN
            X=DABS(DAMP(I))
            L=I
          ENDIF
        ENDIF
      ENDDO
      IRESO=0
      RESO=0.0D0
      IF (X.LT.1.0D-8) THEN
        IRESO=L
        RESO=2.0D0*RESR(IRESO)
      ENDIF
C
C CALCULATE SYSTEM OUTPUT:
      DO K=0,NTOTAL-1
        T=TSTEP*K
        VOKP = 0.0D0
        VOK = 0D0
        DO J=1,NINPUTS
          Y = 0.0D0
          Z = 0.0D0
          IF (T.GE.DELAY(J-1)) Y=1.0D0
          IF (T.GE.DELAY(J)) Z=1.0D0
          VOKP=VOKP+INAMP(J)*(T-DELAY(J-1))*Y-(T-DELAY(J))*Z
          VOK=VOK+INAMP(J)*(Y-Z)
        ENDDO
        TERM3=0.0D0
        DO I=1,QCON
          IF (I.EQ.IRESO) GOTO 200
          EIGR=-DAMP(I)*PIE2
          EIGI=FRQHZ(I)*PIE2
          VIKR=-VOK
          VIKI=0.0D0
          DO J=1,NINPUTS
            Y = 0.0D0
            Z = 0.0D0
            IF (T.GE.DELAY(J-1)) Y=1.0D0
            IF (T.GE.DELAY(J)) Z=1.0D0
            ZR=EIGR*(T-DELAY(J-1))
            ZI=EIGI*(T-DELAY(J-1))
            CALL CEXPRZ(XR,XI,ZR,ZI)
            ZR=EIGR*(T-DELAY(J))
            ZI=EIGI*(T-DELAY(J))
            CALL CEXPRZ(YR,YI,ZR,ZI)
            VIKR=VIKR+INAMP(J)*(XR*Y-YR*Z)
            VIKI=VIKI+INAMP(J)*(XI*Y-YI*Z)
          ENDDO
          CALL CDIVZ(XR,XI,RESR(I),RESI(I),EIGR,EIGI,1)
          CALL CMULTZ(YR,YI,XR,XI,VIKR,VIKI,1)
          TERM3=TERM3+2.0D0*YR
        200 ENDDO
        YOUT(K)=RESO*VOKP+THRUPUT*VOK+TERM3
      ENDDO
C
      RETURN
      END
C*****
C**
C** $Id: order.f,v 1.1.2.1 1992/09/28 16:40:17 d3f011 Exp d3f011 $

```



```

C** SUBROUTINE ORDER
C** Written by D. Trudnowski, PNL, April 1992.
C**
C** This subroutine reorders the paramters of
C**
C**      QCON
C**      yhat(t)=sum AMPOPT(i)*exp(t*DAMP(i)*2*pi)*cos(FRQHZ(i)*2*pi+
C**              i=1                                PHASE*180/pi)
C**
C** so that the Akaike Information Criteria (AIC) between the measurement
C** data XSIG(0...NNFIT-1) and yhat is minimized for a orders 1 thru QCON.
C**
C** INPUTS:
C**      NNFIT = Number of measurment data points.
C**      XSIG  = Measurement data. (0...NNFIT-1).
C**      TSTEP = Sample period.
C**      QCON  = Number of modes.
C**      AMPOPT = Mode amplitudes. (1...QCON).
C**      DAMP   = Mode damping factors. (1...QCON).
C**      FRQHZ  = Mode frequencies. (1...QCON).
C**      PHASE  = Mode phases. (1...QCON).
C**
C** OUTPUTS:
C**      AMPOPT = Mode amplitudes reordered. (1...QCON).
C**      DAMP   = Mode damping factors reordered. (1...QCON).
C**      FRQHZ  = Mode frequencies reordered. (1...QCON).
C**      PHASE  = Mode phases reordered. (1...QCON).
C**      AIC    = Akaike Information Criteria for each order.
C**              (1...QCON).
C*****
      SUBROUTINE ORDER(NNFIT,XSIG,TSTEP,QCON,AMPOPT,DAMP,FRQHZ,
& PHASE,AIC,INSTEP,DCTERM)
      IMPLICIT NONE
      INCLUDE 'dimpar.cmn'
      INTEGER NNFIT,QCON,INSTEP
      INTEGER NORTEMP,ICOUNT,ISAVE(NSIZE),ISV,NSTART,NDATA,NORDER,
& IDC,IDCN
      INTEGER I,J,K,L,M,N
      REAL*8 XSIG,AMPOPT,DAMP,FRQHZ,PHASE,AIC,POLMIN
      REAL*8 YNORM,AICOLD,AICNEW,YDEL,YHAT,PIE,PIE2,AMPTEMP(NSIZE),
& DAMTEMP(NSIZE),FRTEMP(NSIZE),PHTEMP(NSIZE),T,AICNEW2,AICOLD2,
& FPENEW,FPEOLD,DCTERM,AMPDC
      REAL*8 X,Y,Z,DUMMY
      REAL*8 DENERGY
      REAL TSTEP
      DIMENSION XSIG(0:*),AMPOPT(*),DAMP(*),FRQHZ(*),PHASE(*),
& AIC(*),DUMMY(0:NTAILLE)
C
      PIE=DABS(DACOS(-1.0D0))
      PIE2=2.0D0*PIE
C
C DUE TO NOISE EFFECTS AT THE BEGINNING OF
C THE SIGNAL, START ERROR CALCULATIONS AT NSTART:
      NSTART=3
      IF (NNFIT.LE.(NSTART+1)) THEN
        WRITE(*,*)' ERROR IN ORDER'
        STOP
      ENDIF
      NDATA=NNFIT-NSTART
C
C NORM OF MEASUREMENT DATA:
      DO I=NSTART,NNFIT-1
        DUMMY(I-NSTART)=XSIG(I)
      ENDDO
      YNORM=DENERGY(DUMMY,NDATA)*DFLOAT(NDATA)
C
C SAVE PRESENT MODEL AND SAVE DC TERM FOR A THRUPUT IF THE INSTEP IS 1:
      AMPDC=0.0D0
      DCTERM=0.0D0
      POLMIN=1.0D-3
      NORDER=0
      IDC=0
      IDCN=0
      DO I=1,QCON
        IF (INSTEP.EQ.1) THEN
          IF (FRQHZ(I).EQ.0.0D0) THEN

```

```

        IF (DABS(DAMP(I)).LT.POLMIN) THEN
            POLMIN=DABS(DAMP(I))
            IDC=I
            DCTERM=AMPOPT(I)*DCOS(PHTEMP(I)*PIE/180.0D0)
            AMPDC=AMPOPT(I)
        ENDIF
    ENDIF
ENDIF
AMPTEMP(I)=AMPOPT(I)
DAMTEMP(I)=DAMP(I)
FRTEMP(I)=FRQHZ(I)
PHTEMP(I)=PHASE(I)
ENDDO
IF (IDC.GT.0) THEN
    AMPTEMP(IDC)=0.0D0
    AMPOPT(IDC)=0.0D0
ENDIF
C
C REORDER TO MINIMIZE AIC:
    NORTEMP = 0
100  ICOUNT = 1
    AICOLD = 1.0D+35
    AICOLD2 = 1.0D+35
    FPEOLD = 1.0D+35
    DO WHILE (ICOUNT.LE.QCON)
        IF (NORTEMP.GT.0) THEN
            DO J=1,NORTEMP
                IF (ICOUNT.EQ.ISAVE(J)) GOTO 200
            ENDDO
        ENDIF
        ISAVE(NORTEMP+1)=ICOUNT
C
C CALCULATE YHAT AND THE ERROR ASSOCIATED WITH YHAT FOR
C ORDER NORTEMP+1:
        N=NORTEMP+1
        YDEL=0.0D0
C
C-----CALCULATE YHAT
        DO K=NSTART,NNFIT-1
            T=TSTEP*K
            YHAT=DCTERM
            DO I=1,N
                L=ISAVE(I)
                YHAT=YHAT+AMPTEMP(L)*DEXP(-T*DAMTEMP(L)*PIE2)*
&                DCOS(T*FRTEMP(L)*PIE2+PHTEMP(L)*PIE/180.0D0)
            ENDDO
            YDEL=YDEL+(XSIG(K)-YHAT)**2
        ENDDO
        IF ((N*4).EQ.NDATA) THEN
            Z=1.0D+12
        ELSE
            Z=(1.0D0+DFLOAT(N*4)/DFLOAT(NDATA))/
&            (1.0D0-DFLOAT(N*4)/DFLOAT(NDATA))
        ENDIF
        FPENEW=DLOG(YDEL*Z/(YNORM*NDATA))
        AICNEW=NDATA*DLOG(YDEL/DFLOAT(NDATA))+8.0D0*DFLOAT(N)-
&        DLOG(YNORM)
        AICNEW2=NDATA*DLOG(YDEL/(DFLOAT(NDATA)*YNORM))+
&        8.0D0*DFLOAT(N)
C
C-----TEST ERROR;
        IF (AICNEW2.LT.AICOLD2) THEN
            FPEOLD = FPENEW
            AICOLD = AICNEW
            AICOLD2 = AICNEW2
            ISV = ICOUNT
        ENDIF
200  ICOUNT = ICOUNT +1
    ENDDO
    NORTEMP = NORTEMP + 1
    AMPOPT(NORTEMP)=AMPTEMP(ISV)
    IF (ISV.EQ.IDC) IDCN=NORTEMP
    DAMP(NORTEMP)=DAMTEMP(ISV)
    FRQHZ(NORTEMP)=FRTEMP(ISV)
    PHASE(NORTEMP)=PHTEMP(ISV)
    ISAVE(NORTEMP) = ISV

```

```
AIC(NORTEMP) = AICOLD2
IF (NORTEMP .LT. QCON) GOTO 100
C
IF (IDCN.GT.0) AMPOPT(IDCN)=AMPDC
C
RETURN
END
```

Distribution

No. of Copies	Offsite	No. of Copies	Onsite
12	DOE/Office of Scientific and Technical Information		Department of Energy Richland Field Office
2	J. F. Hauer, EOH Bonneville Power Administration P.O. Box 3621 Portland, OR 97208		D. R. Segna
	L. L. Scharf Department of Electrical and Computer Engineering Engineering Center OT 3-12 University of Colorado at Boulder Boulder, CO 80309-0425	19	Pacific Northwest Laboratory M. K. Donnelly D. M. Elwood L. D. Kannberg D. J. Trudnowski (10) Publishing Coordination Technical Report Files (5)
	J. Agee M.S. D-3772 U.S. Bureau of Reclamation P.O. Box 25007 Denver, CO 80225		
	D. A. Pierre Electrical Engineering Department Montana State University Bozeman, MT 59717		

END

**DATE
FILMED**

3 / 8 / 93