PNL--8495

DE93 007463

STABILITY ANALYSIS OF LARGE
ELECTRIC POWER SYSTEMS

D. M. Elwood

January 1993

Prepared for
the Bonneville Power Administration
under a Related Services Agreement
with the U.S. Department of Energy
Contract DE-AC06-76RLO 1830

Pacific Northwest Laboratory
Richland, Washington 99352

MASTER

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

SUMMARY

Modern electric power systems are large and complicated, and, in many regions of the world, the generation and transmission systems are operating near their limits. Ensuring the reliable operation of the power system requires engineers to study the response of the system to various disturbances. The responses to large disturbances are examined by numerically solving the nonlinear differential-algebraic equations describing the power system. The response to small disturbances is typically studied via eigenanalysis. The Electric Power Research Institute (EPRI) recently developed the Extended Transient/Mid-term Stability Program (ETMSP) to study large disturbance stability and the Small Signal Stability Program Package (SSSP) to study small signal stability.

The primary objectives of the work described in this report were to 1) explore ways of speeding up ETMSP, especially on mid-term voltage stability problems, 2) explore ways of speeding up the Multi-Area Small-Signal Stability program (MASS), one of the codes in SSSP, and 3) explore ways of increasing the size of problem that can be solved by the Cray version of MASS.

At the request of the Bonneville Power Administration (Bonneville), the Pacific Northwest Laboratory (PNL) conducted a literature review of methods currently used for the transient/mid-term stability analysis of large electric power systems, PNL also reviewed general methods for the numerical solution of differential equations that are applicable to large power systems. The use of supercomputers was also explored. PNL found the following: 1) several techniques (e.g. variable step size, partitioning, etc.) that have been described in the power system literature but not used in ETMSP could probably provide a significant speed up of ETMSP on many problems, 2) there are a few algorithms for the numerical solution of ordinary differential equations that have not been tried on power system problems but may be useful in certain situations, 3) 40 MFLOPS super-workstations can probably run ETMSP as much as

10 times faster than 0.40 MFLOPS workstations like those currently used at Bonneville, and 4) current parallel and vector supercomputers and algorithms appear to be of limited value for running ETMSP.

The next step in evaluating improved algorithms in ETMSP appears to be the development of a variable step size implementation of the trapezoidal rule. This code should then be used to evaluate 1) the impact of limits and tap changes on variable step size codes, and 2) the possibility of using partitioning algorithms to integrate different devices with different step sizes. Finally, the backward differentiation formulas should be tested.

PNL also investigated ways of speeding up MASS and increasing the size of problem that can be solved by the Cray version of MASS. Bonneville was specifically interested in being able to solve problems with at least 3,000 states. PNL, under a previous contract with Bonneville, converted MASS to run on the Hanford Cray X-MP EA/232 and found that a problem with about 2,200 states could be solved in approximately 26 minutes. During the current work it was found that 1) the LAPACK software package is generally more versatile, robust, and faster than the EISPACK software package that is currently in MASS, 2) simple modifications to MASS would allow problems with approximately 2,800 states to be solved on the Hanford Cray X-MP EA/232; also, problems with 3,000 to 4,000 states can be solved by using one of the Crays at the Los Alamos National Laboratory, 3) a block version of the main computational algorithm in MASS runs as much as twice as fast as the original algorithm on some cache-based machines, and 4) a small cluster of super-workstations may be able to run a parallel version of MASS fast enough to solve problems with several thousand states in under an hour.

The work on MASS shows that it can be improved by replacing the main computational routines by LAPACK routines and adding an option to compute condition numbers and invariant subspaces. It would also be useful to eliminate the use of two of the large arrays in MASS and to experiment with a

parallel version of MASS on a vector supercomputer or on a small cluster of super-workstations.

CONTENTS

SUMMARY	iii
1.0 INTRODUCTION	1.1
2.0 TRANSIENT/MID-TERM STABILITY OF POWER SYSTEMS	2.1
2.1 TRANSIENT/MID-TERM STABILITY	2.2
2.2 NUMERICAL METHODS USED FOR ORDINARY DIFFERENTIAL EQUATIONS	2.5
2.3 NUMERICAL METHODS USED FOR STABILITY SIMULATIONS	2.12
2.3.1 Methods for Transient Stability Problems	2.12
2.3.2 Methods for Longer-Term Stability Problems	2.17
2.4 DESCRIPTION AND EVALUATION OF ETMSP	2.21
2.4.1 Algorithms in ETMSP	2.21
2.4.2 General Comments About ETMSP	2.24
2.4.3 Explicit Methods in ETMSP	2.28
2.4.4 Implicit Methods in ETMSP	2.34
2.5 ADVANCED ARCHITECTURE COMPUTERS FOR STABILITY ANALYSIS	2.42
2.5.1 Super-Workstations	2.42
2.5.2 Vector Supercomputers	2.44
2.5.3 Parallel Supercomputers	2.51
2.5.4 Conclusions	2.59
2.6 GENERAL METHODS FOR SPEEDING UP AN ODE CODE	2.62
2.7 IMPROVED INTEGRATION ALGORITHMS FOR POWER SYSTEMS	2.65
2.7.1 Region 1 - Fixed Step Size Algorithms	2.66
2.7.2 Region 1 - Variable Step Size Algorithms	2.70

2.7.3	Region 2	2.81
2.7.4	Region 3	2.83
2.7.5	Conclusions	2.87
2.8	SUMMARY	2.89
3.0	EIGENANALYSIS OF LARGE POWER SYSTEMS	3.1
3.1	IMPROVING THE PORTABILITY OF MASS	3.2
3.2	INCREASING THE PROBLEM SIZE IN MASS	3.5
3.3	SPEEDING UP MASS	3.12
3.4	INCREASING THE VERSATILITY OF MASS	3.21
3.5	PARALLEL QR ALGORITHM	3.22
3.6	SPARSE EIGENANALYSIS	3.27
3.7	SUMMARY	3.27
4.0	REFERENCES	4.1
APPENDIX A - CONVERSION OF BPA POWERFLOW TO RUN ON A CRAY		A.1

TABLES

3.1	LAPACK on Various Computers	3.15
3.2	EISPACK on Various Computers	3.15
3.3	LAPACK (Eigenvalues Only) on Various Computers	3.17
3.4	EISPACK (Eigenvalues Only) on Various Computers	3.17
3.5	LAPACK/EISPACK on 1000 by 1000 Problem	3.17
3.6	LAPACK/EISPACK (Eigenvalues Only) on 1000 by 1000 Problem	3.18
3.7	SHSEQR versus Number of Shifts	3.19
3.8	Parallel QR Algorithm	3.23
3.9	Block QR Algorithm	3.24
3.10	Parallel versus Block QR Algorithm	3.24

1.0 INTRODUCTION

Modern electric power systems throughout the world are large and complex. In the United States, enormous amounts of power are transferred between various regions; in some of those regions, the generation and transmission systems are operating near their limits. The behavior of these large power systems is complicated. The reliable design and operation of a power system requires an understanding of this complex behavior.

One method used in analyzing power system behavior is stability analysis. Two main types of power system stability are typically analyzed: 1) large signal stability and 2) small signal stability.

Large signal stability describes the response of a power system to large disturbances. The nonlinear characteristics of a power system have a significant impact on its response to large disturbances. Thus, the analysis of large signal stability usually involves using time domain methods to solve the nonlinear differential-algebraic equations governing the behavior of the power system. This type of stability is studied by transient, mid-term, and long-term stability simulations. Transient stability simulations model the first 5 to 10 seconds following a disturbance and are concerned with problems such as loss of synchronism. Mid-term stability simulations model the first few minutes following a disturbance and are concerned with problems such as voltage collapse. Long-term stability simulations model longer term problems.

Small signal stability is the extent to which a power system responds to small disturbances. The nonlinear characteristics of the power system can usually be ignored when analyzing its response to small disturbances. Thus, small signal stability is usually analyzed by linearizing the system equations about a specific operating point and using eigenanalysis to analyze the linearized system.

In the past, transient stability has been the main concern of power system analysts. However, as power systems increase in size and operate

closer to their limits, mid-term stability (Taylor and Rodrigues, 1992) and small signal stability (Van Ness et al. 1980) are becoming more important.

Currently available production-grade software such as EPRI's Extended Transient/Mid-Term Stability Program (ETMSP) can do a 10-second transient stability simulation of a problem with a few hundred generators and a few thousand buses in 10 to 20 minutes on a VAXstation 4000/60. The Bonneville Power Administration (Bonneville) has found that on a VAXstation 3100 ETMSP takes about 6 hours to run a 2-minute voltage stability simulation with 4,960 buses, 8,896 branches, 411 generators, 573 induction motors, 719 under-load tap changing transformers, 729 thermostatically controlled loads, and about 50 undervoltage load-shedding relays (Taylor and Rodrigues, 1992). Furthermore, it would be useful to do voltage stability simulations for 4 minutes or more of real time.

EPRI's Multi-Area Small Signal Stability Program (MASS) can perform a complete eigenanalysis of power systems containing up to about 500 states (Kundur, Rogers, and Wong 1988). Modern power system problems, however, typically involve several thousand states. A Cray version of MASS (Elwood 1991) can solve a problem with about 2,200 states in about 26 minutes on the Hanford Cray X-MP EA/232. Larger problems cannot be solved on this machine because of memory constraints (each job is limited to a maximum of 16 megawords on the Hanford Cray).

Bonneville is interested in incorporating mid-term stability analysis and eigenanalysis as a regular part of the power system design process. Thus, they commissioned the Pacific Northwest Laboratory (PNL) to study the problems of 1) speeding up transient/mid-term stability analysis of large power systems using ETMSP, 2) speeding up MASS, 3) increasing the size of problem that can be solved by the Cray version of MASS, and 4) modifying Bonneville's powerflow program to run on a Cray for use with the Cray version of MASS.

The work done for Bonneville consisted of four main tasks. The first task was to perform a literature review of methods that have been used for the

transient/mid-term stability analysis of large power systems and of general methods for solving differential equations that could be applied to large power system problems. The goals of this review were to determine the best methods currently available for the transient/mid-term stability analysis of large power systems and to identify any new methods that might be used for this problem. The second task was to examine the possibility of using advanced architecture computers, such as vector and parallel supercomputers, to do transient/mid-term stability simulations using ETMSP. The objective here was to determine if modern supercomputers could be used to significantly speed up ETMSP. The third task was to determine if the new LAPACK software package could be used to improve the reliability and speed of MASS. The fourth task was to examine ways of increasing the size of problem (to at least 3000 states) that can be solved by the Cray version of MASS. The objective of this task was to make it practical to do the complete eigenanalysis of problems of interest to Bonneville.

This report focuses primarily on 1) describing ways to modify ETMSP so it will run faster, i.e., improve the coding of the algorithms currently in the ETMSP, 2) identifying the best types of computers on which to run ETMSP, 3) examining the possibility of using the LAPACK software package to improve the reliability and speed of MASS, and 4) determining ways to increase the size of problem that can be solved by the Cray version of MASS.

This report contains several sections. In Section 2, the transient/mid-term stability problem and ways of speeding up ETMSP are described. Section 3 describes ways of improving MASS and of increasing the size of problem that can be solved by the Cray version of MASS. Appendix A contains the details of modifying Bonneville's powerflow program to run on a Cray, for use with the Cray version of MASS.

2.0 TRANSIENT/MID-TERM STABILITY OF POWER SYSTEMS

Bonneville currently performs large numbers of transient stability simulations, and is starting to do significant numbers of mid-term voltage stability simulations. Bonneville currently uses an in-house transient stability program (Dommel and Sato 1972) for transient stability simulations. This program lacks models for the slow-acting devices required for mid-term stability simulations. Thus, Bonneville uses ETMSP for voltage stability studies. Finally, Bonneville is interested in using ETMSP in place of its in-house program for transient stability problems.

On a VAXstation 4000/60 ETMSP takes about 10 to 20 minutes to do a 10-second transient stability simulation of a problem with a few thousand buses and a few hundred generators. On a VAXstation 3100 ETMSP takes about 6 hours to do a 2 minute voltage stability simulation of a problem with 4,960 buses, 8,896 branches, 411 generators, 572 induction motors, 719 under-load tap changing transformers, 729 thermostatically controlled loads, and about 50 undervoltage load-shedding relays. Furthermore, Bonneville would like to do voltage stability simulations for 4 minutes, or more, of real time (Taylor and Rodrigues 1992). It would be useful to speed up transient stability simulations because they are run so frequently (this is especially true in real time power system control problems). Finally, the time required to do voltage stability simulations is much too long. Bonneville would like to be able to complete these simulations in an hour, or less.

This section explores ways of speeding up ETMSP. In particular, this section 1) describes the transient/mid-term stability problem, 2) describes numerical methods for ordinary differential equations (ODEs), 3) describes the methods that have been used in the power industry for transient/mid-term stability simulations, 4) describes and evaluates the current version of ETMSP, 5) explores the potential use of advanced architecture computers for this problem, 6) evaluates the possible use in ETMSP of general algorithms

used to speed up ODE codes, and 7) evaluates improved integration algorithms for use in ETMSP.

2.1 TRANSIENT/MID-TERM STABILITY

In this subsection the characteristics of transient/mid-term stability simulations that are relevant to the numerical solution of the problem are described. More detailed descriptions of the problem can be found in numerous sources (Dembart et al. 1977; Stott 1979; Anderson and Dembart 1980; Arrillaga and Arnold 1990).

A power system is composed of three main components: 1) the transmission network, 2) generators (and their associated controls), and 3) loads.

The transmission network is a set of nodes connected by transmission lines. The dynamics of the transmission network are several orders of magnitude faster than the rest of the power system. Thus, the transmission network responds almost instantly to disturbances and is modelled using a steady-state approximation. This leads to a set of algebraic equations.

Each generator, and its controls, can be described by a set of ordinary differential equations (ODEs) and a set of algebraic equations. These equations depend upon the state variables of the machine and the voltage at the node where the machine is located. (The equations may depend on the voltage at a few other nodes if the device uses remote sensing.) The number of differential equations associated with each machine may vary from 2 to about 20, depending on the amount of detail used in the model.

Generally, loads on the network are modeled using algebraic equations. Occasionally certain loads, such as large motors, may be modeled in detail. In this case the load is modeled by a set of differential-algebraic equations similar to those used to model a generator.

The complete set of equations describing a power system can be written in the form

$$\dot{x} = f(x, v) \quad (2.1)$$

$$Yv = I(x, v) \quad (2.2)$$

where x is the vector of state variables defined by differential equations, v is the vector of network voltages, $I(x, v)$ is the vector of current injections into the network, and Y is the network admittance matrix. $I(x, v)$ has non-zero components only at those nodes where there is a nonlinear load or some other device. Y is a large sparse matrix that is usually symmetric and complex. Furthermore, Y only changes when the network is modified. Equation (2.1) governs the behavior of the various machines and consists of many small subsets that interact only through the network. Equation (2.2) governs the behavior of the network.

Typical power system problems in the western United States have 2,000 to 5,000 nodes in the network and 3,000 to 7,000 state variables (i.e., a few hundred generators). Problems in the eastern United States may be several times larger than this.

Transient/mid-term stability simulations are done by solving Equations (2.1) and (2.2) numerically. Power systems have several characteristics that must be considered when solving these equations.

First, the purpose of a stability simulation is to determine whether or not a power system is stable, not to predict the future state of the system. Thus, a few percentage points of error in the global solution is usually acceptable. In general two to three significant digits per step seems to be sufficient to achieve this goal (Dembart et al. 1977).

Second, the problem is moderately stiff, i.e., the fastest time constant for a generator, including its controls, is typically around 0.01 seconds, while the slowest time constants in the problem are on the order of several seconds. The fastest equations are usually limited to a subset of the generator equations, typically the exciter equations.

Third, in many cases some of the devices experience slowly damped, low frequency oscillations, i.e., with periods of 1 to 2 seconds.

Fourth, the problem contains frequent discontinuities in the first and second derivatives of the state variables. This is probably the most difficult part of the problem and will be described in more detail.

A transient stability simulation experiences two main types of discontinuities. First, frequent discontinuities are caused by limits on variables and/or their derivatives. These discontinuities tend to be the most severe and frequent in the first few seconds of a simulation. Second, large, infrequent discontinuities are caused by changes in the network, e.g., due to a fault.

Voltage stability is the main type of mid-term stability of interest in this report. A voltage stability simulation can be broken down into three periods. Period one is the first few seconds of the simulation. This part of the simulation is similar to a transient stability simulation, except that the discontinuities caused by limits tend to be less frequent and less severe. The second period starts at a few seconds and lasts until under-load tap changing (ULTC) transformers start operating. In this period the problem is relatively smooth with infrequent discontinuities. Finally, the third period is the rest of the simulation during which ULTC transformers are operating.

Each tap change causes a small discontinuity in the network voltages. The small time constants in some of the differential equations, however, can significantly magnify these small changes in voltage. A particular transformer may change the Y matrix once every few seconds until it reaches its limit of operation, or until the node's voltage is restored. Many voltage stability simulations, however, have hundreds of ULTC transformers. Hence several tap changes may occur every second. Finally, in many simulations the ULTC transformers have an initial time delay of about 30 seconds, thus tap changes typically do not start occurring until about 30 seconds into the simulation.

2.2 NUMERICAL METHODS USED FOR ORDINARY DIFFERENTIAL EQUATIONS

This subsection provides a brief introduction to the numerical solution of ODEs. More details can be found in Gupta, Sacks-Davis, and Tischer (1985) and elsewhere (Gear 1971; Shampine and Gear 1979; Watts 1980; Shampine 1980; Enright 1984; Aiken 1985; Byrne and Hindmarsh 1987; Fatunla 1988).

There are many problems where an ODE of the form

$$x' = f(x), \quad x(0) = x_0 \quad (2.3)$$

must be solved for $x(t)$ over some interval, where x and f are vectors of length n . For simplicity it has been assumed the f is a function of x but not time. In most cases Equation (2.3) cannot be solved analytically, hence numerical methods must be used.

Most numerical methods for solving Equation (2.3) generate a sequence of approximate solutions $x_i \approx x(t_i)$, where t_i is a set of time points. The simplest method for solving this problem is Euler's method which computes the sequence

$$x_{n+1} = x_n + hf(x_n), \quad n=0, 1, 2, \dots \quad (2.4)$$

where h is the step size, and $x_0 = x(0)$. Two important properties of a numerical method for solving Equation (2.3) are the accuracy and stability of the method.

The local truncation error (LTE) is a measure of the accuracy of a method when taking one step, starting from the exact solution. The LTE of Euler's method is obtained by substituting the exact solution of Equation (2.3) into Equation (2.4):

$$d_{n+1} = x(t_{n+1}) - x(t_n) - hf(x(t_n)) = \frac{h^2}{2} x''(\xi) \quad (2.5)$$

where ξ is some number between t_n and t_{n+1} . The global error of a method is given by $e_{n+1} = x(t_{n+1}) - x_{n+1}$, and represents the difference between the

numerical and exact solutions to the problem. The global error for a method depends on the LTE of the method and on how local errors propagate. In general, a method is said to be of order k if the LTE is $O(h^{k+1})$. Euler's method is a first order method, i.e., it has a LTE which is $O(h^2)$. If the LTE for a method is $O(h^{k+1})$, then the global error is generally $O(h^k)$.

The users of ODE codes would like to control the global error of the numerical solution. This is difficult and expensive to do, hence most ODE codes control the local error. As a general rule, higher order methods can take bigger steps than lower order methods to achieve the same accuracy. This is especially true at stringent tolerances. Thus, much of the work in the numerical solution of ODEs has focused on finding high order methods.

The stability of a method for solving ODEs is concerned with how local errors propagate. The way stability is typically studied is to determine how the method behaves when applied to the simple test problem

$$x' = \lambda x, \quad x(0) = x_0 \quad (2.6)$$

whose exact solution is

$$x(t) = x(0) e^{\lambda t}. \quad (2.7)$$

The motivation for using this as a test problem is that, locally Equation (2.3) can be linearized and a principal axis transformation used to convert the linearized system into a set of equations like Equation (2.6). Using Equation (2.6) to study the stability of numerical methods has been very successful, but it has its limitations. Thus, more general test equations have been proposed for studying stability (Fatunla 1988).

Clearly, the exact solution of Equation (2.6) grows if $\lambda > 0$ and decays if $\lambda < 0$, and a numerical solution should have this same behavior. The solution of Equation (2.6) given by Euler's method is

$$x_n = (1 + h\lambda)^n x_0 \quad (2.8)$$

which is a good approximation to Equation (2.7) when $h\lambda$ is small. If the real part of λ is less than zero, then Equation (2.8) decays if and only if $|1 + h\lambda| < 1$. The region of absolute stability of a method is defined to be the set of points $z = h\lambda$ in the complex plane for which the numerical solution of Equation (2.6) converges to zero as n approaches infinity. Thus, the region of absolute stability of Euler's method is the disk of radius one centered at 1. A method is called A-stable if its region of absolute stability includes the entire left half-plane.

Many physical problems have many different time scales, i.e., some quantities change very rapidly while others change very slowly. Problems in which the smallest time constants are several orders of magnitude smaller than the largest time constants are generally called stiff. This term comes from problems involving systems of springs with widely varying stiffness constants. Stiff problems typically have an initial transient region in which the solution has rapidly decaying terms associated with the fast variables, followed by a region in which the solution changes slowly. In the transient region, the step size must be small enough to accurately follow the rapid portion of the solution.

In the slowly varying region it is desirable to use a step size small enough to accurately follow the slowly varying component of the solution but not the fast components, which are no longer present. When taking a step, however, a transient component that is small relative to the slowly varying component of the solution will be introduced into the numerical solution. In the slowly varying region it is only necessary that this small transient error component remain small, and preferably decay rapidly, not that it be integrated accurately. This will occur only if $h\lambda$ is in the region of absolute stability of the method, where λ is the eigenvalue of the linearized system associated with the fastest component of the general solution. Thus,

the step size that a numerical method can use is limited by 1) the accuracy of following the solution, and 2) stability. For stiff problems, stability considerations can impose a severe limitation on the step size in the slowly varying region unless the region of absolute stability of the numerical method contains all or most of the left half-plane. A problem is considered to be stiff in the slowly varying region of the integration, but non-stiff in the transient region.

A numerical method is classified as implicit if it must solve a set of implicit equations to step from time t_n to time t_{n+1} ; otherwise the method is called explicit. The region of absolute stability of an explicit method generally contains only a small portion of the left half-plane. Thus, explicit methods do not work well on stiff problems. Hence, all methods for stiff problems are implicit. In general, taking a step with an implicit method is much more expensive than taking a step with an explicit method. On stiff problems, however, implicit methods can take much bigger steps and are faster than explicit methods. Most stiff problems have an initial transient phase. Furthermore, disturbances can re-excite a transient phase in a stiff problem. In these transient regions the problem is not stiff and explicit methods are best. Thus, there has been some work on algorithms that can switch between stiff and non-stiff methods, depending on whether or not the transient components of the solution are present.

The remainder of this subsection will describe some of the most common methods for solving ODEs. More details will be given in section 2.7.

The main explicit methods used to solve ODEs are the Runge-Kutta, Adams-Moulton, and extrapolation methods (Gupta, Sacks-Davis, and Tischer 1985).

Extrapolation methods are used primarily when a high degree of accuracy is needed. Extrapolation methods require that the solution of the system of ODEs be smooth, therefore they are not appropriate for power system problems.

An r -stage Runge-Kutta method takes a step using the formula

$$x_{n+1} = x_n + \sum_{i=1}^r b_i K_i \quad (2.9)$$

where the stages K_i are given by

$$K_i = hf(x_n + \sum_{j=1}^r a_{ij} K_j), \quad i=1, 2, \dots, r. \quad (2.10)$$

A Runge-Kutta method is explicit if $a_{ij} = 0$ for $j \geq i$. In the rest of this paper all references to Runge-Kutta methods will mean the explicit versions, unless stated otherwise. Runge-Kutta methods are usually implemented as variable step size, fixed order methods.

The Adams-Moulton method is actually a family of linear multistep formulas of various orders. A k -step linear multistep formula computes x_{n+1} using the data from k previous steps using the formula

$$x_{n+1} = h\beta_0 f(x_{n+1}) + \sum_{i=1}^k [h\beta_i f(x_{n+1-i}) - \alpha_i x_{n+1-i}]. \quad (2.11)$$

The method is explicit if $\beta_0 = 0$, otherwise it is implicit. The Adams-Bashforth (AB) formulas have $\alpha_1 = 1$, $\alpha_i = 0$, $i = 2, 3, \dots, k$, and $\beta_0 = 0$, while the Adams-Moulton (AM) formulas have $\alpha_1 = 1$, $\alpha_i = 0$, $i = 2, 3, \dots, k$, and $\beta_0 \neq 0$. Thus, the AB methods are explicit, while the AM methods are implicit. The AM formulas are inappropriate for stiff problems because the formulas of order greater than two have small regions of absolute stability. The most common way to use the Adams formulas is as a predictor-corrector method. This method steps from time t_n to time t_{n+1} by using an AB formula to predict a value, x_{i+1}^0 , for x_{n+1} and uses an AM formula to correct the solution using

$$x_{n+1}^{m+1} = h\beta_0 f(x_{n+1}^m) + x_n + h \sum_{j=1}^k \beta_j f(x_{n+1-j}^m), \quad m=0, 1, 2, \dots \quad (2.12)$$

Equation (2.12) may be iterated to convergence, or iterated a fixed number of times. The iterations in Equation (2.12) are referred to as functional iteration and will converge if

$$\|h\beta_0 \partial f / \partial x\| < 1 \quad (2.13)$$

for some matrix norm, where $\partial f / \partial x$ is the Jacobian matrix of f . The condition given by Equation (2.13) is usually easy to satisfy for non-stiff problems but severely restricts the step size on stiff problems. On stiff problems the nonlinear implicit equations like Equation (2.11) must be solved using a method such as Newton's method if the step size restriction imposed by Equation (2.13) is to be avoided. The AM formulas are usually implemented as variable step size, variable order codes.

AM codes are the most popular for solving general non-stiff problems. The cost of taking a step using a method consists of function evaluations, i.e., evaluating $f(x)$ for various values of x , and all the other work, called overhead. AM codes usually require fewer function evaluations than Runge-Kutta codes but have more overhead. Thus, the AM codes are usually superior on problems in which the average cost per equation of evaluating $f(x)$ is moderately high, while the Runge-Kutta methods are better when the cost of evaluating $f(x)$ is low. AM codes are also superior when a problem is integrated using strict error tolerances because of the high order formulas available in these codes. The multistep nature of AM codes causes them to suffer more than Runge-Kutta methods if a problem has frequent discontinuities. The impact of discontinuities on AM codes can be reduced by using Runge-Kutta starters to restart the integration at high order following a discontinuity (Gear 1980).

The trapezoidal rule defined by

$$x_{n+1} = x_n + \frac{h}{2} (f(x_n) + f(x_{n+1})) \quad (2.14)$$

is popular in the power industry. This method is second order accurate. If the trapezoidal rule is applied to Equation (2.6) and $h\lambda$ is moderate to large, then the numerical solution behaves approximately like $x_n = (-1)^n x(0)$. This is an undesirable property for a stiff method since in the stiff region one wants to use a step size h such that $h\lambda$ is large, where λ corresponds to a transient component that has died out. In particular, this property of the trapezoidal rule means that small transients that decay rapidly in the exact solution may remain in the numerical solution as slowly damped, oscillatory components. This property can restrict the step size (Enright 1974).

The most popular methods for solving stiff systems of ODEs are the Backward Differentiation Formulas (BDFs), sometimes called the GEAR method (Gear 1971). The BDFs are a family of linear multistep methods like Equation (2.11) in which $\beta_i = 0$, $i = 1, 2, \dots, k$. The first and second order BDFs are A-stable. The regions of absolute stability for the higher order methods do not include part of the complex plane near the imaginary axis. This problem gets more severe as the order of the BDF increases. This property means that the higher order BDFs usually do not work well (i.e., must use small step sizes) on problems that have eigenvalues close to the imaginary axis. This step size restriction is severe if the imaginary parts of these eigenvalues are large, but will be moderate or non-existent if the imaginary parts of these eigenvalues are small. Most code comparisons have shown that the BDFs are the best methods for stiff problems, unless the problem has eigenvalues near the imaginary axis.

There are several versions of the BDFs. The fixed coefficient version of the BDFs (Gear 1971) can be unstable if the step size is changed frequently. The Newton iteration matrix usually has to be re-factored when the step size changes. Thus, most codes try not to change the step size too often, and instabilities caused by frequent step size changes are usually not a problem.

Some problems, however, require frequent changes in step size. This has led to the development of the variable coefficient and fixed leading coefficient BDFs (Brown, Byrne, and Hindmarsh 1989; Byrne and Hindmarsh 1975; Jackson and Sacks-Davis 1980) which can safely handle frequent changes in step size.

Most research on stiff methods has focused on finding algorithms that have better stability properties near the imaginary axis than the BDFs. Some of the methods that have been considered as alternatives to the BDFs are the implicit Runge-Kutta, Rosenbrock, second derivative, blended linear multistep, and composite and cyclic multistep formulas (Gupta, Sacks-Davis, and Tischer 1985). The implicit Runge-Kutta and Rosenbrock methods are one-step methods, while the other methods are multistep methods. These methods are generally more expensive than the BDFs, hence they are only preferred over the BDFs on problems requiring the improved stability near the imaginary axis. Some of these methods will be described in Section 2.7.

2.3 NUMERICAL METHODS USED FOR STABILITY SIMULATIONS

The problem to be solved in transient/mid-term stability simulations is given by Equations (2.1) and (2.2). Given that $\partial(I-Yv)/\partial v$ is non-singular, then Equation (2.2) can be solved for v , and the result substituted into Equation (2.1) to obtain a standard ODE. Thus, standard ODE methods are applicable to the transient/mid-term stability problem. The main effect of Equation (2.2) is to make the problem more complicated and require that very large sparse linear systems be solved, even when using explicit integration algorithms. The treatment of these sparse linear systems is well developed in the power system community (Alvarado, Tinney, and Enns 1992). This section is divided into two subsections. The first discusses the transient stability problem, while the second one discusses longer-term stability problems.

2.3.1 Methods for Transient Stability Problems

Over the years many of the standard integration methods (e.g., explicit Runge-Kutta, the various Adams methods, the trapezoidal rule, the BDFs, etc.)

have been tried in various experimental and production grade codes on power system problems, mostly on transient stability problems (Stott 1979). The study of mid-term stability is of more recent interest than transient stability, and fewer published results are available.

In general, production grade transient stability codes use fixed order, fixed time step (generally steps on the order of 0.01 seconds) integration methods, without attempting to estimate or control the error. Most of these codes allow the user to specify different time steps in different intervals, but the codes are still basically fixed time step. Furthermore, they do not attempt to locate where discontinuities occur due to variables hitting or backing off limits. They simply enforce limits on variables as necessary.

Most studies testing new algorithms for stability problems look at relatively small test problems and frequently use fairly simple models. Thus, it is difficult to predict how well the algorithms tested in these papers would work on realistic problems. Furthermore, most people write their own stability codes to test the integration algorithms that they are considering. Thus, there may be great variability in how the codes perform, independent of what integration algorithm is used. This makes it very difficult to make meaningful comparisons of the results obtained with different integration algorithms. An example of this problem is given by Shampine, Watts, and Davenport (1976). They found that two general ODE codes performed very differently on a set of test problems, even though they both implemented the same Runge-Kutta formula. It would be much easier to compare the results people obtain using different integration algorithms if 1) there was a reference stability code designed in such a way that new integration algorithms could be easily implemented by modifying just a few subroutines, and 2) all new integration algorithms were implemented in this reference code and run on a set of large, realistic benchmark problems.

It is assumed that the reader is familiar with the general methods used in the power industry to solve transient stability problems. In particular,

the reader is assumed to be familiar with the review paper of Stott (1979). Following are some of the main points of that paper:

- Euler's method requires too small a step size to be competitive with other methods.
- In theory explicit multistep methods are better than Euler's method, but they suffer more from the discontinuities in the problem and have small regions of absolute stability.
- Explicit Runge-Kutta methods work reasonably well and have been used in several industrial programs (mainly third and fourth order versions).
- Predictor-Corrector methods, e.g., the Adams-Moulton methods, have been tested somewhat. On test problems with limited stiffness and discontinuities, good results have been obtained.
- Some promising results have been obtained using the BDFs in some experimental codes.
- The second order Trapezoidal rule is generally faster than the third and fourth order explicit Runge-Kutta methods, even on non-stiff problems. This is generally explained by the following: 1) lax error tolerances make higher order methods less useful, 2) the nonlinear network equation $YV=I(X,V)$ must be solved even when using explicit methods, and 3) the local truncation error is only part of the error in taking a step. In particular, additional error comes from stepping across discontinuities without locating them and making various approximations.
- Partitioning the system into stiff and non-stiff equations and using different step sizes and/or methods on each of these components may be beneficial. Gross and Bergen (1976, 1977) used an explicit method for the rotor mechanical equations and the BDFs for the other equations. They obtained good results on some simple problems. Johnson, Short, and Cory (1988) describe a similar algorithm that uses the trapezoidal rule instead of the BDFs. Bonneville's transient stability program uses sub-time steps, i.e., they solve most of the equations using one time step, and some of the fastest exciter equations using a smaller sub-time step. This technique has been found to work fairly well for Bonneville.
- Automatic step size control would probably be beneficial.

- Switching to higher order implicit multistep formulas may be beneficial after the first few seconds.

The remainder of this subsection looks at work done since Stott (1979) was published.

A simple integration method is to take a step using the Taylor series approximation to $x(t)$. This method can be of arbitrarily high order, but requires computing high order derivatives of $x(t)$ which requires computing derivatives of $v(t)$. The method has the advantage that Equation (2.2) only needs to be solved once per time step, while a k -stage Runge-Kutta method requires that Equation (2.2) be solved k times per time step. Momoh (of Howard University) and Ray (of Bonneville) have suggested the use of this method on power systems and have obtained good results on some simple problems.

The theta method, also called the damped trapezoidal rule, is given by

$$x_{n+1} = x_n + h_n [(1-\theta) f(x_{n+1}) + \theta f(x_n)] \quad (2.15)$$

This method was described in Liniger and Willoughby (1970). Given a value of λ , there is a value of θ such that the theta method will solve Equation (2.6) exactly. Thus, this type of method is called exponential fitting. When $\theta = 1/2$, this method gives the trapezoidal rule, which is second order. Other values of θ give first order methods.

Johnson, Cory, and Short (1988) found that in a fixed step size code the theta method could use bigger step sizes than the trapezoidal rule on power system problems. To achieve this result θ had to be adjusted at every time step, and a different value of θ had to be used for every equation. These results indicate that a fixed step size version of the theta method might be faster than a fixed step size version of the trapezoidal rule. The information in this paper, however, does not allow a determination of how fast the theta method would be compared to the trapezoidal rule when each method uses a step size appropriate for obtaining the same accuracy.

Zhu and Bose (1992) use the coherent characteristics of generators to partition the generators into groups. These groups are combined into a few clusters, each of which is integrated using a different step size. The devices most impacted by the disturbance are integrated using the smallest time step, while less disturbed devices are integrated using larger time steps. This algorithm was implemented in a code previously developed for the solution of transient stability problems on a parallel computer. The partitioning algorithm was found to speed up the parallel code by a factor of about five on moderately sized systems. All of the results published were for the parallel code, thus it is difficult to predict exactly how much this algorithm would speed up a standard sequential code. However, the available data suggests it would speed up a sequential code by a similar amount. Crow and Illic (1990) use a similar partitioning algorithm. This type of algorithm has been explored somewhat in the numerical ODE community, where it is called multirate integration (Gear and Wells 1984; Skelboe 1989).

When solving the powerflow equations in static security analysis it has been found that many of the variables change very little from iteration to iteration. Thus, "localization" procedures have been developed which essentially skip these constant variables (Ejebe, Paliza, and Tinney 1992). This type of procedure can be extended to stability problems. Brandwajn, Chang, and others from ABB Systems Control Company conducted a study where the voltage and generator states at a node were only updated if the predicted value at the next time step for the voltage, or any of the state variables at that node, is significantly different from its value at the previous time step. Initial results on some large problems yielded 20 to 30% reductions in execution time. A paper describing this work has been submitted to the 1993 Power Industry Computer Application Conference.

2.3.2 Methods for Longer-Term Stability Problems

Most of the work on longer term stability has focused on using simplifying assumptions and/or different integration algorithms after the first few seconds of a simulation.

Luini, Schulz, and Turner (1975) describe a program which makes simplifying assumptions about the long term behavior of the power system and can take large time steps. However, this program cannot handle the transient portions of a simulation, hence must be used in conjunction with a traditional transient stability program. Converti et al. (1976) propose using an algorithm that can switch between a transient and longer-term mode. Their longer-term algorithm uses a network time step of 0.5 to 5 seconds, but a smaller time step for the differential equations. A simplified scheme for computing unit electrical power is used when integrating the differential equations over the larger network time step.

Synchronizing oscillations are usually of concern for the first 10 seconds of a simulation. Furthermore, once synchronizing oscillations have died out a code can usually start taking bigger time steps. Based on this, Frowd, Giri, and Podmore (1982) modified an early version of ETMSP so that artificial damping could be added to the rotor swing equations starting at about 10 seconds, provided the synchronizing oscillations are decaying. This forces these oscillations to die out faster than normal, hence one can take larger time steps for a larger part of the simulation. Provision is made to reduce or remove the artificial damping once the oscillations have decayed.

de Mello et al. (1992) also recognize that in longer-term simulations the synchronizing oscillations are usually not of interest. Based on this they use an implicit method, whose step size is not limited by stability, and take small steps (1/2 cycle) when fast phenomena are of interest and much larger steps (0.1 to 0.2 seconds) for periods where fast transients have subsided. This algorithm is based on long time steps inherently filtering out the high frequency effects and the implicit integration algorithm damping the

oscillatory modes. This paper includes an example of a 25-second simulation of a 2,941-bus, 831-machine system in which the exact solution for a machine's shaft speed has oscillations with a period of about 0.5-seconds superimposed on a slowly varying function. The oscillations remain significant throughout the simulation. Using a time step of 0.1 seconds starting at 5 seconds yields a numerical solution that roughly follows the average value of the oscillatory component of the solution; hence, it approximates the slowly varying part of the solution. The central processing unit (CPU) time required to integrate from 5 seconds out to 25 seconds using a time step of 0.2 seconds was only about one-tenth as large as the time required using a time step of 1/2 cycle (which accurately followed the oscillations). When using the 0.2-second time step, all the swing modes were eliminated. This allows a global system frequency to be used.

Kusljagic and Hajro (1990) developed a similar code based on the theta method. They obtained a speedup of only about 40%, but this was for a 20-second simulation of the small New England 10-machine test system. Alvarado, Lasseter, and Sanchez (1983) showed that the theta method could be used with large time steps to compute the average response of a transmission line model in which the oscillations are not of interest.

Berzins and Furzeland (1992) describe a general ODE solver based on an adaptive version of the theta method. They compared their code to a BDF code on a couple of test problems and found that their code can be competitive with the BDFs at lax error tolerances. This code automatically switches between using functional iteration and Newton's method to solve Equation (2.15), depending on whether the problem is non-stiff or stiff, respectively. This gives the code an advantage over the BDF code which always uses Newton's method to solve the relevant nonlinear equations. The authors conclude that their code can be an advantage on problems which require low accuracy and are of variable stiffness. Most of the advantage of this code, however, seems to

be the ability to switch between functional iteration and Newton's method, rather than in the use of the theta method.

Kurita et al. (1992) describe a code called the Extended Time-Scale Stability analysis program (EXSTAB). EXSTAB has three main modes of operation: Transient Stability Simulation (TSS) mode, Extended-Time Simulation (ETS) mode, and Quasi-Steady-State (QSS) mode. The TSS mode uses the fixed step size second-order Adams-Bashforth formula to simulate transients. No reason is given for why this particular formula is used. The ETS mode uses a variable step size implementation of the theta method with $\theta = .48$ and uses the same models as the TSS mode. The theta method was used because it avoids the oscillations that occur in the trapezoidal rule when $h\lambda$ is large; however, this method is only first order (Alvarado, Lasseter, and Sanchez 1983). Finally, the QSS mode converts all of the differential equations to algebraic equations by setting $x' = 0$ and by-passes certain devices, such as power system stabilizers. The QSS mode is called quasi-steady state because events like tap changes and switching operations are taken into account. EXSTAB is designed to automatically switch between modes as needed. Initial results with this code have been promising.

EUROSTAG (Stubbe et al. 1989) is a relatively new production grade code developed for doing transient and mid-term stability simulations. It uses the variable order, variable step size, fixed coefficient BDFs. This code has been used in Europe and has been found to work better than other codes when simulation times exceed a few seconds, i.e., when the problem becomes smoother. This suggests that it may be appropriate to use the BDFs once the worst part of the transient phase is past. Little information is available on the codes with which EUROSTAG has been compared. Thus, it is unknown whether the improved performance of EUROSTAG is mainly due to the variable step size feature of the code, or if the variable order feature of the code contributes significantly to its performance. EUROSTAG only does a full restart of the BDFs at major discontinuities such as network changes. When smaller

discontinuities occur, they only restart the BDFs for those devices most likely to be affected by the discontinuity. This represents a form of partitioning the system and treating each part differently.

At a meeting on Solution Techniques and Related Modeling Issues in power system stability simulations held in Salt Lake City October 30-31, 1991, the developers of EUROSTAG included a paper showing good results on a small problem with a few ULTC transformers. However, this problem is not likely to be representative of systems of interest to Bonneville which have many more tap-changing transformers and are allowed to act more frequently than in the EUROSTAG simulation. Thus, it is not clear if a EUROSTAG-like algorithm would work well when there are frequent tap changes.

Sometimes EUROSTAG must limit the order of the BDFs to second order because some machine rotors experience low frequency, poorly damped oscillations. This corresponds to eigenvalues near the imaginary axis, and outside the region of absolute stability for the higher order BDFs. The published data does not indicate whether the restriction to second order significantly impacts the performance of EUROSTAG on these problems. Note that it is generally preferable to use the second order BDFs rather than the trapezoidal rule on stiff problems because of the trapezoidal rule's poor stability when $h\lambda$ is moderate to large.

Kato and Ikieuchi (1991) implemented a variable step size, variable order version of the BDFs and compared it to a fixed step size implementation of the trapezoidal rule on some small circuit problems that had frequent discontinuities. The codes used to compare these algorithms were identical, except for the integration algorithm used. The discontinuities in these problems were located by the code and a step was taken up to the point where each discontinuity occurred. The BDFs were restarted at first order after each discontinuity. In general, this is the preferred method for handling discontinuities because it makes an ODE code more efficient and reliable.

The BDF version of the code was two to three times faster than the trapezoidal code on an inverter circuit and comparable in speed on a single-conductor transmission system. On most of the test problems the BDF code seldom used a formula of order greater than three. This suggests that most of the improved performance of the BDF code on these problems was the result of using variable step sizes, and that a variable step size implementation of the trapezoidal rule might be of comparable speed. As noted previously, however, the stability properties of the BDFs are superior to those of the trapezoidal rule for stiff problems. Thus, it would be better to use a fixed order, variable step size implementation of the second order BDF than to use a variable order version of the trapezoidal rule.

The papers described in this section show several things about mid-term stability simulations. First, artificial damping of synchronizing oscillations can be beneficial. Second, using different integration algorithms for the transient and stiff phases of the simulation can be useful. Third, a variable step size algorithm is generally useful in the stiff zone. Finally, the BDFs work well on some problems; however, the impact of frequent tap changes on this method is unclear. It should also be mentioned that the partitioning and localization algorithms described in Section 2.3.1 would probably be useful for mid-term simulations. In fact, the use of selective restarting of the BDFs in EUROSTAG represents a form a partitioning applied to longer-term stability problems.

2.4 DESCRIPTION AND EVALUATION OF ETMSP

This subsection describes the main algorithms in ETMSP, and examines the implementation of them.

2.4.1 Algorithms in ETMSP

The algorithms used by ETMSP are described in the draft user's and programmer's guides. ETMSP contains code for the trapezoidal rule, the

second, third, and fourth order Runge-Kutta methods, and the Improved Euler method. The user can specify that different integration methods be used at different times. The code uses a fixed, user-specified time step. The time step, however, can be changed at pre-specified times. ETMSP has two sets of subroutines for evaluating derivatives; one set for use with the explicit methods and one for use with the trapezoidal rule.

When using the explicit integration methods, ETMSP must, when given x , solve Equation (2.2) for v and evaluate $f(x,v)$. Given x and v the evaluation of $f(x,v)$ is a straightforward task. This leaves solving Equation (2.2) for v . The ETMSP draft programmer's guide shows that $I(x,v)$ in Equation (2.2) can be written in the form

$$I(x, v) = -Y_n v - Y_s(x) v + i(x), \quad (2.16)$$

where $Y_s(x)$ and Y_n are the salient and non-salient voltage dependent components of the current injection. Y_n is a constant matrix. Substituting Equation (2.2) into Equation (2.16) yields

$$(Y + Y_n) v = -Y_s(x) v + i(x). \quad (2.17)$$

$Y + Y_n$ is constant between network modifications, hence it only needs to be re-factored following network changes. Furthermore, this matrix does not include any machine saliency, hence it can be represented in the compact, complex form.

The right-hand side of Equation (2.17) involves v ; thus, this equation must be solved using an iterative method. It has been found that using the voltage from the previous time step on the right side of Equation (2.17) usually gives a sufficiently accurate result. Thus, one iteration is usually sufficient. $Y + Y_n$ is very sparse, and the right side of Equation (2.17) is usually a sparse vector. State of the art sparse matrix (the minimum degree ordering algorithm and sparse LU factorization) and sparse vector methods (Alvarado, Tinney, and Enns 1992) are used by ETMSP to solve Equation (2.17).

Using the trapezoidal rule to discretize Equation (2.1) yields a set of nonlinear equations that must be solved simultaneously with Equation (2.2) for x_{n+1} and v_{n+1} . This is done using Newton's method. The iteration matrix for Newton's method has the block form

$$\begin{bmatrix} I - \frac{h}{2} \frac{\partial F}{\partial x} & -\frac{h}{2} \frac{\partial F}{\partial v} \\ -\frac{\partial I(x, v)}{\partial x} & Y + Y_n + Y_s(x) \end{bmatrix} \equiv \begin{bmatrix} A & B \\ C & D \end{bmatrix} \quad (2.18)$$

where I in the definition of A is the identity matrix and h is the step size. The matrix A is a block diagonal (in which each block is sparse), matrices B and C are sparse and blocked, and matrix D has essentially the same sparsity structure as Y . Newton's method is an iterative method for computing x_{n+1} and v_{n+1} . It uses the iterations:

$$\begin{aligned} A(x^{k+1} - x^k) + B(v^{k+1} - v^k) &= r_1^k \\ C(x^{k+1} - x^k) + D(v^{k+1} - v^k) &= r_2^k \end{aligned} \quad (2.19)$$

where k is the iteration counter. The subscripts $n+1$ have been dropped. r_1^k is the residual associated with the discretized version of Equation (2.1) and r_2^k is the residual associated with equation (2.2).

ETMSP rewrites Equation (2.19) as follows: 1) solve the first part of the equation for the increment in x , and substitute the result into the second part of the equation, 2) move the v^{k+1} terms to the left side of the equation and all of the other terms to the right side, 3) replace r_1^k by $(Y v^k - I(x^k, v^k))$, and 4) simplify the right side of the equation using Equation (2.16). This yields

$$(Y + Y_n + Y_s - CA^{-1}B) v^{k+1} = -Y_s v^k + i(x^k) + CA^{-1} r_1^k + (Y_s - CA^{-1}B) v^k \quad (2.20)$$

The matrix on the left side of Equation (2.20) must be re-factored whenever the Jacobian is updated. To avoid this expense ETMSP moves the term

$(Y_0 - CA^{-1}B) v^{k+1}$ to the right side of the equation and replaces v^{k+1} in this term by v^k . This cancels out the last term on the right side of the equation leaving

$$(Y + Y_g) v^{k+1} = -Y_g v^k + i(x^k) + CA^{-1}r_1^k \quad (2.21)$$

This amounts to using one iteration of an iterative method to approximate the solution of Equation (2.20). ETMSP solves Equation (2.21) for v^{k+1} and uses this to solve the first part of Equation (2.19) for $(x^{k+1} - x^k)$. Equation (2.21) has the same form as Equation (2.17), thus the same linear solver can be used for both problems. This method of solving the nonlinear equations has worked well in ETMSP. Doing a full iterative solution of Equation (2.20), rather than using Equation (2.21), could improve the robustness of this algorithm on difficult problems.

In general, when solving ODEs the Newton iteration matrix $(I - k * J)$ can be ill-conditioned. Hence it is recommended that one solve for the increments in the values of the variables, rather than the actual values of the variables. ETMSP does this for the state variables but solves Equation (2.21) for the actual value of the voltage. This does not appear to be a problem in this case because the matrix $(Y + Y_n)$ is usually fairly well conditioned.

2.4.2 General Comments About ETMSP

Overall, ETMSP has been written as a fairly modular code, making it reasonably easy to understand and modify. There are, however, several things that can be done to improve the code. The rest of this subsection will describe some bugs found in the program and some features that reduce the portability and maintainability of the code. Version 3.00 Release 91/08/14 Level OHV3-10 of ETMSP was used for this work.

Several bugs were found in ETMSP:

- Variables are used before they are defined.

- There are data type mismatches between dummy and actual arguments in subroutine calls.
- There are mismatches between the number of dummy and actual arguments in subroutine calls.
- Variable MAXBS appears in more than one DATA statement in subroutine FLODA5.
- Variable ISCREN is initialized in a non-standard data statement in subroutine HELPSC.
- Subroutine DGEN saves the previous generator angles at the start of a time step if the fourth order Runge-Kutta method is used, but not if any of the other explicit methods are used. This is a bug because the previous generator angles are used to determine which generator angle changed the most in a time step and the results are printed in the progress file and to the screen. This bug causes ETMSP to print the wrong "angle change" to these files at each time step.
- The method called the Modified Euler method in the ETMSP documentation is actually called the Improved Euler Method. These names apply to two different methods.

A detailed list of these bugs is being sent to the developers of ETMSP. More serious bugs include the following:

- If the user specifies that the second order Runge-Kutta formula should be used, then ETMSP uses a formula which they call the modified Euler formula, rather than the second order Runge-Kutta formula listed in the code documentation.
- ETMSP uses the third order Runge-Kutta formula defined by:
 $K1 = h f(x_n)$, $K2 = h f(x_n + K1/2)$, $K3 = h f(x_n + K2)$, and
 $x_{n+1} = x_n + 1/6 K1 + 2/3 K2 + 1/6 K3$, which is listed in Dembart et al. (1977). It can be shown, however, that this formula is only second order. A previous version of ETMSP used basically the same formula, but with $K3 = h f(x_n - K1 + 2 K2)$, which gives a standard third order Runge-Kutta formula. Thus, the third order Runge-Kutta formula in ETMSP needs to be replaced.

- It appears that subroutine INTRKG treats induction motors incorrectly when the user specifies that sub-time steps are to be used for these motors. In particular, it appears that the code 1) computes the states of the induction motors at the new time by using sub-time steps, and 2) then recomputes these states using the full size time step, but starting from the solution computed using sub-time steps.

Several things can be done to make ETMSP more readable and maintainable.

Many of the subroutines do not have initial comments describing what the subroutine does. More generally, most of the subroutines have relatively small numbers of comments to describe what the code is doing. More comments would be useful.

Good FORTRAN programming requires that spaces be used to make a program readable. This mainly refers to indenting the bodies of control structures like DO loops. Some of the subroutines in ETMSP are formatted so they are fairly readable, however, in many subroutines all of the statements start in the first column. Furthermore, there are cases where variable names and logical operators are split across lines. Appropriate use of blank spaces would make the code much more readable and understandable.

It is generally considered good programming practice to explicitly declare all variables appearing in a subroutine. A major advantage of this is that many compilers will flag undeclared variables, which helps find misspelled variable names. This helps reduce program bugs. ETMSP generally declares very few of the variables. One misspelled variable was accidentally found in ETMSP; and might have been caught before if all variables were explicitly declared.

ETMSP makes frequent use of ENTRY points. In many cases this is done to combine what are effectively independent subroutines into a single subroutine, i.e., the ENTRY points and the main subroutine do not share any code. This appears to have been done to combine subroutines with similar functions into a single subroutine. This is not what ENTRY points are intended for and it is

not good programming practice. Furthermore, it makes it more difficult for a compiler to optimize the code well. Subroutine URACSY and URBIN fall in this category; both take a long time to compile if optimization is turned on. These subroutines are not critical to performance, so they can generally be compiled without optimization.

There are several things that tend to reduce the portability of ETMSP. First, the subroutine-calling sequence REDLIN - HELPSC - FILEMG - PMTRED is recursive because PMTRED is an ENTRY point in REDLIN. This is non-standard FORTRAN. Second, ETMSP uses the slash, /, as a command separator. This prevents the use of path names with files on UNIX systems because the slash is part of the UNIX path. Third, when doing formatted input, FORTRAN treats a blank as either a zero or a null character. This caused problems when trying to run ETMSP on a SUN Sparcstation 2 using data supplied by Bonneville. The data files used by Bonneville contain blanks which default to zeros on the VAXs at Bonneville, but are treated as null characters on the SUN. This problem was fixed on the SUN by writing a program to add a BZ format specifier to all the FORMAT statements in ETMSP. The preferred fix for this problem is to explicitly use zeros, except for leading zeros, in all formatted input files. However, FORTRAN does not require this; thus, it would be useful if ETMSP used BZ format descriptors in all input formats. This would cause ETMSP to perform consistently on all machines. Fourth, character and non-character data types are mixed in the same COMMON block, this is non-standard. Fifth, long data types, e.g., INTEGER, follow short data types, e.g., INTEGER*2, in some COMMON blocks. This can cause alignment problems on some computers. Sixth, different data types are equivalenced to each other. Seventh, non-standard data types, mainly INTEGER*2, are used.

The equivalencing of INTEGER*2 variables to other data types is the biggest non-standard feature of ETMSP, and would make it difficult to port ETMSP to machines that do not support this data type. Ideally, the INTEGER*2 data type would not be used. When it is used, however, it would be fairly

easy to change the INTEGER*2 variables to standard INTEGER variables, provided INTEGER*2 variables are not equivalenced to other data types. ETMSP uses INTEGER*2 variables and equivalence statements to reduce the memory requirements of the code.

During this project a program was written that can scan a FORTRAN program and determine how much memory is required by all of the arrays in the code. Using this program it was found that the arrays in the 12,000-bus version of ETMSP require about 13.6 megabytes of memory. This program also indicates that these arrays would require about 16.2 megabytes of memory if all INTEGER*2 variables are converted to type INTEGER. This 16.2 megabytes does not account for the fact that this conversion changes how EQUIVALENCE statements cause a few arrays to overlap. If this change in overlap structure is taken into account it appears likely that the use of INTEGER*2 variables and equivalence statements in ETMSP probably saves no more than 3 to 4 megabytes of memory. Part of this 3 to 4 megabytes could probably be saved if INTEGER*2 variables were used, but only equivalenced to other INTEGER*2 variables. Furthermore, the amount of memory available on most modern computers is approaching a point where the memory saved in ETMSP by using INTEGER*2 variables is not critical. It is unlikely that non-standard data types will be removed from ETMSP any time soon. In future software development work, however, it would be preferable to use only standard FORTRAN. If non-standard features must be used in a program that is to be highly portable, they should be well documented and used in such a way that it is as easy as possible to remove them.

2.4.3 Explicit Methods in ETMSP

The explicit methods in ETMSP are mainly useful for the transient part of a problem, i.e., for transient stability simulations and for the first few seconds of longer-term stability simulations, because of their poor stability properties. This subsection describes ways to improve the efficiency and robustness of the implicit methods in ETMSP.

Timing data was collected on a SUN Sparcstation 2 using the Runge-Kutta algorithms in ETMSP on a transient stability problem and the initial part of a voltage stability problem supplied by Bonneville. The transient stability problem is titled 91LTA2T331 and contains 2,110 nodes, 3,331 lines, 957 buses with nonlinear loads, 906 buses with constant current loads, 180 buses with constant megavolt-amperes (MVA) and PF loads, 266 detailed machines, 89 classical machines, 7 automatic switching schemes, and 2 static var compensators (SVCs). The voltage stability problem is titled MELVINSE02 and contains 4,955 buses, 6,601 lines, 928 buses with nonlinear loads, 849 buses with constant current loads, 903 buses with constant MVA and PF loads, 729 buses with thermostatically controlled (TSC) loads, 322 detailed machines, 90 classical machines, 566 induction motors, 3 SVCs, 48 automatic switching schemes, and 719 ULTC transformers.

The results in this section are based on a 10-second simulation for the transient stability test problem and on the first five seconds of the voltage stability simulation. The CPU time required to do these simulations can be broken down into 1) setup time (mainly reading in the dynamic and load flow data), 2) the time required to do network modifications, and 3) the time required to take a step using the integration algorithm. In both simulations the setup time was less than 10% of the total CPU, and the time required to do network modifications (of which there were only a few) was at most a few percent. The rest of the time was spent actually doing the integration. This indicates that improving the setup and network modification portions of the ETMSP would only provide small gains in transient stability simulations involving more than a few seconds of simulated time. Thus, the rest of this subsection will be concerned with the time spent in the integration portion of the code.

On both of these test problems, ETMSP spends roughly half of its time solving Equation (2.17), 5.5 to 7.5% of its time in subroutine RKG computing the values of x at which $f(x,v)$ is evaluated, i.e., the arguments of $f(x)$ in

Equation (2.10), and the rest of the time evaluating $f(x,v)$. The cost of solving Equation (2.17) is split about equally between evaluating the right hand side of Equation (2.17) and the actual solution of the linear equations.

The time required to evaluate $f(x,v)$ and the right side of Equation (2.17) is a function of how efficiently the code is written, but does not depend on any numerical algorithms. An examination of the subroutines that perform these operations found that cleaning up some areas of the code would make it slightly cleaner and more efficient, but would not significantly improve the performance of ETMSP.

ETMSP solves Equation (2.17) using the minimum degree ordering algorithm, sparse LDU factorization, and sparse vector methods (Alvarado, Tinney, and Enns 1992). This represents the state of the art in sparse matrix techniques for power systems. The standard algorithm for solving the equation $Lw=b$, where b is a known vector and L is from the LDU factorization, uses two main loops. The outer loop is over the columns of L . The inner loop is over the elements in a column of L . In the current test cases most of the columns of L have 1 to 3 non-zero elements, and operations with these columns represent about half of the arithmetic involved in solving $Lw=b$. Thus, a large fraction of the inner loops involve only 1 to 3 iterations. Finally, there are numbers N_1 , N_2 , N_3 such that 1) most, if not all, of the first N_1 columns of L contain exactly one non-zero element, 2) most, if not all, of the next N_2 columns of L contain exactly two non-zero elements, and 3) most, if not all, of the next N_3 columns of L contain exactly three non-zero elements.

This structure appears to be fairly typical of power system problems and can probably be used to increase the speed of the solution of $Lw = b$. Increased speed could be accomplished by the following: 1) split L into blocks of contiguous columns that all have the same number of non-zero elements, 2) do an outer loop over the first K blocks of L , K is defined below, and an inner loop over all the columns of the block, and 3) process the columns of L past the K th block using the standard algorithm. The number K in

this algorithm should be chosen such that most of the first K blocks are fairly large. This algorithm has two advantages over the standard algorithm. First, the number of elements in a column only needs to be determined once for each block, rather than once for every column in the block. Second, all of the columns in a block can be processed with one long loop, rather than many very short loops. Thus, this algorithm can significantly reduce the amount of overhead required to process each column of L , and it would be easy to implement. Furthermore, this algorithm can be used to process the rows of U when doing the back substitution. This algorithm would probably provide a modest improvement in the solution of Equation (2.17), but it has not been tested. If this modified algorithm speeds up the solution of the linear system in Equation (2.17) by a factor of two, this would yield about a 12% reduction in the execution time of ETMSP. This is not a very large gain. Testing this algorithm, however, could be done in an afternoon; hence it is probably worthwhile.

Subroutine RKG represents the Runge-Kutta specific part of the integration algorithm, and only uses about 5% of the CPU time in ETMSP. Thus, attempting to modify it to improve the performance of ETMSP is of limited value. There are other factors, however, which suggest that the code should be changed.

The standard way to process the i -th stage of an explicit Runge-Kutta method is as follows: 1) given a vector x , call a subroutine to evaluate $f(x)$, which is essentially K_i in Equation (2.10), and 2) call a subroutine to compute the new value of x at which $f(x)$ will be evaluated when computing K_{i+1} . In this process, step one is performed for all of the equations at once, then step two is performed for all of the equations at once. ETMSP, however, does things differently. Given a vector x , ETMSP calls a subroutine to evaluate $f(x,v)$ for a particular type of device, e.g., for all generators. This subroutine does a loop over all devices. Within this loop it evaluates

$f(x,v)$ for one device, and then calls another subroutine, RKG, to compute the value of x that will be used in stage $i+1$ for this device.

ETMSP's way of implementing the Runge-Kutta formulas has several advantages over the standard implementation. First, ETMSP only needs a vector of length NMAX, the maximum number of states in any one device, to store the values of $f(x,v)$, rather than a vector of length N , the total number of states in the problem. This amounts to a savings of less than 100 kilobytes for most problems, hardly a significant savings. Furthermore, the trapezoidal rule in ETMSP requires a vector of length N to store derivatives. This vector could be used by the Runge-Kutta algorithm to store derivatives; hence, no memory is actually saved by using a "short" vector for derivatives. Second, ETMSP's algorithm makes it easy to implement sub-time steps. In fact, there is code to do sub-time steps within the Runge-Kutta versions of the subroutines used to evaluate $f(x,v)$. Overall, it appears that the ability to easily do sub-time steps is the only real reason for implementing the Runge-Kutta algorithms ETMSP's way, rather than the standard way. The use of sub-time steps has been found to be useful in Bonneville's transient stability program, which uses the trapezoidal rule. It is not clear how useful sub-time steps are with an explicit integration method because stability considerations will limit the step size, even if sub-time steps are used for the fastest equations.

ETMSP pays a penalty because of the way it implements the Runge-Kutta method. First, it experiences unnecessary overhead from calling subroutine RKG hundreds of times per stage of the Runge-Kutta method, rather than once. For devices with only a few states (e.g., classical generators, induction motors, thermostatically controlled loads) the overhead of calling subroutine RKG may exceed the time spent doing useful work. The timing data for the test problems indicate that this extra overhead increases the execution time of ETMSP by at most 1 or 2%; hence it is not of much concern. The second disadvantage of ETMSP's implementation is that the subroutines that evaluate

$f(x,v)$ call subroutines that are dependent on what integration algorithm is being used; this makes it more difficult to change integration algorithms.

Overall, the main effect of ETMSP's method of implementing the Runge-Kutta formulas is to make the code more complicated. If the use of sub-time steps is found to be useful with the explicit methods in ETMSP, then this extra complication is probably worthwhile. Otherwise, cleaning up the implementation of the Runge-Kutta formulas would make the code cleaner and slightly more efficient.

There is one other disadvantage to ETMSP's implementation of the explicit integration algorithms. In an explicit Runge-Kutta method the quantities

$$z_i = x_n + \sum_{j=1}^{i-1} a_{ij} K_j. \quad (2.22)$$

must be computed to evaluate K_1, K_2 , etc. Standard ODE codes compute the values of the z_i s directly from x_n, K_1, K_2 , etc., which requires saving each of these vectors. ETMSP, however, computes the z_i s using a formula of the form $z_i = z_{i-1} + (VQ + a_{i,i-1} K_{i-1})$, where VQ is a vector defined in such a way that this formula gives the correct results. Each component of the vector VQ is updated immediately after it is used to compute the corresponding component of z_i . If there is a z_{i+1} , then VQ is updated for use when computing z_{i+1} . Otherwise, VQ is updated using a formula of the form $VQ(i) = VQ(i) + 3 * CXX - C1 * K_3(i)$, where CXX and $C1$ are scalars chosen such that, in exact arithmetic, $VQ(i) = 0.0$. This is a very poor way of zeroing out VQ because round-off errors will cause VQ to be a vector of round-off noise, rather than the zero vector. This causes small, but unnecessary, errors because VQ must be zero at the start of the next Runge-Kutta step if the code is to give correct results. ETMSP implements the Runge-Kutta formulas this way to save the memory required for a couple of arrays of length N , where N is the total number of states in the system, which amounts to no more than a few hundred Kbytes. It appears, however, that there are already enough work arrays in ETMSP to save x_n, K_1, K_2 , etc., and hence to compute the z_i s using the standard algorithm. Thus,

ETMSP's method of computing the z_i s does not actually save any memory; therefore, it has no real advantage over the standard algorithm.

Furthermore, ETMSP's method of computing the z_i s requires more arithmetic, suffers more round-off errors, and is more complicated than the standard algorithm. In fact, ETMSP's algorithm requires about twice as much arithmetic as the standard algorithm when computing the z_i s in the fourth order Runge-Kutta formula. The lower order Runge-Kutta formulas pay a smaller penalty in extra arithmetic. Overall, ETMSP is paying a moderate price for using its method of computing the z_i s, but obtains no real benefits. Thus, it is probably best to modify ETMSP to use the standard algorithm for computing the z_i s. It appears that this can be done by making fairly minor modifications to just a few subroutines.

Overall, timing data indicates that modifying the Runge-Kutta algorithm and the algorithm to solve Equation (2.17) could speed up ETMSP by no more than about 15% when using the explicit integration methods. Testing the modified solution algorithm for Equation (2.17) would take very little time and is probably worth doing. Modifying the Runge-Kutta algorithms just to reduce the CPU of ETMSP is probably not worthwhile. It appears, however, to be a good idea to modify the Runge-Kutta algorithms to reduce the unnecessary round-off errors.

2.4.4 Implicit Methods in ETMSP

The trapezoidal rule in ETMSP is useful for both transient and longer-term stability simulations. This subsection describes ways to improve the efficiency and robustness of the trapezoidal rule in ETMSP.

The code implementing the trapezoidal rule in ETMSP seems to be fairly good. A modification to the algorithm used to decide when to update Jacobians, however, would increase the robustness of the code. The variables MAXNIT and IJMCT are related to the Newton iterations in ETMSP. If the number of Newton iterations in a time step are greater than or equal to IJMCT, then

ETMSP updates the Jacobian matrices used in the next time step. If the number of Newton iterations in a time step reaches MAXNIT, then ETMSP stops program execution. There are two main reasons why Newton's method would fail to converge fast enough in an ODE code: 1) the Jacobian has not been updated recently, or 2) the initial estimate of the solution is poor, which is caused by using too big of a step size. Thus, failure of Newton's method to converge fast enough means you should proceed as follows. If the Jacobian is out of date, then update it and redo the step. If this fails, then reduce the step size and redo the step. Finally, abort program execution only if several step size reductions fail to solve this problem. Implementing this type of algorithm in ETMSP would reduce the chance of having ETMSP stopping because of occasional difficult spots in the integration. The first part of this algorithm, i.e., if the Jacobian is out of date, then update it and redo the step, is easy to do and should be implemented in ETMSP. The step size adjustment part of the algorithm is more difficult to do in a fixed step code like ETMSP, but may be worth considering.

The remainder of this section deals with improving the efficiency of ETMSP.

The test problems described in Section 2.4.4 were run using the trapezoidal rule. The transient stability case was used to do a 10-second simulation, while the voltage stability case was used to do a 5- and 60-second simulation. The transient stability problem and the 5-second version of the voltage stability problem will be discussed first.

The distribution of CPU time among the various subroutines in ETMSP is similar for both the transient stability problem and the 5-second simulation using the voltage stability problem. The majority of CPU time was spent in the part of the code that actually does the integration steps, with relatively small amounts of time spent reading in data and doing network modifications. Furthermore, the time required to take a step is distributed between several different main tasks. Thus, there is no one large computation that could be

modified to significantly speed up the algorithm. The solution of Equation (2.21), given that the right-hand side has already been computed, only represents about 10% of the time required to take a step when using the trapezoidal rule. Thus, speeding up the solution of this equation is of less value than speeding up the solution of the corresponding equation used with the explicit methods. After examining the various implicit integration routines it was found that by making modifications in many different places, an overall reduction in execution time of as much as 10 to 20% might be possible for some problems. For transient stability problems the lower figure is most realistic, while the higher figure might be possible for voltage stability problems with many induction motors and thermostatically controlled loads. The time required to modify the code to obtain these types of speedup, however, would probably be better spent working on improved integration algorithms such as those described in Section 2.7. Two of the many possible changes are described below.

First, consider the following section of code from subroutine IMPINT:

```

DO 180 IRR=1,2
  DO 190 ICC=2,MT
    ICIDEX=ICIDEX+1
    CCDG(IRR,I)=CCDG(IRR,I)+CJCOB(ICIDEX)*XRES(JSM+ICC)
190    CONTINUE
180    CONTINUE

```

This can be written more efficiently as

```

I1 = ICIDEX - 1 - JSM
I2 = ICIDEX + MT - 2 - JSM
DO 190 ICC = JSM + 2, JSM + MT
  CCDG(1,I)=CCDG(1,I)+CJCOB(I1+ICC)*XRES(ICC)
  CCDG(2,I)=CCDG(2,I)+CJCOB(I2+ICC)*XRES(ICC)
190    CONTINUE

```

This section of code is embedded in another loop over the variable I. Within the I loop CCDG(1,I) and CCDG(2,I) are used repeatedly, and it would be more efficient to use scalars that are stored in CCDG(1,I) and CCDG(2,I) at the end of the loop. A good optimizing compiler will improve the efficiency of the

original code, but it seldom hurts to help the compiler along. This one code modification would not significantly speed up ETMSP. However, there are many places where the code can be made more efficient, and the cumulative effect could be a modest decrease in execution time.

Second, each iteration in a time step requires solving the equation $A_d z = b$ for each device, where A_d is the Jacobian matrix of a device. ETMSP does this by computing the LU factorization of A_d and using forward and back substitution to solve for z . For induction motor loads and thermostatically controlled loads the dimension of A_d is 1, 2, or 3, but ETMSP calls a subroutine to do the solution. It would be much more efficient to eliminate this subroutine call and replace the general solution algorithm with the specific equations obtained for $n = 1, 2, \text{ or } 3$. Making this modification to ETMSP reduced the execution time of the MELVINSE02 problem by about 4%. This performance increase occurs because this case has a lot of induction motor loads and thermostatically controlled loads. Cases without these devices, e.g., standard transient stability simulations, would not see this improved performance.

The timing data for the explicit and implicit methods show that if the Newton iterations in the trapezoidal rule converge in one iteration, then the cost of taking a step with the trapezoidal rule is approximately the same as the time required to take a step with the second-order Runge-Kutta method, and only about half as long as the time required to take a step with the fourth-order Runge-Kutta. The fourth-order Runge-Kutta method is seldom able to take steps twice as big as the trapezoidal rule on power system problems. Furthermore, the simulations done above required an average of just over one iteration of Newton's method when using a time step of 0.01. Thus, the trapezoidal rule was about twice as fast on these problems as the fourth order Runge-Kutta method.

The preceding examples dealt primarily with the transient part of a simulation with the trapezoidal rule. The behavior of ETMSP when ULTC

transformers are operating is important for voltage stability cases. The MELVINSE02 problem has these transformers, and they started operating just after 5 seconds into the simulation. It is more common for them to start operating later in the simulation. The main interest here, however, is in ETMSP's behavior when these transformers are operating. Thus, the fact that they start operating early in the simulation is not a problem. A tap change in a ULTC transformer causes a change in a few of the elements of the network Y matrix. ETMSP handles these changes in one of two ways: 1) update and refactor all of Y, or 2) use an iterative method. The ETMSP user's guide and the developers of ETMSP, however, state that the iterative algorithm can seldom be used because of convergence problems, thus full refactorization is recommended. This makes tap changes fairly expensive. Hence, ETMSP only allows tap changes to occur every K steps, where K is controlled by the user (K tends to be around 10).

ETMSP was used to simulate 60 seconds in the voltage stability case. The problem was run using a time steps of 0.01 seconds for the first 5 seconds, and time steps of 0.010, 0.015, 0.020, 0.025, and 0.030 seconds for the remaining time. ETMSP failed to solve the problem with a step size of 0.030. Each of these simulations allowed tap changes to occur every 10 time steps. In all cases, tap changes actually occurred almost every tenth time step.

The timing results for the problem using a constant step size of 0.01 seconds showed two main differences from the short-term stability simulations above. First, the machine Jacobians were only evaluated and factored a few times in the short-term simulations, but were evaluated an average of once every 5.4 time steps in the longer-term simulation. The cost of doing this only represented about 5% of the total CPU time, which is not bad. The second main difference is that the cost of modifying the network and restarting the integration following tap changes represents about one-third of the CPU time in the long-term problem.

There were two main differences between the simulations using the various step sizes. First, the average number of iterations required for Newton's method to converge increased from about 1.2 iterations per time step to 2.7 iterations per time step as the step size was increased from 0.01 to 0.025. Second, the frequency of evaluating and factoring the machine Jacobians increased from an average of about once every 5.4 steps to once every 2.4 steps as the step size increased. The total cost of evaluating and factoring the machine Jacobians represented 5 to 7% of the total computation time. In all of these simulations the cost of modifying the network and restarting the integration following tap changes represents one-fourth to one-third of the total CPU time. This cost would be higher if tap changes were allowed to occur more frequently when using the larger time steps.

These results indicate that reducing the time required to modify the network and restart the integration following a tap change would moderately reduce the time required to do voltage stability simulations. Furthermore, using improved integration algorithms to take larger steps in the mid-term portion of the simulation will be of limited value without decreasing the cost of doing tap changes. The main costs associated with doing a tap change are 1) modifying the Y matrix, 2) factoring the Y matrix, 3) computing the new voltages, and 4) updating the derivatives of the state variables and checking limits. The time spent in subroutines MODIFY and INTRKG following a tap change represents most of the cost of the tap change. In the 0.01 time step simulation about 1000 seconds were spent in subroutine MODIFY and 526 seconds were spent in INTRKG. Thus, the total cost of tap changes in this problem is about 1526 seconds of CPU time.

In the 0.01 time step simulation, subroutine MODIFY spends about 483 seconds in subroutine AFACTC, factoring the modified network matrix, 169 seconds in subroutine SETSOL, updating pointers for the sparse vector algorithm, 145 seconds in subroutine MODNET, doing input/output (I/O) associated with the network modification, and smaller amounts of time in other

subroutines. There are several ways to reduce the time required by these first three subroutines. First, the sparse vector pointers only depend upon the sparsity structure of the network matrix, not the actual values in the matrix. Hence subroutine SETSOL does not need to be called following a network change. Second, only part of the network matrix is modified, thus partial refactorization algorithms can be used on this problem (Betancourt 1988; Chan and Brandwajn 1986; Alvarado, Tinney, and Enns 1992). The savings obtained using this algorithm will depend on the problem, but there is a potential for significant savings. Third, if partial matrix refactorization works well, then it may be possible to reduce the amount of I/O done in subroutine MODNET.

After the network matrix has been modified ETMSP takes one step using the fourth order Runge-Kutta method with a step size of 0.0-seconds. In particular, Equation (2.17) is solved four times and Equation (2.1) is evaluated four times. The draft ETMSP programmer's guide states that this is only for the calculation of post-fault network conditions and the state vector is not updated. This seems to be an inefficient way of restarting the integration following network changes. For transient stability simulations this inefficiency is not a problem because network modifications are only done a few times. In voltage stability simulations, however, the cost of restarting this way is fairly high. A simple way to reduce the cost of restarting is to use the second-order Runge-Kutta method instead of the fourth-order method. Even this is not great, and a more direct method would be best. In fact, it may be possible to almost totally eliminate the cost of calling INTRKG because after a tap change, subroutine SIMULA calls SETSOL to do a network solution and subroutine PREINT to update the derivatives of the state variables. Thus, the call to subroutine INTRKG appears to do a limited amount of useful work. This has been discussed with the developers of ETMSP. They do not think there is anything special about using the fourth-order Runge-Kutta code for this restarting, but they said they would have to check to make sure. Thus, it is probably possible to significantly reduce, if not

eliminate, the 526 seconds currently spent in subroutine INTRKG following tap changes.

There are two main results of the preceding. First, the costs associated with subroutines SETSOL and INTRKG can probably be reduced to almost zero, which would reduce the cost of doing tap changes by a factor of two. Second, partial matrix refactorization can probably significantly reduce the time spent in subroutines AFACTC and MODNET, yielding an additional reduction in the cost of doing tap changes. If partial matrix refactorization does not work well, then compensation techniques, which are based on the Sherman-Morrison-Woodbury formula for updating the inverse of a matrix, could be tried (Alsac, Stott, and Tinney 1983; Hager 1989; van Amerongen 1990; Alvarado, Tinney, and Enns 1992). Chan and Brandwajn (1986) found that partial refactorization is faster than compensation if the modification has a rank higher than four. Thus, partial refactorization is likely to be more efficient than compensation techniques if more than one tap change occurs at once. Another alternative is to directly update the LDU factorization of the network matrix (Bennett 1965; discussion at the end of Alsac, Stott, and Tinney 1983). If none of these methods work well, then iterative linear equation solvers might be useful (Young 1989; Freund 1992). The methods described above have been developed and used extensively in the power community to avoid refactoring the network matrix following small changes, and should be considered for use in ETMSP.

Overall, the coding of the trapezoidal rule in ETMSP is fairly good. There are many small changes that would make the code slightly more efficient on most problems. The time required to make these improvements, however, is probably not worth the increase in performance. The cost of doing tap changes in ETMSP is fairly high, and should be reduced. Finally, the robustness of ETMSP would be increased by modifying the algorithm which determines when the Jacobian is evaluated.

2.5 ADVANCED ARCHITECTURE COMPUTERS FOR STABILITY ANALYSIS

This subsection will attempt to determine what type of computer, e.g., super-workstations or vector supercomputers or parallel supercomputers are best for running ETMSP. The results in this section are based on the best available data that we could find. This section does not attempt to determine whether one particular computer is better than any other computer. Rather, this section simply attempts to determine what class of computer is best, based on the data that is available for representative computers in each class of computers.

2.5.1 Super-Workstations

The LINPACK benchmark is a timing program used to determine how fast a computer can factor and solve a 100-by-100 linear system. The results of this benchmark yield machine speed in millions of floating point operations per second (MFLOPS). The results of running this benchmark are available for a wide variety of computers and provides a means of comparing the speeds of many different machines (Dongarra 1992). This benchmark, however, only provides a crude estimate of the relative performance of various machines on other applications.

There is a LINPACK benchmark problem that uses a 1000-by-1000 matrix. This problem allows the user to modify the test program and even use assembly language programming to obtain the highest possible speed on any given machine (this is not allowed with the 100-by-100 problem). Thus, the 1000-by-1000 problem is better than the 100-by-100 problem for determining the maximum possible performance of a computer. Power system problems, however, do not spend much time doing dense linear algebra and would not benefit from the optimization that can be done with the 1000-by-1000 LINPACK benchmark problem. Thus, the results obtained using the standard 100-by-100 LINPACK benchmark problem are used in this section when comparing the performance of various computers.

Bonneville currently uses VAXstation 3100s, VAXstation 4000/60s and DECstation 5000s for much of their computing. Dongarra (1992) does not provide timing results for the VAXstation 3100 or VAXstation 4000/60. Thus, the LINPACK benchmark program was run on one of the DECstation 5000/200s, one of the VAXstation 3100s, and one of the VAXstation 4000/60s at Bonneville and yielded results of about 3.5, 0.4, and 1.6 MFLOPS, respectively. These ratings are representative of what might be called standard-workstations. There is another class of workstations which are generally called super-workstations which run the LINPACK benchmark at rates closer to 20 to 40 MFLOPS.

The IBM RS-6000/550 (41 Mhz) runs the LINPACK benchmark at 27 MFLOPS, while the HP-9000/730 runs it at 24 MFLOPS (Dongarra 1992). Figures quoted for the newer IBM RS-6000/580 and HP-9000/735 are around 38 and 40 MFLOPS, respectively. Furthermore, IBM says that they will be shipping a machine which is about twice as fast as the IBM RS-6000/580 in the next six months or so. These machines are considered super-workstations and have the potential of running ETMSP much faster than standard-workstations. An IBM RS-6000/580 with 128 Mb of RAM, a 2 or 3 Gb hard disk, a 19" color monitor, and compact disc and tape drives costs about \$75K. A similarly configured HP-9000/735 costs about \$48K. The costs of these machines are significantly lower if the peripherals are not needed. Thus, a cluster of several machines with only a few peripherals would be significantly cheaper than the same number of fully configured machines. There are a number of super-workstations on the market. The IBM and HP super-workstations are simply representatives for which data was readily available.

The LINPACK performance figures are for a single benchmark problem and may not translate to corresponding speedups for ETMSP. The problem in Taylor and Rodrigues (1992) was integrated using the trapezoidal rule with a time step of 0.01 seconds for the first 30 seconds of the simulation and a time step of 0.02 seconds for the next 90 seconds of the simulation. The voltage

stability test problem described in Section 2.4 is similar in size to the one used in Taylor and Rodrigues (1992). Using the timing data for the voltage stability test problem described in Section 2.4 and assuming that tap changes start occurring at about 30 seconds in the simulation in Taylor and Rodrigues, one can project that the problem in Taylor and Rodrigues (1992) would take about 2.1 hours to run on a SUN Sparcstation 2. This is about 2.8 times faster than on the 0.4 MFLOPS standard-workstation in Taylor and Rodrigues (1992). The SUN Sparcstation 2 runs the LINPACK benchmark at 4.0 MFLOPS. This suggests that 4.0 MFLOPS standard-workstations will generally run ETMSP about 2.8 times faster than 0.4 MFLOPS standard-workstations. A 40 MFLOPS super-workstation would run the LINPACK benchmark about 10 times faster than a 4.0 MFLOPS standard-workstation. Thus, it seems reasonable to expect that a 40 MFLOPS super-workstation would run the voltage stability problem in Taylor and Rodrigues (1992) about 2.8 times faster than a 4.0 MFLOPS standard-workstation and about 8 times faster than a 0.4 MFLOPS standard-workstation. A more quantitative comparison of the speed of ETMSP on various types of computers requires running the same problem on all machines. It is likely, however, that a 40 MFLOPS super-workstation would run ETMSP 5 to 10 times faster than a 0.4 MFLOPS standard-workstation and a few times faster than a 4.0 MFLOPS standard-workstation.

Overall, it appears likely that 40 MFLOPS super-workstations could run ETMSP 5 to 10 times faster than 0.4 MFLOPS standard-workstations and can be obtained at reasonable prices. Furthermore, three to four MFLOPS standard-workstations can probably run ETMSP a few times faster than 0.4 MFLOPS standard-workstations. More quantitative results require running the same ETMSP benchmark problem on the various types of computers.

2.5.2 Vector Supercomputers

The possibility of using vector supercomputers to run ETMSP will be considered in this subsection. An excellent description of this class of

computers can be found in Levesque and Williamson (1989), while a brief description is provided below.

Every floating point operation on a computer (e.g., addition, multiplication) usually involves several steps or segments, each step taking one or more computer clock cycles to complete. For example, a floating point addition may require three steps, each step taking one clock cycle. Consider a program containing the following FORTRAN statements:

```
      DO 10 I = 1, 1000
        A(I) = B(I) + C(I)
      10 CONTINUE
```

A conventional computer will compute $B(1) + C(1)$, executing all three steps of the addition, before starting to compute $B(2) + C(2)$ and so on. Thus, it will produce one result every three clock cycles. This mode of operation is called the scalar mode. A vector computer, however, can do the additions in assembly-line (or pipeline) fashion. This mode of operation is called the vector mode and will produce one result every clock cycle, once the pipeline is filled. Thus, a functional unit with three segments can produce results three times faster in vector mode than in scalar mode. Actual computers typically use functional units with more than three segments, hence vector mode is much faster than scalar mode. Vector mode is used for operations involving vectors, i.e., sections of memory defined by a starting address, a length, and a stride (constant distance between elements in memory). Thus, FORTRAN arrays are vectors, provided that the array elements actually used in a computation are a constant distance apart in memory.

Many vector supercomputers are faster than conventional computers because their CPU is faster in scalar mode than most conventional computers and because of vectorization. Furthermore, vector computers are fairly easy to use because they have compilers that automatically vectorize the innermost loops in computer codes. These compilers also generate diagnostics describing

which loops were vectorized, which were not vectorized, and why they were not vectorized.

Amdahl's Law states that the vector speedup, i.e., the execution time to run a code in scalar mode divided by the execution time to run the vectorized code, is given by

$$S = \frac{1}{(1-f) + \frac{f}{p}} \quad (2.23)$$

where S is the speedup, f is the fraction of utilized code, i.e., CPU-intensive code, vectorized, and p is the speed increase of vector operations over scalar operations (Ortega 1988, p. 29). Let $p = 10$. In this case, a computer code will achieve a speedup of 10 if 100% of the utilized code is vectorized, but a speedup of only 2 when 55% of the utilized code is vectorized. In fact, 90% or more of the utilized code needs to be vectorized to get a speedup that approaches the maximum possible value. Fortunately, large computer codes typically have only a few CPU-intensive subroutines that need to be optimized to make the code run efficiently on a vector computer.

Vector supercomputers perform best on problems where most of the CPU time is spent in DO loops like the one described above. Thus, these machines can achieve speeds of hundreds of MFLOPS on dense linear algebra problems. Computer programs that spend most of their time in short loops, or loops that do not involve vector operations, may perform little if any faster in vector mode than in scalar mode. Thus, these types of problems only run at the scalar speed of the machine. Unfortunately, transient/mid-term stability problems tend to fall in the latter category, and only limited effort has been spent trying to make these codes perform well on vector supercomputers (Tylavsky et al. 1992).

There are two main types of computations in ETMSP. First, there are operations on sparse matrices, i.e., factoring and solving sparse linear systems involving the machine Jacobians. Second, there are the operations

required to compute $f(x,v)$, check limits on variables, and do other assorted tasks.

The sparse matrices present two problems for vector computers.

First, the sparse matrix algorithms use indirect addressing. This means that the data required to do the vector operations are not regularly distributed in memory. This problem can be overcome by using a gather/scatter operation. This consists of 1) gathering the data from the sparse vectors into a contiguous vector, 2) performing the arithmetic operations in vector mode, and 3) scattering the result back into the sparse vector. Older computers, such as the Cray 1, required that the gather/scatter operation be done in software, and this algorithm was of limited success. Modern vector computers, such as the Cray X-MP, have hardware gather/scatter. These computers can achieve high vector speeds even on problems with indirect addressing (Ashcraft et al. 1987; Lewis and Simon 1988).

Second, power system sparse matrix problems typically involve very short inner DO loops. This basically eliminates the possibility of vector speedup. One possible way to avoid this problem is to use an ordering algorithm other than the Minimum Degree Algorithm (MDA). A number of alternatives to the MDA have been considered for sparse linear systems on vector supercomputers, but have been of limited success for power system problems (Barry, Pottle, and Wirgau 1978; Lewis and Simon 1988; Dongarra et al. 1991). When doing forward and back substitution on very sparse matrices it is often possible to solve for several variables simultaneously. This fact has been used to generate long vectors when solving the sparse systems occurring in powerflow problems, which are similar to the sparse systems in stability simulations (Gomez and Betancourt 1990; Graneli et al. 1992). Vector speedups of 3 to 8 have been obtained on Cray X-MPs and Cray Y-MPs using these algorithms on powerflow problems. These results suggest that reasonable vector speedups can be obtained for the sparse network solutions in stability simulations.

On a SUN Sparcstation 2, ETMSP spends only about 10% of its time solving the sparse network problem when using the trapezoidal method (25% for the Runge-Kutta method). This percentage will be different on a vector supercomputer, but it will still be true that other parts of ETMSP use significant amounts of the CPU time. Thus, achieving good vector speedup on just the sparse matrix part of the problem is insufficient for good performance on a vector computer. The other main computational tasks in ETMSP must be able to achieve significant vector speedups. It turns out that some of this other code is currently vectorizable, or could be made vectorizable with a modest effort. Some of ETMSP, however, would be fairly difficult to vectorize, e.g., the computation of $f(x,v)$ for the detailed machines.

Computing $f(x,v)$ for a detailed machine is done using a large outer loop over all machines. Within this loop all of the equations for the machine and its control devices are processed. This loop is not vectorizable because of its length, complexity, and the fact that each machine typically consists of a different set of controls. Furthermore, there are very few vectorizable loops within this main loop. Thus, the computation of $f(x,v)$ for detailed machines would achieve little if any vector speedup using the code currently in ETMSP.

The coding in ETMSP could be modified to increase its overall vectorizability. In particular, modifying the code to treat all devices of a particular type (e.g., Type E exciters) in a single loop would improve the vectorizability of the code. This idea has been suggested, but not tried, by Barry, Pottle, and Wirgau (1978). Doing this, however, would require significant changes to many of the subroutines in ETMSP.

Only two papers that we are familiar with describe the modification of transient stability programs to run on vector supercomputers. Betancourt and Degen (1990) ported the Western States Coordinating Council (WSCC) stability program to a Cray X-MP and a Cray Y-MP. They found that the code, without modifications to improve vectorization, ran twice as fast with compiler optimization and vectorization turned on, as when both of these options were

off. It is unknown how much of the improved performance is from standard optimization and how much (if any) is from vectorization. After doing timing studies and examining the code, the authors made some changes to improve the vectorization of the code. The modifications they made increased the vector performance of the code by less than 20%. They recommended that one of the major subroutines in the code be completely re-written. Thus, the results of this project were that the stability code ran at basically the scalar speed of the Cray.

Vuong, Chahine and Behling (1992) give a very brief description of modifying Power Technologies Inc.'s transient-stability program, PSS/E, to run on a Cray X-MP. After doing the initial conversion of the program to run on the Cray they found that it ran at scalar speed. They made some initial modifications that resulted in a speedup of almost two. Next, additional modifications were made to the code's data structure to improve the code's vectorizability. This yielded an additional factor of two speedup. Thus, an overall vector speedup of about four was achieved. Other code modifications were identified that could provide additional improvements in performance. This paper does not tell how much effort was actually required to achieve these speedups or how significant the code modifications were.

The preceding results indicate that simply modifying ETMSP to run on a vector supercomputer would yield a program that ran at the scalar speed of the machine. Achieving a vector speedup of two could probably be achieved with a modest effort. Large vector speedups, however, are likely to require significant changes to many of the subroutines in ETMSP.

The overall speedup of ETMSP on a vector supercomputer versus a 0.4 MFLOPS standard-workstation depends on the difference between the scalar speeds of these machines. This difference, however, depends upon the problem and computer program. MASS runs about 15 times faster in scalar mode on a Cray than it does on a VAX 8650 (Elwood 1991). The VAX 8650 performs the LINPACK benchmark at 0.70 MFLOPS (Dongarra 1992). This suggests that MASS

would run 15 to 30 times faster on a vector supercomputer (in scalar mode) than on a 0.4 MFLOPS standard-workstation. MASS, however, spends most of its time in one numerically intensive subroutine, which is quite different from ETMSP.

Gomez and Betancourt (1990) found that a decoupled load flow program ran about 10 times faster on a Cray (in scalar mode) than on a VAX 11/780. The VAX 11/780 FPA runs the LINPACK benchmark at 0.14 MFLOPS (Dongarra 1992). This suggests that this problem would run 5 to 10 times faster on a vector supercomputer (in scalar mode) than on a 0.4 MFLOPS standard-workstation.

Results in Anderson and Wollenberg (1992) show that a steady state security analysis code runs three times faster on a Cray (in scalar mode) than on a SUN Sparcstation 2. This code solves many power flows simultaneously and probably spends more of its time doing numerically intensive work than stability codes that solve one linear system at a time. The SUN Sparcstation 2 runs the LINPACK benchmark at 4.0 MFLOPS. This suggests that this problem would run 5 to 10 times faster on a vector supercomputer (in scalar mode) than on a 0.4 MFLOPS standard-workstations.

Finally, Crouch, Brady, and Tylavsky (1991) ran a frequency domain and a time domain transient stability code on a Cray and found that the time domain program ran at the same speed on a Cray (in scalar mode) and a VAX 8650, while the frequency domain code was three times faster on the Cray. This suggests that these codes would probably run a few times faster on a vector supercomputer (in scalar mode) than on a 0.4 MFLOPS standard-workstation.

The data in this section suggest that ETMSP would probably run no more than 5 to 10 times faster on a vector supercomputer (in scalar mode) than on 0.4 MFLOPS standard-workstations. Achieving larger speedups on a vector supercomputer would require ETMSP to effectively utilize the vector capability of the machine. As indicated above, this would probably require a significant amount of work and substantial modifications to ETMSP.

The conclusions in this section are based on using the LINPACK benchmark to give rough estimates of the probable speed of different computer codes on different computers. Furthermore, the speed of a code on a vector computer depends upon which vector supercomputer and which compiler are being used. Dongarra (1992) list the LINPACK benchmark results for several vector supercomputers which range in speed from tens to a few hundred MFLOPS. Most of the Cray's listed in Dongarra (1992) range from 100 to 200 MFLOPS. The published papers referenced in this section do not provide enough information to know what the LINPACK benchmark results are for the vector computers used in these papers. However, it appears that most of the machines used in the referenced papers are probably similar to those with LINPACK speeds of 100 to 120 MFLOPS. Thus, it is possible that vector supercomputers with higher LINPACK benchmark results would run ETMSP moderately faster, relative to 0.4 MFLOPS workstations, than what has been predicted in this section.

2.5.3 Parallel Supercomputers

The possibility of using parallel supercomputers to run ETMSP will be considered in this subsection. Detailed descriptions of these types of machines can be found in Ortega (1988) and Dongarra, Duff, Sorensen, and van der Vorst (1991). A brief description of these machines is provided below.

Parallel computers speed up computations by doing many operations at the same time. Parallel speedup is the time required to solve a problem on one processor divided by the time required to solve the same problem on several processors. Amdahl's law, Equation (2.23), applies to parallel speedup. There are two main types of parallel computer: single-instruction-multiple-data (SIMD), and multiple-instruction-multiple-data (MIMD). SIMD machines work by performing the same operation on many different pieces of data at the same time. Vector computers can be viewed as SIMD machines. MIMD machines contain many different processors, each running its own program. MIMD machines can be broken down into shared memory machines and local (or distributed) memory machines. In a shared memory machine all of the

processors have access to a large common memory, and each processor can also have its own local memory. The common memory is used to share data between processors. In a local memory machine, each processor has its own memory and data is shared by sending messages. The communication overhead of shared memory machines tends to be significantly less than for local memory machines. However, the number of processors that can be used in a shared memory machine is limited by the cost of the switching networks required to connect the processors to the memory. Thus, shared memory machines are best for problems that require only limited numbers of processors and that have a relatively high communication/computation ratio. Local memory machines are best for problems that require large numbers of processors and have a relatively low communication/computation ratio.

Parallel algorithms can be broken down into two main types: fine-grain and coarse-grain. Fine-grain algorithms consist of many small tasks, e.g., a task consisting of a few floating point operations, while coarse-grain algorithms consist of a smaller number of large tasks. SIMD machines tend to be best suited for fine-grain algorithms, while MIMD machines are best for coarse-grained algorithms.

SIMD machines, such as the Connection Machine CM-2, can probably achieve significant speedups on the network solution portion of stability problems (Pothen and Alvarado 1992). These machines, however, are not particularly well suited to the rest of the problem. All of the work on the parallel solution of power system stability problems that we are aware of has been done using MIMD machines.

In some respects the transient/mid-term stability problem is well suited to parallel computing. In particular, the only interaction between different devices is through the network. Thus, given x and v , $f(x, v)$ can be computed simultaneously for all machines. The only part of the problem that is not perfectly parallel is the factorization and solution of the network equations. The timing data in Section 2.4.4 indicates that in a transient stabil

simulation the network solutions take about 10% of the CPU time in ETMSP. Thus, parallelizing everything but the network portions of ETMSP and using 10 processors could give parallel speedups of about 5 on transient stability simulations with ETMSP. This neglects the cost of communication, which is probably a realistic assumption for large problems. Using more processors could improve the speedup, however, there are two points to consider with this alternative: 1) at some point the extra communications cost of using more processors would actually increase the execution time, and 2) this algorithm cannot achieve speedups of more than 10 since the network solution has not been parallelized. This means that large parallel speedups using parallel computers can only be achieved if the network solution is successfully parallelized, or parallelism in time is used. Parallelism in space refers to distributing the various equations to different processors. Parallelism in time refers to computing the solution at several time points simultaneously.

Tylavsky et al. (1992) review work on parallel processing for power system computations. Chai and Bose (1992) examine most of the work done on the parallel solution of the transient stability problem.

A number of theoretical papers have been written on the parallel solution of transient stability problems (Ilic'-Spong, Crow, and Rai 1987; Alvarado 1979; Crow, and Ilic 1990; La Scala, Brucoli, Torelli, and Trovato 1990; La Scala, Bose, Tylavsky, and Chai 1990; La Scala, Sbrizzai, and Torelli 1991; Hatcher, Brasch, and Van Ness 1977). Most of these papers consider various ways of combining parallelism in time and space. Several of these papers predict high speedups, mostly from parallelism in space, by assuming no communication overhead. On most currently available machines, however, this is not a realistic assumption, and these high speedups would not actually be achieved.

Several attempts have been made to parallelize the solution of the sparse network equations occurring in stability simulations. Both direct and iterative methods have been considered.

The factorization path of a matrix describes the precedence relationships in the elimination of nodes for LU factorization and forward and back substitution (Tinney, Brandwajn, and Chan 1985). The factorization path can be drawn as a tree in which each branch represents a set of tasks that are independent of the tasks in other branches. The factorization path trees for sparse network matrices tend to have many independent branches. Lau, Tylavsky, and Bose (1991) use this property to parallelize the forward and back substitution process for the sparse network equations. They achieved parallel speedups of 1.9, 2.08 and 1.68 on problems with 118, 494, and 662 nodes, respectively, when using four processors of an Intel iPSC/2. Using more processors caused the total execution time for these problems to increase because of the additional communications overhead. In many algorithms the parallel speedup increases as the problem size increases. Thus, one would hope that the speedup for problems of interest to Bonneville, which have several thousand nodes, would be higher than the results presented here. The results here, however, indicate that the topology of the power network is at least as important as the size of the power network. Hence, the speedups obtainable on networks of interest to Bonneville cannot be reliably projected from these results. Finally, in the general literature on the parallel solution of sparse matrix problems there has been moderate success on matrix factorization, but little success on forward and back substitution (Heath, Ng, and Peyton 1991).

Another way of parallelizing the network solution using direct methods is based on sparse matrix inverse factors (Alvarado, Yu, and Betancourt 1990; Enns, Tinney, and Alvarado 1990). The solution of the problem $Ly = b$, where L is lower triangular, can be written $y = L^{-1}b$. L can be written $L = L_1 L_2 \dots L_n$, where each L_i differs from the identity matrix only in the i -th column, which contains the i -th column of L . Thus, we can write

$$y = L_n^{-1} L_{n-1}^{-1} \dots L_1^{-1} b \quad (2.24)$$

where L_i^{-1} is a sparse inverse factor which is the same as L_i , except that the signs of the off-diagonal elements are reversed. The right side of Equation (2.24) represents a series of matrix-vector multiplications. Generally, a matrix-vector multiply is a highly parallel operation. Each inverse factor, however, has only a few non-zero, off-diagonal elements. Thus, each of the matrix-vector multiplications represents very little work. Groups of the inverse factors can be multiplied together to get a smaller set of inverse factors. A matrix-vector multiplication using one of these aggregated inverse factors requires much more arithmetic than with the original factors. Furthermore, appropriate choices for groups cause little fill-in to occur when the original inverse factors are multiplied together.

Using these sparse inverse factors, Padilha and Morelato (1992) give theoretical results predicting a parallel speedup of about 45 for a 1,729 bus problem using 956 processors. These results, however, assume that communications costs are negligible and that one processor computes one row of each matrix-vector product. For many of the aggregated inverse factors, this operation only requires 4 to 5 multiply-add operations. Thus, this algorithm represents fine-grain parallelism, and a speedup of 45 is not achievable for this problem on most currently available MIMD machines. Shared memory machines, however, may be able to achieve some speedup using this type of algorithm, provided each processor computes several rows of each matrix-vector product.

Iterative methods are another possibility for the parallel solution of the network equations. Tylavsky and Gopalakrishnan (1990) describe a parallel iterative solver, but have not actually implemented it. Decker, Falcao, and Kaszkurewicz (1991) describe a parallel transient stability program which uses an iterative algorithm, the conjugate gradient method, to solve the network equations. This code was run on a prototype local memory machine consisting

of eight Inmos Transputer T800s. On a system with 88 generators, and 616 nodes they obtained speedups of up to 2.3 for the network solution and 3.9 for the overall problem. These speedups are relative to a program using the standard LU factorization to solve the network equations, hence they represent true speedups. Taoka et al. (1992) use the Gauss-Jacobi method to solve the network equations. Using 512 processors on an nCUBE 2 they were able to run 10 second transient stability problems consisting of up to 261 nodes and 64 generators in CPU times varying from 5 to 25 seconds. The time required to do these simulations was fairly independent of the number of buses. This is because about 80% of the CPU time was communications overhead.

Chai et al. (1991) implemented several algorithms on an Intel iPSC/2 and an Alliant FX/8. The first algorithm used the trapezoidal rule and parallelized everything but the network solution, which was done sequentially. On a US Midwestern 662 bus problem, speedups of 3.91 and 4.56 were obtained on the Alliant and Intel machines, respectively, when using eight processors. Using 32 processors on the Intel machine only increased the speedup to 5.61. By adding parallelism in time to this algorithm, a speedup of 8.8 was obtained using 32 processors on the Intel machine. Thus, parallelism in time is clearly beneficial. By parallelizing the network solution in this algorithm (Lau, Tylavsky, and Bose 1991), additional speedup can probably be achieved in this algorithm.

Chai et al. (1991) also wrote a code that uses a one-step Successive Over-Relaxation(SOR)-Newton algorithm to solve the nonlinear equations in the stability problem. This code achieved a speedup of 7.41 on eight processors of the Alliant and a maximum speedup of 4.01 on the Intel machine (using up to 32 processors). The Alliant performed better than the Intel machine on this problem because the algorithm is moderately fine-grained, the Intel iPSC/2 is a local memory machine, and the Alliant FX/8 is a shared memory machine. These results suggest that shared memory machines are more appropriate than local memory machines for power system problems.

Zhu and Bose (1992) extend the one-step SOR Newton algorithm by partitioning the devices into groups based on the coherent characteristics of the generators, and using different step sizes for each group. They found that this multirate integration sped-up the code by a factor of 4 to 5. This algorithm, however, should be viewed as a means of speeding up stability codes in general, not a means of obtaining better parallel speedup.

Lee et al. (1989) describe a parallel transient stability code that only uses classical machines and reduces the network to the generator buses. They obtained speedups of up to 10 when using 32 processors of an Intel iPSC/2. These results appear to be of limited relevance to practical transient stability codes.

Chai and Bose (1992) examine most of the parallel algorithms that have been applied to the transient stability problem. They find that for this problem shared memory machines, e.g., the Alliant FX/8, seem to work better than local memory machines, and relaxed Newton type algorithms, e.g., the one-step SOR-Newton algorithm, seem to be the best algorithms. The maximum parallel speedup achieved by any of the algorithms described was 11.8 on a 26-processor Sequent/Symmetry machine (a shared memory machine). They concluded that this appeared to be an upper bound for the speedup obtainable on current machines using the algorithms that have been considered to date.

Many of the results with parallel transient stability codes use problems no bigger than the US Midwestern 662 bus test problem. Problems of interest to Bonneville, however, are 5 to 10 times bigger than this. In the general field of parallel computing it has been found that increasing the size of the problem also increases the number of processors that can be used efficiently. Thus, one would expect that significantly higher speedups could be achieved on the problems of interest to Bonneville. The results of Lau, Tylavsky, and Bose (1991), however, show that this is not necessarily the case when parallelizing the network solution in power system problems. Many of the other parallel algorithms for stability simulations, however, would probably

be able to achieve larger speedups on larger problems. Thus, it would be very useful if parallel transient stability codes were tested on larger problems. This would provide better estimates of the speedups possible on real problems. It would also be useful to run some of the currently parallel stability codes on some of the newer parallel computers, e.g., the Alliant FX/2800-200 and/or Intel iPSC/860.

The advantage of using a parallel machine rather than 0.4 MFLOPS workstations depends on 1) the relative speeds of 0.4 MFLOPS workstations and a single processor of the parallel machine, and 2) the parallel speedup obtained on the parallel computer.

The speed of a single processor of the currently available parallel machines varies significantly. Some representative rates on the LINPACK benchmark are: 1) 0.78 MFLOPS for the nCUBE 2, 2) 2.1-2.4 MFLOPS for the Alliant FX/4, FX/40, and FX/80, 3) 6.5 MFLOPS for the Intel iPSC/860, and 4) 6.4 MFLOPS for the Alliant FX/2800-200 (Dongarra 1992). Thus, the single processor speeds for these machines (on the LINPACK benchmark) varies from about 2 to 16 times faster than the speed 0.4 MFLOPS workstations. In Section 2.5.2, however, it was found that ETMSP would probably run about three times faster on 4.0 MFLOPS workstations than on 0.4 MFLOPS workstations. Thus, an optimistic guess is that a single processor of a parallel computer with 6 MFLOPS processors could run ETMSP about three to four times faster than a 0.4 MFLOPS workstation. On many parallel computers, however, a processor must efficiently use a data cache or vector processor to achieve its maximum speed. ETMSP, in its current form, could probably make only limited use of data caches and/or vector processors. Hence, ETMSP would probably run no more than two to three times faster on one processor of a parallel computer (which uses 6 MFLOPS processors with vectorization or data caches) than on a 0.4 MFLOPS workstation.

Much of the recent work on parallel stability programs has been on parallel computers like the Alliant FX/8 and Intel iPSC/2. Computers like

these could be considered to be a generation older than parallel computers like the Alliant FX/2800-200 and Intel iPSC/860. Speedups of 5 to 10 have been achieved with stability programs on some of the older generation of parallel computers. Thus, one might expect the newer generation of parallel computers to achieve similar, or higher, speedups. This, however, is not necessarily the case. For example, the Intel iPSC/860 has a higher communications/computation ratio than an iPSC/2. Generally, it gets harder to obtain good parallel speedups as the communications/computation ratio increases. These results suggests that if an algorithm achieves a given speedup on an older generation parallel computer, then it will achieve a similar or smaller speedup on a newer generation parallel computer. This, suggests that the faster, newer generation parallel computers may achieve speedups closer to 5 than to 10 when using the algorithms that have been developed on the older generation of parallel computers. This suggests that current parallel stability codes would probably run no more than 15 to 20 times faster on one of the newer generation parallel computers than on a 0.4 MFLOPS workstation.

The preceding analysis suggests that currently available parallel computers and algorithms could probably run transient/mid-term stability simulations up to 15 or 20 times faster than 0.4 MFLOPS workstations. This speedup prediction, however, is based on numerous estimates and could be improved by benchmarking ETMSP on various computers. Finally, most of the parallel speedups published in the literature are for problems with less than 1,000 buses. Higher parallel speedups may be possible on larger, more realistic problems. Thus, it would be useful for parallel stability codes to be tested on larger problems.

2.5.4 Conclusions

40 MFLOPS super-workstations can probably run ETMSP 5 to 10 times faster than 0.4 MFLOPS workstations like those currently used at Bonneville. This means that 40 MFLOPS super-workstations could probably run Bonneville's

transient stability problems in about 5 minutes and run Bonneville's 2 minute voltage stability simulations in an hour or less. Some benchmark problems would have to be run, however, to determine the speedup actually attainable. Modifying ETMSP to work on a super-workstation would probably be fairly easy.

The results of section 2.5.2 suggest that 1) a vector supercomputer in scaler mode would probably run ETMSP about 5 to 10 times faster than a 0.4 MFLOPS workstation (however, there may be vector supercomputers that do better than this), and 2) simply modifying ETMSP to run on a vector supercomputer would only result in scaler speed. Thus, ETMSP would probably run faster on a vector supercomputer than on a super-workstation only if significant vector speedups are obtained on the vector supercomputer. Achieving significant vector speedups would probably require a lot of work and significant changes to many parts of ETMSP. Most vector supercomputers have more than one processor and can be used as parallel machines. Thus, one could develop a parallel stability code for a vector supercomputer. We are not aware of any work on this problem. Most vector supercomputers have batch queues and the turn-around time for a job may be significantly greater than the actual run time. Thus, a dedicated super-workstation may give a better turn-around time than a heavily loaded vector supercomputer, even if ETMSP runs faster on the vector supercomputer.

The current data on transient stability programs and parallel supercomputers suggest that ETMSP could probably run about 15 to 20 times faster on a parallel computer than on a 0.4 MFLOPS workstation. This suggests that a stability code on a parallel machine might be two to three times faster than a stability code on a super-workstation. It is possible that parallel machines could yield speedups greater than 20 (relative to a 0.4 MFLOPS workstation), but this is still a research area. Modifying ETMSP to run on a parallel computer would require a moderate to large amount of work.

A lot of work is currently being done on parallel computing using networked workstations (Beguelin et al. 1991; Smith 1991; Benzoni, Richelli,

and Sunderam 1992). Currently, however, the communications overhead on these workstation networks is fairly high. It is possible, however, that a small parallel speedup could be obtained on a small cluster of these super-workstations, but only on large problems. A parallel speedup of even three or four on one of these clusters would be comparable to a significantly larger speedup on a parallel computer with 6 MFLOPS processors. This is because each super-workstation is much faster than one processor in one of these parallel machines. We are not aware of any attempts to run stability codes on clusters of workstations.

Some computer manufacturers are starting to deliver what are essentially clusters of workstations which have a shared memory and can be used for parallel computing. These computers have a fairly low communications overhead. Thus, one of these computers can probably achieve a higher parallel speedup than a cluster of a few networked workstations but would probably cost more.

Overall, it appears that it would take a lot of work to get a stability code to run significantly faster on a vector supercomputer than on a super-workstation. It also appears that a stability code like ETMSP might run two to three times faster on a current parallel computer than on a super-workstation. Parallel computers, however, are generally more expensive than super-workstations. It may be possible to achieve a small parallel speedup on large stability problems by using a small cluster of super-workstations. These results indicate that for most applications a super-workstation is probably the best computer on which to run ETMSP in the near future. Experimenting with a parallel version of ETMSP on a small cluster of workstations may also be beneficial in the near term. Obtaining useful benefits from larger scale parallelism, however, appears to be a longer term research topic.

The results in this section are based on rough estimates for how fast a stability code like ETMSP would run on a single processor of various

computers. Improved performance estimates could be obtained by benchmarking ETMSP on various machines.

2.6 GENERAL METHODS FOR SPEEDING UP AN ODE CODE

A large fraction of the time spent running general codes for the solution of stiff ODEs is used to solve the set of implicit algebraic equations obtained by discretizing the ODEs. Thus, a number of methods have been considered for speeding up the solution of these equations in general ODE codes for stiff problems (Gupta, Sacks-Davis, and Tischer 1985). Most of this work has focused on reducing the cost of evaluating and/or factoring the Jacobian matrix. These algorithms and their possible use in ETMSP are described below.

The simplest and most frequently used methods are 1) to update the Jacobian only when Newton's method takes too many iterations, rather than at every time step, and 2) to use sparse matrix methods when appropriate. ETMSP and most other stability codes already do these things.

Quasi-Newton methods can be used to update the sparse Jacobian, or its sparse factorization, thus reducing the number of times the Jacobian actually needs to be re-evaluated and factored (Brown, Hindmarsh, and Walker 1985). The timing results obtained for the problems described in Section 2.4 indicate that ETMSP only spends about 7% of its time evaluating and factoring the machine Jacobian matrices when they are updated every few time steps. Thus, this method could provide at best only a modest improvement in the performance of ETMSP.

In some problems it is very difficult or expensive to evaluate the Jacobian, hence finite differences have been used to approximate it. Timing results obtained for the problems described in Section 2.4 indicate that the cost of evaluating and factoring the machine Jacobians is only about 5.5 times greater than the cost of evaluating $f(x,v)$. Thus, using finite differences to

approximate the Jacobian would save little or no time in ETMSP, and may actually take longer than directly evaluating the Jacobians.

Most general ODE codes use a variable step size. The Newton iteration matrix is a function of the step size; hence it must be re-evaluated and factored after each change in step size. Two methods have been proposed for reducing this cost. The simplest method is to save a copy of the Jacobian matrix and use it to re-compute the iteration matrix when the step size changes (Enright 1978). The modified iteration matrix must still be factored. The other method is to reduce the original iteration matrix to upper Hessenberg form (where $a_{i,j} = 0$ for $i > j + 1$) (Enright 1978). This method is useful because the LU factorization of the upper Hessenberg matrix is inexpensive to compute. Hence, refactoring the iteration matrix following a step size change is cheap. This method is mainly applicable to dense systems and would not be useful in ETMSP. Furthermore, ETMSP is currently a fixed step size code. Hence, even the first of these algorithms would be of little use in ETMSP. If ETMSP is modified to use a variable step size algorithm, then saving a copy of the machine Jacobians could be beneficial. This is particularly true because the cost of factoring the machine Jacobians in ETMSP is small compared to the cost of evaluating them.

Iterative methods have been used to solve the linear systems of equations appearing in Newton's method (Chan and Jackson 1986; Gear and Saad 1983; Brown and Hindmarsh 1989). All of these methods avoid the cost of factoring the Jacobian. Some of these methods only require a directional derivative; hence they can avoid the cost of evaluating the Jacobian by using a finite difference approximation to the directional derivative. This second technique would not work well in ETMSP because the extra function evaluations required to compute the directional derivatives would exceed the cost of evaluating the Jacobian. Timing results obtained for the problems described in Section 2.4 indicate that ETMSP spends only a very small fraction of its time factoring the machine Jacobian matrices. Thus, direct methods are very efficient for

these equations, and iterative methods are not likely to be competitive. Furthermore, in transient stability simulations the network matrix undergoes only a few changes. Thus, direct methods for solving the network equations are very efficient, and iterative methods are unlikely to be competitive. In Section 2.4 it was found that, in voltage stability simulations, the cost of refactoring the network matrix following tap changes represented a significant fraction of the total CPU time. This seems to be the one place where iterative methods might be useful, but only if the use of techniques such as partial matrix refactorization and compensation fail to work.

In stiff problems Newton's method is used to solve the implicit nonlinear equations because functional iteration will not converge except with small step sizes. However, Newton's method is much more expensive than functional iteration. This has led people to develop algorithms that use functional iteration in the non-stiff portion of the integration and Newton's method in the stiff region (Norsett and Thomsen 1986). The main difficulty is deciding if the current region is stiff or non-stiff. This suggests that functional iteration could be used in ETMSP during the transient phase when the user specifies the smallest time steps. The analysis in the next section, however, indicates that the fast exciter equations will probably prevent this method from converging. This happens because of the low accuracy with which the exciter equations are typically solved.

The cost of Newton's method has led people to try partitioning the system into stiff and non-stiff components. One can then use a stiff method on the stiff components and a non-stiff algorithm on the non-stiff components, or use the same algorithm on both components, but use functional iteration for the non-stiff components and Newton's method on the stiff components. The accuracy of the first method, and the rate of convergence of the second method, are sensitive to the correct identification of the stiff and non-stiff subsystems as well as to the amount of coupling that is present between these subsystems. Thus, the second method is generally recommended (Enright and

Kamel 1979). The main difficulty of this method is finding an appropriate partitioning of the equations.

Various methods have been proposed for obtaining appropriate partitionings, but they are mostly for problems that are dense, and/or only have a few fast components (Enright and Kamel 1979). The use of sub-time steps to integrate power system problems represents a form of partitioning in which the fast exciter equations are integrated using a small time step. Using the same time step for all equations, but Newton's method for the fastest exciter equations and functional iteration for the remaining equations, may be a useful alternative to the sub-time step method. Multirate integration, i.e., the use of large time steps for the slow equations and smaller time steps for the faster equations, has also been explored (Gear and Wells 1984; Skelboe 1989). The partitioning and localization algorithms described in Section 2.3 are forms of multirate integration applied to power systems. The results presented in Section 2.3 suggest that this form of partitioning can significantly increase the speed of a transient/mid-term stability program.

2.7 IMPROVED INTEGRATION ALGORITHMS FOR POWER SYSTEMS

This section examines the possibility of using alternate integration algorithms to speed up ETMSP.

There are three regions to consider when doing a stability simulation. Region one is the first few seconds of a stability simulation, where there are frequent discontinuities caused by limits on variables and/or their derivatives. Region two is the remaining time in a transient stability simulation and the period ending when ULTC transformers start operating (typically at about 30 seconds) in voltage stability simulations. This region is relatively smooth and has infrequent discontinuities. Region three is the rest of a voltage stability simulation. This region may have frequent discontinuities associated with tap change transformers.

2.7.1 Region 1 - Fixed Step Size Algorithms

Finding a better integration algorithm for this region of the simulation depends on understanding what limits the step size used by the algorithms currently in ETMSP. Three main factors may limit the step size: 1) stability, 2) the accuracy of integrating the fastest transients, and 3) the error incurred by stepping across discontinuities without actually locating them.

In at least part of this region transients will be present and the step size must be small enough to follow them with some degree of accuracy. This means the step size will usually be within the region of absolute stability for the Runge-Kutta methods. Furthermore, the trapezoidal rule is A-stable, hence any positive step size will be within its region of absolute stability. Thus, stability is unlikely to limit the step size used by ETMSP in region one.

In most stability simulations a step size of around 0.01 seconds will generally yield a sufficiently accurate solution for problems with time constants as small as 0.01 seconds. Consider the equation $x' = -100x$ as a model for the transient component associated with a time constant of 0.01 seconds. Using a step size of 0.01 seconds with the trapezoidal rule or fourth-order Runge-Kutta method to integrate this model problem will yield relative errors of about 0.1 per step. Furthermore, the fourth-order Runge-Kutta method can only take a step about 30% larger than the trapezoidal rule when a maximum relative error of 0.1 is required. These results indicate that the fastest components of stability simulations are being integrated with an error of around 10% per step. Hence, the component of the numerical solution following the fast transients is fairly inaccurate but decays at roughly the same rate as the true solution. Using moderately larger step sizes would cause the numerical solution to completely lose the true solution.

Bonneville has occasionally observed oscillations in the fastest variables when using the fixed step size trapezoidal rule and found that

reducing the step size by a factor of two eliminates the problem. Consider the problem $x' = \lambda x$, $\lambda < 0$. The trapezoidal rule is A-stable, thus the numerical solution will decay for all $h > 0$. The stability polynomial of this method, however, approaches -1 when $|\lambda h|$ is large in magnitude, and the numerical solution oscillates when $\lambda h < -2.0$. This is probably the cause of the oscillations seen by Bonneville when the step size was too large. Furthermore, this means that when one has oscillations and reduces the step size by a factor of two, then λh is around -1.0. This value of h will cause $x' = \lambda x$ to be integrated with a relative error of about 10% per step.

Finally, Bonneville has said that one generally only needs a crude approximation to the fastest transients in a problem (relative errors as large as 0.1 per step are not unreasonable), but that a reasonable accuracy is needed in the components of the solution associated with time constants that are 3 to 4 times larger than the smallest time constants.

The preceding discussion indicates that the requirement of integrating the fastest equations with a relative error of about 10% per step is the main factor limiting the step size of codes like ETMSP. The fact that using sub-time steps on the fastest exciter equations has been found useful in Bonneville's transient stability code reinforces this conclusion. The preceding results also indicate that higher order methods can only provide small increases in step size.

One of the simplest ways to speed up ETMSP is to retain the fixed order and step size algorithm currently used, but to use a different integration algorithm. In this case the integration algorithm must be able to either 1) take bigger step sizes than the methods currently in ETMSP, or 2) take steps of about the same size, but do it much faster. This possibility will be considered now.

The main explicit ODE algorithms are the Runge-Kutta, Adams-Moulton (AM), and extrapolation methods. Extrapolation methods are primarily for smooth problems requiring high accuracy; hence they are inappropriate for power

system problems. Furthermore, all of the published comparisons between the Runge-Kutta and trapezoidal methods on power system problems indicate that the trapezoidal rule is superior.

The cost of taking a step using the PECE implementation of the AM methods (i.e., doing one corrector iteration) is about the same as the cost of taking a step using a second order Runge-Kutta method. Implementations iterating the corrector to convergence are more expensive. Using the AM formulas as a predictor-corrector method requires that $|\lambda h \beta_0|$ (where λ is the dominant eigenvalue of the Jacobian and β_0 is from Equation (2.11)) be significantly less than one for the corrector iterations to converge rapidly. β_0 is between one-half and one-third for the lower order AM methods. Furthermore, the previous discussion found that the trapezoidal rule currently takes steps where $|\lambda h|$ is near 1.0, indicating that the predictor-corrector versions of the AM methods would have to use smaller step sizes than the trapezoidal rule. In Section 2.4.4 it was found that the second order Runge-Kutta method in ETMSP can take one step about as fast as the trapezoidal rule does, provided only one iteration is required in Newton's method. These results suggest that the predictor-corrector implementation of the AM formulas would not be any faster than the trapezoidal rule currently in ETMSP.

The AM formulas could be implemented using Newton's method to solve the nonlinear equations. (In fact the trapezoidal rule is the second order AM method.) In this case the higher order of the AM methods would probably allow them to use slightly larger steps than the trapezoidal rule. As with the fourth-order Runge-Kutta method, however, the fourth-order AM method probably cannot increase the step size by more than 30 to 50% over the trapezoidal rule. Taking a step with the AM methods would be a little more expensive than with the trapezoidal rule because of their higher overhead. Finally, their multistep character will make the AM methods more sensitive to discontinuities than the trapezoidal rule. Overall, a fixed step size, fixed order, AM method of order three or four, in which the corrector equation is solved using

Newton's method, probably would not reduce the execution time of ETMSP by more than 20 to 30%. Higher order formulas are not appropriate because of the lax error tolerances.

The main reason for using implicit methods is because they have larger regions of absolute stability, not because they are more accurate than explicit methods. Thus, it would seem that using higher order implicit methods, like the BDFs, would not be any more successful than using the AM methods. In fact, the BDFs are likely to be less efficient because the k -th order BDF formula is less accurate than the k -th order AM method. Most of the alternatives to the BDFs are designed to be more efficient when there are eigenvalues near the imaginary axis, and most are more expensive and more complicated than the BDFs. Thus, these methods are likely to be inferior to the BDFs on this problem in this region. It does not seem likely that any of the general implicit methods would be any more likely to increase the efficiency of ETMSP than the explicit methods.

The theta method (described in Section 2.2) allows the integration algorithm to be fitted to the dominant eigenvalue of the problem. The results described in Section 2.3 indicate that this method can take bigger steps than the trapezoidal rule if an adaptive fitting algorithm is used at every time step. This is consistent with the previous finding that it is the accuracy of integrating the fastest transients which limit the step size in stability codes. The data in the papers described in Section 2.3, however, do not indicate how much bigger the step could be when both algorithms are required to solve a problem with the same accuracy. The theta method has the disadvantage that it is only first order (except when $\Theta = 1/2$), while the trapezoidal rule is second order. Thus, the trapezoidal rule will typically provide more accurate values for the slow components of the problem, which are usually of the most interest.

Overall, it appears that there are no constant step size, constant-order integration algorithms that are likely to significantly increase the

performance of ETMSP in the first few seconds of a simulation. The third- or fourth-order AM method using Newton's method (at least for the fast equations) may be able to reduce the execution time of ETMSP by 20 to 30%. The theta method would probably increase the performance of ETMSP, but it is difficult to predict how much. The only way to see if one of these methods actually works better than the trapezoidal rule is to try them.

2.7.2 Region 1 - Variable Step Size Algorithms

Using a variable step size, variable order code is another possible way of improving the performance of ETMSP. Dembart et al. (1977) used the local truncation error in a trapezoidal rule code to estimate the step sizes that a variable step size code could use. They found that some sort of variable step size algorithm would probably be beneficial on some problems. Stott (1979) also thought a variable step size algorithm might be useful.

The value of having ETMSP use a variable step size algorithm in this region was examined by having ETMSP compute the local truncation error (LTE) when simulating the first 2 seconds of the test problems described in Section 2.4. A step size of 0.01 seconds was used in the voltage stability test problem and a step size of 0.0042 seconds was used in the transient stability test problem. These were the step sizes supplied by Bonneville. The LTE was used to estimate the step size that could be used on each step. This was done by requiring that the estimated error in every state variable be less than $RELERR * |x_i| + ABSERR$, where x_i is the value of the i-th state variable and RELERR and ABSERR are relative and absolute error tolerances, respectively. The same values of RELERR and ABSERR were used for all of the variables. In a variable step size code, however, different error tolerances may be used for different variables, e.g., the tolerances for the exciter variables might be less stringent than the tolerances for the mechanical variables. Thus, the step sizes based on uniform error tolerances only give an indication of the step sizes that could actually be used. Step size estimates were obtained using absolute error tolerances of 10^{-8} , 10^{-3} , and 10^{-2} , and relative error

tolerances varying from 10^{-1} to 10^{-3} . Using an absolute error tolerance of 10^{-8} amounts to using almost pure relative error control, which typically does not work well when variables pass through zero.

Using the absolute error tolerance of 10^{-8} and the relative error tolerance of 10^{-3} with the transient stability problem it was found that the allowed step size was between 0.001 and 0.003 seconds for a large fraction of the simulation. The step sizes allowed when using the relative error tolerance of 10^{-2} were almost always twice as large as the values allowed when using 10^{-3} . Similarly, the step sizes allowed when using the relative error tolerance of 10^{-1} were almost always twice as large as the values allowed when using 10^{-2} . These results mean that the absolute error tolerance generally did not influence the allowed step size. There were a number of sections of the simulation, however, where the allowed step size was almost independent of the relative error tolerance, hence it was controlled by the strict absolute error tolerance. In many of these sections, the allowable step size was very small (as low as 0.0001 seconds) and was controlled by the behavior of variables with small values. The relative error tolerance of 10^{-3} produced step sizes that showed a pattern of being several times larger in some areas than in others. Within any given area, however, the step size jumped around a moderate amount. It appears that a lot of this jumpiness was caused by the strict absolute error tolerance.

Using the absolute error tolerance of 10^{-3} and the relative error tolerance of 10^{-3} with the transient stability problem, it was found that the allowed step size was between 0.001 and 0.005 seconds for most of the simulation. At these tolerances, the step size varied somewhat erratically in the first 0.2 seconds, but was a fairly smooth function with only occasional jumps the rest of the time. After the first 0.2 seconds of the simulation the step size was a slowly decreasing function of time, interrupted by spots where the step size would rapidly increase by a factor of about three. The behavior of the step size when using the other relative error tolerances was similar,

except that they allowed uniformly larger step sizes. This pattern was also present when using the absolute error tolerance of 10^{-8} , but was less obvious because the step size jumped around more (mainly where very small step sizes were required). Using the absolute error tolerance of 10^{-2} produced results essentially the same as those obtained using 10^{-3} , except that the step sizes were uniformly larger.

The preceding experiments show that in the transient stability test problem the allowable step sizes are strongly dependent on the choice of error tolerances. The absolute error tolerance of 10^{-8} is probably too strict for many if not all variables. The fairly smooth, slow variation of step size in this problem, at the less restrictive absolute error tolerances, means it is reasonable to use a variable step size algorithm. In fact, a variable step size code would probably run about twice as fast on this problem as a fixed step size code that used the minimum estimated step size. Most of this gain would occur after the first few tenths of a second of the simulation.

Using 10^{-3} for both the absolute and relative error tolerances yielded step size estimates that were almost always less than 0.0042 seconds (the step size used in the simulation); and had a mean value between 0.002 and 0.003 seconds. Bonneville, however, can solve most of its stability problems with sufficient accuracy using step sizes of 0.0042 seconds (one-quarter cycle) or larger. This suggests that using 10^{-3} as both the absolute and relative error tolerances for all variables is probably too strict for some variables. It may also be too lax for other variables. Using a more realistic set of error tolerances for each type of variable in ETMSP may significantly change the behavior of the step size estimates. Ideally, this would yield estimates where the average step size is substantially larger than the largest step size that is found to work well in a fixed step size code. Thus, a final determination of whether a variable step size code would run faster on a problem like this one requires developing a realistic set of error tolerances for each type of variable in ETMSP.

The step size experiments done with the transient stability test problem were repeated using the voltage stability test problem. Overall, the results with this problem were similar to those for the transient stability problem, except for two main differences. First, the variation of step size with time was not quite as smooth for the voltage stability problem. Second, the voltage stability problem showed a different overall pattern for the step size as a function of time. The voltage stability problem initially required a small step size. Over the first few tenths of a second the allowable step size increased by a factor of about three. Starting at about 0.30 seconds the step size changed rapidly and exhibited a general trend to oscillate with a period of about 0.1 seconds. This pattern was most noticeable using the absolute error tolerances of 10^{-3} and 10^{-2} . Using 10^{-3} as both the absolute and relative error tolerances produced a mean value of about 0.01 seconds, and upper and lower bounds of about 0.014 seconds and 0.008 seconds, respectively, for these oscillations.

Always using the maximum possible step size on the voltage stability problem would require changing the step size almost every time step. This would reduce the execution time (not counting the cost of the step size changes) by only about 20%, relative to a code that used a constant step size equal to 0.008 seconds. The costs of doing all of these step size changes, however, would negate most if not all of the gain. Recall that the step sizes in the first 0.03 seconds of this problem were consistently smaller than for the rest of the problem. This indicates that a step size algorithm that monitors the error and occasionally adjusts the step size could be effective on this problem. The comments about the use of more appropriate error tolerances on each of the variables for the transient stability test problem apply here.

The preceding experiments suggest that variable step size algorithms, of one form or another, would probably be useful in region one. This is essentially the same conclusion arrived at by Dembart et al. (1977). A more

detailed evaluation of this possibility requires developing a realistic set of error tolerances for each type of variable in ETMSP and actually experimenting with a variable step size code.

The rest of this section assumes that some sort of variable step size algorithm is probably useful for at least some problems.

Failing to locate discontinuities can cause two difficulties when using a variable step size ODE code. First, the code will generally have difficulty crossing any discontinuities that it detects. A well designed step size selection algorithm can reduce the seriousness of this problem. This problem tends to be less serious when using lax error tolerances, such as those likely to be used on stability problems. Second, the error estimate for steps that cross discontinuities will generally be smaller than the actual error. It is usually recommended that one locate each discontinuity and take a time step that ends at each discontinuity. This generally reduces the amount of work required by an ODE code and yields more accurate results.

The amount of difficulty caused by discontinuities, however, is problem dependent. Experiments using the variable step size trapezoidal rule to integrate the test problem $x' = \lambda x$, with a limit placed on the value of x , found that the actual error when crossing the discontinuity could be almost 10 times larger than the requested error tolerance. This suggests that failing to locate discontinuities could require using error tolerances about a factor of 10 smaller than the tolerances that are actually desired. In a problem with many variables, however, it is possible that the step size required to integrate a smoothly varying component of the solution is smaller than the step size required to accurately cross a discontinuity in another variable. In this case the discontinuity would not cause problems.

There are two main ways to locate discontinuities. The most efficient, and recommended, way is to have the user supply a switching function that determines when a discontinuity can occur. For limits, this amounts to supplying a description of which variables have limits and the values of these

limits. This switching function is used to locate and step to discontinuities. Multistep methods should usually be re-started following a discontinuity. This can be made more efficient by using Runge-Kutta starters to re-start the method at high order (Gear 1980). Not restarting a multistep method following a discontinuity typically reduces the accuracy of the method. The severity of this inaccuracy, however, depends upon the size of the discontinuities and the step size used when passing the discontinuities.

Automatic methods of locating and passing discontinuities have also been proposed (Gear and Osterby 1984; Enright et al. 1988; Cash and Karp 1990). These automatic methods may not detect some discontinuities at lax error tolerances, and the error incurred when stepping across these discontinuities may be larger than requested.

Most stability codes do not locate where discontinuities, such as limits, occur. They simply impose the limits as needed. Whether failing to locate discontinuities in power system problems would cause problems for a variable step size code can only be determined by running simulations with many different problems. The published data on EUROSTAG, which is a variable step size code, does not say whether or not it actually locates discontinuities (Stubbe et al. 1989).

Most step size selection algorithms will produce a large error estimate and significantly reduce the step size when a step crosses a serious discontinuity. When using the absolute error tolerance of 10^{-8} to estimate step sizes in the transient stability problem it was found that there were many places where the allowed step size suddenly dropped significantly. This indicates that discontinuities could cause problems at this error tolerance. At the absolute error tolerance of 10^{-3} , however, these events were fairly rare. Hence, discontinuities do not seem to be a problem at this tolerance. Reality, however, is probably somewhere between these extremes. The results with the voltage stability case are less clear because the step size changes fairly rapidly. A final determination of the effects of discontinuities on a

variable step size code requires developing such a code and doing some numerical experiments.

We now consider the question of what integration algorithms are likely to work best in a variable step size code. An algorithm appropriate for stiff methods is probably most appropriate for a variable step size code for two reasons. In sections where larger step sizes can be used, the transient components will generally be negligible; hence the problem is stiff. Also, the fast transients are integrated with such low accuracy that the problem is almost stiff even in the transient region. Dembart et al. (1977) found that a variable step size, variable order Adams-Moulton code was slower than their fixed time step trapezoidal rule code. They also projected that a third order Runge-Kutta method would be slower than the trapezoidal rule. These results support the idea that variable step size explicit methods generally will not perform better than the trapezoidal rule.

The trapezoidal rule is good for this problem because it is 1) accurate, 2) A-stable, and 3) a one-step method, making it less sensitive to discontinuities than multistep methods. The disadvantages are that it is only second order, and its stability polynomial approaches -1 at negative infinity. The damping at infinity is probably not a serious problem in this part of the integration because $|\lambda h|$, where λ is the dominant eigenvalue of the Jacobian matrix, will probably only be moderately large. In this case the trapezoidal rule will probably provide reasonable damping of the fast transient error components of the solution. Thus, the main reason for looking at other algorithms is to find higher order methods which would allow the use of bigger step sizes.

In Section 2.7.1 it was found that higher order methods are of limited value because the step size appeared to be limited by the requirement of integrating the fast transients with a very crude tolerance. With a variable step size code, however, higher order methods may be useful. This is because larger steps will only be used when the fastest transients have died out, in

which case the step size will be limited by the requirement of following the more slowly varying components of the solution with a higher accuracy. The error tolerance is fairly lax even for these slower components of the solution. Hence, methods of order three or four may be useful, while higher order methods do not appear to be appropriate.

For stiff problems, the BDFs are usually preferred unless there is something about the problem that makes them inappropriate. The frequent discontinuities in the power system problem will probably reduce the efficiency of multistep methods like the BDFs. Testing of EUROSTAG has shown that this variable step size BDF code only ran faster than other codes when the simulation time exceeded a few seconds (Stubbe et al. 1989). This suggests that a variable step size implementation of the BDFs would not perform any better than the trapezoidal rule. Many of the alternatives to the BDFs are also multistep algorithms and seem to have no advantage over the BDFs for this region (Gupta, Sacks-Davis, and Tischer 1985). The implicit Runge-Kutta (IRK) and Rosenbrock methods are one step methods. They are extensions of the explicit Runge-Kutta methods, which are applicable to stiff problems (Shampine 1982; Gupta, Sacks-Davis and Tischer 1985). A third- or fourth-order version of one of these methods may be useful in this region.

A general r -stage IRK method is defined by Equation (2.10) and requires the solution of an Nr -by- Nr system of nonlinear equations, where N is the number of equations in the problem. Hence, the general IRK methods are not practical on large problems.

Diagonally implicit Runge-Kutta Methods (DIRKs) are obtained by setting $a_{ij} = 0$ for $j > i$ in Equation (2.10). DIRKs are only practical if a_{ii} has the same value for $i = 1$ to r ; otherwise, the iteration matrix in Newton's method is different for each of the r nonlinear systems. An r -stage DIRK requires the solution of r nonlinear systems of equations, each one similar to the nonlinear equations solved when using the trapezoidal rule. Hence, they require much less work than a general IRK. Taking a step with an r -stage DIRK

is about r -times as expensive as taking a step with the trapezoidal rule. Finally, an r -stage DIRK has an order of accuracy no greater than $r+1$ (Fatunla 1988, p. 205). This means that the larger step size, relative to the trapezoidal rule, obtainable with a higher order DIRK will be partially counteracted by the higher cost of DIRKs. In fact, with the lax error tolerances in this problem, a higher order DIRK will probably do little, if any, better than the trapezoidal rule.

An r -stage singly implicit Runge-Kutta Method (SIRK) is a method where the matrix consisting of the a_{ij} s in Equation (2.10) has a single r -fold eigenvalue. This fact can be used to transform the variables in the problem such that r standard nonlinear systems need to be solved, rather than one bigger Nr -by- Nr system. SIRKs are somewhat more expensive and complicated than DIRKs because the variables must be transformed at every step. An r -stage SIRK, however, is generally of higher order than an r -stage DIRK. This usually makes the SIRKs more efficient on large problems and may make them competitive with the trapezoidal rule at lax tolerances.

Rosenbrock methods are extensions of the explicit Runge-Kutta methods in which the computation of each stage of the method requires the solution of a system of implicit linear equations (Shampine 1982; Gupta, Sacks-Davis, and Tischer 1985). For the power system problem, this linear system is actually many separate linear systems, one for each device. Solving these implicit linear equations requires evaluating and factoring the machine Jacobian matrices on every step. The evaluation of each stage also requires one solution of Equation (2.2) and one evaluation of Equation (2.1), which is the same as the cost of evaluating one stage of an explicit Runge-Kutta method, and somewhat less than the cost of doing one iteration of Newton's method with the trapezoidal rule.

For the test problems run in Section 2.4 it was found that 1) the cost of evaluating and factoring the machine Jacobian matrices is about 5.5 times greater than the cost of evaluating $f(x,v)$, and 2) the cost of solving

Equation (2.17) is about the same as the cost of evaluating $f(x,v)$, provided only one iteration is required to solve Equation (2.17). These results indicate that if the Newton iterations in the trapezoidal rule converge in only one iteration and the machine Jacobian matrices are only updated occasionally, then the cost of taking a step with the trapezoidal rule will be several times smaller than the cost of taking a step with a 3- or 4-stage Rosenbrock method. In this case, the extra work associated with the Rosenbrock methods will probably eliminate the benefits of being able to take larger steps. If the trapezoidal rule requires more iterations to converge and updates the machine Jacobians fairly frequently, then a 3- or 4-stage Rosenbrock method will probably do about as well as the trapezoidal rule and maybe better. It is possible, however, that the larger step sizes will require more than one iteration to solve Equation (2.17). This would increase the cost of the Rosenbrock method. In the first few seconds of the simulations using the test problems described in Section 2.4, it was found that the Newton iterations converged in an average of just over one iteration, and the machine Jacobian matrices were only updated a few times. A variable step size version of the trapezoidal rule, however, may find that more iterations and Jacobian updates are needed as the step size increases. This would make the work per step similar for the Rosenbrock methods and the trapezoidal rule. In this case a Rosenbrock method may prove to be superior to the trapezoidal rule. A few Rosenbrock methods that use approximate Jacobians (i.e., they do not require computing the machine Jacobian matrices on every step) have been suggested in the literature (Steihaug and Wolfbrandt 1979; Burmeister, Grossmann and Scholz 1991). Little work, however, has actually been done to develop these methods.

The analysis in Section 2.7.1 suggests that in this region the step size may frequently be limited by the requirement of crudely following the fastest transients. In these sections the higher order one step methods will probably require significantly more work than the trapezoidal rule to integrate the same distance. Furthermore, the higher order methods pay a much higher price

for a failed step than does the trapezoidal rule. This will reduce the efficiencies of these methods if discontinuities cause frequent step failures in this region. In conclusion, the frequent discontinuities and transients in this region and the lax error tolerances of this problem will probably prevent the higher order one step methods from working significantly better than the trapezoidal rule in this region. Thus, it appears that the trapezoidal rule is probably the best method to use in this region. Deciding if this is actually the case, however, requires implementing a variable step size version of the trapezoidal rule and examining its behavior. For example, does the requirement of crudely following the fast variables actually control the step size in a large fraction of the simulation? Are there many failed steps caused by discontinuities (this is only a problem if a switching function is not used to locate discontinuities)? How many iterations are usually required with Newton's method? etc.

Is a fixed step size code, as in Section 2.7.1, or a variable step size code, as in this section, likely to be faster in this region of the simulation? With the trapezoidal rule, the cost of estimating the allowed step size is relatively low. Hence a step size estimator could be put in a trapezoidal code without significantly increasing the amount of time to take a step. Thus, on a problem that requires a relatively constant step size, a variable step size code using the trapezoidal rule could be competitive with a fixed step size trapezoidal code, provided they both use comparable step sizes. This requires defining a good set of error tolerances for the variables in ETMSP. The variable step size code would almost certainly be superior on problems that require small step sizes in some areas but allow larger step sizes in others. A variable step size algorithm, however, must be well designed if it is to efficiently handle problems where the step size jumps around erratically. Another factor to consider in variable step size codes is that the Newton iterations may fail to converge if the predicted results at the next time step are not accurate enough. Thus, it is possible

that better predictors may be needed to take full advantage of a variable step size algorithm.

2.7.3 Region 2

This region differs from region one mainly in that discontinuities are much less frequent, and most of the region could be considered stiff. The success of EUROSTAG suggests that a variable step size, variable order version of the BDFs may be more efficient than a variable step size version of the trapezoidal rule, even at the lax tolerances used in this problem. The published data on EUROSTAG, however, does not say whether or not this code has been compared to a code based on the trapezoidal rule. Thus one cannot say that the BDFs are clearly superior to a variable step size trapezoidal rule code (Stubbe et al. 1989). It seems likely, however, that the BDFs would generally be superior in this region because of their higher order and better stability at infinity.

The step size experiments done in region one were repeated for this region. Using the transient stability problem the time period from 2 to 10 seconds was examined. In this time period the required step size continued its pattern of generally being a slowly decreasing function, interrupted by places where the step size rapidly increased by a factor of 2 to 3. As the simulation proceeded, however, the average step size tended to be larger. There were also a few regions where the step size remained fairly large for a few tenths of a second before starting to slowly decrease. The minimum step size in this region was about 0.002 seconds, while the larger step sizes were typically around 0.007 seconds. These results suggest that a variable step size code would work well on this problem.

The step sizes allowed for the voltage stability problem were examined in the integration interval from 2 to 5 seconds. This interval was used because tap changing transformers start operating just after 5 seconds. The step sizes in this region showed the same rapid oscillations exhibited in region one. Thus, a fairly constant step size would have to be used. There were,

however, several load shedding events near the end of this time interval. After each of these events, the required step size dropped sharply and required about 0.02 seconds to climb to its previous value. Thus, occasional step size adjustments would be useful on this problem. The comments in Section 2.7.2 about developing more appropriate error tolerances apply here.

The work with EUROSTAG indicates that there are times when low frequency, poorly damped oscillations in some machine rotors force EUROSTAG to restrict the BDFs to using only the first- and second-order methods. The published information does not state whether or not this significantly impacts the efficiency of the code. It has generally been found that BDF codes are not the best choice when the problem has eigenvalues close to the imaginary axis (Addison 1984; Gaffney 1984). Tischer (1989) has looked at this problem and believes that part of the reason for the poor performance of the BDFs on this class of problems is that they may fail to reduce the order down to two (which gives an A-stable method). Based on this, a new order selection strategy was developed that helps force the order of the method down to two. This was found to significantly increase the efficiency of the BDFs on some of these difficult problems. Gaffney (1984) also found that the efficiency of the BDFs was improved on these problems by restricting the maximum order to two.

Overall, the EUROSTAG results indicate that the BDFs will probably work well in this region of stability simulations. If the need to restrict these methods to second order occurs frequently, and this significantly impacts the performance of the code, then other methods should be investigated. Possible methods include DIRKs, SIRKs, Rosenbrock, blended multistep, and composite and cyclic multistep methods (Fatunla 1988). In region one, the multistep alternatives to the BDFs were not considered particularly useful because of the frequent discontinuities. In region two, however, discontinuities are less common; thus the multistep alternatives to the BDFs are worth considering. Addison (1984) and Gaffney (1984) compare some of these methods on a few test problems. These methods generally require more work per step

and are more complicated than the BDFs; thus it is preferable to use the BDFs if possible.

2.7.4 Region 3

In this region it is possible for discontinuities to occur because of limits on variables. The majority of discontinuities, however, are likely to be caused by tap changes. Thus, this section will be concerned with the impact of tap changes. If tap changes occur infrequently, then this region is not much different than region two, and the methods described for region two should work fairly well here. Thus, the case of interest in this section is when there are frequent tap changes.

Tap changes start occurring in the voltage stability test problem just after five seconds into the simulation. Thus, the step sizes required by the voltage stability problem (when integrated using a time step of 0.01 seconds) were examined in the integration interval from 5 to 60 seconds. In this region, tap changes occurred almost every 10 time steps, the maximum frequency with which they were allowed. Using 10^{-3} for both the absolute and relative error tolerances, it was found that immediately following a tap change a step size of about 0.002 seconds would typically have to be used. The allowed step size would then build up to around 0.006 seconds, and frequently to values as large as 0.01 seconds, before the next tap change occurred. The allowed step size typically reached its pre-tap change value within about 0.05 seconds. Using less stringent relative error tolerances caused moderate overall increases in the allowed step sizes. The behavior of the allowed step size was similar when tap changes were only allowed to occur every 20 time steps. Using less-frequent tap changes, however, did not cause the step size to build up to larger values. Instead, the allowed step size started oscillating near the maximum value it reached in the problem when tap changes occurred every 10 time steps.

This problem was successfully integrated using a step size of 0.01 seconds in this region. Furthermore, Bonneville has been able to use a fixed

step size of 0.02 seconds in this region on other voltage stability problems (Taylor and Rodrigues 1992). This suggests that the step size estimates in this region are too conservative and that a more realistic set of error tolerances would produce larger values for the minimum required step size.

These tests show that if the same error tolerances are used for all variables, then the step size following a tap change must be reduced significantly. The most likely cause of this reduction in step size is that transients associated with some of the fast variables have been re-excited. The rapid increase of step size following a tap change is consistent with this interpretation. These results indicate that the problem is not stiff for about 0.05 seconds following a tap change. The value of 0.05 seconds is problem-dependent, and it will typically depend on the smallest time constants in the problem and which tap changers acted at the end of the current time step. The fact that transients are excited following tap changes is a characteristic of the problem, not of the error tolerances used. The amount, if any, by which the step size must be reduced because of these transients, however, depends upon the error tolerances and the magnitude of the excited transients.

Assume the step size immediately after a tap change must be significantly reduced, even when using more realistic error tolerances. Then a code must change the step size several times following a tap change if it is to take maximum advantage of the fact that the allowable step size increases the farther you get from the tap change (up to a point). Thus, changing the step size must be relatively inexpensive. This appears to be the case in ETMSP, provided copies of the machine Jacobians are stored and used to compute the machine Newton iteration matrices. Thus, if the step size behavior following tap changes obtained using realistic error tolerances is similar to the behavior found using the tolerances above, then a variable step size version of the trapezoidal rule could probably speed up ETMSP by a factor of about two in this region.

If, however, more realistic error tolerances generally eliminate the need to reduce the step size following tap changes, then a standard variable step algorithm would not help ETMSP very much in this region. As in region one, however, the ability to occasionally adjust the step size (automatically) may be useful in passing difficult spots. This may allow a larger average step size to be used in most of this region than would be possible using a step size controlled only by the user. As in region one, a final evaluation of the true value of a variable step size algorithm can only be determined by developing a realistic set of error tolerances and doing experiments with a variable step size code.

We now consider what integration algorithm should be used in this region.

The step size experiments done in this region indicate that significant discontinuities occur in the derivatives of at least some of the state variables at each tap change. It also appears that these discontinuities excite transients associated with the fastest variables and that the step size for the first few steps following a tap change will be limited by the requirement of crudely following these transients. This is the situation considered in region one. This suggests that high order methods are of little value immediately following a tap change. Thus, the trapezoidal is probably the best algorithm to use on these steps, just as in region one.

After taking several steps past a tap change the transients will have died out and the problem will be stiff again. In fact, the problem will be the same as in region two until the next tap change. This suggests that the first few steps following a tap change should be done using a method like the trapezoidal rule. The remaining steps until the next tap change, however, should be taken with the method found most appropriate in region two, e.g., the BDFs. Using this algorithm the BDFs can be started at third- or fourth-order because the data needed to start them will have been generated by the trapezoidal rule. An algorithm like this should speed up ETMSP. The maximum possible speedup, however, will be limited by the frequency with which tap

changes occur and the amount by which the step size must be decreased following each set of tap changes. A more detailed evaluation requires doing experiments using a variable step size code.

Another possible algorithm is to use the BDFs on all steps in this region and not to reduce the step size following a tap change. Instead, one could determine those devices where the discontinuities were significant, and reintegrate them over this interval using a smaller step size. This is the algorithm EUROSTAG uses for some discontinuities (Stubbe et al. 1989). It is not clear, however, whether EUROSTAG does this or completely restarts the BDFs after tap changes. If one uses this algorithm after tap changes, then it is probably best to use the trapezoidal rule or maybe even an explicit Runge-Kutta method to reintegrate the sub-system, rather than using the BDFs. An algorithm like this would be much more complicated to implement than one that treats all equations the same. This algorithm, however, will probably be significantly more efficient on problems where tap changes excite transients on a relatively small fraction of the devices in a problem. A detailed examination of the step size data in this region showed that only 100 to 200 equations (out of several thousand) required that the step size be small following a tap change. Furthermore, most of these 100 to 200 equations could use step sizes moderately to significantly larger than the actually required step size. This indicates that a partitioning algorithm would probably work well on this problem.

The preceding has assumed that one wants to crudely approximate the transients following a tap change. In this region, however, these transients are of less interest than in region one. Thus, one might consider taking steps that are too large to follow these transients and simply require that the numerical approximations to the transients are negligible at the end of the time step. This is not possible with the trapezoidal rule, however, because of its stability properties when $|h\lambda|$ is large. A proposed solution to a similar problem in the Electromagnetic Transients Program (EMTP) is to

take two steps of length $h/2$ with the backward Euler method following discontinuities (Marti and Lin 1989). The backward Euler method is defined by $x_{n+1} = x_n + hf(x_{n+1})$. This method is first order but causes good numerical damping of the solution to the problem defined by Equation (2.6) when $|h\lambda|$ is large. Furthermore, the Newton iteration matrix when using a step size of h with the trapezoidal rule is the same as the Newton iteration matrix when using a step size of $h/2$ with the backward Euler method. This suggests the possibility of using the backward Euler method to take the first few steps after a tap change and then switching to a higher order BDF. This algorithm is just a modification to the standard method of starting the BDFs because the backward Euler method is the first-order BDF.

A final possibility is to convert all of the fast equations in the problem to algebraic equations in this region. This amounts to setting the derivatives of these variables to zero. This will eliminate the fastest transients following a tap change; hence it should reduce or eliminate any need to reduce the step size following tap changes. A difficulty with methods that eliminate the fast transients is knowing when it is not safe to ignore the transients.

2.7.5 Conclusions

This section has considered the possibility of speeding up ETMSP by using alternate integration algorithms. It appears that if one uses a fixed step size code, then methods such as the theta method may be somewhat faster than the trapezoidal rule in ETMSP. The step size experiments done here and in Dembart et al. (1977) indicate that a variable step size code of some form would probably be beneficial on many problems. In the first few seconds of a simulation, it appears that a variable step size version of the trapezoidal rule is probably the best algorithm. After the first few seconds of a simulation, i.e., after most of the discontinuities are past, the use of the BDFs would probably be more efficient than the trapezoidal rule. Immediately after tap changes, however, one should probably switch back to the trapezoidal

rule for a few time steps. The frequency of tap changes and the need to follow the transients excited by these events will limit the maximum possible speedup in the region where tap changes occur.

The preceding results have assumed that the same step size and integration algorithm are applied to all equations in the problem. An alternative is to partition the equations and use different integration formulas and/or step sizes for the devices in each partition. General partitioning algorithms were considered in Section 2.6. Zhu and Bose (1992) found that partitioning the devices, based on their coherent characteristics, and using different time steps for each partition yielded a factor-of-five increase in the performance of a transient stability code. A detailed examination of the step size data obtained for the test problems considered in this section showed that the smaller step sizes are typically caused by controlling the errors in no more than a few dozen variables during the first few seconds of the integration and about 100 to 200 variables after a tap change (out of several thousand). This indicates that using different step sizes on different sets of equations could significantly improve the performance of ETMSP. This would be above and beyond any performance increase allowed by a variable step size algorithm. Partitioning algorithms, however, are more complicated to implement than algorithms that treat all equations the same.

Using the coherent characteristics of the devices is one way of partitioning the system (Zhu and Bose 1992). Another way to partition the system is to determine the largest step size that can be used for all equations associated with a given bus. The devices at buses allowing similar step sizes could then be integrated with the same step size. The equations that can use the largest step sizes will typically be stiff and will have limited numbers of discontinuities. Thus, the BDFs would probably work well on these equations in all regions. The equations requiring the smallest step sizes, however, will tend to have most of the discontinuities and fast

transients. Thus, the methods considered in this section, e.g., the trapezoidal rule in region one and the BDFs for at least part of regions two and three, are probably best for use on these equations.

The next steps in evaluating improved algorithms in ETMSP appear to be 1) developing of a realistic set of error tolerances for the various types of equations in ETMSP, 2) developing of an algorithm for automatically changing the step size in the trapezoidal rule, and 3) doing some experiments with a variable step size version of the trapezoidal rule in ETMSP. Development of partitioning algorithms and the implementation of the BDFs for use after the first few seconds of the simulation should also be done.

2.8 SUMMARY

Overall, ETMSP appears to be a fairly well written code. The developers of the code, however, say that almost all of the time has been spent developing and implementing the various models in the program. Very little effort has been spent improving the performance of the code. The results of Sections 2.1 through 2.7 indicate that improving the integration portion of ETMSP could significantly speed up ETMSP on many problems.

It appears that the efficiency and robustness of ETMSP can be improved moderately by making some changes to the algorithms currently in ETMSP. The biggest change is to reduce the cost of tap changes by using a technique like partial refactorization or compensation, rather than the current method of full refactorization.

A moderate amount of work has been done on longer-term stability problems. Two techniques described in Section 2.3.2 that may be useful in ETMSP for voltage stability problems are 1) artificial damping of oscillations once the transient phase of the computation is past, and 2) partitioning or localization algorithms that treat the most disturbed part of the system differently from the less disturbed parts of the system.

The benefits of running ETMSP on computers such as super-workstations and parallel and vector supercomputers was considered. The results of this analysis indicate that ETMSP would probably run 5 to 10 times faster on a 40 MFLOPS super-workstation than on 0.4 MFLOPS workstations like those used at Bonneville. Benchmark problems would have to be run, however, to confirm this. The use of these machines would probably require little or no modification of ETMSP. The use of vector supercomputers would probably require significant changes to ETMSP before they could perform any better than super-workstations. Furthermore, the time required to develop a good vector computer version of ETMSP would probably be better spent working on improved integration algorithms that would speed up ETMSP on all computers. Finally, the present literature on the parallel solution of power system stability problems suggests that currently available parallel computers and algorithms might run ETMSP as much as two to three times faster than a super-workstation but at a higher cost. Thus, running ETMSP on a super-workstation appears to be the best hardware option in the near future. Experimenting with a parallel version of ETMSP on a small cluster of workstations may also be beneficial in the near term. Obtaining useful benefits from larger scale parallelism appears to be a longer term research topic. Parallel computing, however, is advancing rapidly and work should continue to increase the performance of parallel power system algorithms.

Experiments with ETMSP and results with codes like EUROSTAG indicate that variable step size algorithms would probably work well on many problems. During the initial transient phase of simulations, it appears that the trapezoidal rule is probably the best overall integration algorithm for this problem. In the remaining part of the simulation, however, the BDFs will probably work better than the trapezoidal rule.

The next step in evaluating improved algorithms in ETMSP appears to be the development of a variable step size implementation of the trapezoidal rule. This code should then be used to evaluate 1) the impact of variable

limits and tap changes on variable step size codes, and 2) the possibility of using partitioning algorithms to integrate different devices with different step sizes. Finally, the BDFs and partitioning algorithms should be experimented with in ETMSP.

Finally, the numerical analysis community generally recommends the use of double precision (64-bit arithmetic) when solving ordinary differential equations. This is probably most important with algorithms that use finite differences to approximate derivatives. Also, Stott (1979) says that his experience has been that 32-bit precision was inadequate for large problems. Thus, a double precision version of ETMSP would be useful for checking the results of the single precision code. Also, a double precision version of ETMSP may be necessary for a variable step size version of the trapezoidal rule or the BDFs to work well but this can only be determined experimentally.

3.0 EIGENANALYSIS OF LARGE POWER SYSTEMS

The Small Signal Stability Program (SSSP) package (Kundur, Rogers, and Wong 1988; Rogers and Kundur 1990) consists of two eigenvalue programs. These programs work with the linearized versions of the equations governing a power system. The Multi-Area Small Signal (MASS) stability program is designed to calculate all of the eigenvalues of power systems with up to about 500 states, while the Program for Eigenvalue Analysis of Large Systems (PEALS) is designed to calculate the eigenvalues of very large power systems. MASS forms the state matrix and computes the eigenvalues and right eigenvectors of this dense matrix using the QR algorithm in EISPACK (Smith et al. 1976). The PEALS program was designed to compute limited numbers of eigenvalues of systems that are too large to be analyzed using MASS. PEALS computes eigenvalues using either the modified AESOPS algorithm (Wong et al. 1988) or the iterative Arnoldi algorithm (Wang and Semlyen 1989). The algorithms in PEALS use the sparse matrices obtained by linearizing Equations (2.1) and (2.2), rather than forming the state matrix. Thus, PEALS uses sparse matrix techniques and can handle much larger systems than MASS can handle.

MASS and PEALS can do frequency response computations and compute poles and zeros of transfer functions. The main difference between MASS and PEALS is that MASS can compute all of the eigenvalues, eigenvectors, poles, zeros, etc., of a problem, while PEALS can only compute limited numbers of these quantities. Thus, MASS is more general purpose, but PEALS can handle larger systems. More detailed descriptions of the SSSP package can be found in Rogers and Kundur (1990) and the draft application guide for SSSP. The rest of this section assumes the reader is generally familiar with eigenanalysis of power systems. More details on this subject can be found in Rogers and Kundur (1990) and Elwood (1991).

PNL modified Version 2.0 of MASS to run on a Cray (Elwood 1991). The Cray used for this work limited any given job to 16 megawords of memory. This

limited the problems that could be solved by MASS on this Cray to those with no more than about 1,900 states. By eliminating the frequency response subroutines, problems with up to 2,200 states could be solved on this Cray.

Since the work done in Elwood (1991), a new version of MASS has been released. Bonneville is interested in the ability to run the newest versions of MASS as they become available. Thus, Bonneville wanted to establish guidelines for reducing the effort required to port modified versions of MASS to different computers. Bonneville also wanted to examine the options for increasing the capabilities of the Cray version of MASS to at least 3,000 states and examine ways to speed up MASS on large problems. MASS computes the eigenvalues and eigenvectors of large, nonsymmetric matrices. This computation can be ill-conditioned, i.e., small errors may produce large changes in the computed result. Thus, Bonneville is also interested in ways of validating the results produced by MASS. Version 3.0 of MASS was the code of interest for this work.

Section 3.1 discusses those aspects of MASS that cause difficulties when porting the code to different computers. Section 3.2 discusses ways to increase the size of problem that can be solved by the Cray version of MASS. Section 3.3 examines ways to speed up MASS. Section 3.4 describes ways to increase the versatility of MASS, e.g., by allowing the computation of error estimates. Section 3.5 describes some work done using internal PNL research funds on a parallel version of the QR algorithm. Section 3.6 describes some recent progress in sparse eigenanalysis that is applicable to PEALS. Finally, Section 3.7 is a summary of the results from Sections 3.1 to 3.6.

3.1 IMPROVING THE PORTABILITY OF MASS

The coding in MASS and ETMSP are very similar. In fact, many of the subroutines in the two codes are essentially the same. Thus, the general comments in Section 2.4.2 about the portability of ETMSP also apply to MASS.

Most modern computers and compilers support numerous useful extensions to the FORTRAN 77 standard. This has allowed MASS and ETMSP to be successfully compiled and run on a wide variety of machines with minimal changes. The fact that these codes use non-standard FORTRAN, however, means that it will be difficult to port them to some machines.

Elwood (1991) describes the changes that had to be made to Version 2.0 of MASS to get it to run on a Cray. The most significant changes to the VAX version of MASS were as follows:

- INTEGER*2 and INTEGER*4 statements were changed to INTEGER statements.
- Equivalencing of character variables to numeric variables was eliminated.
- Mixing of character and numeric data in common blocks was eliminated.
- Statements of the form "STOP 'long character string'" were replaced by the pair of statements "WRITE (*, *) 'long character string'" and "STOP".

All of these changes were necessary because MASS uses non-standard features of FORTRAN 77.

Eliminating the use of INTEGER*2 variables was the only change to MASS that was difficult. The Cray automatically treats INTEGER*2 variables as INTEGER variables. Thus, if MASS used INTEGER*2 variables in such a way that eliminating INTEGER*2 variables only required changing their type declarations, then porting MASS to a Cray would be easy. This, however, is not the case. In particular, the equivalencing of INTEGER*2 data types to other data types caused problems. An example of this is given by the section of FORTRAN code:

```
COMMON / WORK / J1(300), J2(600)
INTEGER*2 I1(600), I2(1200)
EQUIVALENCE (I1(1), J1(1)), (I2(1), J2(1))
```

The INTEGER*2 statement in this code cannot simply be changed to an INTEGER statement, as this would cause array I1 to overlap array I2. In this situation, the dimension of J1 must be increased to 600 before the INTEGER*2 statement can be changed to an INTEGER statement. MASS makes extensive use of statements similar to those in the example above. This requires that the EQUIVALENCE statements in MASS be analyzed to determine where adjustments of this type must be made.

During this project, a program was written that can scan a FORTRAN program and determine how much memory is required by all of the arrays in the code. Using this program it was found that the arrays in the 12,000-bus, 800-state version of MASS require about 16.7 megabytes of memory. This program also indicates that these arrays would require about 18.6 megabytes of memory if all INTEGER*2 variables are converted to type INTEGER. This 18.6 megabytes does not account for the fact that this conversion changes how EQUIVALENCE statements cause a few arrays to overlap. If this change in overlap structure is taken into account it appears likely that the use of INTEGER*2 variables in MASS probably saves no more than 3 to 4 megabytes of memory. Part of this 3 to 4 megabytes could probably be saved if INTEGER*2 variables were used but only equivalenced to other INTEGER*2 variables. Furthermore, the amount of memory available on most modern computers is approaching a point where the memory saved in MASS by using INTEGER*2 variables is not critical. It is unlikely that non-standard data types will be removed from MASS anytime soon. In future software developed work, however, it is preferable to use only standard FORTRAN. Furthermore, if non-standard features must be used in a program which is to be highly portable, they should be well documented and used in such a way that it is as easy as possible to remove them.

A new compiler was installed on the Hanford Cray after the work in Elwood (1991) was completed. This new compiler supports most of the FORTRAN extensions that had to be eliminated from MASS when using the old compiler. The use of INTEGER*2 variables, however, is still not supported by the Cray

using the new compiler. Thus, the difficult part of porting MASS to a Cray is still present.

3.2 INCREASING THE PROBLEM SIZE IN MASS

PNL, under a previous contract with Bonneville, modified Version 2.0 of MASS to run on a Cray (Elwood 1991). The machine used for these simulations was a Cray X-MP EA/232. Crays are physical memory machines, hence they can only solve problems that actually fit in memory. Version 2.0 of MASS requires storage for four NSI-by-NSI matrices, where NSI is a parameter in MASS that specifies the maximum number of states allowed in a simulation. The Cray used for this work has 32 megawords of memory, of which only 16 can be used by any given job. This means that the biggest problem that can be solved on this machine by MASS is one with about 1,900 states. By eliminating the frequency response subroutines in MASS, the storage for one NSI-by-NSI matrix was eliminated. This allowed problems with about 2,200 states to be solved on this Cray.

Version 3.0 of MASS also requires storage for four NSI-by-NSI matrices. In this section we look at ways to allow a Cray implementation of Version 3.0 of MASS to solve problems with at least 3,000 states. Methods of doing this, however, should not reduce the functionality of the code (such as eliminating the ability to do frequency response computations).

The easiest way to solve bigger problems with MASS on a Cray is to use a machine with more memory. PNL has access to Crays at the Los Alamos National Laboratory that have 64 megawords of memory each. These machines allow jobs to be run using 30 to 40 megawords of memory. Thus, a Cray implementation of Version 3.0 of MASS could solve problems with about 3,000 states on one of these machines. Solving larger problems requires reducing the memory requirements of MASS. The charges for running a Cray job are usually based on several factors, including CPU time and total memory used. Thus, it would

still be useful to reduce the memory requirements of MASS, even if solving problems with 3,000 states is all that is required.

Reducing the memory requirements of MASS when the number of states is large requires eliminating the use of a few of the NSI-by-NSI arrays currently used in MASS. This required examining MASS to see which subroutines in MASS used these NSI-by-NSI arrays, and seeing if any of the arrays can be eliminated without reducing the functionality of MASS. Ideally, one could do a global search of all the include files and subroutines in MASS to see where the parameter NSI is used. In various places, however, MASS splits variable names across lines. Thus one cannot be certain that such a pattern search would find all of the arrays that are dimensioned using the parameter NSI. To find all of the NSI parameters, a program, SCANNER, was written.

The program, SCANNER, scans a FORTRAN program and determines how much local memory is required by each subroutine, and how much global memory is required by each common block. This program takes into account savings resulting from EQUIVALENCE statements. SCANNER only accounts for the memory required by variables appearing in declaration statements, e.g, type declarations, dimension statements, common statements, etc. Thus, the program accounts for the memory requirements of all arrays. The memory requirements of some scalars, however, may be neglected. Most of the memory used by a program, however, is usually used by arrays. Thus, neglecting the memory required by some scalars is not a problem. Program SCANNER also provides a list of all subroutines with array declarations where the number of array elements depends upon the parameter NSI. This makes it easy to determine which subroutines use arrays that require a lot of memory when NSI is large.

Program SCANNER was used to determine how much of the memory required by Version 3.0 of MASS was the result of having four NSI-by-NSI arrays. There are two main parameters in MASS. NB is the maximum number of allowed buses and NSI is the maximum number of allowed states. If $NB = 12,000$ and $NSI = 800$, then the arrays in MASS require about 16.7 megabytes of memory.

These values of NB and NSI are typical upper bounds for these parameters on most computers. A value of 12,000 for NB is needed for some problems in the eastern United States. If NSI is reduced to 100, then MASS requires about 14.7 megabytes of memory. Thus, when NB is large, the use of four NSI-by-NSI arrays only contributes modestly to the memory requirements of MASS. If NB = 6000 and NSI = 800, then MASS requires about 15.1 megabytes of memory. This value of NB is more reasonable for most of the problems in the western United States. If NSI is reduced to 100, then MASS only requires about 10.9 megabytes of memory. Thus, when NB is moderately large, the use of four NSI-by-NSI arrays significantly increases the memory required by MASS. A total memory requirement of 15.1 megabytes, however, is not a problem on most modern computers.

These results indicate that the use of four NSI-by-NSI arrays is not a significant problem on most machines, where NSI is typically no larger than 500 to 800. It is only on machines like the Cray, where much larger values of NSI are practical, that the use of all of these arrays causes excessive memory requirements. It is the use of equivalence statements that minimizes the impact of using four NSI-by-NSI arrays in MASS when NB is moderate to large in size.

If one only wants MASS to compute eigenvalues, or poles or zeros, then only one NSI-by-NSI array is needed. If eigenvectors are required, however, then one must either use two arrays of dimension NSI-by-NSI or use one array of dimension NSI-by-NSI and do a lot of I/O. This I/O would reduce the efficiency of MASS and would require extensive changes to MASS. In general, eigenvectors provide a lot of useful information about the system and are usually computed by MASS. Thus, the most reasonable goal in reducing the memory requirements of MASS is to eliminate the use of two of the NSI-by-NSI arrays currently used by the code. This would allow problems with about 2,800 states to be solved using the Hanford Cray X-MP EA/232 and problems with about 4,000 states to be solved on the Los Alamos Crays.

Program SCANNER was used to examine Version 3.0 of MASS. It was found that the include files cnamat.ins, cneigv.ins, cnejgv.ins, and cnoap.ins contain common blocks with arrays of dimension NSI-by-NSI. Include file cnfr4.ins contains a common block with an array with $NSI^2/10$ elements. An array with $NSI^2/10$ elements is negligible relative to the NSI-by-NSI arrays. Hence there is no point in trying to eliminate the array in cnfr4.ins. Include file cnamat.ins contains the array A, file cneigv.ins contains the array VECR, file cnejgv.ins contains the array VECI, and file cnoap.ins contains the array LVECT. File cnoap.ins also declares the array LPART to be NSI-by-NSI, and equivalences this array to LVECT. File cnoap.ins is only used in subroutines that use file cnejgv.ins. Thus, LPART is always equivalenced to array VECI in cnejgv.ins.

Using SCANNER it was found that the include files cnamat.ins and cneigv.ins were used by many subroutines; file cnoap.ins is used by only two subroutines; and file cnejgv.ins is used by a moderate number of subroutines. Furthermore, several subroutines locally declare the array CBRES to have NSI^2 elements, while others declare array PART to have NSI^2 elements. These arrays, however, are always equivalenced to array A in cnamat.ins. There are also several subroutines that declare local arrays to have NSI^2 elements. These arrays, however, are actually dummy arguments to these subroutines, hence they do not need to be considered because they must have been explicitly declared in the calling routine. Finally, subroutine EIGS declares array ATEMP to be NSI-by-NSI. This array, however, is stored in a common block such that it is equivalent to array VECI in cnejgv.ins. Thus, it appears that it would be easiest to try eliminating the use of arrays VECI (or equivalently LPART) and LVECT in MASS.

Subroutines ANALYS and PRINTA are the only subroutines that use the include file cnoap.ins. Subroutines EIGENP, COMPVE, ESCALE, HESQR, ANALS, PRINTA, INVERT, GAUS, AEIGEN, RZG, FRESUL, and EIGS are the only subroutines using the include file cnejgv.ins. In the following, it is shown that the use

of arrays VECI and LVECT can be eliminated from MASS. This does not require eliminating any of the functionality of MASS and should not noticeably reduce the efficiency of MASS.

MASS currently computes eigenvalues using the QR algorithm in EISPACK. Subroutines EIGENP, COMPVE, ESCALE, and HESQR are a set of subroutines which can be used in place of the EISPACK routines, but are seldom if ever used. Thus, eliminating subroutines EIGENP, COMPVE, ESCALE, and HESQR from MASS would not reduce the functionality of MASS.

Subroutines ANALYS and PRINTA are for interactive analysis of the results computed by MASS. Subroutine ANALYS sorts the entries of each eigenvector and participation vector from the largest value to the smallest. Participation vectors are derived from the left and right eigenvectors and are defined in Rogers and Kundur (1990). The user may then request that the first K, where K is usually quite small, elements of one or more of these sorted vectors be printed. MASS, prior to entering the interactive portion of ANALYS, sorts all the elements of all the right eigenvectors and participation vectors. The sort key for the participation vectors is stored in LPART, while the sort key for the right eigenvectors is stored in LVECT. Actually, each element of array LVECT contains two integers. This is done by equivalencing two INTEGER*2 variables to an INTEGER variable. One set of integers in LVECT is the sort key when the elements of the right eigenvectors are sorted by magnitude. The other set of integers is the sort key when these vectors are sorted based on the real part of the eigenvectors. Storing these keys is essentially the only use made of arrays LVECT and LPART in these subroutines.

There are two ways to eliminate the use of arrays LVECT and LPART in subroutines ANALYS and PRINTA. First, simply sort a vector when the user requests that it be printed. This would only require a few arrays of dimension NSI. The disadvantage of this method is that there would be a slight delay while the program sorts the vectors. On most computers, however, this delay should be minimal. Furthermore, in the current code one has to

wait for MASS to sort all of the eigenvectors and participation vectors when entering subroutine ANALYS. This is inefficient on large problems where the user may only be interested in a few of the vectors. The second method of eliminating these large arrays is to sort all of the vectors but only store the parts of the sort key that point to the K largest elements of the vectors. On most problems K can probably be 50 to 100, or smaller. Thus, when NSI is greater than 1,000, the storage for the sort keys will be less than about $NSI^2/10$ array elements. This would essentially eliminate the use of the two NSI-by-NSI arrays LVECT and LPART (which is equivalent to VECI) in these subroutines. The first method of eliminating the use of arrays LVECT and LPART is probably the best.

Subroutines INVERT and GAUS take a matrix in array VECR and over-write it with its LU factorization. The inverse of the original matrix is then computed one column at a time and stored in VECI. The LINPACK routine SGEDI can do the same operations, but over-writes the LU factorization with the inverse of the matrix (Dongarra et al. 1979). Hence, would not require the array VECI.

Subroutine AEIGN uses arrays A, VECR, and VECI. If the LINPACK routine SGEGI is used in place of routines INVERT and GAUS, then the main purpose of array VECI is to allow the left eigenvectors, right eigenvectors, and participation vectors to be held in memory at the same time. The only thing really done with these arrays, however, is to print them out in a particular order. The use of VECI could be eliminated by 1) computing and storing the left and right eigenvectors in A and VECR, 2) writing the left eigenvectors to disk, 3) computing the participation vectors and storing them over the left eigenvectors, 4) doing operations with the participation vectors, including writing them to the main output file, 5) writing the right eigenvectors to the main output file, and 6) reading in the left eigenvectors and writing them to the main output file. This modification would allow MASS to do the same things it currently does but eliminates the need for VECI. Furthermore, the

modified code would only require one extra write/read of an NSI-by-NSI matrix. The cost of this is negligible compared to the cost of computing the eigenvalues and eigenvectors.

Subroutine FRESUL only uses one column of array VECI. Thus, VECI can be replaced by an array of length NSI in this subroutine.

Subroutine RZG uses array VECI to compute and store the left eigenvectors. These are then used to compute participation vectors. Finally some of the left eigenvectors in VECI are printed. This is the only use of VECI. VECI could be eliminated by 1) computing and storing the left eigenvectors in array PART (which is equivalenced to array A in cnamat.ins), 2) writing to disk that part of PART which will eventually be printed to an output file, 3) having the participation vectors over-write the left eigenvectors as they are computed, and 4) copying the left eigenvectors temporarily stored on disk to the output file. This algorithm requires more I/O than the current code but eliminates the need for array VECI. Furthermore, the additional I/O is insignificant compared to the other computations.

Subroutine EIGS uses array ATEMP, which is essentially equivalenced to array VECI in file cnejgv.ins. This subroutine 1) stores a copy of array A in ATEMP, 2) does some computations that use ATEMP to modify A, 3) computes the eigenvalues and right eigenvectors of A, which destroys the contents of A, and 4) restores A from ATEMP. The right eigenvectors are stored in VECR. Thus, one could use VECR in place of ATEMP in steps (1) and (2) above, write the contents of VECR to disk, proceed with step (3), and restore A from disk. This algorithm requires more I/O than the current code but eliminates the need for array VECI. Furthermore, the additional I/O is insignificant compared to the other computations.

The preceding analysis of Version 3.0 of MASS indicates that the described changes would allow MASS to use only two NSI-by-NSI arrays, rather than the four arrays currently used. These changes would 1) be fairly easy to

do, 2) retain the full functionality of the current version of MASS, and 3) have a negligible impact on the overall speed of MASS. Furthermore, the changes would allow problems with about 2,800 states to be solved using the Hanford Cray X-MP EA/232 and problems with about 4,000 states to be solved on the Los Alamos Crays. Finally, these changes would moderately reduce the memory requirements of MASS on conventional computers when NB is of moderate size (e.g., around 6,000) and NSI is around 500 to 800.

3.3 SPEEDING UP MASS

Many modern computers have memory hierarchies where some levels of memory are much faster than others, e.g., vector registers on Crays, caches on many machines, main memory, etc. Obtaining peak performance on these machines requires making efficient use of the fastest levels of memory. Traditional algorithms are based on operations between vectors, e.g., adding one vector to another. These operations typically require order (n) arithmetic and order (n) data movement, where n is the length of the vector. On many machines these algorithms work well. The high ratio of memory traffic to arithmetic, however, limits the performance of many computers. Algorithms using matrix-matrix operations, e.g., multiplication of two matrices, can often do order (n^3) arithmetic with only order (n^2) memory traffic.

Efforts to improve the performance of numerical linear algebra computations have led to the development of block algorithms that make use of matrix-matrix operations. These algorithms are built around a set of basic linear algebra subprograms (BLAS). The level 1 BLAS, level 2 BLAS, and level 3 BLAS define a set of standard vector-vector, matrix-vector, and matrix-matrix operations, respectively. A basic set of FORTRAN BLAS is available, and algorithms based on the BLAS are highly portable. Furthermore, the BLAS have been coded in assembly language by many computer manufactures. This provides the speed advantage of assembly language coding on many machines,

without sacrificing portability. A more detailed description of the BLAS and examples of block algorithms can be found in Dongarra et al. (1991).

The work on block algorithms has resulted in a new software package, LAPACK, which supersedes LINPACK and EISPACK. On some machines, some of the codes in LAPACK run several times faster than the corresponding codes in LINPACK and EISPACK. Furthermore, the codes in LAPACK tend to offer more options and be more robust and accurate than the algorithms in LINPACK and EISPACK. A detailed description of LAPACK is given in Anderson et al. (1992) and the references therein.

The current version of MASS computes eigenvalues using the QR algorithm in EISPACK (Smith et al. 1976). A detailed description of this algorithm can be found in Golub and Van Loan (1983). The eigenvalue routines in LAPACK were tested to see if they could increase the speed and reliability of MASS. The results of this work are described below.

Computing the eigenvalues and eigenvectors of a matrix, A , using the QR algorithm requires several steps: 1) reduce A to upper Hessenberg form, i.e., $a_{ij} = 0$ for $i > j + 1$, 2) use a sequence of orthogonal similarity transformations to reduce the upper Hessenberg matrix to upper triangular form, accumulating the transformations along the way, and 3) extract the eigenvectors of the upper triangular matrix and transform them to eigenvectors of the original matrix using the accumulated set of transformations. EISPACK performs step (3) only for right eigenvectors. MASS then computes the left eigenvectors by inverting the matrix of right eigenvectors. LAPACK, however, can perform step (3) for both right and left eigenvectors. The preceding can be summarized as 1) reduce to upper Hessenberg form, 2) compute eigenvalues, 3) compute right eigenvectors, and 4) compute left eigenvectors. These operations represent almost all of the CPU time in MASS on moderate to large problems.

Some driver programs were written to generate a set of random matrices and then use either EISPACK or LAPACK to compute the eigenvalues and

eigenvectors of these matrices. The elements of these matrices were distributed Normal(0, 1), Uniform(0, 1), or Uniform(-1, 1). LAPACK has a number of block parameters that can be adjusted on different machines to improve the performance of the code. A set of standard parameters that work well on many machines are supplied with the code.

The LAPACK/EISPACK test programs were run on several different computers using each probability distribution on problems of dimension 100 to 500. The purpose of this was to determine if LAPACK is consistently faster than EISPACK when both codes are run on a variety of different computers. The default set of block parameters were used on each computer. It was found that the different probability distributions gave similar results. Furthermore, the performance of the current algorithms in MASS is adequate for small problems. Thus, only results for the 400-by-400 problem using the Normal(0,1) distribution are discussed below.

Table 3.1 lists the results of using LAPACK to compute all of the eigenvalues and eigenvectors of a 400-by-400 matrix on several different computers. The computers were a Cray X-MP EA/232, a VAX 6000-420, one node of an Intel iPSC/860 hypercube, and a SUN Sparcstation 2. These computers were used because they were readily accessible. The Cray results are for single precision (64-bit) arithmetic, the SUN and Intel results are for double-precision arithmetic (64-bit), and the VAX results are for single-precision arithmetic (32-bit). "Reduce" is the time required to reduce a matrix to upper Hessenberg form and accumulate the transformations used to do this. "Compute eigenvalues" is the time required to reduce the matrix to upper triangular form, accumulate the transformations used to do this, and extract the eigenvalues. "Compute R.E.V." is the time required to compute the right eigenvectors. "Compute L.E.V." is the time required to compute the left eigenvectors. Finally, the FORTRAN BLAS were used on all machines except for the Cray, which used the assembly language BLAS in the Cray scientific library.

TABLE 3.1. LAPACK on Various Computers

<u>Operation</u>	<u>Time (seconds)</u>			
	<u>Cray</u>	<u>i860</u>	<u>SUN</u>	<u>VAX</u>
Reduce	2.21	47.72	90.03	179.51
Compute Eigenvalues	10.06	168.14	254.39	367.88
Compute R.E.V.	1.29	15.36	30.19	55.08
Compute L.E.V.	<u>1.47</u>	<u>14.86</u>	<u>27.17</u>	<u>54.40</u>
Total	15.10	247.55	406.72	660.86

TABLE 3.2. EISPACK on Various Computers

<u>Operation</u>	<u>Time (seconds)</u>			
	<u>Cray</u>	<u>i860</u>	<u>SUN</u>	<u>VAX</u>
Reduce (ORTHES)	4.82	93.96	115.59	211.82
Compute Eigenvalues	9.40	231.08	273.44	397.44
Compute R.E.V.	1.76	38.15	22.99	91.00
Compute L.E.V.	<u>1.63</u>	<u>23.94</u>	<u>51.86</u>	<u>78.69</u>
Total	17.63	387.63	464.21	779.89
Reduce (ELMHES)	<u>1.47</u>	<u>62.64</u>	<u>49.21</u>	<u>123.20</u>
Total	14.28	356.31	397.83	691.27

Table 3.2 is similar to Table 3.1 but lists the times for the EISPACK test programs. A matrix can be reduced to upper Hessenberg form using either a sequence of orthogonal similarity transformations or a sequence of stabilized elementary similarity transformations (Wilkinson 1965). The orthogonal similarity transformations have better numerical properties, but usually take longer than the stabilized elementary similarity transformations. LAPACK only implements the orthogonal transformations, while EISPACK implements both types of transformations. Thus, Table 3.2 lists two times for the reduction to upper-Hessenberg form. "Reduce (ORTHES)" is the time required when using the orthogonal transformations, while "Reduce (ELMHES)" is

the time required when using the stabilized elementary transformations. The second total in Table 3.2 is the total time required to run a test problem if ELMHES is used instead of ORTHES. MASS currently uses ELMHES.

Comparing the results in Tables 3.1 and 3.2 shows that, if the orthogonal transformations are used in EISPACK, then LAPACK is 10 to 30% faster than EISPACK on all of the machines. The biggest difference being on the iPSC/860, which has an 8K data cache. Furthermore, these tables show that LAPACK does most of the operations significantly faster than EISPACK on almost all of the machines. Tables 3.1 and 3.2 indicate that the factor limiting the speedup obtainable using LAPACK is the actual computation of the eigenvalues. I talked to the developers of LAPACK and they said that the speedups obtained in this part of the computation have generally been disappointing, and that the results in Tables 3.1 and 3.2 are not unusual. Finally, the data in Tables 3.1 and 3.2 show that LAPACK runs significantly faster than the ELMHES version of EISPACK only on the Intel iPSC/860. On the other machines LAPACK runs only moderately faster or negligibly slower than the ELMHES version of EISPACK.

Tables 3.3 and 3.4 are the same as Tables 3.1 and 3.2, except that here only the eigenvalues were computed. In this case the times listed do not include the time required to accumulate the various transformations. The relative performance of LAPACK and EISPACK in these tables is similar to the results in Tables 3.1 and 3.2.

Overall, Tables 3.1 to 3.4 show that on a variety of computers LAPACK is generally as fast or faster than EISPACK.

Table 3.5 lists the times for LAPACK and EISPACK to compute all of the eigenvalues and eigenvectors of a 1,000-by-1,000 matrix on a Cray X-MP EA/232. This table shows that using the assembly language BLAS on the Cray significantly speeds up the computation of everything but the actual eigenvalues. Furthermore, this table shows that LAPACK runs this problem about 20% faster than the ORTHES version of EISPACK, but only about 5% faster

TABLE 3.3. LAPACK (Eigenvalues Only) on Various Computers

<u>Operation</u>	<u>Time (seconds)</u>		
	<u>Cray</u>	<u>i860</u>	<u>SUN</u>
Reduce	1.51	34.10	66.18
Compute Eigenvalues	<u>4.70</u>	<u>63.24</u>	<u>88.39</u>
Total	6.23	97.71	154.98

TABLE 3.4. EISPACK (Eigenvalues Only) on Various Computers

<u>Operation</u>	<u>Time (seconds)</u>		
	<u>Cray</u>	<u>i860</u>	<u>SUN</u>
Reduce (ORTHES)	3.62	83.85	95.39
Compute Eigenvalues	<u>4.85</u>	<u>80.52</u>	<u>93.58</u>
Total	8.49	164.37	189.19
Reduce (ELMHES)	<u>1.46</u>	<u>62.45</u>	<u>48.96</u>
Total	6.33	142.97	142.76

TABLE 3.5. LAPACK/EISPACK on 1000 by 1000 Problem

<u>Operation</u>	<u>Time (seconds)</u>		
	<u>LAPACK</u>		<u>EISPACK</u>
	<u>FORTTRAN BLAS</u>	<u>Assembly BLAS</u>	
Reduce (ORTHES)	44.74	29.63	60.20
Compute Eigenvalues	129.64	127.66	126.77
Compute R.E.V.	17.66	12.76	19.53
Compute L.E.V.	<u>19.35</u>	<u>13.49</u>	<u>24.04</u>
Total	211.79	183.85	230.59
Reduce (ELMHES)	<u>n/a</u>	<u>n/a</u>	<u>23.21</u>
Total			193.60

than the ELMHES version of EISPACK. Table 3.6 lists the results of computing only the eigenvalues for the 1,000-by-1,000 matrix. In this case, LAPACK runs the problem about 30% faster than the ORTHES version of EISPACK and 10% faster than the ELMHES version of EISPACK.

The standard QR algorithm uses a double-shift strategy. The QR algorithm in LAPACK, however, uses a k-shift strategy, where k is usually a small, even integer. The value of k affects the time required to compute the eigenvalues but not the time required by the other operations listed in Tables 3.1 through 3.6.

The number of shifts used by the QR algorithm is the main parameter in LAPACK that can be adjusted to increase the performance of the eigenvalue computations. Thus, a 1,000-by-1,000 matrix was used on the Cray to examine how the time required by subroutine SHSEQR, the LAPACK routine that does the eigenvalue computations, varied as a function of the number of shifts used. Table 3.7 lists the timing data for subroutine SHSEQR as a function of NSHIFT the number of shifts used in the QR algorithm. The default value for NSHIFT in LAPACK is six. Table 3.7 shows that this default value gives fairly good results. The table also shows, however, that varying this parameter can modestly improve the performance of LAPACK.

TABLE 3.6. LAPACK/EISPACK (Eigenvalues Only) on 1000 by 1000 Problem

Operation	Time (seconds)		
	LAPACK		EISPACK
	FORTTRAN BLAS	Assembly BLAS	
Reduce (ORTHES)	31.11	20.38	47.65
Compute Eigenvalues	<u>54.44</u>	<u>51.15</u>	<u>60.14</u>
Total	85.79	71.76	107.83
Reduce (ELMHES)	<u>n/a</u>	<u>n/a</u>	<u>23.17</u>
Total			83.35

TABLE 3.7. SHSEQR versus Number of Shifts

<u>NSHIFT</u>	<u>Time (seconds)</u>
2	130.15
4	117.11
6	124.19
8	133.15

The experiments done in this section show that an untuned version of LAPACK that uses the FORTRAN BLAS runs 10 to 30% faster than the ORTHES version of EISPACK. On the cache-based Intel iPSC/860, this version of LAPACK also ran significantly faster than the ELMHES version of EISPACK. On other machines, however, LAPACK ran about the same speed as the ELMHES version of EISPACK. On the Cray using assembly language BLAS, LAPACK required 5 to 10% less time than the ELMHES version of EISPACK. Thus, on a variety of computer architectures LAPACK is generally as fast or faster than EISPACK.

MASS currently uses the ELMHES version of EISPACK. Thus, replacing EISPACK with the untuned version of LAPACK (with FORTRAN BLAS) would not reduce the portability of MASS and does not appear to significantly reduce the performance of MASS on most machines. Using LAPACK, however, would speed up MASS by as much as 30% on some machines. Tuning LAPACK to the machine and using assembly language BLAS, when available, can further improve the performance of MASS.

Finally, there is the question of whether a super-workstation or a vector supercomputer is the best type of computer on which to run MASS. The main computations in MASS involve dense linear algebra. Thus, MASS would probably run well on a vector supercomputer. In fact, Elwood (1991) shows that this is the case. Dongarra lists speeds of tens to a few hundred MFLOPS for a variety of vector supercomputers. This indicates that vector supercomputers will generally run MASS moderately to significantly faster than a 40 MFLOPS super-workstation. This leaves the question of when one should switch from a super-

workstation to a vector supercomputer. Table 3.1 shows that the Hanford Cray ran EISPACK about 27 times faster than a SUN Sparcstation 2. The SUN is a workstation which runs the LINPACK benchmark at 4.0 MFLOPS (Dongarra 1992). This suggests that the Hanford Cray would run MASS about 2 or 3 times faster than a 40 MFLOPS super-workstation. Furthermore, MASS took about 26 minutes to run a problem with 2,165 states on the Hanford Cray (Elwood 1991). This suggests that it would take about an hour for MASS to solve a 2,200 state problem on a 40 MFLOPS super-workstation. In many cases an hour would be an acceptable run time for a problem with 2,200 states; hence one could reasonably use a 40 MFLOPS super-workstation. For larger problems, or problems which must be solved faster than this, however, a vector supercomputer will probably be required. These results suggest that a super-workstation is probably a reasonable alternative to a vector supercomputer on many problems.

The results in this section show that the eigenvalue algorithms in LAPACK are about as fast or faster than the eigenvalue algorithms in MASS. Furthermore, LAPACK uses orthogonal similarity transformations while MASS uses stabilized elementary similarity transformations. The orthogonal transformations are numerically more stable than the elementary stabilized transformations. Thus, it is preferable to use the orthogonal transformations, especially on large problems like those solved on the Cray. Furthermore, LAPACK is a newer and generally more robust code than EISPACK. Thus, the main computational routines in MASS should be replaced by LAPACK routines. This would generally increase the speed and reliability of MASS. Finally, it appears that a 40 MFLOPS super-workstation could solve problems with up to 2,200 states in about an hour, while a vector supercomputer could solve a 2,200 state problem in less than 30 minutes. Thus, running MASS on a super-workstation is probably worth considering for many problems.

3.4 INCREASING THE VERSATILITY OF MASS

MASS uses the QR algorithm to compute the eigenvalues and eigenvectors of nonsymmetric matrices. The algorithms for the nonsymmetric eigenproblem compute the exact eigenvalues, eigenvectors, and invariant subspaces of slightly perturbed matrices $A + E$, where A is the matrix whose eigenvalues, etc., are required, $\|E\| \leq p(n)\epsilon$, n is the dimension of the matrix, p is a modestly growing function of n , and ϵ is the machine precision (Anderson et al. 1992). Thus, the accuracy of the results computed by MASS depend upon the sensitivity of the eigenvalues and the eigenvectors to perturbations in the state matrix.

It is possible for the nonsymmetric eigenproblem to be ill-conditioned, i.e., sensitive to small changes in the state matrix. Thus, it is useful to be able to compute the condition numbers of the eigenvalues and eigenvectors computed by MASS. Eigenvalues which are close together (and their associated eigenvectors) tend to be ill-conditioned. The mean of a cluster of eigenvalues, however, is usually less sensitive to perturbations than the values of the individual eigenvalues. Similarly, the invariant subspace associated with a cluster of eigenvalues is generally less sensitive to perturbations than the individual eigenvectors (Anderson et al. 1992). Thus, it is useful to be able to compute the mean of a cluster of eigenvalues, and the associated invariant subspace. LAPACK, but not EISPACK, has subroutines to compute condition numbers, the mean of a cluster of eigenvalues, and a basis for the invariant subspace associated with a cluster of eigenvalues.

The ability of LAPACK to compute condition numbers and invariant subspaces is a useful property. Thus, incorporating LAPACK into MASS would increase the versatility of MASS and make it easier to handle ill-conditioned problems.

3.5 PARALLEL QR ALGORITHM

Small signal stability is becoming more important in power system applications. PNL has used some of its internal research funds to work on a parallel version of the QR algorithm used in MASS. This section very briefly describes some preliminary results from PNL's work on this algorithm. A more detailed paper is currently being prepared for publication.

The results in Section 3.3 show that computing the eigenvalues of an upper Hessenberg matrix takes more time than the other computations required to compute the eigenvalues and eigenvectors of a general matrix. Furthermore, previous attempts to parallelize this part of eigenvalue computations have achieved limited success (Davis, Funderlic, and Geist 1987; Stewart 1987; Boley, Maier and Kim 1989; Geist and Davis 1990). Thus, a parallel algorithm was developed to compute the eigenvalues of an upper Hessenberg matrix and to accumulate the transformations required to compute the eigenvectors.

The main idea of the parallel algorithm is to divide the upper Hessenberg matrix into k-by-k blocks and assign several blocks to each processor. This assignment is done in such a way that most communications can be done between nearest neighbors in a ring of processors.

Table 3.8 lists some results obtained when the QR algorithm is applied to upper Hessenberg matrices of various sizes, N, using five processors of an Intel iPSC/860 hypercube computer. The speedup is the time required for the standard EISPACK code to run the problem on one processor of this machine divided by the time required by the parallel code. The efficiency is equal to the speedup divided by the number of processors used. Thus, an ideal parallel algorithm would have an efficiency near one.

The data in Table 3.8 show very good results. In fact, five processors can run large problems more than five times faster than one processor. This is an unusual result, and means that somehow the parallel code is using each processor more efficiently than the standard EISPACK code. It turns out that

TABLE 3.8. Parallel QR Algorithm

<u>N</u>	<u>Speedup</u>	<u>Efficiency</u>
100	1.72	0.35
150	2.74	0.55
200	3.88	0.78
250	4.41	0.88
300	5.40	1.08
350	5.84	1.17
400	6.10	1.22
450	6.65	1.33
500	6.42	1.28

the parallel code uses each processor more efficiently than the sequential code for three reasons:

- The i860 processor used in the Intel iPSC/860 has an 8K data cache.
- The sequential code operates on three rows/columns of the matrix at a time. This prevents the cache from being used effectively when the matrix is large.
- In the parallel code, each processor works on a relatively small block of the matrix and uses the cache efficiently.

These results indicate that modifying the EISPACK code to operate on relatively small sub-blocks of the matrix would significantly improve its performance on machines that have a cache. Thus, a sequential block version of the EISPACK code implementing the QR algorithm was developed.

Table 3.9 shows the speedup of the sequential, block code over the standard EISPACK code on one processor of the Intel iPSC/860. These two codes do exactly the same computations and yield identical results. The block code, however, simply reduces the amount of data movement. The results in Table 3.9 show that the block version of EISPACK achieves a higher speedup than LAPACK over the standard version of EISPACK. This result holds true on the Intel

.. iPSC/860. On a Cray X-MP EA/232 and SUN Sparcstation 2, however, the block version of EISPACK is no faster than the standard EISPACK code. These results suggest that the QR algorithm in LAPACK could be sped up on cache-based machines by using a block algorithm similar to the one used with EISPACK.

Finally, Table 3.10 repeats the data in Table 3.8 but now compares the parallel QR algorithm to the sequential block version of EISPACK. This table

TABLE 3.9. Block QR Algorithm

<u>N</u>	<u>Speedup</u>
100	1.18
150	1.33
200	1.48
250	1.57
300	1.64
350	1.67
400	1.70
450	1.70
500	1.71

TABLE 3.10. Parallel versus Block QR Algorithm

<u>N</u>	<u>Speedup</u>	<u>Efficiency</u>
100	1.46	0.29
150	2.05	0.41
200	2.62	0.53
250	2.80	0.56
300	3.29	0.66
350	3.49	0.70
400	3.59	0.72
450	3.90	0.78
500	3.74	0.75

shows that good speedups are possible with this parallel code when the dimension of the matrix is 50 to 100 times greater than the number of processors used. Similar results were obtained when using more processors on larger problems.

The possibility of using networks of workstations to do parallel computing was discussed in Section 2.5.4. Good parallel performance has been achieved when using small clusters of workstations to solve problems which have high computation to communications ratios (Beguelin et al. 1991; Smith 1991; Benzoni, Richelli, and Sunderam 1992). This suggests that, for problems with several thousand states, it may be possible to achieve a reasonable parallel speedup by running MASS on a small cluster of super-workstations. At the very least one can probably achieve a parallel speedup of about two for the actual eigenvalue computations by using one computer to reduce the upper Hessenberg matrix to upper triangular form and a second computer to accumulate the transformations. The parallel QR algorithm developed at PNL, or a variant of it, may be able to use more than two workstations efficiently. Experiments need to be done, however, to determine if the communications overhead on a cluster of workstations is small enough to allow a parallel QR algorithm to run efficiently. In Section 3.3 it was found that a single 40 MFLOPS super-workstation could probably run MASS on a problem with about 2,200 state in about an hour. Thus, if one can efficiently run MASS in parallel on several 40 MFLOPS super-workstations, then one could probably solve problems with significantly more than 2,200 states in about an hour and/or solve problems with about 2,200 states in a fraction of an hour.

Some computer manufacturers are starting to deliver what are essentially clusters of workstations which have a shared memory and can be used for parallel computing. These computers have a fairly low communications overhead. Thus, for large problems, the parallel QR algorithm developed at PNL would probably run fairly well on several processors of one of these machines. These shared memory workstations, however, are fairly expensive.

Thus, it would be preferable to use a network of super-workstations to run a parallel version of MASS, provided the communications overhead is not too large.

Many vector supercomputers have several processors and can be used to do parallel computing. If several processors on one of the faster vector supercomputers can be used efficiently in eigenvalue computations, then it would be difficult for a parallel computer to solve a problem faster than the vector supercomputer. This is because each processor on one of the faster vector supercomputers is typically many times faster than a single processor on the commonly available parallel supercomputers and the parallel QR algorithm developed at PNL works best with only a moderate number of processors. A variant of the parallel QR algorithm developed by PNL would probably run fairly efficiently on several processors of a vector supercomputer. These results suggest that a parallel version of MASS would run significantly faster on several processors of a vector supercomputer than either a sequential or a parallel version of MASS would run on most other types of computers. Furthermore, it is fairly easy to lease time for production work on vector supercomputers but not on other types of moderate to large scale parallel machines. In Elwood (1991) it was found that the Hanford Cray takes about 26 minutes to run MASS on a problem with 2165 states. Furthermore, the amount of work done by MASS increases as the cube of the number of states. This indicates that developing a version of MASS which could efficiently use several processors of a vector supercomputer may be useful for problems with more than about 2000 states.

The results of this section indicate that MASS can probably be run fastest by using several processors of a vector supercomputer. This, however, would require doing some work to develop a parallel version of the QR algorithm which can efficiently use several processors of a vector supercomputer. The parallel QR algorithm developed by PNL, or a variant of it, is a good place to start developing a parallel QR algorithm for a vector

supercomputer. It also appears that a parallel version of MASS may run fast enough on a cluster of a few super-workstations to make it practical to solve problems with several thousand states in a reasonable amount of time. Furthermore, vector supercomputers are often heavily utilized and the turn-around time for a job may be significantly longer than the actual CPU. Thus, a cluster of super-workstations may actually provide better turn-around times than a vector supercomputer. Finally, if large problems are solved frequently with MASS, then a small cluster of super-workstations would probably be cheaper, in the long run, than using a vector supercomputer.

3.6 SPARSE EIGENANALYSIS

Elwood (1991) examined the state of the art in sparse eigenanalysis of large power systems. In that report it was found that the Arnoldi algorithm used in PEALS (Wang and Semlyen 1989) is one of the best algorithms currently available for computing some of the eigenvalues of large, sparse, nonsymmetric matrices.

The Arnoldi algorithm in PEALS must occasionally be explicitly restarted. A recent paper has described an implicitly restarted Arnoldi algorithm (Sorensen 1992). This new algorithm appears to be more accurate and more robust than the explicitly restarted algorithm in PEALS. Thus, this new algorithm should be tested on power system problems. Sorensen has said that he is interested in collaborating on work to test his code on power system problems.

3.7 SUMMARY

MASS uses a number of extensions to standard FORTRAN 77. Most of these extensions, however, are supported by most modern compilers and MASS has been ported to a variety of computers with only small changes. There are some computers, e.g., the Cray, which do not support the INTEGER*2 data type. This causes a fair amount a difficulty when porting MASS to these machines. Thus,

it would be useful if MASS used INTEGER*2 variables in such a way that changing them to INTEGER variables only required changing their type declarations. In future software developed work, only standard FORTRAN should be used. If non-standard features of FORTRAN must be used in a program, then they should be well documented and used in such a way that it is as easy as possible to remove them.

The current version of MASS requires storage for four arrays of dimension NSI-by-NSI, where NSI is the maximum number of states allowed in a problem. Making simple modifications to MASS would allow two of these large arrays to be eliminated from the program. Eliminating these arrays would allow larger problems to be solved on Crays, and would generally reduce the memory requirements of MASS when the number of buses, NB, is only moderately large, e.g., less than about 6,000.

LAPACK is a new software package designed to replace EISPACK and LINPACK. It was found that the subroutines in LAPACK typically run as fast or faster than the EISPACK subroutines in MASS. Furthermore, the subroutines in LAPACK are more robust and accurate than the EISPACK routines in MASS. Finally, LAPACK contains subroutines for computing condition numbers, and invariant subspaces. Thus, replacing the EISPACK subroutines in MASS with LAPACK subroutines would increase the reliability, functionality and performance of MASS.

It appears that the fastest way to run MASS is by using several processors of a vector supercomputer. This would require developing a parallel version of MASS for a vector supercomputer. PNL has developed a parallel version of the QR algorithm, the main computational algorithm in MASS, and found that it runs well on an Intel iPSC/860 parallel computer. This parallel code, or a variant of it, could be used as a starting point to parallelize the main computations in MASS on a vector supercomputer. A cluster of a few super-workstations can probably run MASS on problems with several thousand states in a reasonable amount of time. Thus, it is probably

worthwhile to test a parallel version of the QR algorithm on a cluster of super-workstations.

Finally, a new version of the Arnoldi algorithm, one of the main algorithms in PEALS, has recently been developed. This new algorithm appears to be superior to the algorithm in PEALS and should be tested on power system problems.

4.0 REFERENCES

- Addison, C. A. 1984. "A Comparison of Several Formulas on Lightly Damped, Oscillatory Problems." SIAM J. Sci. Stat. Comput. 5:920-936.
- Aiken, R. C., ed. 1985. Stiff Computation. Oxford University Press, New York.
- Alsac, O., B. Stott, and W. F. Tinney. 1983. "Sparsity-Oriented Compensation Methods for Modified Network Solutions." IEEE Trans. Pow. App. Sys. PAS-102:1050-1060.
- Alvarado, F. L. 1979. "Parallel Solution of Transient Problems by Trapezoidal Integration." IEEE Trans. Pow. App. Sys. PAS-98:1080-1090.
- Alvarado, F. L., R. H. Lasseter, and J. J. Sanchez. 1983. "Testing of Trapezoidal Integration with Damping for the Solution of Power Transient Problems." IEEE Trans. Pow. App. Sys. PAS-102:3783-3790.
- Alvarado, F. L., W. F. Tinney, and M. K. Enns. 1992. "Sparsity in Large-Scale Network Computations." In Advances in Electric Power and Energy Conversion System Dynamics and Control, ed. C. T. Leondes. Academic Press.
- Alvarado, F. L., D. C. Yu, and R. Betancourt. 1990. "Partitioned Sparse A¹ Methods." IEEE Trans. Pow. Sys. 5:452-459.
- Anderson, D. M. and B. F. Wollenberg. 1992. "Power System Steady State Security Analysis Using Vector Processing Computers." Paper 92 WM 286-5 PWRs, presented at the IEEE/PES 1992 Winter meeting, January 26-30, 1992, New York.
- Anderson, E., Z. Bai, C. Bischof, J. Demmel, J. Dongarra, J. Du Croz, A. Greenbaum, S. Hammarling, A. McKenney, S. Ostrouchov, and D. Sorensen. 1992. LAPACK Users' Guide. Society for Industrial and Applied Mathematics, Philadelphia.
- Anderson, P. M., and B. Dembart. 1980. "Computational Aspects of Transient Stability Analysis." In Electric Power Problems: The Mathematical Challenge, eds. A. M. Erisman, K. W. Neves, and M. H. Dwarakanath, pp. 159-189. Society for Industrial and Applied Mathematics, Philadelphia.
- Arrillaga, J., and C. P. Arnold. 1990. Computer Analysis of Power Systems. John Wiley & Sons, New York.
- Ashcraft, C. C., R. G. Grimes, J. G. Lewis, B. W. Peyton, and H. D. Simon. 1987. "Progress in Sparse Matrix Methods for Large Linear Systems on Vector Supercomputers." Inter. J. Supercomputer Appl. 1:10-30.

Barry, D. E., C. Pottle, and K. A. Wirgau. 1978. Technology Assessment Study of Near Term Computer Capabilities and Their Impact on Power Flow and Stability Simulation Programs. Final Report. EPRI EL-946, Electric Power Research Institute, Palo Alto, California.

Beguelin, A., J. Dongarra, A. Geist, R. Manchek, and V. Sunderam. 1991. "Opening the Door to Heterogeneous Network Supercomputing." Supercomputing Rev. September, pp. 44-45.

Bennett, J. M. 1965. "Triangular Factors of Modified Matrices." Numer. Math. 7:216-221.

Benzoni, A., G. Richelli, and V. S. Sunderam. 1992. "Concurrent LU Factorization on Workstation Networks" In Parallel Computing '91, eds. D. J. Evans, G. R. Joubert, and H. Liddell, pp. 159-166. Elsevier Science Publishers.

Berzins, M., and R. M. Furzeland. 1992. "An Adaptive Theta Method for the Solution of Stiff and Nonstiff Differential Equations." Appl. Numer. Math. 9:1-19.

Betancourt R. 1988. "An Efficient Heuristic Ordering Algorithm for Partial Matrix Refactorization." IEEE Trans. Pow. Sys. 3:1181-1187.

Betancourt, R., and G. F. Degen. September, 1990. Assessment of Supercomputer Technologies for Power Utilities. Final Report. Department of Electrical Engineering, San Diego State University, San Diego, California.

Boley, D., R. Maier, and J. Kim. 1989. "A Parallel QR Algorithm for the Nonsymmetric Eigenvalue Problem." Comput. Phys. Comm. 53:61-70.

Brown, P. N., G. D. Byrne, and A. C. Hindmarsh. 1989. "VODE: A Variable-Coefficient ODE Solver." SIAM J. Sci. Stat. Comp. 5:1038-1051.

Brown, P. N., and A. C. Hindmarsh. 1989. "Reduced Storage Matrix Methods in Stiff ODE Systems." Appl. Math. Comput. 31:40-91.

Brown, P. N., A. C. Hindmarsh, and H. F. Walker. 1985. "Experiments with Quasi-Newton Methods in Solving Stiff ODE Systems." SIAM J. Sci. Stat. Comput. 6:297-313.

Burmeister, W., C. Grossman, and S. Scholz. 1991. "Directional Approximation of the Jacobians in ROW-Methods." BIT 31:89-101.

Byrne, G. D., and A. C. Hindmarsh. 1975. "A Polyalgorithm for the Numerical Solution of Ordinary Differential Equations." ACM Trans. Math. Soft. 1:71-96.

Byrne, G. D., and A. C. Hindmarsh. 1987. "Stiff ODE Solvers: A Review of Current and Coming Attractions." J. Comput. Phys. 70:1-62.

Cash, J. R., and A. H. Karp. 1990. "A Variable Order Runge-Kutta Method for Initial Value Problems with Rapidly Varying Right-Hand Sides." ACM Trans. Math. Soft. 16:201-222.

Chai, J. C., and A. Bose. 1992. "Bottlenecks in Parallel Algorithms for Power System Stability Analysis." Paper 92 WM 285-7 PWRs, presented at the IEEE/PES 1992 Winter meeting, January 26-30, 1992, New York.

Chai, J. C., N. Zhu, A. Bose, and D. J. Tylavsky. 1991. "Parallel Newton Type Methods for Power System Stability Analysis using Local and Shared Memory Multiprocessors." IEEE Trans. Pow. Sys. 6:1539-1545.

Chan, S. M., and V. Brandwajn. 1986. "Partial Matrix Refactorization." IEEE Trans. Pow. Sys. 1:193-200.

Chan, T. F., and K. R. Jackson. 1986. "The Use of Iterative Linear-Equation Solvers in Codes for Large Systems of Stiff IVPs for ODEs." SIAM J. Sci. Stat. Comput. 7:378-417.

Converti, V., D. P. Gelopoulos, M. Housley, and G. Steinbrenner. 1976. "Long-Term Stability Solution of Interconnected Power Systems." IEEE Trans. Pow. App. Sys. PAS-95:96-104.

Crouch, P. E., E. Brady, and D. J. Tylavsky. 1991. "Frequency Domain Transient Stability Simulation of Power Systems." IEEE Trans. Pow. Sys. 6:51-58.

Crow, M. L., and M. Ilic. 1990. "The Parallel Implementation of the Waveform Relaxation Method for Transient Stability Simulations." IEEE Trans. Pow. Sys. 5:922-932.

Davis, G. J., R. E. Funderlic, and G. A. Geist. 1987. "A Hypercube Implementation of the Implicit Double Shift QR Algorithm." In Hypercube Multiprocessors 1987, ed. M. T. Heath, p. 619-626, Society for Industrial and Applied Mathematics, Philadelphia.

Decker, I. C., D. M. Falcao, and E. Kaszkurewicz. 1991. "Parallel Implementation of a Power System Dynamic Simulation Methodology Using the Conjugate Gradient Method." In Conference Papers 1991 Power Industry Computer Application Conference. Institute of Electrical and Electronics Engineers, New York.

- Dembart, B., A. M. Erisman, E. G. Cate, M. A. Epton, and H. Dommel. 1977. Power System Dynamic Analysis Phase I. EPRI EL-484, Electric Power Research Institute, Palo Alto, California.
- de Mello, F. P., J. W. Feltes, T. F. Laskowski, and L. J. Oppel. 1992. "Simulating Fast and Slow Dynamic Effects in Power Systems." IEEE Comp. Appl. Pow. 5:33-38.
- Dommel, H. W., and N. Sato. 1972. "Fast Transient Stability Solutions." IEEE Trans. Pow. App. Sys. 91:1643-1650.
- Dongarra, J. J. 1992. Performance of Various Computers Using Standard Linear Equations Software. CS-89-85, Computer Science Department, University of Tennessee, Knoxville, Tennessee.
- Dongarra, J. J., I. S. Duff, D. C. Sorensen, and H. A. van der Vorst. 1991. Solving Linear Systems on Vector and Shared Memory Computers. Society for Industrial and Applied Mathematics, Philadelphia.
- Dongarra, J. J., C. B. Moler, J. R. Bunch, and G. W. Stewart. 1979. LINPACK User's Guide. Society for Industrial and Applied Mathematics, Philadelphia.
- Ejebe, G. C., R. F. Paliza, and W. F. Tinney. 1992. "An Adaptive Localization Method for Real-Time Security Analysis." IEEE Trans. Pow. Sys. 7:777-783.
- Elwood, D. M. 1991. Eigenanalysis of Large Electric Power Systems. PNL-7632, Pacific Northwest Laboratory, Richland, Washington.
- Enns, M. K., W. F. Tinney, and F. L. Alvarado. 1990. "Sparse Matrix Inverse Factors." IEEE Trans. Pow. Sys. 5:466-471.
- Enright, W. H. 1974. "Second Derivative Multistep Methods for Stiff Ordinary Differential Equations." SIAM J. Numer. Anal. 11:321-331.
- Enright, W. H. 1978. "Improving the Efficiency of Matrix Operations in the Numerical Solution of Stiff Ordinary Differential Equations." ACM Trans. Math. Soft. 4:127-136.
- Enright, W. H. 1984. "Numerical Methods for Systems of Initial Value Problems - The State of the Art." In Computer Aided Analysis and Optimization of Mechanical System Dynamics, ed. E. J. Haug, pp. 309-322. Springer-Verlag, Berlin.
- Enright, W. H., K. R. Jackson, S. P. Norsett, and P. G. Thomsen. 1988. "Effective Solution of Discontinuous IVPs Using a Runge-Kutta Formula Pair with Interpolations." Appl. Math. Comput. 27:313-335.

Enright, W. H., and M. S. Kamel. 1979. "Automatic Partitioning of Stiff Systems and Exploiting the Resulting Structure." ACM Trans. Math. Soft. 5:374-385.

Fatunla, S. O. 1988. Numerical Methods for Initial Value Problems in Ordinary Differential Equations. Academic Press, Boston.

Freund, R. W. 1992. "Conjugate Gradient-Type Methods for Linear Systems with Complex Symmetric Coefficient Matrices." SIAM J. Sci. Stat. Comput. 13:325-448.

Frowd, R.J., J.C. Giri, and R. Podmore. 1982. "Transient Stability and Long-Term Dynamics Unified." IEEE Trans. Pow. App. Sys. PAS-101:3841-3850.

Gaffney, P. W. 1984. "A Performance Evaluation of Some FORTRAN Subroutines for the Solution of Stiff Oscillatory Ordinary Differential Equations." ACM Trans. Math. Soft. 10:58-72.

Gear, C. W. 1971. Numerical Initial Value Problems in Ordinary Differential Equations. Prentice-Hall, Englewood Cliffs, New Jersey.

Gear, C. W. 1980. "Runge-Kutta Starters for Multistep Methods". ACM Trans. Math. Soft. 6:263-279.

Gear, C. W., and O. Osterby. 1984. "Solving Ordinary Differential Equations with Discontinuities." ACM Trans. Math. Soft. 10:23-44.

Gear, C. W., and Y. Saad. 1983. "Iterative Solution of Linear Equations in ODE Codes." SIAM J. Sci. Stat. Comput. 4:583-601.

Gear, C. W., and D. R. Wells. 1984. "Multirate Linear Multistep Methods." BIT 24:484-502.

Geist, G. A., and G. J. Davis. 1990. "Finding Eigenvalues and Eigenvectors of Unsymmetric Matrices Using a Distributed-Memory Multiprocessor." Parallel Comput. 13:199-209.

Golub, G. H., and C. F. Van Loan. 1983. Matrix Computations. John Hopkins University Press, Baltimore, Maryland.

Gomez, A., and R. Betancourt. 1990. "Implementation of the Fast Decoupled Load Flow on a Vector Computer." IEEE. Trans. Pow. Sys. 5:977-983.

Granelli, G. P., M. Montagna, G. L. Pasini, and P. Marannino. 1992. "Vector Computer Implementation of Power Flow Outage Studies." IEEE Trans. Pow. Sys. 7:798-804.

Gross, G., and A. R. Bergen. 1976. "An Efficient Algorithm for Simulation of Transients in Large Power Systems." IEEE Trans. Circuits Sys. CAS-96:791-799

Gross, G., and A. R. Bergen. 1977. "A Class of New Multistep Integration Algorithms for the Computation of Power System Dynamical Response." IEEE Trans. Pow. App. Sys. 96:293-306.

Gupta, G. K., R. Sacks-Davis, and P. E. Tischer. 1985. "A Review of Recent Developments in Solving ODEs." Computing Surveys 17:5-47.

Hager, W. W. 1989. "Updating the Inverse of a Matrix." SIAM Rev. 31:221-239.

Hatcher, W. L., F. M. Brasch, Jr., and J. E. Van Ness. 1977. "A Feasibility Study for the Solution of Transient Stability Problems by Multiprocessor Structures." IEEE Trans. Pow. App. Sys. PAS-96:1789-1797.

Heath, M. T., E. Ng, and B. W. Peyton. 1991. "Parallel Algorithms for Sparse Linear Systems." SIAM Review 33:420-460.

Illic-Spong, M., M. L. Crow, and M. A. Pai. 1987. "Transient Stability Simulation by Waveform Relaxation Methods." IEEE Trans. Pow. Sys. 2:943-952.

Jackson, K. R., and R. Sacks-Davis. 1980. "An Alternative Implementation of Variable Step-Size Multistep Formulas for Stiff ODEs." ACM Trans. Math. Soft. 6:295-318.

Johnson, R.B.I., B. J. Cory, and M. J. Short. 1988. "A Tunable Integration Method for the Simulation of Power System Dynamics." IEEE Trans. Pow. Sys. 3:1530-1537.

Kato, T., and K. Ikieuchi. 1991. "Variable Order and Variable Step-Size Integration Method for Transient Analysis Programs." IEEE Trans. Pow. Sys. 6:206-213.

Kundur, P., G. J. Rogers, and D. Y. Wong. 1988. The Small Signal Stability Program Package. Volume 1: Program Package Development. EPRI EL-5798, Electric Power Research Institute, Palo Alto, California.

Kurita, A., H. Okubo, K. Oki, S. Agematsu, D. B. Klapper, N. W. Miller, W. W. Price, J. J. Sanchez-Gasca, K. A. Wirgau, and T. D. Younkins. 1992. "Multiple Time-Scale Power System Dynamic Simulation." Paper 92 WM 128-9 PWRs, presented at the IEEE/PES 1992 Winter meeting, January 26-30, 1992, New York.

Kusljagic, M., and M. Hajro. 1990. "Extended Transient-Mid-Term Stability Simulation." In Proceedings of the Tenth Power Systems Computation Conference, pp. 159-166. Butterworths, London.

La Scala, M., A. Bose, D. J. Tylavsky, and J. S. Chai. 1990. "A Highly Parallel Method for Transient Stability Analysis." IEEE Trans. Pow. Sys. 5:1439-1446.

La Scala, M., M. Brucoli, F. Torelli, and M. Trovato. 1990. "A Gauss-Jacobi-Block-Newton Method for Parallel Transient Stability Analysis." IEEE Trans. Pow. Sys. 5:1168-1177.

La Scala, M., R. Sbrizzai, and F. Torelli. 1991. "A Pipelined-in-Time Parallel Algorithm for Transient Stability Analysis." IEEE Trans. Pow. Sys. 6:715-722.

Lau, K., D. J. Tylavsky, and A. Bose. 1991. "Course Grain Scheduling in Parallel Triangular Factorization and Solution of Power System Matrices." IEEE Trans. Pow. Sys. 6:708-714.

Lee, S. Y., H. D. Chiang, K. G. Lee, and B. Y. Ku. 1989. "Parallel Power System Transient Stability Analysis on Hypercube Multiprocessors." In Conference Papers: 1989 Power Industry Computer Application Conference, pp. 400-406. Institute of Electrical and Electronics Engineers, New York.

Levesque, J. M., and J. M. Williamson. 1989. A Guidebook to Fortran on Supercomputers. Academic Press Inc., New York.

Lewis, J. G., and H. D. Simon. 1988. "The Impact of Hardware Gather/Scatter on Sparse Gaussian Elimination." SIAM J. Sci. Stat. Comp. 9:304-311.

Liniger, W., and R. A. Willoughby. 1970. "Efficient Integration Methods for Stiff Systems of ODEs." SIAM J. Numer. Anal. 7:47-66.

Luini, J. F., R. P. Schulz, and A. E. Turner. 1975. "A Digital Computer Program for Analyzing Long Term Dynamic Response of Power Systems." 1975 Power Industry Computer Application Conference Proceedings. Institute of Electrical and Electronics Engineers, New York.

Marti, J. R. and J. Lin. 1989. "Suppression of Numerical Oscillations in the EMTP." IEEE Trans. Pow. Sys. 4:739-747.

Norsett, S. P., and P. G. Thomsen. 1986. "Switching Between Modified Newton and Fix-Point Iteration for Implicit ODE Solvers." BIT 26:339-348.

Ortega, J. M. 1988. Introduction to Parallel and Vector Solution of Linear Systems. Plenum Press, New York.

Padilha, A., and A. Morelato. 1992. "A W-Matrix Methodology for Solving Sparse Network Equations on Multiprocessor Computers." IEEE Trans. Pow. Sys. 7:1023-1030.

Pothen, A., and F. L. Alvarado. 1992. "A Fast Reordering Algorithm for Parallel Sparse Triangular Solution." SIAM J. Sci. Stat. Comp. 13:645-653.

Rogers, G. J., and P. Kundur. 1990. "Small Signal Stability of Power Systems." In Eigenanalysis and Frequency Domain Methods for System Dynamic Performance, pp. 5-16. Institute of Electrical and Electronics Engineers, New York.

Skelboe, S. 1989. "Stability Properties of Backward Differentiation Multirate Formulas." Appl. Numer. Math. 5:151-160.

Shampine, L. F. 1980. "What Everyone Solving Differential Equations Numerically Should Know." In Computational Techniques for Ordinary Differential Equations, eds. I. Gladwell, and D. K. Sayers, pp. 1-17. Academic Press, New York.

Shampine, L. F. 1982. "Implementation of Rosenbrock Methods." ACM Trans. Math. Soft. 8:93-113.

Shampine, L. F., and C. W. Gear. 1979. "A User's View of Solving Stiff Ordinary Differential Equations." SIAM Review 21:1-17.

Shampine, L. F., H. A. Watts, and S. M. Davenport. 1976. "Solving Nonstiff Ordinary Differential Equations - The State of the Art." SIAM Review 18:376-411.

Skelboe, S. 1989. "Stability Properties of Backward Differentiation Multirate Formulas." Appl. Numer. Math. 5:151-160.

Smith, B. T., J. M. Boyle, J. J. Dongarra, B. S. Garbow, Y. Ikebe, V. C. Klema, and C. B. Moler. 1976. Matrix Eigensystem Routines - Eispack Guide. Springer-Verlag, New York.

Smith, N. P. 1991. "IBM Supercomputing Competition: Prize-Winners Show Cost-Effectiveness/Performance of Distributed Systems of Networked Workstations." Supercomputing Rev. July, pp. 43-44.

Sorensen, D. C. 1992. "Implicit Application of Polynomial Filters in a K-Step Arnoldi Method." SIAM J. Mat. Anal. 13:357-385.

Steihaug, T. and A. Wolfbrandt. 1979. "An Attempt to Avoid Exact Jacobian and Nonlinear Equations in the Numerical Solution of Stiff Differential Equations." Math. Comput. 33:521-534.

Stewart, G. W. 1987. "A Parallel Implementation of the QR-Algorithm." Parallel Comput. 5:187-196.

Stott, B. 1979. "Power System Dynamic Response Calculations." Proc. IEEE 67:219-241.

Stubbe, M., A. Bihain, J. Deuse, and J. C. Baader. 1989. "STAG - A New Unified Software Program for the Study of the Dynamic Behavior of Electrical Systems." IEEE Trans. Pow. Sys. 4:129-138.

Taoka, H., I. Iyoda, H. Noguchi, N. Sato, and T. Nakazawa. 1992. "Real-Time Simulator for Power System Analysis on a Hypercube Computer." IEEE Trans. Pow. Sys. 7:1-10.

Taylor, C. W., and M. T. Rodrigues. 1992. "Longer-Term Voltage Stability Analysis Using ETMSP 3.0." Presented at the EPRI Voltage Stability Workshop, October 29-30, 1992, San Francisco.

Tinney, W. F., V. Brandwajn, and S. M. Chan. 1985. "Sparse Vector Methods." IEEE Trans. Pow. Sys. 104:295-301.

Tischer, P. 1989. "A New Order Selection Strategy for Ordinary Differential Equation Solvers." SIAM J. Sci. Stat. Comput. 10:1024-1037.

Tylavsky, D. J., A. Bose, F. Alvarado, R. Betancourt, K. Clements, G. T. Heydt, G. Huang, M. Ilic, M. La Scala, M. A. Pai, C. Pottle, S. Talukdar, J. Van Ness, and F. Wu. 1992. "Parallel Processing in Power Systems Computation." IEEE Trans. Pow. Sys. 7:629-638.

Tylavsky, D. J., and B. Gopalakrishnan. 1990. "Precedence Relationship Performance of an Indirect Matrix Solver." IEEE Trans. Pow. Sys. 5:412-418.

van Amerongen, R.A.M. 1990. "A Rank-Oriented Setup for the Compensation Algorithm." IEEE Trans. Pow. Sys. 5:283-288.

Van Ness, J. E., F. M. Brasch, Jr., G. L. Landgren, and S. T. Naumann. 1980. "Analytical Investigation of Dynamic Instability Occurring at Powerton Station." IEEE Trans. Pow. App. Sys. 99:1386-1395.

Vuong, G.T.R. Chahine, and S. Behling. 1992. "Supercomputing for Power System Analysis." IEEE Comp. Appl. Pow. 5:45-49.

Wang, L., and A. Semlyen. 1989. "Application of Sparse Eigenvalue Techniques to the Small Signal Stability Analysis of Large Power Systems." In Conference Papers: 1989 Power Industry Computer Application Conference, pp. 358-365. May 1-5, 1989, Seattle, Washington. Institute of Electrical and Electronics Engineers, New York.

Watts, H. A. 1980. "Survey of Numerical Methods for Ordinary Differential Equations." In Electric Power Problems: The Mathematical Challenge, eds. A. M. Erisman, K. W. Neves, and M. H. Dwarakanath, pp.127-158. Society for Industrial and Applied Mathematics, Philadelphia.

Wilkinson, J. A. 1965. The Algebraic Eigenvalue Problem. Clarendon Press, Oxford.

Wong, D. Y., G. J. Rogers, B. Porretta, and P. Kundur. 1988. "Eigenvalue Analysis of Very Large Power Systems." IEEE Trans. Pow. Sys. 3:472-480.

Young, D. M. 1989. "A Historical Overview of Iterative Methods." Comput. Phys. Comm. 53:1-17.

Zhu, N., and A. Bose. 1992. "A Dynamic Partitioning Scheme for Parallel Transient Stability Analysis." IEEE Trans. Pow. Sys. 7:940-946.

APPENDIX A

CONVERSION OF BPA POWERFLOW TO RUN ON A CRAY

APPENDIX A

CONVERSION OF BPA POWERFLOW TO RUN ON A CRAY

PNL, under a previous contract with Bonneville, modified Version 2.0 of MASS to run on a Cray supercomputer (Elwood 1991). One of the main inputs to MASS is a solved powerflow. Bonneville has their own powerflow program (called BPAPF in this appendix) which is used for most of their simulations. Version 3.0 of MASS can read in the binary output file generated by BPAPF. Thus, it would be useful to have a version of BPAPF that could be run on a Cray to generate binary files for use with the Cray version of MASS.

The time required to run the BPAPF on large problems is negligible compared to the time required to run MASS. Bonneville asked PNL to modify BPAPF so that it would run correctly on a Cray but not to spend any time trying to optimize the performance of the code.

Bonneville supplied PNL with a UNIX version of BPAPF. This appendix gives a general description of the changes that were made to allow the UNIX version of BPAPF to run on a Cray. A detailed listing of the differences between the original BPAPF files and the Cray versions of these files will be supplied to Bonneville.

GENERAL MODIFICATIONS TO BPAPF

This section gives a general description of the modifications made to BPAPF.

Most of the subroutines in BPAPF contain INCLUDE statements that use the absolute directory path /common/ipf/inc/. A directory of this name will not exist on a Cray and generally can't be created by the user. Thus, a global substitution was used to change the absolute path "/common/ipf/inc/" to the

relative path "../inc/". This modified version of BPAPF was compiled and run on a SUN Sparcstation 2.

When BPAPF was compiled on the SUN several unnecessary subroutines and include files were found. These files were eliminated. The unnecessary files were:

baseclos.f	basegeti.f	basegeto.f	baseopen.f	bctbt.inc
brcht.inc	brntyp.f	bsloss.f	bustyp.f	busvlt.f
caperr.f	chekpq.f	chksen.f	cut.inc	cut2.inc
cutbr.f	cutcom.f	cutdat.f	cutinp.f	cutlis.f
cutsys.f	errors.inc	errset.f	evdata.f	fvimag.f
getbdi.f	getbdr.f	gtpdta.f	gtxdta.f	icntpf.f
igbrnd.f	indxbp.f	iupdwn.f	jpi.inc	jpilst.inc
kmpmps.f	modrat.f	opsln4.f	outdbg.f	pecdat.f
prterr.f	putbdi.f	putbdr.f	rdtyp9.f	sccs.adm
strcmn.inc	sumsli.f	swmps.f	trnchk.f	txloss.f
vaxedt.f	vers.f	versin.f	work2.inc	

The code obtained by making the above changes will be called SUNPF. Bonneville supplied PNL with a set of test problems and reference ASCII output files. SUNPF was run on these test problems. The files produced by SUNPF differed from the reference output files in only a few places. Furthermore, all differences between the reference numbers and the SUNPF numbers were only one unit in the last digit printed. These results are consistent with differences in round-off errors on different machines.

Three main types of changes were made to the actual code in BPAPF. First, some machine-dependent subroutines had to be replaced. Second, the use of some non-standard FORTRAN had to be eliminated. Third, some bugs in the program required that changes be made.

Most of the subroutines in the UNIX version of BPAPF are written in FORTRAN 77. BPAPF, however, also contains three subroutines written in C. Subroutine CALTME returns the current time and date, subroutine CPUTMR returns the elapsed CPU time, and subroutine GETUID returns the user's name. The FORTRAN-C interface is non-standard. An attempt was made to compile these C routines on the Cray and call them from FORTRAN, but this didn't work. Thus,

FORTTRAN subroutines were written with the names CALTME, CPUTMR, and GETUID. The FORTRAN versions of CALTME and CPUTMR simply call Cray library subroutines to perform the required tasks. There is no FORTRAN equivalent to GETUID on the Cray. Thus, the FORTRAN version of GETUID returns a dummy result. This was the easiest and fastest way to get these subroutines to run on the Cray.

The UNIX version of BPAPF calls the VAX library subroutines TIME and ERRSNS. Subroutine TIME returns the time of day in the format hh:mm:ss. A FORTRAN subroutine named TIME was written that calls a Cray library subroutine to perform the required task. Subroutine ERRSNS returns an error code. There is no Cray equivalent to this subroutine. Thus, a FORTRAN subroutine named ERRSNS was written. This routine returns a dummy error code.

The BPAPF was compiled on a Cray X-MP EA/232. This produced a list of warning and error messages. A complete list of these messages is being supplied to Bonneville.

There were two common warnings on the Cray. First, there were many places where a variable is used before it is defined. Many compilers will cause these variables to have a default value of zero. This, however, is not part of the FORTRAN 77 standard. Using the option "-a static" with the Cray compiler will cause these undefined variables to have a value of zero. Thus, no changes were made to BPAPF because of these warnings. Bonneville, however, should probably initialize these variables. Second, there were several places where GOTO statements cause a jump into the body of a DO loop or IF-THEN block. This is non-standard and is labeled unsafe by the Cray compiler. Some of these jumps were eliminated. In some subroutines, however, it would require a lot of work to eliminate these jumps. These subroutines were not changed. This did not actually cause any problems on the Cray. However, Bonneville may eventually want to clean up these subroutines.

The Cray compiler listed a number of errors that were caused by the use of non-standard FORTRAN. The only common error was the use of list-directed I/O on internal files. This is non-standard and is not supported by the Cray.

The Cray uses 64-bit arithmetic for single precision arithmetic, which is equivalent to double precision on most other computers. Thus, one seldom needs to use double precision on a Cray, and there is a compiler switch that can be used to disable double precision. BPAPF uses double precision variables in several places. In at least one place a double precision array is equivalenced to an integer array. It would take some time to make sure that one can safely convert all double precision variables in BPAPF to single precision without causing problems. Thus, double precision was not disabled when compiling BPAPF.

BPAPF uses COMPLEX*16 (complex double precision) and INTEGER*2 data types. These data types are non-standard and are not supported by the Cray. The Cray will automatically treat INTEGER*2 variables as INTEGER variables and COMPLEX*16 variables as COMPLEX variables. This required us to verify that these changes in data type will not cause problems in BPAPF. It turns out that they don't.

BPAPF uses some REAL*8 declarations. This is equivalent to double precision on most computers. On a Cray, however, REAL*8 will be treated as single precision. Double precision is not being disabled for BPAPF. Thus, we needed to determine whether the REAL*8 declarations needed to be converted to double precision declarations or left alone. In one case the REAL*8 declaration was left alone, in another case it was changed to a double precision declaration.

Finally, several bugs were found while working on the Cray version of BPAPF. The affected subroutines were replaced by dummy subroutines that stop program execution if they are called. Bonneville, however, should fix these bugs. The bugs are described in the next section.

The Cray version of BPAPF was tested in two phases. First, most of the modified subroutines in BPAPF can be run on any computer. Thus, a version of BPAPF containing most of the modified subroutines was run on the SUN. The test problems supplied by Bonneville were run using this code. This pseudo-

Cray version of BPAPF yielded results that were identical to the results computed by SUNPF. Finally, the test problems were actually run on the Cray. The results were then compared to the results computed by SUNPF. All of the differences found were small and were consistent with the fact that the Cray uses 64-bit arithmetic while the SUN uses 32-bit arithmetic (except where double precision is used).

SPECIFIC MODIFICATIONS OF BPAPF

This section describes the changes made to specific subroutines in BPAPF. Only changes that were not adequately covered above are described.

The Cray does not support complex double precision. Furthermore, the Cray will not recognize the non-standard intrinsic functions DCMPLX and DIMAG when double precision is enabled, as it is with BPAPF. Thus, a global substitution was done in subroutines ABCD, GETZKK, NRYCMP, and YCPSUM to change DCMPLX and DIMAG to CMPLX and AIMAG, respectively.

Subroutines CHGLOD, CTLPOW, EVALFN, GETAGC, GETDRP, HOTCHG, LODSOL, and PRTPRM perform list-directed reads from internal files. This is non-standard FORTRAN and is not supported by the Cray. Code was added to subroutine PWRFL0 to open an auxiliary file, scratch.xxx, attached to logical unit 50. At the end of each run, this file is deleted. All list-directed reads from internal files were then changed so that they write the contents of the internal file to logical unit 50, and then do a list-directed read of the data from file scratch.xxx. In particular, statements of the form

```
READ (WORD(NEXT), FMT=*, ERR=140) PCTP
```

were changed to statements of the form

```
REWIND (50)
WRITE (50, '(A)') WORD(NEXT)
REWIND (50)
READ (50, FMT=*, ERR=140) PCTP
```

This is a quick fix. It would be better to change the list-directed I/O to edit-directed I/O.

Subroutine ANAL

This routine has a jump into an IF-THEN-ELSE block. This jump into the IF-THEN-ELSE block was converted into a separate IF-THEN block.

Subroutine BLKDTA

Subroutine BLKDTA includes file JOBCTL.INC after it includes file VLEVEL.INC. File VLEVEL.INC contains a DATA statement assigning a value to PRGVSN, while JOBCTL.INC declares PRGVSN's data type. PRGVSN's type, however, must be declared before it is assigned a value in the DATA statement. Thus, the statement that includes file VLEVEL.INC in subroutine BLKDTA was moved so that it follows the statement that includes file JOBCTL.INC.

The Cray compiler warned that an array of length one was equivalenced to part of a common block. This equivalencing, however, causes no problems, so it was not changed.

Subroutine BLKDTA declares variables LENPNM and LOCPNM to be of type INTEGER*2. These variables are never actually used and can safely be treated as INTEGER variables. Thus, the type declaration on these variables was changed to INTEGER.

File BRSRT.INC

Variable MBRST is declared to be of type INTEGER*2 in the include file BRSRT.INC. Variable MBRST is only used by subroutines BRREAD, KOMPBR, and SWAPBR. In each of these places MBRST can safely be converted to INTEGER. Thus, the type declaration for variable MBRST was changed to INTEGER in file BRSRT.INC.

Subroutine CHKINV

Subroutine CHKINV declares variable AIJ to be of type REAL*8. Variable AIJ is only used locally and can safely be treated as type REAL or DOUBLE

PRECISION on the Cray. Thus, the REAL*8 declaration was changed to a DOUBLE PRECISION declaration.

Subroutine CNVTLD

On the Cray, numeric variables must be aligned on word (8-byte) boundaries. Common block AMTRX in subroutine CNVTLD contains both numeric and character variables. The character variables caused some of the numeric variables to be misaligned.

Either the character variables in COMMON/AMTRX/ must be moved to the end of the common block, or padding needs to be added after the character variables to align the non-character variables. The preferred method is to move the character variables to the end of the common block or to a different common block. This requires modifying the declaration of common block AMTRX in subroutine CNVTLD. When doing this, however, consistency must be maintained between all subroutines that used this common block.

Common block AMTRX is declared in the include file AMTRX.INC and is also declared explicitly in several subroutines. Most of these declarations for COMMON/AMTRX/ are completely different from the declaration used in subroutine CNVTLD. These declarations indicate that COMMON/AMTRX/ in subroutine CNVTLD only needs to be consistent with COMMON/AMTRX/ in subroutine COMPLD.

The declaration of COMMON/AMTRX/ used in subroutine CNVTLD is:

```
COMMON /AMTRX/ BUSPCT(2,3,MAXBUS), OWNLIS(100), BUSCOD(2*MAXBUS),  
1           NXTBUS(2*MAXBUS), BUSINX(2*MAXBUS),  
2           LSTBUS(2*MAXBUS)  
CHARACTER OWNLIS * 3, BUSCOD * 9, DEFVLT * 8, CHGTYP * 1,  
1           CHG(3) * 1, BUSCHG * 1  
INTEGER BUSINX, COMPLD
```

while the declaration used in subroutine COMPLD is:

```

COMMON /AMTRX/ BUSPCT(2,3,MAXBUS), OWNLIS(100), BUSCOD(2*MAXBUS),
1          NXTBUS(2*MAXBUS), BUSINX(2*MAXBUS),
2          LSTBUS(2*MAXBUS)
CHARACTER BUSCOD * 9
INTEGER BUSINX, FIND

```

The fact that variable OWNLIS is not declared to be of type CHARACTER*3 in subroutine COMPLD means that these declarations for COMMON/AMTRX/ are inconsistent. This appears to be a bug in BPAPF. Furthermore, subroutine COMPLD is a FUNCTION that 1) is only called by subroutine CNVTLD, 2) never assigns a value to the variable COMPLD, 3) does not modify any common block variables, and 4) only modifies the last variable in its dummy argument list. Furthermore, subroutine CNVTLD does not use the last variable in the actual argument list used to call subroutine COMPLD. Thus, subroutine CNVTLD really doesn't do anything. Subroutine CNVTLD, however, uses the value returned by subroutine COMPLD for variable COMPLD (which is always undefined). Thus, the behavior of subroutine CNVTLD will depend on how the compiler initializes undefined variables. These results indicate that there are one or more bugs in subroutine COMPLD.

The problems with subroutines CNVTLD and COMPLD were fixed by making two changes. First, subroutine COMPLD was replaced by a dummy subroutine that causes program execution to stop if it is ever called. Second, the declaration for COMMON/AMTRX/ in subroutine COMPLD was changed to:

```

COMMON /AMTRX/ BUSPCT(2,3,MAXBUS),
1          NXTBUS(2*MAXBUS), BUSINX(2*MAXBUS),
2          LSTBUS(2*MAXBUS),
3          OWNLIS(100), BUSCOD(2*MAXBUS)
CHARACTER OWNLIS * 3, BUSCOD * 9, DEFVLT * 8, CHGTYP * 1,
1          CHG(3) * 1, BUSCHG * 1
INTEGER BUSINX, COMPLD

```

If subroutine COMPLD is fixed and reactivated, then the declaration for COMMON/AMTRX/ in subroutine COMPLD must be changed so that it is the same as the declaration used in the new version of subroutine CNVTLD.

Another error was also detected in subroutine CNVTLD. Variables BUSFLG and MATCH are of type LOGICAL. Logical variables cannot be used with the relational expression ".EQ.", but this is done in the two lines of code:

```
IF (BUSFLG .EQ. .TRUE.) THEN
```

and

```
IF (MATCH .EQ. .TRUE. .AND. ICNVT .NE. OLDCVT) THEN
```

In these lines of code one must either replace ".EQ." with the logical operator ".EQV." or the preceding lines of code must be replaced by the code:

```
IF (BUSFLG) THEN
```

and

```
IF (MATCH .AND. ICNVT .NE. OLDCVT) THEN
```

respectively. The latter option was used.

Subroutine COMPLD

See subroutine CNVTLD.

Subroutine CTLPOW

The second comma in "READ (WORD(JWRD), 220), ..." is illegal and was deleted

Subroutine CURSOL

The second comma in "WRITE (DEBUG,2640), ..." is illegal and was deleted.

EPRIDC.INC

Variables MEPBUS and MEPCTL are declared to be of type INTEGER in the include file EPRIDC.INC, but are assigned LOGICAL values in a DATA statement in subroutine BLKDTA, and are used as LOGICAL variables in subroutine GETEPR. Variables MEPBUS and MEPCTL are only used by subroutines BLKDTA and GETEPR. In all cases these variables are used as LOGICAL variables. Thus, these variables were changed to type LOGICAL in the include file EPRIDC.INC.

Subroutine EQVSEC

See subroutine GETYEQ.

Subroutine GETLFO

The statement "IF (JT .EQ. 1) GO TO 220" is not safe because it causes a jump to the terminal CONTINUE statement of a DO loop. The GO TO 220 was changed to GO TO 221 and a statement "221 CONTINUE" was inserted immediately after the "220 CONTINUE" statement.

Subroutine GETPRM

Variable ENDRCD defaults to type REAL, but is assigned a logical value. Variable ENDRCD is never used; thus, this assignment statement was deleted.

Subroutine GETYEQ

Subroutine GETYEQ declares array YSCR to be of type COMPLEX*16. YSCR is only used as an argument to subroutine EQVSEC. Subroutine EQVSEC does not declare a type for array YSCR; thus, it defaults to type REAL, yet subroutine EQVSEC treats YSCR as a complex number. This appears to be a bug in subroutine EQVSEC. Subroutine EQVSEC was replaced by a dummy subroutine that stops program execution if it is called. Once this was done it is safe for the Cray to automatically convert YSCR to type COMPLEX in subroutine GETYEQ.

Subroutine NRYCMP

Variable A is declared to be of type COMPLEX*16. The lines of code

```
IMAG(JT) = DSQRT((REAL(A(1)))**2 + (DIMAG(A(1)))**2)
IMAG(JT) = DSQRT((REAL(A(3)))**2 + (DIMAG(A(3)))**2)
```

caused the error message "Improper intrinsic function argument type or inconsistent types." In general the statements REAL(A(1)) and REAL(A(3)) should be replaced by DBLE(A(1)) and DBLE(A(3)). Single precision on a Cray, however, is equivalent to double precision on most other machines. Thus, the FORTRAN statements listed above were changed to

```
IMAG(JT) = SQRT((REAL(A(1)))**2 + (AIMAG(A(1)))**2)
IMAG(JT) = SQRT((REAL(A(3)))**2 + (AIMAG(A(3)))**2)
```

The Cray will treat the COMPLEX*16 declaration the same as a declaration of COMPLEX. All of the COMPLEX*16 variables in this subroutine are only used locally for extra precision. Thus, it is safe for the Cray to automatically treat these variables as COMPLEX variables.

Subroutine PRGMON

Subroutine PRGMON declares variables TIMES and TIMEF to be of type REAL*8. Subroutine PRGMON passes these variables to subroutine TIMODA, where they are declared to be of type CHARACTER*8. Thus, these variable need to be 8 bytes long in subroutine PRGMON. The results returned in TIMES and TIMEF by TIMODA are never used. Thus, it is best to leave the REAL*8 type declaration alone. Bonneville, however, should probably remove the calls to TIMODA from PRGMON.

Subroutine PRTPRM

This subroutine does two list-directed writes to CHARACTER*20 internal files. These list directed writes were changed to edit-directed writes using a G20.7 format.

Subroutine PRTUSR

The attributes RECORDTYPE='VARIABLE' and ACCESS='APPEND' are used in an OPEN statement but are non-standard and are not supported by the Cray. The RECORDTYPE='VARIABLE' attribute was removed, while the ACCESS='APPEND' attribute was replaced by the POSITION='APPEND' attribute.

Subroutine REDUCT

The declaration "COMPLEX Y*8,OLDY*8,A*8,V*8,S*8" is non-standard and was changed to "COMPLEX Y,OLDY,A,V,S".

Subroutine SENDEC

The code

```
190 IF (IDAT .EQ. 0) THEN
      WRITE (ERRBUF(1),200 )
200  FORMAT('0 No "B" records follow "BUS_SENSITIVITIES". ')
      CALL PRTERX ('W',1)
      ENDIF
      RETURN
```

is imbedded in an IF-THEN-ELSE block. This block can only be reached by a GOTO 190 statement. There are multiple GOTO 190 statements that cause jumps into the IF-THEN-ELSE block. This is not safe. This problem was fixed by moving the section of code listed above so that it appears just before the subroutine's END statement.

Subroutine SOLTON

One OPEN statement has a CARRIAGECONTROL='LIST' attribute and one has a RECORDTYPE='VARIABLE' attribute. These are non-standard attributes and were removed from the appropriate OPEN statements.

Subroutine STRACE

The variables O and NTYPE are used before they are assigned values. It appears that the variable O is a typo and should really be a zero. Most compilers set uninitialized variables to zero. This problem will not be fixed for now, since it should run alright on the Cray. Bonneville, however, should fix this.

Subroutine SUBDEF

There are multiple I/O statements with the ERR=220 attribute. This causes a jump into an IF-THEN-ELSE block. This is not safe. The line of code containing the label 220, and the 12 lines of code following this line, can only be reached by a "GOTO 220" statement. Thus, these 13 lines of code were moved outside of the IF-THEN-ELSE block.

REFERENCES

Elwood, D. M. 1991. Eigenanalysis of Large Electric Power Systems.
PNL-7632, Pacific Northwest Laboratory, Richland, Washington.

DISTRIBUTION

No. of
Copies

No. of
Copies

OFFSITE

ONSITE

- 2 DOE/Office of Scientific and
Technical Information
- 30 Bonneville Power Administration
ATTN: John Hauer - EOH
P.O. Box 3621
Portland, OR 97208
- 30 Bonneville Power Administration
ATTN: Carson Taylor - EOH
P.O. Box 3621
Portland, OR 97208

- DOE Richland Field Office
- D. R. Segna
- 37 Pacific Northwest Laboratory
- J. G. DeSteeze
D. M. Elwood (25)
L. D. Kannberg
P. S. Lowery
E. W. Pearson
D. J. Trudnowski
G. L. Work
Publishing Coordination
Technical Report Files (5)

END

DATE
FILMED

3 / 24 / 93