ASSESSMENT OF THE IMPACT OF HTSCS ON SUPERCONDUCTING FAULT-CURRENT LIMITERS*

ANL/ES/CP--78917

by

DE93 009986

R.F. Giese
Energy Systems Division
Argonne National Laboratory
9700 South Cass Avenue
Argonne, IL 60439

and

M. Runde
Norwegian Electric Power Research Institute
7034 Trondheim-NTH
Norway

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

The submitted manuscript has been authored by a contractor of the U. S. Government under contract No. W-31-109-ENG-38. Accordingly, the U. S. Government retains a nonexclusive, royalty-free license to publish or reproduce the published form of this contribution, or allow others to do so, for U. S. Government purposes.

RECEIVED
MAR 26 1993
OSTI

for presentation at

American Power Conference
Illinois Institute of Technology
Chicago, IL USA
April 13-15, 1993

MASTER

* This work was supported, in part, by the U.S. Department of Energy, Assistant Secretary for Conservation and Renewable Energy, under contract W-31-109-Eng-38, as well as by the following participating countries: Canada, Denmark, Finland, Germany, Italy, Japan, the Netherlands, Norway, Sweden, Switzerland, Turkey, and the United Kingdom.

ASSESSMENT OF THE IMPACT OF HTSCs ON SUPERCONDUCTING FAULT-CURRENT LIMITERS

R.F. Giese

Energy Systems Division, Argonne National Laboratory,
Argonne, IL 60439

M. Runde

Norwegian Electric Power Research Institute,
7034 Trondheim-NTH, Norway

ABSTRACT

The possible impact of nitrogen-cooled superconductors on the design and cost of superconducting fault-current limiters is assessed by considering the technical specifications such devices must meet and by comparing material properties of 77-K and 4-K superconductors. The main advantages of operating superconductors at 77 K are that the refrigeration operating cost is reduced by a factor of up to 25 and the refrigeration capital cost is reduced by a factor of up to 10. The heat capacity is several orders of magnitude larger at 77 K than at 4 K. This phenomenon increases conductor stability against flux jumps but makes switching from the superconducting to the normal state slow and difficult. Therefore, a high critical current density, probably at least 10^5 A/cm², is required.

INTRODUCTION

As electric power systems grow and become more interconnected, the fault currents (i.e., the currents that would flow if a short circuit occurs) increase. Prudent precautions for handling these increasing fault currents often require the costly replacement of substation equipment or the imposition of changes in the configuration of the system that lead to decreased operational flexibility and lower reliability. The need for a device that can prevent the buildup of fault currents has been obvious for years. A number of fault-current limiter (FCL) concepts have been proposed,¹ but according to a recent study,² they all have major cost or performance disadvantages.

Superconducting materials are a part of several of the proposed FCL schemes. Comprehensive lists of publications and patents on superconducting fault-current limiters (SCFCLs) have been collected.^{1,3} Some SCFCLs have been built as small-scale models (typically a few amperes at a few hundred volts), but most of the designs are purely "paper concepts" that have not been built or tested. To the authors' knowledge, only two full-scale devices have been built, both single-phase prototypes with ratings in the lower end of the distribution system range.^{4,5} However, a similar-scale prototype device is currently under development in Japan.⁶ A very comprehensive design study of SCFCLs for high-power transmission systems also clarified several important issues,^{3,7,8} although no device was built.

The discovery in 1987 of superconductors with transition temperatures above the boiling point of nitrogen has stimulated renewed interest in large-scale applications of superconductors. The SCFCL has been mentioned repeatedly as a likely early application of high-temperature superconductors (HTSC) in the power sector. The purpose of this paper is to assess the potential impact of ceramic

superconductors on the design and performance of the most relevant SCFCL concepts. The evaluation is performed by (1) comparing material parameters typical for HTSC at 77 K with those for low-temperature superconductors (LTSC) at 4 K and (2) considering how the design and cost of SCFCLs will be affected.

Initially, two example power systems with FCLs are analyzed to establish and clarify the technical specifications that an FCL must meet. Power rating is emphasized because this important parameter has been neglected in many earlier studies of SCFCLs.

This paper is a summary of a report prepared for the International Energy Agency.⁹

TECHNICAL SPECIFICATIONS

An FCL, whether it employs a superconductor or not, is basically a variable impedance that is installed in series with a circuit breaker in a substation. In the case of a fault, its impedance increases to a value at which the fault current is reduced to a level that the breaker can handle. Upon removal of the fault or operation of the circuit breaker, the device should return to its low-impedance mode within a few power cycles.

The performance specifications for an FCL in a power system are most conveniently determined by case studies. Figure 1 and Table I describe the two example systems to be used in the present work. For simplicity, only phase-to-ground faults are considered, and unless otherwise stated, any dc offsets are disregarded.

The maximum limited fault currents are set to 10 kA and 63 kA for the distribution and transmission systems, respectively. The highest rating in conventional commercial circuit breakers is 63 kA. Table II lists the minimum FCL impedance values for the two example systems.

In a resistive FCL, the power dissipated is RI^2 , where R is the limiting resistance and I is the RMS value of the limited current. The magnetic energy stored in an inductive FCL is given by $0.5LI^2$, where L is the limiting inductance and I is the peak value of the limited current. Increasing the impedance of the FCL reduces the limiting current and thereby reduces the energies to be handled by the device. Figure 2 shows the energy dissipated per power cycle in a resistive

Figure 1 Circuit Diagram of the Example Systems

Table I Parameters for the Distribution and Transmission Example Systems (the power frequency is 60 Hz)

Parameter	15-kV System	500-kV System
Source voltage (kV _{RMS}), U	8.7	290
Maximum load current (A _{RMS}), I _n	600	3000
Source impedance (Ω)	0.43	2.4
X/R ratio	1.7	10
Source resistance (Ω), R _s	0.22	0.24
Source inductance (mH), L _s	1.0	6.3
Unlimited fault current (kA _{RMS})	20	120
Maximum limited fault current (kA _{RMS})	10	63

FCL and the maximum magnetic stored energy in an inductive FCL, both plotted as a function of the limited current.

Figure 2(b) shows that a fault current of 63 kA in the 500-kV system requires a resistive FCL to dissipate 240 MJ per power cycle. (This value is huge; if this energy were dissipated in 1 m³ of water, the temperature would rise by almost 60°C.) Two power cycles can be considered a minimum time of operation for an FCL, so this device must be able to dissipate 480 MJ per fault. Furthermore, if the relaying system and reclosure procedures are set up in such a way that the FCL in the worst case must operate a second or third time within a few seconds, it must be designed to dissipate energies in the gigajoule range.

By instead applying an inductive device to limit the fault currents to 63 kA in the 500-kV system, up to about 75 MJ of magnetic energy has to be stored in the FCL (see Figure 2[b]); therefore, a very large device is required. If an iron-core reactor with a maximum energy density of 1 kJ/m³ in the iron is used, about 75,000 m³ (the size of a two-story warehouse) of iron is required per phase. If the energy is stored in a 1-T field of an air-core reactor, an air volume of

Table II FCL Impedances (inductances) Required to Reduce the Fault Current to the Predetermined Levels of 10 kA and 63 kA

FCL Type	15-kV System	500-kV System
Resistive (Ω)	0.56	3.7
Inductive (Ω [mH])	0.46 (1.2)	2.2 (5.8)

190 m³ is required, and the device is still huge (the size of a large room).

If the fault current in the 500-kV system is limited to 10 kA instead of 63 kA, the energies involved are reduced by factors of 5 and 3.5 in the resistive and inductive FCL cases, respectively. However, the energies are still very large.

For the 15-kV FCLs, the energies are typically 250 times lower than those in the 500-kV system (see Figure 2[a]). Ohmic dissipation of 0.2 to 1 MJ requires some mass and volume, but this is obviously a much simpler task than dealing with gigajoules. Air-core reactors in the range of 1 to 10 mH for 15-kV FCLs are approximately 1 m³ in volume and are commercially available.

Whether or not a utility will install an FCL is largely a question of economics, and information in the literature about acceptable capital and operating costs is limited. Two surveys of a number of U.S. utilities^{1,10} indicate that the utilities are not willing to pay more for an FCL than at most a few times the cost of a circuit breaker. The electrical losses during normal operation should not exceed 25% of the losses in a transformer in the same system.¹

Figure 2 Energy Dissipated per Power Cycle in a Resistive FCL and Energy Stored in an Inductive FCL for the Example Distribution System (a) and Transmission System (b)

SUPERCONDUCTING FAULT-CURRENT LIMITERS

Simplified circuit diagrams for four generically different SCFCLs are shown in Figure 3. Conceptually, the basic resistive SCFCL, as shown in Figure 3(a), is the simplest design. During normal load, the superconducting element is in its superconducting state and current passes with virtually no losses. In the case of a fault current, the critical current density J_c of the superconductor is exceeded, and the superconductor undergoes a transition to its normal (nonsuperconducting) state; thus, the superconductor is transformed to a series resistor that limits the current. A major drawback associated with this concept is that during a fault, all of the energy is dissipated directly into the superconductor. Consequently, the superconductor must have, or be intimately linked to, a large thermal mass, but this arrangement significantly increases the reset time.

The energy dissipated in the superconductor during a fault can be reduced by employing a shunt impedance as the limiting element (see Figures 3(b) - 3(d)). To efficiently commutate the current to the shunt, the normal-state resistance of the superconducting element must be orders of magnitude larger than the shunt. In addition to conventional resistors and air-core reactors, it has been proposed that a superconducting coil be used as a limiting impedance, as shown in Figure 3(d).

An inherent drawback with the schemes shown in Figure 3 is that the superconducting element is in-line with the power circuit. Because of this arrangement, there will be ac losses; moreover, heat leaking through the current leads and into the cryostat will cause additional thermal losses.

Several SCFCL concepts in which the superconducting element is not in-line with the power circuit have also been proposed. However, these concepts lead to bulky devices and are considered infeasible in the present study. The saturated iron-core device⁴ is more than twice the size of a transformer and is therefore too big and heavy. Inductively linked SCFCLs¹¹ include a transformer and are disregarded for the same reason. Shielding devices^{3,12} also become prohibitively large because of the vast amounts of iron and/or copper needed.

Figure 3 Different SCFCL Concepts (schematically)

IMPACT OF HIGH-CRITICAL-TEMPERATURE SUPERCONDUCTORS

The likely impact of applying the new ceramic superconductors and operating at 77 K (compared with using conventional low-temperature superconductors at 4 K) is discussed in this section. It is assumed that HTSC wires behave according to the "critical state model" proposed by Bean¹³ and extensively applied by Wilson.¹⁴ (Data on HTSC materials appear to be consistent with the "critical state model.") The following topics related to the design and operation of SCFCLs are addressed: material properties, ac losses, refrigeration costs, stability and switching, and transient temperatures.

MATERIAL PROPERTIES

Table III summarizes representative material properties for LTSCs (NbTi) and HTSCs. In the subsequent calculations, T_c for these materials is taken as 9.5 K for an LTSC and 92 K for an HTSC. The values for copper (a commonly used stabilizer) and sapphire (a possible substrate for superconducting films) are also included in Table III.

As shown in Table III, the most evident difference is that the heat capacity at 77 K is several orders of magnitude higher than the heat capacity at 4 K.

ALTERNATING-CURRENT LOSSES

In the concepts illustrated in Figure 3, the superconductor passes the full load current under normal operation. Hence, the magnitude of the ac losses (i.e., hysteresis losses and ohmic losses caused by eddy currents if metallic stabilizers are applied) is crucial to the operating costs of the SCFCL.

The electrical losses are primarily determined by the design and operating conditions of the conductor, not by the material properties referred to above. Consequently, in high-quality materials, the losses are expected to be similar for HTSCs and LTSCs.

TABLE III Representative Values for Thermal Conductivity κ , Heat Capacity c , and Normal-State Resistivity ρ_N for Superconductors, Stabilizers, and Substrate Materials at 4 K and 77 K

Material	κ (W/m K)	c (J/m ³ K)	ρ_N (10 ⁻⁸ Ω m)
LTSC (4 K)	0.1	5000	70
HTSC (77 K)	2	10 ⁶	100
Cu (4 K)	3500	400	0.038
Cu (77 K)	550	1.9 $\times$ 10 ⁶	0.25
Al ₂ O ₃ (4 K)	220	20	insulating
Al ₂ O ₃ (77 K)	960	0.3 $\times$ 10 ⁶	insulating

REFRIGERATION COSTS

The differences in refrigeration costs depend on (1) the relative thermal loads at 4 K and 77 K, (2) the relative refrigeration efficiency at 4 K and 77 K, and (3) the magnitude of refrigeration costs compared with other SCFCL costs.

Thermal Loads

There are three primary sources of thermal load in an SCFCL: (1) thermal conduction through current leads, residual gas, and structural components; (2) radiation losses; and (3) internally generated heat (ac losses). The thermal loads at 77 K and 4 K have been estimated to be approximately equal.⁹ However, as is discussed in the next section, the cost of absorbing the heat is different.

Refrigerator Efficiency

In a survey of cryogenic refrigerators,¹⁵ it was found that their efficiency (relative to the Carnot efficiency) is independent of the lower operating temperature, but efficiency increases with increasing capacity. In this context, capacity refers to the amount of heat that can be absorbed at the lower temperature and rejected at 300 K. Thus, a refrigerator for an SCFCL operating at 77 K requires 25 times less power input than a refrigerator for an SCFCL operating at 4 K, provided that the thermal loads are the same. The factor 25 is simply the Carnot efficiency between 300 K and 77 K relative to 300 K and 4 K.

The capital costs of the refrigerator have been found to scale approximately as the 0.7 power of the input power.¹⁵ With the same thermal load at 77 K and 4 K, the refrigerator capital cost is reduced by a factor of 10.

Refrigeration Costs Relative to Other Costs

The capital cost of the refrigerator relative to the rest of the SCFCL costs decreases with increasing complexity of the SCFCL. For a device that employs a high-power shunt, an external triggering unit, and overvoltage protection, the refrigerator cost savings at 77 K relative to 4 K are unlikely to reduce the total cost of the SCFCL by more than 20%. This percentage is based on the cost estimate for a transmission system SCFCL.³ If it is possible to make a very simple device, the savings become greater, possibly as high as 50% for a distribution system SCFCL. However, because little has been published on the cost of SCFCLs, these percentages must only be considered rough estimates.

The cost of refrigeration is expected to dominate the operating cost of an SCFCL. Thus, the savings in SCFCL operating costs by operating at 77 K are expected to be almost as large as the improvement in Carnot efficiency.

STABILITY AND SWITCHING

The superconducting element of the SCFCL concepts shown in Figure 3 is subjected to stability requirements that, in some senses, are contradictory. On one hand, the superconductor should be stable and remain in its superconducting state during normal load. On the other hand, if a fault occurs, it should switch very rapidly to its normal (nonsuperconducting) state.

Adiabatic Stability

Wires of superconducting materials are inherently unstable unless they have a small cross section. Slight disturbances of almost any kind (thermal, electrical, magnetic, mechanical, etc.) will cause a current-carrying superconductor to quench. A common measure of superconductor stability is the "adiabatic stability criterion." The maximum conductor radius a_{ad} for which a superconducting wire will not exhibit thermal runaway when passing a current density just below J_c is shown in Figure 4. It appears that HTSC wires are adiabatically stable for diameters 25 times larger than those for LTSC wires.

Switching

The required switching time for the superconductor element in an SCFCL depends on the design, but it typically ranges from a few microseconds to a few milliseconds. If the switching is too fast, overvoltages occur across the device, while the fault currents can build up to unacceptable levels if the switching is too slow.

For both passively and actively triggered switching, the superconductor first enters into the so-called "lossy state." In this state, the superconductor is unstable, and the interaction between the current and the magnetic field produces heat, which causes the temperature in the superconductor to rise. However, the superconductor does not reach the full normal-state resistivity ρ_N (and, consequently, the full limiting resistance) until T_c is exceeded. Figure 5 shows an estimate of switching times for a range of J_c . Apparently, switching from the superconducting to the normal state is much slower for HTSCs than for LTSCs; moreover, τ decreases rapidly with increasing J_c .

Experience with LTSCs has shown that unless active triggering is employed, a superconductor initially goes normal only at one or a few small, weak regions. These nonsuperconducting islands then expand throughout the entire superconductor. The velocity at which the front of the

Figure 4 Maximum Adiabatically Stable Conductor Radius for an LTSC at 4 K and an HTSC at 77 K

Figure 5 Switching Times (simplified estimates) for an LTSC and an HTSC

normal region propagates through the superconductor is called the quench propagation velocity v_q . Figure 6 illustrates the quench propagation velocity for an LTSC and an HTSC.

Hence, thermal processes are expected to proceed more slowly in HTSCs than in LTSCs, primarily because of the much greater heat capacities of materials at 77 K relative to 4 K. As shown above, τ is 2.5 orders of magnitude greater and v_q 1.5 orders of magnitude smaller at 77 K than at 4 K. These conditions will make the transition of an SCFCL from the low-impedance to the high-impedance mode substantially more difficult with an HTSC than with an LTSC. This is the case both for passive and active triggering. However, as can be seen from Figures 5 and 6, both τ and v_q improve radically when J_c becomes large. Thus, to obtain sufficiently fast and uniform switching with an HTSC element, a high critical current density is required, probably at least 10^5 A/cm².

TRANSIENT TEMPERATURES

When the superconductor eventually has been switched to the normal state, the temperature will continue to rise as long as current is flowing. The rate at which the temperature increases is, to the first approximation, proportional to the reciprocal of the heat capacity. Thus, HTSCs are superior to LTSCs because of their much greater heat capacity. However, this assertion is only true if the temperature rise during a fault is small. As will be discussed in the next section, temperature transients of hundreds of kelvin must in some schemes be accepted, even for HTSCs. With such large energy dissipations, whether the coolant is at 4 K or 77 K is of minor importance.

DESIGN OF HIGH-CRITICAL-TEMPERATURE FAULT-CURRENT LIMITERS

Several important design trade-offs that are closely related to the power rating of an SCFCL during a fault will now be discussed. The electrical parameters of the example distribution and transmission systems described above are applied, and the discussion is limited to HTSCs and the SCFCL concepts presented in Figure 3.

Figure 6 Quench Propagation Velocities in an LSC and an HTSC

RESISTIVE SCFCL

The basic resistive design in Figure 3(a) is considered first. By assuming a relatively high J_c , the FCL resistance specifications given in Table II are easily met for reasonable HTSC wire cross sections and lengths. However, if the power dissipation during a fault is also taken into consideration, major problems are encountered. Figure 7 shows the temperature rise in kelvin per millisecond during a fault for the two example systems with the SCFCL resistances given in Table II and for $I_c = 5I_n$. Adiabatic conditions are assumed, and all material parameters are considered constant and independent of temperature.

As expected, low J_c values result in a slower heating of the superconductor because its mass is larger. However, because a high current density is required to accomplish sufficiently fast switching, Figure 7 shows that the Figure 3(a) design is not technically feasible, if the SCFCLs have the minimum required resistances given in Table II. Even with a current density as low as 10^4 A/cm², the power dissipation will cause the superconductor to evaporate within the first power cycle (17 ms).

The only way to reduce the dissipation and thereby limit the temperature rise in the superconductor is to limit the current even further by increasing the SCFCL resistance. Because ρ_N of HTSC cannot be increased without reducing J_c drastically, this reduction can only be achieved by increasing the length of the superconductor. Figure 8 shows the rate of temperature rise during a fault as a function of the limiting resistance for two values of J_c . The lower resistance values are those required to limit the current to 10 kA and 63 kA, respectively (see Table II).

Limiting the fault current to the nominal load current I_n corresponds to SCFCL resistances of about 14 Ω and 100 Ω for the two systems. The associated temperature rises after two cycles (33 ms) are, as shown in Figure 8, still of the order of 10^3 K, if J_c is 10^5 A/cm². Hence, the current flowing through the superconducting element while in its normal state must be limited to a value significantly smaller than I_n to prevent the temperature transients from damaging the superconductor. However, the required superconductor

Figure 7 Temperature Rise in the HTSC Element of the Concept Shown in Figure 3(a). (The resistance values are 0.56 Ω and 2.38 Ω for the distribution and transmission system SCFCL, respectively.)

Figure 8 Temperature Rise per Millisecond in the HTSC Element of the Concept Shown in Figure 3(a) as a Function of the Limiting Resistance for the Example Distribution System (broken lines) and Transmission System (solid lines)

length and volume increase correspondingly. For example, to obtain a limiting resistance of 1 k Ω in the two systems, the superconductors must be 3 km and 15 km long, respectively, assuming J_c is 10⁵ A/cm².

INDUCTIVE SCFCL

By applying an inductive shunt instead of a resistive SCFCL (see Figure 3[c] and 3[d]), the L/R ratio increases. (Here, L includes both the stray inductance in the resistive SCFCL and the limiting inductance in the inductive

SCFCL.) Thus, the current commutation to the shunt during a fault becomes much slower when employing an inductive shunt. Consequently, the problems related to energy dissipation in the superconducting element in the early stages of a fault are even greater in this design.

Since the SCFCL already has a cryostat, an interesting scheme is to use an air-core reactor with superconducting windings, as shown in Figure 3(d). The reactor remains in its superconducting state during a fault; the current is limited by its impedance. Compared with applying ambient temperature air-core reactors (Figure 3[c]), this scheme may lead to a more compact SCFCL design because the ampere-turns and the magnetic energy density can be increased substantially. Doubling the magnetic flux density reduces the required reactor volume by a factor of four, but higher structural requirements are needed to balance the increased magnetic forces between the conductors. The engineering problems related to the construction of large, high-field (several tesla) superconducting coils are significant and increase rapidly with the size of the coil. The combined volume and flux density for the transmission system SCFCL discussed here is clearly beyond present conventional technology.

Most of the potential difficulties related to the switching and resetting of the superconducting element exist also in the inductive schemes of Figure 3, because the inductive SCFCLs rely on the same superconducting-to-normal transition. Although these devices limit the fault current inductively, the problems associated with the power dissipation in resistive SCFCLs generally remain.

COST CONSIDERATIONS AND COMPETING TECHNOLOGY

The superconducting element in the concepts shown in Figure 3(b)-(d) is essentially only a switch that commutates the fault current to the limiting impedance. Thus, the large energies associated with the limiting action are handled by the shunt, which causes the shunt to become large and expensive. In a study of a transmission system SCFCL,³ the shunt resistor was found to account for about half the total SCFCL cost.

Consequently, the capital cost of the SCFCL can be reduced significantly if the shunt impedance can be avoided. To make the shuntless concept of Figure 3(a) technically feasible, the fault current must be limited to a small fraction of the nominal load current, and the reset time will probably be at least on the order of seconds. For some applications, as for example in the protection of underground transmission cables, long reset times may, however, be fully acceptable.

Other factors with great impact on the capital cost of an SCFCL include the need for an external trigger and the need to install capacitors across the device to reduce overvoltages.

Competing technology to the SCFCL exists, at least at the distribution system level. The feasibility of using gate turn-off thyristors to commutate the fault current to a limiting shunt has recently been demonstrated.^{1,16} Furthermore, a novel and inexpensive arc runner scheme for fault-current limiting has been tested.¹⁷ These and other concepts create strict cost and reliability requirements that an SCFCL must meet to be competitive. For example, the thyristors that essentially have the same function as the superconductor cost around \$40,000 (U.S.)¹ for a three-phase

FCL rated for the example distribution system. The losses in this device are about 0.05% of the throughput power; therefore, the refrigeration costs of an SCFCL should not exceed this value.

The extent to which these FCL schemes can be scaled up to high-power transmission systems is unclear.

CONCLUSIONS

The following conclusions were drawn on the basis of this work:

- Thorough cost/benefit analyses of FCLs are lacking, but surveys among U.S. utilities indicate that the price the utilities are willing to pay for an FCL is, at most, a few times the price of a circuit breaker of corresponding rating.
- The energy management in an SCFCL is a critical but often ignored issue.
- Although using an air-inductor (coil) as the limiting element avoids problems associated with energy dissipation during faults, such devices usually require a resistive, triggering element; energy dissipation within this element will still be a problem.
- Use of either a resistive or an inductive shunt across a resistive superconducting element adds complexity and cost to an SCFCL while providing little, if any, benefit.
- The most feasible SCFCL concept appears to be an in-line, resistive device. By choosing the resistance to provide a specified temperature rise, one can have a relatively compact design.
- The refrigerator operating cost may be reduced by a factor of up to 25 and the refrigerator capital cost by a factor of up to 10 for an SCFCL operating at 77 K, compared with a device operating at 4 K.
- The several orders of magnitude greater heat capacity of HTSCs, compared with LTSCs, improves the stability of the superconductor but makes switching to the normal state slow and difficult.
- A high critical current density, probably at least 10^5 A/cm², will likely be required to achieve adequate switching speed and an acceptable superconductor volume.
- HTSC wire of sufficient length is not yet available, and information about switching in HTSCs is limited. Therefore, SCFCLs using HTSCs are unlikely to be available in the near term.

The results presented in this paper are based upon work done under the International Energy Agency's (IEA's) Implementing Agreement for a Cooperative Programme for Assessing the Impacts of High-Temperature Superconductivity on the Electric Power Sector. This work was supported, in part, by the U.S. Department of Energy, Assistant Secretary for Conservation and Renewable Energy,

under contract W-31-109-Eng-38, as well as by the following participating countries: Canada, Denmark, Finland, Germany, Italy, Japan, the Netherlands, Norway, Sweden, Switzerland, Turkey, and the United Kingdom. One of the authors (M.R.) gratefully acknowledges partial support from the Royal Norwegian Council for Scientific and Industrial Research.

REFERENCES

1. Study of Fault-Current-Limiting Techniques, EPRI EL-6903, 1990.
2. Fault Current Limiters — Basic Concepts and Associated Technologies, EPRI EL-6275, 1989.
3. Superconducting Fault-Current Limiter, U.S. Department of Energy DOE/ET/29063-1, 1982.
4. Raju, B.P., Parton, K.C., and Bartram, T.C., "A Current Limiting Device Using Superconducting D.C. Bias — Applications and Prospects," IEEE PES Winter Meeting, Paper no. 82 WM 098-2, 1982.
5. Thuries, E., Pham, V.D., Laumond, Y., Verhaege, T., Fevrier, A., Collet, M., and Bekhaled, M., "Towards the Superconducting Fault Current Limiter," IEEE Transactions on Power Delivery, 6, 801-808, 1991.
6. Hara, T., Okuma, T., Yamamoto, T., Ito, D., Tasaki, K., Tsurunaga, K., "Development of a New 6.6-kV/1500-A Class Superconducting Fault Current Limiter for Electric Power Systems," IEEE Transactions on Magnetics, 28(1), 438-441, 1992.
7. Superconducting Fault Current Limiter, EPRI EL-329, 1976.
8. Gray, K.E., and Fowler, D.E., "A Superconducting Fault-Current Limiter," J. Appl. Phys., 49, 2546-2550, 1978.
9. Giese, R.F., and Runde, M., Fault-Current Limiters, prepared for the participating signatories of the International Energy Agency by Argonne National Laboratory, Jan. 1992.
10. Effects of Reduced Fault Duration Upon Power-System Components, EPRI EL-2772, 1982.
11. Damstra, G.C., Greenwood, A., Sabot, A., and Schramm, H.-H., "Superconducting Technology for Current Limiters and Switchgear," CIGRE, 1990.
12. Bashkurov, Y.A., Fleishman, L.S., Patsayeva, T.Y., Sobolev, A.N., and Vdovin, A.B., "Current-Limiting Reactor Based on High-T_c Superconductors," IEEE Transactions on Magnetics, 27, 1089-1092, 1991.
13. Bean, C.P., "Magnetization of Hard Superconductors," Phys. Rev. Lett., 8, 250-253, 1962.
14. Wilson, M.N., Superconducting Magnets, Oxford, U.K.: Clarendon Press, 1983.
15. Strobridge, T.R., "Cryogenic Refrigerators — An Updated Study," NBS Technical Note, 1976.
16. Slade, P.G., Wu, J.L., Stacey, E.J., Stubler, W.F., Voshall, R.E., Bonk, J.J., Porter, J., and Hong, L., "The Utility Requirements for a Distribution Fault Current Limiter," IEEE Transactions on Power Delivery (in press).
17. Engelman, N., Schreurs, E., and Drugge, B., "Field Test Results for a Multi-shot 12.47 kV Fault Current Limiter," IEEE Transactions on Power Delivery, 6, 1081-1087, 1991.

END

**DATE
FILMED**

6 / 11 / 93