DOE GRANT #DE-FG06-90ER54095

Formation and Sustainment of a Very
Low Aspect Ratio Tokamak Using
Coaxial Helicity Injection
(the Helicity Injected Torus [HIT]
Experiment)

Progress Report No. 2

February 1, 1991- January 31, 1992

T.R. Jarboe and B.A. Nelson
University of Washington
Seattle, Washington

UWAERP/35

NOTICE

This report was prepared as an account of work sponsored by the United States Government. Neither the United States nor the United States Department of Energy, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness or usefulness of any information, apparatus, product or process disclosed, or represents that its use would not infringe privately owned rights.

MASTER

88
DOE/ER/54095-2 DE-FG06-90ER54095-2

DOE GRANT #DE-FG06-90ER54095

Formation and Sustainment of a very
Low Aspect Ratio Tokamak using
Coaxial Helicity Injection
(the Helicity Injected Torus [HIT]
Experiment)

Progress Report No. 2

February 1, 1991 – January 31, 1992

T. R. Jarboe and B. A. Nelson
University of Washington
Seattle, Washington

Contents

1	Introduction and Summary	6
1.1	Program Plan	6
1.2	Status of the Experiment	6
1.2.1	Preliminary Data and Interpretation	7
1.2.2	Diagnostic Set	7
1.2.3	Vacuum Vessel and Pumping System	7
1.2.4	Helicity Source and Power Supplies	8
1.2.5	Toroidal Field Coil and Power Supply	8
1.2.6	Data Acquisition System	8
1.2.7	Collaboration with General Atomics	9
1.3	Personnel	9
1.4	Papers and Presentations	10
2	Preliminary Data and Interpretation	11
2.1	Experimental Results	11
2.2	Model	12
2.2.1	Model and Data Comparison	12
3	Diagnostic Systems	17
3.1	Rogowski Loops	17
3.1.1	Toroidal Plasma Current Partial Rogowski	17
3.1.2	Helicity Source and Insulator End Rogowskis	17
3.2	Magnetic Field Probes	18
3.2.1	Internal Magnetic Field Probes	18
3.2.2	Surface Magnetic Field Probes	18
3.3	Flux Loops	19
3.4	VUV Spectroscopy	19
3.5	Voltage Dividers	19
3.6	Framing Camera Photography	19
3.7	Laser Interferometry	19
4	Vacuum Vessel and Pumping System	23
4.1	Vacuum Vessel for Outer Conducting Shell	23
4.2	Pumping System	23
4.3	Vacuum Control System	24

4.4	Ti Gettering	24
4.5	Gas Delivery System	24
5	Helicity Source and Power Supply	26
5.1	The Helicity Source	26
5.1.1	Outer Conducting Shell	26
5.1.2	Inner Conducting Shell	26
5.2	Helicity Source Power Supply System	26
5.2.1	PI Bank	27
5.2.2	Formation Bank	27
5.2.3	Sustainment Bank	27
5.3	Safety and Interlock Systems	27
6	Toroidal Field Coil and Power Supply	33
6.1	Toroidal Field Coil	33
6.2	Toroidal Field Coil Capacitor Bank	33
7	Data Acquisition System	37
7.1	Fourth Floor Computer System	37
7.2	Avoidance of Ground Loop Signal Interference	37
7.3	Programmable Logic Controller	37
8	HIT Program Collaboration with General Atomics	39
8.1	Advanced Divertor Experiment on DIII-D	39
8.2	GA Numerical Support of the HIT Project	39
A	Contributed Abstracts	41
A.1	Thirty-Second American Physical Society Division of Plasma Physics Meeting	41
A.1.1	Hardware and Experimental Plan	41
A.1.2	Diagnostics	42
B	Taylor-State Stretch Current Model	43
B.1	Solution of Magnetic fields	43
B.2	Determination of λ	45
B.3	X-point	45
B.4	Determination of I_{tf}	45
B.5	Results	46

C Outside Safety Report

49

List of Figures

1	Formation bank and helicity source current time waveforms. .	13
2	B_z radial profiles.	14
3	Conservation of helicity in HIT.	15
4	Helicity source stretch current model and data.	16
5	Schematic layout of HIT diagnostics.	20
6	Schematic diagram of surface magnetic field probes.	21
7	Surface magnetic field probe array locations.	22
8	Vacuum vessel for HIT experiment with conducting outer shell.	25
9	Schematic diagram of the preionization bank.	29
10	Preionization, formation, and sustainment bank waveforms. . .	30
11	Schematic diagram of the formation bank.	31
12	Schematic diagram of the sustainment bank.	32
13	Toroidal field coil and winding supports.	34
14	Electrical schematic of the toroidal field coil capacitor bank. .	35
15	Toroidal field coil waveform.	36
16	Geometry for Taylor-state stretch current model.	47
17	Contours used for Green's Theorem.	48

1 Introduction and Summary

This is the second Progress Report on the Helicity Injected Tokamak (HIT) at the University of Washington, Seattle, DOE Grant #DE-FG06-90ER54095. This report covers the period of February 1, 1991 through January 31, 1992.

1.1 Program Plan

Preliminary experiments to characterize the helicity source have been performed. Initial results show good agreement between data and a simplified model.

The construction and installation of the outer conducting shell and the vacuum vessel are nearing completion.

1.2 Status of the Experiment

In the following sections we will detail the progress of the HIT experiment construction, including the following components:

- Preliminary Data and Interpretation
- Diagnostic Systems
- Vacuum Vessel and Pumping System
- Helicity Source and Power Supplies
- Toroidal Field Coil and Power Supply
- Data Acquisition System
- Collaboration with General Atomics

with a brief summary given below.

1.2.1 Preliminary Data and Interpretation

The first plasma in HIT was achieved in April 1991. After an initial period of orchestrating and tuning the various operating instruments, helicity source characterization experiments were performed. Initial results of these experiments show the source to behave as a constant current load, in agreement with a Taylor-state source model. Preliminary helicity balance calculations have been made, also with good agreement.

Measurements of the source currents, internal magnetics, and plasma midplane VUV spectra have been made. These measurements indicate a thin plasma near the central column, lasting up to 5 ms.

1.2.2 Diagnostic Set

Each capacitor bank current is measured by a Rogowski coil. Rogowski coils are around both outer copper electrodes, allowing measurement of plasma current from inner to outer electrode at each end. A partial Rogowski measures part of the toroidal plasma current. Nine internal magnetic field probes are spaced along a radius at the chamber midplane. A VUV spectrometer system is aimed at the midplane and has been used to generate spectra photographs. A red and IR laser interferometry system is being assembled

1.2.3 Vacuum Vessel and Pumping System

The vacuum system is at a mature and reliable level. Base vacuums in the low 10^{-7} Torr range are routinely achieved. The vacuum control system has been completed, tested, and installed. An RGA system is used for impurity control and leak checking, and an improved system is on order.

Presently, a single Ti getter is being installed on the vacuum vessel.

A gas delivery system has been constructed to allow fast flow and fill of the experiment with ultra-pure H_2 . Air-actuated piston valves mounted close to the vacuum vessel are used to provide gas filling. The gas-fill manifold also allows He fill for discharge cleaning, and dry N_2 fill for bringing the machine up to air.

1.2.4 Helicity Source and Power Supplies

The helicity sources are presently finishing up characterization experiments. They have been hi-potted to 10 kV, and are typically run in the 1 - 7.5 kV range.

To achieve better plasma break-down, formation, and sustainment, we have implemented a three-bank system of helicity source power supplies. A 7.5 kV 100 μ F pre-ionization (PI) bank breaks down the gas. A critically damped 3.3 mF 2 kV formation bank helps push the bias flux out of the source region and prevents reversal of the PI bank. The sustainment bank (up to 0.36 F at 900 V) then drives the current for the final plasma configuration.

The outer conducting shell is constructed and surface probes (see Section 3.2.2) are being installed.

Fiber optic triggers have been installed on all banks with electrical cross-talk eliminated.

Ivars Henins of Los Alamos National Laboratory (LANL) conducted an outside safety inspection of the HIT experiment. His recommendations have been taken and are on file.

1.2.5 Toroidal Field Coil and Power Supply

The toroidal field (TF) coil and power supply have been completed and operated at up to 600 kA-turns. The TF power supply has two resistive energy dump safety systems and a hard-short dump included in the interlock system.

1.2.6 Data Acquisition System

We have been routinely using the MIT MDS/IDL data acquisition system. The machine is easily operated by two personnel, with post-shot graphical display of data waveforms. CAMAC-based digitizers are housed in electromagnetically shielded racks, with vigorous attention given to the avoidance of ground loops.

A GE-Fanuc programmable logic controller (PLC) arbitrates the logic of the HIT firing sequence. The HIT dump, charging, and firing system can be operated manually, and the PLC acts as a reproducible "button pusher". The PLC is programmed from a PC (with commercial software), and we are writing software to monitor and control the PLC during the firing sequence.

1.2.7 Collaboration with General Atomics

Prof. Jarboe has continued to participate in the Advanced Divertor experiment on DIII-D at General Atomics (GA). He has maintained close contact with Drs. Mahdavi, Stambaugh, and Schaffer of GA, and has attended workshops at GA.

Prof. Nelson is adapting the GA EFIT equilibrium solving code to run on in-house computers. Dr. Emilia Solano of the University of Texas-Austin has converted all the proprietary routine calls to public domain. She has made this code available to us. We are planning to incorporate HIT data into the EFIT calculations and solving for an equilibrium between discharges. EFIT's author, Dr. Lao of GA, has also helped us with various aspects of the code.

Mr. Orvis spent the summer of 1991 at GA for his DOE Fusion Fellowship practicum. He assisted Dr. Schaffer with writing front-end codes to analyze advanced-divertor data, using EFIT, the 'ENERGY' energy code, and the 'ONETWO' transport codes.

1.3 Personnel

The HIT experimental group is lead by Prof. Thomas R. Jarboe. Prof. Glen A. Wurden supervises diagnostic equipment acquired from Los Alamos National Laboratory. Prof. Brian A. Nelson assists in supervising students, and oversees the data acquisition system. Research Engineer Daniel E. Lotz is responsible for much of the mechanical design of the HIT experimental apparatus, the toroidal field coil power supply, and is the building experimental safety coordinator. Engineering Technician John A. Rogers oversees modifications of the sustainment bank power supply and the interlock system. Instrument Maker Dennis Peterson oversees the machining of the experimental components.

The graduate students have been tentatively identified with their research areas. Adam K. Martin (Physics) will study source physics and use internal magnetic field probes to determine the internal field structure and compare with the EFIT equilibrium code from GA. David J. Orvis (Nuc. Engr., DOE Fusion Fellow) will construct and install surface magnetic field probes in the thick copper flux conservers, study the mode structure of relaxation and correlate these measurements with EFIT, checking with internal probes. Chad L. Painter (Nuc. Engr.) is conducting the initial survey of the VUV

spectrum in HIT. LiYong Zhou (Nuc. Engr.) is assembling the first interferometer ($3.391\text{ }\mu\text{m}$) system and will then assemble the Thomson scattering diagnostic and study energy confinement. JianPing Xie (Nuc. Engr.) is the newest student on HIT, and will be working with Prof. Wurden in assembling the FIR polarimeter/interferometer.

1.4 Papers and Presentations

During the present reporting period we have presented the following papers at the Thirty-third Annual Meeting of the Division of Plasma Physics, American Physical Society, – October 1991, Tampa, FL. (Conference abstracts included in Appendix A.1).

- D. Orvis, T. R. Jarboe, D. E. Lotz, A. Martin, B. A. Nelson, C. Painter, and J. A. Rogers, The Helicity Injected Tokamak Experiment, *Bulletin of the American Physical Society* **36**, 2442 (1991).
- A. Martin, T. R. Jarboe, D. E. Lotz, B. A. Nelson, D. Orvis, C. Painter, and J. A. Rogers, The Helicity Injected Tokamak Experiment, *Bulletin of the American Physical Society* **36**, 2442 (1991).

We have also presented seminars about HIT.

- B. A. Nelson, The Helicity Injected Tokamak, Presentation to the Plasma Physics Seminar, University of Wisconsin–Madison, Oct. 1991.

2 Preliminary Data and Interpretation

Results of the initial helicity source characterization experiments have shown that the source behaves like a constant-current load for the sustainment bank. Initial data measurements show good agreement with a simplified Taylor-state model.

The radial magnetic field profile shows reversal of the B_z field about 10 cm from the central column.

Initial calculations show conservation of helicity.

Details of the various power supply banks and diagnostics are given in following Sections.

2.1 Experimental Results

The sequence of a plasma discharge is as follows: The bias coil is operated DC 2 seconds before the discharge, allowing the flux to diffuse into all the metal. At a point defined as $t = 0$, the pre-ionization (PI) bank (7 kV) is triggered, breaking down the H_2 gas puffed in at $t = -4.5$ ms. At $t = 25 \mu s$, the formation bank (2 kV) is triggered, pushing the bias flux out of the helicity source into the 'equilibrium region'. The sustainment bank (0.9 kV) then drives current along these flux lines. Current can also flow along field lines between the central column and the wall, and across the insulator. We have been concentrating on conducting a current inventory for various bias coil and bank operating points.

Figure 1 shows time waveforms of the helicity source and formation bank currents. The helicity source current rises with the PI bank current (not shown) then reaches a point where it levels off, (the 'flat-top' region) even while the formation bank current is changing. As the formation bank current decreases from its peak, the helicity source current remains level until both reach nearly the same value. The helicity source current then again tracks the formation bank current.

Figure 2 shows the radial magnetic field profile for several times during a shot. The B_z reversal point tended to increase during the shot.

Figure 3 shows an initial calculation of helicity balance. The applied electrode voltage (helicity injection rate) is integrated and compared with the plasma current (total helicity), taking into account the helicity decay

rate and a scale factor for a Taylor state equilibrium, respectively. Thus the helicity injected is in good agreement with the total plasma helicity.

2.2 Model

A simplified model of the physics is given in its entirety in Appendix B. This model considers a Taylor state plasma ($\nabla \times \mathbf{B} = \lambda \mathbf{B}$) in the region between two infinitely long coaxial cylinders. We assume the bias flux is flattened against each wall, and solve for the current necessary to hold it there. We call this value the 'stretch' current, *viz.* the value necessary to stretch the flux out of the helicity source.

We represent our calculations as shown in Fig. 4. A family of stretch current values (I_{st}) are graphed *vs.* toroidal field coil current values (I_{tf}) for various values of bias coil current (I_b). The behaviour to note is that I_{st} decreases for increasing values of I_{tf} .

2.2.1 Model and Data Comparison

Also plotted in Fig. 4 are the helicity source flat-top currents *vs.* the toroidal field coil current for several bias coil current values. The good agreement bodes well for operation at higher toroidal field current values.

Shot 671

Figure 1: Formation bank and helicity source current time waveforms. The PI bank current (not shown) ionizes the gas and drives current through the helicity source, then the formation bank pushes the bias flux out. After the flux is pushed out, (at $t \sim 90 \mu\text{s}$) the helicity source acts as a constant-current load until the formation bank current decreases. (The sustainment bank was not used for this discharge.)

Figure 2: Radial profiles of B_z for three times. Note that the B_z reversal point moves outward with time.

Figure 3: Helicity balance calculations. K injected is integrated from the helicity source gap voltage. K total is calculated from the toroidal current, correcting for helicity decay.

Figure 4: Comparison of coaxial Taylor-state stretch current model with data. The helicity source stretch current, I_{hs} , required for a Taylor-state equilibrium decreases with increasing toroidal field coil current, I_{tf} , for a given bias coil current, I_{bias} . Experimental data points are plotted (using the same line style as the corresponding model lines) over the model calculations. The data shown the reduced I_{hs} required for larger I_{tf} .

3 Diagnostic Systems

HIT diagnostics presently consist of Rogowski loops, magnetic field probes, flux loops, VUV spectroscopy, voltage dividers, framing camera photography, and laser interferometry. A schematic view of diagnostic locations is given in Fig. 5.

3.1 Rogowski Loops

Rogowski loops are used to measure (part of) the toroidal plasma current and the current between the inner and outer electrodes at each end. These monitors will be described below. Rogowski coils also monitor the current supplied by each capacitor bank system, *viz.* the TF bank, the PI bank, the formation bank, and the sustainment bank.

3.1.1 Toroidal Plasma Current Partial Rogowski

A partial Rogowski loop, shown in Fig. 5, measures a lower limit of the toroidal plasma current. It is constructed of # 30 wire-wrap wire tightly wound around an RG-8/U cable (with the outer insulator and shield removed). There are approximately 20 turns/cm, giving a sensitivity of approximately 9.4 kA/V. The coil is housed in a 0.9 mm thick 1.26 cm O.D. stainless steel sheath. This Rogowski is 2.13 m in length, covering roughly 73 % of the plasma perimeter. To correct this lower limit of toroidal plasma current, the internal magnetic field probes (see Section 3.2.1) are used to estimate B_z at the inner conductor. This value of field is assumed constant and integrated along the portion of the perimeter not enclosed by the partial Rogowski.

3.1.2 Helicity Source and Insulator End Rogowskis

One set of split rogowski pairs is located around each outer copper electrode, also shown in Fig. 5. Two-piece split Rogowskis are used for ease of placement and also to monitor the azimuthal symmetry of the current in each end. So far, no azimuthal asymmetries of current have been seen.

In this initial experiment, several plasma current paths exist. Monitoring each bank current and the current from each of these Rogowskis allows us to

determine these various currents.

3.2 Magnetic Field Probes

We are implementing both internal and surface magnetic field probes in HIT. Presently we have installed a single radial array of internal magnetic field probes. More internal magnetic field probes are under construction, and will be mounted in the source regions and used during the helicity source characterization experiment. Surface probes are presently being constructed and installed in the copper flux conservers.

3.2.1 Internal Magnetic Field Probes

Internal magnetic field probes are constructed of # 32 magnet wire wound on machined 4.3 mm by 4.3 mm lucite forms. Each probe is a nearly orthogonal triplet, each winding about 20 turns with about 20 cm²-turns area. Sensitivities are in the 3 V/T range. The probes are electrostatically shielded with 25 μ m thick stainless steel, and encased in a 1-1.2 cm OD quartz sheath. The signals are either passively or actively integrated ($RC = 10^{-3}$ s).

For preliminary experiments, the probes are calibrated by physical measurements and calculations. A probe calibrator and calibration routine are being developed.

3.2.2 Surface Magnetic Field Probes

Surface magnetic field probes are constructed of small winding triplets, Fig. 6, consisting of # 32 magnet wire on machined KLF forms. Multiple probe triplets will be mounted in arrays both on the inner (14 probes) or outer (22 probes) flux conserver, Fig. 7.

On the outer flux conserver, (Fig. 6), the probe triplet is inserted into an inconel case mounted on the outside of the outer flux conserver wall. Swagelok fittings will be used for the vacuum seal of the 1/8" stainless steel tube shield encasing the probe leads out into the lab area.

On the inner flux conserver the probe triplet is mounted in an inconel case mounted from the inside of the flux conserver pipe, similar to that shown in Fig. 6. Vacuum seals are provided by inconel discs hard-soldered over through-holes in the inner flux conserver. The probe leads come out along

the PVC toroidal field coil winding matrix, and will feed into a electrically floating diagnostic rack, tied to the inner flux conserver potential.

3.3 Flux Loops

Two flux loops of stripped-back RG-58/U cable, mounted externally to the vacuum vessel are used to measure the toroidal flux, and the poloidal flux diffusing through the chamber wall.

3.4 VUV Spectroscopy

A 1-m VUV spectrometer is used to measure the plasma light spectrum. Two gratings are available, 600 and 1200 rules/mm which resolve lines in the 2000-4500 nm and 500-1200 nm range respectively. These lines are imaged onto photographic film.

3.5 Voltage Dividers

Voltage dividers are used to monitor the gap voltage at both the helicity source and insulator ends. Each node of the sensing resistor is returned *via* twisted pair to the diagnostic racks and fed into differential amplifiers.

3.6 Framing Camera Photography

A model Imacon 790 framing camera is used to photograph either the helicity source or insulator end electrodes. This lets us diagnose success in suppressing insulator end current.

3.7 Laser Interferometry

An IR He-Ne laser ($\lambda = 3.391 \mu\text{m}$) is used in a heterodyne quadrature Mach-Zender interferometer system. One double-pass chord travels through a minimum tangential radius of 18 cm (7 cm from the inner conductor). This system is presently under construction. As we progress with particle control, we expect to change to a $10.6 \mu\text{m}$ CO₂ laser interferometer, then to the $180 \mu\text{m}$ FIR interferometer.

Figure 5: Layout of internal diagnostics on HIT. Internal probes are in quartz jackets where they encounter plasma. All Rogowski coils are in stainless steel jackets. The "Tee" internal probe allows an axial profile measurement during a discharge, and ranges from the central column to the outer wall.

Figure 6: Surface magnetic field probe construction. Toroidal and poloidal coils are wound on the lower probe form. The 'radial' coil is wound on the upper probe form. The probe is at atmospheric pressure, with vacuum seals provided by Swagelok connectors.

Figure 7: Location of surface magnetic field probe arrays. Three probes are in the helicity source region, and fifteen encompass the equilibrium region. This array pattern occurs at two diametrically opposed azimuthal locations.

4 Vacuum Vessel and Pumping System

The vacuum vessel used in the helicity source characterization experiments is described in the previous Progress Report.

The vacuum vessel for use with the outer copper flux conserver has been modified, and is presently awaiting the construction of the end flanges. In the interest of vacuum cleanliness we have decided that all metal vacuum surfaces (other than the copper flux conservers) be stainless steel, and also all vacuum seals used on this vessel must either be metal or differentially pumped double Viton O-rings, bakeable to 150° C.

The vacuum control system has been completed and has proved reliable.

The pumping system is presently being augmented by Ti gettering.

4.1 Vacuum Vessel for Outer Conducting Shell

A vacuum vessel, Fig. 8, has been modified by MDC Vacuum Engineering to allow midplane access through the 5 cm gap in the outer conducting shell. The port layout allows complete through-the-vessel optical access through two sets of 10 chords, converging at a point between the poloidal current posts connecting the outer conducting shell halves.

We are presently awaiting bids on the design of the new stainless steel end flanges. The helicity source end flange is quite similar to the present aluminum flange, with a few conflat ports added. The insulator end flange, still axisymmetric, has an azimuthal insulating break added. This will allow us the flexibility to establish a different potential on the insulator end outer flux conserver, if deemed necessary. All end flange sealing surfaces are designed to be compatible with metal seals.

4.2 Pumping System

The pumping system was described in the previous Progress Report, and is now routinely operated at a base vacuum of mid 10^{-7} Torr.

An RGA head purchased to operate with a previously existing controller proved to be insensitive to small-scale leaks. A more sensitive RGA system is presently on order.

4.3 Vacuum Control System

The vacuum interlock and control system, which provides procedural logic enforcement is fully interlocked, allowing operation of valves only when proper conditions exist.

4.4 Ti Gettering

We are presently installing one Ti sublimation getter to provide additional pumping. The new vessel will allow up to three getters to sublime onto the plasma side of the flux conservers. A getter blind is being designed to prevent Ti obscuration of optical ports. Additional getters may be installed to sublime between the outer flux conserver and the vessel wall if necessary.

4.5 Gas Delivery System

The gas delivery system allows fast flow and fill of the experiment with H_2 passed through a palladium purifier. Solenoid valves, located at field nulls between the TF coil returns, actuate piston valves closely mounted to the vacuum vessel. The system is reliable and reproducible, producing flow rates filling the chamber to 1-2 mTorr in a few milliseconds.

The gas-fill manifold also allows He fill for discharge cleaning, and dry N_2 fill for bringing the machine up to air.

5 Helicity Source and Power Supply

The complete copper flux conserver/helicity source system is nearing completion of fabrication, and is awaiting the modification of the end flanges for assembly.

The duty of the helicity source power supply system is divided into three functions; ionization of the fill gas, pushing the bias flux into the flux conserver region (*formation* of the outer flux surfaces), and sustainment of helicity injection current drive. Each function is assigned a separate power supply, each tailored to the voltage and time scale necessary.

5.1 The Helicity Source

A schematic view and details of the helicity source were given in the previous Progress Report, and the present status of the inner and outer conducting shells is given below.

5.1.1 Outer Conducting Shell

The 1 cm thick copper two-piece outer conducting shell is fabricated. Flanges are welded to each section, with 256 holes drilled for the 64 poloidal image current connections. The inner surface will be tungsten sprayed. Each shell section will bolt to the helicity source or insulator region copper piece.

Ten holes for surface probes are located in each shell half, Fig. 7. Two holes for surface probes will be drilled in the helicity source end copper piece.

5.1.2 Inner Conducting Shell

The 1.26 cm thick copper inner conducting shell is constructed. The central copper region will be tungsten sprayed, with the inconel-disc probe covers masked from the tungsten spray.

5.2 Helicity Source Power Supply System

The helicity source power supply system consists of three capacitor banks, the preionization (PI), the formation, and the sustainment. Each bank size (characteristic time) and voltage is tailored for its function. This delegation of bank duties adds considerable flexibility in operation.

5.2.1 PI Bank

The PI bank, Fig. 9, provides the fast high-voltage required to ionize the fill gas. It consists of a single 100 μF capacitor, operable at up to 7.5 kV. Six RG-8/U cables lead from the size-A ignitron housing to the insulator end 'hot-plate'. The central column has an inductance of approximately $L_{cc} \sim 0.5 \mu\text{F}$, which isolates this bank from the formation and sustainment banks on its fast time scale.

A typical plasma discharge, with the PI charged to 6 kV, has 40-60 kA of PI bank current, with a quarter-period rise time of $\tau_{1/4} \sim 15 \mu\text{s}$, Fig. 10-a.

5.2.2 Formation Bank

The formation bank, Fig. 11, is a medium energy critically-damped bank that provides energy to move the bias flux into the plasma equilibrium region. Six RG-8/U cables connect the 3 mF, 2 kV formation bank A-size ignitron output to the helicity source end hot-plate. The resistors prevent the voltage applied by the formation bank from reversing. The formation bank is fired soon after the PI bank, to prevent the PI bank from applying a reversed voltage too, Fig. 10-b. (We wish to keep $\mathbf{E} \times \mathbf{B}$ always pointing out of the helicity source and into the insulator.)

5.2.3 Sustainment Bank

The sustainment bank, Fig. 12, (0.36 F at 900 V) has been slightly modified since the last Progress Report. Fast and slow energy dump systems have been installed, and new charging supplies have been acquired. Improvements in the fiber-optically isolated triggering system have eliminated all electrical cross-talk with the other bank systems.

A current waveform of the sustainment bank is given in Fig. 10-c.

5.3 Safety and Interlock Systems

Obviously, safety in the operation of all capacitors banks is of prime importance. Several levels of safety have been integrated into each bank and tied into the interlock system. Safety procedures have been documented and safety seminars are held periodically.

Ivars Henins of LANL conducted an outside safety review of the HIT experiment, suggesting several additions to provide more safety. This report is included as Appendix C.

A 'room-sweep' button has been added to the interlock system. After the interlocks have been interrupted, *e.g.* opening the lab doors, the system won't operate until the room-sweep button has been pressed. It is located at a point in the lab where the entire room can be surveyed. This corrects the possibility of allowing charging after someone opens the lab door, interrupting the interlocks, going inside and shutting the door, unseen to the operators. The operators must go in and press the room-sweep button, allowing them to see the miscreant.

For personnel (and bank) safety we have also installed interlocked grounding rods. If a bank needs to be serviced, (after all the energy dumps have been activated) an extra level of safety is added by manually inserting a grounding rod across the capacitor terminals. Each bank has a manual grounding rod residing on an interlocked hook. When the grounding rod is removed from the hook, the interlock system is interrupted. Thus the bank cannot be charged while it is serviced, *and* the bank cannot be charged if the grounding rod is left across its terminals.

Figure 9: Schematic diagram of the preionization bank. The load is the insulator end gap.

Figure 10: Preionization a), formation b), and sustainment c) bank waveforms. Each bank provides currents on different time scales.

Figure 11: Schematic diagram of the formation bank. The load is the helicity source end gap.

Figure 12: Schematic diagram of the sustainment bank. The bank was modified from the 2XII-B Flat Top Module electrolytic banks from LLNL.

6 Toroidal Field Coil and Power Supply

The toroidal field coil consists of forty turns of 250,000 circular mil cable threaded through the inner conducting shell and through ten return bundles external to the vacuum vessel. The toroidal field coil capacitor bank is designed to provide up to 25 kA for a total value of 1 MA-turns.

6.1 Toroidal Field Coil

The toroidal field coil, Fig. 13, has 34 turns wound through a hexagonal matrix of PVC tubes, located inside the inner conducting shell. Six brass straps with cable clamps on the ends are located on each face of the matrix, providing cable splices, breaking the coil into reduced length threads.

The cables return in ten bundles, shaped to produce only tension forces. Phenolic, aluminum tube, and plywood supports are used to hold the return bundles in place, Fig. 13.

6.2 Toroidal Field Coil Capacitor Bank

The toroidal field coil power supply is a $24 \times 550 \mu\text{F}$, 11 kV capacitor bank, D-size ignitron switched, and crowbarred with diode stacks, Fig. 14. A resistor/capacitor combination is mounted across the cable feeds at the bank end to eliminate transients that can develop if the helicity source banks should fire before the TF bank.

Safety is provided by fuses, and two sets of dump resistors, carbon and water. For safety while servicing the bank, pneumatically-activated shorting balls are installed across each capacitor pair. An interlocked shorting rod is available as well.

The toroidal field coil bank has been tested at up to 600 kA, Fig. 15. The quarter period rise time is $\tau_{1/4} = 7.5 \text{ ms}$, and the crowbar decay time is $\tau_{L/R} = 47 \text{ ms}$. This corresponds to coil inductance and resistance of $L_{TF} = 1.73 \text{ mH}$ and $R_{TF} = 36.7 \text{ m}\Omega$.

Thicker-walled aluminum tube returns are being installed to allow operation at the design value of 1 MA-turns.

Figure 13: Toroidal field coil and winding supports. The coil is held in a shape designed to produce only tension forces along the winding cables.

Toroidal Field Coil Bank

Figure 14: Electrical schematic of the toroidal field coil capacitor bank. It is designed to provide up to 1 MA-turns through the toroidal field coil.

Shot 1158

Figure 15: Toroidal field coil waveform. The feature near $t = 0$ is the PI bank breaking down the plasma and inductively affecting the TF coil.

7 Data Acquisition System

The HIT experiment data acquisition system shares resources with the Coaxial Slow Source (CSS) data acquisition system, also located on the fourth floor of the Aerospace and Energetics Research Laboratory.

Waveform digitizers for the HIT experiment have been purchased and acquired on loan. There are at present, more than 100 available channels, though we need more CAMAC crates and controllers to use them all.

7.1 Fourth Floor Computer System

The HIT VAXstation 3100, with a 650 MB hard disk and a 1.2 GB digital audio tape (DAT) mass storage drive, is VAXclustered to the CSS program's CTR VAXstation 3200. The CTR VAX is interfaced with a Kinetic Systems 2060 Serial Highway Driver, which can control up to 63 CAMAC crates. The serial highway is a combination of twisted pair and coaxial cable, and is planned to be replaced by fiber optic links.

The MIT Model Data System (MDS) is used on the CTR VAX, using the Interactive Data Language (IDL) program for data analysis and plotting.

7.2 Avoidance of Ground Loop Signal Interference

Extreme care in design of the data acquisition system minimizes the potential for ground loops on the HIT experiment. Cable runs are separated into two trays: one for data cables and one for power and control cables. Electromagnetically shielded racks are used in lieu of screen rooms, each with two 2.5 kVA, 126 dB isolation transformers.

A 'ground loop detector' is used to inductively drive an audio frequency current in the cable trays. The only place a current is driven is in a ground loop, which can then be detected with a small audio pick-up coil.

7.3 Programmable Logic Controller

The GE-Fanuc Model 90 Programmable Logic Controller (PLC) provides a very versatile way to charge and monitor the HIT experiment. All bank and dump systems are controlled and charged by the PLC. We are presently

writing software to select charge voltages and have the PC controlling the PLC display and verify charging cycles.

8 HIT Program Collaboration with General Atomics

The HIT program is fortunate to participate in a collaborative effort with General Atomics (GA) of San Diego, CA. The GA DIII-D tokamak group is one of the international fusion community's leading experimental programs.

The HIT program collaborates with GA on two levels: experimental participation of HIT personnel with the Advanced Divertor experiment on DIII-D, and GA numerical support of the HIT program.

8.1 Advanced Divertor Experiment on DIII-D

Prof. Jarboe directly participates with the GA DIII-D group (principals: Drs. Stambaugh, Mahdavi, and Schaffer) during their Advanced Divertor experiment. Prof. Jarboe also attends workshops and presents seminars at GA.

HIT graduate student David Orvis fulfilled his DOE Fusion Fellowship summer laboratory practicum by working on DIII-D in the summer of 1991. Mr. Orvis helped Dr. Schaffer analyze the loop-voltage drop seen during the helicity injection current drive experiments on DIII-D. Mr. Orvis ran the EFIT and the ENERGY codes and wrote front-end routines to use this output in the ONETWO transport code on the NERSC supercomputers.

8.2 GA Numerical Support of the HIT Project

Drs. Lao, Schaffer, and Stambaugh of GA have generously assisted Prof. Nelson with adapting the GA EFIT code for use on HIT. EFIT, widely used on DIII-D experiments, can solve the Grad-Shafranov equation with a conducting boundary and accepts experimental magnetic field and flux measurement data for use in equilibrium solving. The output can be directly input in a number of stability codes.

Dr. Solano of the IFS group at the University of Texas-Austin, replaced all proprietary code in EFIT with public domain routines. This not only allows code portability to a number of platforms, but also sped up execution. Dr. Solano has provided us with the code replacements, and they are presently being incorporated into our EFIT version, to allow execution on

the HIT VAX, with the goal of solving for experimental equilibriums between discharges.

We will enter the helicity source characterization experiment data into the EFIT code. The internal probe measurements of the helicity source characterization experiment will benchmark EFIT for HIT, to provide a reliable and powerful analysis tool for future HIT experimental conditions too hot for internal probes.

A Contributed Abstracts

A.1 Thirty-Second American Physical Society Division of Plasma Physics Meeting

A.1.1 Hardware and Experimental Plan

7P13 The Helicity Injected Tokamak Experiment, D. ORVIS, T. R. JARBOE, A. MARTIN, B. A. NELSON, C. PAINTER, AND J. A. ROGERS U. Washington^a—The Helicity Injected Tokamak (HIT) experiment proposes to use coaxial DC helicity injection to drive steady state toroidal current in a very low aspect ratio ($A = 1.5$) tokamak. HIT is nearing completion of construction and has begun helicity source characterization experiments. A low-ripple (10 return bundles) toroidal field coil operates at up to 0.8 MA-turns. Plasma equilibrium is provided by a closely-fitting 1 cm thick copper flux conserver (85 ms flux decay time). Helicity injection is provided by a 30×36 mF 900 V capacitor bank. Diagnostics include internal magnetic field probes, Rogowski loops, surface probes, a HeNe interferometer, a framing camera, and a VUV spectrometer, and are described in detail in the accompanying paper. A Thomson scattering system is being constructed. Data is stored and analyzed using a CAMAC/MDS/IDL data acquisition system. A PC-based programmable logic controller provides safety-interlocked bank charging and system control. Details of machine hardware and design, and the HIT program plan are presented.

^aWork supported by the U. S. Department of Energy.

A.1.2 Diagnostics

7R14 Diagnostics on the Helicity Injected Tokamak, A. MARTIN, T. R. JARBOE, B. A. NELSON, D. ORVIS, C. PAINTER, AND J. A. ROGERS, *University of Washington*^a—The Helicity Injected Tokamak (HIT) experiment tests coaxial DC helicity injection current drive on a low aspect ratio ($A = 1.5$) tokamak. Diagnostics for helicity source characterization experiments on HIT are described. They include a full array of internal 3D magnetic field probes and Rogowski loops to be used in conjunction with the General Atomics EFIT code to reconstruct the HIT equilibrium. The Rogowski loops will also be used to measure the toroidal plasma current and to monitor the helicity source currents. For use with the probes, active integrators with long integration times have been designed and constructed. Data analysis techniques will be described. In addition, we describe a framing camera for monitoring the helicity source, a visible spectrometer for surveying the plasma content, a VUV spectrometer, an interferometer, and an H_α detector. Surface magnetic field probe arrays on the flux conserver will also be described.

^aWork supported by the U. S. Department of Energy contract No. DE-FG06-90ER54905.

B Taylor-State Stretch Current Model

The following documentation details a solution for Taylor's state for the infinite coaxial geometry shown in Fig. 16. The calculation will find a relationship between the axial flux Ψ_g ; the toroidal field current, I_{tf} ; and the source current, I_{sc} .

B.1 Solution of Magnetic fields

The magnetic fields in Taylor's state are solutions to the equation

$$\nabla \times \mathbf{B} = \lambda \mathbf{B} \quad (1)$$

The magnetic fields may now be found in terms of I_{tf} and λ . Taking the cross product of both sides of Eq. 1 gives the following relation:

$$\nabla^2 \mathbf{B} + \lambda \mathbf{B} = 0 \quad (2)$$

By using the azimuthal and axial symmetry of the plasma and Gauss' law for the magnetic field, each component of Eq. 2 may be written as:

$$B_r = 0 \quad (3)$$

$$\frac{\partial^2 B_z}{\partial r^2} + \frac{1}{r} \frac{\partial B_z}{\partial r} + \lambda^2 B_z = 0 \quad (4)$$

$$\frac{\partial^2 B_\phi}{\partial r^2} + \frac{1}{r} \frac{\partial B_\phi}{\partial r} + \left(\lambda^2 - \frac{1}{r^2} \right) B_\phi = 0 \quad (5)$$

The solution to Eq. 5 is a linear combination of first order Bessel and Neumann functions:

$$B_\phi(r) = \alpha J_1(\lambda r) + \beta Y_1(\lambda r) \quad (6)$$

By setting B_ϕ equal to the vacuum field at the boundaries;

$$B_\phi(a) = \frac{\mu_0 I_{tf}}{2\pi a} \quad B_\phi(b) = \frac{\mu_0 I_{tf}}{2\pi b} \quad (7)$$

the coefficients α and β can be determined by Cramer's rule:

$$\alpha = \frac{\mu_0 I_{tf}}{2\pi D} \left(\frac{Y_1(\lambda b)}{a} - \frac{Y_1(\lambda a)}{b} \right) \quad (8)$$

$$\beta = \frac{\mu_0 I_{tf}}{2\pi D} \left(\frac{J_1(\lambda a)}{b} - \frac{J_1(\lambda b)}{a} \right) \quad (9)$$

$$D = J_1(\lambda a) Y_1(\lambda b) - J_1(\lambda b) Y_1(\lambda a) \quad (10)$$

Using Eq. 1, the axial magnetic field can now be determined:

$$(\nabla \times \mathbf{B})_z = \lambda B_z \quad (11)$$

$$\frac{1}{r} \frac{\partial (r B_\phi)}{\partial r} = \lambda B_z \quad (12)$$

Now substitute Eq. 6 into Eq. 12 and rearrange terms.

$$B_z = \alpha \left(\frac{J_1(\lambda r)}{\lambda r} + \frac{\partial J_1(\lambda r)}{\partial \lambda r} \right) + \beta \left(\frac{Y_1(\lambda r)}{\lambda r} + \frac{\partial Y_1(\lambda r)}{\partial \lambda r} \right) \quad (13)$$

Using the recursion identities for Bessel and Neumann functions, Eq. 13 simplifies to:

$$B_z(r) = \alpha J_0(\lambda r) + \beta Y_0(\lambda r) \quad (14)$$

To simplify calculations, I_{tf} is factored out of the coefficients.

$$\alpha' = \frac{\alpha}{I_{tf}} \quad \beta' = \frac{\beta}{I_{tf}} \quad (15)$$

$$B_\phi(r) = I_{tf} (\alpha' J_1(\lambda r) + \beta' Y_1(\lambda r)) \quad (16)$$

$$B_z(r) = I_{tf} (\alpha' J_0(\lambda r) + \beta' Y_0(\lambda r)) \quad (17)$$

B.2 Determination of λ

Using Ampere's law and Eq. 1, we obtain λ in terms of Ψ_g

$$I_{sc} = \int_a^x J_z 2\pi r dr = \int_a^x \frac{(\nabla \times \mathbf{B})_z}{\mu_0} 2\pi r dr \quad (18)$$

$$= \frac{\lambda}{\mu_0} \int_a^x B_z 2\pi r dr = \frac{\lambda}{\mu_0} \Psi_g \quad (19)$$

$$\lambda = \frac{\mu_0 I_{sc}}{\Psi_g} \quad (20)$$

B.3 X-point

The x-point is the radial value where B_z is 0, which can easily be determined on a computer once λ has been calculated. A value for I_{tf} is not needed to determine the x-point.

B.4 Determination of I_{tf}

Once the x-point is calculated, the calculation of I_{tf} follows by using Eq. 1 and employing Green's Theorem (see Fig. 17).

$$\Psi_g = \int_a^x B_z 2\pi r dr = \frac{1}{\lambda} \int_a^x (\nabla \times \mathbf{B})_z 2\pi r dr \quad (21)$$

$$= \frac{1}{\lambda} \int_A \nabla \times \mathbf{B} \cdot d\mathbf{A} = \frac{1}{\lambda} \oint \mathbf{B} \cdot d\boldsymbol{\ell} \quad (22)$$

$$= \frac{1}{\lambda} (B_\phi(x) 2\pi x - B_\phi(a) 2\pi a) \quad (23)$$

By rearranging terms and using Eq. 16, the following equation can be obtained:

$$I_{tf} = \frac{\lambda \Psi_g}{2\pi x (\alpha' J_1(\lambda x) + \beta' Y_1(\lambda x)) - 2\pi a (\alpha' J_1(\lambda a) + \beta' Y_1(\lambda a))} \quad (24)$$

B.5 Results

Figure 4 gives several plots of I_{sc} versus I_{tf} for various values of the bias current I_{bias} . The dimensions of the helicity source on HIT are used ($a = 0.11m$, $b = 0.16m$). The bias current determines the gun flux ($\Psi_g = 59 \times 10^{-6} \frac{Wb}{amp} I_{bias}$).

Figure 16: Geometry for Taylor-state stretch current model. Lines at a and b are conducting boundaries, and x is the B_z reversal point.

Figure 17: Contours used for Green's Theorem. Counter-clockwise contour at x goes through a radial cut then travels clockwise at a , then back out, cancelling the radial cut, and completing the contour.

C Outside Safety Report

The following pages is Ivars Henins report on the safety aspects of the HIT experiment. This report is on file in the AERL office.

INTERDEPARTMENTAL

AEROSPACE AND ENERGETICS RESEARCH PROGRAM, FL-10

21 June 1991

To: Professor Thomas R. Jarboe
Nuclear Engineering
University of Washington
Seattle, WA 98195

From: Ivars Henins
121 Monte Rey Drive
Los Alamos, NM 87544

Re: Safety Review of the HIT Experiment

This is in response to your request for me to review the safety aspects of the HIT experimental operations.

The experiment is now being brought on-line. It involves high voltage and energy capacitor banks, and the primary hazards are electrical. In general, danger to personnel can be minimized by recognizing the hazards and establishing operating procedures that do not permit operations that have any probability of injury.

We conducted a formal inspection on June 19, 1991 with the following individuals present: Bob Brooks, Dan Lotz, John Rogers, Brian Nelson, and myself. The following is a summary of some of the things we discussed.

In general, the experiment has been constructed with attention to safety considerations. The experiment and its power supplies are housed in one room on the fourth floor of the AERL Building. The three entrance doors to this room have interlock switches that prevent the capacitor banks from being charged unless the doors are closed. In addition, there are two "scram" interlock switches on the walls that can be opened to disable the power supplies.

The operating controls and data acquisition equipment are located in an adjacent room equipped with TV monitoring of the experiment.

We agreed that an additional "Area Sweep" interlock should be installed in the experiment room. This interlock would open whenever any one of the door interlocks is opened, and would have to be manually reset by the operator. The purpose is to ensure that someone has not entered the room and closed the door behind them while remaining in the room out of view of the TV cameras. With this, the operator is required to enter the room, inspect it, and to push a reset button on the interlock box before closing any remaining open interlocks.

There are two capacitor banks associated with the experiment. One is the 11 kV, 780 kJ bank for energizing the toroidal field coil, and the other is the + and - 450 V electrolytic capacitor bank for the coaxial gun helicity injector. The primary safety consideration with capacitor banks is to ensure that they are completely discharged whenever anyone is about to come in contact with terminals or conductors to do maintenance or repairs. There are fences and cabinets to prevent inadvertent contact with capacitor bank conductors.

The toroidal field bank has a triply redundant dumping system. First, the bank is discharged through high power ceramic resistors with an RC time constant of about 2.5 seconds. Then a switch is closed that connects the capacitors to ground through electrolytic (CuSO_4 in water) resistors and, finally, manually controlled air driven direct shorting switches can be closed across each capacitor. In addition, a manual resistor discharge wand and shorting bar is provided. I consider these precautions to be adequate. However, to be completely safe, a shorting hook should be provided that can be attached and left connected while repair or maintenance is being done.

The ± 450 volt electrolytic capacitor bank is still being modified. The present bleed resistors have an RC time constant of approx. 35 seconds, which is too long. Additional ceramic dump resistors with dump switches are going to be installed. These will dump the bank in a few seconds. Again, shorting hooks should be provided for directly grounding the components to be worked on.

Additional shorting hooks could be provided for shorting the coil and gun terminals at the experiment when anyone is working on (or near) the vacuum tank. There is danger that these shorting hooks may be inadvertently left connected when the experiment is fired, causing an abnormally high current, which may damage the capacitor bank or blow up the shorting lead, possibly causing damage to adjacent equipment. Therefore, for each of these hooks, it may be desirable to have a storage hanger that would close an interlock switch. This will prevent the capacitor banks from being charged unless these shorting hooks are first hung up on the storage hangers.

At the present, there is no formal Standard Operating Procedure (SOP) document for the experiment. This should be written and should include at least the following:

- a) A short description of the experiment and a list of people responsible for the experiment who are knowledgeable in its operation.
- b) A description of the potential hazards and the precautions and procedures that have, or are to be taken to minimize the danger from these hazards.
- c) Emergency shutdown procedures. Location of circuit breakers, etc.
- d) A description of normal operating procedures.
- e) Safety precautions to be observed when making repairs and modifications.

The SOP should be periodically reviewed and updated as conditions and the experiment change.

Everyone working on the experiment should have a copy and be familiar with the SOP. A copy should be posted at the experiment.

New employees or students should be given a safety orientation briefing by a senior member of the operating team. Records should be kept of who has been given the orientation and when.

A current list of those trained and authorized to operate the experiment should be maintained and posted at the experiment.

An up-to-date complete set of electrical drawings should be maintained.

All interlock "scram" switches, circuit breakers, power cables, compressed gas lines, compressed air lines, water lines, chemicals (such as the electrolytic resistors) should be labeled. Labels on warning lights should indicate their significance.

The two-man rule should be strictly adhered to whenever electrical equipment that has been energized is to be worked on. After it is established that no voltages are present, the work may be done by one person.

In general, an attitude of safety awareness should be developed. Everyone should be encouraged to look for unsafe practices or conditions. If any are perceived, they should be immediately brought to the attention of senior management for evaluation and correction. Formal safety meetings should be held at regular intervals, perhaps monthly. Any safety problems and questions can then be discussed. Minutes should be kept and attendance recorded. There may be safety training films or videos available for use in some of these meetings.

IH:cw

cc: Robert Brooks
Dan Lotz
Brian Nelson
John Rogers

END

**DATE
FILMED**

7 / 6 / 92