NOTICE

**CERTAIN DATA
CONTAINED IN THIS
DOCUMENT MAY BE
DIFFICULT TO READ
IN MICROFICHE
PRODUCTS.**

MICROWAVE GENERATION FOR MAGNETIC FUSION ENERGY APPLICATIONS

Progress Report

September 15, 1991 to July 15, 1992

Principal Investigators

T.M. Antonsen, Jr., W.W. Destler, V.L. Granatstein, and B. Levush

Laboratory for Plasma Research
and
Electrical Engineering Department
University of Maryland
College Park, MD 20742

January 1992

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

PREPARED FOR THE U.S. DEPARTMENT OF ENERGY
UNDER CONTRACT NUMBER DE-FG05-87ER52147

MASTER
DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

PREFACE

This progress report encompasses work on two separate projects, both related to developing sources for electron cyclotron resonance heating of magnetic fusion plasmas. The report is therefore divided into two parts as follows:

Task A Free Electron Lasers with Small
Period Wigglers

Task B Theory and Modeling of High Frequency,
High Power Gyrotron Operation

Task A is experimental and eventually aims at developing continuously tunable, cw sources for ECRH with power per unit as high as 5 megawatts. Task B provides gyrotron theory and modeling in support of the gyrotron development programs at MIT and Varian.

TASK A
FREE ELECTRON LASERS WITH SMALL PERIOD WIGGLERS

Contents

1	INTRODUCTION	1
2	RESEARCH PROGRESS	3
2.1	Wiggler Magnet Progress	3
2.1.1	Planar Wiggler Field Character	3
2.1.2	Wiggler Specifications	4
2.1.3	Wiggler Energizing Principles	4
2.1.4	Design Advantages and Trade-offs	4
2.1.5	Magnet Performance	6
2.2	Sheet Electron Beam Propagation Progress	7
2.2.1	Sheet Beam Confining Forces	8
2.2.2	Experimental Configuration	9
2.2.3	Propagation Results	10
2.2.4	Wiggle Plane Focusing	12
2.3	FEL Amplifier Progress	14
2.3.1	Linear Gain Amplifier at 94 GHz	15
2.3.2	Higher Power, Tapered, Millimeter Wave, FEL Amplifiers	21
3	STATEMENT OF WORK (TASK A)	24
3.1	Sheet Electron Beam Propagation	24
3.2	Linear Gain Amplification at 94 GHz	24
3.3	Amplifier Saturation and Wiggler Tapering for Efficiency Enhancement	24
3.4	A High Power Amplifier at 94 GHz	24
4	Task A Appendices	26

1 INTRODUCTION

This section details progress over the past year on Task A: Free-Electron Lasers With Small Period Wigglers. This introduction explains the impetus for the work and provides a review of our free-electron laser (FEL) concept.

It is recognized that free-electron lasers are potentially attractive sources of high power millimeter wave radiation which would be useful for a number of important applications. In magnetically confined plasmas these applications include bulk heating, profile control, and assisting startup. Among its attractions is the FEL's ability to operate over an extremely large frequency range - including centimeter, millimeter, and submillimeter wavelengths. The FEL is inherently tunable through adjustments to the beam energy, wiggler magnetic field, or wiggler period. Such tunability is useful in the applications mentioned above.

The resonant FEL frequency f_s is given approximately by the relationship:

$$f_s = 2\gamma_z^2 c / \lambda_w \quad (1)$$

where γ_z is the average axial normalized energy factor, c is the speed of light, and λ_w is the wiggler period. Our philosophy for achieving millimeter wave frequencies is to operate at conventional modulator power supply voltages ≤ 1 MV ($\gamma = 2 - 3$) but with wigglers of period $\lambda_w \sim 1$ cm. Wigglers with this period are considered short-period wigglers and their development has been, and remains, a critical part of our work.

We have chosen to investigate the FEL amplifier as a source of high power millimeter wave radiation. An envisioned system is shown in the schematic of Fig. 1. This device might, for example, represent a 150 GHz amplifier designed for cw operation on the ITER experiment. As is shown, the amplifier employs two power supplies and a spent beam energy recovery system. The high voltage supply at $\lesssim 1$ MV biases the gun while the low voltage supply at ~ 200 kV - 300 kV provides the majority of the ~ 30 A beam current. Assuming an energy recovery efficiency of 80%, and an electronic interaction efficiency of 19% which is achievable with wiggler tapering, this device would operate with 54% wall-plug efficiency.

Toward this eventual end, our research can has concentrated in three areas: short-period wiggler magnet development, sheet electron beam propagation studies, and pulsed FEL amplifier experiments. Integral to our efforts are pulsed planar electromagnet wigglers and sheet electron beams. Figure 2 is a schematic of the sheet electron beam - wiggler configuration. Dimensions of the electron beam are thickness $\Delta \sim 1.0$ mm by width $W = 2.0 - 3.0$ cm. A customized waveguide, typically 0.5 cm $\times$ 4.0 cm is necessary for radiation propagation at the millimeter wave frequencies of interest.

Figure 1: Schematic view of an FEL amplifier system for use in electron cyclotron resonance applications.

Figure 2: Geometry showing sheet electron beam propagating through waveguide channel and planar wiggler.

Sheet electron beams have several advantages over pencil beams. One advantage is the ability to increase total beam current simply by increasing the wide dimension of the beam. A second advantage is the large magnetic fields obtained by a small magnet gap into which, geometrically, the sheet beam fits well. Finally, for strong FEL interaction the magnetic field should remain constant (vary less than 5%) over the cross-section of the beam. This is easily satisfied in the sheet configuration.

Progress in the FEL amplifier development is presented in three parts: Wiggler Magnet Progress (Section 2.1), Sheet Electron Beam Propagation Progress (Section 2.2), and FEL Amplifier Progress (Section 2.3).

2 RESEARCH PROGRESS

2.1 Wiggler Magnet Progress

The present wiggler magnet is the product of several years of work with numerous prototypes. Past wiggler development has concentrated on planar, pulsed electromagnet wigglers compatible with sheet electron beams with emphasis placed upon high fields and good field uniformity. Within the limitations presented by its design simplicity, the present wiggler magnet has succeeded in these goals. The following discussion of wiggler magnet progress is divided into five parts: (1) Planar Wiggler Field Character, (2) Wiggler Specifications, (3) Wiggler Energizing Principles, (4) Design Advantages and Trade-offs, and (5) Magnet Performance.

2.1.1 Planar Wiggler Field Character

The planar wiggler, unlike the helical wiggler, is characterized by fields of all odd harmonics of the wiggler period. However, a good assumption in a planar wiggler for an electron beam deviating slightly off-axis ($y \neq 0$) is to consider only the fundamental order. The fundamental order magnetic fields are given as:

$$\begin{aligned} B_y &= B_w \cosh\left(\frac{2\pi y}{l_w}\right) \sin\left(\frac{2\pi z}{l_w}\right) \\ B_z &= B_w \sinh\left(\frac{2\pi y}{l_w}\right) \cos\left(\frac{2\pi z}{l_w}\right) \end{aligned} \quad (2)$$

where B_w is the peak wiggler field and l_w is the wiggler period. Note that on the wiggler axis the electron beam experiences no axial magnetic field ($B_z = 0$). Also note that the vertical magnetic field (B_y) increases exponentially off-axis.

2.1.2 Wiggler Specifications

Our wiggler is a pulsed planar electromagnet with a nominal period of 1 cm (i.e. $l_w = 0.96$ cm). A modular design, three modules each with 19 periods, allows for a total length of 54 cm. The magnet gap is typically 0.38 cm allowing a stainless steel waveguide of inside dimension 0.32 cm to be inserted. Large magnetic fields are obtained by operating at a gap to period ratio $\alpha = \frac{1}{3}$. A one period taper at the wiggler entrance assists in matching the beam to the interaction region. This taper consists of reduced iron material in the first two wiggler half-periods.

To drive the wiggler we have constructed a low voltage 450 V, large capacitance 3 mF power supply. As one might expect, the magnet circuit is both reactive ($L = 18 \mu\text{H}$) and resistive ($R = 25 \text{ m}\Omega$). At the ~ 210 Hz resonant frequency of the underdamped circuit, the inductive impedance $21 \text{ m}\Omega$ and resistive impedance $25 \text{ m}\Omega$ are essentially equal.

2.1.3 Wiggler Energizing Principles

Energization of the wiggler is through a conducting structure consisting of copper bar stock hard soldered into a "meander path" configuration. Placed between the copper are soft iron poles consisting of thin lacquered laminations. Single input and output current feeds are used to energize the one path of the wiggler circuit. The rather elaborate four-layer current path is illustrated in Fig. 3. Shown is the copper meander structure without the iron poles inserted. The sheet electron beam passes from left to right in the figure and between the wiggler halves. Referring to Fig. 3, energizing current enters at the wiggler front and is conducted along the bottom portion of the top half. At the wiggler back energizing current is passed to the top portion of the top half. At the front the current is passed by way of a jumper, not shown, to the bottom half of the wiggler where it undertakes a similar path.

2.1.4 Design Advantages and Trade-offs

At least four advantages of this design are apparent from Fig. 3. First, the wiggler feeds enter in close proximity to each other. This minimizes stray fields from the energizing input current. Ideally, the current feeds might consist of a coaxial structure producing no external fields. Second, each pole is wound twice, enhancing the effective current. Third, note that on the edges of the wiggler, the arrows representing current polarity are opposed. Undesired fields from this edge current are therefore reduced. Finally, at the entrance and exit of the wiggler, there is a single copper conducting bar instead of the two found elsewhere. This

Figure 3: Wiggler magnet schematic showing four-layer copper windings without iron pole pieces. Arrows represent path of energizing current.

effectively reduces the current about the nearby pole piece. Fields should be reduced for this first and last half-period resulting in a natural entrance and exit taper.

It was decided early in the development that the entire wiggler would be placed in vacuum. The reasoning for this decision concerned the structural integrity of the waveguide which must necessarily be evacuated. The thickness required to hold off atmospheric pressure in the large aspect ratio waveguide made its use as an interface impractical. From the standpoint of magnet performance, it is important that the waveguide walls be thin. The thickness of the waveguide increases the magnet gap separation and reduces the wiggler field. Field penetration time through the waveguide must also be considered. Typically, we employ thin stainless sheets of thickness 0.3 mm to construct the waveguide.

Several engineering sacrifices and concerns result from placing the entire wiggler in vacuum. One sacrifice is the inability to make adjustments on the wiggler due to its inaccessibility. One concern results from the placement of hard vacuum incompatible structures and materials within the vacuum system. Specifically, the wiggler has a high density of small airspaces and is comprised of materials such as adhesives and lacquers. In our present configuration the wiggler - vacuum interface occurs via feedthroughs on the two current inputs. Although pumping requires time, extremely high vacuum is not necessary in our initial development program, and the vacuum which can be achieved is acceptable for operation. It

Figure 4: Magnetic field B_y as a function of energizing kiloAmpere-turns in the $l_w = 0.96$ cm, 56 period wiggler magnet.

should be noted that an occasional problem of wiggler arcing may be related to residual gas in the wiggler.

2.1.5 Magnet Performance

Our amplifier at 91 GHz will operate in the “high gain Compton” regime for which spatial growth rate and efficiency scale as the two-thirds power of magnetic field $B^{2/3}$.¹ In accordance with the goal of large signal gain, the 54 cm long wiggler has proven its capability of generating sufficient fields. Shown in Fig. 4 is the peak magnetic field as a function of energizing Amp-turns. Note that since there are effectively two turns per pole the actual current in the magnet is one-half the value on the abscissa. The peak field of 5100 G is among the highest values reported for such a small period wiggler. A 14 kA current is required for this field. Some pole saturation is undoubtedly occurring at these higher field values.

In addition to high peak magnetic fields, good peak-to-peak field uniformity is important. Field uniformity influences not only beam propagation, and possible beam - waveguide interception, but also the signal growth rate. Field uniformity results for the 54 cm are illustrated in Fig. 5. Shown are the peak magnetic field $|B_y|$ amplitudes for each half-period. This data is characterized by a statistical fluctuation (standard deviation) of 2.95%. Achieving this error fluctuation required shimming the magnet gap in the three separate

Figure 5: Peak fields in the 56 period wiggler magnet showing peak-to-peak fluctuation of 2.95%.

modules and the deliberate movement of those poles for which the field greatly deviated, a tedious iterative process. The inability to precisely adjust or tune the individual fields is an unattractive feature of the present magnet design and improved magnet configurations are under consideration.

Field uniformity measurements are made with a Hall effect probe at reduced energizing current (i.e. at low field values). It is assumed that the error fluctuations measured at reduced fields is scalable to higher fields. Numerical modeling indicates that the $\sim 3\%$ errors will not significantly degrade beam propagation or signal growth. This is elaborated in the FEL Amplifier Progress section.

2.2 Sheet Electron Beam Propagation Progress

Stable and confined sheet electron beam propagation is essential for FEL amplifier viability if the results of the present pulsed experiments are to be relevant to cw designs. Multi-megawatt cw FEL amplifiers must operate without serious threat of beam interception with the tube body. Such interception would result in catastrophic tube damage. Consequently, much of our effort has been devoted to the study of beam propagation. Beam propagation assumes added significance with regard to the large aspect ratio sheet beam configuration. In this configuration the sheet electron beam must propagate through a narrow tunnel, 3.2

mm $\times$ 4.0 cm in the present experiment, over typical interaction lengths of 1 m to 2 m. The large wiggler fields required for high gain necessitate such a narrow magnet gap.

The following discussion on sheet beam progress is presented in four parts: 1) Sheet Beam Confining Forces, 2) Experimental Configuration, 3) Propagation Results, and 4) Wiggle Plane Focusing.

2.2.1 Sheet Beam Confining Forces

At least three mechanisms may negatively affect beam transport. These mechanisms are divergent ballistic motion of the beam, wiggler field errors or inhomogeneities, and space charge effects. From the experiments and numerical propagation simulations, we have found the first two effects to be most important. Space charge effects at currents of ~ 30 A (densities $n \approx 3.7 \times 10^{10} \text{ cm}^{-3}$) appears to have little influence on beam propagation. Confinement of the sheet electron beam is to be implemented entirely by the wiggler magnetic fields. No external solenoidal field can or will be applied since sheet electron beams are subject to a shearing type instability under the influence of a solenoidal guide field.

When discussing confinement one needs to distinguish between the two transverse dimensions, the wiggler plane or wide dimension x and the narrow dimension y of Fig. 2. Within the narrow dimension focusing occurs through the B_z field component given in Eq. (2). The Lorentz force component in the narrow dimension $F_y = \frac{q}{c} v_x B_z$ tends to focus the electron toward the wiggler axis $y = 0$ where v_x is the electron wiggler velocity. Shown in Fig. 6 is a computer simulation of a sample electron trajectory through the 54 cm wiggler. The sample electron enters 0.2 mm below wiggler axis with an initial $v_x/v_z \sim 3^\circ$ divergence angle. Electrons entering with zero divergence but off axis ($y_0 \neq 0$) will also undergo betatron oscillations but at different phase. Experimentally we have observed focusing in the narrow dimension both for earlier 10 period² experiments and in the current 54 cm, 56 period work.³

Previous work has shown that focusing in the wiggler plane can be accomplished by a variety of means. These include quadrupole magnets, trapezoidal poles,⁴ and shaped pole faces.⁵ Prior work in our laboratory has employed the shaped pole principle.³ However, for the beam propagation and linear gain amplifier experiments we are implementing a novel "offset poles" scheme to be discussed shortly. First, a discussion on experimental configuration including beam monitoring diagnostics is in order.

Figure 6: Sample electron trajectory in the narrow dimension y through the 56 period wiggler magnet.

2.2.2 Experimental Configuration

The sheet electron beam for the initial experimental studies is formed in an effective, but inefficient, manner through aperturing slits. The beam is generated from a pulse-line accelerator “DRAGON” characterized by pulse length of ≈ 100 ns. The flat top portion of the pulse is ≈ 80 ns with a 3% to 5% voltage ripple. A velvet cathode is used for the field emitter while a graphite and stainless steel anode (Anode 1 in Fig. 7) is held at ground potential. The process of sheet beam formation is inefficient since tens of kiloAmperes of current are scraped on the two anodes while only 10 A to 30 A enters the interaction region. Two aperturing slits or anodes are used to provide a high quality beam of reduced space charge and small divergence angle. At times the slit aperture is replaced by a linear array of small holes permitting even higher quality beams. With the slit apertures the divergence angle is typically 2° resulting in an axial beam energy spread $\Delta\gamma_z/\gamma_0 = 0.3\%$.

Included among the diagnostics illustrated in Fig. 7 are entrance and exit Rogowski coils. These are used to monitor input and exiting current. The DRAGON environment is electromagnetically noisy and noise reduction refinements of the coils is an ongoing process. In addition to the Rogowski coils a low inductance Faraday cup measures transported current and verifies the exit Rogowski signal. Also, at times, an acrylic Cerenkov witness plate

Figure 7: Experimental configuration for the beam propagation experiments.

is placed in the beam path. Electrons striking the acrylic emit light from Cerenkov and fluorescent effects. A photographic camera captures the emission producing an image of the beam.

Although several techniques have been attempted, there is presently no diagnostic to directly measure the current intercepting the waveguide walls. To date the signals have proven too noisy. One prospective technique is to isolate the waveguide plates. When the beam intercepts the plates, they act as a capacitor and become charged. A monitor of the voltage on the plates and the value of plate capacitance provides total charge, and hence, time-averaged intercepted current. Efforts will continue to develop an acceptable beam intercepted current diagnostic.

2.2.3 Propagation Results

An effort has been made to determine beam transport behavior through the 54 cm long wiggler at parameters of relevance to the amplifier experiment. Specifically, a 440 keV, ~ 20 kA, $0.1 \text{ cm} \times 2.0 \text{ cm}$ beam was injected into the wiggler and input and output current monitored. Results for transmitted current fraction as a function of wiggler field are presented in Fig. 8.

Note that with no applied field only a very small fraction of beam current is transported to the end of the wiggler. With the application of wiggler field the transported fraction

Figure 8: Sheet beam propagation results showing transmitted current fraction as a function of applied wiggler field.

increases, dips, and increases again; the dip is not understood. The largest transported current is 13.5 A and the highest transported fraction is 67%. Although there is clearly room for improvement, the data is encouraging. It is important to note that this data is obtained with a wiggler characterized by peak-to-peak field errors of 7.8%. Equally important, there is no wiggler plane focusing and the beam can be freely lost in this dimension. We plan to conduct a transport experiment with the reduced field errors of 3.0% (magnet discussed in section 2.5) in which we expect improved transport efficiency. Offset poles wiggler plane focusing will be used once we are satisfied with the no focusing propagation results.

Several additional factors may influence the transport measurement. During the ~ 10 ns rise and fall times of the electron beam, low energy electrons are reflected before entering the wiggler region. This low energy current is monitored by the entrance Rogowski but not by that at the exit. A narrowing of the current pulse should occur and is apparent on some of the Rogowski waveforms. Another factor is the sensitivity of Rogowski coils to the angular incidence of the current. Since there is no wiggler exit taper the electron beam leaves the interaction region with finite transverse velocity, i.e. at some angle with respect to the axis. If the current is incident on the Rogowski coil at an angle Θ from the normal to the loop, the sensed signal will be reduced by a factor $\cos \Theta$. This sensitivity of the current monitoring coils will be addressed in future propagation experiments.

Figure 9: The offset pole technique of wiggler plane focusing. Each pole is alternatively offset $\pm\delta x$.

2.2.4 Wiggler Plane Focusing

In planar magnets, narrow dimension focusing is inherently provided by the wiggler axial field component. Focusing in the wiggler plane, however, requires some deliberate action. As mentioned, we have chosen to examine the offset poles method of wiggler plane focusing. The principle is illustrated in Fig. 9 providing a downward perspective on the wiggler magnet. The first few iron poles are labeled alternatively north and south. Each pole has been offset in the wide dimension by an amount $\pm\delta x$.

Electrons traveling along the wiggler center should experience no effect from the offset poles. It is intended that those electrons straying toward the sides (top and bottom in Fig. 9) should experience a focusing force. Imagine an electron traveling off-axis, say along the top in Fig. 9. Since the south pole faces have been shifted away (and the north toward), this electron should experience a more northerly field in its motion. The sinusoidal B_y field it experiences will be shifted to the north, i.e. given a displacement. Similarly, an electron traveling off-axis along the bottom in Fig. 9 will experience a field displacement to the south. It is anticipated that the Lorentz force component in the x-dimension $F_x = \frac{e\hbar}{c}v_z B_y$ will provide the necessary correction to the electron trajectory.

The narrow dimension field B_y is expected to remain constant over most of the wide dimension and increase exponentially as the offset region is approached. Figure 10 presents

Figure 10: Predicted field profile B_y in the wide dimension x for three offsets.

a model of B_y as a function of the wiggler plane dimension x for three offset values. The wiggler period λ_w , narrow waveguide dimension Δy are indicated. The parameter x_0 is the unshifted position of the pole piece. The three offsets δx are 0.5 mm, 2.0 mm, and 5.0 mm. Note the abruptness of the field increase (or decrease) at the point of offset.

Hall probe measurements in the wiggler indicate field profile behavior similar to that just described. Figure 11 shows a field profile measurement at five selected points along the wide dimension. This data is obtained by measuring B_y in five selected channels along the entire length of the wiggler. The points shown are the mean of the field data over the entire length. Therefore these points represent the amount of field displacement which can be expected. A pole shift $\delta x = 7.0$ mm is probably larger than that which will be used in the beam propagation and amplifier configurations. Note the similarity in Fig. 11 to the expected fields in Fig. 10. As desired, in the central region of the wide dimension, the field is flat and unperturbed by the pole offsets.

A preliminary test of the offset poles scheme was performed numerically with the field profile shown in Fig. 10 incorporated in the propagation code. Using parameters from the amplifier experiment and a pole offset $\delta x = 1.0$ mm, the code found excellent beam transport. A sample electron trajectory is traced in Fig. 12. The sample electron is given a 1° initial divergence angle. Executing its wiggler motion on a ballistic trajectory, the electron senses no field variation until near the pole offset. As it approaches the offset the electron is

Figure 11: Measured field profile at five points in the wide dimension x for an offset $\delta x = 7.0$ mm. The ordinate $B_{y \text{ ave}}$ gives the amount of field shift.

reflected back toward the wiggler axis. If the wiggler were longer the electron would execute several betatron orbits in this plane.

2.3 FEL Amplifier Progress

The sheet electron beam FEL amplifier is proceeding in two phases. In the first phase we will show linear gain amplification at a frequency of 94 GHz using the 0.96 cm period wiggler described previously. We are well into this first phase; nearly all the necessary amplifier components have been either built or acquired. Following successful demonstration of linear gain, we shall extend the length of the wiggler magnet to achieve interaction saturation and then taper the wiggler magnet for efficiency enhancement. A total output power of 520 kW is theoretically predicted in this tapered magnet experiment.

In the second phase of our amplifier development we will seek power levels of 4 MW to 5 MW. We envision an experiment using a ~ 10 kW driver signal at 94 GHz provided by either a magnetron or a gyrotron. The following describes the progress to date in our FEL amplifier development.

Figure 12: Sample electron trajectory in the wide dimension x through the 56 period wiggler magnet showing wiggler plane focusing with the offset pole technique.

2.3.1 Linear Gain Amplifier at 94 GHz

Development of the pulsed amplifier at 94 GHz is well underway. Most of the necessary components have been constructed or are in the final phases of completion. A schematic of the linear gain amplifier is shown in Fig. 13. Among the amplifier components are an extended interaction oscillator (E.I.O.) at 94 GHz, a linear waveguide taper from WR-10 to the customized wiggler waveguide dimension, a miter bend for coupling the input signal to the injected electron beam, and a 54 cm long planar electromagnet wiggler. This wiggler is the same 0.96 cm wiggler used for the propagation experiments.

Given the goal of a mm-wave amplifier, the specific frequency choice was dictated largely by the availability of a signal source. The available source is to be loaned free-of-charge by the U.S. Army Harry Diamond Laboratories. Specifically, this signal source is a continuous operation Varian E.I.O. mechanically tunable from 94 GHz to 98 GHz with output power of 10 W to 20 W. Delivery of the complete E.I.O. system is anticipated in February 1992. Cold testing of the linear taper, miter bend, and wiggler waveguide configuration will begin after an initial check-out of the E.I.O.

The 94 GHz amplifier parameters can be found in column 1 of Table 1. A resonant beam energy of 163 kV and beam current of 10 A is well within the capabilities of the DRAGON

Figure 13: Cross-section of the linear gain amplifier at 94 GHz showing the sheet electron beam generation and signal injection methods.

pulse-line accelerator. The parameters listed for the wiggler magnet and sheet beam were previously achieved in the propagation experiments. Predictions from a 3D numerical code, with results detailed shortly, indicate this amplifier will saturate at 180 kW after 90 cm of interaction length. A tapered length of 110 cm could increase the total output power to 520 kW and result in an interaction efficiency of 11%. These best-case values assume a perfect wiggler field and cold electron beam. Radiative heat loading to the wall of 71 W/cm^2 will pose no problem to this $\sim 100 \text{ ns}$ pulsed experiment. It should be noted that this wall loading is very much below the 2 kW/cm^2 that we have determined is safely removable in continuous amplifier operation with water cooling.⁷ Low rf wall losses are an important advantage of our FEL amplifier configuration.

For a better understanding of anticipated amplifier results we have performed extensive numerical simulations. Specifically, using a 3D code⁸ we investigated amplifier output power and gain as well as the influences of beam energy spread, energy detuning, wiggler tapering, and wiggler errors. Shown in Fig. 14 is the expected power as a function of axial distance. The amplifier parameters used for this run are listed in the figure and are the same as those found in column 1 of Table 1. Note that an axial energy spread of 0.5% has been used for this simulation. This provides a somewhat conservative result since the actual beam energy spread, as determined from geometric considerations of the beam entrance apertures, should

TE₀₁ Mode ($a = 4.0$ cm; $b = 0.32$ cm; $f = 94$ GHz; $P_{in} = 10$ W)

Figure 14: Power evolution in the linear gain amplifier with $\Delta\gamma_z/\gamma_0 = 0.5\%$ axial energy spread.

not exceed 0.3%. This simulation predicts a saturated output power of 118 kW after 98 cm of interaction length given 10 W of input power. Since the present wiggler length is 54 cm, we do not expect saturation in the initial experiment. Power levels around ~ 3 kW are more likely at this length.

The power gain per unit length as a function of axial distance is found in Fig. 15. Again, this is for a beam with axial energy spread $\Delta\gamma_z/\gamma_0 = 0.5\%$. There is considerable structure to this plot but an average gain of ~ 0.5 dB/cm is evident. Note that the gain passes through zero at the saturation distance near 95 cm.

The effect of beam energy detuning on the output power and on the saturation length is found in Fig. 16. This is for a cold electron beam, i.e. $\Delta\gamma_z/\gamma_0 = 0$. The solid line represents the saturation power while the dashed curve represents the saturation length. Both are given with dependence upon beam energy. Operation at a beam energy slightly above the resonant energy of 463 keV, say at 470 keV, would be optimum. With positive energy detuning there is a region of increased power with little change in saturation length.

As discussed earlier, the sheet electron beam is generated from a cold field emission cathode and is formed into a sheet by rectangular slit apertures. These apertures determine the beam net current, dimensions, and thermal spread. Typically we use two 0.1 cm $\times$ 2.0 cm slit apertures spaced 5 cm apart. From geometric considerations we calculate a 2° divergence

Table 1: Table showing parameters for three experiments. First column entitled "1 cm Wiggler" refers to the linear gain amplifier. The second column presents near future work using a magnetron or gyrotron driver. The third column refers to an ITER relevant experiment.

	1 cm Wiggler	Future Exp.	Design Goal
frequency (GHz)	94	94	150
V_{beam} (MV)	0.47	0.65	0.86
I_{beam} (A)	10	30	30
S_{beam} (cm ²)	0.1 x 2.0	0.1 x 3.0	0.1 x 3.0
$B_{w,0}$ (kG)	5.1	7.0	7.0
l_w (cm)	0.96	1.5	1.5
$a_{w,0}$	0.46	.98	.98
S_{wg} (cm ²)	0.32 x 4.0	0.75 x 4.0	0.75 x 4.0
P_{in} (kW)	180 ^a	610 [*]	620 [†]
z_{int} (cm)	90	41	63
Gain (dB/cm)	0.47	0.44	0.44
L_{laser} (cm)	110	45	66
P_{out} (MW)	0.5	4.2	5.0
η (%)	11	21	19
$\langle P_{wall} \rangle_t$ (W/cm ²)	71	39	23

^a 10 W input power

^{*} 10 kW input power

[†] 1 MW input power

TE₀₁ Mode ($a = 4.0$ cm; $b = 0.32$ cm; $f = 94$ GHz; $P_{in} = 10$ W)

Figure 15: Growth rate along the linear gain amplifier length for a warm electron beam and error-free wiggler.

TE₀₁ Mode ($a = 4.0$ cm; $b = 0.32$ cm; $f = 94$ GHz; $P_{in} = 1$ kW)

Figure 16: Expected saturation power and saturation length as a function of electron beam energy (or energy detuning).

angle for the beam entering the wiggler region. This corresponds to an axial beam thermal spread $\Delta\gamma_z/\gamma_0 = 0.3\%$. Figure 17 shows the harmful influence of beam thermal spread upon saturation power (solid line) and saturation length (dashed line). At the anticipated 0.3% thermal spread the saturation power and length have not degraded seriously.

An additional source of reduced gain are wiggler field errors. One of the most serious effects of wiggler errors is beam loss to the walls resulting in reduced gain and possible structural damage. Gain reduction can be understood by relating wiggler errors to an effective beam thermal spread. The actual $\sim 3\%$ errors measured in the 54 cm long wiggler were simulated in the 3D numerical code along with $\Delta\gamma_z/\gamma_0 = 0.5\%$ beam axial energy spread. The results are presented in Fig. 18. This simulation assumes 10 W of input power and shows power evolution in the wiggler up to the 54 cm length for three different scenarios. “Ideal Beam” refers to zero thermal spread beam while “Ideal Wiggler” refers to no field errors. The simulation shows that wiggler errors are not as serious as beam thermal spread with regard to gain. Note that the middle curve (incorporating wiggler errors) is only slightly below the power curve of the ideal case. The lowest power curve, “Real Beam & Wiggler” is a good estimation of what can be expected with our initial amplifier experiment.

Once satisfactory results are observed with the present interaction length of 54 cm, plans are to increase wiggler length and investigate wiggler tapering. The modular design of the

TE₀₁ Mode ($a = 4.0$ cm; $b = 0.32$ cm; $f = 94$ GHz; $P_{in} = 10$ W)

Figure 17: Saturation power and saturation length degradation with axial energy spread.

TE₀₁ Mode ($a = 4.0$ cm; $b = 0.32$ cm; $f = 94$ GHz)

Figure 18: Power evolution under ideal and realistic conditions in the present 56 period, 54 cm amplifier length.

TE₀₁ Mode ($a = 4.0$ cm; $b = 0.32$ cm; $f = 94$ GHz; $P_{in} = 1$ kW)

Figure 19: Power growth with wiggler tapering. Taper begins at $z_0 = 50.4$ cm. Curve $\epsilon_w = 0$ shows power evolution in an untapered wiggler.

wiggler magnet makes its lengthening convenient. An investigation of the influence of wiggler tapering on output power was performed using the 3D numerical code. Wiggler tapering employs a method of slowly or adiabatically lowering the wiggler parameter a_w . The key is to maintain electron trapping within the ponderomotive potential wells as the entire potential well is lowered. Figure 19 shows that, for the 0.96 cm wiggler, output power can be increased from 180 kW to 520 kW. Although this is not a large increase in terms of gain, it is attractive in terms of increased efficiency (from 3.8% to 11.1%). The specific taper length required for this power increase is about 110 cm. If a more modest increase in power was acceptable, a shorter length could be used by designing for the intermediate peak power value shown in Fig. 19.

The rather sensitive dependence of output power on start taper position is shown in Fig. 20. In designing the tapered magnet, field or period adjustability will be key to handling this sensitivity. Note that in both Fig. 19 and Fig. 20 an input power of 1 kW was used. This does not alter the relevance to our amplifier for the case of a 10 W input; only the point of start taper would need to be increased.

TE₀₁ Mode ($a = 4.0$ cm; $b = 0.32$ cm; $f = 94$ GHz; $P_{in} = 1$ kW)

Figure 20: Output power showing sensitivity to start taper point.

2.3.2 Higher Power, Tapered, Millimeter Wave, FEL Amplifiers

Operation of the linear gain amplifier at 94 GHz is relevant to planned future, higher power, experiments. These future experiments will be enabled through our acquisition of a high power magnetron or by making operational a gyrotron traveling wave tube (gyro-TWT). This tube was supplied to us on a long-term loan basis from the U.S. Army and was originally purchased by the Walter Reed Army Medical Center. Characteristics of this amplifier tube include operation at 94 GHz, power 12 kW, 1% bandwidth, and pulselength 20 μ s to 100 μ s. For the amplifier driver source we plan to use the E.I.O. described above. Presently the gyro-twt amplifier is not a complete system since several additional components are needed. These include a 50 kV, 5 A pulse modulator as well as cryogenic and room temperature solenoidal magnets. We will continue to pursue low-cost means of obtaining the needed equipment. In the meanwhile, acquisition of a 94 GHz magnetron will allow study of the nonlinear operation of our FEL amplifier albeit over a very limited range of frequencies.

We propose to use the magnetron or the 12 kW, 94 GHz gyro-twt as a driver source for an FEL amplifier. Parameters for this future experiment are given in the second column of Table 1. Power, saturation length, gain, and taper length are determined from a 1D universal formulation discussed in the article included in Appendix 2. It is suggested that for this experiment, a new larger period wiggler magnet ($l_w = 1.5$ cm) be constructed. This

will permit larger fields ($B_w = 7kG$) and allow a larger beam tunnel for transport. The estimated saturated power of 610 kW is significantly larger than that of the 0.96 cm period amplifier. In addition, as a result of the larger wiggler parameter $a_w \approx 1$, wiggler tapering should be more efficient. With wiggler tapering an output power of 4.2 MW and an overall efficiency of 21% is estimated. The 650 kV operating voltage for this amplifier is within the acceptable voltage limits of the DRAGON pulse-line accelerator.

Shown in the third column of Table 1 are parameters for a 150 GHz experiment relevant to ITER. Again, these values were found using the formulation described in Appendix 2. This amplifier could use the same 1.5 cm wiggler magnet mentioned above. Note that this 5 MW device will require a wiggler magnet only ~ 1.3 m in length. However, the higher voltage 860 kV precludes use of the DRAGON pulse-line accelerator. It is suggested that a pulse modulator and sheet electron beam thermionic gun be used for this purpose. With wiggler tapering the predicted efficiency of this amplifier is 19%. Of course in a cw embodiment, efficiency could be enhanced by the depressed collector technique.

REFERENCES

1. P. Sprangle, R.A. Smith, Phys. Rev. A, **21**, 293 (1980).
2. D.J. Radack, J.H. Booske, Y. Carmel, and W.W. Destler, Appl. Phys. Lett., **55**, 2069 (1989).
3. S.W. Bidwell, et al., Bull. Amer. Phys. Soc., **36**, 2436 (1991).
4. K. Mima, et al., Thirteenth Intl. Free-Electron Laser Conf., 125 (Aug. 25-30, 1991, Santa Fe, NM).
5. E.T. Scharlemann, J. Appl. Phys., **58**, 2154 (1985).
6. H. Bluem, R.H. Jackson, H.P. Freund, D.E. Pershing, and V.L. Granatstein, Phys. Rev. Lett., **67**, 824 (1991).
7. J.H. Booske, et al., Nucl. Instr. Meth. Phys. Res., **A 285**, 92 (1989).
8. A.K. Ganguly and H.P. Freund, Phys. Rev. A, **32**, 2775 (1985).

3 STATEMENT OF WORK (TASK A)

We propose to do the following tasks during the funding period July 15, 1992 to May 14, 1993. order of its listing.

3.1 Sheet Electron Beam Propagation

- Complete propagation experiments through 0.96 cm period, 54 cm long wiggler wiggler with reduced field errors ($\leq 3\%$ peak-top-peak fluctuation).
- Study propagation through an offset-poles scheme of wiggle plane focusing.

3.2 Linear Gain Amplification at 94 GHz

- Complete component construction of amplifier (e.g. waveguide, signal driver input system)
- Cold test signal driver input system with the cw 94 GHz E.I.O. to be delivered February 1992.
- Amplifier experiments using ~ 10 W input studying output power, gain, and efficiency. Investigate the effects of wiggler field errors and beam thermal spread on these output parameters.

3.3 Amplifier Saturation and Wiggler Tapering for Efficiency Enhancement

- Length of present wiggler increased to achieve signal saturation. Modifications to the pulsed wiggler power supply may be needed to drive the longer wiggler.
- Methods of tapering the wiggler magnet through period and/or field variation will be investigated.
- Add tapered wiggler sections to the existing magnet. Investigate the effects of the taper upon amplifier operation.

3.4 A High Power Amplifier at 94 GHz

- Detailed design of a high power (~ 5 MW) pulsed amplifier at 94 GHz. Overall length of wiggler need not exceed 1 m given large wiggler fields and high power input signal.

- Construct a larger period ($l_w = 1.5$ cm) higher field ($B_w = 7kG$) wiggler magnet incorporating wiggler tapering.

TASK B
THEORY AND MODELING OF HIGH FREQUENCY, HIGH POWER
GYROTRON OPERATION

Contents

1	INTRODUCTION	1
2	TECHNICAL PROGRESS	2
2.1	Nonlinear Simulation of High Power Gyrotrons	2
2.1.1	Single Mode Simulation: The Effect of the Beam Temperature	2
2.1.2	Multimode Simulations	4
2.1.3	Comparison with MIT 148 GHz Short Cavity Experiment	6
2.1.4	Comparison with MIT 140 GHz: University of Maryland Cavity Experiment	6
2.1.5	Comparison with Varian 140 GHz Experiment	8
2.2	Effect of Window Reflection on Gyrotron Operation	8
2.3	Effect of Space Charge Instability on the Beam Quality	9
3	STATEMENT OF WORK (Task B)	12
3.1	Gyromonotron Studies	12
3.2	Quasi-optical Gyrotron Studies	12
4	TASK B APPENDICES	14

1 INTRODUCTION

One of the main issues in the development of high power gyrotrons is the present discrepancy between the theoretically predicted efficiency and that observed in the experiments. The 148 GHz gyrotron experiments at MIT¹ with single section cavities have achieved efficiencies less than 20% at high currents for the $TE_{16,2,1}$ mode of operation. Theoretical predictions indicate up to 45% should be possible for the MIT single section cavity design. A better theoretical understanding of the causes of these discrepancies is essential to the scaling of gyrotrons to higher power and higher frequency.

Mode competition from neighboring modes, poor magnetic compression of the beam, space charge effects, including excitation of spurious electron beam instabilities or the inability of the pulsed experiment to operate in the hard excitation region are listed as possible reasons for the low efficiency.

The results of our studies (to be discussed in the next section) indicate that mode competition is partially responsible for the degraded efficiency in the MIT experiments. Although we have found that this competition can be eliminated by proper design of the cavity shape, the measured efficiency is somewhat smaller than the predicted efficiency. To improve our modeling capabilities, we are considering including in our code such effects as window reflection and mode transformation due to the wall tapering. We also investigated the degradation of the electron beam quality induced by the nonlinear multi-frequency saturation of the space charge instability.

In summary, two key areas requiring further theoretical research are determining the source of the degradation of efficiency and investigating the means of control of the operating mode in a highly overmoded cavity.

2 TECHNICAL PROGRESS

2.1 Nonlinear Simulation of High Power Gyrotrons

We have developed a nonlinear, self-consistent, time-dependent, multimode simulation code that allows us to study gyrotron operation in the time domain.¹ The radiation field in the code is expressed as a superposition $TE_{\ell m}$ waveguide modes modulated by a time and axial distance dependent amplitude. The radiation field profile satisfies outgoing boundary conditions on both the gun side and collector side of the cavity. Further, AC space charge effects are accounted for in the so-called distributed beam limit.² In addition we have included the pitch angle spread and energy spread to simulate the beam temperature effect on the gyrotron operation.³ We used our code to model the megawatt, 148 GHz experiments carried out at MIT and Varian.⁴⁻⁵

In cases in which only a single transverse mode is allowed the maximum efficiency obtainable from this code is consistent with that predicted by “steady state codes” such as the Fliflet code. In Fig. 1 are shown the plots of the efficiency versus magnetic field obtained with the “steady state code” and our code. The simulation was performed for beam current $I=35$ Amps and beam voltage $V=80$ kV and pitch angle $\alpha = 1.53$ for Varian 140 GHz cavity. We used our code with (dotted line) and without (solid line) taking the voltage depression into account, in the Fliflet code the voltage depression was not included (dashed line). The value of the magnetic field at which the efficiency is maximum is different in all three cases, but the efficiency is the same. However, the efficiency predicted by these models at large beam currents is much higher than observed in the experiments. In Fig. 2 is plotted the efficiency versus current for the short MIT cavity obtained from the single frequency simulation with fixed pitch angle $\alpha = 1.93$ (Δ) and with varying pitch angle (+) together with the experimental data ($\bullet$). The experimental values are different almost by a factor of two from the calculated values. Our main effort is devoted to identify the physical mechanisms which will shed light on understanding this discrepancy.

2.1.1 Single Mode Simulation: The Effect of the Beam Temperature

The non-zero pitch angle spread has little effect on the efficiency of a gyrotron operating at single frequency. Energy spread, on the other hand, can reduce the efficiency significantly if the spread is more than 10%. This is illustrated in Fig. 3 where plots of the optimized efficiency at current $I=30$ Amps against RMS pitch angle (curve a) and energy spread (curve b) are shown. This phenomenon found here can be understood by looking at the relativistic

Figure 1: Efficiency versus cavity magnetic field for the Varian cavity obtained from the stationary code (dashed line) and time-dependent code (solid and dotted line).

Figure 2: Efficiency versus current results for the short cavity obtained from the multifrequency simulations with varying pitch angle α (*), the single mode simulations with fixed pitch angle of $\alpha = 1.93$ (Δ), and single mode simulations with varying pitch angle (+). The values of the pitch angle are indicated next to the (*) symbol. The same values were used at the same current for the single mode cases indicated by (+). The cases (+) and (*) included 20% RMS pitch angle spread. The measured efficiency is indicated by solid dot ($\bullet$).

Figure 3: Effects of (a) pitch angle spread and (b) energy spread on the efficiency of a gyrotron operated in single mode.

cyclotron dispersion relation

$$\omega - \kappa_z v_z \simeq \frac{\Omega}{\gamma}$$

which depends weakly on v_z , because for gyrotrons $k_z \cong 0$, but strongly on the electron energy γ . Pitch angle spread in the experiments is estimated to be under 40%. Thus, according to Fig. 3, to attribute the discrepancy as a result of electron beam energy spread one would need to invoke an energy spread larger than 5%.

2.1.2 Multimode Simulations

When we carried out multifrequency simulations for the MIT short cavity we found that there is substantial interaction in the “throat” of the cavity which induces an energy spread on the beam in an unfavorable way for energy extraction in the main cavity. This interaction is due to the excitation of a lower frequency $TE_{15,2}$ mode. The growth of the lower frequency mode is, as illustrated in Fig. 4, due to a backward-wave instability. Figure 5 shows the typical mode amplitude profiles.

Although the amplitude of the $TE_{15,2}$ mode in Fig. 5(b) is small, the interaction between $TE_{15,2}$ and the beam can still cause a large thermal spread in the beam energy: In the simulation shown, the energy spread can be on the order of 10% although the total energy

Figure 4: Dispersion curves showing the potential growth of the backward waves. The desired operation point is depicted near the cutoff of the $TE_{16,2}$ mode.

Figure 5: Mode profiles in the short cavity obtained from multimode, multifrequency simulations with $I = 30A$ and $\alpha_0 = 1.64$, when (a) the beam has no pitch angle spread and (b) the beam has 20% RMS pitch angle spread.

converted into $TE_{15,2}$ mode is less than 1%.

In Fig. 2, we compare our multifrequency simulations (*) with single frequency simulation results. The experimental data fall between the results of the multifrequency simulations and the single frequency simulations with varying pitch angle. More detailed comparison with experiments is the subject of our present research.

2.1.3 Comparison with MIT 148 GHz Short Cavity Experiment

The multimode simulations of the MIT 148 GHz short cavity has suggested that mode competition with backward wave is responsible for the lower than expected efficiency at high current. We conducted a thorough comparison between the predicted and measured features of parasitic modes in the MIT short cavity.⁶⁻⁷

In Fig. (6a) is shown the measured efficiency (○) and the calculated efficiency versus the pitch angle for the beam current $I=40$ A and voltage $V=80$ kV. The efficiency was calculated for a fixed magnetic field (+) and for an optimized magnetic field (●). The predicted efficiency is somewhat lower than the measured. In Fig. (6b) is shown the measured and predicted frequency of the parasitic $TE_{15,2}$ mode versus the pitch angle. There is a difference between these two of about 2 GHz. However, when the angle of the cavity input wall taper is changed from 1° to 0.8° the difference between the predicted frequency and the measured is reduced to about 1 GHz. Finally, in Fig. (6c) is shown the measured power in the parasitic $TE_{15,2}$ mode relative to the power in the operating $TE_{16,2}$ mode.

2.1.4 Comparison with MIT 140 GHz: University of Maryland Cavity Experiment

The mode competition with backward wave can be eliminated by forcing the backward wave back into the straight section of the cavity where it must compete with the desired mode. Based on this thinking, we designed a new cavity.¹ The multimode simulations predicting single mode operation is achieved with this new cavity. The experiments with this cavity are currently conducted at MIT. In Fig. (7) is shown the efficiency versus pitch angle experiment (preliminary) data together with the predicted efficiencies. Although the parasitic modes have not been observed in these experiments, the measured efficiency is somewhat lower than the calculated.

In summary, following the theoretical predictions the parasitic modes have been observed in the MIT 148 GHz short cavity experiments and not observed in the cavity which was designed to suppress these parasitic modes. However, there is not enough evidence that

Figure 7: Efficiency versus pitch angle for the University of Maryland cavity; the experiment (dashed line) and the theory (solid line) and 15% reduction due to the ohmic heating and window losses (dotted line).

the presence of the parasitic modes are solely responsible for the degradation in gyrotron efficiency at large beam currents.

The result of our studies has been presented in a number of conferences⁶⁻⁸ and summarized in two publications.^{1,3}

2.1.5 Comparison with Varian 140 GHz Experiment

We performed multimode simulations of Varian 140 GHz gyrotron. In Fig. (8) are shown the calculated efficiency versus beam current together with the measured efficiencies. The values of the pitch angle which have been used in the simulation are indicated above the (+) symbol. The simulations predict single frequency operation and somewhat higher than measured efficiencies for all beam currents. If smaller values of the pitch angles are used in the simulations the predicted and measured efficiencies become comparable. For example, for $I = 18$ Amps and $\alpha = 1.7$ the predicted efficiency is about 40%, and the measured efficiency is 35%.

2.2 Effect of Window Reflection on Gyrotron Operation

The output power from a gyrotron is usually extracted through a window which is not perfectly transmitting. Thus, a fraction of the power is reflected back into the interaction

Figure 8: Efficiency versus current for the Varian 140 GHz cavity. The experimental data is denoted by (●) and the results obtained from the multimode simulations with varying pitch angle (+) and 12% reduction due to the losses (x).

region.⁸ This reflection can affect the operation of a gyrotron in several ways. First, the reflection modifies the Q factor of the cavity and changes the operating characteristics such as start current and efficiency. Second, due to the so-called long line effect the spectrum of stationary modes in the cavity becomes dense with a spacing equal to the reciprocal of the round trip travel time from the cavity to the window and back. A third consequence is the effect of the variation of reflection coefficient with frequency on mode competition.

We examined these effects with the aid of simple models.⁹ The main results of these studies are as follows. When the product of the reflection coefficient from the window and the delay time (time for the wave to travel from the cavity to the window and back to the cavity) is large enough, frequency of the radiation can jump as the delay phase varies. When a gyrotron operation is optimized for highest efficiency, the operation is usually in a hard excitation regime and is near the boundary of stable gyrotron operation. Therefore, the operation will be very sensitive to window reflection. The frequency jumping phenomena has been observed in some experiments¹⁰ where the delay phase was changed due to a gradual heating of the gyrotron output waveguide.

2.3 Effect of Space Charge Instability on the Beam Quality

The efficiency of operation of a gyrotron depends sensitively on the quality of the electron beam driving the device. In particular, a nearly monoenergetic beam is desired. Relatively

low voltage beams produced by magnetron injection guns must be propagated long distances (measured in Larmor radii) from the cathode to the cavity. We have considered the possible excitation of electrostatic cyclotron maser modes on the beam and their effect on the beam's energy spread. In the linear regime the growth of the fluctuations is limited by the gradient in the confining magnetic field; further, the mode is self-stabilized by trapping at small amplitudes.

The nonlinear effect of the instability is to induce a spread in beam energy and pitch angle. We found that the thermal spread induced by the unstable multi-modes at nonlinear saturation stage is enhanced by a factor of two compared to the spread induced by the single mode.¹¹ Presently we are in the process of incorporating a realistic axial profile of the magnetic field into our model. This will allow us to investigate the electrostatic instability effects closer to experimental conditions.

REFERENCES

1. S. Y. Cai, T. M. Antonsen, Jr., G. Saraph, and B. Levush, "Multi-frequency Theory of High Power Gyrotron Oscillators," Int. Jour. of Electronics, to be published (1991).
2. R. G. Kleva, T. M. Antonsen, Jr., and B. Levush, Phys. Fluids **31**, 375 (1988).
3. G. P. Saraph, T. M. Antonsen, B. Levush, and G. I. Lin, IEEE Trans. Plasma Science, submitted (1991).
4. K. Kreischer et al., Phys. Fluids **B2**, 640 (1990).
5. K. Felch, et al., 15th Int. Conf. Infrared and Millimeter Waves Conf. Digest, **315** , (1990).
6. T. Antonsen, et al., 16th Int. Conf. Infrared and Millimeter Waves Conf. Digest, **51**, (1991).
7. B. Guss et al., APS, DPP, Tampa, November (1991).
8. S. Y. Cai et al., 1991 IEEE Inter. Conf. Plasma Se., Williamsburg, VA.
9. T. Antonsen, S. Y. Cai and G. Nusinovich, 16th Int. Conf. Infrared and Mill. Waves Conf. Digest **57**, (1991).
10. K. Felch, private communication.
11. H. Li and T. Antonsen, 16th Int. Conf. Infrared and Mill. Waves Conf. Digest **129** (1991).

3 STATEMENT OF WORK (Task B)

We propose to do the following tasks during the funding period July 15, 1992 to May 14, 1993.

3.1 Gyromonotron Studies

We propose the following tasks for the funding period.

- We will complete our studies of mode competition in the MIT 148 GHz experiments.
- We will study the mode competition problem in the Varian 110 GHz ($TE_{22,2}$ mode) design.
- We will study the mode competition problem in the MIT 230 GHz and 280 GHz design and search for cavity shapes which are “immune” to mode competition. We will compare our predictions with the experimental data.
- We will complete development of our simulation code so that it can be made available to users.
- In addition we will continue to improve the code’s modeling capabilities. We plan to include in the code the following new features:
 1. voltage time dependence
 2. pitch angle spread and energy spread together
 3. mode transformation due to the wall tapering, including TE and TM modes.

3.2 Quasi-optical Gyrotron Studies

During the coming year the following theoretical issues thought to be important to the operation of quasioptical gyrotrons will be addressed. This effort will be made in collaboration with scientists at the Centre de Recherches en Plasma Physique of the Ecole Polytechnique Federale de Lausanne.

- Generation of first harmonic radiation. Experiments conducted at CRPP indicate that a large amount of first harmonic radiation power circulates in the cavity. This circulating power level is estimated to be in excess of that in the fundamental. We will adopt our multimode codes to include radiation at the harmonics of the cyclotron

frequency and model the effect of the presence of the harmonic on the operation of the fundamental. Results will be compared with the previous CRPP experiment as well as the coming experiment in which the harmonic will be suppressed by a diffraction grating.

- Radiation power which does not couple to cavity modes. Existing models of quasi-optical gyrotrons assume that the radiation is well represented by a superposition of empty cavity modes. This is thought to be a good approximation so long as the output coupling is small and the cavity Q is high. In high power devices the output coupling will be increased and the previous approximation may no longer be valid. We will develop a model that allows for the self-consistent modification of the radiation field by the beam.

conf abstracts,
reprints & preprints
removed;
conf paper cycled
separately. ds

END

**DATE
FILMED**

5 / 20 / 92