AIM

Association for Information and Image Management

1100 Wayne Avenue, Suite 1100
Silver Spring, Maryland 20910
301/587-8202

Centimeter

Inches

MANUFACTURED TO AIM STANDARDS
BY APPLIED IMAGE, INC.

1 of 1

GA-A21326
UC-224

TFE VERIFICATION PROGRAM
SEMIANNUAL REPORT
FOR THE PERIOD ENDING MARCH 31, 1993

Prepared under
CONTRACT DE-AC03-86SF16298
FOR THE SAN FRANCISCO OPERATIONS OFFICE
DEPARTMENT OF ENERGY

GENERAL ATOMICS PROJECT 3450
MAY 1993

GENERAL ATOMICS

MASTER

yp

CONTENTS

	<u>Page</u>
1. INTRODUCTION	1
1.1 Objective of Progress Report	1
1.2 TFE Verification Program Goal	1
1.3 Technical Approach	1
1.4 Program Restructuring	4
2. CONCEPT DESIGN TASK	5
2.1 Objective	5
2.2 Technical Approach	5
2.3 System Definition Update	5
3. CONVERTER PERFORMANCE TASK	7
3.1 Objective	7
3.2 Task Description/Result of Program Restructuring	7
3.3 PC-1 (MOD) Testing	9
3.4 Converter Performance Under Transient Conditions	13
3.4.1 Apparatus and Test Article	13
3.4.2 Planned Tests	15
3.4.3 Initial Test Results	15
4. INSULATOR SEAL TASK	18
4.1 Objective and Technical Approach	18
4.2 Task Description	19
4.3 Design and Materials Downselection	20
4.4 In-Reactor Testing	21
4.5 Status Summary	23
5. SHEATH INSULATOR TASK	25
5.1 Objective and Technical Approach	25
5.2 Task Description	27
5.3 Design and Materials	28
5.4 Ex-Reactor Testing	28
5.5 In-Reactor Testing	28
5.5.1 UCA-3 Irradiation	32
5.5.2 IFAC-SI	32
6. FUELED EMITTER TASK	35
6.1 Objective and Technical Approach	35
6.2 Status of Test Articles	36
6.3 PIE of Fueled Emitters	40

CONTENTS

	<u>Page</u>
7. CESIUM RESERVOIR AND INTERCONNECTIVE TFE COMPONENTS	41
7.1 Objective	41
7.2 Task Description	41
7.3 Progress During Present Reporting Period	42
7.3.1 Background of the Temperature Gradient Tests	43
7.3.2 Experimental Procedures	45
7.3.3 Test Matrix	46
7.3.4 Experimental Results To Date	46
8. THERMIONIC FUEL ELEMENT	51
8.1 Objective	51
8.2 Task Description	51
8.2.1 Testing Logic	51
8.2.2 Program Restructuring	54
8.2.3 TFE Design	54
8.2.4 TRIGA Facility	58
8.3 TFE Testing	58
8.3.1 TFE Operations	58
8.3.2 TFE-3H1	59
8.3.3 TFE-3H5	59
8.3.4 Shipment Schedule	83

FIGURES

	<u>Page</u>
1-1 Logic to demonstrate technology readiness of megawatt class TFE	2
3-1 PC-1 (MOD) ignited J-V curves at 2472 hours	10
3-2 PC-1 (MOD) testing	11
3-3 PC-1 (MOD) testing	12
3-4 CC-1X cylindrical converter	14
3-5 Current density during simulated startup of CC-1X	17
4-1 Thermionic cell showing insulator locations	19
4-2 Insulator seal designs	20
5-1 Thermionic cell showing insulator locations	26
6-1 Road map: fueled emitter testing in EBR-II	37
6-2 UFAC irradiation schedule	39
7-1 Isothermal pressure vs UCA-3 data	48
7-2 Isothermal pressure vs UCA-3 data	48
7-3 Pressure-temperature relationship in a temperature gradient	49
7-4 Pressure-temperature relationship in a temperature gradient	49
7-5 Dual graphite reservoir model calculation	50
8-1 H-series thermionic converter (typical of 3H1)	56
8-2 TFEs for TRIGA test	57
8-3 3H1 I-V curves	60
8-4 3H5 operating history	62
8-5 Graphite Cs reservoir is thermally coupled to heater block - <u>and also</u> to emitter lead	63
8-6 3H5 I-V curves	64
8-7 3H5 electrical schematic	66
8-8 3H5 electrical schematic	67
8-9 TFE dummy cell configuration	70
8-10 Equivalent circuit of dummy cell and voltage probes	72
8-11 Equiv. circuit of dummy cell and voltage probes with shorting path R_2	73
8-12 3H5 VP1-3 measurements	74
8-13 3H5 VP1-3 measurements	76
8-14 3H5: R1 vs power dissipated in R1	77
8-15 3H5: VP1-VP3 resistance	79
8-16 3H5: VP1-VP3 resistance	80
8-17 3H5: VP1-VP3 resistance	81
8-18 3H5 VP1-3 resistance vs temperature	82

TABLES

	<u>Page</u>
2-1 TFE design definition	6
3-1 Ex-reactor planar converter test program	8
3-2 Ex-reactor cylindrical converter test program	8
4-1 In-reactor seal summary	22
4-2 Insulator seal development effort	24
5-1 Ex-reactor summary	29
5-2 In-reactor summary	33
5-3 Sheath insulator technology status	34
6-1 Fueled emitter design requirements	35
6-2 Summary status of UFAC test series in EBR-II as of Sept. 1, 1992	38
7-1 Test matrix	46
7-2 Asymmetric reservoir isothermal loading conditions	46
7-3 Cesium pressure data sets	47
8-1 Comparison of TFE test requirements with system baseline design requirements	52
8-2 TFE in-reactor test summary matrix	53
8-3 TFE test matrix	55
8-4 Pre-startup TFE-3H5 electrical resistance	68
8-5 Voltage readings on 11/6/92	69

1. INTRODUCTION

1.1 OBJECTIVE OF PROGRESS REPORT

The objective of the semiannual progress report is to summarize the technical results obtained during the latest reporting period. The information presented herein will include evaluated test data, design evaluations, the results of analyses and the significance of results.

1.2 TFE VERIFICATION PROGRAM GOAL

The program objective is to demonstrate the technology readiness of a TFE suitable for use as the basic element in a thermionic reactor with electric power output in the 0.5 to 5.0 MW(e) range, and a full-power life of 7 years.

1.3 TECHNICAL APPROACH

The TFE Verification Program builds directly on the technology and data base developed in the 1960s and early 1970s in an AEC/NASA program, and in the SP-100 program conducted in 1983, 1984 and 1985. In the SP-100 program, the attractive features of thermionic power conversion technology were recognized but concern was expressed over the lack of fast reactor irradiation data. The TFE Verification Program addresses this concern.

The general logic and strategy of the program to achieve its objectives is shown on Fig. 1-1. Five prior programs form the basis for the TFE Verification Program:

- 1) AEC/NASA program of the 1960s and early 1970s.
- 2) SP-100 concept development program.
- 3) SP-100 thermionic technology program.
- 4) Thermionic irradiations program in TRIGA in FY-86.
- 5) Thermionic Technology Program in 1986 and 1987.

These programs provide both the systems and technology expertise necessary to design and demonstrate a megawatt class TFE.

Figure 1-1

LOGIC TO DEMONSTRATE TECHNOLOGY READINESS OF MEGAWATT CLASS TFE

The approach to be followed is to design a TFE that will meet the reliability and lifetime requirements for the 2 MW(e) conceptual reactor design, and initiate component testing in a fast reactor. The demonstration of a 7-year component lifetime capability will be through the combined use of analytical models and accelerated, confirmatory tests. Iterative testing will be performed where the results of one test series will lead to evolutionary improvements in the next test specimens.

The TFE components will undergo screening and initial development testing in ex-reactor tests. Several design and materials options will be considered for each component. As screening tests permit, down selection will occur. It is necessary to rapidly make baseline design and materials selections to make optimum use of irradiation testing.

In parallel with ex-reactor testing, and fast reactor component testing, components will be integrated into a TFE and tested in the TRIGA. Realtime testing of partial length TFEs will be used to test support, alignment and interconnective TFE components, and to verify TFE performance in-reactor with integral cesium reservoirs. Realtime testing will also be used to verify the relation between TFE performance and fueled emitter swelling, to test the durability of intercell insulation, to check temperature distributions, and to verify the adequacy over time of the fission gas venting channels.

Predictions of TFE lifetime will rest primarily on the accelerated component testing results, as correlated and extended to realtime by the analytical models developed.

The fast reactor testing of fueled emitters will be calibrated by verifying the accuracy of emitter temperature predictions through complementary analysis and ex-reactor and in-reactor diagnostic tests. Instrumented sheath insulators will be tested in a fast reactor with an applied voltage.

A test of prototypic TFEs will be run in a fast reactor as a verification of the basic TFE design. This design may be upgraded based on the final component testing results.

The deliverables of the program are:

- 1) Conceptual design of a megawatt class power system including component specifications and a system description.
- 2) Thermionic components with verified performance.
- 3) TFE demonstration in a fast reactor.
- 4) Fabrication process specifications.
- 5) Verified performance models.

1.4 PROGRAM RESTRUCTURING

During 1992 a decision was made to restructure the TFE Verification Program and bring it to a close at the end of FY-94. It is possible that TRIGA operations and on-going tests will be continued in FY-95 and beyond in a follow-on technology program to be defined at a later date.

The details of this restructuring will be given in appropriate sections of this report.

2. CONCEPT DESIGN TASK

2.1 OBJECTIVE

Task 2 provides the design guidance for the TFE Verification Program. The primary goals of this task are:

- 1) Establish the conceptual design of an in-core thermionic reactor for a 2 MW(e) space nuclear power system with a 7-year operating lifetime.
- 2) Demonstrate scalability of the above concept over the output power range of 500 kW(e) to 5 MW(e).
- 3) Define the TFE which is the basis for the 2 MW(e) reactor design. This TFE specification will then be the basis for the test program.

2.2 TECHNICAL APPROACH

The technical approach being taken in the concept design effort can be characterized as follows:

- 1) Perform system-level tradeoffs to determine initial TFE features and reactor scalability trends;
- 2) Refine these results and identify the 2 MW(e) reactor general arrangement with primary emphasis on characterizing the features and performance of the TFE;
- 3) Enter this information into the program data base via two separate design description documents:
 - Two MW(e) reactor-converter system description.
 - TFE component specification.

2.3 SYSTEM DEFINITION UPDATE

The current description of the 2 MW(e) thermionic power system used to define the reference TFE for the program is shown on Table 2.1. This has not changed during the current reporting period.

TABLE 2-1
TFE DESIGN DEFINITION

PERFORMANCE	
Overall TFE:	
Output electrical power (We)	662
Efficiency	9.3
Maximum voltage	5.9 (15)
U-235 burnup (a/o)	4.1 avg, 5.3 peak
Fluence (nvt)	2.7×10^{22} avg, 3.5×10^{22} peak
Converter:	
Converter power (Wt/We)	594/55.2
Emitter power flux (We/cm ²)	2.72
Diode current density (a/cm ²)	7.0
Thermionic work function (eV)	4.9
Emitter temperature (K)	1800
Collector temperature (K)	1000
Cesium pd (mil-torr)	30
Converter output voltage	0.49
Converter current (amp)	140
CONFIGURATION	
Overall TFE:	
TFE length (active core) (in)	39.6
TFE length (overall)	TBD
Sheath tube o.d. (in)	0.694
Lead o.d. (in)	0.875
Lead length (in)	4
Converters per TFE	12
Converter:	
Emitter o.d. x L x t (in)	0.52 x 2.0 x 0.040
Emitter stem L x t (in)	0.45 x 0.020
Diode gap (in)	0.010
Trilayer t: collector	0.028
insulator (in)	0.016
outer cylinder	0.028
Fuel specification	93% enriched UO ₂ ; variable volume fraction
Intercell axial space (in)	0.74

3. CONVERTER PERFORMANCE TASK

3.1 OBJECTIVE

The objective of the converter performance task is to establish accurate converter performance models which have been correlated to observe test data. The data base will be developed from near prototypic converters using emitter and collector materials of interest over the full range of anticipated operating parameters. Part of the data base will include off-design and non-ideal operation of the converters. The resulting models will be used to determine the optimum converter configuration (materials, additives, spacing, etc.) for use in the prototypic TFE and reactor design.

A thermionic reactor is composed of a large array of thermionic cells, each of which has a unique input power, emitter temperature, and operating current density. In addition, individual cells will vary in performance over the system lifetime due to changing operating conditions caused by fuel burnup and variations in operating power requirement, or losses of some of the cells. Thus, the design and performance prediction of a thermionic reactor require an extensive data base on prototypical cell performance over a wide range of operating conditions.

The data and models will also be used in the startup of the TFEs in TRIGA and the FFTF and also in the startup of thermionic reactors. The observed current-voltage data during startup can be related to system temperatures through the ex-reactor correlations.

3.2 TASK DESCRIPTION/RESULT OF PROGRAM RESTRUCTURING

The reference test matrix had been as shown on Tables 3-1 and 3-2. Planar Converter-1 (PC-1) is a planar (variable spacing) converter with a tungsten $\langle 110 \rangle$ emitter, a niobium collector and a graphite cesium reservoir external to the converter. The emitter has a small cavity for accepting a fuel pellet of depleted uranium oxide. The converter designation with the UO_2 pellet in the converter is PC-1 (Mod). The initial

TABLE 3-1
EX-REACTOR PLANAR CONVERTER TEST PROGRAM

	Emitter	Collector	Cs Reservoir	Rationale for Test
PC-1	Duplex W*	Nb	Graphite	Performance map with graphite-cesium reservoir.
PC-2	Duplex W	Nb tilted	Pool	A verification of the model which relates converter output to emitter distortion
PC-3	High Strength Emitter	Nb	Pool	Establish data base on performance with high strength emitter
PC-1 (MOD)	Duplex W*	Nb	Graphite	UO ₂ in contact with the emitter. Differential data on the UO ₂ effect will be obtained during a life test.

*To be combined into one experiment to be designated PC-1 (MOD).

TABLE 3-2
EX-REACTOR CYLINDRICAL CONVERTER TEST PROGRAM

	Emitter	Collector	Reservoir	Life Test	Rationale for Test
CC-1	Duplex W	Nb	Graphite	No	Performance map with reference electrodes and reservoir

performance maps would be characteristic of a thermionic device with no oxygen on the electrode surfaces. The subsequent life test will show the effects of oxygen diffusion.

PC-2 provided data on converter performance with reference electrodes but with the electrodes not uniformly spaced. These tests have been finished.

PC-3 was to have been a test with a high strength emitter. This test has been dropped from the program.

CC-1 provided data on converter performance with reference electrodes and a graphite-cesium reservoir. Initial tests were completed but additional testing simulating various transient conditions, e.g., startup, has begun.

3.3 PC-1 (MOD) TESTING

As of February 10, 1993, converter PC-1 had accumulated 2470 hours with the emitter at a constant temperature of about 1800 K. Periodic sweeps of the ignited J-V characteristics for various cesium-graphite reservoir temperatures, such as that shown in Fig. 3-1, have been performed under the following conditions:

Emitter temperature	1800 K
Collector temperature	1070 K
Interelectrode gap	10 mils

Prior to each periodic sweep, the data acquisition system was checked by running known currents and voltages through it. Simultaneously, the emitter temperature was checked with an optical pyrometer.

Some evolution appears to have already occurred. In Fig. 3-2, the current density J_k at the knee of the J-V curve is plotted for two reservoir temperatures versus elapsed time. The initial data obtained at TTC during the converter processing are plotted at time zero. A general rise is obtained.

Figure 3-1 - PC-1(MOD) Ignited J-V curves at 2472 hours.

Figure 3-2 - PC-1 (MOD) testing.

In Fig. 3-3, the barrier index V_B measured from the recorded J-V families at 5 and 15 A/cm² is plotted versus time. The initial data at 15 A/cm² is missing because the reservoir temperature was not high enough to get an accurate envelope of the J-V curves. While V_B (5 A/cm²) remains nearly constant, V_B (15 A/cm²) exhibits a small decline.

Using TECMDL, a simple correlation between the current density at the knee J_k and the saturation current density J_s can be derived:

$$\frac{J_s}{J_k} = 1 + \frac{pd}{30} ,$$

where p is the cesium pressure in torr and d the interelectrode spacing in mils.

Figure 3-3 - PC-1 (MOD) testing.

With a knowledge of J_s , the cesiated work function, O , can be determined using the Richardson equation. The bare work function, O_0 , can then be determined from a Rasor plot. This method is not very sensitive to the choice of J_s since an error in J_s of 50% results in an uncertainty in O_0 of only .05 eV.

The initial current densities measured at TTC are consistent with an emitter bare work function O_0 in the range 4.90-4.95 eV. The increase in current densities of Fig. 3-2 could then be interpreted as a small increase in O_0 of .03-05 eV. It could also have been caused by an increase in the cesium pressure in equilibrium with the graphite compound, but this can be ruled out since the output voltage in the obstructed mode would have then decreased, which was not the case. On the contrary, the output voltage rose by .025 V over the same period.

The small increase in ϕ_o is also consistent with the drop in $V_b(15)$. We believe that $V_b(5)$ is dominated by back emission and does not related easily to the emitter work function.

The effect is still quite small and we cannot conclude yet that the small increase in ϕ_o is due to oxygen diffusion through the cladding.

3.4 CONVERTER PERFORMANCE UNDER TRANSIENT CONDITIONS

The objective of these tests is to determine converter performance for various relationships between the electrode temperatures and the cesium-graphite reservoir temperature around the steady state design point and also during converter startup.

3.4.1 Apparatus and Test Article

The CC-1X laboratory converter, shown in Fig. 3-4 has an external graphite cesium reservoir for which the pressure vs temperature relationship has been experimentally determined. This reservoir is heated by an auxiliary electric heater, as opposed to a prototypic arrangement in the TFE in which the reservoir is thermally coupled to the emitter. The CC-1X emitter, which is much thicker than prototypic, is equipped with four thermocouple probes which can accurately measure its temperature profile. Other characteristics of CC-1X are:

Emitter area:	20 cm ₂
Emitter material:	Duplex tungsten
Collector material:	Niobium
Interelectrode gap:	10 mils
Cs reservoir:	POCO graphite
Cs pressure:	$P = 3 \times 10^6 \exp(-14177/T_R)$

Figure 3-4 - CC-1X cylindrical converter.

Test stand instrumentation will be developed to:

- 1) Make the cesium reservoir controller programmable.
- 2) Permit coupling between the graphite reservoir temperature and the emitter and/or collector temperatures.
- 3) Permit a specially-controlled power supply to simulate a load resistance during both startup and steady state operation.

The reservoir-emitter and reservoir-collector thermal couplings are simulated by programming the cesium-graphite reservoir temperature to maintain the desired relationship with the emitter and/or collector temperatures.

3.4.2 Planned Tests

The converter will be tested under conditions simulating the steady-state design operating point. The effect of reservoir-emitter thermal coupling on thermionic stability will be measured to determine what relationship between emitter temperature and cesium pressure will avoid "cesium burnout" over the anticipated range of operating conditions:

T_E	=	1700 - 1900 K
T_c	=	800 - 1000 K
P_{Cs}	=	0.5 - 5 torr
d	=	10 mils
J	=	0-10 amp/cm ₂
Q_{emit}	=	10-40 W/cm ₂

For each reservoir-emitter coupling, the emitter heating will be gradually increased until burnout begins or a safety limit of 2000 K is reached, thus mapping the extent of the desirable operating range. A safety circuit will prevent overheating of the emitter due to cesium burnout.

The converter will be tested under conditions simulating startup, with the converter initially short-circuited. The emitter heater power will then be gradually increased. The effect of the emitter temperature-cesium pressure relationship on the time history of the emitter temperature and other parameters will be determined.

3.4.3 Initial Test Results

To check out of the test procedures and equipment, a simulated startup transient was run.

A 0.5 milliohm resistor was connected across the emitter and collector current leads where they exit the high-vacuum test system. Together with the leads and connections internal to the bell jar, this gave an effective load resistance of about 4.67 milliohms across the converter. Current through the load was monitored by the voltage reading across the 0.5 milliohm resistor, while voltage was read from the emitter and collector voltage probes.

Emitter heater power was then slowly raised. The emitter temperature profile was measured by four W-5%Re/W-26%Re thermocouple probes inserted at different depths. As the emitter heated up, the graphite cesium reservoir temperature was increased so as to keep a constant ratio between the temperature at one of the emitter thermocouples and the reservoir temperature. The ratio was chosen to give a cesium pressure of about 3 torr at the final operating emitter temperature of 1800 K. More realistic formulas will be used for later runs. The reservoir temperature was allowed to come to equilibrium at each level of input power.

Figure 3-5 shows the current density as a function of percent of full thermal input power (full power is taken to be 650 Watts). Ignition occurred at 48.5% power, resulting in a sudden current density increase from 11.6 to 94.2 amps. The current decreased over about 40-50 seconds to about 50 amps due to emitter cooling. The emitter temperature dropped by about 140 K. Thermal input power continued to increase, finally bringing the average emitter temperature to 1770 K.

In retrospect, the simple linkage of reservoir temperature to emitter temperature overestimated the decrease in cesium pressure when the emitter temperature dropped after ignition. The prototypic case has linkage both to the emitter and coolant temperatures. Whereas the emitter cools off at ignition, the coolant will not. Some sort of linkage rule which involves both the emitter and collector temperatures could possibly simulate prototypic behavior.

Figure 3-5 - Current density during simulated startup of CC-1X.

4. INSULATOR SEAL TASK

4.1 OBJECTIVE AND TECHNICAL APPROACH

The overall objective of the insulator seal task is to develop and validate the performance of an insulator seal for use in the thermionic fuel element reference design. In particular, the objectives are:

1. Produce designs for the insulator seal.
2. Develop required fabrication processes for the insulator seals designed and document the process specifications.
3. Fabricate insulator seals for ex-reactor and in-reactor testing.
4. Verify the performance characteristics and lifetimes associated with insulator seals by means of ex-reactor and in-reactor testing. Perform postirradiation examination of the seal specimens and use the test results to improve the seal design.
5. Develop an analytical model of the performance and lifetime of the insulator seal and validate the model with test data.

The insulator seal, shown schematically in Fig. 4-1, must provide electrical isolation between adjacent collectors while maintaining a leak-tight seal separating the cesium vapor of the interelectrode space from the fission products. The current design requirements are listed below:

1.	Insulator temperature	1070 to 1150 K
2.	Nominal fast fluence, $E > 0.1$ MeV	2.3×10^{22} n/cm ²
3.	Nominal applied voltage	0.49 volts
	Maximum applied voltage	0.63 volts
4.	Operating environment	1-3 torr Cs and fission gases
5.	Leak tightness	$< 2 \times 10^{-11}$ std cc/s (fabricated)
$< 5 \times 10^{-5}$ std cc/s (end lifetime)
6.	Electrical resistance	> 10 ohms (1150 K)
7.	Lifetime	≥ 7 years

Figure 4-1 - Thermionic cell showing insulator locations

4.2 TASK DESCRIPTION

The insulator seal task consists of five subtasks:

1. Seal design. Seal designs consistent with the TFE requirements are to be developed. Designs being considered are the taper seal, the butt seal and trilayer seal.

2. Fabrication development. Select appropriate insulator materials. Develop appropriate bonding techniques for each insulator material selected. Fabricate sufficient insulator seal specimens to support the ex-reactor and in-reactor test effort. Prepare and issue process specifications. Insulator materials considered are alumina (Al_2O_3), yttria (Y_2O_3), and YAG ($\text{Y}_3\text{Al}_5\text{O}_{12}$).
3. Ex-reactor testing. Perform ex-reactor tests to evaluate the effects of thermal cycling, cesium compatibility, applied voltage and material interdiffusion on insulator seal performance and lifetime.
4. In-reactor testing. Perform in-reactor tests and the related post-irradiation examinations to determine seal mechanical stability, electrical resistance and hermeticity after exposure to fast neutron fluences.
5. Modeling. Develop and validate analytical models to predict seal lifetime and performance.

4.3 DESIGN AND MATERIALS DOWNSelection

The seal design has been downselected to the taper and trilayer configurations as shown in Fig. 4-2. The trilayer design is similar in technology to the sheath

Figure 4-2. Insulator seal designs

insulator (Task 5). The insulator materials used for the taper seal are single crystal alumina, polycrystalline alumina and polycrystalline YAG. PIE results of the UCA-2 single crystal YAG taper seal shows that YAG has good neutron damage resistance and requires additional testing. YAG exhibits considerably less swelling than alumina but is not as strong. The insulator material selected for the trilayer seal is alumina in either the graded or cermet configurations.

4.4 IN-REACTOR TESTING

The objectives of the in-reactor test program is to determine the integrated performance of leading insulator seals in uninstrumented fast reactor environment tests (UCA and UFAC).

Table 4-1 summarizes all of the in-reactor tests performed on insulator seals since the beginning of the TFE Verification Program.

UCA-3 is the last in the series of in-reactor component testing. It incorporates results from ex-reactor testing as well as results from the postirradiation examination of UCA-1 and UCA-2 insulator seals. Irradiation of Batch A started in cycle 156 of EBR-II in December, 1990 and ended in March, 1991 with a total of 95 EFPD and an estimated peak fast fluence of 1.5×10^{22} n/cm² (E > .1 MeV). Batch B was irradiated in cycles 157 and 158 of EBR-II with irradiation ending on January 19, 1992. Batch B samples accumulated a total of 110 EFPD with an estimated peak fast fluence of 1.8×10^{22} n/cm² (E > .1 MeV).

Terminal nondestructive examinations were completed at the Hot Fuels Examination Facility. Examinations included visual examination of the sample capsules and neutron radiography at three orientations. The radiography showed that the tapered seals with single crystal aluminum oxide have local distortions at the ceramic-to-metal interface similar to those seen on other irradiated single crystal aluminum oxide taper seals. The polycrystalline taper YAG seal and the trilayer seals with

Table 4-1

IN-REACTOR SEAL SUMMARY

TEST SN	MATERIAL AND PROCESS	FLUENCE (md)	TEMPERATURE IRRADIATION	PIE VISUAL	DIMENSIONAL RADIAL AXIAL	PIE RESISTANCE Ohms	PIE He LEAK RATE Std cc/sec	PIE METALLOGRAPHY
UCA-1	FFTF 9/86 - 10/87	9164 hours						
B-1	AL2O3-Gas pressure	3.00E+22	1094 K	Axial cracks	-0.16%	1.6x10+6 (1173 K - 1V)	1	
B-2	AL2O3-Gas pressure	4.10E+22	1114 K	Axial cracks, separated	-0.16%	2.1x10+6 (1173 K - 1V)	1	
B-4	AL2O3-Gas pressure	7.10E+22	1156 K	Axial cracks, separated				
L-1	AL2O3-Taper	3.90E+22	1126 K	Distortion Al2O3-Nb Int.	0.31%	3.1x10+7 (1173 K - 1V)	0.5	Crack through Al2O3
L-2	AL2O3-Taper	3.10E+22	1110 K	Distortion Al2O3-Nb Int.	0.77%	5.2x10+7 (1173 K - 1V)	0.5	
L-3	AL2O3-Taper	7.20E+22	1159 K	Distortion Al2O3-Nb Int.	-0.77%	9.9x10+7 (1173 K - 1V)	0.1	
T-1	Y2O3-Trilayer-Graded	3.00E+22	1113 K	Circum cracks at ends	0.46%	162 (1173 K - 1V)	1x10-8	
T-2	Y2O3-Trilayer-Graded	3.00E+22	1113 K	Circum cracks at ends	0.31%	130 (1173 K - 1V)	1	
T-3	Y2O3-Trilayer-Graded	7.20E+22	1170 K	Circum cracks at ends	0.92%	53 (1173 K - 1V)	1	
UCA-2	FFTF 11/87 - 1/89	8040 hours						
003	AL2O3-Taper	4.40E+22	1115 K	Distortion Al2O3-Nb Int.	0.20%	7.1x10+8 (1214 K - 1V)	0.5	Crack through Al2O3
001	YAG-Taper	5.50E+22	1162 K	No cracks or distortion	0.15%	6.9x10+3 (1212 K - 1V)	1	Crack through YAG
297B	Y2O3-Trilayer-Graded	3.80E+22	1138 K	Circum cracks at ends	0.57%	219 (12083 K - 1V)	1x10-2	
280B	Y2O3-Trilayer-Graded	4.00E+22	1135 K	Circum cracks at ends	0.46%	338 (1209 K - 1V)	1x10-2	Axial cracks
UFAC-3	EBR-II 1/90 - 9/90	4080 hours						
A-III	AL2O3-Taper	2.40E+22	1198 K	Distortion Al2O3-Nb Int.				Fractured during handling
A-MT	AL2O3-Metalized ring	2.50E+22	1229 K	No cracks	-0.75	5.30%		
A-CR	AL2O3-ring	2.50E+22	1252 K	No cracks	-0.83	4.96%		
YAG-I	YAG-Taper	2.60E+22	1279 K	No cracks or distortion	-0.53%	0.33%	.4	
YAG-II	YAG-Taper	2.70E+22	1220 K	No cracks or distortion	-0.25%	0.55%	.04	
YAG-III	YAG-Taper	2.80E+22	1233 K	No cracks or distortion	-0.32%	0.40%	.06	
YAG-MT	YAG-Metalized ring	2.50E+22	1228 K	No cracks	-0.44%	0.04%		
YAG-CR	YAG-ring	2.50E+22	1248 K	No cracks	-0.41%	0.16%		
S-I	Top Nb skirt	2.40E+22	1208 K	No distortion				Damaged during removal from capsule
S-II	Bottom Nb skirt	2.60E+22	1270 K	No distortion	-0.10%	-0.50%		
UCA-3A	EBR-II 6/90 - 4/91	2280 hours						
SC-1	AL2O3-Taper	1.50E+22	1150 K	Distortion Al2O3-Nb Int.				
SC-2	AL2O3-Taper	1.50E+22	1150 K	Distortion Al2O3-Nb Int.				
UCA-3B	EBR-II 5/91 - 2/92	2640 hours						
SC-3	AL2O3-Taper	1.80E+22	1150 K					
1439	AL2O3-Taper-(Nb-Zr)	1.80E+22	1150 K					
Y-NbV-1	YAG-Taper	1.80E+22	1150 K					
1606	YAG-ring	1.80E+22	1150 K					
1607	YAG-ring	1.80E+22	1150 K					
1392	Top Nb skirt	1.80E+22	1150 K					
1616	AL2O3-Trilayer-Graded	1.80E+22	1150 K					
1617	AL2O3-Trilayer-Graded	1.80E+22	1150 K					
1620	AL2O3-Trilayer-Cer. 5%	1.80E+22	1150 K					
1621	AL2O3-Trilayer-Cer. 5%	1.80E+22	1150 K					
1623	AL2O3-Trilayer-Cer. 10%	1.80E+22	1150 K					
1629	AL2O3-Trilayer-Cer. 10%	1.80E+22	1150 K					

graded aluminum oxide and aluminum oxide cermets with 5 and 10% niobium particles showed excellent structural stability and are similar to their preirradiated appearance. The sample capsules will be shipped to WHC in March, 1993 for detailed examination. Detailed examination requirements were drafted and are being reviewed prior to submittal to the hot cell for preparation of examination procedures.

4.5 STATUS SUMMARY

The current reference insulator seal specifications are summarized below:

Insulator material: Polycrystalline alumina

Design: Trilayer

Fabrication: Plasma sprayed-HIP.

The insulator seal backups are:

Taper polycrystalline YAG

Taper polycrystalline alumina.

The alumina trilayer design used in the sheath insulator task (Task 5), has remained hermetic after irradiation to three times the nominal fluence expected for the insulator seals and has been selected as the reference design. The single crystal alumina taper seal was the reference insulator seal but it was dropped as a reference since it has failed to remain hermetic after irradiation.

The polycrystalline alumina taper seal has experienced over 30,000 real time test hours in the TRIGA reactor, good evidence that its lifetime is at least several years. YAG is also being carried as a backup because of its low irradiation induced swelling and good electrical properties. More fabrication development and testing, both in-reactor and ex-reactor, are needed for YAG.

Table 4-2 summarizes the seal development effort so far.

Table 4-2
INSULATOR SEAL DEVELOPMENT EFFORT

Material	Design	Electrical Properties	Neutron Stability	Fabricability	Test Matrix (No. of Specimens)				
					UCA-1	UCA-2	UFAC-3	UCA-3	TFE 1H1, 1H2, 1H3, 3H1, 3H5, 6H1
Alumina	Taper SC	Good	Poor	Good	3	1	1	4	
YAG	Taper SC	Good	Good	Good		1			
Alumina	Taper PC	Good	Acceptable*	Good					19
YAG	Taper PC	Good	Good	Good			3	1	
Alumina	Trilayer Graded	Good	Good	Good	6	2		2	
Alumina	Trilayer Cermet	Good	Good	Good	3	2		4	9

PC Polycrystalline

SC Single crystal

* Good to a fluence of 5×10^{21} nvt ($E_n > 0.1$ MeV)

5. SHEATH INSULATOR TASK

5.1 OBJECTIVE AND TECHNICAL APPROACH

The overall objective of the sheath insulator task is to develop and validate the performance of a sheath insulator for use in the TFE reference design. In particular, the objectives are:

1. Produce designs for the sheath insulator.
2. Develop required fabrication processes for the sheath insulators designed and document the process specifications.
3. Fabricate sheath insulators for ex-reactor and in-reactor (uninstrumented and instrumented) testing.
4. Verify the performance characteristics and lifetimes associated with sheath insulators by means of ex-reactor and in-reactor testing.
5. Develop an analytical model of the performance and lifetime of the sheath insulator and validate the model with test data.

The sheath insulator, shown schematically in Fig. 5-1, must provide electrical isolation between the collector of each converter and the outer sheath tube. The outer sheath tube is in contact with the reactor liquid metal coolant. The sheath insulator must also provide good thermal conduction between the collector and the sheath tube. The current design requirements are listed below:

1.	Insulator temperature	1070 K
2.	Nominal fast fluence, $E > 0.1$ MeV	2.3×10^{22} n/cm ²
3.	Nominal applied voltage	5.9 volts
	Maximum applied voltage	7.5 volts
4.	Operating environment	Fission gases
5.	Electrical resistance	> 1000 ohms (1070 K)
6.	Thermal conductivity	> 0.03 W/cm-K)
7.	Lifetime	≥ 7 years

Figure 5-1. Thermionic cell showing insulator locations.

The technical concerns are the unbonding of the sheath insulator structure due to fast neutron induced damage, and electrolysis that could lead to low electrical resistance, and electrical breakdown. The objective of the sheath insulator task is to resolve these concerns and to develop and validate the performance of a sheath insulator for use in a prototypic TFE.

5.2 TASK DESCRIPTION

The sheath insulator task consists of five subtasks:

1. **Sheath design.** Sheath designs consistent with the TFE requirements are to be developed. The current design is the trilayer, consisting of an insulator between the niobium collector and the outer niobium sheath tube.
2. **Fabrication development.** Select appropriate insulator materials. Develop appropriate fabrication techniques for each insulator material selected. Fabricate sufficient sheath insulator specimens to support the ex-reactor and in-reactor test efforts. Prepare and issue process specifications. Insulator materials being considered are alumina (Al_2O_3), yttria (Y_2O_3), and YAG ($\text{Y}_3\text{Al}_5\text{O}_{12}$). The fabrication techniques include plasma spraying the insulator onto the niobium collector, and thermal bonding of free standing ceramic tubes to the collector.
3. **Ex-reactor testing.** Perform ex-reactor tests to evaluate the effects of thermal cycling, applied voltage and material interdiffusion on the sheath insulators performance and lifetime.
4. **In-reactor testing.** Perform uninstrumented and instrumented in-reactor tests and the related postirradiation examinations. Determine the sheath insulator mechanical stability, electrical resistance and thermal conductivity after exposure to fast neutron fluence with and without an applied voltage.
5. **Modeling.** Develop and validate analytical models to predict sheath insulator lifetime and performance.

5.3 DESIGN AND MATERIALS

Two manufacturing processes and one insulator material are currently being evaluated. The manufacturing processes are the plasma sprayed graded trilayer being developed at GA and the cermet trilayer being developed at Thermo Trex Corporation (TTC), formerly Thermo Electron Technologies. The insulator material under investigation is aluminum oxide.

5.4 EX-REACTOR TESTING

Rasor Associates, Inc. (RAI) performs all the ex-reactor testing of the sheath insulators. Tests include long term tests at the nominal operating temperature (1070 K) and applied potential (7.5 volts), and accelerated tests at higher temperatures (1170 K and 1270 K) and higher applied potentials (30, 50 and 100 volts).

Testing of the FY-91 samples was terminated. Nine out of the twelve samples were tested for a total of 469 days. The last 377 days were at the accelerated potential of 100 volts. The performance of these samples as a function of time, temperature, and potential was very good. The three cermet samples with 10% niobium failed under accelerated conditions.

Table 5-1 summarizes all of the ex-reactor tests performed on sheath insulators since the start of the TFE Verification Program.

5.5 IN-REACTOR TESTING

The objectives of the in-reactor test program are:

1. Determine the integrated performance of leading sheath insulators in uninstrumented fast reactor environment tests (UCA).
2. Determine the on-line performance of selected sheath insulators in instrumented fast reactor environment tests (IFAC-SI).

Table 5-1

EX-REACTOR SUMMARY

SERIAL NUMBER	MATERIAL	PROCESS	TEMPERATURE	POTENTIAL	TIME (HOURS)	RESISTANCE END	ACTIVATION ENERGY	COMMENTS
Y1	YTTRIA	GA GRADED	1100 K	15 V	354	< 100		Failed, carbon contamination
Y2	YTTRIA	GA GRADED	1030 K	10 V	838	< 100		Failed, carbon contamination
245	ALUMINA	GA GRADED	1130 K	10 V	2267	4.00E+08		Heater failure
244	YTTRIA	GA GRADED	1060 K	10 V	16	< 100		Failed, carbon contamination
247	YAG	GA GRADED	1120 K	10 V	500	2.80E+03		Test completed
250	ALUMINA	GA GRADED	1094 K	10 V	7031	3.00E+08	2.15 eV	Test completed
251	ALUMINA	GA GRADED	1094 K	10 V	7031	2.00E+08	2.15 eV	Test completed
252	ALUMINA	GA GRADED	1094 K	10 V	4752	7.10E+08	2.15 eV	Test completed
253	YTTRIA	GA GRADED	1120 K	10 V	28	< 100		Failed, carbon contamination
254	YTTRIA	GA GRADED	1120 K	10 V	339	< 100		Failed, carbon contamination
255	YAG	GA GRADED	1096 K	10 V	6931	1.10E+04	1.92 eV	Test completed
317	ALUMINA	GA GRADED	1020 K	10 V	24	2.00E+08		UCA-2 Sample S/N 317
333	YAG	GA GRADED	1050 K	10 V	24	2.00E+03		UCA-2 Sample S/N 333
334	YAG	GA GRADED	1020 K	10 V	24	2.00E+03		UCA-2 Sample S/N 334
346	YTTRIA	GA GRADED	1050 K	10 V	24	6.00E+05		UCA-2 Sample S/N 346
467	YTTRIA	GA GRADED	995 K	10 V	792	5.70E+04		Heater failure
471	YTTRIA	GA GRADED	1050 K	10 V	792	5.90E+04		Heater failure
472	YTTRIA/ALUMINA	GA GRADED	1110 K	10 V	792	3.70E+04		Heater failure
473	YTTRIA/CERIA	GA GRADED	1090 K	10 V	168	1.25E+02		Failed, shorted
474	YTTRIA/ZIRCONIA	GA GRADED	970 K	10 V	792	1.10E+04		Heater failure
735	ALUMINA	GA GRADED	1100 K	7.5 V	360	1.00E+08	1.93 eV	Vacuum failure
736	ALUMINA	GA GRADED	1100 K	7.5 V	360	1.00E+08	2.5 eV	Vacuum failure
737	ALUMINA	GA GRADED	1100 K	7.5 V	360	1.00E+08	2.5 eV	Vacuum failure
738	ALUMINA	GA GRADED	1100 K	7.5 V	360	1.00E+08	2.5 eV	Vacuum failure
739	ALUMINA	GA GRADED	1100 K	7.5 V	360	1.00E+08	2.1 eV	Vacuum failure
740	ALUMINA	GA GRADED	1250 K	7.5 V	1560	1.08E+08	2.76 eV	Test stopped
741	ALUMINA	GA GRADED	1250 K	7.5 V	1560	1.11E+08	2.79 eV	Test stopped
742	YTTRIA	GA GRADED	1250 K	7.5 V	2256	3.67E+02	2.28 eV	Failed, short
743	YTTRIA	GA GRADED	1250 K	7.5 V	2256	9.23E+02	2.27 eV	Failed, short
744	YTTRIA	GA GRADED	1250 K	7.5 V	2256	3.20E+01	2.4 eV	Failed, short
745	YTTRIA	GA GRADED	1250 K	7.5 V	2256	6.00E+01	2.4 eV	Failed, short
1108	ALUMINA	GA GRADED	1250 K	7.5 & 30 V	3696 TOTAL	6.93E+07	2.41 eV	Test stopped
1109	ALUMINA	GA GRADED	1250 K	7.5 & 30 V	3696 TOTAL	6.60E+07	2.41 eV	Test stopped
1110	ALUMINA	GA GRADED	1150 K	7.5 V	1440	5.77E+07		Furnace problems
1111	ALUMINA	GA GRADED	1150 K	7.5 V	1440	7.50E+08		Furnace problems
1112	ALUMINA	GA GRADED	1050 K	7.5 & 30 V	3696 TOTAL	1.54E+10		Test stopped
1113	ALUMINA	GA GRADED	1050 K	7.5 & 30 V	3696 TOTAL	9.58E+09		Test stopped
1114	YTTRIA	GA GRADED	1250 K	7.5 V	312	< 100		Test stopped
1115	YTTRIA	GA GRADED	1250 K	7.5 V	528	< 100		Test stopped
1116	YTTRIA	GA GRADED	1150 K	7.5 & 30 V	2208 TOTAL	< 100		Test stopped
1117	YTTRIA	GA GRADED	1050 K	7.5 & 30 V	3696 TOTAL	2.13E+04		Test stopped
1342	YTTRIA	GA GRADED	1270 K	7.5 V	960	4.00E+01		Failed, short

Table 5-1

EX-REACTOR SUMMARY (Continued)

1343	YTTRIA	GA GRADED	1170 K	7.5 & 30 V	2232 TOTAL	7240/ 7.5 V	Failed, short
1344	YTTRIA	GA GRADED	1070 K	7.5 & 30 V	2472/TOTAL	4.20E+04	Failed, short
1345	ALUMINA	GA GRADED	1270 K	7.5, 30, 50 & 100V	6048/TOTAL	6.9E+7/100V	Test completed
1346	ALUMINA	GA GRADED	1170 K	7.5, 30, 50 & 100V	6048/TOTAL	1.3E+9/100V	Test completed
1347	ALUMINA	GA GRADED	1070 K	7.5, 30 & 50 V	4560/TOTAL	2.06E+10/50V	Test completed
1348-A	ALUMINA	GA GRADED	1270 K	7.5, 30, 50 & 100 V	6048 TOTAL	1.4E7 / 100 V	Test completed
1348-B	ALUMINA	GA GRADED	1170 K	7.5, 30, 50 & 100 V	6048 TOTAL	1.4E9 / 100 V	Test completed
1348-C	ALUMINA	GA GRADED	1070 K	7.5, 30, 50 & 100 V	4560 TOTAL	2.04E10 / 50 V	Test completed
1685	ALUMINA	GA GRADED	1270 K	100 V	9048	3.90E+08	Test stopped
1686	ALUMINA	GA GRADED	1170 K	100 V	9048	3.50E+09	Test stopped
1687	ALUMINA	GA GRADED	1070 K	100 V	8160	2.80E+10	Test stopped
1705A	ALUMINA	GA GRADED	1270 K	100 V	9048	5.70E+08	Test stopped
1705B	ALUMINA	GA GRADED	1170 K	100 V	9048	4.90E+07	Test stopped
1705C	ALUMINA	GA GRADED	1070 K	100 V	9048	1.30E+09	Test stopped
1-24-1	ALUMINA	CERMET	1100 K	10 V	48		Failed, short
1-24-1	ALUMINA	CERMET	1100 K	10 V	48		Failed, short
1-36-3	ALUMINA	CERMET	1100 K	10 V	48		Failed, short
1-36-5	ALUMINA	CERMET	1100 K	10 V	48		Failed, short
AL-1	ALUMINA	CERMET 10%	1130 K	10 V	96	< 100	Failed, short
AL-2	ALUMINA	CERMET 10%	1130 K	10 V	2602	3.00E+07	Heater failure
AL-4	ALUMINA	CERMET 10%	1086 K	10 V	4752	7.10E+08	Test completed
Y-0	YTTRIA	SLIP CAST	1130 K	10 V	1253	< 300	Failed, short
001-1	YTTRIA	CERMET 10%	1074 K	7.5 V		50	Failed, short
001-2	YTTRIA	CERMET 10%	1074 K	7.5 V		50	Failed, short
001-3	YTTRIA	CERMET 10%	1074 K	7.5 V		50	Failed, short
082688-001	YTTRIA	SLIP CAST	1250 K	7.5 V	2496	52.9	Failed, short
082688-002	YTTRIA	SLIP CAST	1250 K	7.5 V	2496	8.32	Failed, short
082688-003	YTTRIA	SLIP CAST	1250 K	7.5 V	2496	7.01	Failed, short
082688-004	YTTRIA	SLIP CAST	1250 K	7.5 V	2496	15.4	Failed, short
100588-001	ALUMINA	CERMET 10%	1250 K	7.5 V	2496	278	Failed, short
100588-002	ALUMINA	CERMET 10%	1250 K	7.5 V	2496	1.48E+04	Failed, short
111088-001	ALUMINA	CERMET 10%	1250 K	7.5 V	2496	1.17E+07	Test stopped
111088-002	ALUMINA	CERMET 10%	1250 K	7.5 V	2496	1.11E+07	Test stopped
111688-01	ALUMINA	CERMET 15%	1100 K	7.5 V	150		Failed, short
111688-02	ALUMINA	CERMET 15%	1130 K	7.5 V	24		Failed, short
051089-01	YAG	SLIP CAST	1090 K	7.5 V	1100	2.10E+04	Test stopped
Sapphire 1	ALUMINA	SINGLE CRYSTAL	1250 K	7.5 V	750	3.00E+06	No temp. dependance
Sapphire 2	ALUMINA	SINGLE CRYSTAL	1250 K	7.5 V	750	3.00E+06	No temp. dependance
021B-1	ALUMINA	CERMET 10%	1300 K	7.5 V	450	9.00E+05	Test stopped
021B-2	ALUMINA	CERMET 10%	1310 K	7.5 V	450	7.00E+05	Test stopped
025B-1	YTTRIA	SLIP CAST	1280 K	7.5 V	12	15	Failed, short
033-1	ALUMINA	CERMET 5%	1330 K	7.5 V	500	5.00E+05	Test stopped
033-2A	ALUMINA	CERMET 5%	1270 K	7.5, 30, 50 & 100 V	5568/Total	4.12E-5 / 100 V	Test stopped
033-2B	ALUMINA	CERMET 5%	1170 K	7.5, 30, 50 & 100 V	6048/Total	1.40E-7 / 100 V	Test stopped

Table 5-1

EX-REACTOR SUMMARY (Continued)

033-2C	ALUMINA	CERMET 5%	1070 K	7.5, 30 & 50 V	4560/Total	3.01E+9 / 50 V		Test stopped
034 A	ALUMINA	CERMET 5%	1280 K	7.5 V	500	1.00E+06		Test stopped
039-1A	ALUMINA	CERMET 5%	1270 K	7.5, 30, 50 & 100 V	6048/Total	1.10E+6 / 100 V	2.2 eV	Test stopped
039-1B	ALUMINA	CERMET 5%	1170 K	7.5, 30, 50 & 100 V	6048/Total	1.90E+7 / 100 V	2.5 eV	Test stopped
039-1C	ALUMINA	CERMET 5%	1070 K	7.5, 30 & 50 V	4560/Total	3.66E+9 / 50 V		Test stopped
039-2A	ALUMINA	CERMET 5%	1300 K	7.5 V	450	9.00E+05		Test stopped
040-2	ALUMINA	CERMET 10%	1300 K	7.5 V	100	1.80E+02		Failed, short
040-6B	ALUMINA	CERMET 10%	1100 K	7.5 V	1	3.00E+02		Failed, short
040-6C	ALUMINA	CERMET 10%	1100 K	7.5 V	1	1.00E+02		Failed, short
041-1	ALUMINA	CERMET 10%	1300 K	7.5 V	64	4.30E+01		Failed, short
043A-1	ALUMINA	CERMET 10%	1100 K	7.5 V	24	2.75E+02		Failed, short
043A-2	ALUMINA	CERMET 10%	1300 K	7.5 V	4	6.00E+01		Failed, short
054A-1	ALUMINA	CERMET 5%	1300 K	7.5 V	1100	2.00E+06		Test stopped
056-3	ALUMINA	CERMET 10%	1100 K	7.5 V	240	2.00E+07		Test stopped
056-6	ALUMINA	CERMET 10%	1300 K	7.5 V	1200	7.00E+05		Test stopped
059-2	ALUMINA	CERMET 10%	1300 K	7.5 V	1	8.00E+01		Failed, short
061-1	ALUMINA	CERMET 10%	1300 K	7.5 V	8	100		Failed, short
061-2	ALUMINA	CERMET 10%	1300 K	7.5 V	48	100		Failed, short
066-1	ALUMINA	CERMET 5%	1300 K	7.5 V	530	7.50E+05		Test stopped
067-1	ALUMINA	CERMET 10%	1300 K	7.5 V	72	2.00E+05		Test stopped
067-2	ALUMINA	CERMET 10%	1300 K	7.5 V	72	3.00E+05		Test stopped
067-3	ALUMINA	CERMET 10%	1300 K	7.5 V	72	2.50E+05		Test stopped
068-1	ALUMINA	CERMET 5%	1300 K	7.5 V	120	2.50E+05		Test stopped
068-2	ALUMINA	CERMET 5%	1300 K	7.5 V	72	3.50E+05		Test stopped
068-3	ALUMINA	CERMET 5%	1300 K	7.5 V	144	3.00E+05		Test stopped
068-4	ALUMINA	CERMET 5%	1300 K	7.5 V	72	4.00E+05		Test stopped
068-5	ALUMINA	CERMET 5%	1300 K	7.5 V	72	4.00E+05		Test stopped
068-6	ALUMINA	CERMET 5%	1300 K	7.5 V	96	4.00E+05		Test stopped
1706A	ALUMINA	CERMET 5%	1270 K	100 V	9048	7.70E+06	2.2	Test stopped
1706B	ALUMINA	CERMET 5%	1170 K	100 V	9048	9.70E+05	0.31	Test stopped
1706C	ALUMINA	CERMET 5%	1070 K	100 V	9048	4.80E+09	2.74	Test stopped
1707A	ALUMINA	CERMET 10%	1270 K	100 V	24	< 100		Failed, short
1707B	ALUMINA	CERMET 10%	1170 K	100 V	312	< 100		Failed, short
1707C	ALUMINA	CERMET 10%	1070 K	100 V	8160	< 100		Failed, short

Table 5-2 summarizes all of the in-reactor tests performed on sheath insulators since the start of the TFE Verification Program.

5.5.1 UCA-3 Irradiation

UCA-3 is the last in the series of in-reactor component testing in EBR-II. It incorporates results from ex-reactor testing as well as results from the postirradiation examination of UCA-1 and UCA-2 sheath insulators. The UCA-3 sheath insulators were irradiated in cycles 157 and 158 of EBR-II with irradiation ending on January 19, 1992. The samples accumulated a total of 110 EFPD with an estimated peak fast fluence of 1.8×10^{22} n/cm² (E > .1 MeV).

Terminal nondestructive examinations were completed at the Hot Fuels Examination Facility. Examinations included visual examination of the sample capsules and neutron radiography at three orientations. The radiography showed no observable differences as a result of the irradiation. The sample capsules will be shipped to WHC in March, 1993. Detailed examination is planned in FY-94 subject to available funds and program priorities.

5.5.2 IFAC-SI

On January 27, 1993, a decision was made to pursue an IFAC-SI test in the TRIGA research reactor. The overall objective of the TRIGA insulator test is to validate SI performance for use in thermionic fuel elements. The TRIGA insulator test will simultaneously expose 11 insulator samples to a temperature, electric field, and neutron flux environment. The temperature, electric field, and neutron flux will be representative of those found in a 5 to 40 kW(e) thermionic space nuclear reactor. Three of the selected samples will be diamond films, six of the samples will be alumina in a trilayer sheath insulator configuration, and two of the samples will be alumina in a spray coat configuration.

Table 5-2

IN-REACTOR SUMMARY

TEST S/N	MATERIAL AND PROCESS	FLUENCE (mvd)	TEMPERATURE IRRADIATION	PIE VISUAL	DIMENSIONAL RADIAL AXIAL	PIE RESISTANCE Ohms	PIE He LEAK RATE Std cc/sec	PIE METALLOGRAPHY
UCA-1	FFTF 9/86 - 10/87	8164 hours						
AL-1	AL203-GRADED	3.50E+22	1109 K	Circum cracks at ends	0.58%	3650 (1173 K - 1V)	>10 ⁻⁴	Cracks penetrate 1.3mm into ceramic
AL-2	AL203-GRADED	3.30E+22	1110 K	Circum cracks at ends	0.58%	1370 (1173 K - 1V)	5x10 ⁻⁵	No circumferential crack in center
ALN-1	AL203-GRADED	6.90E+22	1135 K	Circum cracks at ends	1.16%	4590 (1173 K - 1V)	>10 ⁻⁴	
AA-1	AL203-GRADED	3.60E+22	1112 K	Circum cracks at ends	0.43%	38 (1073 K - 1V)	5x10 ⁻⁵	
AA-2	AL203-GRADED	3.30E+22	1104 K	Circum cracks at ends	0.58%	8.1x10 ⁻⁵ (1173 K - 1V)	7.5x10 ⁻⁵	Cracks penetrate 1.3mm into ceramic
AAN-1	AL203-GRADED	3.80E+22	1114 K	Circum cracks at ends	0.58%	540 (1173 K - 1V)	2.6x10 ⁻⁶	
ALH-1	AL203-GRADED	3.60E+22	1115 K	Circum cracks at ends				
Y-1	Y2O3-GRADED	3.10E+22	1104 K	Circum cracks at ends	0.30%	10 (1173 K - 1V)	4.3x10 ⁻⁸	Crack extends full length
Y-2	Y2O3-GRADED	3.70E+22	1112 K	Circum cracks at ends	0.43%	8 (1173 K - 1V)	1.1x10 ⁻⁷	Circumferential crack in center
Y-3	Y2O3-GRADED	6.80E+22	1133 K	Circum cracks at ends	0.58%	3 (1173 K - 1V)	8.5x10 ⁻⁸	
TEA-1	AL203-CERMET 25%	3.10E+22	1090 K	No cracks	0.48%	27 at RT (1V)	1.1x10 ⁻⁷	No Cracks
TEA-2	AL203-CERMET 25%	7.00E+22	1137 K	No cracks	0.58%	1460 at RT (1V)	1.3x10 ⁻⁷	
TEA-3	AL203-CERMET 25%	3.50E+22	1111 K	No cracks	0.43%	50 at RT (1V)	5x10 ⁻⁵	
TEYAG-1	YAG-CERMET 25%	3.40E+22	1096 K	No cracks	0.30%	220 (1174 K - 1V)	1	No Cracks
TEYAG-2	YAG-CERMET 25%	6.60E+22	1130 K	No cracks	0.15%	2900 at RT (1V)	1	
TEYAG-4	YAG-CERMET 25%	3.40E+22	1106 K	No cracks	0.30%	150 (1173 K - 1V)	1.0x10 ⁻²	
UCA-2	FFTF 11/87 - 1/89	8040 hours						
317	AL203-GRADED	3.70E+22	1114 K	No cracks	1.41%	7.7x10 ⁻⁶ (1196 K - 7.5 V)	9.2x10 ⁻⁵	No cracks
336	AL203-GRADED	5.80E+22	1128 K	No cracks	1.15%	8.2x10 ⁻⁶ (1209 K - 7.5 V)	5.4x10 ⁻⁷	No cracks
345	Y2O3-GRADED	3.40E+22	1117 K	No cracks	0.58%	4.62E+05 (873 K - 7.5V)		
346	Y2O3-GRADED	5.90E+22	1128 K	No cracks	0.58%	69 (1207 K - 7.5 V)	1x10 ⁻⁸	No cracks
333	YAG-GRADED	3.80E+22	1113 K	No cracks	0.15%	23 (1214 K - 7.5 V)	4.1x10 ⁻⁴	
334	YAG-GRADED	5.60E+22	1130 K	No cracks	0.15%	49 (1210 K - 7.5 V)	1.6x10 ⁻⁴	
TA8	AL203-CERMET 10%	3.70E+22	1109 K	No cracks	1.09%	3.0x10 ⁻⁶ (1197 K - 7.5V)	2.7x10 ⁻⁶	No cracks
TA9	AL203-CERMET 10%	6.00E+22	1121 K	No cracks	1.15%	7.6x10 ⁻⁶ (1209 K - 7.5 V)	1.2x10 ⁻⁴	No cracks
TY2	Y2O3-CERMET 10%	3.40E+22	1112 K	No cracks	0.51%	37 (1210 K - 7.5V)	2.8x10 ⁻⁴	
TY5	Y2O3-CERMET 10%	6.20E+22	1122 K	No cracks	0.58%	31 (1213 K - 7.5 V)	2.9x10 ⁻⁴	
UCA-3B	EBR-II 5/91 - 2/92	2640 hours						
1380	AL203-GRADED	1.80E+22	1070 K					
1383	AL203-GRADED	1.80E+22	1070 K					
065-1	AL203-CERMET 10%	1.80E+22	1070 K					
065-4	AL203-CERMET 10%	1.80E+22	1070 K					
066-2	AL203-CERMET 5%	1.80E+22	1070 K					
066-3	AL203-CERMET 5%	1.80E+22	1070 K					

Table 5-3
SHEATH INSULATOR TECHNOLOGY STATUS

Material	Priority	Electrical Properties	Neutron Stability	Fabricability	Test Matrix (No. of Specimens)				Fueled Emitter	Ex-Reactor
					UCA-1	UCA-2	UCA-3	TFE 1H1, 1H2, 1H3, 3H1 3H5, 6H1		
Y ₂ O ₃ (PC)	Low	Poor	Good	Good	3	4		1		23
YAG (PC)	Low	Good	Good	Difficult	3	2				7
Al ₂ O ₃ (PC)	High	Good	Good	Good	10	4	6	12	9	34
Al ₂ O ₃ (SC)	Low	Good	-	Difficult						2

PC Polycrystalline.
SC Single Crystal

6. FUELED EMITTER TASK

6.1 OBJECTIVE AND TECHNICAL APPROACH

The function of the fueled emitter is to generate the heat necessary to drive the thermionic conversion process with the geometry, power densities and temperatures required by the reference TFE design, using materials compatible with both the thermionic process and reactor requirements. Specific requirements for the emitter are given in Table 6-1.

TABLE 6-1
FUELED EMITTER DESIGN REQUIREMENTS

<u>Emitter</u>	
Material	Duplex tungsten
Outside diameter, cm	1.27
Thickness, cm	0.10
Emitter/collector gap, cm	0.025
Nominal temperature, K	1800
<u>Fuel</u>	
Outside diameter, cm	1.0
Inside diameter, cm	Variable
Enrichment, % U-235	93
Fuel length, cm	4.65
Nominal fuel burnup, atom percent	4.1
Peak fuel burnup, atom percent	5.3

The key technical concern is the emitter distortion as a result of fuel swelling over the 7-year lifetime. It is the objective of the fueled emitter task to develop and demonstration by appropriate ex-reactor testing, in-reactor testing and analytical verification a fueled emitter capable of meeting the above design requirements.

The strategy to demonstrate the performance and lifetime of the fueled emitter is based on extensive in-reactor testing. While duplex tungsten will be the focus of most of the testing, alternate materials, particularly the HfC strengthened materials, look very promising and will be considered. Additionally, alternate fuel forms will be evaluated which either weaken the fuel or change its swelling characteristics, thereby minimizing emitter distortion. These forms include insulated fuel, and wafered fuel.

6.2 STATUS OF TEST ARTICLES

The uninstrumented fast reactor accelerated component (UFAC) test program in EBR-II has tested two batches of fueled emitters (FEs). The accelerated testing of several specimens in Batch 1 has been completed and the PIE is underway. The accelerated specimens in Batch 2 completed their irradiation in January, 1992, and PIE will be performed in the future. The real time specimens of Batch 1 and Batch 2, UFAC-2C, were removed in January, 1992 for neutron radiography and nondestructive examination. Two of the fueled emitters, SU2-1 and SU2-15 were bowed and could not be reconstituted into the current bundle design for continued irradiation. They will be shipped to WHC for PIE. The bowing occurred because of the existence of both temperature and flux gradients across the subassembly. Capsule SU2-2 had a fractured emitter at the Ta transition region in a manner similar to the SU2-3 emitter. It will also undergo PIE.

The remaining 3 emitters in UFAC-2, SU2-11, SU2-12 and SU2-14, will resume irradiation with Run 164 in May, 1993 at the completion of the annual maintenance outage, as UFAC-2D.

A road map showing the irradiation strategy for the FEs in EBR-II is shown on Fig. 6-1. More detail is shown on Table 6-2 which also shows the current irradiation status of the test vehicles. The recent irradiation history is shown on Fig. 6-2 for both the UFAC subassemblies and EBR-II. Periodically, an interim nondestructive examination is performed during which a neutron radiography (NR) is taken, and at

Figure 6-1. Road Map: Fueled Emitter Testing in EBR-II

TABLE 6-2

SUMMARY STATUS OF UFAC TEST SERIES IN EBR-II AS OF SEPTEMBER 1, 1992

Test Designation	Test Content	Status	EFPD*	Irradiation Fast Fluence $\times 10^{22} \text{n/cm}^2$	Peak Burnup (at. %)	Postirradiation Examination Status*
UFAC-1	7 Batch-1 FEs	Complete 8-87	94.5	1.5	1.0	NDE 7 capsules complete 11-87
UFAC-1A	7 Batch-1 FEs	Complete 4-88	221.5	3.6	2.1	NDE 7 capsules complete 7-88 DE 3 capsules complete 6-89
UFAC-1B	4 Batch-1 FEs	Complete 4-90	518	7.6	4.3	NDE 4 capsules complete 6-90
UFAC-2	3 Batch-1 FEs	Complete 4-88	285	2.8	0.5	NDE 3 capsules complete 6-88 DE 1 capsules complete 6-89
UFAC-2A	2 Batch-1 FEs	Complete 3-89	467	4.2	1.1	NDE 2 capsules complete 6-89
UFAC-2B	2 Batch-1 FEs 4 Batch-2 FEs	Complete 4-91	798 331	7.5 2.9	2.0 .85	NDE 6 capsules complete
UFAC-2C	2 Batch-1 FEs 4 Batch-2 FEs	Complete 1-92	908 441	8.5 4.1	2.3 1.1	NDE 6 capsules complete
UFAC-2D	3 Batch-2 FEs	Continue FY-93	0	0	0	Continue test FY-93
UFAC-3	3 Batch-2 FEs	Complete 4-90	64	1.1	0.66	NDE 3 capsules complete 5-89
UFAC-3A	3 Batch-2 FEs	Complete 9-90	172	2.9	1.73	NDE 3 capsules complete 11-90
UFAC-3B	3 Batch-2 FEs	Complete 4-91	266	4.5	2.7	NDE 3 capsules complete
UFAC-3C	2 Batch-2 FEs	Complete 1-92	376	6.2	3.5	NDE 2 capsules complete. DE planned.

* Equivalent full power days.

* NDE: nondestructive examinations: visual, dimensional, gamma-scan, neutron radiography.

* DE: destructive examinations: gas sampling, radiochemical burnup, metallography.

FIGURE 6-2
UFAC IRRADIATION SCHEDULE

that time the letter designation of the subassembly is changed, e.g., UFAC-1 to UFAC-1A, etc.

6.3 PIE OF FUELED EMITTERS

No PIE was performed over the last six months.

7. CESIUM RESERVOIR AND INTERCONNECTIVE TFE COMPONENTS

7.1 OBJECTIVE

The overall objective of the cesium reservoir and interconnective TFE components task is to develop and validate the performance of cesium reservoirs and interconnective TFE components, such as intercell insulation, fission product vents and fission product traps. In particular, the objectives are:

1. Design integral cesium reservoirs and interconnective TFE components.
2. Develop required fabrication processes for integral cesium reservoirs and interconnective TFE components and document the process specifications.
3. Fabricate integral cesium reservoirs and interconnective TFE components for in-reactor and ex-reactor tests.
4. Verify the performance characteristics and lifetimes associated with integral cesium reservoirs and interconnective TFE components by means of in-reactor and ex-reactor testing.
5. Develop an analytical model of the performance and lifetime of the Cs reservoir and interconnective TFE components.

7.2 TASK DESCRIPTION

The integral cesium reservoir and interconnective TFE tasks consists of five subtasks:

1. Cesium reservoir and interconnective TFE components design. Design integral cesium reservoir test specimens consistent with the TFE design

requirements. Design test specimens of intercell insulation and inter-connective TFE components such as TFE end restraint and fission product traps, ports and tubes consistent with TFE design requirements.

2. Fabrication development. Determine integral cesium reservoir materials with the capability for storing cesium either as intercalation compounds or as sorption reservoirs. Develop systems for containing the integral reservoir material in a TFE environment. Select insulator materials such as Al_2O_3 , Y_2O_3 and YAG and develop processes for fabricating TFE end restraints and intercell insulation components. Develop materials for use as fission product traps and develop components for fission product vent and port tubes.
3. Ex-reactor testing. Perform ex-reactor tests to determine the cesium pressure of integral reservoir materials as a function of cesium loading and temperature. Examine the ability of intercell insulation coatings to reduce parasitic discharges. Determine the mechanical stability of TFE end restraints.
4. In-reactor testing. Determine the effect of fast neutron fluence on the stability of the pressure versus temperature characteristics of integral cesium reservoirs at a fixed cesium loading. Also examine the mechanical stability of prototypical TFE end restraints and intercell insulation coatings. Determine fission product release characteristics from the fuel and evaluate the effectiveness of the fission product control components and assemblies.

7.3 PROGRESS DURING THE PRESENT REPORTING PERIOD

The test plan for the cesium reservoir temperature gradient tests was written and released. The temperature gradient tests have the following objectives:

- 1) Establish the cesium pressure-graphite temperature relationship for a nonisothermal graphite reservoir.
- 2) Establish the cesium pressure-graphite temperature relationship for coupled isothermal reservoirs containing unequal amounts of graphite.
- 3) Establish the cesium pressure-graphite temperature relationship for a single graphite reservoir coupled to an auxiliary porous molybdenum reservoir.
- 4) Establish the duration of the pressure transients that occur in the configuration noted above.

The designed requirements for these tests have been redefined as follows:

Nominal cesium pressure:	2 to 4 torr
Nominal graphite temperature:	1000 to 1100 K
Nominal temperature gradient:	≤ 50 K
Pressure transient due to ΔT :	≤ 30 sec

7.3.1 Background of the Temperature Gradient Tests

The cesium pressure in a thermionic converter employing a liquid cesium reservoir is determined by the lowest temperature within the cesium envelope, whether or not that temperature is located at the site of the intended reservoir. In that instance the cesium pressure responds nearly instantaneously to a change in the temperature of the region where the cesium is condensed. The duration of any transient response will be determined solely by the conductance between the condensate and the interelectrode space.

The cesium pressure over a cesium-graphite reservoir is determined by a solid-state phase equilibrium between intercalation compounds of ascending order. These

intercalation compounds are well known and tests in the pre-1973 thermionics program and in the ongoing TFE Verification Program have shown them to be well behaved, stable and largely unaffected by neutron irradiation. However there are two areas in which further study is required: operation of a graphite reservoir in a temperature gradient and transient behavior as might be experienced after an abrupt change in the load of the power system.

The question of operation in a temperature gradient can be addressed by considering dual reservoirs. If two discreet graphite reservoirs are present, and are operating at slightly different temperatures, the loading will be different so that the system will remain isobaric. Note however that the cesium pressure will not be determined solely by the colder of the two reservoirs, as in the case of the liquid reservoir. Rather, the specific loading of the cold reservoir will be somewhat larger than that of the hot reservoir. The formation of the intercalation compounds involves not only the kinetics of the solid-state chemical reactions, but also adsorption and diffusion steps. Thus the response of the cesium-graphite reservoir to a change in temperature involves a transient of longer duration than occurs with liquid reservoirs. While the duration-determining factor may be the vacuum conductance in both cases, it is necessary to investigate the behavior of cesium-graphite in a simulated temperature gradient.

The nature of the transient response is also important for a monolithic, isothermal reservoir. Part of the question relates to the thermal coupling of the reservoir enclosure to the emitter and collector and is being investigated both analytically and experimentally, as described in Task 3. The ability to adequately couple the graphite to the reservoir enclosure to achieve the desired transient response is also important. One possible solution is to incorporate an auxiliary reservoir composed of a material with high porosity, such as sintered molybdenum, with close thermal coupling to the reservoir enclosure. In this concept, the small amount of cesium held in capillary channels within the Mo would be liberated

instantaneously and provide transient electron cooling until the cesium-graphite equilibrated.

7.3.2 Experimental Procedures

Symmetric reservoirs. In these tests, an equal mass of graphite will be placed in each reservoir and the temperature difference (ΔT) between the reservoirs will be established by changing the temperature of either one, but not both. The graphite reservoirs will be loaded isothermally and isolated from the liquid reservoir. The cesium pressure will be measured as a function of T and $\pm \Delta T$. The measurements will be repeated for a minimum of two loading values, one in the C_{10} - C_{24} equilibrium and one in the C_{24} - C_{36} equilibrium. The changes in ΔT will be imposed as rapidly as possible and the pressure transients will be monitored.

Asymmetric reservoirs. In these tests, the mass of graphite in one reservoir will be three times that of the other. Thus when the smaller reservoir is at the higher temperature its specific loading is less, and it will contain only a small fraction of the total Cs inventory. This will make the overall system more sensitive to temperature variations since small changes in the larger reservoir will dominate. The graphite reservoirs will be loaded isothermally and isolated from the liquid reservoir. The cesium pressure will be measured as a function of T and $\pm \Delta T$. In these asymmetric tests, the temperature of both reservoirs will be varied to establish $\pm \Delta T$. The measurements will be repeated for a minimum of two loading values, one in the C_{10} - C_{24} equilibrium and one in the C_{24} - C_{36} equilibrium. The changes in ΔT will be imposed as rapidly as possible and the pressure transients will be monitored.

Auxiliary reservoirs. A single graphite reservoir will be encapsulated with a porous Mo structure that is bonded to the internal walls of the can. The graphite reservoir will be loaded isothermally and isolated from the liquid reservoir. During the graphite loading, the Mo structure will also be charged with cesium. From earlier studies it is known that the cesium uptake will be much less than that of the graphite.

The cesium pressure will be measured as a function of T. The measurements will be repeated for a minimum of two loading values, one in the C₁₀-C₂₄ equilibrium and one in the C₂₄-C₃₆ equilibrium. The changes in T will be imposed as rapidly as possible and the pressure transients will be monitored.

7.3.3 Test Matrix

The test matrix proposed for these experiments is shown in Table 7-1.

TABLE 7-1
TEST MATRIX

	Symmetric Reservoirs	Asymmetric Reservoirs	Auxiliary Reservoirs
Reservoir loading, mgCs/gC Case A: Case B:	461 to 1108 273 to 461	Same Same	Same Same
Reservoir temperature, K	900 to 1100	Same	Same
Temperature gradient, K	10,20,30,40 K	Same	-

7.3.4 Experimental Results To Date

The first experiments have employed asymmetric reservoirs. One reservoir contains 3 grams of POCO graphite and the other contains 1 gram. Two isothermal loading conditions have been used as indicated in Table 7-2.

TABLE 7-2
ASYMMETRIC RESERVOIR ISOTHERMAL LOADING CONDITIONS

Cesium Pressure torr	Graphite Temperature °C	Estimated Loading mg Cs/gC
3	730	~ 600
1	800	~ 300

The loading was estimated from UCA-3 and UFAC-3 preirradiation data using Cs-134.

Cesium pressure data sets as indicated in Table 7-3 have been obtained. In addition, isothermal measurements were made, i.e., the Cs pressure was measured as a function of graphite temperature with $\Delta T = 0$. Comparisons of the isothermal data with the UCA-3 results are shown in Figs. 7-1 and 7-2.

TABLE 7-3
Cesium Pressure Data Sets

Estimated Loading mg Cs/gC	Temperature Range of 3 gram Reservoir, °C	Temperature Range of 1 gram Reservoir, °C
600	655	650-780
	765	660-765
	650-825	655
	670-765	765
300	800	743-963
	890	750-894
	751-950	800
	730-840	890

The asymmetric data sets are plotted in Figs. 7-3 and 7-4. Qualitatively, the pressure is controlled by the 3 gram reservoir in all cases. For example, if both reservoirs are initially at 800°C (for the 300 mg Cs/gC case), the pressure is a bit over 1 torr. If the 3 grams reservoir is held at 800°C and the 1 gram reservoir is heated to ~950°C, the pressure increases to 4 torr.

The original specific loading of the two reservoirs is the same (300 mg Cs/gC). When either reservoir is heated there is a transfer of cesium from the hot to the cold reservoir. This transfer stops only when each reservoir is in equilibrium with the new system pressure. Since the pressure-temperature response of Cs-graphite depends on the specific loading, not the absolute loading, and since the same amount of cesium leaves one reservoir and enters the other, the equilibrium pressure over the larger reservoir is less effected, and it dominates the system pressure.

Figure 7-1. Isothermal Pressure vs UCA-3 Data

Figure 7-2. Isothermal Pressure vs UCA-3 Data

Figure 7-3. Pressure-Temperature Relationship in a Temperature Gradient.
Loading Approximately 600 mg Cs/gC.

Figure 7-4. Pressure-Temperature Relationship in a Temperature Gradient.
Loading Approximately 300 mg Cs/gC.

These considerations are being incorporated into a dual graphite reservoir model. Where available, experimental isotherms are employed. An approximate method is employed to mock up the isotherms outside the range of past experiments. An example of the behavior of the model is shown in Fig. 7-5. Qualitative agreement with the experiments of Figs. 7-3 and 7-4 is obtained in the preliminary calculations shown in Fig. 7-5.

Figure 7-5. Dual Graphite Reservoir Model Calculation

The experiments and model calculations are continuing in the next reporting period.

8. THERMIONIC FUEL ELEMENT

8.1 OBJECTIVE

The overall goal of the thermionic fuel element task is to demonstrate that TFEs prototypic of a 2 MW(e) thermionic space nuclear power system of seven year life can be fabricated from well modeled components, and that their performance is as predicted when operated in a prototypic thermionic reactor environment. Derivative goals include:

- 1) Produce a TFE engineering design and specification.
- 2) Develop required TFE assembly processes, process specifications, and demonstrate manufacturing capability.
- 3) Fabricate TFEs and test them to demonstrate the processes and the integrated performance of the components.
- 4) Develop and verify a TFE model that can predict TFE performance and lifetime.

Components with demonstrated performance and which are projected to meet lifetime requirements will be used in these TFEs. The performance of one prototypic TFE will be demonstrated in EBR II. Thermionic fuel elements leading up to the prototype will undergo irradiation in the General Atomics Mark F TRIGA reactor.

8.2 TASK DESCRIPTION

8.2.1 Testing Logic

All converters tested in the TFEs will be of the baseline configuration. The balance of the test article will be as close to the baseline TFE design in geometry and performance as practicable. Test and design requirements are compared in Table 8-1.

The separate in-reactor tests and the distinctions between them are outlined in Table 8-2. Note that tests 3H2 thru 3H4, which were originally proposed, have been deleted.

TABLE 8-1
COMPARISON OF TFE TEST REQUIREMENTS WITH SYSTEM BASELINE
DESIGN REQUIREMENTS

	TFE Test Requirements (BOL)	Baseline Design Requirements (BOL)
Converter power density average (W/cm ²)	3.4	3.4
Current density average (A/cm ²)	7	7
Emitter temperature average (K)	1800	1800
Collector temperature average (K)	1070	1070
Sheath-collector voltage maximum (V)	7.5	7.5
Converter configuration	Baseline	Baseline
TFE materials	Baseline or variants for performance structural improvements	Section 2
Fuel enrichment (% U-235)	Variable enrichment	93: variable fuel volume fraction
Fast fluence: nominal (E>0.1 Mev)	Real time	2.7x10 ²² / 7 years
Fuel burnup: nominal (a/o)	4.1	4.1
Cesium reservoir type	Variable with test	Integral graphite
TFE environment/heat sink	Helium/test reactor coolant	Liquid metal (Li)
Reflector above/below within TFE	No	Yes
Reactor vessel penetration integral with TFE	No	Yes

The logic behind this test series is a step-by-step development of the fabrication processes, culminating in the fast reactor prototype. The first step is the development of the processes for a single cell, and the integration of the single cell into a TFE sheath tube with appropriate end fittings. These end fittings involve the cesium

TABLE 8-2
TFE IN-REACTOR TEST SUMMARY MATRIX

TFE ID	Fuel/Emitter Collector	Cs Reservoir	Purpose	Reactor
1H1	UO ₂ /W/Nb	Pool	Verification of reference cell design performance and fabrication processes. Sheath integration.	TRIGA
1H2	UO ₂ /W/Nb	Graphite	Verification of integral cesium reservoir design, performance.	TRIGA
1H3	UO ₂ /W/Nb	Pool	Study effect of fission products mixing with cesium.	TRIGA
3H1	UO ₂ /W/Nb	Graphite	Intercell process development. Fission product control.	TRIGA
3H5	UO ₂ /W/Nb	Graphite	Backup to 3H1. Introduction of prototypic components outside cell.	TRIGA
6H1	UO ₂ /W/Nb	Graphite	Verification of long-TFE fabricability.	TRIGA
6H2	UO ₂ /W/Nb	Integral Graphite	Backup to 6H1. Introduction of prototypic components. Test has been dropped from the program.	TRIGA
6H3	UO ₂ /W/Nb	Integral Graphite	Verification of TFE performance in fast reactor environment. Test has been dropped from the program.	EBR-II

reservoir, fission gas venting and the conduction of electrical current produced. This single-cell TFE is designated "1H", where the H refers to the latest generation of thermionic cell in a megawatt class TFE, and the "1" refers to the number of cells in the TFE.

The second step is the development of the intercell region of the TFE. The test vehicle will be the 3H-series TFE which will contain three of the H-series cells welded end-to-end in an electrical series circuit. The center cell in the series is isolated from TFE end-fittings and is thereby typical of cells within the interior of a thermionic reactor. The testing of the three cell TFE also allows the study of fission gas venting in a representative multicell environment at a minimum expense.

As the last step in the testing before the fast reactor prototype test, 6H-series TFEs will be built to demonstrate the fabricability of a long TFE where axial alignment is critical. Testing of these TFEs will provide additional demonstration of fission product venting and the capability to maintain unobstructed fission gas passages.

Success in the process development will be evidenced by the observed in-reactor performance and stability.

The following materials and/or components are used in all TFEs:

- Insulator crystal state: polycrystalline
- Emitter body material: W from WF_6
- Emitter surface material: W from WCl_6
- Emitter stem material: W from WF_6
 - Length: .43 in.
 - Thickness: .020 in.
- Collector material: Nb
- Emitter transition material: tantalum.

Other TFE features that vary are shown on Table 8-3.

8.2.2 Program Restructuring

In a detailed review of the TFE Verification Program in June, 1992 it was decided to drop TFE-6H2 and 6H3 from the program. The rationale was that these TFEs, which were to be prototypic TFEs, should be replaced by test articles responsive to the Thermionic Space Nuclear Power System (TI-SNPS) program. The funding for fabrication and test should come from the TI-SNPS program and TFE design should reflect the 5 to 40 kW range of this program.

8.2.3 TFE Design

The TFE design has been described in previous semiannual reports (Ref. 8-1). The H-series thermionic converter design is as illustrated in Fig. 8-1, and the representative TFEs for TRIGA test are pictured in Fig. 8-2.

TABLE B-3
TFE TEST MATRIX

	1H1	1H2	1H3	3H1	3H5	6H1	6H2	6H3
Emitter cap material	Ta	Ta	Ta	Nb	Nb	Nb		
Flight fuel holddown	No, use spring						Yes	
Volatile fission product trap								
Location	Vac		Cell					
Material	-		Al ₂ O ₃					
Optimized design	-		No				Yes	
Trilayer								
Insulator	Y ₂ O ₃	Al ₂ O ₃						
Square or shaped ends	Square						Shaped	
Ceramic-to-metal seal								
Insulator	Al ₂ O ₃							
Configuration	Litton						Trilayer	
Emitter alignment								
W/Re spring	Belleville			Cylindrical Spring				
Insulator	Solid Al ₂ O ₃			Planar Al ₂ O ₃ Trilayer				
Configuration	2 piece			Trilayer in Cap				
Cesium reservoir material	Liquid	POCO	Liquid	POCO				
Fuel pedestal, material design	W/Re				W			
Top of converter string								
Bus bar material	Nb				Nb/Mo			
Lead trilayer insulator	Al ₂ O ₃							
Stem seal insulator	Al ₂ O ₃							
Stem seal configuration	Litton						Proto	
Fission product port tube	Proto							
Vessel head penetration	Not applicable						Proto	
Dummy reflector block	Not applicable							
Bottom of converter string								
Dummy cell	Yes		No		Yes	No		
Dummy reflector block (and positioner)	Not applicable							
TFE alignment pin	Not applicable

Figure 8-1. H-series thermionic converter (typical of 3H1)

Figure 8-2. TFEs for TRIGA test

8.2.4 TRIGA Facility

The Mark F TRIGA reactor at General Atomics will be used for TFE testing. TRIGA is a water-moderated pool-type research reactor. The Mark F includes a neutron radiography facility located within the reactor pool for periodic nondestructive diagnostic examinations of the TFE internals. A hot cell at the site provides capability for postirradiation examination.

The TRIGA typically operates at about 1.4 MW(t). At this power level, the fast fluence is about 1×10^{21} nvt ($E > .1$ Mev) per year.

8.3 TFE TESTING

8.3.1 TFE Operations

The status of TFE irradiations in TRIGA as of March 31, 1993 is shown below:

TFE	Hours Total Operation	Hours Operation in Power Quadrants	Output Voltage, volts	Output Current, amps/cm ²	Current Status
1H1	17,100	12,000	-	-	Awaiting shipment to WHC and PIE
1H2	14,000	8,800	-	-	Awaiting shipment to WHC and PIE
1H3	13,500	12,500	-	-	Awaiting shipment to WHC and PIE
3H1	14,167	8,000*	1.5	3.0	Awaiting shipment to WHC and PIE.
3H5	3,718	3,718	1.4	6.25	Irradiation ongoing
6H1	-	-	-	-	Irradiation to start 4/2/93

*Performance of TFE-3H1 started to decline at 8000 hours although it is still in power quadrant.

8.3.2 TFE-3H1

In September, 1992, the TRIGA reactor was shutdown for the insertion of TFE-3H5 and restarted on Sept. 29, 1992. As shown in Fig. 8-3, upon restart, the ignited portion of the I-V curve of TFE-3H1 was out of the power quadrant, as compared to the I-V curve generated on Aug. 25, 1992, before the shutdown. Part of this was because the reservoir temperature on Sept. 29 (734°C) had not yet been brought up to the preshutdown reservoir temperature of 762°C.

The graphite Cs reservoir on TFE-3H1 uses two sheath heaters in parallel. On Oct. 3, one of these two parallel heaters burned out, further lowering the Cs reservoir temperature to 670°C. Figure 8-3 also shows I-V curves taken from Oct. 5 to Oct. 26. The Cs pressure drop resulting from the heater failure caused a further degradation in the I-V curve. Attempts to raise the Cs reservoir temperature at this point ran the risk of burning out the surviving Cs reservoir heater.

On February 8, 1993, the remaining Cs reservoir heater burned out leaving no active heater for the Cs reservoir of TFE-3H1. At the time, nothing unusual was occurring; the heater was carrying its rated current. On March 19, 1993, TRIGA was shut down for an annual fuel inspection and, at this time TFE-3H1 was removed from the core and stored in the TRIGA pool.

8.3.3 TFE-3H5

On September 29, 1992, the TRIGA reactor was restarted with TFE-3H5 loaded into the core. There was an apparent slow decline in the output voltage of TFE-3H5 during October. This appears to have been due, chiefly, to a change in the Cs pressure. The output voltage dropped from 1.40 v at 144 hrs on Oct. 5 to 1.23 v at 748 hrs on Oct. 30, 1992.

The secondary containment volume was initially filled, to a subatmospheric pressure, with a gas mixture of 75% He/25% Ar. The absolute pressure in this

Figure 8-3. 3H1 I-V Curves.

secondary containment volume rose during October. This could be due to a leak or from outgassing. Either a leak or outgassing into this volume would lower the effective thermal conductivity of the gas mixture and cause the TFE temperatures to rise. The measured average collector temperature and the secondary containment volume pressure are plotted vs time in Fig. 8-4. The rise in average collector temperature correlates with the rise in secondary containment pressure. It should be noted that the admittance of air into the secondary containment causes no damage. The primary and secondary envelopes are fabricated from stainless steel. The insulators of the primary hard seal run at a low temperature such that oxidation of the ceramic/metal braze is not a concern.

The collector temperature rise is not sufficient to cause the voltage decline. A schematic of the graphite Cs reservoir used in TFE-3H5 is shown in Fig. 8-5. The thermocouples used to measure the reservoir temperature are attached to the outer envelope of the Cs reservoir oven. The Cs reservoir heater maintains a preset outer envelope temperature, as measured by one of these outer thermocouples. The temperature of the graphite within the Cs reservoir is influenced by this outer envelope temperature as well as by the temperature of the center block, which is thermally tied to the emitter lead. If the temperature of the TFE rises, it would drive more heat into this block and cause a rise in the graphite temperature within the reservoir, without an apparent rise in the outer envelope.

Figure 8-6 shows I-V curves taken on Oct. 1 and Oct. 30, 1992 at an indicated Cs reservoir temperature of 520°C. While the measured Cs reservoir temperature remained unchanged during October, the I-V curves would indicate that there had been an increase in the reservoir temperature and Cs pressure. Apparently, the temperature rise in the TFE (caused by reduction in secondary containment gas conductivity) caused a temperature rise in the graphite within the Cs reservoir, even though the measured temperature of the outer envelope was held constant. The voltage output was seen to increase from 1.23 v to 1.32 v when the indicated Cs reservoir temperature was lowered from 520°C to 505°C on Oct. 30.

Figure 8-4. 3H5 Operating History.

Figure 8-5. Graphite Cs reservoir is thermally coupled to heater block - and also to emitter lead.

Figure 8-6. 3H5 I-V Curves.

Swagelock fittings are used in external tubing which communicates with the TFE-3H5 secondary containment. These fittings were possible sources of leaks and were repeatedly tightened. Throughout the rest of calendar year 1992, the secondary containment pressure continued to rise but changes in collector temperature and electrical output were small.

During the Christmas shutdown, the secondary containment volume was pumped out and a fresh mixture of 75% He/25% Ar was backfilled into the secondary containment volume. After startup on Jan. 6, 1993, the pressure in the secondary volume was noticed to again rise slowly. The Cs pressure in TFE-3H1 was periodically optimized in an effort to minimize the effect of changes in the Cs reservoir temperature and pressure. Despite the rise in secondary containment pressure, collector temperatures remained fairly constant throughout the reporting period and electrical output remained steady, producing 1.4 volts at 125 amps (6.25 A/cm²).

TFE-3H5 was fabricated such that a voltage could be placed across the its sheath insulator. This was not possible with TFE-3H1, the electrical schematic of which is shown in Fig. 8-7. The sheath tube of TFE-3H1 is bonded to the collector bus and thus runs at the same potential as the bottom collector. Sheath insulators existed to stand off the middle and top collectors and the emitter lead from the sheath tube. The TFE stem insulator seal forms the vacuum seal between the sheath tube and the emitter bus at the top of the TFE. Because the sheath tube is bonded to the collector bus, it is not possible to apply an external voltage to the sheath tube without affecting TFE output.

The electrical schematic of TFE-3H5 is shown in Fig. 8-8. TFE-3H5 was fabricated so as to isolate the sheath tube from the current-carrying path of the TFE. This was accomplished by using a "dummy" cell at the bottom (right side of Fig. 8-8) of TFE-3H5. This "dummy" cell is not a thermionic device but has similar geometric features which permit an additional sheath insulator and insulator seal. The "dummy"

TRIGA Containment Tubes and Pool

Figure 8-7. 3H1 Electrical Schematic.

Figure 8-8. 3H5 Electrical Schematic.

cell insulator seal provides a vacuum barrier between the secondary containment and the fission gas spaces within the sheath tube. It also electrically isolates the bottom of the sheath tube from the collector bus. With the sheath tube totally isolated, an independent potential can be applied between current probe (CP) and the collector voltage probe (VP1), without affecting converter performance. As can be seen in Fig. 8-8, the voltage applied across the sheath tube is stood off not solely by the 3 cell sheath insulators, but by 7 different insulators, all in parallel. Leakage from any of these insulators, or any other source, will be reflected in a leakage current at the time that voltage is applied.

Electrical resistances were measured on Sept. 28, 1992, immediately before startup, when TFE-3H5 was in the TRIGA core. The matrix of these resistances is shown in Table 8-4. These resistance measurements indicate that no short existed at the time of startup between the sheath tube and either the emitter or collector busses.

Table 8-4. Pre-Startup TFE-3H5 Electrical Resistance.

ELECTRICAL RESISTANCE (Ω)		
	EMIT BUS	COL BUS
CP	> 20E6	> 20E6
VP3	> 20E6	> 20E6
VP2	1.10	.41E6
VP1	.33E6	1.34
COL BUS	24E6	N/A

In November a power supply was connected between the CP and VP1. The current in this circuit (1) was measured continuously by the data acquisition system

and the voltage at the sheath connection of the current probe was measured with VP3. The voltage VP3-VP1 (V) was also recorded. The original intent was to measure the resistance of the sheath insulator of the lower cell trilayer by dividing V by I. On Nov. 6, 1992, voltages were measured across various instrumentation probes and are tabulated in Table 8-5. The voltage matrix corresponds to the voltage relationships shown in Fig. 8-8: 1.53 volts between the emitter and collector busses; 0.27 volts between the sheath and collector bus; and 1.25 volts between the sheath and the emitter bus. An unexpected resistance path (tens of ohms) existed between VP1 and VP3-CP.

Table 8-5. Voltage Readings on 11/6/92.

VOLTAGE (v) MEASURED ACROSS:				
	CP	VP3	VP2	VP1
CP	0	0	-1.25	0.269
VP3	0	0	-1.25	.0267
VP2	1.25	1.25	0	1.53
VP1	-0.27	-0.27	-1.53	0

Figure 8-9 is a cross-section view of the TFE, showing all components that are relevant. (The dummy cell collector lead shown is actually that of 1H3; however 3H5 differs only slightly in detail and not at all functionally.) VP1 is attached to the lower end of the dummy lead, while VP3-CP are connected to the sheath tube at the top of the TFE assembly. There are several possible locations for current paths connecting VP1 and VP3-CP including:

- 1) Support insulator
- 2) Dummy cell insulator seal

Figure 8-9. TFE Dummy Cell Configuration.

- 3) Lower cell trilayer sheath insulator (internal path)
- 4) End effects at sheath insulator due to failure of plasma spray (and subsequent plating out of fission products, etc.).

Note that current paths in the middle and upper cell trilayers could also occur, and the cell(s) voltage would appear additively to the voltage V , measured across VP3-VP1. Figure 8-10 is a simplified schematic showing only the equivalent resistances that are most likely to appear in the present measurements. The lumped resistance R_{col} represents the distributed resistance of the collector electrode. Similarly $R_{DL1,2}$ are the resistances representing the dummy lead located on either side of the support insulator and $R_{col\ bus}$ is the lumped resistance representing the collector bus. The resistance values shown were calculated from the as-built dimensions, with the appropriate temperature corrections. VP3 and CP are shown connected to the sheath, with no current path to the rest of the TFE.

Figure 8-11 is an electrical schematic showing a current path between the sheath and the TFE through R_x . R_1 represents the TFE resistance between the location of the resistance path and VP1. R_1 may include some or all of the resistances $R_{DL1,2}$ and R_{col} . The apparent resistance of the sheath circuit, calculated by dividing the measured values of V by I , is

$$R_{\text{apparent}} = V/I = [1 + I_{\text{TFE}}/I]R_1 + R_x.$$

The current vs voltage relationship is shown in Fig. 8-12 for reactor powers of 1400, 1270, and 1090 kW during shutdown for the Christmas holidays. The TFE current, maintained by the driving power supply (DPS), was reduced from 128 amps to 88 amps as the reactor power was lowered, in order to keep the emitter temperature up. A pure resistance would be indicated by a straight line relationship between the current and voltage, as the line drawn for 44 ohms, which passes through the origin. The experimental curves are not straight lines and there is a

$R_{col\ bus} \approx 2.75$ milliohms

$R_{col} \approx 0.22$ milliohms

$R_{DL1} \approx R_{DL2} \approx 0.14$ milliohms

Figure 8-10. Equivalent circuit of dummy cell and voltage probes.

$$R_{apparent} = \frac{V}{I} = \left(1 + \frac{I_{TFE}}{I}\right) R_1 + R_x$$

Figure 8-11. Equivalent circuit of dummy cell and voltage probes with shorting path R_2 .

Figure 8-12. 3H5 VP1-3 measurements.

residual voltage at zero current. The low current portion of the curves is shown in Fig. 8-13. With no current flowing in the voltage probe circuit, the voltage which ranges from 0.025 to 0.1 volts represents the voltage developed across R_1 by I_{TFE} as shown in Fig. 8-12.

The variation of R_1 is tentatively attributed to temperature variations due to the change in joule heat generated by the TFE current. As a first approximation, the temperature of R_1 is taken to be governed only by this heat source and conduction to ambient. With this simple approximation, the temperature is given by

$$T_{R1} \approx [V \times I_{TFE}] / K'$$

where V is the voltage when the external current is zero and K' is the thermal conductance to the reactor pool, by whatever route. The resistance is given by

$$R_1 = R_o [1 + a\Delta T] \approx R_o [1 + aT_{R1}]$$

Substitution of the expression for T_{R1} into the expression for R_1 gives the following expression:

$$R_1 = V(I=0)/I_{TFE} \approx R_o [1 + (a/K')(V \times I_{TFE})].$$

The ratio of $V(I=0)$ obtained from Fig. 8-13 to the corresponding value of I_{TFE} is plotted versus their product in Fig. 8-14. Data points from measurements made in November and January are also included. Extrapolating the data to zero power yields the value of R_o , the ambient temperature value of R_1 of 0.0002 ohms. From the slope of the curve, taking $a \approx .005$ per degree C, the thermal conductance K' is 0.167 watts/degree. This value can be compared with about 0.8 watts/degree for the collectors and about 0.3 watts/degree for the emitter (after allowing for electron cooling) in typical TFE operation.

The value of R_x is determined using the equation for R_{apparent}

$$R_{\text{apparent}} = V/I = [1 + I_{TFE}/I]R_1 + R_x$$

R_{apparent} is calculated from the current vs voltage plots shown in Fig. 8-12. R_1 is

Figure 8-13. 3H5 VP1-3 measurements.

Figure 8-14. C45: R_1 vs power dissipated in R_1 .

calculated by dividing the voltage V (@ 0 CP-VP1 current) shown in Fig. 8-13, by the TFE current. Figure 8-15 shows the result obtained at a reactor power of 1403 kW, with $I_{TFE} = 128$ A. The solid squares in Fig. 8-15 are the measured values of R_{apparent} obtained as various values of I , the CP-VP1 current. The dashed line is the solution to the above equation for R_{apparent} using the calculated value of $.78 \text{ m}\Omega$ for R_1 (from Fig. 8-13) and an assumed value of $R_x = 46 \text{ ohms}$. The agreement between the measured values (solid squares) and the algebraic solution (dashed line) suggests that $R_x = 46 \text{ ohms}$.

In a similar way, $R_x = 44 \text{ ohms}$ was obtained at 1269 kW (Fig. 8-16), and $R_x = 40 \text{ ohms}$ was obtained at 1092 kW (Fig. 8-17). The changing value of R_x correlated with the respective collector temperatures is plotted in Fig. 8-18. The increase in R_x with temperature implies that the resistance is metallic in character.

In addition to the temperature dependence observed at the Christmas shutdown (Fig. 8-13), there has been a general decrease in the derived value of R_x with time. In early November the value of R_x was about 75 ohms. The drop to 44 ohms at full power was gradual until the shutdown. However immediately after start-up on January 6, 1993, it had dropped to 30 ohms. Furthermore, during shutdown, it was 2.7 ohms measured with an ohmmeter (and therefore including the resistance of the leads to the top of the capsule) and about 1.6 ohms with the three-probe measurement, until the reactor reached a power level of 1000 kW ($T_{\text{collector}} \approx 550 \text{ }^\circ\text{C}$).

The analysis described above is internally consistent for the circuit shown in Fig. 8-11. Identifying the equivalent resistance R_1 with the internal components of the TFE, such as R_{DL} etc., and locating R_x within the thermionic cell is not conclusive. Since the derived values of the series resistance R_1 are rather large (0.5 to 2 milliohms), it would seem that the conducting path couldn't be in the dummy cell (maximum resistance ≈ 0.28 milliohms). Adding a single collector electrode resistance of 0.22 milliohms to the dummy cell resistance would produce 0.50 milliohms, at the

Figure 8-15. 3H5: VP1-VP3 resistance.

Figure 8-16. 3H5: VP1-VP3 resistance.

■ R(1092kW)
 --- 88A,40/.000295 ohm

Figure 8-17. 3H5: VP1-VP3 resistance.

Figure 8-18. 3H5 VP1-3 resistance vs temperature.

low range of derived R_1 values. This would put R_x somewhere in the vicinity of the top of the bottom cell. The correlation of Fig. 8-14 strongly suggests that R_1 restricted to components that are in the main current path of the TFE, i.e., I_{TFE} flows through R_1 . The correlation of Fig. 8-18 suggests that the conductive path, R_x , is metallic and is near the collector temperature. If there should be a defect in the intercell plasma spray coating, metallic fission products could deposit and provide a conducting path across the end of the trilayer.

The existing power supply used to apply voltage across the TFE-3H5 sheath was found to be limited to about 200 mA. Another power supply was ordered which will allow higher driven current and thus allow higher voltages to be applied.

The TRIGA reactor was shut down on March 19, 1993 for its annual fuel inspection and in preparation for the insertion of TFE-6H1. Because of the nonfunctioning Cs reservoir heater, TFE-3H1 was removed from the core. Neutron radiographs were taken of TFE-3H1, -3H5, and -6H1. Preliminary readings of the TFE-3H5 radiographs show no emitter thinning after 3700 hrs of irradiation. Similar radiographs of TFE-3H1, at 4255 hrs of irradiation, had shown some emitter thinning. TFE-3H5 contains the first emitters to use tungsten-only (no Re) in the fuel pedestal.

8.3.4 Shipment Schedule

Several thermionic test articles are being stored at GA, awaiting shipment to WHC for PIE. TFE-1H2 and -1H3 and -3H1 are presently stored in the TRIGA pool, out of the core. TFE-1H1 underwent partial disassembly and PIE and is in the GA hot cell. Nine thermionic fueled devices and several irradiated sheath insulator specimens, from the SP-100 Technology Program, are also awaiting shipment. The initial shipment will include TFE-1H3 and the parts of disassembled TFE-1H1.

A search for a suitable shipment cask was completed. The lengths of the BMI and T-2 casks would require that the fission gas plenum be removed from TFE-1H3.

The T-3 shipping cask is sufficiently long to accommodate TFE-1H3 with the fission gas plenum intact. GA has asked be put on the T-3 Authorized Users list.

**DATE
FILMED**

9 / 9 / 93

END