AIM

Association for Information and Image Management

1100 Wayne Avenue, Suite 1100
Silver Spring, Maryland 20910
301/587-8202

Centimeter

Inches

MANUFACTURED TO AIM STANDARDS
BY APPLIED IMAGE, INC.

1 of 1

Lower-Hybrid Poloidal Current Drive for Fluctuation Reduction in a Reversed Field Pinch

E. Uchimoto,^{a)} M. Cekic, R. W. Harvey,^{b)} C. Litwin,^{c)} S. C. Prager,
J. S. Sarff, and C. R. Sovinec.

Department of Physics, University of Wisconsin, Madison, Wisconsin 53706

ABSTRACT

Current drive using the lower-hybrid slow wave is shown to be a promising candidate for improving confinement properties of a reversed field pinch (RFP). Ray-tracing calculations indicate that the wave will make a few poloidal turns while spiraling radially into a target zone inside the reversal layer. The poloidal antenna wavelength of the lower hybrid wave can be chosen so that efficient parallel current drive will occur mostly in the poloidal direction in this outer region. Three-dimensional resistive magnetohydrodynamic (MHD) computation demonstrates that an additive poloidal current in this region will reduce the magnetic fluctuations and magnetic stochasticity.

PACS: 52.55.Ez, 52.35.Hr, 52.35.Py, 52.65.+z

- a) Permanent address: Department of Physics and Astronomy, University of Montana, Missoula, Montana 59812.
- b) Permanent address: General Atomics, San Diego, California 92186.
- c) Also Department of Nuclear Engineering and Engineering Physics, University of Wisconsin, Madison, Wisconsin 53706.

MASTER

Recent experimental and computational results indicate that magnetic stochasticity arising from tearing-like fluctuations produces the anomalous energy and particle transport in the reversed field pinch. This has been established in the MST (Madison Symmetric Torus) reversed field pinch¹ through the direct measurement of energy and particle flux driven by magnetic fluctuations,^{2,3} and through resistive MHD computation which evolves the plasma pressure.⁴ The responsible tearing fluctuations, typically dominated by several helical modes,⁵ are driven by current density gradients. Hence, through current profile control the fluctuations and transport can be reduced. Current drive in the outer region of the RFP (in the direction parallel to the magnetic field, which is dominantly poloidal at the edge) suppresses the gradients while supplying current to sustain reversal. Stabilization of the tearing fluctuations was first demonstrated in MHD computation in which current is injected electrostatically at the edge ("dc helicity injection").⁶ An encouraging experimental result has been obtained in MST in which the energy confinement time was doubled by modest edge current drive by a transient inductive poloidal electric field.⁷

To optimize and sustain an improved confinement state, however, it is desirable to effect this control using a method that is nontransient, noninvasive, and internally controllable (as opposed to surface current injection). One such method is radio-frequency current drive (RFCD) in the poloidal direction. The higher plasma beta in the RFP has stimulated interest in fast wave current drive. It has been shown that the fast wave can be used to drive a poloidal current in the outer region and a toroidal current in the central region.^{8,9}

In this Letter, we show that the lower-hybrid slow wave is ideally suited for poloidal current drive in the outer region of the RFP. We examine

accessibility, ray propagation, and current drive efficiency. The optimal radial location for rf current drive to suppress fluctuations is established by incorporating auxiliary current drive in a nonlinear resistive MHD code.

To demonstrate auxiliary current drive suppression of magnetic fluctuations, a parallel electron force has been added to the 3-D, nonlinear, resistive MHD code DEBS (described in detail elsewhere¹⁰). This electron force reduces to a term in Ohm's law and a term in the single-fluid momentum equation. The force is assumed to be Gaussian in its radial profile, and it is directed to produce current parallel to the magnetic field. These simulations are in cylindrical geometry, with Lundquist number of 10^4 and effective aspect ratio of 3. Figure 1a shows the mean parallel current density profile normalized to the magnetic field, $j_{\parallel}/B$, with and without the auxiliary force centered at $0.8a$. The profile includes the Ohmic and fluctuation-driven current (the dynamo effect) as well as the auxiliary ("rf") current. The profile flattening in the interior reduces the fluctuation energy by about an order of magnitude, as is evident in Fig. 1b which displays the axial mode n spectra for the azimuthal mode number $m = 1$. The residual dominant modes are resonant in the outer half of the plasma radius. As seen in Fig. 2, reducing the fluctuation restores closed, nested flux surfaces in the core which are stochastic without auxiliary current drive. To effect these changes in this uniform resistivity case, about 25% of the total poloidal current is rf-driven. The current drive efficiency is discussed later.

The optimal centering of the added current profile is roughly $0.1a$ inside the reversal layer. Added current profiles centered at smaller radii stabilize a smaller fraction of the region, while profiles centered at larger radii do not stabilize the core. This result is weakly dependent on variation of the safety factor profile (i.e., "shallow" or "deep" reversal). Since the reversal

surface is typically located near $0.8a$, the target radius for rf current drive is typically $0.7a$.

Having established the rf current drive target zone, we examine the feasibility of the lower hybrid wave. Distinguishing features of the RFCD problem in the RFP include i) large $\omega_{pe} / \omega_{ce}$ ranging from 3 to 10, ii) large magnetic shear with a reversal layer, and iii) small fraction of trapped particles. Here, ω_{pe} and ω_{ce} are electron plasma and electron cyclotron frequencies. In contrast, a comparably sized tokamak has $\omega_{pe} / \omega_{ce} < 1$, a strong toroidal magnetic field with small shear, and a large fraction of trapped particles. The lower hybrid frequency $\omega_{LH} \approx \omega_{pi}\omega_{ce} / (\omega_{pe}^2 + \omega_{ce}^2)^{1/2}$ can be approximated by $(\omega_{ce}\omega_{ci})^{1/2}$ in the RFP. (The subscript i refers to ion quantities.) Our lower-hybrid poloidal current drive (LHPCD) study is based on the theory developed for the tokamak^{11,12,13} but appropriate conversions have been made to take into account differences in magnetic topology and plasma parameters.

Because of a larger $\omega_{pe} / \omega_{ce}$, the parallel refractive index $n_{\parallel}$ of the lower-hybrid slow wave must be chosen larger than that in a comparably sized tokamak to insure accessibility. In the frequency range $2 - 3\omega_{LH}$, the slow wave branch of the cold plasma dispersion relation leads to an approximate inequality $n_{\parallel}^2 \gtrsim [(1 + \omega_{pe}^2 / \omega_{ce}^2)^{1/2} + \omega_{pe} / \omega_{ce}]^2$ for a propagating wave. The lower hybrid wave satisfying this accessibility condition is predominantly electrostatic and the wave vector $\mathbf{k}$ points almost perpendicular to the magnetic field. The direction of the group velocity is almost perpendicular to $\mathbf{k}$ and its magnitude is of order $c / n_{\parallel}$, where c is the speed of light in vacuum. The energy and momentum carried by the lower hybrid wave will be mostly in the poloidal direction, but a small radially inward component will cause the wave to spiral into the plasma.

As an example, we consider a typical MST RFP plasma (major radius $R = 1.5$ m, minor radius $a = 0.5$ m) with a toroidal current of 400 kA, a poloidal magnetic field strength of 1.6 kG at the plasma edge, and an electron density of $1.2 \times 10^{19} \text{ m}^{-3}$ on the magnetic axis. To permit penetration of the lower hybrid wave, we must choose $n_{\parallel} \gtrsim 8$ at the edge. For example, this corresponds to a poloidal antenna wavelength of 19 cm and frequency $\omega / 2\pi = 2f_{LH} \sim 200$ MHz. The radial penetration of the wave into a higher density region is facilitated by an upshifting of $k_{\parallel} = 2\pi / \lambda_{\parallel}$, which is due to $1/r$ geometric reduction of $\lambda_{\parallel}$. Here, $\lambda_{\parallel}$ is the wavelength in the direction of the equilibrium magnetic field (predominantly poloidal in the outer region). For $n_{\parallel} < 8$, $n_{\perp}$ is imaginary, even at the plasma edge, and the wave fails to penetrate.

The damping of the wave energy along a ray trajectory is estimated by calculating the imaginary part of the warm plasma dielectric tensor. To control the poloidal current profile by a traveling lower hybrid wave, we need to choose $n_{\parallel}$ such that the wave energy be mostly deposited in moderate to high energy electrons in the target zone. This can be accomplished by choosing $\lambda_{\parallel}$ at the edge such that $v_{ph\parallel} / v_{the} \sim 2$ to 3 in the target zone, where, $v_{ph\parallel}$ is the parallel phase velocity of the wave and v_{the} is the electron thermal speed. This kinetic constraint imposes an upper limit on $n_{\parallel}$ for wave energy accessibility, precludes the possibility of traveling wave penetrating to the core of an RFP plasma, and makes the lower hybrid wave suitable for poloidal current drive in the outer plasma region.

For the typical MST discharge mentioned earlier the electron temperature in the target zone $0.7a$ is about 200 eV and electron density is about $8 \times 10^{18} \text{ m}^{-3}$. The lower hybrid wave at $\omega / 2\pi = 250$ MHz with $n_{\parallel} = 10$

(or $\lambda_{\parallel} = 12$ cm) at the plasma edge will complete about two poloidal turns before reaching the target zone where electron Landau damping is efficient.

The analytic estimates for the typical MST discharge have been confirmed by using an extended version of the Brambilla's ray tracing code.¹⁴ In the code we specify the values of ω and $n_{\parallel}$ of the lower hybrid wave at the wall and launch a single ray from an outboard point on the equatorial plane. The magnetic field structure is chosen to match an experimental profile in MST. The ray integration is carried out until the ray energy drops to 0.1% of the initial value. Figure 3a shows the ray trajectory projected on a constant toroidal angle plane. The ray travels about 90° in the toroidal direction before being fully damped.

The efficiency of RFCD can be characterized by a local quantity $\eta = j_{\parallel}^{rf} / p^{rf}$, where $j_{\parallel}^{rf}$ is the rf-driven current density and p^{rf} is the rf power density deposited in the plasma. A useful but approximate formula for the total rf power requirement is given by assuming that LHPCD takes place uniformly within a cylindrical shell of inner radius r_1 and outer radius r_2 . In this case, the rf-driven poloidal current I_{θ}^{rf} per total rf-power absorbed P is

$$I_{\theta}^{rf} / P = j_{\parallel}^{rf} 2\pi R(r_2 - r_1) / [p^{rf} 2\pi R(\pi r_2^2 - \pi r_1^2)] = \eta / (2\pi r_{av}),$$

where $r_{av} = (r_1 + r_2) / 2$. In a tokamak, the rf-driven toroidal current per total rf-power absorbed is $I_{\phi}^{rf} / P = j_{\parallel}^{rf} \pi r^2 / (p^{rf} 2\pi R \pi r^2) = \eta / (2\pi R)$. Hence, poloidal current drive in an RFP has a topological advantage of R / r_{av} over toroidal current drive in a tokamak. It is useful to note that for typical RFP equilibria,¹⁵ $I_{\theta} \approx (3R / a\Theta) I_{\phi}$ where I_{θ} and I_{ϕ} are the total poloidal and toroidal plasma currents respectively, and $\Theta \approx 2$ is the pinch parameter. Recall the MHD simulation predicted $I_{\theta}^{rf} \approx 0.25 I_{\theta}$ for stabilization.

The current drive efficiency is approximately given by $\eta = (38.4 \times 10^{18} / \ln \Lambda) (T_e / n_e) \eta_0$ [A-m/W], where $\ln \Lambda$ is the Coulomb logarithm, T_e is the electron temperature in keV, and n_e is the electron density in meter⁻³. The dimensionless quantity η_0 is plotted in the paper by Ehst and Karney¹⁶ as a function of the parallel phase velocity of the wave normalized to the electron thermal speed and the fraction of trapped electrons. The poloidal magnetic field in the outer region of the RFP varies less than 10% on a flux surface, so only a small fraction of current carrying electrons will be trapped. Hence, the reduction in current drive efficiency due to particle trapping is small.

For the MST example above, we expect to achieve $\eta_0 \approx 10$ and $I_\theta^f / P \approx 0.5$ A/W. The rf-driven current density peaks at around $r = 0.7a$ (see Fig. 3b), and the anticipated total rf power for stabilization is $P \approx 1$ MW. Magnetic fluctuations and anomalous particle losses may reduce the current drive efficiency. However, these effects might be avoided by preconditioning the target plasma with the aforementioned transient inductive current profile control.⁷

In summary, we have demonstrated that the lower-hybrid slow wave is a promising candidate for efficient poloidal (parallel) current drive in the outer region of an RFP. Accessibility, energy absorption, and current drive have been evaluated through a combination of analytical calculations and computational ray tracing. To demonstrate the effect on magnetic fluctuations, auxiliary current drive in the outer region has been added to a nonlinear MHD code. The magnetic fluctuations are greatly reduced by the current profile flattening, and magnetic stochasticity in the core is essentially eliminated. Hence, we anticipate that lower-hybrid current profile control is a suitable means to substantially improve confinement in the RFP.

ACKNOWLEDGMENTS

This work is supported by the U.S. Department of Energy grant no. DE-FG02-85ER53212 and contract no. DE-AC03-89ER51114.

REFERENCES

- ¹R. N. Dexter, D. W. Kerst, T. H. Lovell, S. C. Prager, and J. C. Sprott, *Fusion Technol.* **19**, 131 (1991).
- ²G. Fiksel, S. C. Prager, W. Shen, and M. Stoneking, *Phys. Rev. Lett.* **72**, 1028 (1994).
- ³M. Stoneking, S. A. Hokin, S. C. Prager, G. Fiksel, H. Ji, and D. Den Hartog, *Phys. Rev. Lett.*, in press.
- ⁴D. Schnack, Y. L. Ho, B. A. Carreras, K. Sidikman, G. G. Craddock, N. Mattor, R. A. Nebel, S. C. Prager, P. W. Terry, and E. J. Zita, in *Plasma Physics and Controlled Nuclear Fusion Research, 1992*, Wurzburg (International Atomic Energy Agency, Vienna, 1993), Vol. 2, p. 553.
- ⁵See, for example, I. H. Hutchinson, M. Malacarne, P. Noonan, and D. Brotherton-Ratcliffe, *Nuclear Fusion* **24**, 59 (1984).
- ⁶Y. L. Ho, *Nucl. Fusion* **31**, 341 (1991).
- ⁷J. S. Sarff, S. A. Hokin, H. Ji, S. C. Prager, and C. R. Sovinec, *Phys. Rev. Lett.*, in press.
- ⁸S. Shiina, K. Saito, Y. Kondoh, H. Ishii, T. Shimada, Y. Hirano, in *Proceedings of the 19th EPS Conference on Controlled Fusion and Plasma Physics, 1992* (European Physical Society, Innsbruck, 1992), Vol. 16C, p. 917.
- ⁹H. Ishii, Y. Kondoh, T. Shimada, Y. Hirano, S. Shiina, and K. Saito, in *Proceedings of the 20th EPS Conference on Controlled Fusion and Plasma Physics, 1993* (European Physical Society, Lisbon, 1993), Vol. 17C, p. 495.
- ¹⁰D. D. Schnack, D. C. Barnes, Z. Mikic, D. S. Harned, and E. J. Caramana, *J. Comp. Physics* **70**, 330 (1987).
- ¹¹N. J. Fisch, *Phys. Rev. Lett.* **41**, 875 (1978).
- ¹²P. T. Bonoli and R. C. Englade, *Phys. Fluids* **29**, 2937 (1986).
- ¹³N. J. Fisch, *Rev. Modern Phys.* **57**, 175 (1987).
- ¹⁴M. Brambilla, *Computer Physics Reports* **4**, 71 (1986).
- ¹⁵J. C. Sprott, *Phys. Fluids* **31**, 2266 (1988).
- ¹⁶D. A. Ehst and C. F. F. Karney, *Nucl. Fusion* **31**, 1933 (1991).

FIGURE CAPTIONS

Figure 1: (a) The $j_{\parallel} / B$ profile, and (b) the axial mode number spectrum of magnetic energy, for $m = 1$ fluctuations before (solid line) and after (broken line) the addition of auxiliary current (the electron force). The toroidal magnetic field is only slightly reversed in this MHD computation.

Figure 2 : Magnetic field line puncture plots in the axial-radial plane (a) before and (b) after the addition of auxiliary current (the electron force).

Figure 3 : (a) The ray trajectory of a lower hybrid wave ($\omega / 2\pi = 250$ MHz and $n_{\parallel} = 10$ at the wall) projected on a constant toroidal angle plane. An effective aspect ratio of 30 was used to reduce variations in the poloidal magnetic field on a flux surface. (b) The profile of the rf driven current. The vertical axis is in arbitrary units.

FIG. 1

FIG. 2

FIG. 3

EXTERNAL DISTRIBUTION IN ADDITION TO UC-20

S.N. Rasband, Brigham Young University
T. Dolan, EG&G Idaho, Inc.
R.A. Moyer, General Atomics
J.B. Taylor, Institute for Fusion Studies, The University of Texas at Austin
E. Uchimoto, University of Montana
F.W. Perkins, PPPL
O. Ishihara, Texas Technical University
M.A. Abdou, University of California, Los Angeles
R.W. Conn, University of California, Los Angeles
P.E. Vandenplas, Association Euratom-Etat Belge, Belgium
Centro Brasileiro de Pesquisas Físicas, Brazil
P. Sakanaka, Institute de Física-Unicamp, Brazil
Mme. Monique Bex, GANIL, France
J. Radet, CEN/CADARACHE, France
University of Ioannina, Greece
S. Ortolani, Istituto Gas Ionizzati, EURATOM-ENEA-CNR Association, Italy
R. Andreani, Associazione EURATOM-ENEA sulla Fusione, Italy
Plasma section, Energy Fundamentals Division Electrotechnical Laboratory, Japan
Y. Kondoh, Gunma University, Kiryu, Gunma, Japan
H. Toyama, University of Tokyo, Japan
Z. Ypsjoda, University of Tokyo, Japan
FOM-Instituut voor Plasmafysica "Rijnhuizen," The Netherlands
Z. Ning, Academia Sinica, Peoples Republic of China
P. Yang, Shandong University, Peoples Republic of China
S. Zhu, University of Science & Technology of China, People's Republic of China
I.N. Bogatu, Institute of Atomic Physics, Romania
M.J. Alport, University of Natal, Durban, South Africa
R. Storer, The Flinders University of South Australia, South Australia
B. Lehnert, Royal Institute of Technology, Sweden
Librarian, CRPP, Ecole Polytechnique Federale de Lausanne, Switzerland
B. Alper, Culham Laboratory, UK
A. Newton, UK

2 for Chicago Operations Office
5 for individuals in Washington Offices

INTERNAL DISTRIBUTION IN ADDITION TO UC-20
80 for local group and file

DATE

FILMED

8/24/94

END