AIM

Association for Information and Image Management

1100 Wayne Avenue, Suite 1100
Silver Spring, Maryland 20910
301/587-8202

Centimeter

Inches

MANUFACTURED TO AIM STANDARDS
BY APPLIED IMAGE, INC.

1 of 1

DECLASSIFIED

-1-

HW-69940

[REDACTED]
[REDACTED]
[REDACTED] document contains [REDACTED] as
defined [REDACTED] Energy Act of 1954.
Its transmittal [REDACTED] and [REDACTED] of its
content [REDACTED] manner to an [REDACTED]
[REDACTED] prohibited.

This document consists of
32 pages, Copy 26 of
28 copies, [REDACTED]

This document classified by

RA Karvey.

ANALOG PROGRAM IN REACTOR SPEED OF CONTROL STUDIES

by

W. D. Cameron
Systems Research Operation
Physics and Instrument Research and Development
HANFORD LABORATORIES OPERATION

and

R. E. Tiller
Reactor Physics Operation
Process & Reactor Development Operation
IRRADIATION PROCESSING DEPARTMENT

Classification Cancelled and Changed To

DECLASSIFIED

By Authority of WA Snyder

CGPR-2 2-28-94

By J E Saperly 3-4-94

Verified By PT Schmitt 3-16-94

June 14, 1961

DECLASSIFIED

MASTER

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

DECLASSIFIED

-2-

HW-69940

Distribution

- 1 - C. W. Allen
- 2 - C. E. Bowers
- 3 - J. M. Brown
- 4 - W. D. Cameron
- 5 - R. D. Carter
- 6 - F. G. Dawson
- 7 - G. C. Fullmer
- 8 - C. R. Gallagher - HOO-AEC
- 9 - P. F. Gast
- 10 - O. M. Greager
- 11 - A. K. Hardin
- 12 - R. A. Harvey
- 13 - R. E. Heineman
- 14 - E. D. Jones
- 15 - R. H. Meichle
- 16 - D. I. Monnie
- 17 - W. S. Nechodom
- 18 - R. Nilson
- 19 - G. F. Owsley
- 20 - R. S. Paul
- 21 - R. W. Reid
- 22 - G. R. Taylor
- 23 - R. E. Tiller
- 24 - R. E. Trumble
- 25 - F. W. Van Wormer
- 26 - A. D. Vaughn
- 27 - 300 Files
- 28 - Record Center

DECLASSIFIED

TABLE OF CONTENTS

	Page
ABSTRACT	4
INTRODUCTION	4
Purpose of Report	4
Purpose of Study	4
Scaling	4
System Analog	5
Kinetic Equations	5
Temperature Equations	6
List of Constants	7
List of Variables	8
Potential Settings	10
Limit Curve Calculations	16
Results Checking	19
ACKNOWLEDGEMENTS	19

LIST OF TABLES

Number		Page
I	Switching Logic	10
II	Old Pile Parameters - OIIN Slug	11
III	Old Pile Parameters - OIIN Slug	15
IV	"C" Pile Pot Settings	17
V	Green Uranium	17
VI	Changes for 0 Exposure to 400 Exposure	18
VII	Initial Temperature Distribution Chart	20

LIST OF FIGURES

Number		Page
1	Computer Notations	21
2	Old Reactors Speed of Control	22
3	Old Reactors Speed of Control	23
4	Old Reactors Speed of Control	24
5	Old Reactors Speed of Control	25
6	RWWL Function for BDF Tube - C and H Piles	26
7	D-Function vs. Megawatt-Sec.	27
8	Normal VSR Function - Rod Drop	28
9	Specific Heat vs. Temperature	29
10	Limit Curves for C and H Piles	30
11	Typical Transient Result	31
12	Typical Transient Response	32

DECLASSIFIED

ABSTRACT

This report describes the methods used in calculating the speed of control of the Hanford reactors and explains the analog simulator used in these calculations.

INTRODUCTIONPurpose of Report

The purpose of this report is to show the techniques used to analyze the speed of control of the Hanford reactors. This report will help to standardize the methods and reduce to a routine the solution of this type of problem. The analog circuits will be presented and explained.

A report has been written previously on the speed of control. The changes in the problem have necessitated the redesigning of the analog circuit and also the issuing of this report. This report compiles and organizes the analog work done on the speed of control to date.

Purpose of Study

One of the characteristics of the safety control system of the Hanford reactors which is of primary concern from the standpoint of reactor safety is the response time. The purpose of this study is to determine whether the safety control system is sufficiently fast-acting to prevent an intolerably large power excursion from developing. An intolerably large power excursion is one that would cause a melting of the uranium while the reactor power is above the previous operating level. The purpose of the study is discussed more fully in report HW-63157(1), and also the significance of the results.

The parameters used in obtaining the curves shown in this report may not be the best current values. These curves are included in this report to aid in checking out the simulation.

Scaling

The operating limits of all computer components are between +100 volts and -100 volts. These limits require that the problem be scaled to operate inside of these limits. For this reason the output of an amplifier may be indicated by $0.1X$, $0.01X$, $10X$, $1000X$, etc., where X is the variable to be measured. If the output of an amplifier has the indicator $100X$ and the voltage is measured to be 62.57 volts, then at this time

$X = \frac{62.57}{100} = 0.6257$. If some quantity X may have a value up to Z units, then the output

of the component generating this function must generate no more than $\frac{100}{Z}$ times the

value of the quantity X . For example, suppose the quantity X will have magnitudes up to 10,000 units, then the output of the component generating X could be labeled

$\frac{100}{10,000} X = 0.01X$ or a lesser fraction such as $0.005X$ depending on the nature of the

(1) Peden, J. C., R. Nilson, R. E. Tiller. Parametric Analysis of Hanford Speed of Control Criterion.

DECLASSIFIED

other circuits.

System Analog

Figure 1 shows the computer notations that are used in this report. The analog computer circuit used to simulate the reactor is shown in Figures 2, 3, and 4. The size of the circuit has necessitated drawing the circuit on three separate sheets. Figure 2 is the circuit for the reactor kinetics and associated logic. The thermal model; i.e., the heat transfer model, is shown in Figure 3. The special function generators used to simulate the effects of specific heat in each of the five regions are shown in Figure 4. The wiring diagrams for the variable base function generators are shown in Figure 5.

Amplifiers 6, 7, 10, 11, 20, 21, and 4 in Figure 2 generate the delayed neutrons. Six groups are used in this study. Amplifier 3 generates the neutron density n , or power. When the output of amplifier 3 (or 50) equals 10 volts, the reactor power is 4000 MW. Amplifier 34 is the power level controller. Potentiometer 85 is set so the output equals the operating power level voltage. If the power level is to be 3000 MW, the potentiometer is set at 0.0750 or 7.5 volts. This will control the output of amplifier 3 to 7.5 volts and allow the delayed neutrons to come to the proper initial conditions. The control rods can then be moved in or out by adjusting potentiometer H1, going into amplifier 5, until the output of amplifier 34 is zero. Amplifier 34 can then be removed from the circuits by the use of a switch.

System EquationsKinetic Equations

$$\frac{dn}{dt} = \left(\frac{\delta K_T - \beta}{\ell^*} \right) n + \sum_{i=1}^6 \lambda_i C_i + S \quad (1)$$

$$\frac{dC_i}{dt} = \left(\frac{\beta_i}{\ell^*} \right) n - \lambda_i C_i \quad (2)$$

$$\beta = \sum_{i=1}^6 \beta_i \quad (3)$$

$$\delta K_T = \delta K_M + \delta K_C + \delta K_{VSR} + \delta K_R \quad (4)$$

DECLASSIFIED

Temperature Equations

$$\frac{dT_1}{dt} = \frac{1}{c_1} \left[A_1 n(t) + B_1 n(\text{eq.}) + k_{12} A_1^+ (T_2 - T_1) + D A_1^- (T_w - T_1) \right]$$

$$\frac{dT_2}{dt} = \frac{1}{c_2} \left[A_2 n(t) + B_2 n(\text{eq.}) + k_{23} A_2^+ (T_3 - T_2) - k_{12} A_2^- (T_2 - T_1) \right]$$

$$\frac{dT_3}{dt} = \frac{1}{c_3} \left[A_3 n(t) + B_3 n(\text{eq.}) + k_{34} A_3^+ (T_4 - T_3) - k_{23} A_3^- (T_3 - T_2) \right]$$

$$\frac{dT_4}{dt} = \frac{1}{c_4} \left[A_4 n(t) + B_4 n(\text{eq.}) + k_{45} A_4^+ (T_5 - T_4) - k_{34} A_4^- (T_4 - T_3) \right]$$

$$\frac{dT_5}{dt} = \frac{1}{c_5} \left[A_5 n(t) + B_5 n(\text{eq.}) + A_5^+ (T_w - T_5) D - k_{45} A_5^- (T_5 - T_4) \right]$$

where,

$$K_{i,i+1} = \left[A + B/2(T_i + T_{i+1}) \right]$$

$$A_i^+ = \frac{2r_{i+1}L}{\rho \Delta r^2 (2r_i + \Delta r) L_f} \quad \text{for } i = 1 \text{ to } 4$$

$$A_i^- = \frac{2r_i L}{\rho \Delta r^2 (2r_i + \Delta r) L_f} \quad \text{for } i = 2 \text{ to } 5$$

$$A_5^+ = (\rho R_{\text{out}} V_5)^{-1}$$

$$A_1^- = (\rho R_{\text{in}} V_1)^{-1}$$

$$A_i = 2.2815 \times 10^5 \frac{f_i \sigma}{\rho V_i (\text{ECT})}$$

$$B_i = 1.419 \times 10^5 \frac{f_i \sigma}{V_i (\text{ECT})}$$

DECLASSIFIED

List of Constants

<u>Parameter</u>	<u>CIIN Slug</u>	<u>VALUE</u>	
		<u>OIIN Slug</u>	<u>KIIN Slug</u>
A_1^+	1.2918	1.1836	1.3084
A_2^+	1.2504	1.1338	1.26304
A_3^+	1.2248	1.10504	1.23751
A_4^+	1.0403	1.08663	1.22003
A_5^+	.08829	.084177	.084452
A_1^-	.07452	.064548	.072052
A_2^-	.9847	.86463	.998584
A_3^-	1.0101	.89303	1.03007
A_4^-	1.0274	.91172	1.04042
A_5^-	1.0403	.92471	1.05285
A_1	.5225	.5488	.5194
A_2	.5261	.5264	.5197
A_3	.5485	.5329	.5396
A_4	.5895	.5617	.5783
A_5	.6524	.6131	.6390
B_1	.03250	.03413	.03230
B_2	.03272	.03274	.03232
B_3	.03411	.03314	.03356
B_4	.03666	.03494	.03597
B_5	.04058	.03813	.03974
ECT	1500	1500	2500

DECLASSIFIED

List of Variables

n = neutron density

δK = excess reactivity ($K_{eff} - 1$)

β = fraction of fission neutrons which are delayed

β_i = fraction of fission neutrons which are born in the i^{th} delayed group $\beta = \sum_i \beta_i$

ℓ^* = neutron mean lifetime (sec.)

λ_i = decay constant for the i^{th} group of delayed neutrons

C_i = concentration of the precursor for the i^{th} delayed group

δK_M = reactivity due to fuel temperature

δK_C = reactivity due to coolant temperature

δK_{VSR} = reactivity due to vertical safety rods

δK_R = reactivity due to control rods, Xe^{135} , etc.

T_i = average temperature of region i

V_i = volume of region i

R_{out} = resistance to heat flow between the node of region 5 and the H_2O

R_{in} = resistance to heat flow between the node of 1 and H_2O

$K_i(i+1)$ = the average conductivity between region i and $i+1$

L = the total charge length including end caps

L_f = actual length of uranium

K_u = conductivity of uranium = 0.059 cal/sec - cm - $^{\circ}C$

K_{AL} = conductivity of aluminum = 0.050 cal/sec - cm - $^{\circ}C$

ρ_u = density of uranium = 18.9 gm/cm³

V_i = inner radius of region i

$\Delta r = r(i+1) - r_i$

f_i = fraction of heat generated in region i , $\sum_i f_i = 1$

ECT = number of effective tubes

σ = scale factor

The output of amplifier 5 is $(\delta K - \beta)10^3$. When steady state conditions are reached, the output of this amplifier must equal $\beta \times 10^3$ since δK must equal 0. If $\beta = 6.25 \times 10^{-3}$, then the output here should be -6.25 volts. For accurate transient results the output must be between -6.22 volts and -6.28 volts. If this output is not within these limits, then multiplier (M-0) being fed from this amplifier is probably out of calibration and should be adjusted.

Potentiometer 11 is fed to amplifier 3 through switch 2-3 and serves as a neutron source. This source is switched out of the circuit shortly after startup. Potentiometer 61 is also fed through switch 2-3 and is likewise removed from the circuit after startup. This potentiometer is set to approximately five times the value of potentiometer 85. If the operating power is 2000 MW, potentiometer 85 is set at 0.0500 and potentiometer 61 is set to about 0.2500. This potentiometer is used as a source to initialize amplifier 43. The output of amplifier 43 is two times the output of amplifier 3 at steady state. Amplifier 43 is locked in at this value which represents twice the steady state operating power level. This voltage is attenuated through potentiometer 1, the output of which represents the power due to the delay neutrons. This power is assumed to remain constant since the delayed power decay is relatively slow during the fast transients being studied here.

Amplifier 2 is wired as an integrator and is used to drive function generators 13 and 14. This integrator is limited to prevent its output from exceeding 100 volts. A switch is used to short the output to the input to prevent drift on integrator 2 while the reactor is reaching operating conditions.

Function generator 13 is the reactivity weighted water loss (RWWL) function. This function represents the amount of reactivity due to the water coolant in the reactor, and is shown in Figure 6 for 'C' and 'H' piles.

Function generator 14 is the D₀ function. D₀ equals unity when the channel is full with water and equals zero at no flow. This allows for the resistance of the heat transfer to the water to become infinite when water is lost. This function is shown in Figure 7.

Amplifier 16 is wired as an integrator and is used to drive function generator 15. This integrator is limited to prevent its output from exceeding 100 volts. The initial condition on this integrator has the opposite sign as the driving voltage. This allows a time delay between the time the switch is thrown and the function starts in.

Function generator 15 is the vertical safety rods (VSR) insertion function. This function is shown in Figure 8. This function represents the reactivity worth of the VSR's as a function of time, from the instant the rods actually start to go in. The delay between the scram signal and the start of rod fall is simulated by putting an initial voltage of opposite sign on the driving integrator.

The thermal model is shown in Figure 3. The fuel has been divided into five radial sections, section one being the inner region and five being the outer region. The region temperatures are averaged in amplifier 17. The temperature observed in these studies for melting is T₅.

The special function generator (SFG) used in each region has the same function on it and is shown in Figure 9. These function generators are all specially built on the computer. The diagram for these function generators is shown in Figure 4. The output of each of these function generators is $10\left(\frac{1}{c(t)} - 36.6\right)$, where $c(t)$ is the specific heat.

There are four function switches used in this program. Each of these switches is a double-pole, triple-throw, telephone-type switch. Each switch has a two digit numerical representation; i.e., 0-1, 2-3, etc. Table I, below, lists the use of each of these switches.

TABLE I

Switching Logic

<u>Switch</u>	<u>Function Up</u>	<u>Function Down</u>
0-1	Scram	Normal operating position
2-3	Source in	Source out
6-7	Controller In, Integrator 2 Shorted	Controller Out, Integrator 2 Open
8-9	Controller in	Controller out

When the reactor is first started up, the switches should be in the following positions: 0-1, down; 2-3, up; 6-7, up; and 8-9, up. The switches will be used in the following order:

- First - Switch 2-3 is placed in the down position a few seconds after the computer is placed in operate.
- Second - Switch 8-9 is placed in the down position a few seconds before scram.
- Third - Switch 6-7 is placed in the down position.
- Fourth - Switch 0-1 is placed in the up position to scram.

This order of switching must be followed. The scram switch must be thrown when integrator 16 is at the proper initial condition voltage, and integrator 5 has $\beta \times 10^3$ volts. These conditions must be met to obtain valid results.

Potential Settings

The potentiometer settings and their value, when pertinent, are listed in Table II for the old piles with OIIN slugs. The potentiometers, used in the special function generators, are not included in this table but are listed separately in Table III. In Table III the actual reading of the dial is listed with loading factors already considered.

DECLASSIFIED

HW-69940

TABLE II

Old Pile Parameters
OLIN Slug

<u>Pot Number</u>	<u>Pot Setting</u>	<u>Value or Purpose</u>
1	0.03375	
2	0.25	2.5
3		
4		
5	0.1896	
6	0.02230	metal coefficient ($-10^3 \delta K_M$)
7	0.15234	$.1 \frac{\beta_1}{\ell^*} = 0.0223$
8		$.1 \frac{\beta_2}{\ell^*} = 0.15234$
9	0.3037	λ_4
10	0.13960	$.1 \frac{\beta_3}{\ell^*} = 0.13960$
11		source
12	0.2140	used in $\frac{1}{\text{conductivity}}$
13	0.2510	
14	0.3660	
15	0.7012	10 D ₁
16		
17	0.1247	
18	0.1407	
19	0.42774	
20	0.092276	$.1 \frac{\beta_5}{\ell^*} = 0.092276$
21	0.22676	
22	.02410	

DECLASSIFIED

TABLE II (cont.)

<u>Pot Number</u>	<u>Pot Setting</u>	<u>Value or Purpose</u>
23	0.2510	
24	0.366	
25	0.366	
26	0.275	
27	0.1675	
28	0.1675	
29	0.17861	
30	0.2410	Used in $\frac{1}{\text{conductivity}}$
31	0.2510	
32	0.1675	
33	0.2750	
34		
35	0.6000	Ramp on V.S.R.
36	0.2410	Used in $\frac{1}{\text{conductivity}}$
37	0.2510	
38	0.3660	
39	0.3660	
40	0.5617	
41		
42		
43		
44	0.2410	Used in $\frac{1}{\text{conductivity}}$
45	0.2510	Used in $\frac{1}{\text{conductivity}}$

DECLASSIFIED

TABLE II (cont.)

<u>Pot Number</u>	<u>Pot Setting</u>	<u>Value or Purpose</u>
46	0.81678	
47	0.01906	2 delayed sources
48	0.2750	
49		
50		
51	0.0684	
52	0.3896	10^3 SK rods
53	0.602	
54	0.1147	$.1 \lambda_5 = 0.1147$
55	0.30533	$.1 \lambda_6 = 0.30533$
56	0.0125	λ_1
57	0.0306	λ_2
58		
59	0.1125	λ_3
60	0.28595	$.1 \beta_4 \frac{1}{\ell^*} = 0.28595$
61	0.5	
62	0.3858	
63	0.01707	2 delayed source 1
64	0.2367	2 C_{12}
65	0.5488	$S_1 \frac{1}{N}$
66		.3 for 30 mk
47	0.11391	
68	0.19725	

DECLASSIFIED

-14-

HW-69940

TABLE II (cont.)

<u>Pot Number</u>	<u>Pot Setting</u>	<u>Value or Purpose</u>
69	0.032936	$.1 \beta_6 \frac{1}{\ell^*} = 0.032936$
70	0.17293	
71	0.01637	2 delayed source 2
72	0.3858	
73	0.5264	
74	0.055	$.1 T_w = 0.055$
75	0.1675	
76	0.1675	
77	0.275	
78	0.01657	2 delayed source 3
79	0.22101	
80	0.3858	
81	0.5329	
82	0.1675	
83	0.1675	
84		I.C. on ampl. 16
85		Power level setpoint
86	0.3858	Used in $\frac{1}{\text{conductivity}}$
87	0.01747	2 delayed source 4
88	0.18234	
89	0.21733	
90		
91		

DECLASSIFIED

TABLE II (cont.)

<u>Pot Number</u>	<u>Pot Setting</u>	<u>Value or Purpose</u>
92		
93		
94	0.3858	Used in getting $\frac{1}{\text{conductivity}}$
95	0.18494	
96	0.6131	
97		
98	0.1675	
99		
100		

TABLE III

Old Pile Parameters
OLIN Slug

<u>Pot Number</u>	<u>Pot Dial Reading</u>	<u>Value or Purpose</u>
h2	0.6951	All of these potentiometers are used in SFG 1, 2, 3, 4, and 5.
h3	0.8039	
h4	0.6951	
h5	0.8039	
h6	0.6951	
h7	0.8039	
h8	0.6951	
h9	0.8039	
h10	0.6951	
h11	0.8039	

All settings used in obtaining $\frac{1}{C}$

The potentiometer changes to be made are listed in Table IV to simulate "C" pile. All of these changes are in the thermal model.

To study the effects of a green pile, the potentiometer settings in kinetics should be set as shown in Table V.

Table VI lists the potentiometer changes for zero (0) exposure to 400 exposure. Again, all of these potentiometers are in the kinetic simulator.

There are five significant potentiometers in the model; i.e., potentiometers that will be changed often. These potentiometers are listed below for quick reference.

- Pot. 85 - Determines equilibrium power $10v = 4000$ MW
- Pot. 61 - Set at approximately five times potentiometer 85 (50 volts maximum)
- Pot. 66 - Water worth: $20v = 20$ milli k
- Pot. 52 - Rods length: $20v = 20$ milli k
- Pot. 84 - I.C. on amplifier 16*: for 0.8 second rod delay = 48 v
for 0.4 second rod delay = 24 v

* In each case set potentiometer 6 to 10 volts high to allow for leakage while delayed neutrons stabilize.

Limit Curve Calculations

A typical limit curve is shown in Figure 10. This curve is for "C" and "H" piles using the parameters shown. There are two limit curves shown in this figure, one for the green pile and one for the ripe pile.

A method will now be shown to check one of the points on the limit curve. If it is desired to check the point at 3000 MW on the green pile curve, the following method should be used:

1. Locate the 3000 MW point on the curve.
2. Locate the corresponding point on the water activity curve (= 20.7 milli k).
3. Set potentiometer 85 at 7.5 volts.
4. Set potentiometer 65 at 37.5 volts.
5. Set potentiometer 66 at 20.7 volts.
6. Set potentiometer 52 at 52.0 volts.
7. Set potentiometer 84 at 24.0 volts (or slightly higher).

The problem is now ready to run. A typical transient result is shown in Figure 11. This is not a true case but an example. The reactor power curve is checked and noted where the power returns and crosses through the operating power level; 3000 MW in this case. The outside temperature at this time is noted. If curve "A" in Figure 11 is obtained; i.e., if $T_c = 720^\circ\text{C}$, then a point on the limit curve is obtained at 3000 MW and a water reactivity worth of 20.7 milli k.

DECLASSIFIED

TABLE IV

"C" File Pot Settings

<u>Pot Number</u>	<u>Pot Setting</u>
15	0.7452
65	0.5194
64	0.25836
63	0.01615
70	0.19694
21	0.25008
73	0.5197
71	0.01616
29	0.20202
79	0.24496
81	0.5396
78	0.01678
88	0.25048
89	0.24148
40	0.5783
87	0.01798
95	0.20806
46	0.8829
96	0.6390
47	0.01987

NOTE: All of these potentiometers are in the temperature equations.

TABLE V

Green Uranium

<u>Pot Number</u>	<u>Pot Setting</u>	<u>Value or Purpose</u>
6	0.01618	0.1 $\frac{\beta_1}{\rho^*}$
7	0.11051	0.1 $\frac{\beta_2}{\rho^*}$
10	0.10126	0.1 $\frac{\beta_3}{\rho^*}$
60	0.20742	0.01 $\frac{\beta_4}{\rho^*}$
20	0.06694	0.1 $\frac{\beta_5}{\rho^*}$
69	0.023894	0.1 $\frac{\beta_6}{\rho^*}$

$$\rho^* = 1.3 \times 10^{-3}$$

NOTE: All these potentiometers are in the kinetics.

DECLASSIFIED

TABLE VI

Changes for 0 Exposure to 400 Exposure

<u>Pot Number</u>	<u>Pot Setting</u>	<u>Value or Purpose</u>
6	0.0194	
7	0.1406	
10	0.1279	
60	0.2589	
20	0.0845	
69	0.0305	
56	0.0125	
57	0.0306	
59	0.1144	
9	0.3085	
54	0.1188	
55	0.3161	
51	0.0625	Changes $\Sigma_1 \beta_1$

$$\ell^* = .943 \times 10^{-3}$$

NOTE: New potentiometer settings for 0 exposure to 400 exposure MWD

Changes delay groups also now at .8 second delay (P84).

All of these potentiometers are in the kinetics.

DECLASSIFIED

If curve "B" is obtained; i.e., if T_5 is greater than 720°C at this point, then another try should be made with the water reactivity worth at some lesser value, such as 20.3 MK. This can be accomplished by resetting potentiometer 66 to 20.3 volts.

If curve "C" is obtained; i.e., if T_5 is less than 720°C at this point, then another try should be made with the water reactivity worth at some greater value, such as 21.1 MK. This can be done by resetting potentiometer 66 at 21.1 volts.

Results Checking

In this study the results are checked by comparing them with previous studies of speed of control of the Hanford reactors. This method of checking is justified because of the number of times this study has been made by several different engineers over a period of years.

There are three solution areas that can be compared with previous results. The main item to look for is consistency of the results with previous studies. These solution areas are: initial values of the problem variable, limit curve(s) obtained, and transient response.

The initial temperature in each node for various power levels is shown in Table VII. These temperatures must be accurate to within 4°C to obtain satisfactory results. The other initial conditions are readily calculable from the equations and the curves.

A point (or points) on the limit curve shown in Figure 10 can be obtained using the method previously explained. This point should be reasonably close to the curve; i.e., within the limits of the computer and recorder - 10°C . If the point is not reasonably close to the curve, the following should be checked: 1) the initial temperatures, power and other variable of time $t = 0$; 2) the water worth; 3) the output of the amplifier calculating $\delta K - \beta$; 4) the multiplier used in the kinetic circuit; 5) compare the transient response with the one shown in Figure 12. The test run must use the same data as given in the figures compared.

A typical transient response is shown in Figure 12. This response will be obtained using the data listed in the figure. If the proper response is not obtained, the discrepancies will give clues as to where the error is occurring in the problem.

ACKNOWLEDGEMENTS

The authors acknowledge the efforts of the many people who contributed to this study, particularly J. C. Peden who helped derive the equations and analyze the results, and W. E. McClung for drawing the figures in this report. This report is a compilation of the work of many people over a period of five years.

TABLE VII

Initial Temperature Distribution Chart

Power	T ₁	T ₂	T ₃	T ₄	T ₅
1000	102	133	141	124	96.5
1500	127	171	182	158	117
2000	152	208	221	190	136
3000	202	278	296	266	180
4000	245	341	360	319	217
5000	298	414	440	374	255

DECLASSIFIED

High Gain Amplifier
HG

Summing Amplifier
 Σ

Integrating
Amplifier
 $\int$

Potentiometer

Electronic Multiplier

Variable Base
Function Generator

Special
Function Generator

Differential Relay

Function Switch

Function Relay

Diode

Output Shunt Limiter

FIGURE 1. COMPUTER NOTATIONS

DECLASSIFIED

FIG. 2

SYSTEMS RESEARCH, H.L.O.

ENGINEER

DATE

3-16-61

TITLE

OLD REACTORS,
SPEED OF CONTROL

MACHINE

EASE

DECLASSIFIED

FIG. 3

SYSTEMS RESEARCH, H.L.O.

ENGINEER

DATE

3-16-61

TITLE

OLD REACTORS

SPEED OF CONTROL

MACHINE

EASE

DECLASSIFIED

FIG. 4

SYSTEMS RESEARCH, H. L. O.

ENGINEER

DATE

3-16-61

TITLE

OLD REACTORS

SPEED OF CONTROL

MACHINE

EASE

DECLASSIFIED

FIG. 5

SYSTEMS RESEARCH, H.L.O.

ENGINEER

DATE

3-16-61

TITLE

OLD REACTORS

SPEED OF CONTROL

MACHINE

EASE

DECLASSIFIED

DECLASSIFIED

SPECIFIC HEAT VS TEMPERATURE

$10 \frac{1}{2} \times 36.5$

F16.9

DECLASSIFIED

DATA TABLE

Page 1

HW 69940

- 32 -

DECLASSIFIED

DECLASSIFIED

TRANSIENT
 RESPONSE

II

DATE

FILMED

8/23/94

END