FIBER DISTRIBUTED DATA INTERFACE (U)

by

A. J. Johnson

Westinghouse Savannah River Company
Savannah River Site
Aiken, South Carolina 29808

Received by OSTI
AUG 20 1992

A technical report being deposited at OSTI

The information contained in this paper was developed during the course of work done under Contract No. DE-AC09-89SR18035 with the U.S. Department of Energy. By acceptance of this paper the publisher and/or recipient acknowledges the U.S. Government's right to retain a nonexclusive, royalty-free license in and to any copyright covering this paper, along with the right to reproduce and to authorize others to reproduce all or part of the copyrighted paper.

MASTER

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

This report has been reproduced directly from the best available copy.

Available to DOE and DOE contractors from the Office of Scientific and Technical Information, P.O. Box 62, Oak Ridge, TN 37831; prices available from (615) 576-8401, FTS 626-8401.

Available to the public from the National Technical Information Service, U.S. Department of Commerce, 5285 Port Royal Rd., Springfield, VA 22161.

Reviews of Computing Technology:

Fiber Distributed Data interface (U)

by A. J. Johnson

WSRC-IM-90-83-6

April 1, 1992

Authorized Derivative Classifier

G. F. Hayhoe

Westinghouse Savannah River Company
P. O. Box 616
Aiken, SC 29802

Table of Contents

1	Introduction	1
2	FDDI Technology.....	3
	The ISO Reference Model	3
	Fiber Optic Technology.....	5
	FDDI Over Copper Wires.....	7
	FDDI Ring Topology	7
	Components of the Standard	12
	FDDI Components.....	14
	Fault Tolerance.....	16
	FDDI Equipment	18
3	FDDI Applications	24
	LAN Interconnections	24
	LANs for High Performance Systems	26
4	FDDI at Savannah River	28
	Central Computer Facility LAN	28
	SRL Workstation LAN	29
	Intra-area LANs	30
	Inter-area LAN Connections	31

5 Summary	32
Appendix A - FDDI Frame Format	33
Appendix B - FDDI Bit Encoding	35

1 Introduction

Fiber Distributed Data Interface, more commonly known as **FDDI**, is the name of the standard that describes a new local area network (LAN) technology for the coming decade. This technology is based on fiber optics communications and, at a data transmission rate of 100 million bits per second (mbps), provides a full order of magnitude improvement over previous LAN standards such as Ethernet and Token Ring. FDDI as a standard has been accepted by all major computer manufacturers and is a national standard as defined by the American National Standards Institute (ANSI). FDDI will become part of the U. S. Government Open Systems Interconnection Profile (GOSIP) under Version 3 GOSIP and will become an international standard promoted by the International Standards Organization (ISO). It is important to note that there are no competing standards for high performance LANs so that FDDI acceptance is nearly universal.

The finalization of all aspects of the FDDI standard is not yet complete. However, the standard has been complete enough for the last year that many vendors have begun producing FDDI-compliant equipment, and this equipment has been proven to be interoperable via demonstrations at testing facilities and industry trade shows.

FDDI provides an order of magnitude increase in the rate data is transferred across the LAN as compared to the existing Savannah River Site LAN, and thus represents a major improvement to support increasing numbers of LAN users and ever greater demands to move large volumes of data across the site LAN. Two major developments are driving the need for this improvement. These are the movement of personal computers to direct LAN attachments and the increasing use of images in site applications and in documents transferred across the site.

Many personal computers (PCs) are now being attached directly to the site LAN instead of being attached indirectly to the site LAN via a device called a terminal server. PCs attached to terminal servers use the LAN to communicate to site host computers (IBM, DEC, or Cray) and require approximately ten thousand bits per second of peak network bandwidth.

PCs attached directly to the LAN and utilizing LAN-based file and printer sharing services can utilize approximately one million bits per second of peak network bandwidth and use this capability to move large files across the network. Thus, LAN-attached PCs can require 100 times as much network performance as terminal server-attached PCs.

One of the major developments in the last two years in the use of office computers has been the acceptance of applications that use scanned images stored in electronic format. This trend allows the extension of computer documents beyond word processing to documents that include diagrams, pictures, and photos as well as text. Electronic storage of a page containing a scanned image requires approximately one half to one million bits of information while storage of a page of text requires only about 25-50 thousand bits. Thus computer applications which depend on the network to transfer documents containing images stress the capacity of the network much more than existing text-based applications.

PC LAN and document image applications together or separately threaten potential overloads of the site network. FDDI represents the technology that the site will use to selectively upgrade parts of the network in order for the network to remain viable over the next few years.

This technology report describes FDDI as a technology, looks at the applications of this technology, examines the current economics of using it, and describe activities and plans by the Information Resource Management (IRM) Department to implement this technology at the Savannah River Site.

2 FDDI Technology

The ISO Reference Model

The International Standards Organization (ISO), the world-wide body responsible for defining and promoting computer network standards, has developed a Reference Model (ISORM) as a method for defining the Open Systems Interconnection (OSI) networking protocols. The goal of the ISO is to establish and promote this set of network protocols, or rules for communicating, which will be non-proprietary and implemented by all vendors of computer equipment. The OSI protocols themselves are grouped into seven distinct layers. Protocol "layering" is just a way of formalizing the concept that successful communications requires a lot of rules and that these rules can be grouped by function. For example, the rules about the shape and size of the connectors and the way "bits" will be represented on some physical media (such as electrical voltages on a copper wire or light pulses for FDDI) are part of the "physical layer". All other rules (how data messages are constructed, how transmission errors are detected, the text encoding scheme, etc.) rest on top of the first layer. In fact, if the interfaces between layers are well defined, changes can be made within the layers. That is, the rules about one specific function of communications can be changed without redoing the entire communications system. For example, the same set of "higher level" protocols can be used in local area networks as in wide area networks even though the physical layers for the two are quite different.

Figure 1 on the next page shows the seven layers of communications as defined by the ISORM. The "physical" layer defines the signaling of bits on the physical medium and defines such things as media characteristics, shape and size of the connectors, etc. The "link" layer deals with the access of a device to the network media and the basic construction of data packets, a collection of bits which includes the user's data as well as addressing and control information. The "network" layer deals with the routing of packets to final destinations. The "transport" layer defines the methods to ensure error-free end-to-end delivery of messages. Note that the transport layer

uses the services provided by the network layer to route the messages, and the network layer uses the link layer to move the messages from node (network processor) to node via the physical medium.

Figure 1: ISO Reference Model

The "session" layer provides the user interface to the network. It defines the method of establishing and using communications links between two end systems. The "presentation" layer defines data representations, that is, how bits within the data being transported are to be interpreted. The "application" layer defines the services to which the end user of the network has access. For example, the protocol for exchanging complete computer files between systems is at the application layer. Obviously, the file transfer itself will depend on the lower layers as well.

FDDI is one of several (Ethernet, Token Ring, and X.25 are alternatives) standards that define the lower two layers of the ISORM, the physical and link layers. That is, FDDI defines the fiber optic physical interfaces between communicating systems, how the bits are signalled on the fiber optic cables; how bits are collected together into data messages, called frames or data packets; and how several devices share the physical communications facilities. Higher level protocols rest on top of FDDI. FDDI can support several alternative stacks of higher level protocols such as OSI, TCP/IP, and DECnet.

Fiber Optic Technology

Fiber optic cables are thin glass fibers (the core) surrounded by another concentric layer of glass called the cladding. If a laser or light emitting diode (LED) is used to shine light down the core of a fiber optic cable, the cladding (through its reflective properties) traps the light so that the signal remains coherent for relatively long distances. Data communications is achieved by converting data bits to pulses of light from a source projector and using light sensitive electronics at the far end of the cable to detect the light pulses and recover the original data bits. Figure 2 illustrates this concept.

Figure 2: Signalling with fiber optics

The remarkable features of fiber optic communications technology is the speed with which light pulses can be transmitted and received (billions of bits per second) and the distances the light signals can be transmitted without an intermediate repeating function (miles). Generally, LED transmitters are less expensive than lasers, but lasers are required for longer distance applications. FDDI products are normally constructed with LED transmitters.

It is important to remember that communications based on a single fiber optic cable is simplex. That is, there is a transmitter on one end of the cable, a receiver on the other end, and signals go in only one direction. Thus useful data communications (i.e., full duplex) with fiber optics requires that the cables be used in pairs as shown in Figure 3 on the next page.

Figure 3: Full duplex signalling with fiber optics

Fiber optic cables are distinguished by the diameters of their glass cores. Relatively large diameter cables are used with LED transmitters and are called multimode fibers. Smaller diameter cores are used with more powerful laser transmitters and are called single-mode fibers. Single-mode fibers are used for longer distance applications. The FDDI standard specifies the use of multimode fiber, primarily fiber with a core diameter of 62.5 microns. However, various manufactures of FDDI equipment are adding a single-mode fiber option to allow the extensions of FDDI networks to greater than standard distances, and operation of single-mode FDDI will be incorporated into the standard.

Besides specifying the type, size, and light passing characteristics of the fiber optic cable it uses, the FDDI physical layer standard also defines the size and shape of the connectors used at the ends of the cables. FDDI cables come in send/receive pairs. Figure 4 shows FDDI connectors joined to a pair of cables. Standardization of connector configurations ensures that the equipment can all plug together.

Figure 4: FDDI duplex cable and connectors

FDDI Over Copper Wires

A recent development in the FDDI arena is the development of the ability to build FDDI networks using copper wires in twisted pairs as the network medium rather than fiber optic cables. This implementation requires the ability to transmit (and receive) data at 100 million bits per second over copper wiring. Such a development a few years ago would have been unthinkable, but the success of Ethernet over unshielded twisted pairs (UTP) cable and advances in signalling technology make it likely that FDDI without fiber optics will be possible. (Some call this CDDI for Copper Distributed Data Interface.) Vendors are hoping to be able to demonstrate reliable CDDI links at distances of up to 100 meters.

Economics is driving this effort. Both the electronics for driving and receiving optical signals and the fiber itself are relatively expensive. Most of corporate America is wired with either shielded or unshielded copper wires for data communications. The pace of deployment of FDDI networks will be greatly accelerated if expensive new fiber optic cables are not required and if the LAN controllers that computers require for an FDDI connection are inexpensive. Today, the major expense of an FDDI controller is in the optics.

Various vendors and vendor consortia are looking to establish standards for FDDI over either shielded or unshielded copper cables. If the technology is proven to work, ANSI will eventually adopt one of the schemes as the standard way of doing FDDI over copper. Today, it would be premature to buy FDDI products that use other than standard fiber optics.

FDDI Ring Topology

FDDI LANs utilize an access method called token passing technology. Stations on the net are connected to each other in a ring configuration. Each station is connected to its upstream neighbor with a pair of fiber optic cables. Figure 5 (see the next page) shows a simple FDDI network.

Normally, only the receive cable from the upstream neighbor and the send cable to the downstream neighbor are used for passing data. This set of cables forms what is called the primary ring. The other two cables attached to each workstation, called the secondary cables, are used for recovery of the network after a primary cable failure.

Primary ring is composed of the outer cables.
Secondary ring is used for fault recovery only.

Figure 5: Simple FDDI ring

In an FDDI ring, data frames (messages) are sent counterclockwise from station to station using the primary fiber cables. Each station acts as a repeater for bits received from the upstream neighbor, retransmitting incoming messages to the downstream neighbor. During periods of nonactivity, a special short message, called the token, circulates around the ring. Stations gain permission to write a data frame by receiving the token, replacing the token with a data frame, and putting a new token at the end of the data frame. Subsequent stations on the ring can see the frame with the trailing token, "absorb" the token, and put another data frame on the network immediately behind the first one and append a token to the last data frame. Each data frame contains the physical network address (a unique number for each station) of both the sending station and the station which is to receive the data. Stations monitor data frames as they flow through and read (copy to memory) any data frames addressed to them. Each sending station must remove any data frame that the station originated when the frame makes a complete trip around the ring. Receiving stations mark frames as copied so that the senders know that their frames were successfully received.

Figures 6a and 6b on the next two pages show a simple example of FDDI's Token Passing protocol.

Figure 6a: FDDI token passing protocol

As Frame 1 proceeds around the ring, Station 2 takes the Token off the ring and puts a message to Station 4 on the ring as Frame 2.

Station 2 transmits the Token. Station 3 passes them along. Station 4 copies Frame 2 and sends it and Token along. Station 1 removes Frame 1 from the ring.

Station 1 lets Frame 2 and the Token pass.

Station 2 removes Frame 2 from the ring and lets the Token pass. Station 3 is free to absorb the Token and put a frame on the ring.

Figure 6b: FDDI token passing protocol- (continued)

It is important to note that the FDDI protocol is built into the FDDI hardware (computer chip sets), and the overhead of FDDI packet passing is not tasked to the workstation's or computer's CPU. Generally, a computer's CPU is required to process the higher level communications protocols above FDDI.

The following are the key parameters that define an FDDI ring:

- Basic data rate — 100 million bits per second (mbps)
- Cable — fiber optic, multimode, 62.5 microns
- Maximum distance between stations — 2 kilometers
- Maximum ring circumference — 100 kilometers (redundant ring allows total of 200 kilometers for fiber path)
- Maximum data packet — 4500 bytes

These operating parameters compare very favorably with those of the Ethernet technology currently in use at the site:

- Basic data rate — 1.0 mbps
- Cable — coax or unshielded twisted pairs
- Maximum distance between stations — 500 meters (single coax)
- Maximum network distance — 2800 meters (coax extended by fiber)
- Maximum data packet — 1500 bytes

Components of the Standard

The ANSI standard for FDDI divides the functionality of FDDI into five component functions, each defined as an ANSI or IEEE standard. These five components of FDDI and the relationship of FDDI to the ISORM are shown in Figure 7.

Figure 7: FDDI architecture

Logical Link Control

Logical Link Control (LLC) is defined by the IEEE 802.2 standard as the packet format. FDDI shares 802.2 LLC in common with IEEE 802.3 (Ethernet) networks and IEEE 802.5 (Token Ring) networks, facilitating the joining of these different networks together. Appendix A describes LLC formats.

Media Access Control

The Media Access Control (MAC) protocol defines the FDDI frame structure and the interactions that take place between the stations on the FDDI ring. In addition to token management, MAC handles system timer support as well as response to normal and system error conditions on the ring. That is, the MAC protocol defines the ring operation illustrated in Figure 6 and thus is the heart of the FDDI specification. Appendix A describes the relationship of FDDI frames and LLC data.

Physical Protocol

The Physical protocol (PHY) is the medium-independent portion of the physical layer. It is equivalent to the upper half of the ISORM physical layer and defines the interface between the MAC protocol and the physical medium-dependent protocol. PHY specifies the encoding of digital data for transmission, clocking, and a set of line states that perform a handshake between adjacent stations.

Appendix B describes the bit encoding system used by FDDI.

Physical Medium Dependent Protocol

The Physical Medium Dependent (PMD) sublayer protocol defines the fiber optic drivers and the attachment of stations to the fiber media via the standardization of cables and connectors. The PMD protocol, for example, specifies that the optical transmitters operate at 1300 nanometers (nm) wavelength.

Station Management Protocol

The Station Management (SMT) protocol provides the control necessary at the station level to manage the various components of an FDDI station (the other FDDI protocols) so that a station may work cooperatively on a ring. SMT addresses ring configuration and monitoring, connection management, and fault isolation / recovery. The SMT is still a draft ANSI standard, but vendors are already using the draft standard to produce FDDI equipment. Vendors are promising to retrofit their FDDI equipment if the SMT changes before its final acceptance as an ANSI standard.

FDDI Components

What makes up an FDDI? An FDDI network consists of the fiber optic cable pairs and the stations that the fiber pairs join together. Stations are classified into three types: Class A, Class B, and Concentrators.

Class A Stations

Class A stations, also called Dual Attachment Stations (DAS), are devices that connect to both the primary fiber ring and the secondary fiber ring. That is, a DAS has four fiber optic connections: Primary In, Primary Out, Secondary In, and Secondary Out. Because of the dual fiber nature of the FDDI connectors these four connections are grouped into two ports. Primary In and Secondary Out make up the A port of a DAS. The DAS B port consists of Primary Out and Secondary In. An FDDI cable joins a station's A port with the B port of its upstream neighbor, as shown in Figure 8 below.

Figure 8: Class A stations connected by fiber pair

Class B Stations

A station that has only a single pair of fiber optic connections (that is, a single fiber optic connection for incoming data and a single connection for outgoing data) is called a Class B station, or a Single Attach Station (SAS). Stations of this type may not connect directly to the fiber ring, but must be attached via another type of device called a concentrator. Because they contain only one set of fiber optics drivers/receivers, SAS are more economical than DAS. A SAS has a single port, called the S (for slave) port.

Concentrators

Every station directly attached to the FDDI ring must be a DAS. A special type of DAS, called a concentrator, is used to connect other devices (either DAS or SAS, though SAS is more common) to the ring. A concentrator will have A and B ports for connection to the ring and multiple M (for master) ports for attachment of SAS. A FDDI network can consist of a single concentrator with SAS attached, as shown in Figure 9.

Figure 9: FDDI Concentrator as FDDI Network

Cables

The PHY component of the FDDI standard specifies 62.5 micron multimode fiber optic cable pairs terminated by the duplex connectors shown in Figure 3. Other grades of multimode fiber may be used, usually with some minor performance penalty expressed as reduced distances

allowed between stations. As discussed earlier, some manufactures include a single-mode fiber capability at increased cost that permits extended distances between stations (up to 25 miles).

Fault Tolerance

One of the major advantages of the FDDI LAN technology is the ability of an FDDI network to remain operational in the event of a single cable disruption. This is accomplished by utilization of the secondary fiber optic ring to which all Class A stations must connect which is called a network "wrap" (as in wrap around). Figure 10 on the next page illustrates this.

In the event of more than one cable break, an FDDI LAN will segment into multiple rings. Each of the new rings will be operational, but devices connected to different rings will not be able to communicate with each other.

Another reliability feature of FDDI equipment is the use of optical bypass switches that enable inactive nodes (i.e., powered off) to pass data directly from one neighbor to another without active power.

Finally, the use of SAS and concentrators enhances the overall reliability of the ring. Remember that each DAS is an active repeater on the ring. Should such a station fail to repeat data frames, then the ring has been effectively broken. If only one such event occurs, then a network wrap using the secondary ring prevents the disruption of the ring operation. However, if two or more stations experience this type of failure, the ring is segmented. Obviously, the more stations directly on the ring (that is, the more DAS) the more opportunities for station failure. Concentrators attaching SAS or DAS stations to the ring reduce the overall ring vulnerability to station induced inoperability. Any SAS failure disrupts communications only to that station. The concentrator will restore the integrity of the ring by bypassing the failed station.

As a practical matter, it is IRM policy that the major FDDI rings will consist only of concentrators and key DAS such as routers and bridges (Described below). Specifically, individual computer or workstations which wish to attach to the FDDI ring must do so via a concentrator.

Figure 10: FDDI fault tolerance via a secondary ring

FDDI Equipment

FDDI equipment (things one can buy) consists of communications controllers for workstations and host computers, concentrators, and FDDI bridges and/or routers for joining multiple FDDI rings together or for connecting Ethernet or Token Ring LANs to an FDDI ring. Each of these is discussed below.

FDDI Controllers

Makers of high performance workstations are now adding optional FDDI controller cards to attach these workstation to an FDDI LAN. These include IBM for the RS 6000, SUN for the Sparcstation, DEC for the DECStation (not the VAXstation), and Hewlett Packard for the HP 9000 / Series 700 workstations. Typically, these cost several thousand dollars. By contrast, Ethernet and Token Ring LAN controllers for workstations are built in at no cost or offered as an option at a cost of a few hundred dollars. No doubt, the cost of FDDI controllers will come down over time, and FDDI over copper wire could get the cost down as low as \$1000 per workstation within two years.

Some manufacturers of FDDI controllers make Class A (DAS) devices, and some make Class B (SAS) devices. Typically, SAS cards are less expensive than DAS cards, but the use of an FDDI concentrator is required.

DEC makes FDDI controllers for the larger (6000 and 9000) VAX systems. IBM makes an external communications controller, the IBM 3172 Model 2, for attaching an IBM mainframe (via a channel) to an FDDI LAN. Cray supercomputers can be attached to the FDDI by means of an external LAN controller from Network Systems Corporation.

As yet, no significant computer equipment manufacturer makes FDDI controllers for the Macintosh or IBM PS/2 personal computers. This situation will change soon.

Concentrators

As explained above, FDDI concentrators are DAS for the purpose of attaching SAS stations to an FDDI. Concentrators may be used as stand-alone FDDI LAN's, or they may attach to an FDDI fiber ring. Concentrators may also attach to other concentrators (but only two

deep), and this allows a more complex physical topology. As concentrators act only at layers 1 and 2 of the ISORM, there are no higher level protocol issues associated with concentrators, with the exception of the protocol used for station management at the lower two layers.

Several manufacturers make FDDI concentrators. Cost for one is currently around \$10,000 to provide support for 8 SAS connections.

Figure 11 shows an FDDI LAN with wiring concentrators attached to the ring and cascaded two deep.

Figure 11: FDDI concentrators in a network

Bridges and Routers

Network bridges and routers are devices used to connect one LAN to another. Some bridges (routers) can connect a LAN of one type to a technologically different LAN. Vendors are now making bridges (routers) to join Ethernet or Token Ring LANs to an FDDI LAN and others that join two FDDI LANs together.

The difference between a bridge and a router is based on what level of the ISORM they work in. Bridges operate at layer 2, the link layer. As such, bridges are concerned only about moving data packets between adjacent LANs. Bridges do not concern themselves with the upper layer

protocols reflected in the contents of the data. Routers, on the other hand, operate at layer 3, the network layer. Layer 3 is used for routing data packets across a collection of networks and is very protocol dependent. That is, a network router may function only for certain protocols. For example, an AppleTalk router routes only AppleTalk packets; a DECnet router generally routes only DECnet packets.

There are places for both bridges and routers in a large network such as that at SRS. In general, bridges join up local LANs in a single area, and routers are used to join the area LANs together. Some manufacturers (e.g., Cisco Systems, Inc.) make devices that can function as a router for some protocols and as a bridge for others.

Figure 12 shows a collection of LANs using bridges and routers to join FDDI, Ethernet, and Token Ring LANs together. Bridges and routers can be either DAS or SAS. In addition, some are built with single-mode fiber support for longer distances between FDDI stations. Costs of these devices vary greatly, as do their capabilities. The most inexpensive FDDI/Ethernet bridge can be found for about \$10,000. Full feature FDDI-FDDI router/bridges can cost up to \$50,000. Some FDDI-Ethernet bridges and routers can support multiple Ethernet LAN connections to a single FDDI.

Figure 12: FDDI joined to other LANs

Encapsulation vs Translation Bridging

There is one important distinction to be made in evaluation of products by the makers of FDDI-Ethernet bridges. This is because there are two different methods of bridging Ethernet packets to and from an FDDI LAN. These methods are called encapsulation and translation.

The most common method today is encapsulation, and it works like this. Encapsulation bridges are intended to work in pairs. As shown in Figure 13, when an Ethernet packet is received by the FDDI bridge to be forwarded, the FDDI bridge encapsulates the entire Ethernet packet in the data portion of the FDDI frame. Another bridge removes the encapsulation bytes and inserts the original Ethernet packet on the receiving Ethernet. There is no standard way to do this encapsulation, and each vendor does it differently. Thus, if one builds a network of encapsulating bridges, one must be sure to stay with the same vendor. Also, Ethernet devices attached to an FDDI network via an encapsulation bridge can not communicate with devices directly attached to the FDDI ring.

Figure 13: Encapsulating Ethernet/FDDI bridges

In contrast to encapsulation bridges, translation bridges break apart the incoming Ethernet packets into their constituent address, protocol, and user data components, and build a complete FDDI packet with this information. In other words, an Ethernet packet is translated into an FDDI packet. This requires higher performance capabilities from the bridge but has the advantage that Ethernet devices can communicate directly with FDDI devices and that translation bridges from a variety of vendors could be combined in a network without loss of interoperability.

Translation bridges are preferred to encapsulation bridges. Vendors are now reworking their bridge products to provide translation bridging. For example, DEC's bridge products are high performance translation bridges that support up to three Ethernet attachments to an FDDI, can be either a DAS or a SAS, and have a single-mode fiber option. Cisco Systems now makes encapsulating bridges, but that company is converting their bridge hardware and software to support translation bridging. The Cisco device, called a gateway, can function as both a bridge and a router. A single gateway can support two FDDI interfaces for FDDI-FDDI bridging and routing. It can also support up to 12 Ethernets (for maximum performance a limit of 4 Ethernets per FDDI gateway is recommended) attached to a single FDDI and act as either a DAS or a SAS.

3 FDDI Applications

Given the success of Ethernet and Token Ring local area networks, why would one need to pay the added expense of implementing an FDDI network? The answer, of course, is speed, and to a lesser extent, distance. FDDI networks are an order of magnitude faster (100 mbps) than Ethernet (10 mbps) or Token Ring (4 or 16 mbps). FDDI networks, especially with a single-mode fiber option, can cover greater geographical areas than the other LAN technologies.

Given that the typical personal computer (PC) can utilize only about 1 mbps in LAN applications today, why do we need this speed? The answer is twofold. First, there are now high performance workstations with the capability to completely utilize the bandwidth of an Ethernet LAN in a single file transfer. Obviously, it would not take many of these workstations to severely congest an Ethernet LAN to the point that its performance would degrade substantially. Secondly, although individual PCs do not stress an Ethernet (or Token Ring) LAN, many of them together can (and do). These reasons suggest the two main uses of FDDI today: the construction of a high performance workstation LAN for rapid file transfers of large amounts of data and the implementation of a LAN trunk to support the interconnection of slower speed Ethernet and Token Ring LANs.

LAN Interconnections

FDDI LANs relate to Ethernet and Token Ring LANs like the U. S. Interstate Highway System relates to the network of two lane highways. The two lanes are adequate for low volume traffic, but if a road is needed between major population centers, then a four lane Interstate Highway is called for. People still use the two lane roads as feeders into the Interstate Highways

Figure 14 illustrates this point for LANs. Suppose Ethernets 1 through 6 experience maximum loads of only 40% of the total bandwidth available to Ethernet. (That is, traffic peaks at 4 mbps on each of these networks). Bridges isolate the networks so that only traffic intended to cross network boundaries actually does so. Can the Main Ethernet which ties these

networks together have performance problems under these conditions? The answer is that it can. Suppose the traffic patterns are such that Ethernet 1 devices talk to Ethernet 4 devices, Ethernet 2 devices talk to Ethernet 5 devices, and Ethernet 3 devices talk to Ethernet 6 devices. Then, as the traffic peaks in each network, the trunk that ties it all together would overload (6 times 20% equals 120%), even though load in each individual Ethernet does not exceed 40% (20% of local traffic plus 20% from traffic from its companion network.)

Total traffic on the Main Ethernet is the sum of all traffic between Ethernets 1,2,3,4,5 and 6.

Figure 14a: Ethernet as a network trunk

Total traffic on the FDDI is the sum of all traffic between Ethernets 1,2,3,4,5 and 6.

Figure 14b: FDDI as a network trunk

FDDI resolves this problem by putting the fastest network where it is needed, at the focal point of the network, as shown in Figure 14b.

Note that with this type of network the only FDDI devices are the bridges (or routers) which tie the individual Ethernet LANs to the FDDI trunk. This preserves the original investment in the Ethernet LANs and Ethernet adapters for the workstations but still restricts any one "conversation" to a theoretical maximum of 10 mbps. Also take note of the fact that the network bridges and routers can be bottlenecks, if their performance characteristics are not adequate to scan the FDDI at 100 mbps, the Ethernet at 10 mbps and still be able to transfer data from one network to the other at the full 10 mbps. Some bridges and routers can handle worst case traffic patterns, and others can not.

LANs for High Performance Systems

The tremendous advances in computer technology over the last decade have led to the development of "desk top" (or at least "desk side") computers with processing speeds approaching 100 million instructions per second. Disk access and data transfer speeds are also improving, though not as fast as processor speeds. Disk storage capacities found on these systems are beginning to exceed gigabytes, and the appetite for storage by users of these systems is voracious. What this means to the network is that some machines have the potential to demand huge file transfers from the network and the ability to drive these transfers at rates faster than our existing networks can sustain.

FDDI today represents the only standards-based way of providing a faster LAN for high performance workstations. (There are solutions in the gigabit per second range, but these products are proprietary to single vendors and prohibitively expensive.)

How fast can today's high performance workstations transfer data on an FDDI LAN? (Or the related question: How many workstations can such a LAN support before running out of bandwidth?) Today, the limiting factor on disk to disk file transfers across a LAN is the speed of the disks. If a workstation can transfer data at 5 mbps (still very fast for disk to disk transfers) on an Ethernet, it will do no better on an FDDI. However, an FDDI LAN could support upwards of 20 such transfers, while an Ethernet LAN would have trouble with two. Given the fact that workstations are not constantly transferring files on the LAN, then an FDDI LAN should be able to support a few hundred of today's fast workstations before network overload becomes a problem.

Some vendors have used high performance (i.e. expensive) FDDI adapters and stripped down protocols to demonstrate file transfers over an FDDI in excess of 50 mbps. Simulation studies show that 83 mbps is possible with protocol improvements. Of course, such speed would put us right back where we are today, with one file transfer able to take the entire bandwidth of the FDDI LAN.

4 FDDI at Savannah River

FDDI is currently being implemented at the Savannah River Site. The primary organization responsible for FDDI LAN implementation is the Computer and Telecommunications Management (CTM) Section of the Information Resource Management (IRM) Department. CTM's current FDDI work and plans are described below.

Central Computer Facility LAN

With the installation of the Cray supercomputer in 1989, CTM established a high performance computer room LAN for the Central Computer Facility (CCF) located in 703-44A, 703-A, and 773-A. This LAN was based on proprietary technology, called HYPERchannel, from Network Systems Corporation (NSC). The HYPERchannel originally operated at 50 mbps using coaxial cable and connected the Cray to the IBM 3090, the IBM 4381, and a VAX 8550. It was used for large file transfers, primarily between the Cray and the VAX and the Cray and the Common File System (CFS) managed by the IBM 4381. TCP/IP protocols were supported on the HYPERchannel as well as proprietary CFS protocols, and a router from NSC was used to connect the HYPERchannel to the site Ethernet LAN.

During the fourth quarter of 1991, the HYPERchannel was converted from its proprietary protocols to FDDI at the physical and link layers. NSC HYPERchannel communications controllers were modified to provide FDDI interfaces. Figure 15 on the next page shows the CCF FDDI as it existed late in 1991. The major advantage of this conversion is that a proprietary LAN has been replaced by a LAN based on standards, and equipment from vendors other than NSC can now be used to extend the capabilities of the CCF LAN.

Figure 15: Central Computer Facility FDDI

SRL Workstation LAN

The Savannah River Laboratory (SRL) is beginning to acquire high performance workstations which will have the capability to attach directly to an FDDI LAN. Also, SRL researchers generate large amounts of data and need to use a high performance network to transfer this data between the workstations and other SRS computers, mainly the Cray, the SRL VAX cluster, and the IBM 3090. SRL has funded a project to install a FDDI LAN during 1992. IRM is providing network design and installation support for this project.

This LAN will consist of an FDDI backbone running throughout key locations in the SRL Technical Area (773-A and surrounding buildings) and will have a high performance FDDI router link to the CCF FDDI LAN. The SRL FDDI will consist of FDDI concentrators for attaching FDDI-capable workstations as well as FDDI/Ethernet bridges so that non-FDDI workstations are connected.

Intra-area LANs

There is a proposed project (at the time of this writing it is uncertain whether the project will be funded) for Fiscal Year 1992 to install FDDI trunk LANs in the 300/700 area as well as other areas on the site where existing LANs are experiencing heavy network traffic loads. These FDDI rings will be central to the areas in which they are installed and provide the basic area LAN trunks. The rings will consist of FDDI concentrators, Ethernet bridges, and routers to Ethernet and Token Ring LANs. In the 300/700 area the FDDI trunk will attach to both the CCF ring and the SRL ring. Existing routers will link the area rings together with high speed digital telephone circuits. Figure 16 shows a simplified schematic of the proposed 300/700 area FDDI trunk and its connections to the existing site LAN, the LAN connections to remote areas, the CCF FDDI ring, and the SRL FDDI ring.

Figure 16: Proposed site FDDI Installation (1992)

Inter-area LAN Connections

With the completion of FDDI trunks in most site areas by 1995, the site LANs will provide for high bandwidth requirements to transfer data around the area. However, a LAN bottleneck will remain, namely the transfer of data between areas. Currently, inter-area LAN connections are based on digital telephone T1 circuits that provide approximately 1.5 million bits per second data rate. This is adequate today to support linking the site area Ethernet LANs and support mostly host-based applications which generate modest amounts of network traffic. However, future requirements to link PC LANs across the site and to move graphic images across the site will make the T1 data rate grossly inadequate.

Improving the site inter-area data communications capability beyond T1 will require the site to install inter-area fiber optic cables (single-mode variety). With this fiber available, several high performance inter-area network enhancement options will be feasible. These include utilizing T3 digital telephone data circuits at 45 mbps, running one or more single-mode FDDI rings linking the areas, or adding high speed point-to-point links between areas utilizing the new Synchronous Optical Network (SONET) standard for high speed data communications over fiber optics. SONET has been defined for speeds ranging from T3 rates to over four gigabits per second

The site has plans to install the prerequisite inter-area fiber optics cables as part of a planned upgrade to the site telephone system. Under this project, fiber optic cables between areas will be installed by 1994.

5 Summary

The existing site LAN based on Ethernet technology is inadequate to provide high data transfer speeds in support of the increasing needs to transfer large amounts of data across the site. Applications based on image technology in particular can stress existing site LANs because of the large amounts of data required to encode computer-based images. Increasing use of personal computer LANs also stress network capabilities. FDDI, using fiber optics technology, provides the only standards-based solution and offers an improvement in throughput of 10 times that of an Ethernet LAN. The site has begun to install FDDI networks at key locations, and there are plans to install FDDI trunks in most site areas. FDDI complements existing LANs rather than replacing them everywhere. Initial FDDI implementations will provide high performance workstation support and provide central LAN trunks to link existing Ethernet and Token Ring LANs.

Appendix A

FDDI Frame Format

FDDI frames are made up of Media Access Control (MAC) and Logical Link Control (LLC) fields. The MAC fields provide a FDDI-specific wrapper around the LLC data as shown in Figure A1 below.

Figure A1: FDDI frame with MAC and LLC components

Logical Link Control is defined by the IEEE 802.2 standard as the packet format. FDDI shares 802.2 LLC in common with IEEE 802.3 networks (Ethernet) and IEEE 802.5 networks (Token Ring), facilitating the joining of these different networks together. The LLC portion of an FDDI frame consists of the following fields:

Source and Destination Service Access Points (SSAP and DSAP) — numbers which define entities within a single station. SAPs can be thought of as individual addresses within a station using network services. A single station may support numerous conversations across a network.

SAPs are used to differentiate between the end points of these conversations.

Control field — specific bits that specify LLC control functions

Information field — the data being transferred across the network. For FDDI this can be nearly 4500 bytes (4500 maximum frame size minus media access header and trailer, SSAP, DSAP, control field, and frame check sequence).

Appendix B

FDDI Bit Encoding

The encoding system used by FDDI is designed to provide for bit synchronization as well as data transmission. The 16 possible 4 bit symbols (hexadecimal numbers) are encoded with a set of 5 bit values, using what is called a 4B/5B code. Each 5 bit value is then represented using a scheme called Nonreturn to Zero Inverted (NRZI) encoding. With NRZI, a 1 bit is represented by a transition in the signal and a 0 bit by no transition. The 5 bit values used to represent symbols are chosen so that there will never be more than three 0 bits in a row and thus no more than three bit times without a transition. The frequent transitions insure that bit synchronization is maintained. Bits are actually signalled at 125 mbps, but because of the 4B/5B scheme, the data rate is 100 mbps.

Table B1 on the next page is the 4B/5B encoding.

Table B1
FDDI 4B/5B Encoding

Symbol	Binary	FDDI 5 Bit Code
0	0000	11110
1	0001	01001
2	0010	10100
3	0011	10101
4	0100	01010
5	0101	01011
6	0110	01110
7	0111	01111
8	1000	10010
9	1001	10011
A	1010	10110
B	1011	10111
C	1100	11010
D	1101	11011
E	1110	11100
F	1111	11101

END

**DATE
FILMED**

10 / 6 / 92