TEST OF FRONT-END CIRCUIT FOR SUPPRESSING COMMON-MODE COMPONENT OF MAIN RING DAMPER

Hengjie Ma
August 3, 1995

OBJECTIVE

To improve the efficiency of a transversal damper, the common-mode components in the beam signal due to any off-center closed orbit must be suppressed as much as possible. In the present Super Damper the common-mode suppression is accomplished by using a feedback to adjust the dc offset of the front-end integrator. For the proposed main ring damping system, a new front-end circuit using balanced cross-feed forward and feedback has been developed to improve the common-mode rejection and adaptability to changes in the closed-orbit of the front-end. The circuit had been proved on a bench test. The test done on July 30 was to evaluate its effectiveness on the real beam signals.

2. CIRCUIT DESCRIPTION

For each plane the damper pickup has two electrodes, designated as A and B respectively. If the beam is off center at the pickup location the static amplitude of A signal will be different from that of B signal. Consequently, a certain amount of static common-mode component will be generated in the difference signal, which will be fed back to the kicker. To eliminate the common-mode component a new equalizing circuit called cross-feed forward (CFF in short) is tested. The basic principle of the circuit is to multiply A signal with the static amplitude of B signal, and multiply B signal with the static amplitude of A signal. As the result, the amplitude of both signals after the processing will become equal, which is $A \times B$. If the bandwidth of the static amplitude detection is properly chosen such that the changes in the detected amplitudes are not fast enough to follow the betatron motion, the desired harmonics due to the betatron oscillation will still be able to survive, while the static

common-mode component will be suppressed in the difference signal after the equalization.

3. TEST METHOD AND RESULT

The beam signals were obtained from the monitoring ports of Super Damper. The beam detector is located at E49. The amplitude of the signal is usually about 1V @ intensity of $2.5E11$ protons/bunch. The signals of A and B channel were adjusted to become in-phase with trombones before being sent to the CFF circuit. The amplitudes of the two signals were detected with two ultra-fast sample/hold IC chips, which were triggered by the AA marker of main ring beam SYNC. Therefore, the amplitude detection was locked on a certain bunch all the time. During the test, main ring was running /29/ cycle with an intensity of around $2.7E12$ and one booster batch in the ring. The circuit was first adjusted so that the common-mode component in the difference signal reached the minimum. The outputs of difference (A-B) and the sum (A+B) were then recorded. Next, different attenuations were added to A and B input signals so that a static amplitude difference of 6 dB between the two signals were created. The 6 dB amplitude mismatch is equivalent to the effect of about a 10 mm change in the closed-orbit. The outputs of difference (A-B) and the sum (A+B) were then recorded again. If we define the common-mode suppression as the ratio of the increase of the common-mode in the equalizer (A-B) output to the increase of the common-mode in the (A-B) input (normalized by (A+B)), the suppression observed is greater than 40 dB. This preliminary test has shown the effectiveness of CFF circuit in suppressing the common-mode component.