LA-UR- 98-2751

Approved for public release;
distribution is unlimited.

Title: MODULATOR CONSIDERATIONS FOR THE SNS
RF SYSTEM

CONF-980665--

Author(s): P. J. Tallerico
W. A. Reass

Submitted to: 1998 23rd International Power
Modulator
Rancho Mirage, CA
June 22-25, 1998

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

MASTER

Los Alamos

NATIONAL LABORATORY

Los Alamos National Laboratory, an affirmative action/equal opportunity employer, is operated by the University of California for the U.S. Department of Energy under contract W-7405-ENG-36. By acceptance of this article, the publisher recognizes that the U.S. Government retains a nonexclusive, royalty-free license to publish or reproduce the published form of this contribution, or to allow others to do so, for U.S. Government purposes. Los Alamos National Laboratory requests that the publisher identify this article as work performed under the auspices of the U.S. Department of Energy. The Los Alamos National Laboratory strongly supports academic freedom and a researcher's right to publish; as an institution, however, the Laboratory does not endorse the viewpoint of a publication or guarantee its technical correctness.

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

Modulator Considerations for the SNS RF System¹

Paul J. Tallerico, William A. Reass
Los Alamos National Laboratory
Los Alamos, NM 87545

Abstract

The Spallation Neutron Source (SNS) is an intense neutron source for neutron scattering experiments. The project is in the research stage, with construction funding beginning next year. The SNS is comprised of an ion source, a 1000 MeV, H⁻ linear accelerator, an accumulator ring, a neutron producing target, and experimental area to utilize the scattering of the neutrons. The linear accelerator is RF driven, and the peak beam current is 27 mA and the beam duty factor is 5.84%. The peak RF power required is 104 MW, and the H⁻ beam pulse length is 0.97 ms at a 60 Hz repetition rate. The RF pulses must be about 0.1 ms longer than the beam pulses, due to the Q of the accelerating cavities, and the time required to establish control of the cavity fields. The modulators for the klystrons in this accelerator are discussed in this paper. The SNS is designed to be expandable, so the beam power can be doubled or even quadrupled in the future. One of the double-power options is to double the beam pulse length and duty factor. We are specifying the klystrons to operate in this twice-duty-factor mode, and the modulator also should be expandable to 2 ms pulses at 60 Hz. Due to the long pulse length and low RF frequency of 805 MHz, the klystron power is specified at 2.5 MW peak, and the RF system will have 56 klystrons at 805 MHz, and three 1.25 MW peak power klystrons at 402.5 MHz for the low energy portion of the accelerator. The low frequency modulators are conventional floating-deck modulation anode control systems.

I. Introduction

The pulsed power system is an important factor in the cost and reliability of the SNS project. The relatively long pulse length and high duty factor make conventional PFN modulators difficult. We

discuss and compare four types of modulators that could be applied to this application. The baseline design modulator is a floating-deck design that utilizes a single switch tube to drive the modulation anodes of two klystrons in the same oil tank. This type of system has worked very reliably in the Ballistic Missile Early Warning Radar System (BMEWS), and also in Los Alamos the Los Alamos Meson Facility (LAMPF)[1]. A cathode-pulsed klystron is always less expensive and more reliable than one with a modulation anode, and three types of cathode pulsed modulators were considered for this project. The three cathode-pulsing modulators considered are the compensated switch and pulse transformer design[2], and two types of fast IGBT power supplies. The compensated transformer coupled design is a design in which the capacitor bank droop is largely canceled by a second, low energy storage capacitor circuit. This circuit was developed at FermiLab for the TESLA klystrons, and for long pulse lengths above 1 ms, it is simpler and less expensive than the conventional pulse transformer and pulse forming network designs. It is possible to eliminate the modulator completely and simplify the pulsed-power system if we had a very fast power supply that could rise to 120 kV in less than 0.1 ms. This may well be possible with the current IGBT technology, and two types of such fast power supplies are being considered for this application. We discuss and compare the advantages and disadvantages of various modulator designs. Reliability, total costs and the ability to easily double the pulse length are important attributes for this application. The klystrons will frequently arc, especially when they are new, and the modulator must not damage the klystrons when they arc.

¹*Work performed under the auspices of the US Department of Energy.

simplified schematic of the modulator itself is shown in Fig 2.

The most expensive item is the switch tube, and more than one klystron can be driven by a single switch tube. In the SNS baseline design we choose 8 klystrons per power supply and capacitor bank, and two klystrons per modulator. A more detailed description of the floating deck modulator is in [1]. The voltage droop can be reduced by either passive[3] or active[4] compensation in the modulator, but space limitations prevent a discussion of these methods here, except to note that the parallel RL circuit in Fig. 2 is a type of passive compensation circuit.

III. The Fast IGBT Power Supply

A common method to build power supplies at powers below 1 kW is to have a rectifier, followed by a high-frequency switch mode power supply, which is a dc-to-dc converter. By largely eliminating the 60-Hz magnetics, the supply can be made smaller, lighter, and more economical. One trades silicon for iron, and as power switches become less expensive, the break even point in power increases with time. If the power supply can be made fast enough, the modulator, crowbar, and high-voltage storage bank can be eliminated, along with considerable cost reduction.

Fig 3 Block diagram of the fast pulsed power supply

A block diagram of the proposed system is shown in Fig. 3. The power supply must be able to rise to full voltage in under 0.1 ms, and to keep the

system efficiency high, a high frequency (several kilohertz), multi-phase, current-fed, resonant or quasi-resonant chopper is used in the dc-to-dc converter in Fig. 3. Several possible circuits for the converter are being considered, and a quasi-resonant, current-fed boost circuit with a 12:1 step-up transformer is one of the leading candidates. The transformers will be relatively small, due to the several kHz operation frequency, and we realize that there are many significant challenges to make such a system work reliably and without a failure cascade when one component or the klystron arcs. In this type of converter, the power supply can regulate, so the stored energy can be lower than in the baseline system. The plan is to store the energy at about 10 kV, where the energy density and capacitor costs are favorable.

IV. The Medium-Speed IGBT Power Supply

Commercial vendors make power supplies that can be modulated in the 6 to 18 kHz range for short-wave AM transmitters. All the magnetics operate at 50 or 60 Hz, so the transformers are large, but they can be reliable. A simplified schematic of one such power supply, called a solid-state power module is shown in Fig 4.

For this circuit, 96 separate power supplies are operated in a series configuration. These individual supplies are powered by four separate power transformers to give 24-pulse rectification of the 60 Hz power.

V. The Compensated-Transformer Modulator

The compensated transformer modulator is like a conventional PFN modulator, except that a capacitor bank, rather than a pulse-forming network is used to store the pulse energy. The capacitor droop during the long pulse may be passively compensated by a switched LC circuit that is in series with the pulse transformer. If there is a logic circuit to choose the time that the compensation circuit operates relative to the main pulse, active compensation is possible. The pulse transformer may also be smaller than in conventional designs, since some of its droop may

Fig 4 Block diagram of the multiple fast-pulsed power supply system.

be canceled by the compensation circuit. This circuit has been developed at FermiLab, and used for 1 to 2 ms klystron modulators[2]. A simplified version of the circuit is shown in Fig. 5. For long pulses, above 1 ms, this circuit is less expensive than the conventional PFN circuit with a thyatron switch, and one would expect the reliability to be better, although not much life experience has been accumulated to date.

Fig 5 Block diagram of the compensated pulse transformer modulator

VI. Conclusions

Long-pulse, high-power, high-voltage modulators present difficult design choices, since no one technology is able to meet all the desired characteristics. The solid-state power modulator seems to have real cost and maintainability advantages, but these details are still being worked out. However, the trends are to solid-state switches replacing the previous thyatrons and vacuum tubes, and more silicon power devices to replace the previous switches and large transformers. For the SNS application, we prefer the high frequency, switched dc-to-dc converter, but we will retain the conventional floating deck modulator as a backup until the advantage of the newer circuits can be conclusively proven.

VII. References

1. P.J. Tallerico, R.L. Cady, J.D. Doss, "Design and Performance of the LAMPF 1-1/4 MW Klystron Modulator," Proceedings of the 1973 11th Modulator Symposium, New York, NY, pp 56-60, Sept.4-7, 1973
2. H. Pfeffer, L. Bartelson, K. Bourkland, C. Jensen, Q. Kerns, P. Prieto, G. Saewert, D. Wolff, "A Long Pulse Modulator for Reduced Size and Cost," Proceedings of the 1994 21st International Power Modulator Symposium, Costa Mesa, CA, June 27-30, 1994, pp. 48-51
3. Thomas A. Weil, "A Passive Assist for Hard Tube Modulator," Proceedings of the 1976 12th Modulator Symposium, New York, NY, Feb. 4-5, 1976, pp. 168-171
4. Paul J. Tallerico, "The GTA 850-MHz High-Power RF System," Presented at the First Annual Neutral Particle Beam Technical Symposium, Monterey, CA, July 17-21, 1989