LA-UR-97- 2407

TITLE: A REGULATED MAGNETRON PULSER

CONF-9706113--

AUTHOR(S): Chris R. Rose

LANSCE-1

RECEIVED

AUG 27 1997

OSTI

SUBMITTED TO:

To be presented at the 11th IEEE International Pulsed Power
Conference, Baltimore, MD
June 29 - July 2, 1997

MASTERDISTRIBUTION OF THIS DOCUMENT IS UNLIMITED *ng*

Los Alamos
NATIONAL LABORATORY

Los Alamos National Laboratory, an affirmative action/equal opportunity employer, is operated by the University of California for the U.S. Department of Energy under contract W-7405-ENG-36. By acceptance of this article, the publisher recognizes that the U.S. Government retains a nonexclusive, royalty-free license to publish or reproduce the published form of this contribution, or to allow others to do so, for U.S. Government purposes. The Los Alamos National Laboratory requests that the publisher identify this article as work performed under the auspices of the U.S. Department of Energy.

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, make any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

**Portions of this document may be illegible
in electronic image products. Images are
produced from the best available original
document.**

A REGULATED MAGNETRON PULSER

C. R. Rose

Los Alamos National Laboratory
PO Box 1663 M/S H808
Los Alamos, NM 87545

Abstract

This paper describes the design and analysis of a 4.5-kV, 500-mA, regulated current pulser used to drive a Hitachi 2M130 magnetron in a particle-accelerator injector. In this application, precise and stable magnetron current is crucial to extract a stable and accurate particle beam from the injector. A high-voltage triode vacuum tube with active feedback is used to control the magnetron current. Current regulation and accuracy is better than 1%. The pulse width may be varied from as little as 5 μ s to cw by varying the width of a gate pulse. The current level can be programmed between 10 and 500 mA. Design of the pulser including circuit simulations, power calculations, and high-voltage issues are discussed.

Introduction

The Accelerator Production of Tritium (APT) project at Los Alamos is developing a Low-Energy Demonstration Accelerator (LEDA) which uses a magnetron rf source in its injector. The injector output-current amplitude is dependent on the magnetron rf level which depends on the magnetron anode current. To generate stable and precise injector current, the rf source amplitude must be stable and repeatable controlled by its current. Thus stable and precisely controlled magnetron current directly affects the injector current. This paper describes a design for a pulsed and cw magnetron current regulator to be used in LEDA. Some of the important specifications of the pulser are listed in the following table.

Item	Value	Units
minimum pulse width	5	μ s
minimum duty factor	≤ 0.001	%
maximum duty factor	100	%
pulse-current risetime	≤ 2	μ s
pulse-current set-point range	10 - 500	mA
maximum hold-off voltage	≥ 5000	VDC
pulse-to-pulse regulation	≤ 1	%
pulse flat-top regulation	≤ 1	%
pulse flat-top accuracy	≤ 1	%

Similar work has been done by Liu¹ using a 2200-V BJT modulator to drive a magnetron rf source but because of the higher required operating voltage of the LEDA system, the BJT method is not feasible. Others have also built magnetron pulsers, but they are invariably PFN

types with no explicit current control. A triode vacuum tube regulator has been chosen for this implementation because of its high average-power, high-voltage and control capabilities.

Pulser Design and Analysis

A simplified block diagram of the pulser is shown below in Fig. 1. The modulator, consisting of

Fig. 1 Block diagram of the recommended magnetron pulser system.

an EIMAC 3CPX1500A7 triode, its control circuitry, and power supplies are connected to the cathode side of the Hitachi magnetron. Control signals are fed to the modulator via fiber-optic cables. The GATE signal is used to turn the triode on and off. The LEVEL signal, ranging from 0-10 Vdc, sets the output current from 10 to 500 mA. A feedback signal is provided for monitoring purposes. This type of modulator is capable of both pulsed operation at low duty factors and continuous operation at 100% duty factor. The modulator pulse width is solely controlled by the gate signal.

The V-I response of a magnetron resembles that of a zener diode. A graph of the response is shown in Fig. 2. For simulation purposes, the magnetron was modeled as a string of zener diodes with selected series resistance values and breakdown voltages to yield a response similar to that of Fig. 2.

A simplified regulator schematic used in SPICE simulations is shown below in Fig. 3.

Fig. 2 V-I response of the Hitachi magnetron.

Fig. 3 Schematic of the modulator used in SPICE.

The anode side of the magnetron is connected to ground, and the cathode is connected via cabling to the anode side of the triode. The triode, in this configuration, is used as a linear regulator capable of both pulsed operation and continuous duty.

In the model, the input signal is voltage-source V7 with amplitude ranging from 0 to 10 V and the ability to vary the pulse width and duty factor. In hardware, there will be two fiber-optic

signals coming into the modulator—a pulse or gate signal, and an amplitude signal. For simulation purposes, it is easier to incorporate these two attributes into one pulse signal. The first OP AMP is used as a variable gain stage, if needed, and to invert the polarity of the input signal. Its output is fed to the power OP AMP X25 shown in the figure. This amplifier, an APEX model PA08, drives the grid on the triode. To linearize the transfer function of the triode, which is intrinsically non-linear with an exponential $3/2$ transfer function, a cathode resistor of $10\ \Omega$ is inserted in the cathode circuit and used as a voltage (current) feedback point for the power OP AMP. The output of the PA08 is allowed to swing positive to turn on the triode, and negative to turn it off. By using a high- μ triode like the 3CPX1500A7, the required grid voltage for complete cut-off is less than $-40\ \text{Vdc}$ with respect to the cathode.

Fig. 4 Simulated input and output waveforms for the circuit of Fig. 3.

As shown in Fig. 3, this design requires the use of a "hot deck" on which the OP AMP drivers and other control circuitry are allowed to float at the potential of the negative high-voltage power supply.

The expected waveforms for a typical 500 mA pulse are shown Fig. 4. The top waveform is the input-signal pulse at $10\ \text{V}_{\text{peak}}$ and the bottom waveform is the magnetron current shown at $200\ \text{mA/div}$. The risetime of the current pulse is about 695 ns, and can be controlled by adjusting the values of R6 and C2 in Fig. 3. These two elements set the overall-system bandwidth and must be set lower than any other bandwidth limiters such as the grid-to-cathode capacitance in the triode circuit.

This triode specifies a heater voltage of $5.5\ \text{Vrms}$, but by using $5.0\ \text{Vrms}$, one will decrease the maximum pulse current (not applicable in our situation) to 24 A, but will increase the overall lifetime of the triode. Second, the required airflow for the tube at our elevation is about 10 CFM assuming 500 W of plate dissipation. This also assumes slightly more than 500 V drop across the tube during DC operation. Initially, the tube will be used at low duty factor operation and the system high-voltage power supply will be set for about a 500 V drop across the tube under full current pulse conditions. Later, this voltage drop will be empirically tested to determine if it can be reduced to say, 250 or 300 V during operation. The actual setting of the tube voltage drop

will be done by setting the voltage of the high-voltage power supply. The design specifies that the initial high-voltage be set for -4500 VDC which will yield about 500-600 V drop across the tube during pulse or DC operation. The issue of tube voltage drop will be re-examined when the hardware is built and tube performance can be monitored.

The fabrication of the hot-deck is done to minimize stray circuit inductance and capacitance around the grid and cathode feedback circuits. Excessive stray capacitance or inductance will limit the available risetime and hence loop bandwidth. Additionally, suitable fans are required for proper cooling of the triode. The triode is rated at 1500 W plate dissipation, and in the present scenario, the maximum plate dissipation is expected to be less than 400 W at 100% duty factor. Thus, it is quite conservatively rated, but does need proper air flow.

Conclusions

The circuit described in Fig. 3 is being assembled as of this writing. The author wishes to thank D. Warren for his work in assembling the magnetron pulser, and T. Zaugg for his technical input.

¹ Liu, Jian, et. al., "A New Microwave Power Source and its Application," IEEE MTT-S, San Francisco, 1996.