THE DATACON MASTER - RENOVATION OF A DATACON FIELD BUS COMMUNICATIONS SYSTEM FOR ACCELERATOR CONTROL*

T. M. Kerner, AGS Department, Brookhaven National Laboratory, Upton, NY 11973-5000 USA

I. OVERVIEW

The Datacon system is a serial coaxial transformer isolated communication field bus system used to control and monitor accelerator remote devices. The Datacon field bus has been a BNL accelerator standard since its initial use in 1965. A single Datacon field bus supports up to 256 devices on a multidrop RG62A/U coaxial cable with up to 33 devices or 2000 feet between repeaters or buffered branches.

A. Why Renovate?

The forcing factor to renovate was the inability to repair the aging PDP-8E and PDP10 computers. The maintenance on this aging system was costly and the large number of accelerator devices dependent on the Datacon system could not be converted in a reasonable period of time to a new modern field bus.

B. Upgrading to a Real Time Object Oriented Solution

The changeover to a new system had to be done quickly and cleanly. With as many as 2600 existing accelerator devices to control and monitor, a compatible and well-defined solution was required which could literally plug into our existing Datacon field bus coaxial cables. The limited time available during maintenance cycles was all that was available to change over to and qualify a new system. A well defined and low risk system architecture and strategy had to be developed. As a control system was being designed for the Relativistic Heavy Ion Collider (RHIC), the decision to merge a real-time object-oriented architecture with the Datacon field bus was reached.

C. The Solution

A commercial VMEbus host CPU mated with a custom designed VMEbus SBC event driven serial communications engine featuring a superscaler RISC 32-bit Intel i960 CPU met the design challenge. The commercial VMEbus host runs the VxWorks real-time operating system and connects to UNIX workstations over a Ethernet LAN. The V110 Datacon Master is the custom designed front end computer that integrates an accelerator event time line system with accelerator devices for up to 8 PPM users adding new capabilities. The V110 with the added multiple user or PPM capability, with increased bandwidth, with shorter latency and overhead would outpace the original system in functionality and performance by at least an order of magnitude. Great improvements came from a robust set of supported network protocols allowing even engineering PCs to be used to develop

and test complex control system components. As communications improved and performance issues were no longer the limiting factor driving accelerator devices, a jump in controls effectiveness and efficiency could be realized.

II. SYSTEM COMPONENT DESCRIPTION

The Datacon Master System is divided into five functional parts.

A. The Commercial VMEbus Front End Computer

A Motorola MVME 162-222 was selected for use in the Datacon Master System. This SBC was selected for use in the new RHIC control system where large numbers of these SBCs would be used. The selection requirements for this computer are omitted here to conserve space. The MVME162-222 with the VxWorks real time operating system provided an adequate platform for the FEC functionality required to support Datacon Master functionality as well as being well positioned to make best use of resident programming skills.

B. The V110 Datacon Master Serial Communications Engine

The V110 is a single board VMEbus compatible custom designed communications engine. The V110 includes an event link or a time line event decoder, a microsecond time stamp counter, 4 parallel ports for 4 individual Datacon field busses, a full featured VMEbus interface which includes block transfer capability, 2 Mbytes of fast static RAM, a 33 MHz 32-bit Intel i960 RISC superscaler μ P, five large custom designed Altera programmable logic devices and 32-bit fast burst access PROM.

C. The P110 P2 Buffer Board

The P2 Buffer Board connects the VMEbus back plane to a ribbon cable assembly via buffers to allow high speed signals to travel over ribbon cable assemblies to the T110 Datacon Master Transition Module.

D. The T110 Datacon Master Transition Module

The T110 Datacon Master Transition module contains 4 large Altera programmable logic devices that provide the serialization from a 32-bit wide multiplexed high speed data bus to the relatively slow 1 MHz serial data stream. The Altera devices send and receive TTL level serial differential data to the Datacon Driver.

*Work Performed under the auspices of the U.S. Department of Energy.

V. SYSTEM ARCHITECTURE

A. EPROM

The 64 Kbytes of EPROM are arranged 32-bits wide by 16 K deep. The EPROM is a burst access variety that makes use of the pipelined burst access mode of the i960. This is a high throughput memory region programmed with zero wait states for 132 Mbyte per second transfer rates, the highest performance available in a commercial μ P at the time of the Datacon Master design.

B. Superscaler RISC Processor

The Intel A80960CA-33 is a 33 MHz μ P with superscaler technology that enables the μ P to execute up to three instructions per clock cycle. The μ P has a two-way set associative 1 Kbyte 32-bit wide zero wait state internal instruction cache, a 32-bit wide 1 Kbyte zero wait state internal data RAM, 5-15 set register cache, and a high speed vector cached interrupt controller. The bus control unit allows the main external static RAM region to be configured as big endian for compatibility with dual porting to the VMEbus, while keeping μ P specific externals such as EPROM and its firmware little endian for compatibility with Intel compilers and software development tools.

C. 2 Mbytes SRAM

The 2 Mbytes of SRAM is configured as 32-bit wide by 500 K deep. It is in a pipelined burst memory region with one wait state. The SRAM is dual ported with bus arbitration to the VMEbus and is configured as big endian for compatibility with 68000 addressing.

D. Time Line Decoder Filter

The time line decoder filter is set up as 8 pages in static RAM to accommodate 8 possible users. The memory table may be updated by the local μ P and then page swapped on the arrival of a time line fiducial code that signifies a user change.

E. Priority Interrupt Control Logic

To efficiently prioritize incoming Datacon line data available, parity error and time-outs for the 4 Datacon lines serviced plus VMEbus requests and VMEbus register interrupts, VMEbus error, and time line interrupts, custom interrupt control logic was designed to allow maximum throughput with minimum latency.

F. Time Line Event FIFO

Time line events may arrive back to back or 100 ns apart. To handle this possibility, a timeline event FIFO temporarily

stores each event until the μ P can service the interrupts that nominally take a few microseconds.

G. NVRAM

NVRAM is available for storing volatile data to handle power dips. The Datacon Master finishes initialization after a power dip in about 1 second. This avoids the long host computer boot up time lag.

H. I/O Functions, Watchdog, Time Stamp

A watchdog monitors the voltage on the Datacon Master power planes. If the voltage should dip to 4.5 volts the watchdog reinitializes the local μ P, which then reinitializes the on board logic and VMEbus interface. This insures an orderly power on reset as well as power dip reset. An early AC fail condition interrupts the μ P at the highest priority and saves volatile data. The watchdog is pinged by the local μ P as part of normal firmware operation. Should the μ P halt or hang, the watchdog would reset the μ P and reinitialize the board.

I. Timer Counters

Four timer counters are used to control the time-outs for each Datacon line. The 1 μ S clock on the timer counters provides delays up to 512 μ S that may be programmed in 2 μ S increments. These counters insure minimal turnaround time should a field device be disconnected or fail.

VI. FIRMWARE

The Datacon Master protocol defines four types of information blocks: Input Request Blocks, Message Descriptor Blocks, Source Message Blocks, and Reply Message Blocks. IRBs are created by an off board host and are used to append or delete SMBs via a linked list of pointers in the MDB. IRBs contain a PPM user, time event code, Datacon line number, and MDB pointer. The MDB chains together SMB and RMBs that are executed on the same time event. MDBs contain a forward and backward linking pointer, a SMB element count, a RMB repeat index, a SMB pointer and RMB pointer(s). SMBs and RMBs are therefore dynamically linked which gives rise to an efficient method for making modifications with little overhead. This technique allows multiple buffering, and complex triggering sequences to be created. MDB may be efficiently cut and pasted using the linked list of pointers. RMBs contain a start time stamp, end time stamp, reply message, and status code. The off board host is responsible for memory management and is required to secure exclusive use of sufficient memory space for each of the SMBs and RMBs that the host creates. For space reasons this protocol description has been oversimplified.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

E. The DD110 Datacon Driver

The DD110 Datacon Driver converts the differential serial TTL level data found on the T110 DCM Transition Module into the ± 15 Volt levels transmitted and received on the Datacon field bus coaxial cables. The DD110 is located in its own rack mountable enclosure with its own power supply to isolate Datacon electrical noise from the rest of the Datacon Master system.

III. SYSTEM OPERATIONAL REQUIREMENTS

The renovated system must be compatible with all accelerator devices that predated it. There are approximately 28 device types. A recent survey found 2616 active addresses. Some of the 28 device types are power supply controls, stepping motor positioning systems, collimator jaw positioners, beam profile monitors, scalars, autodelays, analog signal acquisition, video multiplexing, function generators, and chipmunk radiation monitors. A comprehensive plan to port over drivers and integrate the new real-time operating system was devised. Creation of a test platform with real Datacon devices and loop back testing would answer most of the compatibility issues facing the cut-over to the new system. Persistence of software objects would have to be added to the new system for power dips or outages. Integration of the new time line event link capabilities would require some development and coordination in both hardware and software. The firmware for the V110 Datacon Master would have to be developed jointly between the hardware designers and the software group. A specification for the host front end computer to the V110 Datacon Master had to be developed which was flexible and broad enough to accommodate both single user machines such as RHIC and multiple user machines such as the LINAC, the BOOSTER, and the AGS. The Datacon Master was designed to allow modular additions to the existing Datacon field bus controls. Up to 8 V110 Datacon masters accommodating 32 Datacon field lines could be accommodated in a single VME chassis. Power savings over the original main frame PDP10 and PDP8 computers with two 20-ton and one 5-ton air conditioning units would not be insignificant.

A. Integration Testing

A series of stress tests were created to run the new Datacon Master system at full bandwidth in conjunction with a test set that looped back transmissions for testing the error rate and qualifying both hardware and software. Tests were devised which were time line controlled as well as load and go immediately. The insertion and extraction of devices from chains of linked lists was tested using the host and Datacon Master firmware. Thousands of operations could be tested with the loop back features while looking for data failures or scheduling failures or overlaps. The time line code table acts as a time line code filter and is maintained by

the Datacon Master μ P. Codes designated as active are downloaded from the host front end computer. Any and all codes may be used as an event code, fiducial, or user change. The interpretation of the codes is completely under tabular program control. Connection to the real time line demonstrated the proper dispatching of chained commands. Active time line event codes are stored in a FIFO such that any code arrival rate can be handled properly. An Apollo terminal was used to dispatch and display the reply messages with microsecond arrival time stamps and any DNA (Did Not Answer) status for unconnected devices after a preset microsecond time-out period. Time out periods were preset and observed on a line by line basis. On board non-volatile RAM may be used to safeguard against power interruption. The Datacon Master re-initializes within 1 second of power restoration.

B. Throughput or Performance

No significant degradation in system performance will be permitted with 4 lines simultaneously operating at the highest permissible bandwidth supported by the Datacon Line Specification. All overhead for processing and time sharing with the VMEbus must be included in the serial shift out time of the Datacon transmission. Latency time from a time line event to the beginning of a Datacon transmission shall not exceed 25 microseconds with 4 lines operating at maximum bandwidth. The Datacon Master was designed to modularly replace the Transition module with a fiber optic driver such that upgrading to fiber can be accomplished with minimal impact on system design.

The time-out may be individually tuned to each line to provide the fastest possible turnaround time in the presence of a missing device. The time-out period is a function of line length, number of repeaters used, and device requirements.

The main memory consists of 2 Mbytes of high speed static RAM. This is enough RAM to support several users with long chained sequences of command and response messages.

IV. WHAT'S NEW IN THE RENOVATION

- A. Time Line Interface*
- B. Ethernet Interface*
- C. VxWorks real-time operating system*
- D. PC based terminal diagnostics and testing*
- E. Multi-user capabilities*
- F. Microsecond Time stamp*
- G. Software Object Persistence through power dips*
- H. VMEbus Based System*

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.