231085

UCRL-ID-126849

Fourier Analysis

J. Lawson

March 3, 1997

Lawrence
Livermore
National
Laboratory

This is an informal report intended primarily for internal or limited external distribution. The opinions and conclusions stated are those of the author and may or may not be those of the Laboratory.

Work performed under the auspices of the U.S. Department of Energy by the Lawrence Livermore National Laboratory under Contract W-7405-Eng-48.

DISCLAIMER

This document was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor the University of California nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or the University of California. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or the University of California, and shall not be used for advertising or product endorsement purposes.

This report has been reproduced
directly from the best available copy.

Available to DOE and DOE contractors from the
Office of Scientific and Technical Information
P.O. Box 62, Oak Ridge, TN 37831
Prices available from (615) 576-8401, FTS 626-8401

Available to the public from the
National Technical Information Service
U.S. Department of Commerce
5285 Port Royal Rd.,
Springfield, VA 22161

March 3, 1997

Hi Qiang,

Sorry it took so long to respond to your request for more information. It took longer than I anticipated to piece together everything that I had done. What follows is a description of my analysis.

First, the FFT that I use is described on the attached pages. Note that the scaling factor for the forward transform is $1/N$.

I compute the following rms values:

$\text{rms}(\text{original data}) = 64.9463 \text{ nm}$

$\text{rms}(\text{data} * \text{hanning}) = 55.7723 \text{ nm}$ (before renormalization)

The use of the hanning filter is accompanied by a renormalization to insure that the rms value is maintained.

I also fit to the curvature of the scan. The data corrected for focus gives the following rms values:

$\text{rms}(\text{corrected data}) = 56.8835 \text{ nm}$

$\text{rms}(\text{corrected data} * \text{hanning}) = 53.2179 \text{ nm}$ (before renormalization)

The PSD is shown for various data. The PSD is calculated as:

$\text{PSD} = |\text{FFT}(y)|^2 * x_l$

where x_l is the length of the x axis, 45.9952.

I did find an error in the plot that you were sent. If k_x is the frequency axis, i.e., values from (0, Nyquist), then $k_x(1, \text{Nyquist})$ is plotted versus $\text{PSD}(0, \text{Nyquist})$. This error is corrected in the attached plots. The plot you have appears to be the PSD of the original data with no hanning applied.

The removal of the quadratic term appear to have a negligible effect on the PSD. It changes only the first couple of terms (which lie outside of the data valid range). The removal of the center feature has a much stronger effect.

Janice *JKL*

FFT

The FFT function returns a result equal to the complex, discrete Fourier transform of *Array*. The result of this function is a single- or double-precision complex array.

The discrete Fourier transform, $F(u)$, of an N -element, one-dimensional function, $f(x)$, is defined as:

$$F(u) = \frac{1}{N} \sum_{x=0}^{N-1} f(x) \exp[-j2\pi ux/N]$$

And the inverse transform, (*Direction* > 0), is defined as:

$$f(x) = \sum_{u=0}^{N-1} F(u) \exp[j2\pi ux/N]$$

If the keyword **OVERWRITE** is set, the transform is performed in-place, and the result overwrites the original contents of the array.

The result returned by FFT is a complex array that has the same dimensions as the input array. The output array is ordered in the same manner as almost all discrete Fourier transforms. Element 0 contains the zero frequency component, F0. F1 contains the smallest non-zero positive frequency, which is equal to $1/(NT)$ where N is the number of elements in the respective dimension and T is the sampling interval. F2 corresponds to a frequency of $2/(NT)$. $FN/2$ contains the component corresponding to the Nyquist frequency, $1/(2T)$, which is the highest frequency that can be sampled.

Negative frequencies are stored in reverse order from $FN-1$, $FN-2$, ..., $FN/2+1$, corresponding to frequencies of $-1/NT$, $-2/NT$, and $-(N/2 - 1)/NT$, respectively.

Calling Sequence

Result = FFT(Array [, *Direction*])

Arguments

Array

The array to which the Fast Fourier Transform should be applied. If *Array* is not of complex type, it is converted to complex type. The dimensions of the result are

identical to those of *Array*. The size of each dimension may be any integer value and does not necessarily have to be an integer power of 2, although powers of 2 are certainly the most efficient.

Direction

Direction is a scalar indicating the direction of the transform, which is negative by convention for the forward transform, and positive for the inverse transform. If *Direction* is not specified, the forward transform is performed.

A normalization factor of $1/N$, where N is the number of points, is applied during the forward transform.

Note: When transforming from a real vector to complex and back, it is slightly faster to set *Direction* to 1 in the real to complex FFT.

Note also that the value of *Direction* is ignored if the INVERSE keyword is set.

Keywords

DOUBLE

Set this keyword to a value other than zero to force the computation to be done in double-precision arithmetic, and to give a result of double-precision complex type. If DOUBLE is set equal to zero, computation is done in single-precision arithmetic and the result is single-precision complex. If DOUBLE is not specified, the data type of the result will match the data type of *Array*.

INVERSE

Set this keyword to perform an inverse transform. Setting this keyword is equivalent to setting the *Direction* argument to a positive value. Note, however, that setting INVERSE results in an inverse transform even if *Direction* is specified as negative.

OVERWRITE

If this keyword is set, and the *Array* parameter is a variable of complex type, the transform is done "in-place". The result overwrites the previous contents of the variable. For example, to perform a forward, in-place FFT on the variable *a*:

```
a = FFT(a, -1, /OVERWRITE)
```

Running Time

For a one-dimensional FFT, running time is roughly proportional to the total number of points in *Array* times the sum of its prime factors. Let N be the total number of elements in *Array*, and decompose N into its prime factors:

$$N = 2^{K_2} \cdot 3^{K_3} \cdot 5^{K_5} \dots$$

Running time is proportional to:

$$T_0 + N(T_1 + 2K_2T_2 + T_3(3K_3 + 5K_5 + \dots))$$

where $T_3 \sim 4T_2$. For example, the running time of a 263 point FFT is approximately 10 times longer than that of a 264 point FFT, even though there are fewer points. The sum of the prime factors of 263 is 264 ($1 + 263$), while the sum of the prime factors of 264 is 20 ($2 + 2 + 2 + 3 + 11$).

Example

Display the log of the power spectrum of a 100–element index array by entering:

PLOT, /YLOG, ABS(FFT(FINDGEN(100), -1))

As a more complex example, display the power spectrum of a 100–element vector sampled at a rate of 0.1 seconds per point. Show the 0 frequency component at the center of the plot and label the abscissa with frequency:

N = 100

Define the number of points.

T = 0.1

Define the interval.

N21 = N/2 + 1

Midpoint+1 is the most negative frequency subscript.

F = INDGEN(N)

The array of subscripts.

F(N21) = N21 - N + FINDGEN(N21-2) *Insert negative frequencies in elements*
F(N/2 + 1), ..., F(N-1).

F = F / (N*T)

Compute T0 frequency.

PLOT, /YLOG, SHIFT(F, -N21), SHIFT(ABS(FFT(Y, -1)), -N21)

Shift so that the most negative frequency is plotted first.

See Also

HILBERT

original data $\equiv y$

mm

9

y corrected for curvature

quadratic fit to data

8

PSD of ycorrected * hanning

PSD of ycorrected

PSD of $y_{fix} * \text{hanning}$

PSD of y_{fix}

y_{fix} = center feature removed

$y_{fix} = y_{fix} - \text{quadratic fit}$

PSD of $y_{fixc} * \text{hanning}$

PSD of y_{fixc}