LA-UR-99-1055

*Approved for public release;
distribution is unlimited.*

Title: LASER FIELD IMAGING THROUGH FOURIER
TRANSFORM HETERODYNE

Author(s): Bradley J. Cooke, Amy E. Galbraith, Bryan E. Laubscher, Charlie E.
Strauss, Nicholas L. Olivas, and Andrew C. Grubler

Submitted to: SPIE AeroSense, Laser Radar Technology and Applications IV, 5-9
April 1999, Marriot World Center, Orlando FL

Los Alamos

NATIONAL LABORATORY

Los Alamos National Laboratory, an affirmative action/equal opportunity employer, is operated by the University of California for the U.S. Department of Energy under contract W-7405-ENG-36. By acceptance of this article, the publisher recognizes that the U.S. Government retains a nonexclusive, royalty-free license to publish or reproduce the published form of this contribution, or to allow others to do so, for U.S. Government purposes. Los Alamos National Laboratory requests that the publisher identify this article as work performed under the auspices of the U.S. Department of Energy. Los Alamos National Laboratory strongly supports academic freedom and a researcher's right to publish; as an institution, however, the Laboratory does not endorse the viewpoint of a publication or guarantee its technical correctness.

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, make any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

Laser Field Imaging Through Fourier Transform Heterodyne

Bradly J. Cooke, Amy E. Galbraith[†], Bryan E. Laubscher, Charlie E. Strauss,
Nicholas L. Olivas, and Andrew C. Grubler[‡]

Los Alamos National Laboratory
P.O. Box 1663, MS-D448
Los Alamos, NM 87545

RECEIVED
SEP 01 1999
OSTI

ABSTRACT

We present a detection process capable of directly imaging the transverse amplitude, phase, and Doppler shift of coherent electromagnetic fields. Based on coherent detection principles governing conventional heterodyned RADAR/LADAR systems, Fourier Transform Heterodyne incorporates transverse spatial encoding of the reference local oscillator for image capture. Appropriate selection of spatial encoding functions allows image retrieval by way of classic Fourier manipulations. Of practical interest: (i) imaging may be accomplished with a single element detector/sensor requiring no additional scanning or moving components, (ii) as detection is governed by heterodyne principles, near quantum limited performance is achievable, (iii) a wide variety of appropriate spatial encoding functions exist that may be adaptively configured in real-time for applications requiring optimal detection, and (iv) the concept is general with the applicable electromagnetic spectrum encompassing the RF through optical.

Key Words: Coherent Field Imaging, Laser Imaging, Laser Radar, Heterodyne Detection.

1.0 INTRODUCTION

Central to Fourier Transform Heterodyne (FTH) field imaging is the concept of a Fourier projection operator through which the image field is decomposed into Fourier states via a detection process employing familiar heterodyne detection principles. The ability to spatially image and manipulate both amplitude and phase of optical coherent electromagnetic fields enables important adaptations of current Laser Radar (LADAR) systems. Candidate LADAR functions, potentially enhanced through exploitation of spatial field imaging, include target classification and identification, Doppler field imaging, optimized target discrimination and clutter suppression through spatial filtering, and deployment of coherently phased optical arrays. Additionally, phase imaging permits the measuring, and hence correction of phase-front distortion imposed by atmosphere and receiver optics. A coherent receiver capable of unobtrusively tracking and correcting atmospheric induced phase-front error may permit the realization of large aperture, long-range communication systems,¹ while the direct and unambiguous measurement of wavefront distortion may be applied to the development of lightweight, space-borne deployable optical apertures.

[†] Electrical and Computer Engineering Department, University of Arizona

[‡] United States Naval Academy, P.O. Box 12939, Annapolis, MD 21412

Figure 1. Transverse and longitudinal components of propagating electromagnetic field.

photosensitive device subjects the transverse field to a process referred to as squared modulus or square-law detection.³ The square-law imaging of a complex field composed of a spatial amplitude and phase distribution, Φ_{Image} , results in the observer imaging the field's *intensity*⁴

$$I_i \propto |\Phi_{Image}|^2, \quad [1]$$

whereby all spatial phase information is lost. Preservation of *both* spatial amplitude and phase prompts a detection process that sidesteps the limitations imposed by the square-law operation.

The goal of this paper is the introduction of a detection process that circumvents the square-law limitations, and therefore, is capable of directly imaging the transverse amplitude and phase of coherent electromagnetic fields. Section 2 introduces the underlying principles governing FTH field detection through the calculus of Fourier spatial projection operators, while Section 3 demonstrates Fourier projection concepts and field imaging via a simple experimental setup based on a HeNe laser and a 69 element spatial phase modulator. Finally, practical considerations followed by several LADAR examples exploiting spatial field imaging are described in Section 4. It should be noted that while the emphasis of this paper is on systems operating in sub-millimeter through optical wavelengths (i.e. physical-optics approximation⁵ where the transverse dimensions of the field, aperture, and other surface curvatures are large compared to wavelength), the theory is relatively general and in many cases is readily extended to longer wavelength systems.

2.0 FOURIER TRANSFORM HETERODYNE

2.1. Fourier Projection Operator

Central to FTH field imaging are Fourier projection concepts based on square-law heterodyne detection principles relating the spatial distribution of an image field, Φ_{Image} , to that of a (typically user defined) reference field, Φ_{Ref} .

1.1. Field Imaging

The transverse and longitudinal components of a propagating coherent electromagnetic field are shown in Figure 1. The spatial amplitude and phase distributions comprising the transverse field lie in a two-dimensional surface normal to the longitudinal direction of propagation with constant phase surfaces spaced a wavelength apart². The propagating field conveys image information to an observer at z through the temporal variations in the spatial amplitude and phase distribution. Observing (imaging) the field with eyes, film, CCD camera or other

Figure 2. Heterodyned square-law detection can be perceived as a Fourier projection with the intermediate frequency (I.F.) current conveying the magnitude (β) and phase (α) of the projection.

Referring to **Figure 2**, the heterodyning of the image field, Φ_{Image} , with the reference field, Φ_{Ref} , in a square-law detector of surface area, s , results (after filtering) in a complex intermediate frequency (I.F.) current. As will be demonstrated, the magnitude (β) and phase (α) of the I.F. current conveys the spatial Fourier projection of the reference field onto the image field

$$\beta e^{i\alpha} = \langle \Phi_{Ref}, \Phi_{Image} \rangle \equiv \iint_s \Phi_{Image} \Phi_{Ref}^* dx dy. \quad [2]$$

The derivation of **Equation 2** follows from Poynting's relation^{6,7,8} which relates the induced detector current, I , to the detector's quantum efficiency, η , and the spatial distribution of the image and reference electromagnetic fields, Φ_{Image} and Φ_{Ref} respectively, over the detector surface, s , through

$$I = k \iint_s \eta (\mathbf{E} \times \mathbf{H}) \cdot d\mathbf{s} \quad [\text{Ampere}], \quad [3]$$

where

$$\mathbf{E} = \Phi_{Image} + \Phi_{Ref}, \quad \mathbf{H} = \mathbf{H}_{Image} + \mathbf{H}_{Ref}, \quad k = \text{constant}. \quad [4]$$

Assuming the image and reference fields are transverse electromagnetic in nature,

$$\Phi_{Image} = \rho(x, y) e^{-i\omega t - i\phi(x, y)}, \quad [5]$$

$$\Phi_{Ref} = A e^{-i\omega' t - i\theta(x, y)}, \quad [6]$$

and the reference fields form a complete orthonormal⁹ basis set such that

$$\iint_s e^{i\theta(k_x, k_y, x, y)} e^{-i\theta(k'_x, k'_y, x, y)} dx dy = \delta(k_x - k'_x) \delta(k_y - k'_y), \quad [7]$$

then the detector current at the intermediate frequency, $\Delta\omega = \omega - \omega'$, reduces to

$$I(k_x, k_y, \Delta\omega) = 2kA\eta\sqrt{\frac{\varepsilon}{\mu}} \operatorname{Re} \left[\iint_s \Phi_{Image}(x, y) e^{i\omega't + i\theta(k_x, k_y, x, y)} dx dy \right] \quad [8]$$

$$= 2kA\sqrt{\frac{\varepsilon}{\mu}} \beta(k_x, k_y) \cos(\Delta\omega t + \alpha(k_x, k_y)) \quad [\text{Ampere}]. \quad [9]$$

Complex Fourier coefficients, $C(k_x, k_y) \propto \beta(k_x, k_y) e^{i\alpha(k_x, k_y)}$, can then be formed from the I.F. current's complex phase and magnitude, resulting in the following transform pair relating the image field, complex Fourier coefficient and reference basis set:

$$C(k_x, k_y) = \iint_s \Phi_{Image}(x, y) e^{i\theta(k_x, k_y, x, y)} dx dy \Leftrightarrow \Phi_{Image}(x, y) = \iint_s C(k_x, k_y) e^{-i\theta(k_x, k_y, x, y)} dk_x dk_y. \quad [10]$$

In general, spatial variations may be present in both the reference beam and detection quantum efficiency. Taking these variations into account, **Equation 8** would be rewritten as

$$I(k_x, k_y, \Delta\omega) = 2k\sqrt{\frac{\varepsilon}{\mu}} \operatorname{Re} \left[\iint_s \eta(x, y) \Phi_{Image}(x, y) \Phi_{Ref}(x, y)^* dx dy \right], \quad [11]$$

$$\text{with } \Phi_{Ref}(x, y) = \rho'(x, y) e^{-i\omega't - i\theta(x, y)}. \quad [12]$$

Finally, if the image field is heterodyned with a discrete set of reference fields ($\Phi_{Ref}(x, y) \rightarrow \Phi_{m,n}$), then **Equation 11** reduces to the following Fourier expansion pair

$$\Phi_{Image}(x, y, \Delta\omega_l) = \Phi_{Image}(x, y, l) = \sum_m \sum_n C_{l,m,n} \Phi_{m,n}(x, y), \quad [13]$$

$$C_{l,m,n} = \langle \Phi_{m,n}, \Phi_{Image} \rangle, \quad \langle \Phi_{m,n}, \Phi_{Image} \rangle \equiv \iint_s \Phi_{Image} \Phi_{m,n}^* dx dy. \quad [14]$$

The bracket operator notation of **Equation 2** has been introduced to simplify notation and convey the field projection nature of the operation. Additionally, the index l , representing the l^{th} I.F. bandpass frequency ($\Delta\omega_l$) has been included to account for Doppler shifts.

Of practical interest in the development of synthetic apertures and multi-element detectors (such as focal plane arrays and phased array¹⁰ receivers), the detecting surface, s , can be partitioned into multiple detection surfaces and coherently summed in the following manner

$$\iint_s \Phi_{Image} \Phi_{m,n}^* dx dy \Rightarrow \sum_{s_l} \iint_{s_l} \Phi_{Image} \Phi_{m,n}^* dx dy. \quad [15]$$

Figure 3. Fourier Transform Heterodyne field imaging. Based on coherent detection principles, FTH applies Fourier projection concepts through the transverse spatial encoding ($\Phi_{m,n}$) of the local oscillator for electromagnetic field capture. FTH preserves both spatial amplitude and phase information.

Finally, generalized to three-dimensional (3-D) surfaces, the Fourier projection operator conveys the degree of correlation between image and reference fields,

$$\iint_s \mathbf{J} \cdot d\mathbf{s} = k \iint_s \eta(\mathbf{E} \times \mathbf{H}) \cdot d\mathbf{s} \Leftrightarrow \langle \Phi_{Ref}(x, y, z, t, \mathbf{p}, \lambda), \Phi_{Image}(x, y, z, t, \mathbf{p}, \lambda) \rangle, \quad [16]$$

where $\mathbf{J}$ is the induced current density, t the time variable, $\mathbf{p}$ the field polarization and λ the wavelength. The projection is maximized when image and reference field states are matched (matched filter condition). Field states may be tailored to introduce signal uniqueness, and/or noise and clutter suppression for the design of optimal detection processes. Spatial and temporal field states include time, frequency, polarization, and spatial amplitude and phase.

2.2. FTH Field Imaging

Applying **Equations 13 - 14**, and referring to **Figure 3**, the basic steps involved in image field capture follow:

- Heterodyne the image field, Φ_{Image} , with the local oscillator (l.o.) whose transverse amplitude and phase is sequentially modulated with a known set of reference spatial phase functions, $\Phi_{Ref} = \Phi_{m,n}$, that span a valid basis set.
- Measure the projected detector current's magnitude and phase and form the complex Fourier coefficient, $C_{m,n}$, for each spatial function, $\Phi_{m,n}$.
- Through **Equation 13**, reconstruct the image field from the basis functions, $\Phi_{m,n}$, and the measured $C_{m,n}$:

$$\Phi_{Image}(x, y) = \sum_m \sum_n C_{m,n} \Phi_{m,n}(x, y).$$

While a single element system is demonstrated in **Figure 3**, image capture rates may be improved through reference field partitioning, multi-element detection, and frequency multiplexing.

3.0 EXPERIMENT

A simple experiment demonstrating the FTH concept has been constructed. Illustrated in Figure 4 with photographed apparatus in Figure 5, the experiment implements a Zeeman split. HeNe laser ($\Delta f = 250$ kHz) for source and local-oscillator lines, and a 69 element spatial phase modulator to encode the 36 term basis used in the experiment. A description of the experimental procedure follows:

- The two orthogonally polarized laser lines ($\Delta f = 250$ kHz) at the output of the HeNe laser are separated with the polarizing beam splitter into two beams paths.
- The first beam illuminates the target forming the image, Φ_{Image} , while the second beam passes through the 69-element spatial modulator generating the n^{th} reference term, Φ_n , $n = 0, 1, \dots, 35$.
- The two beams are recombined and heterodyned at the single-element silicon detector generating a 250 kHz intermediate frequency current I_n .
- A digital oscilloscope measures the 250 kHz I.F. current's phase and magnitude from which the Fourier coefficients, C_n , are formed (see Figure 6).
- Once all 36 basis coefficients, C_n , $n = 0, 1, \dots, 35$, are sequentially measured, the resulting magnitude and phase of the detected image, Φ_{Image} , are displayed on the computer screen.

Figure 4. Schematic diagram of FTH experiment.

Figure 5. Experimental apparatus.

Figure 6. A digital oscilloscope measures the 250 kHz I.F. current's phase and magnitude from which the Fourier coefficients, C_n , are formed.

The 2-D spatial phase modulator, implemented to encode the reference beam phase front, is the commercially produced Meadowlark Optics Hex69 spatial light modulator (SLM). The Meadowlark SLM is a 69 pixel, two-dimensional array of hexagon shaped, liquid-crystal variable retarders developed for real time programmable phase masking applications. As Meadowlark Optics conveniently supplies the software to generate the first 36 terms of the Zernike¹¹ polynomial expansion set, the Zernike set was adopted for the experiment and Equation 12, in circular coordinates, takes on the form

$$\Phi_{ref} \rightarrow \Phi_n = \rho'(r, \theta) e^{-i\omega't - i2\pi Z_n(r, \theta)}, \quad n = 0, 1, \dots, 35. \quad [17]$$

Figure 7. Beam targets: A) No target, B) 1/3 Center block, C) 1/2 Dielectric block (glass microscope slide with transmission $T = 90\%$ and phase shift $\Delta\theta = 0.9\pi$).

The beam targets employed in the experiment are catalogued in **Figure 7**. Note that commensurate with the rather limited 36-term expansion set, simple target geometry was maintained throughout the experiment.

For the purpose of providing a comparative baseline between measurement and theory, the complex coefficients were directly evaluated from **Equation 14** resulting in

$$C_n = \int_0^{2\pi} \int_0^1 T(r, \theta) \rho(r, \theta) \rho'(r, \theta) e^{2\pi i Z_n(r, \theta)} r dr d\theta, \quad n = 0, 1, \dots, 35, \quad [18]$$

with

$T(r, \theta) \equiv$ beam targets of **Figure 7**,

$\rho(r, \theta) = \rho'(r, \theta) = 1$ for a plane wave, and

$\rho(r, \theta) = \rho'(r, \theta) = e^{-\frac{r^2}{w^2}}$ for a simple Gaussian beam¹².

From **Equation 13**, given the measured coefficients, the field image is expanded through

$$\Phi_{Image}(r, \theta) = \sum_n C_n \Phi_n(r, \theta), \quad n = 0, 1, \dots, 35, \quad [19]$$

and the intensity (energy) evaluated with

$$Intensity(r, \theta) = |\Phi_{Image}(r, \theta)|^2. \quad [20]$$

Plotted in **Figure 8** are measured spectral coefficients (no target) along with the calculated spectral coefficients for the simple plane wave and Gaussian ($w = 1/2$) models.

Figure 8. Measured spectral coefficients (no target). Included are plane-wave and Gaussian ($\omega = 1/2$) coefficients for baseline comparison (coefficients have been normalized) with Gaussian model providing the best fit.

The Gaussian model was evaluated for the remaining targets of **Figure 7**, generating baseline comparison with measurements. The theoretically predicted and experimentally measured amplitude, phase, and intensity (energy) for the beam targets of **Figure 7** are plotted in **Figures 9 – 11**. Both calculated and measured coefficients are normalized and a constant phase offset was added to the measured coefficients, equalizing pedestal/piston. **Figure 11** was further subjected to the linear transform, described next, to clarify the phase image.

A consequence of raising the Zernike polynomials to an exponent, as prescribed by **Equation 12**, is noted in the fact that the 36-term basis set is no longer orthogonal. A non-orthogonal basis set will result in the off diagonal coupling of the expansion coefficients which, depending on coupling strength and image spectrum, can in turn degrade image fidelity. The magnitude of off diagonal coupling of **Equation 17** is on the order of a rather high 5% - 10%. The coefficients may be decoupled through the following linear transform¹³

$$\mathbf{C} \rightarrow \mathbf{\Lambda}^{-1} \mathbf{C}, \quad [21]$$

where:

$$\mathbf{\Lambda} = \begin{bmatrix} \langle Z_0, Z_0 \rangle & \cdots & \langle Z_0, Z_{35} \rangle \\ \vdots & \ddots & \vdots \\ \langle Z_{35}, Z_0 \rangle & \cdots & \langle Z_{35}, Z_{35} \rangle \end{bmatrix},$$

$$\text{and } \langle Z_p, Z_q \rangle = \int_0^{2\pi} \int_0^1 e^{-2\pi i Z_p(r, \theta)} e^{2\pi i Z_q(r, \theta)} r dr d\theta. \quad [22]$$

A) Gaussian Model

B) Measured

Amplitude

Amplitude

Phase

Phase

Intensity

Intensity

Figure 9. No target. A) Theoretically predicted and B) Experimentally measured amplitude, phase, and intensity.

A) Gaussian Model

B) Measured

Amplitude

Amplitude

Phase

Phase

Intensity

Intensity

Figure 9. No target. A) Theoretically predicted and B) Experimentally measured amplitude, phase, and intensity.

A) Gaussian Model

B) Measured

Amplitude

Amplitude

Phase

Phase

Phase

Phase

(Top View)

(Top View)

Figure 11. 1/2 Dielectric block - Diagonalized. **A)** Theoretically predicted ($T = 90\%$, $\Delta\theta = 0.9\pi$), and **B)** Experimentally measured amplitude and phase. Within the limitations imposed by the 36 Term Zernike expansion, the formation of the phase shift discontinuity caused by the microscope slide edge is visible down the center of the phase image.

The transform is sensitive to systematic errors including source coherence, pixel distribution and geometry, and SLM phase drift that introduce deviations from the ideal basis functions (a strong endorsement for the use of orthogonal basis sets), and hence difficult to apply in practice. However, the transform was successful in bringing out the phase structure of **Figure 11**. Within the limitations imposed by the 36-term expansion, the formation of the phase shift discontinuity caused by the microscope slide edge is visible down the center of the phase image.

The primary purpose of the experiment is the demonstration of the underlying principles governing FTH imaging. Images shown in **Figures 9–11** do indeed indicate that the basic mechanisms expected, such as Fourier projection, are present and valid. However, care should be taken when interpreting image content as the actual image essentially is filtered through the relatively low-resolution 36-term expansion window. Sharp amplitude and phase structure in the imaged field tends to excite energy into higher spatial modes that will fall outside of the 36-term window and result in image distortion.

4.0 CONSIDERATIONS & EXAMPLE APPLICATIONS

Figure 12. Practical FTH receiver. Note that an all-reflective spatial modulator is used in this example.

4.1. Practical Considerations

Practical improvements based on the simple FTH experiment described in **Section 3** are briefly discussed in sections 4.1.1. – 4.1.5. Practical considerations include active phase-front correction, phase locked detection, pulsed mode correlated double sample, basis functions, and aperture dimensions based on spatial resolution requirements.

4.1.1. Active Phase-Front Correction

The subsystem generating the spatial phase-fronts will require systematic monitoring and calibration for the removal of phase distortion introduced, for example, by alignment error or modulator drift. Inserting an interferometer into the phase-front beam path is one approach to direct wavefront monitoring of short-wavelength sub-mm through optical systems. Referring to the phase-front generation subsystem of Figure 12, as the spatial modulator (SM) scans through pre-programmed phase functions, the interferometer array monitors the phase-front interference distribution and provides corrective feedback through the SM controller. Note that each SM element must be programmable within a spatial phase-shift of at least $\pm \pi$ (for the wavelength of interest) or larger depending on the feedback algorithm implemented.

4.1.2. Phase Locked Detection

Detection of coefficients requires the precision measurement of the I.F. phase and magnitude. Unlike the simple technique applied in the experiment of Section 3, precision high-speed acquisition is accomplished through techniques employing multi-pulse and I.F. phase-locking¹⁴ for measurement of magnitude and phase (α and β).

Figure 13. Imaging resolution may be limited by the fundamental coherence properties governing Laser and RF sources. Correlated sampling algorithms can aid in mitigating the limitations imposed by a source's finite coherence time, τ_c .

4.1.3. Pulsed Mode Correlated Double Sample

FTH imaging resolution can be limited by the fundamental coherence properties governing laser and RF sources. The degradation is a manifestation of transverse amplitude and phase fluctuations on the order of the coherence time¹⁵, τ_c , which is intrinsic to a given coherent source. In essence, source variations cannot be distinguished from image induced modulations, thereby limiting resolution.

What follows is a description of a correlated sampling algorithm that aids in mitigating the limitations imposed by a source's finite coherence. Correlated double sampling (CDS), as applied to FTH, is the process of removing source fluctuations from the target by correlating the outgoing transmitted pulse to the return, target-modulated pulse, through a common reference.

For example, a pulsed transmitter-receiver system acquiring one coefficient $C_{m,n}$ per pulse would implement the following algorithm.

- Measure the Fourier projection coefficient, $C_{Xm,n}$, from the basis function $\Phi_{m,n}$ of the outgoing transmitted pulse. The measurement must be performed within the sources coherence time τ_c .
- Measure the Fourier projection coefficient, $C_{Rm,n}$, from the basis function $\Phi_{m,n}$ of the target-modulated return pulse (after a transit time τ_t).
- Subtract the common transverse amplitude and phase error:

$$C_{m,n} \Phi_{m,n} = (C_{Rm,n} - C_{Xm,n}) \Phi_{m,n} \rightarrow C_{m,n} = C_{Rm,n} - C_{Xm,n}.$$

As both the outgoing and return pulses are compared to a common reference, it is essential that the reference field is properly conditioned (for example, spatially filtered) and stationary over the transit time τ_t . Note that as an additional benefit to employing CDS, any stationary spatial phase or amplitude structure in the reference field will be subtracted out.

4.1.4. Basis Functions

FTH receivers, in general, may implement basis functions in which both amplitude and phase are modulated. Complex modulators are practical only if they can achieve sufficiently high modulation rates and are readily calibrated. Systems in which the phase is modulated through a refractive/reflective element or a RF phased array are referred to as pure phase modulators. From **Equation 12**, pure phase modulation requires the phase function argument

$$\theta(x, y) = i \ln \left(\frac{1}{\rho'(x, y)} \Phi_{Ref}(x, y) \right), \quad [23]$$

remain real for synthesis with a refractive or reflective spatial modulator. For example, the familiar two-dimensional Cartesian exponential Fourier series (x, y normalized to a unit square)

$$\Phi_{m,n}(x, y) = e^{-i 2\pi(m x + n y)}, \quad [24]$$

possesses the real phase function

$$\theta(x, y) = 2\pi(m x + n y). \quad [25]$$

Implementation of **Equation 25** suggests a spatial phase modulator generating an x, y phase pattern across the modulator with slope proportional to m, n respectively. Furthermore, as coherent fields are longitudinally periodic, the spatial phase “wraps around” every 2π , limiting the dynamic modulation requirements to $\pm \pi$.

4.1.5. Aperture Diameter

Field imaging, as does any other electromagnetic imaging technology, requires the appropriate matching of the receiver aperture diameter to a given set of resolution requirements. To resolve a target feature size, δ , at range R and wavelength λ will require a minimum aperture diameter of¹⁶

$$D_o = 2.44 R \frac{\lambda}{\delta} \quad [m]. \quad [26]$$

4.2. Example Applications

Several example LADAR applications exploiting spatial field imaging are presented in **Figures 14 – 16**. **Figures 14 and 15** illustrate spatial and Doppler imaging concepts that enable optimal target discrimination and/or signature detection. **Figure 16** provides an example of clutter suppression through spatial field filtering. Field based spatial filtering can potentially aid in discriminating a desired target signature from the unwanted background clutter and noise, provided, target and clutter signatures are spatially distinguishable. The optical clutter suppression principles of **Figure 16** are similar to techniques already practiced in current RF RADAR systems deploying phased array receivers.^{17, 18}

Figure 17 demonstrates the utility of spatial phase imaging. Direct and unambiguous measurement of wavefront distortion may be applied to the development of self-correcting, deployable optical apertures. Motivating **Figure 17**, is the recognition that large-area, lightweight, near-diffraction limited optical apertures deployed as a reduced volume payload represents an important ingredient to future low-cost space-borne applications - i.e. large monolithic apertures are excessively heavy and bulky, and prohibitively expensive to launch.

As a practical note, the reflected phase fronts of examples **Figure 14 - 17** may exceed a wavelength in depth, leading to $\pm \pi$ phase ambiguities in the retrieved images. For applications requiring preservation of phase depth, the ambiguities may be resolved through multiple wavelength interferometry¹⁹ where the target is illuminated and imaged, preferably simultaneously, with two or more wavelengths resulting in the two-dimensional synthetic phase image:

$$\phi_{\lambda_s}(x, y) = \phi_{\lambda_1}(x, y) - \phi_{\lambda_2}(x, y), \quad \text{where } \lambda_s = \frac{\lambda_1 \lambda_2}{|\lambda_1 - \lambda_2|}. \quad [27]$$

The technique may also be used to reduce image phase sensitivity due to fluctuations resulting from moving target dynamics (target scintillation).

5.0 Summary

We have presented the concept of a spatial Fourier projection operator and how it applies to field imaging via Fourier decomposition using familiar heterodyne detection principles. A simple experimental setup, based on a HeNe laser and a 69 element spatial phase modulator, demonstrated the underlying principles governing field projection theory and FTH imaging.

Figure 14. Field imaging – spatial signature discrimination. Field imaging may be a useful tool to aid or enhance LADAR target classification and identification. Real-time configurable spatial reference functions permit the synthesis of adaptive spatial filters and/or optimal detection algorithms.

Figure 15. Doppler imaging – velocity field discrimination. Spatially distinguishable targets may be velocity resolved through the (temporal) frequency filtering of Doppler shifted spatial Fourier coefficients, $C_{l,n}$. l is the Doppler shifted index representing the l^{th} I.F. bandpass frequency, $\Delta\omega$, (see Equations 13-14) .

Figure 16. Spatial field filtering - clutter suppression. Provided the target signature is spatially distinguishable from the clutter signature, field based spatial filtering can potentially aid in discriminating the desired target(s), Φ_{Target} , from the unwanted clutter and noise, Φ_C . Shown in the above example, spatial filtering is accomplished by first pre-sampling the image field, Φ_{Image} , followed by the construction of a reference set with components orthogonal to the clutter spatial signature. The spatial filter coherently nulls (through orthogonal field projection) the lower-order spatial clutter components at the detector (before entering the I.F. circuitry), while passing the higher order target signature.

Figure 17. Spatial phase imaging. A large-area, lightweight, near-diffraction limited optical aperture is deployed as a reduced volume payload reducing costs over equivalent heavy and bulky monolithic aperture. Field imaging permits direct and unambiguous measurement of wavefront distortion. A control algorithm translates measured wavefront distortions into a sequence of error vectors, which are applied to the aperture's electro-mechanical actuators and electro-optic control surfaces forcing the optical distortion to zero.

Summary (Cont.) Of further research interest is the development of the generalized field projection operator (**Equation 16**). As the projection may be employed in a matched filter configuration, reference and image field states may be tailored to introduce detection uniqueness. Important research issues to be addressed include speckle mitigation, coherent imaging systems based on "off the shelf" lasers and focal plane arrays, and heterodyne systems maintaining 100% detection efficiencies in the presence of random and systematic spatial phase distortion.

REFERENCES

- ¹ M. C. Roggemann and B. Welsh, *Imaging Through Turbulence*, CRC Press, 1996.
- ² M. Born and E. Wolf, *Principles of Optics*, Cambridge University Press, 6th Ed., 1980.
- ³ J. W. Goodman, *Introduction to Fourier Optics*, McGraw-Hill, 1968.
- ⁴ G. O. Reynolds, J. B. DeViles, G. B. Parrent and Brian J. Thompson, *Physical Optics Notebook Tutorials In Fourier Optics*, SPIE and American Institute of Physics, pp. 94-96, 1989.
- ⁵ C. A. Balanis, *Antenna Theory Analysis and Design*, pp. 797-801, John Wiley & Sons, 2nd Ed., 1997.
- ⁶ J. D. Jackson, *Classical Electrodynamics*, John Wiley & Sons, 2nd Ed., 1975.
- ⁷ S. C. Cohen, "Heterodyne Detection: Phase Front Alignment, Beam Spot Size, and Detector Uniformity," *Applied Optics*, Vol. 14, No. 8, pp. 9153-1958, Aug. 1975.
- ⁸ S. Fowler, G. W. Kamerman, and G. Lawson, "Analysis of Heterodyne Efficiency for Coherent Laser Radars," *SPIE Applied Laser Radar Technology*, Vol. 1936, pp. 137-146, 1993.
- ⁹ F. B. Hildebrand, *Advanced Calculus for Applications*, pp. 203-209, Prentice-Hall, 2nd Ed., 1976.
- ¹⁰ C. A. Balanis, *Antenna Theory Analysis and Design*, pp. 309-324, John Wiley & Sons, 2nd Ed., 1997.
- ¹¹ J. Y. Wang and D. E. Silva, "Wave-Front Interpretation With Zernike Polynomials," *Applied Optics*, Vol. 19, No. 9, pp. 1510-1513, May 1980.
- ¹² K. Chang, *Handbook of Microwave and Optical Components Vol. 3*, pp. 28-32, John Wiley & Sons, 1990.
- ¹³ O. K. Ersoy, *Fourier-Related Transforms, Fast Algorithms and Applications*, Prentice Hall, 1997.
- ¹⁴ F. M. Gardner, *Phaselock Techniques*, John Wiley & Sons, 1979.
- ¹⁵ J. W. Goodman, *Statistical Optics*, John Wiley & Sons, 1985.
- ¹⁶ B. J. Cooke, B. E. Laubscher, M. Cafferty, N. L. Olivas, M. J. Schmitt, K. R. Fuller, R. M. Goeller, D. E. Mietz, J. J. Tice, R. K. Sander, J. L. Vampola, S. L. Price, and I. Kasai, "Analysis and Design Methodology for the Development of Optimized, Direct-Detection CO₂ DIAL Receivers," *SPIE Infrared Instrumentation VII*, 1997.
- ¹⁷ M. I. Skolnik, *Introduction to Radar Systems*, pp. 547-553, McGraw-Hill, 1980.
- ¹⁸ K. Chang, *Handbook of Microwave and Optical Components Vol. 1*, pp. 675-702, John Wiley & Sons, 1989.
- ¹⁹ L. McMackin, D. G. Voetz, and M. P. Fetrow, "Multiple Wavelength Heterodyne Array Interferometry," *Opt. Express* 1, 1997.