SUPERCONDUCTING SEXTUPOLES AND TRIM QUADRUPOLES FOR RHIC*

Conf-950512--143

P. Thompson, M. Anerella, G. Ganetis, A. Ghosh, A. Greene, R. Gupta
A. Jain, E. Kelly, M. Lindner, G. Morgan, J. Muratore, W. Sampson, P. Wanderer, E. Willen

RHIC Project

Brookhaven National Laboratory, Upton, NY 11973

RHIC requires 288 sextupole and 72 trim quadrupole magnets. These iron poletip superconducting magnets have been constructed by Everson Electric Co. Room temperature field measurements have been completed for 75% of these magnets with acceptable results. Approximately 15% of them have been tested at 4.6 K for maximum (quench) current. The quench performance for the early magnets was good and improved to excellent during the production run. These magnets have more than 100% margin at quench.

I. INTRODUCTION

The Relativistic Heavy Ion Collider (RHIC) will be a colliding beam facility with design energy of 100 X 100 GeV/u for heavy ions. The two accelerator/storage rings are divided into "regular arcs" and intersection regions. A set of 288 sextupole elements are necessary to reduce the natural chromaticity ($\chi \sim -42$) and correct sextupole field imperfections in the dipole magnets.

These are positioned at every quadrupole in the regular arcs, and have a design strength of 588 Tesla/meter with an inner bore of 80 mm and length of 750 mm. The detailed design of these "superferric" magnets has been published previously¹ In addition, to vary the β in the interaction regions 72 trim quadrupoles are required. These are assembled with quadrupoles Q4, Q5, and Q6. Their overall dimensions are identical to the sextupoles and their detailed construction is very similar. This paper will emphasize the test results and design differences of the quadrupoles.

II. DESIGN

Table 1 lists the basic parameters of these magnets. They consist of racetrack layer wound coils mounted on iron poletips. The method used in the sextupoles for securing the coils proved somewhat cumbersome. For the quadrupoles, a projection was added to the iron yoke so that the coil fits in a slot between this projection and the poletip (see Fig. 1). A thin non-ferrous spring is inserted between the poletip and the coil to hold it against the support projection. There is no real "prestress" in this design. A small tab is placed over the ends of the coils so that they can not move radially but the ends are unsupported against the Lorents forces.

Table 1: Parameters of RHIC Sextupoles and Trim Quadrupoles

Parameter	Value	
	Sextupole	Quadrupole
Wire Diameter	0.508mm	0.508mm
Copper/SuperConductor	3:1	3:1
Ic(2.0 T, 4.22 K)	230 A	230 A
Turns per pole	200	200
Clear Bore	80 mm	80 mm
Length	750 mm	750 mm
Design Current	100 A	100 A
Design Strength	588 Tesla/meter	22 Tesla
Quench Current	220 A	205 A
Quench Strength	780 Tesla/meter	37 Tesla
Inductance at 100 A	530 mH	590 mH
Number for RHIC	288	72

Figure 1: Cross Section of RHIC Trim Quadrupole.

A. Magnetic Design

Since these magnets operate with a pole tip field of ~ 1.1 Tesla, iron poletips were used. At low field, the poletip dominates the field, reducing the sensitivity

Figure 3: Sextupole Notch Harmonics

to coil location errors. For the sextupole, because of mechanical limitations, the actual poletip is narrower than optimum. This results in very noticeable saturation. For the trim quadrupole the poletip was widened to reduce this saturation. The poletip was also shaped and a hole was put in it to further reduce the saturation. The coil support projection of the yoke does not affect the field. For ease in coil manufacture, the ends are semi-circular and generate acceptably small error fields.

III. QUENCH RESULTS

The results of quench testing are summarized in Fig. 2. Note that only the last and the worst (usually the first) quenches are plotted. For the initial sextupoles the worst quench was at least 80% of the conductor limit. As production progressed, a problem developed with the coil support hardware. This subset typically displayed a first quench in the range 55 to 75% of I_{cs} and very rapid training to short sample. At about magnet SRE260, a problem developed in the epoxy potting of the coils. This group of magnets trained slowly, and many of them were not trained to short sample. At magnet SRE280 all known problems were fixed and the quench plot looks much better.

For the trim quadrupoles, the support mechanism was much more robust and the problems of quality control in production were understood. Twelve quadrupoles have been tested with only one quench below (92%) the conductor limit. Except for the epoxy problem sextupoles (which are being 100% tested), only 10% of these units are subjected to quench testing.

Table 2: Sextupole Integral Field Harmonics measured at 0.25 A - 300 magnets

Harmonic	Calculated	Measured	
	bn only ¹	bn	an
B2/A(T/m*A)	8.66	8.69(0.013)	...
b3	0	-0.27(1.14)	-0.08(2.82)
b4	0	-4.58(1.37)	-0.14(1.17)
b5	0	0.24(0.21)	0.15(1.01)
b6	0	-2.67(0.55)	-0.12(0.54)
b8	-93.15	-90.3(0.19)	-0.31(0.12)

¹...All skew(an) harmonics are calculated to be 0
bn is 10^{-4} of the Sextupole field at R= 25mm
The measured values are the mean of 300 magnets.
The rms spread is given in ()

Figure 2: Quench Histories

IV. FIELD QUALITY -SEXTUPOLE

All of these magnets are measured at room temperature at 0.25 A. A small sample is also measured at 4.5 K with currents ranging up to 150 A. There is good agreement between the two measurement techniques. Table 2 shows the low current integral field measurements. The non-negligible b0 and b4 terms are probably due to the dipole symmetry of the yoke assembly. Fig. 4 shows a trend plot of the transfer function. There appear to be steps associated with the fixes in the assembly technique. The allowed harmonics measured in 49 magnets at 4.6 K are presented in Fig. 5. The strong saturation arises from the "neck" of the poletip which is narrower than optimum. The reproducibility is apparent.

A. Anomalous Behavior

The b0 and b4 data in Fig. 3 show a distinct "notch" at 45 A, this may be a manifestation of the dipole

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, make any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

**Portions of this document may be illegible
in electronic image products. Images are
produced from the best available original
document.**

symmetry of the assembly. This has persisted through 300 magnets and appears in both up and down ramps. For mechanical compatibility with the rest of the magnets, the sextupole yoke is assembled in two pieces with an overall dipole symmetry. These harmonics are dipole symmetric, but why they should have this reproducible variation with excitation is unknown.

V. FIELD QUALITY -QUADRUPOLE

The low current measurements for the trim quadrupole are presented in Table 3. The b3 term is probably a manifestation of the dipole assembly symmetry. The difference between calculation and measurement for b5 is unexpectedly large, however this harmonic is well within the accelerator requirements.

Figure 4: Sextupole Transfer Function History

Figure 5: Sextupole Allowed Harmonics.
Total 49 Magnets Measured.
average=dashed curve. calculation=solid curve.

Harmonic	Calculated	Measured	
	bn only ¹	bn	an
B1 (Tesla/A)	0.2437	.2357(0.0002)	...
b2	0	0.692(0.684)	-0.837(1.510)
b3	0	-3.98(0.581)	0.038(0.197)
b4	0	-0.031(0.168)	0.063(0.197)
b5	+2.5	-10.22(0.247)	-0.157(0.114)
b9	-0.73	-0.816(0.028)	0.001(0.006)

¹...All skew(an) harmonics are calculated to be 0
bn is 10⁻⁴ of the Quadrupole field at R= 25mm
The measured values are the mean of 53 magnets.
The rms spread is given in ()

Table 3: Integral Field Harmonics for Trim Quadrupoles
Total 53 Magnets. 0.25 A measurements.

Figure 6: Trim Quadrupole Allowed Harmonics Saturation Behavior
Total 11 magnets measured.

VI. CONCLUSIONS

Almost 400 of these two types of magnets have been built. The racetrack coil mounted on an iron poletip design has proven straightforward for commercial construction. The field quality of all the magnets tested has been acceptable without any iteration. With the final design used for the trim quadrupoles the quench performance is essentially perfect.

7. REFERENCE

1. M. Lindner et al. *Construction Details and Test Results from RHIC Sextupoles*, IEEE Trans. on Magnetics, Vol. 30, No 4, pp 1730-3 (1994).

*Work supported by the U.S. Department of Energy under Contract No. DE-AC02-76CH00016