LAWRENCE
LIVERMORE
NATIONAL
LABORATORY

Multi-Channel Time-Reversal Communications in a Highly Reverberative, Environment

J. V. Candy, B. L. Guidry, A. J. Poggio, C.
Robbins, C. Kent

May 20, 2004

147th Meeting Acoustical Society of America
New York, NY, United States
May 24, 2004 through May 28, 2004

This document was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor the University of California nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or the University of California. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or the University of California, and shall not be used for advertising or product endorsement purposes.

***MULTI-CHANNEL
TIME-REVERSAL COMMUNICATIONS
IN A
HIGHLY REVERBERATIVE, ENVIRONMENT***

147th Meeting
Acoustical Society of America
24 May 2004
New York, NY

J. V. CANDY, B. L. GUIDRY, A. J. POGGIO, C. ROBBINS, C. KENT

This work was performed under the auspices of the U.S. Department of Energy by University of California, Lawrence Livermore National Laboratory under Contract W-7405-Eng-48.

ORGANIZATION

- ***INTRODUCTION***
- ***TIME-REVERSAL***
- ***BACKGROUND***
- ***EXPERIMENT***
- ***RESULTS***
- ***SUMMARY***

INTRODUCTION

T/R offers an alternate solution to the communications problem in hostile environments

PROBLEM:

*Transmit information in a hostile medium (mpath, mscatterers, reverb, noise)
and extract it with minimal symbol/bit error*

APPROACH:

Time reversal (T/R) communication system

(a) PROBLEM:

HOST

(b) SOLUTION:

T/R communication systems can:

- **mitigate** multipath, multiple scattering, inhomogeneous effects
- **focus** signal energy at a client station through a hostile medium
- provide a **secure** link (unique medium function) from host-to-client
- **be deployed in** point-to-point (P2P) or array configurations (A2P, A2A)
- **compliment** existing communications technology
- **be implemented** in software

TIME-REVERSAL

A T/R system is an intelligent, *optimal*, space-time, matched-filter that “learns” the medium

The medium (Green's function) provides **UNIQUE** paths (channels) from the host array to each client station---this is the key in T/R communications

T/R signal processing can be applied at either the transmitter or receiver:

TRANSMITTER

RECEIVER

T/R Receiver Realization I: G-function on Tx

ANALYSIS: T/R Receiver / Operation

$$\mathbf{z}_{i\hat{g}_m X}(t) = \mathbf{G}(\mathbf{r}; t) * \mathbf{x}(t) = \mathbf{G}(\mathbf{r}; t) * (\hat{\mathbf{g}}_m(-t) \otimes i(t))$$

$$\mathbf{z}_{i\hat{g}_m X}(t) = \begin{bmatrix} \mathbf{g}_1^T(t) \\ \vdots \\ \mathbf{g}_M^T(t) \end{bmatrix} * (\hat{\mathbf{g}}_m(-t) \otimes i(t)) = \begin{bmatrix} \mathbf{g}_1^T(t) * \hat{\mathbf{g}}_m(-t) \otimes i(t) \\ \vdots \\ \mathbf{g}_M^T(t) * \hat{\mathbf{g}}_m(-t) \otimes i(t) \end{bmatrix} = \begin{bmatrix} \sum_{\ell=1}^L g_{1\ell}(t) * \hat{g}_{m\ell}(-t) * i(t) \\ \vdots \\ \sum_{\ell=1}^L g_{M\ell}(t) * \hat{g}_{m\ell}(-t) * i(t) \end{bmatrix}$$

$$\mathbf{z}_{i\hat{g}_m X}(t) = \begin{bmatrix} \sum_{\ell=1}^L C_{g_1 \hat{g}_m}(\ell; t) * i(t) \\ \vdots \\ \sum_{\ell=1}^L C_{g_M \hat{g}_m}(\ell; t) * i(t) \end{bmatrix} = \begin{bmatrix} \bar{C}_{g_1 \hat{g}_m}(t) \\ \vdots \\ \bar{C}_{g_M \hat{g}_m}(t) \end{bmatrix} \otimes i(t)$$

$$z_k(t) \equiv z_{i\hat{g}_m X}(k; t) = \bar{C}_{g_k \hat{g}_m}(t) * i(t)$$

$$z_k(t) = \begin{cases} \bar{C}_{g_m \hat{g}_m}(t) * i(t) & k = m \\ \bar{C}_{g_k \hat{g}_m}(t) * i(t) & k \neq m \end{cases}$$

T/R Receiver Realization III: G-function on Rcv

ANALYSIS: T/R Receiver III Operation

$$\mathbf{R}_{i\hat{g}_m R}(t) = z_m(t) * \hat{\mathbf{g}}_m(-t) = \left(\mathbf{g}_m^T(t) * \mathbf{i}(t) \right) * \hat{\mathbf{g}}_m(-t)$$

$$\mathbf{R}_{i\hat{g}_m R}(t) = \sum_{\ell=1}^L C_{g_m \hat{g}_m}(\ell; t) * \mathbf{i}(t) = \bar{C}_{g_m \hat{g}_m}(t) * \mathbf{i}(t)$$

$$R_{i\hat{g}_m R}(t) = \left(\mathbf{1}^T \times \mathbf{i}(t) \right) * \bar{C}_{g_m \hat{g}_m}(t) = L \times i(t) * \bar{C}_{g_m \hat{g}_m}(t)$$

THE EXPERIMENT

We developed A2P ACOUSTICS experiment in a hostile, highly reverberant free space environment to evaluate the T/R receiver:

The experiment was accomplished with:

- SOURCE/AMP: B&K 4296/2716 20dB
- PILOT/CODE: Analogic 2020 arbitrary waveform generator
- MICROPHONE: B&K 2716
- DIGITIZER: LeCroy 8-bit

• -----

- PILOT: Chirp pulse swept from 0.8-2KHz
- CODE: BPSK 0.1KHz BW
- MODULATION: AM center frequency at 1.207KHz
- SAMPLING FREQUENCY: 10KHz
- SYMBOL/BIT RATE: 100 samples/symbol

T/R acoustic receiver for stairwell experiment

Typical T/R Receiver Output P2P

RESULTS

T/R RECEIVER I: Focuses on Each Client

T/R Receiver I: Performance

MEASURED GREENS' FUNCTIONS: Client #1

T/R RECEIVER III: Focus on Client Receiver

T/R Receiver III: Performance

Receiver Type 3, Station #1

Receiver Type 3, Station #2

MEASURED GREENS' FUNCTIONS: Client #2

Greens' Functions

Spectral Functions

T/R RECEIVER I: Greens' Function Analysis

Green function xcorr for client station #1

Green function xcorr for client station #2

Proof-of-principle experiments have shown great results!

- *standard receivers try to "ignore" multipath by using only direct path information (time gating)*
- *arrays have been recently introduced into comms area, but not intelligent (learn Green's function) T/R arrays*

BUT

- *we have shown for array-to-point (A2P) communications the concept of a time-reversal (T/R) receiver is **capable** of operating successfully in a highly reverberative environment*

Summary:

- We have discussed the idea of **communications** in a hostile environment using *time-reversal processing* with *multi-channel* (intelligent array) *signal processing*
- We have discussed the approach using **theory**, **simulation**, and **experiment** to evaluate the performance of T/R receiver realizations
- We have using a set of performance metrics based on symbol error to perform the evaluations

T/R acoustic receiver performance comparison (ensemble average) of Symbol Error vs. Threshold

We define the following terms:

- Symbol Error - error between true symbol sample transmitted and sample extracted by recvr (made up of bits)
- Bit Error - error between true bit transmitted and actual bit extracted by recvr
- Open Communications - both host & clients can broadcast openly in the environment (city, urban env., etc.) and everyone can listen
- Secure Communications - both host & client broadcast but NO ONE can listen
- Covert Communications - host broadcasts & ONLY client can listen

T/R processing is accomplished spatially or temporally:

MEDIUM: $z(t) = g(r;t) * i(t) \Leftrightarrow Z(\omega) = G(r;\omega) \times I(\omega)$

Temporal

In the time domain, the T/R processor is:

$$\hat{i}(t) \approx z(t) * \hat{g}(r; -t) = [g(r;t) * \hat{g}(r; -t)] * i(t) = C_{gg}(t) * i(t)$$

While in the temporal frequency domain it looks more familiar:

$$\hat{I}(\omega) = Z(\omega) \times G^*(r; \omega) = [G(r; \omega) \times G^*(r; \omega)] \times I(\omega) = |G(r; \omega)|^2 \times I(\omega)$$

Spectral