MOR-6

MORSE-L

MASTER

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency Thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

UCID - 16680

This is an informal report intended primarily for internal or limited external distribution. (The opinions and conclusions stated are those of the author and may or may not be those of the laboratory.) This report is not to be given additional external distribution or cited in external documents without the consent of the author or LLL Technical Information Department.

LAWRENCE LIVERMORE LABORATORY

University of California/Livermore, California

MORSE-L; A SPECIAL VERSION OF THE MORSE PROGRAM DESIGNED TO
SOLVE NEUTRON, GAMMA, AND COUPLED NEUTRON-GAMMA PENETRATION PROBLEMS

Unclassified

Tom Wilcox

September 1, 1972

NOTICE

This report was prepared as an account of work sponsored by the United States Government. Neither the United States nor the United States Atomic Energy Commission, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness or usefulness of any information, apparatus, product or process disclosed, or represents that its use would not infringe privately owned rights.

MASTER

September 1, 1972

MOR-6

MEMORANDUM

TO: Distribution

FROM: T. P. Wilcox

SUBJECT: MORSE-L, A Special Version of the MORSE Program
Designed to Solve Neutron, Gamma and Coupled
Neutron-Gamma Penetration Problems

I INTRODUCTION

MORSE-L is a computer code which uses the Monte Carlo method to transport both neutrons and gamma rays. The special features of this code make it particularly suitable in the solution of deep penetration problems (many mean-free-paths of material), problems with a large geometrical attenuation, and problems involving coupled neutron-gamma reactions. As such, it supplements the other LLL codes available for transport problems. The basic MORSE program⁽¹⁾, and the SAMBO output module⁽²⁾, both which were obtained from the Oak Ridge National Laboratory, were modified in order to make a single code which was useful for a specific class of transport problems. The ability to do criticality problems was deleted in this version, but kept in the MORSE-C version⁽³⁾. Some of the changes made from the original code are very briefly listed under the following three categories:

1. Improved physics:

- a. Additional methods of estimating the flux and current from the random walk have been incorporated into the code. Eight different methods may now be utilized.
- b. A general source routine was written so that most sources may easily be simulated by the code without having to write a special source program.
- c. The code now makes the choices of splitting, Russian roulette, and production weights. Rather than having to input quantities specifying the particle weights at which various processes are to be accomplished, the code now expects simple input parameters expressing the amount of a process to be done. The weights are continuously calculated in the code using the solutions already obtained.
- d. When following gamma rays, the point flux estimator now makes use of an analytical form for Compton scattering.
- e. The albedo options have been expanded to allow more than one albedo per problem and to allow a description of an albedo to be made by using input tables.
- f. Additional checks are made on the statistical accuracy of the results.

2. Improved ease of operation:

- a. The code's input was reorganized in order to make problem setup more logical and easier. A free-form input format was adopted which allows the use of key words in the input rather than numerical flags. The output was made consistent with the input.
- b. Many input quantities are now read from a prepared library tape in order to reduce the amount of required input.
- c. The output results are automatically plotted using the CRT features of our computers.

- d. Input to the general geometry package was modified in order to make it much simpler. Specific input equations needed by this package for the commonly used surfaces can be formulated by the code thus reducing errors caused by the user's lack of knowledge in the field of analytic geometry. Simulated three dimensional CRT pictures of the defined geometry are now available on option.
3. Improved machine operations:
- a. Increased speed was made possible by the use of registers and elimination of unneeded subroutine calls.
 - b. The program was broken into a main-overlay-segment version in order to reduce required core storage.
 - c. Cross section data may now be stored in a packed mode in order to accomodate larger problems. The entire cross section module was altered to reduce core storage requirements.

This memo will first briefly outline the Monte Carlo process as it is used in this code. The necessary items needed in order to run a problem are then described followed by a very detailed description of the required problem input. The output is briefly explained and a sample problem provided in order to illustrate the concepts that have been presented.

A detailed description of the available cross section libraries will be given in a subsequent MORSE note and are, consequently, not described in this memo. It is also anticipated that additional memos will be written describing in more detail the use of the Monte Carlo techniques available in MORSE-L.

The author is indebted to those patient users who, over the last year, have run preliminary versions of this code armed only with blackboard descriptions or pages of unreadable handwritten notes. Their persistence has given to future users a code freed from many errors and a write-up which may be understood.

II. MONTE CARLO METHOD

It is not intended in this section to present a theoretical derivation of the Monte Carlo solution of the Boltzmann equation nor is it intended to list every equation used in MORSE-L. Both of these fields are reasonably well taken care of in references (1) and (2). What we hope to accomplish here is to give the user a feeling for how MORSE-L works. If he can grasp that understanding, he will have control over the code and will know what must be done to insure a better and faster solution to his problems.

To start with, MORSE-L solves the "group" integrated Boltzmann equation. This implies that the equation has already been integrated over energy to form a series of energy groups. This is similar to the discrete ordinates (S_N) codes which have been widely used over the years. It implies that the code does not know about the existence of 10 MEV neutrons, for example, but only knows about the existence of neutrons in a group between, say, 9 to 12 MEV. Input cross section data describes the average reaction in a group and is no longer point wise in nature. Standard group structures have been assumed for the purpose of generating cross section data and for general convenience but the number of groups that should be used to obtain a good solution to any given problem should be determined by that particular problem. MORSE-L may be run with as few as one group or as many groups as desired within machine storage limitations.

MORSE-L does not keep track of the cross sections for reactions (i.e., inelastic or elastic neutron scattering) nor does it contain built-in equations describing the physics of the scattering for such reactions. All data describing scattering is input in the cross section sets themselves. Thus, the code may treat either neutrons or gamma-rays since it does not have to know that there is any real difference between the two (the only reason it is told there is a difference is to obtain the correct cross sections from the library tape and to save machine storage space). The angular scattering cross sections are described by supplying terms in a Legendre expansion; i.e.:

$$\sigma(\mu) = \sigma^{\ell=0} P_0(\mu) + \sigma^{\ell=1} P_1(\mu) + \sigma^{\ell=2} P_2(\mu) + \dots + \sigma^{\ell=L} P_L(\mu)$$

where μ is the cosine of the polar scattering angle and $P_n(\mu)$ is the Legendre polynomial. Using this system, the properties of a mixture are easily obtained from its isotropic composition. Only data for the complete mixture is retained in the machine. This eliminates the need to store large blocks of cross section information.

The Monte Carlo process tends to follow what happens in nature. A particle is generated at the described source location. This particle has a known position, energy group, age (time), and initial direction. These are determined from distributions specified by the user. This particle will then be followed as it goes through a "random walk" through defined space. The first step, after the source has been determined, is to choose from an exponential distribution the number of mean-free-paths the particle will go before it has its first collision. Using this data with the geometrical description of what materials exist in space and the cross section information that goes with each material, the location of this collision site is determined. The physics of the scattering process at this collision site is then used to determine at what direction and with what energy a scattered particle will emerge. A new value is chosen for the number of mean-free-paths and a new collision site chosen. Thus the movements of the particle are followed as it travels through space.

A word of explanation should be made about the scattering process and how MORSE-L treats it. In nature, a particle which undergoes a collision can scatter so that it comes out of the collision with a new energy and direction (usually the two are related to each other), or it may be absorbed and not come out at all, or it may undergo a $(n,2n)$ or pair production reaction so that two (or more) particles are produced and each emerges with its own new direction and energy. In MORSE-L, one particle always comes out of each scattering reaction (forget, for the minute, fission and the neutron to gamma processes). It is obvious that this particle no longer represents a single particle as it exists in nature. For this reason, a source particle is assigned a statistical weight, usually one. At every collision this weight is altered so that the new weight represents the number of real particles (as existing in nature) that the simulated Monte Carlo particle represents. At high neutron and gamma energies, this weight usually becomes greater after a collision due to $(n,2n)$ and pair production reactions. The description of the energy and angle of the scattered particle in this case properly describes all of the new particles produced. At low neutron and gamma energies, the weight rapidly decreases due to absorption. This method of survival weighting tends to keep particles in existence and provides better statistical results when a high percentage of reactions result in absorption.

The collision routine considers the energy group of the incident particle and the material in which the collision occurs. By choosing a random number and by looking at the tables of cross section data, the new energy group for the emitted particle is found. Now the input angular description of the scattering cross section has been used to generate a series of polar angles (really the cosines of these angles) and the probability of going to each. For each group to group transfer, $(L+1)/2$, where L is the maximum order of the Legendre expansion, possible angles exist. A new random number is chosen to determine the proper polar angle from those available. The azimuthal scattering angle is then chosen uniformly. This means for scattering in energy group 1 (highest energy) of a 30 group P_3 set of cross sections, 60 possible polar scattering angles exist. It is possible to devise problems in which this method of scattering through discrete polar angles can produce erroneous results⁽⁴⁾. It is also possible to devise ways in which to solve these same problems with MORSE-L without encountering difficulties.

Fission and secondary gamma production are treated separately in MORSE-L. The amount of particles produced for these types of reactions are controlled by production parameters supplied by the user. This is a method of controlling the number of such particles produced (the sum of their statistical weights, however, always represents the physically correct value) and, therefore, the statistical accuracy of the results. MORSE-L will not handle problems in which the multiplication of a fissionable system is greater than, or even close to, one. The input section describing production parameters describes in more detail how this control is performed.

The above description of the random walk process gives a reasonable idea of what the code does. For problems in which results are desired close to a specified source, the above techniques are adequate to produce good results. For problems, however, in which answers are required at greater distances (either physically or in terms of mean-free-paths) from the source, the use of the simple Monte Carlo techniques above will not produce acceptable answers in reasonable lengths of computing time. One, or more, of the following techniques can then be used to modify the random walk process in order to spend more computing time on useful histories and less on those which are unimportant.

The easiest method to use is Russian roulette. In this method, particles which have a low statistical weight, compared to other particles in the same location and of the same energy, undergo a Russian roulette game. Those losing the game are killed (i.e., they are no longer followed) while those winning have their statistical weight increased to represent those which have been killed and are then followed further. The choice of playing this game as well as the probability of survival are dependent upon the energy group of particles coming out of a collision and the geometrical position of the collision. It is normal practice to play this game in the lower energy group of both neutron and gamma problems to weed out very low weight particles. It is also possible to kill off all particles in a geometrical position where random walk histories contribute nothing to the desired result.

Opposite to Russian roulette, splitting provides a way of increasing the number of particles which have gone to some point in space. If, at a given geometrical position and given energy, a particle coming out of a scattering collision has a statistical weight greater than a predetermined value, the particle can be divided into two particles, each with half the statistical weight, which will be followed independently. Generally, splitting is used at high neutron or gamma energies.

Age termination is a way to terminate random walks when the age of a particle gets bigger than a fixed value. It saves computing histories when the information is not needed. In the same way, lower energy cut-offs are used to accomplish similar results.

Occasionally problems are found where there is a high probability that most of the particles will not react and will simply leak from the defined geometry into space. In this case it is possible to alter the code so it will not allow leakage to take place. At the start of every random walk trajectory, the number of mean-free-paths to the outside of the defined geometry is evaluated. The statistical weight of the particle is then reduced by the factor $(1 - \exp(-mfp))$, which represents the non-leakage probability, and the new collision site is then chosen in such a manner that it is within the system. Meaningful histories are therefore generated without the need to produce an excessive number of source histories.

In a number of places within the code, it is possible to bias a selection which is based upon the probabilities generated in nature. We offer the following illustration to show how this is done. Assume that the following distribution exists for the relative intensity of three point sources.

<u>Position</u>	<u>Probability</u>
1	0.50
2	0.25
3	<u>0.25</u>
	1.00

Under normal, unbiased conditions, particles born in each location will be assigned a statistical weight of one. Fifty percent of the time a choice of position one will be made, twenty-five percent of the time at position two, and twenty-five percent at position three. Note that the sum of the probabilities times the initial statistical weight is one. Now assume that particles produced at position one are only one-fourth as effective in producing a detector response as those of position three while position two particles are only half as effective as those at position three. In order to not generate as many particles at positions one and two, as compared to position three, we will bias this source distribution thusly:

<u>Position</u>	<u>Probability</u>	<u>Bias</u>	<u>Modified Probability</u>	<u>Statistical Weight</u>
1	0.50	0.25	0.25	2.00
2	0.25	0.50	0.25	1.00
3	0.25	1.00	0.50	0.50

The modified probability is simply the real probability times the bias normalized to a total of one. The statistical weight corrects things so that the modified probability times the weight equals the original (real) probability. This new distribution will produce twice as many particles at position three but will give each a statistical weight of only a half. Only half as many will be produced at position one but their weight will be two. Thus, more problem effort will be expended generating and following particles which are, if the bias was chosen correctly, more important to the desired result while less effort is spent on undesired particles. If enough computation time is taken, problems using either the natural probability or the biased probability will yield the same results. MORSE-L allows biasing to be made in all phases of the source description (position, energy, time and angle) and in the group to group transfer in the scattering process.

The most powerful technique available for deep penetration problems is the exponential transformation. (A review of this method appears in reference 5). In general, this method stretches the path of a particle which is headed toward a given point in space and shortens the path of a particle headed away from the point. The effective number of mean-free-paths a particle will travel before its next collision can be given as:

$$mfp' = mfp \times (1 - q \mu)$$

where mfp is the number chosen from an exponential distribution, μ is the cosine of the angle between the particle's direction of travel and a line drawn from the particle's starting location and the desired point, and q is an input constant whose value is between zero and one. (A zero value of q implies no path stretching, higher values imply more stretching. Negative values of q imply that the particles will be forced to move away from the given point.) The value used for q depends upon the geometrical location of the particle's starting point and the energy group of the particle and is supplied by the user. It should be pointed out that, in general, the use of this method (at least with positive values of q) tends to make the results more accurate at or around the given point while making answers at other points less accurate. A memo describing the use of this technique in more detail will be written in the near future.

Under normal conditions, the last thing a user wants is a collection of random walk histories. The quantity desired is usually the neutron or gamma-ray fluence (which used to be called flux) and, in most cases, the energy integral of the fluence times a detector response function - the detector response itself - is all that is desired. The following simple words of explanation are offered so the user can have a feeling for how one can get from the random walk histories to a fluence answer.

Particle fluence, in general terms, is a function of position, energy, time, and direction; i.e.:

$$\Phi(\vec{r}, E, t, \vec{\Omega})$$

The same word is used to describe this quantity when integrated over one or more of the variables; i.e.:

$$\Phi(\vec{r}, E, t) = \int \Phi(\vec{r}, E, t, \vec{\Omega}) d\vec{\Omega}$$

$$\Phi(\vec{r}, E) = \int \Phi(\vec{r}, E, t) dt$$

One can also talk about a spatial average:

$$\bar{\Phi}(E) = \int \Phi(\vec{r}, E) d\vec{r} / \int d\vec{r}$$

It is also possible to integrate over energy to obtain what is sometimes called the "total" fluence:

$$\bar{\Phi} = \int \bar{\Phi}(E) dE$$

Within a given volume, the total number of reactions that occur can be expressed by the volume integral of the fluence times the total cross section. Within a given energy group g this is:

$$\begin{aligned} \# \text{ reactions in volume } V \text{ and} \\ \text{in energy group } g &= \int_V \Phi(\vec{r}, E_g) \Sigma_T(E_g) d\vec{r} \end{aligned}$$

Assuming that only one material mixture exists in the volume (which is not a necessary condition but simplifies the relationships for the purposes of this report) and dropping the g subscript for the same reason, one may obtain:

$$\# \text{ reactions in volume } V = \Sigma_T \bar{\Phi} V$$

Now the left side of this expression can easily be obtained from a random walk process by just counting how many collisions occur in a given volume at a given energy. The fluence is then calculated by:

$$\bar{\Phi} = (\# \text{ reactions in volume } V) / (\Sigma_T V)$$

This method is called a reaction type fluence estimator. The number of reactions is simply the sum of the statistical weights of all particles undergoing a collision in the given volume and of the proper energy group.

$$\bar{\Phi} = \sum_V (wt)_{\text{collision}} / (\Sigma_T V)$$

The fluence may be further defined by including time and angular dependence, if desired. This method is simple, exact, and fast. However, it breaks down when few or no reactions occur in a volume either because the volume is small or because the material in the volume has a low cross section. As the volume becomes larger, more reactions occur but nothing is known about the spatial fluence dependence within the volume.

In order to solve the problem of few reactions within the volume, the predicted reaction estimator was developed. In this case the number of reactions in volume V is estimated by the number of particles which pass through the volume rather than by the number of reactions occurring. Since a particle that starts into a volume has a probability of reaction equal to:

$$1 - \exp(-\Sigma_T \rho)$$

where ρ is the particle's path length through the volume, the estimated number of reactions will be equal to:

$$(\# \text{ particles entering volume}) (1 - \exp(-\Sigma_T \rho))$$

and the fluence may be found from:

$$\bar{\Phi} = \sum_V \{ (wt)_{\text{entering}} (1 - \exp(-\Sigma_T \rho)) \} / (\Sigma_T V)$$

This method takes more calculational time since the path length must be determined and an exponential evaluated. Every particle going through the volume, however, contributes to the desired result.

If the maximum size of the volume times its cross section is a small number, the exponential may be approximated by the first two terms of a series expansion:

$$\exp(-\Sigma_T \rho) \approx 1 - \Sigma_T \rho$$

and the fluence becomes:

$$\bar{\Phi} = \sum_V \{ (wt)_{\text{entering}} \rho \} / V$$

This is the path-length estimator for fluence and saves taking the exponential.

Now consider that the volume used above is in the shape of a box of such a size that its thickness (T) is very small. For all practical purposes, no particles will hit this volume on its thin sides. The volume can be given by $A \times T$ where A is the area of the larger side. The path length through the volume can be estimated by $T / \cos \theta$ where θ is the angle between the normal to the surface and the incident particle's path. This, of course, neglects the effects of going out the thin sides of the volume. Using the above relationship, the fluence can then be estimated by:

$$\bar{\Phi} = \sum_A \{ (wt)_{\text{hitting}} / \cos \theta \} / A$$

This is referred to as a boundary crossing estimator since the concept of a volume gets lost and is replaced instead by an area concept. If a particle hits the surface with a value of θ approaching 90° , this estimator blows up. This is solved by resetting $\cos \theta$ to a finite value if it is less than a given small amount. Obviously, the original equation does not have discontinuities. Reference (2), page 51, discusses this correction in more detail.

It should be pointed out that the boundary crossing estimator technique can also be used to calculate the current as well as the fluence. The current is defined as:

$$J \equiv \int \Phi(\vec{n}) \cdot \vec{n}' d\vec{n}$$

where $\vec{n}'$ is a reference direction. Using the reference as the normal to the boundary crossing surface gives:

$$\bar{J} = \sum_A (wt)_{\text{hitting}} / A$$

Both the above estimators give values that are the average over the surface area used in the summation.

Another completely different type of estimator may be used. This method, referred to as a point fluence estimator, uses the integral form of the transport equation which states that:

$$\Phi(\vec{r}) = \int \frac{S(\vec{r}')}{\rho^2} e^{-\text{mfp}} d\vec{r}'$$

where ρ is the distance from $\vec{r}$ to $\vec{r}'$, $S(\vec{r}')$ is the source at $\vec{r}'$ in the direction pointing toward $\vec{r}$, and mfp is the number of mean free paths from $\vec{r}$ to $\vec{r}'$.

The source can be considered to be of two types. The first is the fixed source as specified in the problem. The second is a scattering source which represents the flux at a point times a scattering cross section. This second part is simulated in the random walk by the location of scattering collisions. The integral may then be evaluated in Monte Carlo terms by adding the contribution at each scattering site in the random walk process. Considerably more work is performed using this estimator than any of those illustrated above, but, at the same time, much more information is obtained since each collision in the problem contributes to the desired solution. The user should be aware of the fact that the above estimator yields correct results only when the sampling of collisions is taken over all the space which can contribute to the flux solution. If part of the volume in a given problem has no, or few, collisions in it and the integral over this particular volume yields a significant fraction of the fluence, the results will be in error.

The point estimator determines the probability of scattering through a fixed angle by evaluating each term in the Legendre expansion of the angular dependent cross section. As all curve fits which retain only a finite number of terms, this method sometimes returns negative results. In order to prevent this, MORSE-L contains an option to suppress negative probabilities. For neutron groups, the calculated distribution has negative results set to zero and re-normalizes the positive results so that the integral of the angular cross section remains constant. For gamma groups, the code uses the analytic form of the Klein-Nishina scattering equation for Compton scattering and allows other types of scattering to be treated isotropically.

The above discussion covers the random walk and estimation schemes used in MORSE-L in very, very brief detail. One more topic has raised many questions and should be included. This is the overall method for calculation of a given problem. The procedure followed is to generate source particles and follow them as described above. After a fixed number of these source particles have been produced, the desired results are obtained.

This is then referred to as one batch. Normally, a number of batches are run (each with the same number of source particles) and results obtained for each. This is exactly the same as performing an experiment a number of times. The best answer available is an average of the batch results. The variation of the batch results allows one to calculate the statistical uncertainty in the result. This is expressed as the standard deviation. It should be noted that this deviation is valid only if the batch results have a normal distribution. If they do not, or if the deviation is quite large, it is an indication that insufficient source particles have been generated.

III CODE OPERATION

MORSE-L was written for the CDC-6600 machines with the MONITOR-402 system. With this system, the following control cards are necessary:

```
*ID . . . . .
*T  CG513=5=CG513
*T  CG419=6=CG419
*   LOAD (1,5)
```

Title card of first problem, etc.

Tape unit 5 contains the program tape (a MAIN-OVERLAY-SEGMENT program) while tape 6 contains the cross section library. Tape 6 may be omitted or replaced by another tape if the standard L-Division library is not to be used. Tape CG513 will always contain the present up-to-date version of the code. This is a "purple" tape and therefore may be used on the G-machine.

During daytime operation, a user may desire to replace the tapes with disk files. If this is the case, either or both of the *T cards above may be replaced by:

```
* ASSIGN (5,0,MORSEMON)
* ASSIGN (6,0,LIBRARY)
```

The word LIBRARY is to be replaced with the appropriate name of the desired library, as will be explained in a future MORSE memorandum. The file MORSEMON may be read from tape CG611 by the standard read files routine.

More than one problem may be run by simply stacking problems behind each other.

The CDC-7600 version of MORSE-L has been made operational and is being checked out. Its availability will be announced by a separate memorandum. Other than the required control cards to run under the ORDER system, the input and operation of the 7600 version is identical to the 6600 version.

IV CODE INPUTS

Almost all of the input to the MORSE-L code makes use of a free form input format designed specifically for this code. This scheme allows each input quantity to be separated from other inputs by the use of one or more blank columns. There is no upper limit as to the number of blanks used; the code will even read over entire blank cards without trouble. The specific required inputs, described below, are therefore given as a list only and the user may space them on cards as he desires.

The code considers a comma (",") to be the same as a blank space. Input variables may therefore be separated by commas if the user is used to this type of input. In some free form input schemes, a double comma (",,") is equivalent to inputting a zero. In MORSE-L, the double comma is equivalent to only two blank spaces.

Any of the following numerical inputs will convey the value of one-thousand to the code:

```
1000
1000.
+1000.
+1000.000
1.0E+03
1.0E+3
1.E+3
1.0+3
1+3
```

The code converts all input numbers to a floating point form and then reconverts those which should be integers back into the integer form.

If the same numerical input is to appear a number of times, the repeat input option may be used. This option has the form:

jRa

where j is a numerical value representing the number of times the value is to be repeated; R is the letter; and a is the value written in any of the above approved forms. Thus, thirty values of one may be input with:

30R1.0

Note that no blanks appear within this input. If the repeated input quantity is zero, the letter Z may be written in place of the letter R and the following numerical input omitted. Thus, thirty values of zero may be input with:

30Z

If a specific number of input values are being read (such as the average velocity in each energy group), and the user desires to fill this matrix with the same value after specifying part of the matrix, he may do so by giving the desired value and following it by the letter F. Thus the input

10.0 8.5 7.32F

would put ten in the first position of a matrix, eight-and-one-half in the second position, and then fill in all remaining positions with 7.32.

An octal number is input by specifying the number and following it by the letter B. Thus:

1750B

inputs the octal number 1750 (integer value of 1000).

An input which does not start with a plus or minus sign, a decimal point, or the integer numbers zero through nine, is considered by the input routines to be an alphabetic word. It will be returned to the code as a BCD word. Only the last ten characters will be retained in this word, the rest will be ignored by the code. A number of input names in the code are written with hyphens to make them a single word; i.e.:

CROSS-SECTION

If this had been written as:

CROSS SECTION

the code would have considered it to be two words and would not have been able to understand the input. Alphabetic words may not use the repeat of fill option described above. In describing the inputs throughout the rest of this report, alphabetic inputs will be placed in quotes; i.e., "CROSS-SECTION". The quotes are not to be input.

The free form input will read data in columns 1 through 72 of an input card. Columns 73-80 may be used for identification purposes. A single input, either numerical or alphabetic, may not be split so that part appears on one card and part on another card.

The input to the MORSE-L code is broken into twenty data blocks of information. Not all of these blocks need be present in every problem. The presence or absence of some of these blocks signify what is to be done or what is not to be done in a given problem. Each block of information, except the title card, starts with a key word. Data then follows and the word "LAST" appears to indicate that all input for this block has been provided. The blocks must appear in the order described. Table I indicated each block and the general information it contains while the rest of this section describes each block in detail.

Within the block inputs, a slash ("/") is used to terminate some input lists. This symbol is used when the code does not know how much data is to follow. New users will have trouble with the proper use of the slash and will wish it didn't exist. The only alternative to its use would be for the code to ask for additional information on the amount of data to read. Note that at least one blank must precede and follow the slash.

Examples of the punched card input are given with each data block description. The example given assume a problem with five neutron groups coupled to three gamma groups. All other data described, however, has no relationship to a real problem nor do the values input in one block necessarily correspond to those input in another block. The example problem shown in Section VI of this report illustrates a consistent problem input.

TABLE I DATA BLOCKS REQUIRED FOR INPUT TO THE MORSE-L CODE

BLOCK	KEY WORD	PAGE	INFORMATION IN BLOCK'S INPUT	FORMAT	WHEN REQUIRED
I		21	Title	(8A10)	Always
II	"BASIC"	21	Basic problem parameters	free form	Always
III	"DETECTOR"	24	Detector definition(s)	free form	Always
IV	"DRF"	26	Detector response function(s)	free form	Always
V	"ENERGY-BIN"	27	Detector energy bin definitions	free form	Only when energy dependence is desired in quantities calculated at the detector
VI	"TIME-BIN"	28	Detector time bin definitions	free form	Ditto - time dependence
VII	"ANGLE-BIN"	30	Detector angle bin definitions	free form	Ditto - angle dependence requires energy bins to be also defined
VIII	"GEOMETRY"	31	Geometrical description - defines a geometry medium in terms of its position in space	free form	Always
IX	"EQUIVALENCE"	46	Equivalence between geometrical and cross section medium numbers	free form	Only when the two media do not have the same identifying number
X	"MIX"	48	Mixing table which defines the cross section media in terms of their material (or isotopic) composition	free form	Always (except for an all albedo problem)
XI	"SEBIAS"	50	Scattering energy bias	free form	Only when it is desired to alter the normal group-to-group scattering in order to favor certain energies
XII	"ENERGY"	52	Group energy boundaries	free form	Only when cross section information is not taken from a library tape
XIII	"VELOCITY"	52	Group average velocities	free form	Ditto - or when the existing velocities are to be modified
XIV	"FISSION"	53	Group fission spectra	free form	Ditto
XV	"CROSS-SECTION"	54	Cross section inputs	fixed fld.	Only when cross section library does not contain needed information
XVI	"ALBEDO"	57	Albedo scattering description	free form	Only when used in a given problem
XVII	"WALK"	60	Parameters to modify random walk	free form	Only if splitting, Russian roulette, or the exponential transform methods are utilized
XVIII	"PRODUCTION"	62	Parameters controlling the production of secondary gammas and fission neutrons	free form	Only for a coupled neutron-gamma problem or if fission produced neutrons are to be followed
XIX	"SOURCE"	63	Description of the source of neutrons and/or gamma rays	free form	Always
XX	"END"	80	End flag	(A3)	Always

Block I Title Card

This block contains a single card on which an identification of the problem being run is made. An (8A10) field is used to read this data which is then printed at various points in the problem's output.

Example:

EXAMPLE TITLE CARD -- DATA MAY EXTEND TO FULL 80 COLUMNS

Block II Basic Problem Parameters ("BASIC")

The information contained in this block establishes the basic description of the problem being run. Data is read using the free form input described previously and is identified by the key word "BASIC". There will be either 23 or 26 individual inputs in this block depending upon whether the exponential transform is or is not to be used. Each is described below in the order that they must be provided. Questions as to whether a certain option is to be used may be answered with the input words "YES" or "NO" or by numerical inputs with one meaning yes and a zero meaning no.

1. Number of neutron energy groups in the cross sections which are to be used in this problem.
2. Number of gamma energy groups in the cross sections which are to be used in this problem.
3. Number of groups downscatter plus one existing in the cross sections to be used. Usually equal to the sum of the above two quantities.
4. Maximum order of the Legendre expansion of the cross sections used in this problem.
5. Number of sets of cross sections which are to be read from input cards. A single set includes all the Legendre expansion matrices for the input material. All other cross section information required (if any) will be taken from the cross section library tape.

6. When the point fluence/current estimator is used, are negative scattering probabilities (resulting from the use of only a finite number of terms in the Legendre expansion) to be set to zero for neutron groups and the analytic expression for Compton scattering to be used for gamma groups?
7. Output print option for the cross section data:
 - 0 = Title cards of input cross sections only will be printed
 - 1 = Above plus macroscopic cross sections for each media
 - 2 = Above plus scattering angles and probabilities
 - 3 = Above plus cross sections as read
 - 4 = Above plus cross sections as stored
 - 5 = Above plus moments
8. Is the cross section library tape to be unloaded after its use at the beginning of this problem? This clears a tape unit for someone else to use during the run of a single long problem. Do not unload the library tape if it is to be used in a subsequent problem.
9. Are neutrons which are produced by fission reactions during the random walk process to be followed? If yes, the data required in block XVIII must be provided.
10. Is this an adjoint problem?
11. The number of initial source particles in each batch.
12. Maximum number of batches which will be run unless the problem is terminated by the input maximum running time, sense switch one depression, or an interrupt dump.
13. Maximum running time (minutes). If the problem has consumed more than this amount of time at the end of any batch, the problem will undergo a standard termination.
14. Group number of the lowest energy group of neutrons which will be followed. Transfer to a lower group will terminate a random walk by the minimum energy cut-off. Set to either the maximum number of neutron groups or to zero if this type of termination is not desired. (Note: group number one is the highest neutron energy group.)

15. As above but for the lowest energy group of gammas.
16. The maximum age (seconds) that a particle may have in the random walk process. A particle which has an age greater than this at a collision site will be terminated by an age cut-off. A zero input value will turn-off this type of termination.
17. Is the random walk to be modified so that no particle is allowed to escape from the system? Do not use with the path length, predicted reaction, or boundary crossing type of flux estimators.
18. Is Russian Roulette to be played in order to terminate a particle's random walk? If yes, the parameters in block XVII must be specified.
19. Is splitting to be used in the random walk process? If yes, the parameters in block XVII must be specified.
20. Is the exponential transform method to be employed in the random walk process? If yes, the parameters in block XVII and the following three numbers must be specified.
21. If, and only if, the exponential transform is to be used, the x position (cm.) of the point in space toward which the particles will be preferentially directed.
22. Ditto, the y position.
23. Ditto, the z position.
24. Choice of the initial starting random number. If equal to zero, the next number in the sequence will be used. If between one and nine (inclusive), one of the nine built-in starting random numbers will be used. These numbers are spaced 10^7 apart in the normal sequence. If this input is not either of the above, the code expects a twenty digit octal input number to start the random number sequence.
25. Are the calculated detector responses and fluences to be punched onto cards at the end of the problem? This will automatically be done if the problem is terminated by sense switch one depression.
26. Are the CRT plots made for this problem classified? The first problem run in a group of problems determines the classification of the entire group.

The block is ended by the word "LAST".

Example:

BASIC	5	3	8	3	0	NO	2	NO	NC	NO	1500	50	5.7	5	8	0.0
NO	YES	NO	YES	-10.37	+5.739	+107.29	2	YES	NO	LAST						

Block III Detector Definitions

("DETECTOR")

Within the context of this report, a detector is a mathematical device which is capable of estimating the particle fluence or current from the history of collisions generated during the random walk process. This block of input data specifies how many detectors are to be used, where they are located, and the type of prediction to be used for each.

As many detectors as desired may be used. They may all use the same detection techniques or they may each use different techniques. Each detector is defined by a series of from eight to ten input parameters which specify the quantity being calculated, the method used, a definition of the detector's volume or area (if needed), a normalization factor for use with this detector only, and the specification of a direction to determine the reference for the angle dependence of the result. Table II describes the input requirements for the eight different types of detectors now available.

For convenience in the remaining input and in the problem output, the detectors are assigned numbers in the order of their input.

At least one detector must be specified.

The block is ended by the word "LAST".

Example:

DETECTOR

FLUENCE	REACTION	3	12.731	1.0	1.0	0.0	0.0		
CURRENT	BOUNDARY-CROSSING	7	6	.325	1.0E+24	-2.0	0.0	0.0	
FLUENCE	POINT	-10.37	+5.739	+107.29	0	1.0	1.0	0.0	0.0
LAST									

TABLE II DESCRIPTIONS OF INPUT REQUIREMENTS FOR MORSE-L DETECTOR TYPES

Description of Detector Type	Input Words									
	1st	2nd	3rd	4th	5th	6th	7th	8th	9th	10th
Reaction estimation of fluence in a volume defined by geometry medium MED. Volume is given as V (cc).	"FLUENCE"	"REACTION"	MED	V	XNOR*	u_{ref}^{**}	v_{ref}	w_{ref}	-	-
Path length estimation of fluence in a volume defined by geometrical medium MED. Volume is given as V (cc).	"FLUENCE"	"PATH-LENGTH"	MED	V	XNOR	u_{ref}	v_{ref}	w_{ref}	-	-
Predicted reaction estimation of fluence in a volume defined by geometry medium MED. Volume is given as V (cc).	"FLUENCE"	"PREDICTED-REACTION"	MED	V	XNOR	u_{ref}	v_{ref}	w_{ref}	-	-
Boundary crossing estimation of fluence on an area defined as between geometry media MED1 and MED2. Area is given as A (cm ²). If $u_{ref} < -1$, reference direction is normal to surface defined above.	"FLUENCE"	"BOUNDARY-CROSSING"	MED1	MED2	A	XNOR	u_{ref}	v_{ref}	w_{ref}	-
As above but estimates current. Positive current is defined as transfer from MED1 to MED2.	"CURRENT"	"BOUNDARY-CROSSING"	MED1	MED2	S	XNOR	u_{ref}	v_{ref}	w_{ref}	-
Point Flux estimation at (x_{det} , y_{det} , z_{det}). If MED > 0, only the contribution from that geometrical medium will be included in the flux estimate. Otherwise all media will be included. This technique does not sum contributions from albedo scattering collisions.	"FLUENCE"	"POINT"	x_{det}	y_{det}	z_{det}	MED	XNOR	u_{ref}	v_{ref}	w_{ref}
Ditto, but calculates current with respect to a plane perpendicular to the reference direction.	"CURRENT"	"PCINT"	x_{det}	y_{det}	z_{det}	MED	XNOR	u_{ref}	v_{ref}	w_{ref}
Estimates the total current on a boundary at which albedo scattering occurs. The statistical region (NREG)*** defines the area of the detector (A, cm ²). If $u_{ref} < -1$, the reference direction is taken as the normal to the surface. Positive current implies particles going into the albedo media.	"CURRENT"	"ALBEDO"	NREG	A	XNOR	u_{ref}	v_{ref}	w_{ref}	-	-

* XNOR is a normalization value -- the results of MORSE-L problem are normalized to one source particle. In the detector printout, these results will be multiplied by XNOR.

** (u_{ref} , v_{ref} , w_{ref}) are the direction cosines of a vector which defines a reference direction for the angle bins used for a given detector.

*** The statistical region used refers to the region just outside of the albedo medium, not to the region associated with the albedo medium number.

Block IV Detector Response Functions

("DRF")

At each specified detector, the particle fluence (or current) is estimated. This quantity is a function of energy, time, and angular direction. (The detector's location specifies the position dependence.) While the fluence is the solution of a given radiation transport problem, it is often more answer than is required. In most cases the total response of a detector is what is observed and, consequently, what should be calculated. This quantity is given by:

$$\text{Total response} = \int_0^{\infty} \Phi(E) \text{ DRF}(E) dE$$

where $\Phi(E)$ is the fluence and $\text{DRF}(E)$ is the detector's response function - i.e., the response of this detector to unit fluence of a given energy. The angular dependence is normally integrated out while the time dependence may be left in, thus giving a response per unit time, or integrated over all times. Since MORSE-L deals with quantities averaged over fixed energy groups, the above integral is replaced by a summation over all energy groups:

$$\text{Total response} = \sum_g \Phi_g \overline{\text{DRF}}_g \Delta E_g$$

The average detector response function per group is defined thusly:

$$\overline{\text{DRF}}_g = \frac{\int_g \Phi(E) \text{ DRF}(E) dE}{\int_g \Phi(E) dE}$$

This block of input specifies the detector response functions to be used in this problem. At least one response function must be specified. There are no limits to the maximum number of functions that may be input. Each response function is used to determine a response at each detector location even though the result may not be meaningful.

It should be noted that MORSE-L calculates fluence and current in units of particles per square centimeter so detector response functions based upon energy fluence (MEV per square centimeter) should be adjusted accordingly.

The first detector response function is input as a series of numbers of length equal to the total of the number of neutron and gamma groups. The response to be used with the first (highest energy neutron) group is input first, followed by the second group, etc. The second response function follows directly behind the first, etc. The block is ended by the word "LAST".

Example:

```
DRF
  5R1.0 3R0.0
  5R0.0 3R1.0
  14.5 12.25 10.5 8.75 6.0 3R0.0
  5R0.0 7.5 2.0 1.25
LAST
```

Block V Energy-Bin Definitions

("ENERGY-BIN")

If it is desired that the output for each detector include the energy dependence of the fluence (or current), this block of input information must be provided.

The energy bin structure is directly tied to the energy structure of the cross sections used in the problem. A single energy bin may include exactly one or more cross section groups but may not include just part of a group. The first energy bin always has its maximum energy equal to the maximum energy of the first cross section group. It is not necessary to specify this point in the input. Thereafter, the energy bin definition is specified by a list of energy group numbers. The lowest energy in each listed group forms the lower energy for each bin. Since the bins must be defined in order of decreasing energy, the input group numbers occur in increasing order. All the energy groups must be included in the bin structure so the last number input must be equal to the total number of energy groups. The transition between neutrons and gammas in a coupled problem is handled automatically by the code as long as the lowest neutron energy group is specified as one of the inputs in the bin structure definitions.

The sketch below illustrates how eight energy groups in a problem could be compressed into five energy bins. The example input shown is for this case.

The same energy bin structure is used for all detectors.

This entire block may be omitted if no energy dependence is desired.

Example:

ENERGY-BIN 1 3 5 6 8 LAST

Block VI Time-Bin Definitions

("TIME-BIN")

The addition of this block of data forces the code to output a time dependent fluence (or current) and a series of time dependent detector responses. If energy bins have also been specified, a series of time and energy dependent fluence values will be given.

If just one set of time-bin definitions is provided, it will be used for all the detectors. If more than one set is provided, the code expects a set for each detector. The first such specified will be used with the first detector, the second with the second detector, etc.

Each set of time-bins is specified thusly: The first value is zero. This represents the earliest time in the bin structure. The zero is not used but is replaced, during the random walk procedure, with the earliest time of arrival in the first bin. The second, and succeeding values, represent the largest value in the first bin, in the second bin, etc. If a particle which has an age greater than the end of last bin arrives at a detector, the maximum time of the last bin will be moved backwards in order to accommodate this particle. Disregarding the first zero value in each set, the remaining time values must be in increasing order. A bin boundary equal to zero is not allowed since the input part of the code thinks it is the start of a new set of time-bins. Use a very small number instead of zero.

If more than one set of time-bins is specified, each set does not have to have the same number of bins. Since it is easier for the code to assume that the same number of time-bins exist for each detector, fictitious bins will be established if unequal numbers were specified in the input.

The units of time are seconds.

Each set of time bins follows directly after the previous set. The block is ended with the word "LAST".

Omit if time dependence is not desired.

Example:

```
TIME-BIN
0.  1.E-8  2.E-8  3.E-8  5.E-8  7.E-8  1.E-7
0.  7.E-8  1.E-7  2.E-7  3.E-7  5.E-7
0.  -1.0E-7 -7.0E-8 -5.0E-8 -3.E-8 -1.E-8  1.E-99
    1.0E-8  5.0E-8
LAST
```

Block VII. Angle-Bin Definitions

("ANGLE-BIN")

It is possible to obtain a limited form of the angular dependent fluence (or current) by inclusion of this block of data. Its presence forces the output of data for each detector which is tabulated in bins corresponding to the cosine of one angle. This angle is defined as the angle between a particle's trajectory and a reference direction. The reference direction is specified for each detector in the detector definitions.

The angle-bins are specified thusly. The lower edge of the first bin is assumed to be equal to -1.0 and is not input. Subsequent inputs define the upper edge of each bin and must be in increasing order. The last input value must be equal to +1.0.

The same bin definitions are used for all detectors.

If angle-bins are specified, the code will output angle and energy dependent fluence (or current). For this reason, it is necessary that energy bins be established if the angle-bins are defined.

This block is ended with the word "LAST".

Omit if angle dependence is not desired.

Example:

```
ANGLE-BIN  -.8090  -.3090  +.3090  +.8090  +1.0000  LAST
```

Block VIII Geometry Descriptions

("GEOMETRY")

The geometrical description necessary to run a given problem is provided by this block of input. It must always be input in every problem.

It is first necessary to define two terms used in this input and throughout the code. A material medium is a given geometrical volume in which there exists the same physical material. This material is identified by a given medium number. A statistical region is a given geometrical volume in which the same set of splitting parameters, Russian Roulette parameters, path stretching parameters, and secondary production control parameters are to be used. This volume is identified by a region number. The output summaries of reactions are also tabulated by statistical regions. The words medium and region when used alone always signify material media and statistical regions.

A void may be represented by one of two medium numbers. Medium number 1000 represents an "interior" void. A particle tracked into this medium will have its trajectory extended through the medium until it exits from the far side. Medium number 0 (zero) represents an "exterior" void. A particle tracked into this medium is considered to escape from the system without being tracked further. Neither of these two media have cross sections specified to go with them.

Medium number -1 may be used to represent a "black" sink of particles. Any particle entering this medium will be considered to have escaped from the system (similar to medium zero) while any mean free path measured through the medium will be infinite in magnitude. Again, no cross sections need be specified for this medium.

Two options are available to describe the required system geometry. The first assumes that the system can be adequately described in one-dimensional spherical coordinates. The second allows the use of surfaces described by the zeros of any general quadratic equation. Needless to say, the input for the spherical option is much simpler than for the general option. Each is described below.

Spherical Geometry Option

This option assumes that the center of the sphere is at the center of a cartesian coordinate system. (The code still operates in x,y,z, geometry - it just finds the geometrical medium and regions in a spherical system. The source specifications may be non-spherical.) The input first describes the material medium and then describes the statistical regions. Each description starts with the centermost sphere and progresses outward through increasingly larger spherical shells. Everything beyond the last described medium is considered to be outside of the defined geometry.

The first word input, after the block word "GEOMETRY", is "SPHERICAL".

Material medium descriptions are then made by giving the medium number followed by the outer radius of the medium (in centimeters). After the outermost medium, a slash is used to terminate the list.

Statistical regions are defined next in the same manner as the media. This list is terminated by the word "LAST". No additional geometry inputs are required. (The geometry picture routine, described below, does not function with this option.)

Example:

```

GEOMETRY  SPHERICAL
  1  5.0   2  7.0   1  9.0   3  10.0  /
  1  5.0   2  7.0   3  9.0   4  9.0   5  10.0  LAST
    
```

General Geometry Option

The use of the general geometry option allows the description of everything from very simple to exceedingly complex systems. For all practical purposes, any given system geometry may be approximated by this routine. The following explanation should be general enough for the user to grasp the fundamentals of this option. Proficiency will come only through experience.

The description of a given problem's geometry follows the following steps:

1. An x,y,z cartesian coordinate system is established at a convenient place in space.
2. A "big box", with its sides parallel to the xy, yz, and xz planes, is placed around that part of space which is to be defined. This box does not need to include the origin of the coordinate system. Any point outside of this "big box" is in an undefined volume. In tracking a particle in the random walk, exit from the defined volume is termed escape or leakage and the particle is no longer followed. An initial source particle generated in an undefined volume causes a fatal problem error. If a detector is located outside of the "big box" for a point fluence/current estimator, the undefined volume is considered to contain a void.
3. The "big box" is then broken into one or more boxes* by passing planes, which are parallel to the sides of the "big box", all the way across it. The number of boxes, their size, and placement are defined by giving the intercepts of the box sides with the x,y, and z-axis. (The number of boxes in a given direction is one less than the number of intercepts given.) Each box is identified by its position in the x direction (IX) (starting with the minimum value of x), the y direction (IY), and the z direction (IZ). A full description is then given of every box.

* In the 05-R and MORSE codes, the word zone was used instead of box. Since "zone" already stands for a multitude of different things at LLL, the word box has been used in MORSE-L instead.

4. A box is broken into a series of one or more blocks* by passing planes parallel to the sides of the box in a manner similar to the division of the "big box". Note that these planes cut only a single box and do not transverse adjoining boxes. The blocks are identified by JX, JY, and JZ where the first block within the box is that with the minimum coordinate value within the given box in the desired direction. The values of JX, JY, and JZ refer to this box only and have no relationship to the other boxes in the system. A full description is then given of every block within a given box.
 5. Each block is then broken into one or more sectors by defining surfaces within the block. These surfaces are the zeros of given quadratic equations. A sector is defined by its relationship to given equations (either on the side where an evaluation of the equation is positive or on the side where it is negative). Only those equations which define a given sector need be used in its definition even though these are additional equations used within the block. Every point within a block must be in one, and only one, sector. Medium and region numbers are associated with each sector.
 6. The equations of the surfaces are then specified.
- Figure 1 illustrates the use of the terms used above.

* These blocks have nothing whatsoever to do with the blocks of information required in the MORSE-L input.

BIG BOX

BOX 3, 1, 1

BLOCK 2, 1, 1

FIGURE 1

Illustration of Geometry Terms

The form of the input is then:

1. The box boundaries in the x,y, and z directions in order to define each box in the system.

2. Box description of one of the boxes.

a. Box position

b. Block boundaries within this box in the x,y, and z directions in order to define each block in this box.

c. Block description of one block

i Block position

ii First sector definition

iii Second sector definition

etc.

d. Block description of another block

i Block position

ii First sector definition

etc.

e. Block description of another block

etc.

.....

(Repeat until all blocks in this box are defined

.....

3. Box description for another box

a. Box position

b. Block boundaries within this box in the x,y, and z directions in order to define each block in this box.

c. Block description of one block

etc.

.....

(Repeat until all boxes are described)

.....

N Definition of all equations used in the above sector descriptions.

The use of boxes and blocks allows a complicated part of the geometry to be isolated in the geometry description. In the tracking process, the multitude of surfaces required to keep track of the location of a given particle will not be required once the particle has gotten out of the block where such a detailed description is necessary. The problem can therefore operate more efficiently. The user should attempt to place complicated geometry descriptions into single blocks.

Besides the special media numbers already described, any positive integer number may be used to describe a material medium, a statistical region, or a surface equation. The code expects, however, that medium and region numbers be contiguous; i.e., if medium number 12 is specified, medium numbers 1 through 12 must exist. No such requirement exists for surface equation numbers.

In order to allow a box which was described for use in one problem to be easily inserted into another problem, several features have been added to the input. The first allows all media numbers, with the exception of media -1, 0, and 1000, to be shifted from the input value by a given constant amount. In other words, media numbers input within a given box as 101, 102, and 103 can be altered, before the code uses them, to 1, 2, and 3 by inserting the constant as -100. Likewise, statistical region numbers may be shifted. The second change allows the block boundaries specified within a box to be different in value than the specified box boundaries. For example, if a given box was specified to be between $x=5$ and $x=10$, it would normally be expected that the block boundaries would start with 5 and end with 10; say 5, 7.5, and 10 for two equal blocks. The code will accept as block boundary input any set of values provided that the size of the box fits into the specified size. In the above example, an input of 0, 2.5, and 5 will be accepted and transformed into 5, 7.5, and 10. An input of 0, 2.5, and 4.5 would not be acceptable since the code will not fit a box of width 4.5 into a specified width of 5. The third change that allows easy interchangeability is the provision that lets surface equations be evaluated on a box basis. In the normal problem, surface equations are evaluated in an x,y,z system based upon the originally defined coordinate axes. It is now possible to flag an equation so it will be evaluated at a coordinate system whose center is at the center of the box in which it is used (the x,y , and z directions are unchanged). The use of these three items are explained in the input description below.

The code checks as much of the input as possible for potential errors or omissions. In order to allow even greater checks, it is possible to have the code draw CRT picture of parts of the defined geometry. The user may then compare these to his original problem description.

All the required inputs are described below. If the reader will follow the example at the end of this section while going through the descriptions, the text will be more understandable.

1. Box Boundaries

Three sets of inputs giving, respectively, the x, y, and z coordinates of the box intercepts with the coordinate axes. Each set starts with a label ("BOX-X", "BOX-Y", or "BOX-Z") and then contains the intercepts with the minimum value first followed by the next larger value, etc. Each set is terminated with a slash.

2. Box Description

Each box is completely described by the following cards. It makes no difference as to the input order of the boxes as long as each box is specified.

a. Box Position

The word "BOX" followed by the integer values of IX, IY, and IZ indicating the box's relative position in the "big box". If the material medium numbers and statistical region numbers specified on the following input cards for this box are to be shifted, follow these three numbers by the amount of shift for medium numbers (IDM) and the amount for region numbers (IDR). The medium number used in this problem will then be the input number plus IDM. Similarly for the region number. Terminate this input (either 3 or 5 numbers) with a slash. If there is only one box in the problem, and no shift is to be made, this input may be omitted.

b. Block Boundaries

Three sets of inputs are provided giving the x, y, and z coordinates of the boundaries of the blocks inside this box. Each set starts with a label ("BLOCK-X", "BLOCK-Y", or "BLOCK-Z"), then the intercepts with the coordinate axes followed by a slash. Normally, the minimum (first) value given is the value at the minimum side of the box, while the maximum (last) value is the maximum for the box. This may be altered as described above. If there is only one block in a given direction, the input for that direction may be omitted.

c. Block Description

Each block within the given box is described with the following inputs. No required order exists for describing the blocks as long as all are specified.

i. block position

A single entry containing the label "BLOCK" followed by the values of JX, JY, and JZ. No slash is used. If only one block exists within a box, this input may be omitted.

ii. sector description

Each sector within the given block is described as follows:

- label word "SECTOR"
- identifying label (alphabetic or numerical) which will be printed in the output in order to assist the user in identifying this sector. Is not used by the code.
- material medium number in this sector
- statistical region number in this sector
- reference to surface equations which define this sector.
Only equations which are necessary to this sector need be given even though there exists other equations within the block. The reference is given as +N, where N is an integer number, if the sector is on the positive side of equation number N, and as -M if on the negative

side of equation M. Terminate the reference to equations with a slash. It is possible that no equation references will be given - i.e., the block contains a single medium.

3. Surface Equations

After all boxes, and all blocks within these boxes, have been specified, the code expects to find a definition for each surface equation used. There is no order of input required for the equation numbers. An equation may be used in as many blocks as it is needed. If no surfaces have been used in the geometry description, omit this input.

Start this part of the input with the label "SURFACES". Then describe each equation thusly:

- number of the surface.
- if the equation is to be evaluated from the center of the box in which it is to be used, rather than from the defined coordinate system, insert the word "BOX" at this point.
- equation definition. Several different forms are available and each is described below.
- a slash to terminate this equation's input.

The surface equations may be defined by any one of the following six methods.

a. The general quadratic equation form

If the complete equation is known in its analytic form; i.e.:
 $Ax^2 + By^2 + Cz^2 + Dxy + Exz + Fyz + Gx + Hy + Iz + J = 0$,
 the coefficients of each of the terms may be input followed by a label to indicate which term they are associated with. The acceptable labels are:

"XSQ"	"X*X"	"X**2"	"XX"
"YSQ"	"Y*Y"	"Y**2"	"YY"
"ZSQ"	"Z*Z"	"Z**2"	"ZZ"
"XY"	"X*Y"	"YX"	"Y*X"
"XZ"	"X*Z"	"ZX"	"Z*X"
"YZ"	"Y*Z"	"Z*Y"	"ZY"
"X"			
"Y"			
"Z"			
"CONSTANT"	(none)		

The terms may be input in any order and individual terms may be repeated (causing the code to sum the coefficients). A term with a zero coefficient need not be specified. A coefficient of one is assumed by the code if no leading coefficient is input to go with a given label.

b. Sphere

The proper analytic equation of a sphere will be generated by the code upon inputing:

"SPHERE" x_1 y_1 z_1 r

where the center of the sphere is at (x_1, y_1, z_1) and the sphere's radius is equal to r . Points inside the sphere are negative with respect to this surface while points outside will be positive.

c. Cylinder

The code will generate the equation of a cylinder if the input is:

"CYLINDER" x_1 y_1 z_1 x_2 y_2 z_2 r

where the two points are on the axis of the cylinder and r is the cylinder's radius. Note that the cylinder is infinitely long and is not terminated by the two given points. Points inside the cylinder will be negative with respect to this surface while points outside will be positive. The axis does not have to be parallel to a coordinate axis.

d. Cone

In like manner, an input of:

"CONE" $x_1 y_1 z_1 x_2 y_2 z_2 r_2$

will generate the equation of a cone with its apex at point one, with point two on the axis of the cone, and with r_2 equal to the radius of the cone at point two. The cone, like the cylinder, is infinite in extent and includes both nappes. Points inside the cone will be negative with respect to this surface. Points outside will be positive. The axis does not need to be parallel to the coordinate axes.

e. Plane - two points

The code recognizes the following input to describe a plane:

"PLANE" $x_1 y_1 z_1 x_2 y_2 z_2$

In this input, point one is a point on the desired plane while point two is a point not on the plane. The normal line to the plane passing through the first point goes through the second point. All points off the plane on the same side as the second point produce positive evaluations of the resulting quadratic equation while points on the other side produce negative values. The plane may be oriented in any spacial direction.

f. Plane - four points

It is also possible to describe a plane with the following input:

"PLANE" $x_1 y_1 z_1 x_2 y_2 z_2 x_3 y_3 z_3 x_4 y_4 z_4$

The first three points all lie on the desired plane (but not in a straight line) while the fourth point lies off of the plane on the side where the equation is to be positive.

4. Picture

If the user desires, CRT pictures will be drawn to illustrate the geometry specified in the previous input. Each picture is a simulated 3D view of a rectangular parallelepiped whose sides are parallel to the coordinate planes. A cut is made into this figure to expose part of the interior and then lines drawn to indicate surfaces across which there is a change of medium or region data. The reproduced output of the example problem illustrates such a picture.

In order to obtain these pictures, first add the label "PICTURE" and for each picture, then add an additional set of six numbers:

$$x_{\min} \ x_{\max} \ y_{\min} \ y_{\max} \ z_{\min} \ z_{\max}$$

where these are the minimum and maximum coordinate values for the desired picture. As many pictures as desired may be drawn by adding groups of six numbers to the list already existing. These groups of six numbers are not separated by a slash. Terminate with the word "LAST".

If all six numbers in the input for a single picture are set to zero, the code will survey the entire geometry by drawing pictures of every block within the defined system.

The end of the geometry data block will resemble either:

SURFACES / LAST

or: SURFACES / PICTURE LAST

depending whether pictures are or are not to be drawn.

There are limits to the complexity of the geometry inputs that may be used in any one problem. These limits result from packing data in the core and could be changed if necessary.

total number of boxes ≤ 511

number of blocks in given direction ≤ 63

total number of blocks ≤ 511

total number of sectors in any given block ≤ 63

total number of surfaces in any given block ≤ 59

maximum medium number ≤ 1023

Example:

GEOMETRY

```

BOX-X  0.0  5.0  10.0  /
BOX-Y  0.0  5.0  20.0  /
BOX-Z  0.0  10.0  /

```

```

BOX  1  1  1  /
BLOCK-X  0.0  5.0  /
BLOCK-Y  0.0  5.0  /
BLOCK-Z  0.0  5.0  10.0  /

```

```

BLOCK  1  1  1
  SECTOR  INSIDE  1  1  -1  /
  SECTOR  OUTSIDE 2  1  +1  /
BLOCK  1  1  2
  SECTOR  INSIDE  3  1  -2  /
  SECTOR  OUTSIDE 2  1  +2  /

```

```

BOX  2  1  1  /
BLOCK-X  5.0  10.0  /
BLOCK-Y  5.0  10.0  /
BLOCK-Z  0.0  2.50  5.0  7.5  10.0  /

```

```

BLOCK  1  1  1
  SECTOR  VOID  1000  2  -3  /
  SECTOR  LEAD  4  2  +3  /
BLOCK  1  1  2
  SECTOR  VOID  1000  3  -3  /
  SECTOR  IRON  5  3  +3  /
BLOCK  1  1  3
  SECTOR  VOID  1000  4  -3  /
  SECTOR  VOID  1000  4  +3  -4  /
  SECTOR  LEAD  4  4  +3  +4  /
BLOCK  1  1  4
  SECTOR  LEAD  4  5  +3  /
  SECTOR  JUNK  6  5  -3  /

```

```

BOX  1  2  1  /
BLOCK-X  0.0  5.0  /
BLOCK-Y  5.0  10.0  20.0  /
BLOCK-Z  0.0  10.0  /

```

```

BLOCK  1  1  1
  SECTOR  INSIDE  7  6  -10  +11  /
  SECTOR  OUTSIDE 3  6  -11  /
  SECTOR  OUTSIDE 3  5  +10  +11  /
BLOCK  1  2  1
  SECTOR  ELLIPSOID  4  7  -15  /
  SECTOR  VOID  1000  7  +15  /

```

Example:

BOX 2 2 1 / SECTOR CCNCRETE 9 8 /

SURFACES

1	SPHERE	2.5	2.5	2.5	2.0	/
2	SPHERE	2.5	2.5	7.5	2.0	/
4	CYLINDER	5.0	0.0	6.25	10.0	5.0 6.25 0.5 /
3	CYLINDER	7.5	2.5	0.0	7.5	2.5 1.0 2.0 /
10	CONE	2.5	7.5	9.0	2.5	7.5 0.0 2.2 /
11	PLANE	2.5	7.5	9.0	2.5	7.5 0.0 /
15	BOX	0.25	XSQ	-1.25	X	0.25 YSQ -7.5 Y 0.04 ZSQ -.4 Z
		57.8125	/			

PICTURE 6R0.

5.0	10.0	0.0	5.0	5.0	7.5
5.0	10.0	0.0	5.0	7.5	10.0

LAST

(Box (1,1,1) contains two spheres, one above the other. Box (2,1,1) contains a cylindrical hole drilled downward through layers of junk, lead, iron, and lead. A small hole is drilled through the top-most lead piece which intersects the larger hole at right angles. Box (1,2,1) contains a cone with its point upward. The described ellipse in this box does not exist within the box. Box (2,2,1) is filled with concrete.)

Block IX Equivalence Tables

("EQUIVALENCE")

In a normal situation, a given geometrical volume is defined as medium number NMED and then cross sections are specified to go with this media. In other words, there is a cross section medium number, say XMED, which goes with the geometrical medium NMED and they are both the same identical number; i.e., $XMED = NMED$. At times it is desirable that such an equivalence can be made without having the two numbers identical. This can be easily seen from the code input already described; as, for example, if a reaction type detector is specified in the middle of a medium of the same composition. Since the detector volume is defined by a given medium number, it must have a number different from the material around it even though they are both the same substance.

Another situation in which the equivalence of geometrical and cross section media is desirable is that in which one material is identical to another with the exception of a different density. This could be shown as various regions of water with a different void fraction in each. Almost all the stored cross sections within MORSE-L are identical for those regions with the exception of values which can easily be obtained knowing the relative density of each.

Both the above examples of equivalence can easily be specified in the MORSE-L code input by the inclusion of this block of data. The data in this block is made up of a series of triplets. Each triplet contains the quantities:

NMED, XMED, and DF

where: NMED is a given geometry defined medium number,
XMED is the corresponding cross section medium number, and
DF is the ratio of the density of the material defined by NMED
divided by the density of the material defined in the cross
section input as material medium XMED.

If $NMED = XMED$ and $DF = 1.0$, no input is required. The code automatically makes such equivalence statements. (If this block of data is not input, these normal equivalence statements are all that exist.)

The block input is terminated by the word "LAST".

EQUIVALENCE	1	1	0.5	2	1	1.0	3	1	1.5	4	1	2.0	10	1	1.0
	8	-3	1.1075	LAST											

Block X Mixing Tables

("MIX")

With the exception of a problem which includes only void and albedo materials, the mixing tables must always be input. These tables, which comprise this block of data, are used to define the composition of each cross section medium in terms of available input cross sections.

The input for this block consists of a series of specifications for the mixing instructions. Each specification consists of five input numbers:

- 1st) The cross section medium number for which this instruction pertains.
- 2nd) Identification of the isotope (or mixture) which forms part of the medium. This input may be either a word or number from the list of available isotopes.
- 3rd) Numerical designation of the flux weighting used to obtain the desired isotope's (or mixture's) cross sections. This parameter may also be used to separate cross sections of the same isotope which have been obtained from different sources.
- 4th) The maximum order of the Legendre expansion of this set of input cross sections.
- 5th) Density of this isotope or mixture. In units of atoms per barn-centimeter if the cross sections are in barns per atom or in units of grams per cubic centimeter if the cross sections were mixed so that they have units of square centimeters per gram.

The specifications for an entire medium must be placed together in the input without being interrupted by the specifications of another medium. The input does not have to be ordered by medium numbers, however. Each cross section medium appearing in the equivalence table (including those implied by their absence in the code's input) must be defined in the mixing table. If a material is defined which is not needed in the problem, it will be listed in the output but it will not be mixed or stored.

The input to this block is ended by the work "LAST".

Example:

MIX	1	H	0	3	.0668	1	0	0	3	.0334
	2	PB	0	3	.0330					
	3	FE	0	3	.0847					

LAST

Block XI Scattering Energy Bias

("SEBIAS")

In some problems, it may be desirable to bias the group to group scattering in order to obtain a result with a smaller statistical error than the unbiased problem would yield. An example of this would be a detector which is much more sensitive to high energy neutrons than low energy ones. If the normal scattering (as fixed by nature) quickly transfers high energy neutrons to low energy groups, a biasing could be made in which the high energy groups are assigned a greater importance than the low energy ones. The effect would be to keep the neutrons being followed in the problem's random walk process at a higher energy. The statistical weights associated with each neutron would be adjusted accordingly so that the answers would reflect a correct solution to the transport problem.

If this block of data is provided, this type of bias will be used. There are two parts to the input for scattering energy bias. The first part is a list of which cross sections are to be biased, while the second part of the input contains the bias functions themselves.

The first part is a series of two numbers, the first of which is the cross section medium number of a medium which is to be biased and the second of which is the number of the bias function to be used with this medium. Any medium which is biased will be biased wherever it is used in the problem. The input bias functions are numbered according to their order of input. The list input in the first part is terminated by a slash.

The input bias functions are a list of the relative importance of each energy group in the problem. (The first group is the highest energy primary particle.) Each function must have the same number of values as the total number of energy groups. The first function is followed by the second, etc. This list is terminated by the word "LAST".

No additional time per scattering event is used during the random walk process when scattering energy bias is employed.

This entire block may be omitted if biasing is not to be performed.

Example:

```
SEBIAS  1 1    3 1    2 2  /
1.75  1.50  1.25  1.00  0.75  1.70  1.50  0.80
1.95  1.80  1.45  1.00  0.32  7.50  3.00  0.45  LAST
```

Block XII Energy Boundaries

("ENERGY")

If all the cross section information is to be read from input cards, or if an all albedo problem is to be run, or if, for some reason, it is desired to change the energy description read from the library tape, this block may be input. The block contains the energy (in Mev) at the boundaries established for the cross section groups. The highest energy of the first neutron group is given first followed by the energy at each boundary until the lowest energy of the last neutron group is provided. (There will be one more input than the number of neutron groups up to this point.) These are then followed by the boundaries, highest to lowest, of the gamma groups. Omit neutron or gamma data if they are not included in the cross section set. Terminate this block with the word "LAST".

Example:

ENERGY 10. 8. 5. 2.5 1.5 .1 11.5 7.0 3.0 1.0 LAST

Block XIII Velocities

("VELOCITY")

Similar to the energy boundaries, this block provides information on the average velocity of particles within a given energy group. This information is necessary input if a library tape has not been used or may be used to alter data on the library tape if it was used. Values are input for each group, starting with the highest energy neutron group, with units of centimeters per second. Terminate the input by the word "LAST".

Example:

VELOCITY 4.3+9 3.4+9 2.5+9 1.8+9 1.4+9 3R3.0+10 LAST

Block XIV Fission Spectra

("FISSION")

Similar to the energy and velocity data. Input is the probability that a fission neutron will be born into a given neutron group, for energy groups which represent neutrons. The sum over all neutron groups should be one. For gamma groups, the inputs are zero. Input the highest energy neutron group first. Terminate by the word "LAST".

Note that the fission spectra as used in the code is not dependent upon the incident neutron energy.

Example:

FISSION .009 .043 .184 .208 .556 32 LAST

Block XV Cross Sections

("CROSS-SECTION")

If any cross sections are to be input on cards, the following input is required. Note that an identification card is required only for the isotope (or mixture), not for each scattering matrix associated with the isotope. Cross sections to be obtained from the library tape require no additional inputs beyond that already given. The block label is read with the free form input routines while all other data in this block has fixed formats. The block of input data occurring immediately after this block must start on a new card.

Identification Card (A10,4I5)

- col. 1-10 Identification symbol of the isotope. This must be the same as used in the material definitions in the mixing tables.
- col. 11-15 Numerical designation of the flux weighting used to obtain the isotope's cross sections.
- col. 16-20 Maximum order of the expansion of this set of cross sections. There will be one more than this number of input matrices. This value may not be greater than the maximum order specified for the problem as given in the basic parameter block of input.
- col. 21-25 Type of format used to input the cross sections. A zero for FIDO formats, a one for DTF-IV formats (see below).
- col. 26-30 A one if the scattering matrices do not include a factor of $(2\ell+1)$ factor. Cross sections of LASL and the cross sections input to the DTF-IV code do not include the $(2\ell+1)$ factor. Cross sections from ORNL intended for the ANISN and DOT codes do include this factor. The output of the LLL code CLYDE does not include the factor.

Cross Sections

Cross sections may be input in either a FIDO type format (as used by the ANISN and DOT codes) or in a DTF-IV format. FIDO input allows the use of a repeat option to enable zero values to be input more easily and ignores blank fields. The formats for FIDO input have a specification of (6(I2,A1,F9.0)). A numerical input may be placed in the F9.0 location (a right adjusted exponential field may be used) and the two preceeding fields left blank. Another method of inputing numerical values is to put the value in the F9.0 field, the exponent of the associated power of ten in the I2 field, and a + or - in the A1 field to indicate the sign that goes with the exponent. Thus a cross section of 1234. barns may be represented either by $\wedge 3++1.234 \wedge \wedge \wedge$ (where the $\wedge$'s represent blanks) or by $\wedge \wedge \wedge +1234. \wedge \wedge \wedge$. A zero input must be specified by a +0.0 in order not to be mistaken as a blank. A repeat option is available where the I2 field contains the number of times an input is to be repeated, the A1 field contains the letter R and the numerical field contains the value. Thus, fifteen zeros may be input by 15R+0.0 $\wedge \wedge \wedge \wedge \wedge$.

The DTF-IV format is a simple (6E12.4) card with all zeros requiring a full field and blank fields being read as negative aeros.

The order of cross section input is the same as used in the discrete ordinate codes, i.e.:

$$\sigma_a, \nu\sigma_f, \sigma_g, \sigma_{g \rightarrow g}, \sigma_{g-1 \rightarrow g}, \dots, \sigma_{g-N \rightarrow g}$$

Group one inputs are followed by group two, etc. Even though a cross section is zero by definition, as a transfer between group -5 and group 1, it is input as zero. With the DTF-IV format, no blanks are allowed and each group, except the first, does not necessarily start on a new card.

The P_0 matrix is read in first followed by the P_1, P_2 , etc.

Each matrix does start on a new card.

Activation cross sections are not allowed in MORSE-L inputs.

As many sets of input cross sections as specified in the basic problem description will be read. Not all of those read need be used in any given problem.

This block of input data is not terminated by the word "LAST".

Example:

CROSS-SECTION

NAME	0	0	0	0		
+0.10	+0.30		+1.00	+0.20	7R+0.00	
+0.10	+0.00		+0.80	+0.25	+0.25	6R+0.00
+0.10	+0.00		+0.60	+0.20	+0.25	+0.20
5R+0.00	+0.25		+0.00	+1.20	+0.75	+0.30
+0.20	+0.15	4R+0.00		+1.50	+0.00	+4.00
+2.50	+0.20	+0.00		+0.00	+0.10	3R+0.00
-0.45	+0.00	+3.75		+0.20	+0.01	+0.07
+0.10	+0.30	+0.65	2R+0.00		+0.10	+0.00
+2.50	+0.25	+1.00		+8.00	+0.03	+0.05
+0.15	+0.35	+0.00		+1.50	+0.00	+3.00
+1.50	+2.15	+3.00		+0.00	+0.01	+0.10
+0.20	+0.70					

Block XVI Albedo Descriptions

("ALBEDO")

If one or more albedos are to be used in a given problem (as specified by the equivalence table input), this block of data must be present. Each albedo is input using the free formats in the following form.

Initial Data

1. Albedo medium number (to agree with the equivalence table input).
2. Type:
 - 2 signifies that the albedo is specular reflection with 100% of the incident particles being returned without a change of energy group. The equivalence table may be used to alter the fraction returned.
 - 1 signifies that the albedo has a cosine distribution from the normal to the surface and is uniform in distribution in rotational angle around the normal. All the incident particles are returned without energy change. Again, the equivalence table may be used to alter the fraction returned.
 - 0 signifies that the albedo is to be described with card input. This albedo varies as the angle between the normal and reflected directions but is uniform in rotational angle around the normal.
 - >0 signifies that the albedo description is located on the cross section library tape. The number is the identification number of the desired albedo.
3. Print option - a "YES" or "NO" to signify if the full description of the albedo is to be printed in the code's output.
4. Number of incident directions in the input - necessary only if the input is to be read on cards.
5. Number of reflected directions in the input - only input if the input is on cards.

Terminate this data with a slash. The following information is necessary only if the full albedo is to be described by input cards.

Incident Particle Directions

The cosines of the incident particle directions (these are the cosines of the angle between the incident direction and the normal to the surface). Smallest cosine first followed by next smallest, etc. Terminate this data with a slash.

Return Particle Directions

The cosines of the points on the cumulative distribution function where the function is defined by input data. Smallest cosine first followed by next smallest, etc. All cosines are greater than zero. Last value must be equal to one. Terminate this data with a slash.

Probability of Return

Number of particles which return for one incident neutron. Input for incident group 1, incident angle 1; incident neutron group 1, incident angle 2; etc. Terminate this data with a slash.

Cumulative Distribution Functions

One set of input for each incident energy group and incident angle combination. The sets are input in the same order as the previous input. Within each set, the input is ordered thusly: return to same group, angle 1; same group, angle 2,, same group, last angle; return to next lower energy group, angle 1; etc. The final value in each set will be equal to one. All other values should be between zero and one and in increasing order. Terminate this data with a slash.

Up to five albedos may be input. The word "LAST" is used after all inputs in this block.

Example:

```
ALBEDO 1.0 YES 3.55 .05 .5 .95
.05 .1 .15 .2 .25 .3 .35 .375 .4 .425 .45 .475 .5 .525 .55 .575 .6 .633
.666 .7 .72 .74 .75 .8 .81 .82 .83 .84 .85 .86 .87 .88 .89 .9
.905 .91 .915 .92 .925 .93 .935 .94 .945 .95 .955 .96 .965 .97 .975
.98 .985 .99 .995 1.0
1.0 1.0 1.0 /
.0025 .01 .0225 .040 .0625 .09 .1225 .1406 .16 .1806 .2025 .2256
.25 .2756 .3025 .3306 .35 .4007 .4436 .49 .5184 .5476 .5776 .6084
.64 .6561 .6724 .6889 .7056 .7225 .7396 .7569 .7744 .7921 .81 .819
.828 .8372 .8464 .8556 .8649 .8742 .8836 .8930 .9025 .9120 .9216
.9312 .9409 .9506 .9604 .9702 .9801 .99 1.0 /
.0025 .01 .0225 .040 .0625 .09 .1225 .1406 .16 .1806 .2025 .2256
.25 .2756 .3025 .3306 .35 .4007 .4436 .49 .5184 .5476 .5776 .6084
.64 .6561 .6724 .6889 .7056 .7225 .7396 .7569 .7744 .7921 .81 .819
.828 .8372 .8464 .8556 .8649 .8742 .8836 .8930 .9025 .9120 .9216
.9312 .9409 .9506 .9604 .9702 .9801 .99 1.0 /
.0025 .01 .0225 .040 .0625 .09 .1225 .1406 .16 .1806 .2025 .2256
.25 .2756 .3025 .3306 .35 .4007 .4436 .49 .5184 .5476 .5776 .6084
.64 .6561 .6724 .6889 .7056 .7225 .7396 .7569 .7744 .7921 .81 .819
.828 .8372 .8464 .8556 .8649 .8742 .8836 .8930 .9025 .9120 .9216
.9312 .9409 .9506 .9604 .9702 .9801 .99 1.0
/ LAST
```

Block XVII Random Walk Parameters

("WALK")

If the random walk process is to be modified by using the splitting, Russian roulette, or exponential transform techniques, this block of input data is required. Otherwise, this block may be omitted. Note that the inputs for all three techniques are required even though only one or two of the techniques are to be employed. The unnecessary data will not be stored or used in the problem.

The input is in a series of eight input numbers. The first four numbers in the series describe in which statistical region and energy group the following parameters will be used. Representing these inputs as NRG1, NRG2, NGP1, and NGP2, the data on each line is used from statistical region NRG1 to region NRG2 (inclusive) and from energy group NGP1 to NGP2 (inclusive). If NRG1 is zero, all regions are included in the input of the indicated energy groups. If NGP1 is zero, all energy groups are included in the input of the given statistical regions. It is necessary that sufficient inputs be provided to describe all the energy groups in all the problem's statistical regions. Failure to do so will result in a problem error. If the input for a given region and energy group is specified more than once, the last definition input will be used.

The remaining four inputs in each series describe the random walk parameters. In the order in which they must appear, these are defined as:

- a. The probability that a particle, after it has a collision, will be split into two particles (each with half the initial particle's weight) and each of these particles followed separately. After the first batch, this input is used to derive a weight standard, for a given statistical region and energy group, above which particles are split and below which they are not. This weight standard is altered at the end of each batch so that the given probability of splitting is achieved.

- b. The probability that a particle, after it has a collision, will undergo a game of Russian roulette in an attempt to kill it off. Like the above input, this probability is used to generate a weight standard. Particles with a post collision weight below this standard will undergo the Russian roulette game. The weight standard is revised after each batch to achieve the input probability.
- c. The probability that a particle which is involved in a Russian roulette game will survive. If equal to one, all particles will survive. If equal to zero, all particles will be killed. The particles which survive will be given a weight equal to their initial weight divided by the survival probability.
- d. The exponential transform variable "q". When this method is used, particles have their path stretched when they are headed toward the preferred point. The degree of this stretching is determined by this input. A value of "q" equal zero means that the problem is run normally. Larger values (but less than one) result in greater path stretching.

If the value of "q" is set less than zero, but greater than -1, the path stretching is performed so that the particles will be directed away from the given point in space rather than towards it.

This block of data is terminated by the word "LAST".

Example:

WALK

1	3	1	1	0.5	0.0	1.0	0.7
1	3	2	4	0.0	0.0	1.0	0.0
1	3	5	5	0.0	0.1	0.5	0.0
1	3	6	7	0.0	0.0	0.0	0.0
1	3	8	8	0.0	0.1	0.5	0.0
4	8	0	0	0.0	0.0	1.0	0.0

LAST

Block XVIII Production of Secondaries

("PRODUCTION")

During the random walk process, a new neutron may be produced by a neutron collision which causes fission or a new gamma ray may be produced by a neutron collision which causes secondary gamma production. In either case, it is desirable to control the number of secondaries that are produced. The parameters in this block, which are needed only for problems involving fission or gamma production from neutrons, are designed to accomplish this. Note that the parameters for both neutron and gamma production are to be input even though only one is to be employed.

The input is in a series of six input numbers. The first four are as explained for block XVII input (above) and describe the statistical regions and energy groups associated with the following two parameters.

- a. The number of fission produced neutrons to be generated, on the average, for a collision in which fission is possible.
A weight standard is generated from this input which is used to determine if a fission produced neutron is kept. In general, neutrons produced with large statistical weights will be retained (or even split so as to produce more than one new neutron) while those with the lowest weight will be dropped.
- b. The number of secondary gammas to be generated, on the average, for a collision in which secondary production is possible.
Similar to the neutron production above.

End the block with the work "LAST".

Example:

```

PRODUCTION
0 0 0 0 0.0 0.35
LAST
    
```

Block XIX Source Description

("SOURCE")

It is necessary in all problems of the type solved by MORSE-L that the initial source of neutrons and/or gamma rays be specified. This specification of the source can be very simple or exceedingly complex, depending upon the particular problem to be solved. In very general terms, the source is a function of spacial position, energy, time, and direction; i.e., $S(\vec{r}, E, T, \vec{\Omega})$. These variables may be inter-related - i.e., the energy dependence may be related to the time. This completely general source can not be simulated with a simple code input.

The standard MORSE-L routines for source specification make the assumption that the general source can be expressed as the sum of defined sources in a given number of increments and that, within each increment, the variables are separable; i.e.:

$$S(\vec{r}, E, t, \vec{\Omega}) \approx \sum_k S_k(\vec{r}) S_k(E) S_k(t) S_k(\vec{\Omega})$$

This method allows an approximation to be made to the general form and should be adequate for most problems. If, for a given problem, this assumption is not valid, an alternate method of specifying the source is explained in the next section of this report.

Two examples should make this source approximation method more clear.

Assume that the first problem is to describe two point cesium-137 gamma sources located at different spacial positions. Two increments would be used. The first describes a source at the first point in space as a delta function in position with a delta function also in energy (cesium-137 emits only a single energy gamma). The time dependence is constant, while the angle dependence is isotropic. The second increment would be similar except that the spacial position represents the position of the second gamma source. If the original cesium-137 was replaced by cobalt-60, the description would remain the same except that the energy dependence would have to be described by a spectrum allowing for the production of two different energies.

For the second example, assume that we must simulate the gamma source in a cylinder of fissionable material upon which a pulsed incident neutron beam impinges. The fission rate is assumed to be known as a function of both spacial position and time. The simulation of this source would assume that the single cylinder could be broken into a number of smaller cylindrical segments, each counted as an increment. Within each, the source would be described as constant throughout the volume and given an energy dependence corresponding to the fission gamma spectrum. The time dependence could be made equal to a delta function at different times for each increment or given a different time distribution for each increment. The angular description would be isotropic for each case. The size of the original cylinder and the required accuracy would determine the number of increments that would be used.

The input to the code includes a description of each increment in the following order:

P_k B_k / POSITION DESCRIPTION / ENERGY DESCRIPTION /
TIME DESCRIPTION / ANGULAR DESCRIPTION /

Note the use of the slashes. P_k is a number proportional to the number of source particles born in this increment:

$$P_k = \int_{k^{th} \text{ increment}} \int S(\vec{r}) S(E) S(t) S(\vec{\Omega}) d\vec{r} dE dt d\vec{\Omega}$$

The MORSE-L output is always scaled to one average source particle so the proportionality constant used with P_k has no affect on the answer. The input labeled B_k represents the relative importance to the final result of particles born in this increment. It is used to bias the selection of the number of particles which will be born into this increment. The quantities between the slashes represent inputs describing the position, energy, time, and angular dependence of the source in this increment. The words written above are not used, but the appropriate description described below is to be inserted.

After all increments have been described, the block is ended by the word "LAST" (note that the block ends with a slash, then the word "LAST"). As many increments as necessary (within core storage limitations) may be used.

Position Description

Use one of the following descriptions. Each is started with the given word and followed by certain parameters describing the given configurations. In a number of cases, additional input parameters may be added to restrict the defined figure. All dimensions are in centimeters and measured from the center of the coordinate system specified in the geometry input. All angles are input in degrees. The available descriptions are given below in detail and are then summarized in Table III for convenience.

"POINT" $x_1 y_1 z_1$

A point source in space at (x_1, y_1, z_1) .
More than one point would be specified by a number of increments.

"LINE" $x_1 y_1 z_1 x_2 y_2 z_2$

Uniform distribution per unit length on a line running between point one and point two. A number of short lines, each described in a separate increment, could be used to approximate a curved line source.

"CIRCLE" $x_1 y_1 z_1 x_2 y_2 z_2 r$

A uniform distribution per unit length on a circular line. The center of the circle is at point one while point two is on the normal to the plane of the circle which passes through the circle's center. The circle does not have to be in one of the coordinate planes. r is the radius of the circle. This input data may be followed by:

$x_3 y_3 z_3 \theta_{\min} \theta_{\max}$

Addition of this information restricts the source to an arc between the angle $\theta_{\min}$ and $\theta_{\max}$ (given in degrees) as measured from the reference line. Point three must lie in the circle's plane.

"RECTANGLE" $x_1 y_1 z_1 x_2 y_2 z_2 x_3 y_3 z_3$

Uniform source per unit area on a plane rectangle in space. Point two must be between points one and three. The plane may be orientated in any direction in space.

"TRIANGLE" $x_1 y_1 z_1 x_2 y_2 z_2 x_3 y_3 z_3$

Uniform source per unit area on a plane triangle in space. The triangle does not have to be in one of the coordinate planes.

"DISK" $x_1 y_1 z_1 x_2 y_2 z_2 r_0$

Uniform source per unit area on a circular disk whose center is at point one with point two on the normal to the disk passing through the disk's center. r_0 is the outer radius of the disk. This input may be followed by:

r_i

in which case the source is on an annulus with an inner radius of r_i . The inner radius may be followed by:

$x_3 y_3 z_3 \theta_{\min} \theta_{\max}$

which further restricts the source to a segment of the annulus. Point three is in the disk's plane and defines the starting location of the two angles.

"SPHERE-SS" $x_1 y_1 z_1 r$

Uniform source per unit area on the surface of a sphere with its center at point one and a radius of r . This information may be followed by:

$x_2 y_2 z_2 \Phi_{\min} \Phi_{\max}$

which restricts the source to that surface which lies between polar angles of $\Phi_{\min}$ and $\Phi_{\max}$ as measured from a line through the sphere's center and reference point two. This data may be further supplemented by:

$x_3 y_3 z_3 \Theta_{\min} \Theta_{\max}$

which restricts the source to a spherical triangle. Point three is on the perpendicular to the line between points one and two at point one.

"CONE-SS" $x_1 y_1 z_1 x_2 y_2 z_2 r_1$

A uniform source per unit area on the surface of a right circular cone (but not including the end). Point one is the center of the base and point two is the apex. r_1 is the radius at the base. To this data may be added:

h

the height, in which case only a frustrum of a cone is used. It is also possible to specify:

$x_3 y_3 z_3 \Theta_{\min} \Theta_{\max}$

The third point, in the plane of the base, establishes a reference direction while $\Theta_{\min}$ and $\Theta_{\max}$ restrict the source to the surface of a wedge.

"CYLINDER-SS" $x_1 y_1 z_1 x_2 y_2 z_2 r$

A uniform source per unit area on the outside of right circular cylinder (but not on it's ends). Point one and point two are on the axis at either end of the cylinder while r is the radius. If desired, the definition may be restricted to the surface of a wedge by including:

$x_3 y_3 z_3 \theta_{\min} \theta_{\max}$

Point three is in the plane of the first end, and $\theta_{\min}$ and $\theta_{\max}$ define the limits of the desired wedge.

"BOX" $x_1 y_1 z_1 x_2 y_2 z_2 x_3 y_3 z_3 x_4 y_4 z_4$

A uniform source per unit volume within a quadrilateral defined by four of its corners. Corners one, two, and three are all in the same plane with corner two between one and three. Corner four is directly above corner two.

"PRISM" $x_1 y_1 z_1 x_2 y_2 z_2 x_3 y_3 z_3 x_4 y_4 z_4$

A uniform source per unit volume within the right triangular prism defined by four of its corners. Corners one, two, and three are in the same plane. Corner four is opposite corner two.

"PYRAMID" $x_1 y_1 z_1 x_2 y_2 z_2 x_3 y_3 z_3 x_4 y_4 z_4$

A uniform source per unit volume within the triangular pyramid defined by its four corners.

"CYLINDER" $x_1 y_1 z_1 x_2 y_2 z_2 r_0$

A uniform source per unit volume within the right circular cylinder defined with points one and two on each end at the center and with r_0 equal to the outer radius.

May be restricted to an annular source by adding:

r_i

the inner radius. Further addition of a reference point (three) in the plane of the first end and a minimum and maximum angle:

$x_3 y_3 z_3 \theta_{\min} \theta_{\max}$

limits the source to a segment of the annulus.

"CONE" $x_1 y_1 z_1 x_2 y_2 z_2 r_0$

Uniform source per unit volume within the given right circular cone defined by point one at the center of the base, point two at the apex, and with r_0 the outer radius of the base. May be restricted to that volume which lies between two cones with the same center line and apex by specifying an inner radius,

r_i

to define the second cone. A height:

h

may also be added to this list which will limit the volume to the frustrum of a cone. Beyond this input, the addition of a reference point (three) in the plane of the base and a minimum and maximum angle:

$x_3 y_3 z_3 \theta_{\min} \theta_{\max}$

further limits the source to a segment.

"SPHERE" $x_1 y_1 z_1 r_0$

A uniform source per unit volume within a sphere with its center at point one and with an outer radius of r_0 . Addition of an inner radius:

r_i

restricts the source to a spherical shell. Further addition of a second point to define the polar direction and a minimum and maximum polar angle:

$x_2 y_2 z_2 \phi_{\min} \phi_{\max}$

restricts the source to that volume between the two angles. Finally, a third reference point defining the measuring point for an azimuthal direction and a minimum and maximum angle:

$x_3 y_3 z_3 \theta_{\min} \theta_{\max}$

will restrict the volume to a solid spherical triangle.

"SPHERE-ZONE" $x_1 y_1 z_1 r_0$

Exactly as above but limits in polar angle describe a zone. Note that the inner radius need not be zero.

"ELLIPSOID" $a b c$

A simple case for those who might like to try this form. Assumed to have its center at the center of the coordinate system and the axes of the ellipsoid lined up with the coordinates of the system's axes. Give a , the ellipsoid's vertice along the x -axis (maximum value of x), b , along the y -axis, and c , along the z -axis.

TABLE III SUMMARY OF AVAILABLE SOURCE POSITION DEPENDENT INPUTS

Quantities appearing in brackets in the table below denote the x, y, z coordinates of the described position. The input on any line may stop at any indicated comma if further restriction of the source is not desired. Each description must end with a slash.

<u>LABEL</u>	<u>INPUT QUANTITIES</u>
"POINT"	(position)
"LINE"	(one end) (other end)
"CIRCLE"	(center) (normal ¹) radius, (azimuthal reference ²) $\theta_{\min} \theta_{\max}$
"RECTANGLE"	(one corner) (2nd corner) (3rd corner)
"TRIANGLE"	(cone corner) (2nd corner) (3rd corner)
"DISK"	(center) (normal ¹) outer radius, inner radius, (azimuthal ref. ²) $\theta_{\min} \theta_{\max}$
"SPHERE-SS"	(center) radius, (polar ref. ⁴) $\phi_{\min} \phi_{\max}$, (azimuthal ref. ⁴) $\theta_{\min} \theta_{\max}$
"CONE-SS"	(center of base) (apex) radius at base, height, (azimuthal ref. ²) $\theta_{\min} \theta_{\max}$
"CYLINDER-SS"	(center 1st end) (center 2nd end) radius, (azimuthal ref. ²) $\theta_{\min} \theta_{\max}$
"BOX"	(1st corner) (2nd corner ³) (3rd corner) (4th corner ³)
"PRISM"	(1st corner) (2nd corner) (3rd corner) (4th corner ³)
"PYRAMID"	(1st corner) (2nd corner) (3rd corner) (4th corner)
"CYLINDER"	(center 1st end) (center 2nd end) outer r, inner r, (azimuthal ref. ²) $\theta_{\min} \theta_{\max}$
"CONE"	(center base) (apex) outer r at base, inner r at base, height, (az. ref.) $\theta_{\min} \theta_{\max}$
"SPHERE"	(center) outer radius, inner radius, (polar ref. ⁴) $\phi_{\min} \phi_{\max}$, (az. ref. ⁴) $\theta_{\min} \theta_{\max}$
"SPHERE-ZONE"	same as above
"ELLIPSOID"	a b c

¹ A point on a line normal to the plane of the circle (or disk) and passing through the circle's center

² A point in the plane of the circle or disk or first end of cylinder or base of cone.

³ The 2nd corner is between the first and third corners and is in the same plane, the fourth point is opposite the second point.

⁴ Polar ref. pt determines zero value of ϕ ; azimuthal reference point is in plane perpendicular to polar reference line passing through sphere's center and is used to determine zero value of θ .

Energy Dependence

The energy dependence is specified in a manner similar to the position dependence, but with far fewer options. It is possible with these inputs, however, to input a bias parameter to indicate the relative importance of each energy group in the initial source. The choice of the initial energy group, within the given increment only, is affected by this importance. The available descriptions are given below and summarized in Table IV.

"SINGLE" I

The source will be placed into energy group I only.

"FUSION"

The source will be placed into that energy group which includes 14.1 MEV neutrons only.

"FISSION"

When used for an all-neutron problem, distributes the source in energy according to the same distribution indicated by the input fission spectra. Do not use this method of describing the energy dependence for all-gamma or coupled neutron-gamma problems.

It is possible to bias this input by adding:

"BIAS" $B_1 B_2 B_3 \dots B_N$

where the B_n 's are the relative importance of each energy group, starting with the highest energy neutrons, to the calculated results. (Note: no slash is used between the word "FISSION" and the word "BIAS".)

"SPECTRUM" $S_1 S_2 S_3 S_4 \dots S_N$

As many inputs as there are energy groups. Each input is a number proportional to the total number of source particles that are to be born into that group. May be biased by adding the word "BIAS" (no slash between S_N and "BIAS") and data as described above.

"CURVE" $E_1 S_1 E_2 S_2 E_3 S_3 \dots E_M S_M$

The spectra dependence is input as a series of points defining a curve. E_m defines the energy (in MEV) while S_m defines the energy spectrum (source per MEV) at given energy. The first entry is for the highest energy neutron followed by the next highest energy point, etc. These input points are followed by the highest energy gamma point, etc. The source strengths are relative and may be scaled by any factor without changing the output results. It is assumed that the source between input points may be obtained by linear interpolation. The input curve will also be extrapolated to yield points beyond the input energies, if necessary.

The input portion of MORSE-L will integrate this input to obtain a SPECTRUM type input. If the source, so obtained, in any group is negative, the code will not precede further. This type of input may be biased as described above. Note that the bias is always given by energy groups, never by an input curve.

Time Dependence

Again, the time dependence is similar to the other inputs already described. It should be pointed out that time is relative to some base chosen by the user and that negative times are just as good as positive ones. The units of time are seconds.

"DELTA" t_0

All particles will be assigned an age of t_0 at their birth. If the problem being run has no time dependence, this is the easiest time function to specify.

"GAUSSIAN" $t_0 \Delta t$

Particles will be assigned an age picked from a Gaussian distribution whose center occurs at a time t_0 and which has a full width at half the maximum amplitude of Δt . No particle will be generated with an initial age less than $(t_0 - 1.2738 \Delta t)$.

"DELAYED" $t_0 \rho$

Each particle will be given an age of t_0 plus ρ/v where ρ is a distance (in centimeters) and v is the particle's velocity (obtained from its energy and type).

"DISTRIBUTION" $t_1 S_1 t_2 S_2 t_3 S_3 \dots t_M S_M$

The selection of initial ages is chosen from an input curve. Points of time, t_m , and time dependent source, S_m , are used to describe the curve. The smallest value of t is input first followed by the next smallest, etc. The source has units of source per second while the time is in seconds. It is assumed that the source is zero before the first given time and after the last given time. Between input points, it is assumed that the value of the source per second may be obtained by linear interpolation. The input source may be scaled by any factor, only its relative magnitude is of importance.

Angular Dependence

Angular dependence is specified in a manner similar to the previous inputs. Though there is some similarity between the position dependence of a sphere and the inputs described here, it should be stressed that direction cosines are not positions. The sum of the squares of the direction cosines should be one (or, in the input, very close to one). The input angles, where used, are in degrees.

"FIXED" u v w

The source direction will be set so that the initial direction cosines are always equal to u, v, and w. (u is the cosine between the given direction of motion and the plus x-axis, v with the plus y-axis, and w with the plus z-axis.)

"ISOTROPIC"

The initial source direction will be picked from an isotropic distribution (i.e., uniform per unit solid angle). This choice may be altered so that only particles headed between two cones will be chosen by adding:

$u_{ref} \ v_{ref} \ w_{ref} \ \phi_{min} \ \phi_{max}$

where the three direction cosines define a reference direction and the angles indicate the minimum and maximum limits of the cones. The restriction may be further imposed by providing

$u_2 \ v_2 \ w_2 \ \theta_{min} \ \theta_{max}$

which specify a second reference direction, perpendicular to the first, and another set of minimum and maximum angles.

"COSINE" u_{ref} v_{ref} w_{ref}

The direction of the initial source particles are chosen from a cosine distribution ($S = \cos \Phi$) where the cosine is evaluated from the reference direction given by u_{ref} , v_{ref} , and w_{ref} . Only positive values of the cosine will be chosen.

"DISTRIBUTION" u_{ref} v_{ref} w_{ref} μ_1 S_1 μ_2 S_2 . . . μ_M S_M

The distribution of initial directions are picked from an input distribution. The input is in terms of points of the cosine of the angle, μ , measured from a reference direction, specified by u_{ref} , v_{ref} , w_{ref} , and a specified source per steradian, S_m . Between given points, it is assumed that the distribution is linear. μ_1 must be equal to +1.0 and subsequent input values of μ_m must decrease in value until the last is equal to -1.0. If u_{ref} is input as -2.0, the reference direction will be taken as the normal to a surface source defined on a sphere, cylinder, or cone. This special case may not be used with any other position definition.

Example:

SOURCE

```

1.0  1.0  / POINT 1.7  2.3 -0.8 / SINGLE 1 / DELTA 0 / ISOTROPIC /
1.7  0.8  / DISK  0 0 0  0 0 1  5.0  4.75 / SPECTRUM  1.0 0.8 0.6
0.0  0.0  3.7  4.23  8.90 / GAUSSIAN 1.7-6  1.0-6 / FIXEC 0 0 1 /
2.7  5.3  / SPHERE-SS 3Z 10 0.0 15 0 45 / CURVE 10 .001  8 .005
6 .010  4 .15  3 .5  2 1.7  1 2.6  .9 1.3  .7 .85  .5 .6  .3 .2
.1  .05 11.5 0  1.0 0  / DELAYED 0 1.0+6 / DISTRIBUTION -2 0 0
1.0  1.0  0.9  0.81  0.8  0.64  0.7  0.49  0.5  0.25  0.3  0.09
0.0  0.  -1.0  0.0  /

```

LAST

TABLE IV SUMMARY OF AVAILABLE SOURCE ENERGY, TIME, AND DIRECTION DEPENDENT INPUTS

The input on any line may stop at any indicated comma if further restriction of the source is not desired. Each description is ended with a slash.

LABEL	INPUT QUANTITIES
ENERGY ↑ ↓	"SINGLE" group number
	"FISION"
	"FISSION" , BIAS $B_1 B_2 B_3 \dots B_N$
	"SPECTRUM" $S_1 S_2 S_3 \dots S_N$, "BIAS" $B_1 E_2 B_3 \dots S_N$
↓	"CURVE" $E_1 S_1 E_2 S_2 E_3 S_3 \dots E_M S_M$, "BIAS" $B_1 B_2 B_3 \dots S_N$
TIME ↑ ↓	"DELTA" t_0
	"GAUSSIAN" $t_0 \Delta t$
	"DELAYED" t_0
	"DISTRIBUTION" $t_1 S_1 t_2 S_2 t_3 S_3 \dots t_M S_M$
ANGLE ↑ ↓	"FIXED" $u v w$
	"ISOTROPIC" , $u_{ref} v_{ref} w_{ref} \phi_{min} \phi_{max}$, $u_2 v_2 w_2 \theta_{min} \theta_{max}$
	"COSINE" $u_{ref} v_{ref} w_{ref}$
	"DISTRIBJTION" $u_{ref} v_{ref} w_{ref} \mu_1 S_1 \mu_2 S_2 \mu_3 S_3 \dots \mu_M S_M$

Block XIX Alternate Source Description

("SOURCE")

If the previously described method of specifying the initial problem source is not satisfactory, an alternate method exists. This alternate method consists of the user writing his own subroutine, which describes the source, and then inserting this subroutine into an assembly containing the rest of the program. The present input routines have the capability of reading and storing data into the core for use in a user-written routine.

The activation of the alternate method is made in the input description of the source data block. In this case, the input is:

"SOURCE" "SPECIAL" N X₁ X₂ X₃ X_N "LAST"

The value N informs the code as to the number of input parameters which are to follow. The code will check to insure that there are exactly N parameters and will then print them out. N may be zero. The use of these parameters is up to the specially written subroutine. Each of the input parameters will be stored as a floating point number in blank common starting with location LSOR+1. The value of LSOR will be found in the first location of labeled common SORKEEP.

Subroutine SOURCE must be written by the user and inserted in the main link of the program to replace the presently existing routine of that name. The argument list for this subroutine is:

(X,Y,Z,IG,AGE,U,V,W,WT)

where:

X = x position of the source
 Y = y position of the source
 Z = z position of the source
 IG = energy group in which the source is born
 AGE = age (time) associated with the source when it is born
 U = x direction cosine of the source's direction
 V = y direction cosine of the source's direction
 W = z direction cosine of the source's direction
 WT = initial statistical weight assigned to a source particle
 (usually equal to one if source is unbiased)

SOURCE is called each time this list of arguments is needed for a new source particle. Reference 6 is useful in describing how to specify a source.

A version of the MORSE-L code containing a user written SOURCE routine may still be used with the normal source package as described previously. The special routines are triggered only when the word "SPECIAL" is inserted.

An example is provided which generates a uniform source per unit length along a spiral with one end at (0,0,0) and the other at (10,0,0). The radius of the spiral and the number of turns are read in the input (in that order). The initial energy is always assumed to be in group 2, the age is set to zero, and the directions chosen isotropically.

Example SOURCE routine:

```

SUBROUTINE SOURCE(X,Y,Z,IG,AGE,U,V,W,WT)
COMMON /SORKEEP /LSOR,DUM(11)
COMMON C (1)
DATA(IT=0)
C FOLLOWING OUTPUTS DESCRIPTION OF THIS ROUTINE
IF(IT) , ,10
IT=1
WRITE OUTPUT TAPE 3,100
100 FORMAT(25H SOURCE - SPIRAL ROUTINE)
C C(LSOR+1) CONTAINS RADIUS OF SPIRAL, C(LSOR+2) CONTAINS NUMBER OF TURNS
10 RAN=RNFL(0)
X=10.*RAN
ROT=6.28318*C(LSOR+2)*RAN
Y=C(LSOR+1)*SINF(ROT)
Z=C(LSOR+1)*COSF(ROT)
IG=2
AGE=0.0
WT=1.0
W=1.0-2.0*RNFL(0)
CONS=SQRTF(1.0-W*W)
THETA=6.28318*RNFL(0)
U=CONS*SINF(THETA)
V=CONS*COSF(THETA)
RETURN
END

```

Example input:

```

SOURCE SPECIAL 2 5.739 12.0 LAST

```

Block XX End Card

("END")

The end of each problem is indicated by the presence of the single word "END". Though this word may appear anywhere on an input card, the error routines are capable of finding the beginning of a new problem only when this word occurs in the first three columns of an input card. All data on a card after the "END" word will be ignored.

V CODE OUTPUT

The MORSE-L output includes titles so that each printed item can be recognized and identified. This section will discuss output which is not clear after reading the input section. Reference to the example problem's output, in the next section, will greatly assist the reader. The output is discussed in the order in which it comes from the machine.

1. Basic Parameters

Printed as read except for the energy cut offs which have been set if input as zero and the initial random number option if the number itself was input. The last output line always will specify that CRT plots are to be made and will not indicate their security classification. The machine, date of run, time, and code version number are added at the bottom of the page.

2. Detector related quantities

Printed as read with explanations

3. Geometry

Printed as read with expansion of some inputs. Box and block identifiers and block boundaries omitted in the input will be printed in the output as if they had been supplied. Also medium and region numbers will be printed as they are to be used in the problem. The specified CRT pictures will be drawn. For these pictures, it should be noted that the plotting routine sweeps across the geometry from right to left starting with the bottom of the picture and working towards the top. The sweeps are parallel to the bottom of the printed page, not to the geometry figure's bottom. Each time a change of medium or region is found, a dot is plotted and, if it is the first time such a combination has been found in this area, a label indicating these two numbers will be added to the plot. The title block of each CRT plot identifies the location of the plot.

4. Material definitions and cross sections

Printed as input or as read from the cross section library and as calculated for this problem. The equivalence table is not printed if it has not been altered by input. An indication of the room available for cross section storage is shown. The user need not worry about space unless the indication is for negative additional materials with a packed mode of operation.

In the cross section printout, PNABS is the probability of non-absorption, PGAMMA is the probability of a neutron making a gamma and PFISS is the probability of making a fission neutron. If zero total cross sections were specified, they will be set to 10^{-99} in order to avoid division errors.

5. Random Walk and production parameters

Printed as input.

6. Source

As input with additional derived data in a few cases. This data is followed by an indication of the size of the bank established to store secondary particles produced by fission, gamma production, or splitting.

7. Map

Most of the data and results obtained during code operation are stored dynamically in blank common. A map is given of where certain variables may be found. This is of use only in case of problem malfunction or an operator interrupt which results in a core dump. If a problem has run for some time before this terminal dump, it may be worthwhile to obtain the desired results from the dump rather than rerunning the problem. In order that the user may know how to do this on his own, we offer the following explanation.

Three separate numbers are stored for each quantity calculated by the code. The first of these is the sum of results obtained during the present batch. The second is a sum of the results per batch times the number of particles started per batch for all batches before the present one. The third quantity is the sum of the squares of each batch result times the number of particles per batch; again for all batches before the present one. The last two quantities may be used to obtain the average result and its standard deviation. Each quantity is stored as if it was a Fortran array of the type $X(I,J,K, \dots)$ where the leftmost variable moves most rapidly and the rightmost the slowest. The maximum dimensions of these arrays are:

uncollided and total response
 $U(NRESP,ND,K)$
 energy dependent fluence
 $QE(NE,ND,K)$
 time dependent response
 $QT(NRESP,NT,ND,K)$
 time and energy dependent fluence
 $QTE(NT,NE,ND,K)$
 angle and energy dependent fluence
 $QAE(NA,NE,ND,K)$

where: NRESP is the maximum number of response functions
 ND is the number of detectors
 NE is the number of energy bins
 NT is the maximum number of time bins
 NA is the number of angle bins
 K is 1, 2, or 3 as explained above.

The values stored in the arrays will probably not have been divided by the bin widths or multiplied by the normalization factors or divided by the detector volume or area (if applicable).

In addition to the above, the total response for each detector and response function for each previous batch is stored within the core at the indicated location.

8. Batch results

Summary results for each batch are printed at the completion of each batch. The average source parameters indicate the operation of the source package while the counters indicate the number of particles started or generated and their termination. If more particles are started than terminated, it is possible that particles are scattering so many times that their statistical weight underflows the machine. Russian roulette should therefore be tried.

9. Final Summaries

The final summaries exist to give the user an idea of what happened during his problem run. Though they convey results, they were not meant to be the real problem results but, rather, indicators of a successful or unsuccessful problem. The first part merely presents the sum of the batch results described above. Then comes the total number of scattering collisions by geometrical medium number. These are then followed by a series of counters. Each counter presents data based upon energy group number (not bins) and statistical region number. Both the number of events recorded and the sum of the statistical weights, normalized to one average source particle, are shown. The weight represents the real result while the number of events is only an indication of the accuracy of the answer. Not all counters are used in each problem but only those applicable to the problem. The available counters are:

- a. Real scattering - sums the statistical weight of particles as they enter a collision. The weights shown may be divided by the region's volume and its total cross section (if only one material exists within the region) to obtain an estimate of the average fluence within the region and for a given energy group.
- b. Scattering source - tabulates the weight of particles as they exit from a collision.

- c. Fission production probability - sums the incident weight of a particle entering a collision times the probability of producing a fission neutron.
- d. Fission production - sums the weights of fission neutrons produced by the energy of the produced neutron. The sum, in any region, of this counter should approximate the sum of the fission probability counter above if fission produced particles are being followed.
- e. Secondary production probability - like fission probability but indicates secondary gamma production.
- f. Secondary gamma production - like fission production but sums each contribution twice; first as a function of incident neutron energy and, second, by produced gamma energy. Sum should approximate twice the sum of the probability (e) above.
- g. Splitting counter - lists number and energy of particles produced by splitting.
- h. Russian roulette kills - number and energy of particles killed while involved in a Russian roulette game.
- i. Russian roulette survivals - like above but those that survive.

10. Results

All results are presented as two output quantities. The first is the result itself while the second is the fractional standard deviation (FSD). This latter quantity is one standard deviation divided by the absolute value of the quantity itself. The FSD is a tag indicating the validity of the result.

The first output is always the detector responses. There will be values for each detector and each response function both for uncollided and total responses. The uncollided represents the contribution at the detector by particles which have had no collision since they were generated by the source routine. The total response includes both the uncollided response as well as that response caused by scattered particles.

Following the printout of the total response, there will be one or more pages of output giving the total response for each detector and response function combination for each completed batch which was run. This is the only place within the code which lists results for each batch. Immediately under the result for the last batch will be found the average over all batches, the estimated standard deviation (not FSD) for this result, the standard deviation of the above distribution (previous number times the square root of the number of batches), and a number labelled "W-test". The W-test results are an indication if the batch by batch results have a normal distribution (which they should). A value for the W-test greater than ten (percent) indicates that both the average and standard deviation are meaningful. A value between one and ten indicate that the average is meaningful but that the standard deviation is not. Values less than one indicated that both the average and standard deviation may not be meaningful. Our experience to date has shown that results which pass the W-test always have been good answers, while those which fail this test sometimes have been good and sometimes have been bad. Usually, the failure of this test is an indication of insufficient initial source particles. References 7 and 8 discuss the W-test in more detail.

It is appropriate to discuss the units of the output at this point. In a standard problem, the integrated fluence (or current) will have units of particles per square centimeter per average source particle. This is exactly true if the normalization factor for each detector was given as one (no units). The detector response will then have units of (particles/cm²) (normalization factor units) (detector response units) per average source particle. As an example, if the normalization was to 10⁷ source particles and the detector response function was in Rem/particle/cm², the detector response would be in Rem. If the normalization factor equaled the detector's volume, in cc., and the response function equaled the detector's macroscopic (n,α) cross section, the indicated response would be in units of alphas produced per average source particle.

The time dependent response will have units similar to those shown above except they will be divided by time (in seconds). The indicated output is the average value within the bin limits.

The energy dependent fluence (or current, if the detector is estimating that quantity) has units of (particles/cm²) times the normalization factor units per MEV per average source particle. The energy and time dependent fluence has these units divided by seconds while the energy and angle dependent fluence has units of particles/cm² times the normalization factor units per MEV per steradian per average source particle.

If a steady state problem has been run, the time dependence of the source and result has no meaning: The source normalization factor can be assumed to have the units of per second when interpreting the output.

Note that an average source particle includes both neutrons and gammas. This fact should be kept in mind in normalizing to a fixed number of source neutrons from fission.

Both printed output and CRT plots are provided for all the above results. When energy dependent plots are made, separate plots are made for neutrons and gamma rays. The simulated 3D pictures are useful only in understanding the output, not to convey numerical results.

11. Punched cards

Upon input option or when a problem is terminated by sense switch one depression, the computed results will be punched onto cards. These cards may be used to combine the results of several problems, to enable data to be plotted by special routines, or as the input to other codes. In case of problem termination, the punched output may be combined with the output of a subsequent problem, started with a different random number, to effectively give a re-start capability. Each punched output gives a value and then the FSD associated with that value. All numerical results are punched with a (6E12.5) format. The output will occur as if it had been written with the following Fortran statements. Items not calculated by a given problem will be omitted. The first card in any given group carries the indicated title. The symbols are defined in the discussion of the map of blank common above.

- a. Title card (columns 1-72)
- b. Uncollided response (columns 1-19)
 $((U(I,J)), I=1, NRESP, J=1, ND)$
- c. Total response (columns 1-14)
 $((T(I,J), FSD(I,J)), I=1, NRESP, J=1, ND)$
- d. Energy dependent fluence (columns 1-24)
 $((QE(I,J), FSD(I,J)), I=1, NE, J=1, ND)$
- e. Time dependent response (columns 1-23)
 $((QT(I,J,K), FSD(I,J,K)), I=1, NRESP, J=1, NT, K=1, ND)$
- f. Time and energy dependent fluence (columns 1-33)
 $((QTE(I,J,K), FSD(I,J,K)), I=1, NT, J=1, NE, K=1, ND)$
- g. Angle and energy dependent fluence (columns 1-34)
 $((QAE(I,J,K), FSD(I,J,K)), I=1, NA, J=1, NE, K=1, ND)$

VI EXAMPLE PROBLEM

An example problem has been provided so that the reader may see a complete problem. The input, as well as the output, is shown on the following pages. This problem illustrates the use of MORSE-L. It does not necessarily convey to the user the "correct" way to solve this problem or was it meant to convey magic parameters to be used in other problems..

This problem, which does not represent any specific experiment or project, concerns itself with the calculation of neutron and secondary gamma fluences. The source is considered to be a lead shielded spherical Ra-Be neutron source suspended at the bottom point of a wood pyramid. This assembly is floated in sea water. A hole, one inch in diameter, is drilled off-center into the wood from the flat top towards the source sphere. The fluence is to be calculated by means of a point estimator at the center and at the edge of the top surface. Other problem details are evident in the problem output.

TPW:dmb

EXAMPLE PROBLEM FOR MORSE-L REPORT

```

BASIC 30 15 45 3 1 YES 1 YES NO NO 50 100 25.0 0 0 0.0
NO YES NO YES 0. 0. 0. 2 YES NO LAST
DETECTOR FLUENCE POINT 0. 0. 37.85 0 1.7E+7 0. 0. 1.
FLUENCE POINT 15.155 37.85 0 1.7E+7 0. 0. 1. LAST
DRF 30R1. 15R0. 30R1. 15R1. 30P0. 9.09 7.45 6.10 5.00 4.09
3.35 2.74 2.25 1.84 1.51 1.23 1.01 .83 .68 .56 LAST
ENERGY-BIN 3 6 8 11 12 14 16 18 20 24 26 30 31 32 33 34
35 36 37 38 39 40 41 42 43 44 45 LAST
TIME-BIN 0. 1.5-9 2.-9 5.-9 1.-8 3.-8 5.-8 7.-8 1.-7 3.-7
7.-7 1.-6 1.-5 1.-4 1.-3 1.-2 LAST
ANGLE-BIN 0. .2 .4 .6 .8 .9 .95 1. LAST
GEOMETRY
BOX-X -100 +100 / BOX-Y -100 +100 / BOX-Z -20 +35.31 /
BLOCK-Z -20 +5.0 +35.31 /
BLOCK 1 1 1
SECTOR SOURCE 1 1 -7 / SECTOR IRON 2 2 +7 -8 / SECTOR LEAD 3 2 +8 -9 /
SECTOR WATER-A 4 3 +9 -10 / SECTOR WATER-B 4 4 +10 -11 / SECTOR
WATER-C 4 5 +11 -12 / SECTOR WATER-D 4 6 +12 -13 / SECTOR WATER-E
4 7 +13 -14 / SECTOR WATER-F 4 8 +14 -15 / SECTOR WATER-G 4 9 +15 -16
/ SECTOR WATER-H 4 10 +16 -18 / SECTOR WATER-I 4 11 +18 /
BLOCK 1 1 2
SECTOR HOLE 1000 24 -6 +10 /
SECTOR WOOD-A 5 24 -1 -2 -3 -4 -10 /
SECTOR WOOD-B 5 24 -1 -2 -3 -4 +10 +6 -11 /
SECTOR WOOD-C 5 25 -1 -2 -3 -4 +6 +11 -13 /
SECTOR WOOD-D 5 26 -1 -2 -3 -4 +6 +13 -15 /
SECTOR WOOD-E 5 27 -1 -2 -3 -4 +15 /
SECTOR WATER-1 4 12 -10 +1 /
SECTOR WATER-1 4 12 -10 +3 /
SECTOR WATER-1 4 12 -10 -1 -3 +2 /
SECTOR WATER-1 4 12 -10 -1 -3 +4 /
SECTOR WATER-2 4 13 +10 -11 +1 /
SECTOR WATER-2 4 13 +10 -11 +3 /
SECTOR WATER-2 4 13 +10 -11 -1 -3 +2 /
SECTOR WATER-2 4 13 +10 -11 -1 -3 +4 /
SECTOR WATER-3 4 14 +11 -12 +1 /
SECTOR WATER-3 4 14 +11 -12 +3 /
SECTOR WATER-3 4 14 +11 -12 -1 -3 +2 /
SECTOR WATER-3 4 14 +11 -12 -1 -3 +4 /
SECTOR WATER-4 4 15 +12 -13 +1 /
SECTOR WATER-4 4 15 +12 -13 +3 /
SECTOR WATER-4 4 15 +12 -13 -1 -3 +2 /
SECTOR WATER-4 4 15 +12 -13 -1 -3 +4 /
SECTOR WATER-5 4 16 +13 -14 +1 /
SECTOR WATER-5 4 16 +13 -14 +3 /
SECTOR WATER-5 4 16 +13 -14 -1 -3 +2 /
SECTOR WATER-5 4 16 +13 -14 -1 -3 +4 /
SECTOR WATER-6 4 17 +14 -15 +1 /
SECTOR WATER-6 4 17 +14 -15 +3 /
SECTOR WATER-6 4 17 +14 -15 -1 -3 +2 /
SECTOR WATER-6 4 17 +14 -15 -1 -3 +4 /
SECTOR WATER-7 4 18 +15 -16 +1 /
SECTOR WATER-7 4 18 +15 -16 +3 /
SECTOR WATER-7 4 18 +15 -16 -1 -3 +2 /
SECTOR WATER-7 4 18 +15 -16 -1 -3 +4 /
SECTOR WATER-8 4 19 +15 -17 +1 /
SECTOR WATER-8 4 19 +15 -17 +3 /
SECTOR WATER-8 4 19 +15 -17 -1 -3 +2 /
SECTOR WATER-8 4 19 +15 -17 -1 -3 +4 /

```

Example Problem Input

-90-

MOR-6

SECTOR WATER-9 4 20 +17 -18 /
 SECTOR WATER-10 4 21 +18 -19 /
 SECTOR WATER-11 4 22 +19 -20 /
 SECTOR WATER-12 4 23 +20 /
 SURFACES 1 PLANE 0. 0. 5. -15.155 -15.155 35.31 15.155
 -15.155 35.31 0.0 -15.155 5.0 /
 2 PLANE 0. 0. 5. 15.155 -15.155 35.31 15.155 15.155 35.31
 15.155 0. 5. /
 3 PLANE 0. 0. 5. 15.155 15.155 35.31 -15.155 15.155 35.31
 0. 15.155 5.0 /
 4 PLANE 0. 0. 5. -15.155 15.155 35.31 -15.155 -15.155 35.31
 -15.155 0. 5.0 /
 6 CYLINDER 0. 0. 5 35.31 0. 0. 0. 1.27 /
 7 SPHERE 0. 0. 0. 1.16 /
 8 SPHERE 0. 0. 0. 2.50 /
 9 SPHERE 0. 0. 0. 5.00 /
 10 SPHERE 0. 0. 0. 10.0 /
 11 SPHERE 0. 0. 0. 15.0 /
 12 SPHERE 0. 0. 0. 20.0 /
 13 SPHERE 0. 0. 0. 25.0 /
 14 SPHERE 0. 0. 0. 30.0 /
 15 SPHERE 0. 0. 0. 35.0 /
 16 SPHERE 0. 0. 0. 40.0 /
 17 SPHERE 0. 0. 0. 45.0 /
 18 SPHERE 0. 0. 0. 50.0 /
 19 SPHERE 0. 0. 0. 55.0 /
 20 SPHERE 0. 0. 0. 60.0 /

PICTURE 6Z LAST

MIX 1 BE 0 3 .117 2 FE 0 3 .0847 3 PB 0 3 .033
 4 H 0 3 .0668 4 O 0 3 .0334 4 NA 0 3 .00026
 4 CL 0 3 .00036 5 C 0 3 .0116 5 H 0 3 .0174
 5 O 0 3 .0060 5 K 0 3 2.-5 LAST

CROSS-SECTION

X**COMFTON 0 0 0
 99R 0. 99R 0. 99R 0. 99R 0. 99R 0. MORSE- 1
 99R 0. 99R 0. 99R 0. 99R 0. 99R 0. MORSE- 2
 99R 0. 99R 0. 56R 0. 1- 1.436043 2- 4.80431046R 0. MORSE- 3
 1- 1.518138 2- 5.983150 2- 8.51857045R 0. 1- 1.609812 2- 5.395300MORSE- 4
 2- 8.996540 2- 7.28522044R 0. 1- 1.712520 2- 5.746440 2- 9.528180MORSE- 5
 2- 7.671440 2- 6.4471043R 0. 1- 1.827930 2- 6.142710 1- 1.012100MORSE- 6
 2- 8.095620 2- 6.769150 2- 5.87758042R 0. 1- 1.957926 2- 6.591360MORSE- 7
 1- 1.078360 2- 8.561740 2- 7.118430 2- 6.154960 2- 5.49017041R 0. MORSE- 8
 1- 2.104614 2- 7.100720 1- 1.152500 2- 9.073650 2- 7.496110 2- 6.452090MORSE- 9
 2- 5.737100 2- 5.22752040R 0. 1- 2.270310 2- 7.680260 1- 1.235530MORSE-10
 2- 9.634760 2- 7.903240 2- 6.769060 2- 5.999190 2- 5.454410 2- 5.050830MORSE-11
 39R 0. 1- 2.457433 2- 8.340610 1- 1.328470 1- 1.024770 2- 8.339900MORSE-12
 2- 7.105280 2- 6.276190 2- 5.694210 2- 5.265630 2- 4.93409038R 0. MORSE-13
 1- 2.668686 2- 9.093570 1- 1.432310 1- 1.091350 2- 8.804560 2- 7.459260MORSE-14
 2- 6.566980 2- 5.946590 2- 5.493100 2- 5.143140 2- 4.85988037R 0. MORSE-15
 1- 2.906439 2- 9.952100 1- 1.547960 1- 1.163110 2- 9.294020 2- 7.828550MORSE-16
 2- 6.870820 2- 6.212700 2- 5.734390 2- 5.366510 2- 5.068560 2- 4.816710MORSE-17
 36R 0. 1- 3.173170 1- 1.092970 1- 1.676140 1- 1.239610 2- 9.802940MORSE-18
 2- 8.209920 2- 7.186890 2- 6.492830 2- 5.991950 2- 5.607310 2- 5.295030MORSE-19
 2- 5.129870 2- 4.79714035R 0. 1- 3.470490 1- 1.204110 1- 1.817200MORSE-20
 1- 1.320010 1- 1.032400 2- 8.600420 2- 7.516210 2- 6.791070 2- 6.271120MORSE-21
 2- 5.871540 2- 5.545310 2- 5.266230 2- 5.019470 2- 4.79654034R 0. MORSE-22
 1- 3.800010 1- 1.330350 1- 1.971030 1- 1.403030 1- 1.084950 2- 8.999910MORSE-23
 2- 7.854720 2- 7.117110 2- 6.583120 2- 6.170550 2- 5.830300 2- 5.535680MORSE-24
 2- 5.272500 2- 5.032140 2- 4.81231033R 0. 1- 4.161960 1- 1.472670MORSE-25
 1- 2.136950 1- 1.487040 1- 1.137470 2- 9.416760 2- 8.249560 2- 7.492170MORSE-26

2- 6.950620 2- 6.526440 2- 6.169830 2- 5.855650 2- 5.571160 2- 5.309780 MORSE-27
 2- 5.067910 2- 4.843350 30R 0. MORSE-28
 WALK 1 2 1 20 0. 0.005 0.2 -0.75 1 2 21 29 0. 0.005 0.2 0.0
 3 27 1 29 0. 0.005 0.33 0.0 1 27 30 30 0. 0.2 0.5 0.0
 1 27 31 44 0. 0.005 0.33 0.0 1 27 45 45 0. 0.2 0.5 0.0

LAST

PRODUCTION 0 0 1 25 0 .1 0 0 26 45 0 .035 LAST

SOUPCE

.0760 15.0 / SPHERE 0. 0. 0. 1.27 / SPECTRUM 3R0. .0083
 .016 .0376 .1084 .0763 .2506 .1687 .1438 .0729 .0347 .0347
 .0236 .016 .0056 .0014 .0007 .0007 25R0. / DELTA 0 /
 ISCTROPIC 0. 0. 1.0 0. 32.0 /
 .07045 10.0 / SPHERE 0. 0. 0. 1.27 / SPECTRUM 3R0. .0083
 .016 .0376 .1084 .0763 .2506 .1687 .1438 .0729 .0347 .0347
 .0236 .016 .0056 .0014 .0007 .0007 25R0. / DELTA 0 /
 ISCTROPIC 0. 0. 1.0 32.0 45.0 /
 .35355 7.5 / SPHERE 0. 0. 0. 1.27 / SPECTRUM 3R0. .0083
 .016 .0376 .1084 .0763 .2506 .1687 .1438 .0729 .0347 .0347
 .0236 .016 .0056 .0014 .0007 .0007 25R0. / DELTA 0 /
 ISCTROPIC 0. 0. 1.0 45.0 90.0 /
 .5000 2.0 / SPHERE 0. 0. 0. 1.27 / SPECTRUM 3R0. .0083
 .016 .0376 .1084 .0763 .2506 .1687 .1438 .0729 .0347 .0347
 .0236 .016 .0056 .0014 .0007 .0007 25R0. / DELTA 0 /
 ISCTROPIC 0. 0. 1.0 90.0 180.0 / LAST

END

Input (cont.)

-92-

MOR-6

1
EXAMPLE PROBLEM FOR MORSE-L REPORT

BASIC PARAMETERS

30 NUMBER OF NEUTRON ENERGY GROUPS
15 NUMBER OF GAMMA ENERGY GROUPS
45 NUMBER OF GROUPS DOWNSCATTER PLUS ONE IN INPUT CROSS SECTION SET
3 MAXIMUM ORDER OF LEGENDRE EXPANSION OF THE CROSS SECTIONS
1 NUMBER OF ISOTOPES (OR MIXTURES) TO BE READ FROM CARDS

YES NEGATIVE SCATTERING PROBABILITIES (FOR POINT FLUX ESTIMATOR) SET TO ZERO
1 PRINT OPTION FOR CROSS SECTION DATA (0 GIVES MINIMUM, 2 REASONABLE, 5 EVERYTHING)
YES CROSS SECTION LIBRARY TAPE UNLOADED AFTER ITS USE IN THIS PROBLEM
NO FISSION -- FOLLOW NEUTRONS PRODUCED BY FISSION
NO ADJOINT PROBLEM

50 NUMBER OF INITIAL SOURCE PARTICLES PER BATCH
100 MAXIMUM NUMBER OF BATCHES (IF TIME ALLOWS)
2.50E+01 MAXIMUM RUNNING TIME (MINUTES)
30 MINIMUM ENERGY CUT-OFF -- NUMBER OF THE LAST GROUP IN WHICH NEUTRONS WILL BE FOLLOWED
45 MINIMUM ENERGY CUT-OFF -- NUMBER OF THE LAST GROUP IN WHICH GAMMAS WILL BE FOLLOWED
0. MAXIMUM AGE CUT-OFF -- GREATEST AGE A PARTICLE CAN HAVE IN RANDOM WALK PROCESS (SEC.)
NO NON-LEAKAGE -- MODIFY RANDOM WALK SO THAT NO PARTICLE WILL ESCAPE FROM THE SYSTEM
YES RUSSIAN ROULETTE USED TO TERMINATE THE RANDOM WALK
NO SPLIT PARTICLES WHEN THEIR WEIGHT IS OVER A GIVEN AMOUNT
YES EXPONENTIAL TRANSFORM USED TO STRETCH A PARTICLES PATH TOWARD THE FOLLOWING POINT IN SPACE
 $x = 0.$ $y = 0.$ $z = 0.$
2 INITIAL RANDOM NUMBER OPTION (17170743676371402011)
YES PUNCH OUTPUT
YES CRT OUTPUT

Printed Output

-93-

MOR-6

DATE L09/15
CLCK 11.858
VERSION 6

1 DETECTOR DEFINITIONS

DETECTOR NUMBER 1

QUANTITY CALCULATED ---FLUENCE
METHOD USED --- POINT ESTIMATOR
X POSITION OF DETECTOR --- 0.
Y POSITION OF DETECTOR --- 0.
Z POSITION OF DETECTOR --- 3.78500E+01
FLUENCE CALCULATED FROM SCATTERINGS IN ALL MEDIA
NORMALIZATION FACTOR --- 1.70000E+07
DIRECTION COSINE FROM X-AXIS TO DEFINE ANGLE BINS --- 0.
DIRECTION COSINE FROM Y-AXIS TO DEFINE ANGLE BINS --- 0.
DIRECTION COSINE FROM Z-AXIS TO DEFINE ANGLE BINS --- 1.00000E+00

DETECTOR NUMBER 2

QUANTITY CALCULATED ---FLUENCE
METHOD USED --- POINT ESTIMATOR
X POSITION OF DETECTOR --- 1.51550E+01
Y POSITION OF DETECTOR --- 1.51550E+01
Z POSITION OF DETECTOR --- 3.78500E+01
FLUENCE CALCULATED FROM SCATTERINGS IN ALL MEDIA
NORMALIZATION FACTOR --- 1.70000E+07
DIRECTION COSINE FROM X-AXIS TO DEFINE ANGLE BINS --- 0.
DIRECTION COSINE FROM Y-AXIS TO DEFINE ANGLE BINS --- 0.
DIRECTION COSINE FROM Z-AXIS TO DEFINE ANGLE BINS --- 1.00000E+00

DETECTOR RESPONSE FUNCTIONS

RESPONSE NUMBER 1

1 1.000E+00	2 1.000E+00	3 1.000E+00	4 1.000E+00	5 1.000E+00	6 1.000E+00
7 1.000E+00	8 1.000E+00	9 1.000E+00	10 1.000E+00	11 1.000E+00	12 1.000E+00
13 1.000E+00	14 1.000E+00	15 1.000E+00	16 1.000E+00	17 1.000E+00	18 1.000E+00
19 1.000E+00	20 1.000E+00	21 1.000E+00	22 1.000E+00	23 1.000E+00	24 1.000E+00
25 1.000E+00	26 1.000E+00	27 1.000E+00	28 1.000E+00	29 1.000E+00	30 1.000E+00
31 0.	32 0.	33 0.	34 0.	35 0.	36 0.
37 0.	38 0.	39 0.	40 0.	41 0.	42 0.
43 0.	44 0.	45 0.			

RESPONSE NUMBER 2

1 0.	2 0.	3 0.	4 0.	5 0.	6 0.
7 0.	8 0.	9 0.	10 0.	11 0.	12 0.
13 0.	14 0.	15 0.	16 0.	17 0.	18 0.
19 0.	20 0.	21 0.	22 0.	23 0.	24 0.
25 0.	26 0.	27 0.	28 0.	29 0.	30 0.
31 1.000E+00	32 1.000E+00	33 1.000E+00	34 1.000E+00	35 1.000E+00	36 1.000E+00
37 1.000E+00	38 1.000E+00	39 1.000E+00	40 1.000E+00	41 1.000E+00	42 1.000E+00
43 1.000E+00	44 1.000E+00	45 1.000E+00			

RESPONSE NUMBER 3

1 0.	2 0.	3 0.	4 0.	5 0.	6 0.
7 0.	8 0.	9 0.	10 0.	11 0.	12 0.
13 0.	14 0.	15 0.	16 0.	17 0.	18 0.
19 0.	20 0.	21 0.	22 0.	23 0.	24 0.
25 0.	26 0.	27 0.	28 0.	29 0.	30 0.
31 9.090E+00	32 7.450E+00	33 6.100E+00	34 5.000E+00	35 4.090E+00	36 3.350E+00

Output (cont.)

-94-

MOR-6

1	37	2.740E+03	38	2.250E+00	39	1.840E+00	40	1.510E+00	41	1.230E+00	42	1.010E+00
	43	8.300E-01	44	6.800E-01	45	5.600E-01						

ENERGY BIN DEFINITIONS

BIN NO.	UPPERMOST GROUP	LOWERMOST GROUP
1	1	3
2	4	6
3	7	8
4	9	10
5	11	12
6	13	14
7	15	16
8	17	18
9	19	20
10	21	24
11	25	26
12	27	30
13	31	31
14	32	32
15	33	33
16	34	34
17	35	35
18	36	36
19	37	37
20	38	38
21	39	39
22	40	40
23	41	41
24	42	42
25	43	43
26	44	44
27	45	45

TIME BIN DEFINITIONS

BINS FOR ALL DETECTORS

BIN NO.	MAX. TIME	DELTA-TIME
1	1.5000E-09	*
2	2.0000E-09	5.0000E-10
3	5.0000E-09	3.0000E-09
4	1.0000E-08	5.0000E-09
5	3.0000E-08	2.0000E-08
6	5.0000E-08	2.0000E-08
7	7.0000E-08	2.0000E-08
8	1.0000E-07	3.0000E-08
9	3.0000E-07	2.0000E-07
10	7.0000E-07	4.0000E-07
11	1.0000E-06	3.0000E-07
12	1.0000E-05	9.0000E-06
13	1.0000E-04	9.0000E-05
14	1.0000E-03	9.0000E-04
15	1.0000E-02	*

* CALCULATED AFTER PROBLEM IS RUN

Output (cont.)

-95-

MOR-6

1 --ANGLE BIN DEFINITIONS

BIN NO.	LOWER LIMIT (COSINES)	UPPER LIMIT (COSINES)
1	-1.0000E+00	0.
2	0.	2.0000E-01
3	2.0000E-01	4.0000E-01
4	4.0000E-01	6.0000E-01
5	6.0000E-01	8.0000E-01
6	8.0000E-01	9.0000E-01
7	9.0000E-01	9.5000E-01
8	9.5000E-01	1.0000E+00

GEOMETRY SPECIFICATIONS

BOX BOUNDARIES

IDENTIFICATION
IX IY IZ

POSITION
Y

1 1 1 -1.00000E+02 TO 1.00000E+02 -1.00000E+02 TO 1.00000E+02 -2.00000E+01 TO 3.53100E+01

DESCRIPTION OF BOX IDENTIFIED BY IX= 1, IY= 1, IZ= 1

BLOCK BOUNDARIES WITHIN THIS BOX

IDENTIFICATION
JX JY JZ

POSITION
Y

1 1 1 -1.0000E+02 TO 1.0000E+02 -1.0000E+02 TO 1.0000E+02 -2.0000E+01 TO 5.0000E+00
1 1 2 -1.0000E+02 TO 1.0000E+02 -1.0000E+02 TO 1.0000E+02 5.0000E+00 TO 3.5310E+01

DESCRIPTION OF BLOCK IDENTIFIED BY JX= 1, JY= 1, JZ= 1

SECTOR MATERIAL STATISTICAL
IDENTIFICATION MEDIUM REGION

RELATIONSHIP TO INDICATED SURFACE EQUATIONS

SOURCE	1	1	-7	
IRON	2	2	7	-8
LEAD	3	2	8	-9
WATER-A	4	3	9	-10
WATER-B	4	4	10	-11
WATER-C	4	5	11	-12
WATER-C	4	6	12	-13
WATER-E	4	7	13	-14
WATER-F	4	8	14	-15
WATER-G	4	9	15	-16
WATER-H	4	10	16	-18
WATER-I	4	11	18	

DESCRIPTION OF BLOCK IDENTIFIED BY JX= 1, JY= 1, JZ= 2

SECTOR MATERIAL STATISTICAL
IDENTIFICATION MEDIUM REGION

RELATIONSHIP TO INDICATED SURFACE EQUATIONS

HCLE	1000	24	-6	10					
WOOD-A	5	24	-1	-2	-3	-4	-10		
WOOD-B	5	24	-1	-2	-3	-4	10	6	-11
WOOD-C	5	25	-1	-2	-3	-4	6	11	-13
WOOD-D	5	26	-1	-2	-3	-4	6	13	-15
WOOD-E	5	27	-1	-2	-3	-4	15		

Output (cont.)

-96-

MOR-6

WATER-1	4	12	-10	1			
WATER-1	4	12	-10	3			
WATER-1	4	12	-10	-1	-3	2	
WATER-1	4	12	-10	-1	-3	4	
WATER-2	4	13	10	-11	1		
WATER-2	4	13	10	-11	3		
WATER-2	4	13	10	-11	-1	-3	2
WATER-2	4	13	10	-11	-1	-3	4
WATER-3	4	14	11	-12	1		
WATER-3	4	14	11	-12	3		
WATER-3	4	14	11	-12	-1	-3	2
WATER-3	4	14	11	-12	-1	-3	4
WATER-4	4	15	12	-13	1		
WATER-4	4	15	12	-13	3		
WATER-4	4	15	12	-13	-1	-3	2
WATER-4	4	15	12	-13	-1	-3	4
WATER-5	4	16	13	-14	1		
WATER-5	4	16	13	-14	3		
WATER-5	4	16	13	-14	-1	-3	2
WATER-5	4	16	13	-14	-1	-3	4
WATER-6	4	17	14	-15	1		
WATER-6	4	17	14	-15	3		
WATER-6	4	17	14	-15	-1	-3	2
WATER-6	4	17	14	-15	-1	-3	4
WATER-7	4	18	15	-16	1		
WATER-7	4	18	15	-16	3		
WATER-7	4	18	15	-16	-1	-3	2
WATER-7	4	18	15	-16	-1	-3	4
WATER-8	4	19	16	-17	1		
WATER-8	4	19	16	-17	3		
WATER-8	4	19	16	-17	-1	-3	2
WATER-8	4	19	16	-17	-1	-3	4
WATER-9	4	20	17	-18			
WATER-10	4	21	18	-19			
WATER-11	4	22	19	-20			
WATER-12	4	23	20				

SURFACE EQUATIONS

NUMBER	REFERENCE	DEFINITION
1	SYSTEM	PLANE --- POINT ON THE PLANE (0. , 0. , 5.0000E+00) ANOTHER POINT ON THE PLANE (-1.5155E+01, -1.5155E+01, 3.5310E+01) ANOTHER POINT ON THE PLANE (1.5155E+01, -1.5155E+01, 3.5310E+01) POINT OFF PLANE WHERE EQ IS POSITIVE (0. , -1.5155E+01, 5.0000E+00)
1	SYSTEM	-1.5839749E-15 X -4.0000000E-01 Y -2.0000000E-01 Z 1.0000000E+00
2	SYSTEM	PLANE --- POINT ON THE PLANE (0. , 0. , 5.0000E+00) ANOTHER POINT ON THE PLANE (1.5155E+01, -1.5155E+01, 3.5310E+01) ANOTHER POINT ON THE PLANE (1.5155E+01, 1.5155E+01, 3.5310E+01) POINT OFF PLANE WHERE EQ IS POSITIVE (1.5155E+01, 0. , 5.0000E+00)
2	SYSTEM	4.0000000E-01 X 1.5839749E-15 Y -2.0000000E-01 Z 1.0000000E+00

```

1      3      SYSTEM      PLANE --- POINT ON THE PLANE          ( 0.          , 0.          , 5.0000E+00)
                                ANOTHER POINT ON THE PLANE      ( 1.5155E+01, 1.5155E+01, 3.5310E+01)
                                ANOTHER POINT ON THE PLANE      (-1.5155E+01, 1.5155E+01, 3.5310E+01)
                                POINT OFF PLANE WHERE EQ IS POSITIVE ( 0.          , 1.5155E+01, 5.0000E+00)

3      SYSTEM      1.5839749E-15 X      4.0000000E-01 Y      -2.0000000E-01 Z      1.0000000E+00

4      SYSTEM      PLANE --- POINT ON THE PLANE          ( 0.          , 0.          , 5.0000E+00)
                                ANOTHER POINT ON THE PLANE      (-1.5155E+01, 1.5155E+01, 3.5310E+01)
                                ANOTHER POINT ON THE PLANE      (-1.5155E+01, -1.5155E+01, 3.5310E+01)
                                POINT OFF PLANE WHERE EQ IS POSITIVE (-1.5155E+01, 0.          , 5.0000E+00)

4      SYSTEM      -4.0000000E-01 X      -1.5839749E-15 Y      -2.0000000E-01 Z      1.0000000E+00

6      SYSTEM      CYLINDER --- POINT ON CENTER-LINE      ( 0.          , 5.0000E-01, 3.5310E+01)
                                ANOTHER POINT ON CENTER-LINE ( 0.          , 0.          , 0.          )
                                RADIUS = 1.2700E+00

6      SYSTEM      1.0000000E+00 XSQ      9.9979953E-01 YSQ      -2.8314912E-02 YZ      8.8928864E-14 Z
                                2.0047374E-04 ZSQ      -1.6129000E+00

7      SYSTEM      SPHERE --- CENTER AT ( 0.          , 0.          , 0.          ) RADIUS = 1.1600E+00

7      SYSTEM      1.0000000E+00 XSQ      1.0000000E+00 YSQ      1.0000000E+00 ZSQ      -1.3456000E+00

8      SYSTEM      SPHERE --- CENTER AT ( 0.          , 0.          , 0.          ) RADIUS = 2.5000E+00

8      SYSTEM      1.0000000E+00 XSQ      1.0000000E+00 YSQ      1.0000000E+00 ZSQ      -6.2500000E+00

9      SYSTEM      SPHERE --- CENTER AT ( 0.          , 0.          , 0.          ) RADIUS = 5.0000E+00

9      SYSTEM      1.0000000E+00 XSQ      1.0000000E+00 YSQ      1.0000000E+00 ZSQ      -2.5000000E+01

10     SYSTEM      SPHERE --- CENTER AT ( 0.          , 0.          , 0.          ) RADIUS = 1.0000E+01

10     SYSTEM      1.0000000E+00 XSQ      1.0000000E+00 YSQ      1.0000000E+00 ZSQ      -1.0000000E+02

11     SYSTEM      SPHERE --- CENTER AT ( 0.          , 0.          , 0.          ) RADIUS = 1.5000E+01

11     SYSTEM      1.0000000E+00 XSQ      1.0000000E+00 YSQ      1.0000000E+00 ZSQ      -2.2500000E+02

12     SYSTEM      SPHERE --- CENTER AT ( 0.          , 0.          , 0.          ) RADIUS = 2.0000E+01

12     SYSTEM      1.0000000E+00 XSQ      1.0000000E+00 YSQ      1.0000000E+00 ZSQ      -4.0000000E+02

13     SYSTEM      SPHERE --- CENTER AT ( 0.          , 0.          , 0.          ) RADIUS = 2.5000E+01

13     SYSTEM      1.0000000E+00 XSQ      1.0000000E+00 YSQ      1.0000000E+00 ZSQ      -6.2500000E+02

14     SYSTEM      SPHERE --- CENTER AT ( 0.          , 0.          , 0.          ) RADIUS = 3.0000E+01

```

Output (cont.)

-98-

MOR-6

```

1      14      SYSTEM      1.0000000E+00 XSQ      1.0000000E+00 YSQ      1.0000000E+00 ZSQ      -9.0000000E+02

      15      SYSTEM      SPHERE --- CENTER AT ( 0.          , 0.          , 0.          ) RADIUS = 3.5000E+01

      15      SYSTEM      1.0000000E+00 XSQ      1.0000000E+00 YSQ      1.0000000E+00 ZSQ      -1.2250000E+03

      16      SYSTEM      SPHERE --- CENTER AT ( 0.          , 0.          , 0.          ) RADIUS = 4.0000E+01

      16      SYSTEM      1.0000000E+00 XSQ      1.0000000E+00 YSQ      1.0000000E+00 ZSQ      -1.6000000E+03

      17      SYSTEM      SPHERE --- CENTER AT ( 0.          , 0.          , 0.          ) RADIUS = 4.5000E+01

      17      SYSTEM      1.0000000E+00 XSQ      1.0000000E+00 YSQ      1.0000000E+00 ZSQ      -2.0250000E+03

      18      SYSTEM      SPHERE --- CENTER AT ( 0.          , 0.          , 0.          ) RADIUS = 5.0000E+01

      18      SYSTEM      1.0000000E+00 XSQ      1.0000000E+00 YSQ      1.0000000E+00 ZSQ      -2.5000000E+03

      19      SYSTEM      SPHERE --- CENTER AT ( 0.          , 0.          , 0.          ) RADIUS = 5.5000E+01

      19      SYSTEM      1.0000000E+00 XSQ      1.0000000E+00 YSQ      1.0000000E+00 ZSQ      -3.0250000E+03

      20      SYSTEM      SPHERE --- CENTER AT ( 0.          , 0.          , 0.          ) RADIUS = 6.0000E+01

      20      SYSTEM      1.0000000E+00 XSQ      1.0000000E+00 YSQ      1.0000000E+00 ZSQ      -3.6000000E+03

```

MATERIAL COMPOSITION

MEDIA	ISOTOPE (OR MIXTURE)	FLUX WEIGHTING	P-L ORDER	DENSITY
1	BE	0	3	1.170000E-01
2	FE	0	3	8.470000E-02
3	PB	0	3	3.300000E-02
4	H	0	3	6.680000E-02
4	O	0	3	3.340000E-02
4	NA	0	3	2.600000E-04
4	CL	0	3	2.600000E-04
5	C	0	3	1.160000E-02
5	H	0	3	1.740000E-02
5	O	0	3	6.000000E-03
5	K	0	3	2.000000E-05

ENERGY GROUP PARAMETERS

GROUP	ENERGY	VELOCITY	FISS SPECTRA
-------	--------	----------	--------------

1

1	1.8000E+01	5.6676E+09	9.8870E-04
2	1.5620E+01	5.2785E+09	4.6986E-04
3	1.3540E+01	4.9715E+09	4.0388E-04
4	1.1750E+01	4.5909E+09	3.5189E-04
5	1.0190E+01	4.2635E+09	2.3893E-03
6	8.8400E+00	3.9688E+09	5.8283E-03
7	7.6600E+00	3.6957E+09	6.5380E-03
8	6.6500E+00	3.4419E+09	1.6695E-02
9	5.7700E+00	3.2045E+09	1.9694E-02
10	5.0000E+00	2.9561E+09	3.7189E-02
11	4.2100E+00	2.7121E+09	5.0885E-02
12	3.5400E+00	2.4867E+09	6.2081E-02
13	2.9700E+00	2.2809E+09	7.2578E-02
14	2.5000E+00	2.0636E+09	1.0377E-01
15	1.9900E+00	1.8414E+09	1.0527E-01
16	1.5800E+00	1.6436E+09	9.7171E-02
17	1.2600E+00	1.4667E+09	8.8674E-02
18	1.0000E+00	1.3259E+09	5.6783E-02
19	8.4200E-01	1.2164E+09	4.9785E-02
20	7.0800E-01	1.1132E+09	4.3887E-02
21	5.9000E-01	1.0204E+09	3.3450E-02
22	5.0000E-01	7.9332E+08	9.5771E-02
23	2.2400E-01	5.3150E+08	3.3690E-02
24	1.0000E-01	2.4919E+08	1.4796E-02
25	1.2610E-02	8.8592E+07	6.9079E-04
26	1.5900E-03	3.1427E+07	3.1091E-05
27	2.0000E-04	1.1147E+07	1.3896E-06
28	2.5200E-05	3.9630E+06	0.
29	3.1800E-06	1.4051E+06	0.
30	4.0000E-07	3.2760E+05	0.
	1.0000E-10		
31	1.0000E+01	2.9979E+10	7.5530E-04
32	8.1896E+00	2.9979E+10	3.5380E-03
33	6.7070E+00	2.9979E+10	1.2170E-02
34	5.4928E+00	2.9979E+10	3.2440E-02
35	4.4984E+00	2.9979E+10	7.0080E-02
36	3.6840E+00	2.9979E+10	1.2730E-01
37	3.0171E+00	2.9979E+10	2.0050E-01
38	2.4709E+00	2.9979E+10	2.8080E-01
39	2.0236E+00	2.9979E+10	3.5720E-01
40	1.6572E+00	2.9979E+10	4.3020E-01
41	1.3572E+00	2.9979E+10	5.5590E-01
42	1.1115E+00	2.9979E+10	6.7590E-01
43	9.1028E-01	2.9979E+10	7.6530E-01
44	7.4549E-01	2.9979E+10	8.1750E-01
45	6.1053E-01	2.9979E+10	7.3240E-01
	5.0000E-01		

Output (cont.)

-100-

MOR-6

CROSS SECTIONS STORED IN PACKED MODE W/ LEGENDRE COEFFICIENTS --- ROOM FOR 4 ADDITIONAL MATERIALS

TAPE INPUT - ELEMENT 2	HYDROGEN	30 NEUTRON PLUS 15 GAMMA GROUPS - L-DIVISION - FEB 1972
TAPE INPUT - ELEMENT 3	BERYLLIUM	30 NEUTRON PLUS 15 GAMMA GROUPS - L-DIVISION - OCT 1971
TAPE INPUT - ELEMENT 4	CARBON	30 NEUTRON PLUS 15 GAMMA GROUPS - L-DIVISION - FEB 1972
TAPE INPUT - ELEMENT 5	OXYGEN	30 NEUTRON PLUS 15 GAMMA GROUPS - L-DIVISION - OCT 1971
TAPE INPUT - ELEMENT 6	SODIUM	30 NEUTRON PLUS 15 GAMMA GROUPS - L-DIVISION - FEB 1972

1
TAPE INPUT - ELEMENT 7 CHLORINE 30 NEUTRON PLUS 15 GAMMA GROUPS - L-DIVISION - OCT 1971
TAPE INPUT - ELEMENT 8 POTASSIUM 30 NEUTRON PLUS 15 GAMMA GROUPS - L-DIVISION - OCT 1971
TAPE INPUT - ELEMENT 9 IRON 30 NEUTRON PLUS 15 GAMMA GROUPS - L-DIVISION - OCT 1971
TAPE INPUT - ELEMENT 10 LEAD 30 NEUTRON PLUS 15 GAMMA GROUPS - L-DIVISION - FEB 1972

Output (cont.)

-101-

MOR-6

1
MACROSCOPIC CROSS SECTIONS FOR MEDIA 1

GROUP	TOTAL	SCATTER	PNABS	PGAMMA	PFISS	DOWNSCATTER PROBABILITY (GRCUP G TO G, G TO G+1, ETC.)			
1	1.000E-99	1.000E-99	1.0000	1.0000	0.	0.	0.	0.	0.
2	1.435E-01	2.021E-01	1.4085	0.0002	0.	0.1616	0.1800	0.0638	0.0690
3	1.616E-01	2.230E-01	1.3802	0.0009	0.	0.0248	0.0232	0.0214	0.0176
4	1.620E-01	2.257E-01	1.3934	0.0018	0.	0.0155	0.0185	0.0208	0.0202
5	1.783E-01	2.421E-01	1.3573	0.0021	0.	0.0000	0.0000	0.0000	0.0000
6	1.774E-01	2.411E-01	1.3591	0.0025	0.	0.3179	0.0838	0.0741	0.0657
7	1.860E-01	2.495E-01	1.3414	0.0026	0.	0.0173	0.0158	0.0135	0.0135
8	1.963E-01	2.574E-01	1.3114	0.0026	0.	0.0183	0.0208	0.0204	0.0987
9	2.049E-01	2.633E-01	1.2851	0.0025	0.	0.0000	0.0000	0.0000	0.0000
10	2.090E-01	2.617E-01	1.2526	0.0025	0.	0.2491	0.1333	0.0876	0.0784
11	2.245E-01	2.674E-01	1.1910	0.0023	0.	0.0088	0.0075	0.0082	0.0066
12	2.848E-01	3.138E-01	1.1016	0.0018	0.	0.0223	0.0224	0.1131	0.0678
13	3.684E-01	3.694E-01	1.0027	0.0014	0.	0.0000	0.0000	0.0000	0.0000
14	2.202E-01	2.137E-01	0.9705	0.0023	0.	0.2609	0.1361	0.0761	0.0807
15	2.094E-01	2.055E-01	0.9816	0.0023	0.	0.0032	0.0049	0.0056	0.0053
16	2.694E-01	2.679E-01	0.9942	0.0018	0.	0.0176	0.1064	0.0763	0.0306
17	3.559E-01	3.551E-01	0.9977	0.0014	0.	0.0000	0.0000	0.0000	0.0000
18	4.040E-01	4.033E-01	0.9983	0.0012	0.	0.2367	0.1401	0.0665	0.0767

Output (cont.)

-102-

MOR-6

1	19	4.454E-01	4.448E-01	0.9987	0.0011	0.	0.2978	0.4007	0.2529	0.0485	0.	0.	0.	0.
	20	5.491E-01	5.486E-01	0.9991	0.0009	0.	0.	0.	0.	0.	0.	0.	0.	0.
	21	4.251E-01	4.247E-01	0.9990	0.0011	0.	0.2412	0.3662	0.3926	0.	0.	0.	0.	0.
	22	4.686E-01	4.683E-01	0.9993	0.0010	0.	0.	0.	0.	0.	0.	0.	0.	0.
	23	5.853E-01	5.851E-01	0.9997	0.0008	0.	0.2520	0.7480	0.	0.	0.	0.	0.	0.
	24	6.803E-01	6.801E-01	0.9998	0.0007	0.	0.	0.	0.	0.	0.	0.	0.	0.
	25	7.018E-01	7.017E-01	0.9998	0.0007	0.	0.7229	0.2771	0.	0.	0.	0.	0.	0.
	26	7.021E-01	7.019E-01	0.9998	0.0007	0.	0.	0.	0.	0.	0.	0.	0.	0.
	27	7.020E-01	7.019E-01	0.9998	0.0007	0.	0.7308	0.2692	0.	0.	0.	0.	0.	0.
	28	7.020E-01	7.019E-01	0.9998	0.0007	0.	0.8952	0.1048	0.	0.	0.	0.	0.	0.
	29	7.021E-01	7.019E-01	0.9997	0.0011	0.	0.9008	0.0992	0.	0.	0.	0.	0.	0.
	30	6.238E-01	6.233E-01	0.9991	0.0040	0.	0.8988	0.1012	0.	0.	0.	0.	0.	0.
	31	2.975E-02	2.942E-02	0.9890	0.0000	0.	0.8994	0.1006	0.	0.	0.	0.	0.	0.
	32	3.288E-02	3.077E-02	0.9357	0.0000	0.	0.9006	0.0994	0.	0.	0.	0.	0.	0.
	33	3.667E-02	3.272E-02	0.8921	0.0000	0.	0.8990	0.1010	0.	0.	0.	0.	0.	0.
	34	4.108E-02	3.509E-02	0.8542	0.0000	0.	1.0000	0.	0.	0.	0.	0.	0.	0.
	35	4.597E-02	3.754E-02	0.8167	0.0000	0.	0.0418	0.0742	0.0634	0.0561	0.0512	0.0478	0.0455	0.0440
	36	5.154E-02	4.040E-02	0.7838	0.0000	0.	0.0430	0.0423	0.0419	0.0418	0.0418	0.0419	0.3234	0.0505
	37	5.774E-02	4.339E-02	0.7515	0.0000	0.	0.0488	0.0863	0.0736	0.0650	0.0591	0.0551	0.0523	0.0570
	38	6.458E-02	4.643E-02	0.7189	0.0000	0.	0.0494	0.0486	0.0483	0.0482	0.0483	0.2665	0.0591	0.0570
	39	7.212E-02	4.942E-02	0.6852	0.0000	0.	0.0560	0.0988	0.0840	0.0738	0.0669	0.0622	0.0591	0.0570
	40	8.024E-02	5.188E-02	0.6466	0.0000	0.	0.0557	0.0549	0.0546	0.0547	0.2222	0.0695	0.0659	0.0635
	41	8.902E-02	5.357E-02	0.6018	0.0000	0.	0.0637	0.1121	0.0948	0.0830	0.0750	0.0695	0.0659	0.0635
	42	9.840E-02	5.363E-02	0.5451	0.0000	0.	0.0621	0.0614	0.0613	0.1876	0.0839	0.0776	0.0734	0.0708
	43	1.083E-01	5.049E-02	0.4662	0.0000	0.	0.0726	0.1274	0.1072	0.0933	0.0839	0.0776	0.0734	0.0708
	44	1.187E-01	4.116E-02	0.3467	0.0000	0.	0.0693	0.0689	0.1557	0.1557	0.0839	0.0776	0.0734	0.0708
	45	1.295E-01	1.908E-02	0.1473	0.0000	0.	0.0822	0.1437	0.1201	0.1040	0.0930	0.0856	0.0809	0.0782
							0.0769	0.1354	0.1201	0.1040	0.0930	0.0856	0.0809	0.0782
							0.0932	0.1622	0.1345	0.1156	0.1028	0.0943	0.0891	0.0864
							0.1219	0.1622	0.1345	0.1156	0.1028	0.0943	0.0891	0.0864
							0.1061	0.1835	0.1507	0.1284	0.1134	0.1038	0.0983	0.1159
							0.1213	0.2083	0.1691	0.1426	0.1251	0.1144	0.1193	
							0.1405	0.2392	0.1915	0.1595	0.1391	0.1302		
							0.1654	0.2785	0.2193	0.1803	0.1565			
							0.2005	0.3334	0.2574	0.2087				
							0.2583	0.4228	0.3190					
							0.3836	0.6164						
							1.0000							

Output (cont.)

-103-

MOR-6

1
- NEUTRON TO GAMMA TRANSFERS FOR MEDIA 1

NEUT GROUP	PROD.PROB.	TRANSFER PROBABILITIES (GROUP G TO 1ST GAMMA GROUP, G TO 2ND GAMMA GROUP, ETC.)									
1	1.0000E+00	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
2	1.8227E-04	0.0009	0.0125	0.0359	0.0217	0.0201	0.0274	0.0275	0.0278	0.0465	0.1034
3	9.3464E-04	0.1394	0.1533	0.1519	0.1257	0.1061	0.0274	0.0275	0.0278	0.0465	0.1034
4	1.7981E-03	0.0009	0.0125	0.0359	0.0217	0.0201	0.0274	0.0275	0.0278	0.0465	0.1034
5	2.1316E-03	0.1394	0.1533	0.1519	0.1257	0.1061	0.0274	0.0275	0.0278	0.0465	0.1034
6	2.4577E-03	0.0009	0.0125	0.0359	0.0217	0.0201	0.0274	0.0275	0.0278	0.0465	0.1034
7	2.5601E-03	0.1394	0.1533	0.1519	0.1257	0.1061	0.0274	0.0275	0.0278	0.0465	0.1034
8	2.5530E-03	0.0009	0.0125	0.0359	0.0217	0.0201	0.0274	0.0275	0.0278	0.0465	0.1034
9	2.5153E-03	0.1394	0.1533	0.1519	0.1257	0.1061	0.0274	0.0275	0.0278	0.0465	0.1034
10	2.5037E-03	0.0009	0.0125	0.0359	0.0217	0.0201	0.0274	0.0275	0.0278	0.0465	0.1034
11	2.3398E-03	0.1394	0.1533	0.1519	0.1257	0.1061	0.0274	0.0275	0.0278	0.0465	0.1034
12	1.8377E-03	0.0009	0.0125	0.0359	0.0217	0.0201	0.0274	0.0275	0.0278	0.0465	0.1034
13	1.4078E-03	0.1394	0.1533	0.1519	0.1257	0.1061	0.0274	0.0275	0.0278	0.0465	0.1034
14	2.2982E-03	0.0009	0.0125	0.0359	0.0217	0.0201	0.0274	0.0275	0.0278	0.0465	0.1034
15	2.3471E-03	0.1394	0.1533	0.1519	0.1257	0.1061	0.0274	0.0275	0.0278	0.0465	0.1034
16	1.7826E-03	0.0009	0.0125	0.0359	0.0217	0.0201	0.0274	0.0275	0.0278	0.0465	0.1034
17	1.3564E-03	0.1394	0.1533	0.1519	0.1257	0.1061	0.0274	0.0275	0.0278	0.0465	0.1034
18	1.1928E-03	0.0009	0.0125	0.0359	0.0217	0.0201	0.0274	0.0275	0.0278	0.0465	0.1034
19	1.0745E-03	0.1394	0.1533	0.1519	0.1257	0.1061	0.0274	0.0275	0.0278	0.0465	0.1034
20	8.6580E-04	0.0009	0.0125	0.0359	0.0217	0.0201	0.0274	0.0275	0.0278	0.0465	0.1034
21	1.1120E-03	0.1394	0.1533	0.1519	0.1257	0.1061	0.0274	0.0275	0.0278	0.0465	0.1034
22	9.9734E-04	0.0009	0.0125	0.0359	0.0217	0.0201	0.0274	0.0275	0.0278	0.0465	0.1034
23	7.8906E-04	0.1394	0.1533	0.1519	0.1257	0.1061	0.0274	0.0275	0.0278	0.0465	0.1034
24	6.7379E-04	0.0009	0.0125	0.0359	0.0217	0.0201	0.0274	0.0275	0.0278	0.0465	0.1034
25	6.5124E-04	0.1394	0.1533	0.1519	0.1257	0.1061	0.0274	0.0275	0.0278	0.0465	0.1034
26	6.5153E-04	0.0009	0.0125	0.0359	0.0217	0.0201	0.0274	0.0275	0.0278	0.0465	0.1034
27	6.5088E-04	0.1394	0.1533	0.1519	0.1257	0.1061	0.0274	0.0275	0.0278	0.0465	0.1034
28	6.5143E-04	0.0009	0.0125	0.0359	0.0217	0.0201	0.0274	0.0275	0.0278	0.0465	0.1034
		0.1394	0.1533	0.1519	0.1257	0.1061					

Output (cont.)

-104-

MOR-6

1	29	1.0547E-03	0.0009	0.0125	0.0359	0.0217	0.0201	0.0274	0.0275	0.0278	0.0465	0.1034
			0.1394	0.1533	0.1519	0.1257	0.1061					
	30	4.0356E-03	0.0009	0.0125	0.0359	0.0217	0.0201	0.0274	0.0275	0.0278	0.0465	0.1034
			0.1394	0.1533	0.1519	0.1257	0.1061					

Output (cont.)

-105-

MOR-6

RANDOM WALK PARAMETERS

(DATA ON EACH LINE IS USED FROM STATISTICAL REGION NRG1 TO REGION NRG2 (INCLUSIVE) AND FROM ENERGY GROUP NGP1 TO NGP2 (INCLUSIVE). IF NRG1 IS ZERO, ALL REGIONS ARE INCLUDED. IF NGP1 IS ZERO, ALL GROUPS ARE INCLUDED.)

NRG1	NRG2	NGP1	NGP2	SPLIT PRGB	RR PRGB	RR SURVIAL	PATH STRETCH
1	2	1	20	0.	5.0000E-03	2.0000E-01	-7.5000E-01
1	2	21	29	0.	5.0000E-03	2.0000E-01	0.
3	27	1	29	0.	5.0000E-03	3.3000E-01	0.
1	27	30	30	0.	2.0000E-01	5.0000E-01	0.
1	27	31	44	0.	5.0000E-03	3.3000E-01	0.
1	27	45	45	0.	2.0000E-01	5.0000E-01	0.

SECONDARY PRODUCTION CONTROL PARAMETERS

(DATA ON EACH LINE IS USED FROM STATISTICAL REGION NRG1 TO REGION NRG2 (INCLUSIVE) AND FROM ENERGY GROUP NGP1 TO NGP2 (INCLUSIVE). IF NRG1 IS ZERO, ALL REGIONS ARE INCLUDED. IF NGP1 IS ZERO, ALL GROUPS ARE INCLUDED.)

NRG1	NRG2	NGP1	NGP2	FISSION PROD	GAMMA PROD
0	0	1	25	0.	1.0000E-01
0	0	26	45	0.	3.5000E-02

SOURCE DESCRIPTION

INTERVAL NUMBER 1

NUMBER BORN IN THIS INTERVAL = 7.60000E-02

RELATIVE IMPORTANCE = 1.50000E+01

POSITION DEFINITION

SPHERE

POINT AT CENTER X= 0. Y= 0. Z= 0.

OUTER RADIUS = 1.2700E+00

ENERGY DEFINITION

INPUT SPECTRUM

0.	0.	0.	8.3000E-03	1.6000E-02	3.7600E-02	1.0840E-01	7.6300E-02	2.5060E-01
1.6870E-01	1.4380E-01	7.2900E-02	3.4700E-02	3.4700E-02	2.3600E-02	1.6000E-02	5.6000E-03	1.4000E-03
7.0000E-04	7.0000E-04	0.	0.	0.	0.	0.	0.	0.
0.	0.	0.	0.	0.	0.	0.	0.	0.
0.	0.	0.	0.	0.	0.	0.	0.	0.

TIME DEFINITION

DELTA FUNCTION AT T= 0. SEC.

ANGULAR DEFINITION

ISOTROPIC - LIMITED ABOUT U= 0.

V= 0.

W= 1.0000E+00 WITH PHI-MIN= 0.

PHI-MAX= 3.2000E+01

1. INTERVAL NUMBER 2

NUMBER BORN IN THIS INTERVAL = 7.04500E-02
 RELATIVE IMPORTANCE = 1.00000E+01
 POSITION DEFINITION

SPHERE

POINT AT CENTER X= 0. Y= 0. Z= 0.

OUTER RADIUS = 1.2700E+00

ENERGY DEFINITION

INPUT SPECTRUM

0.	0.	0.	8.3000E-03	1.6000E-02	3.7600E-02	1.0840E-01	7.6300E-02	2.5060E-01
1.6870E-01	1.4380E-01	7.2900E-02	3.4700E-02	3.4700E-02	2.3600E-02	1.6000E-02	5.6000E-03	1.4000E-03
7.0000E-04	7.0000E-04	0.	0.	0.	0.	0.	0.	0.
0.	0.	0.	0.	0.	0.	0.	0.	0.
0.	0.	0.	0.	0.	0.	0.	0.	0.

TIME DEFINITION

DELTA FUNCTION AT T= 0. SEC.

ANGULAR DEFINITION

ISOTROPIC - LIMITED ABOUT U= 0.

V= C.

h= 1.0000E+00 WITH PHI-MIN= 3.2000E+01

PHI-MAX= 4.5000E+01

INTERVAL NUMBER 3

NUMBER BORN IN THIS INTERVAL = 3.53550E-01
 RELATIVE IMPORTANCE = 7.50000E+00
 POSITION DEFINITION

SPHERE

POINT AT CENTER X= 0. Y= 0. Z= 0.

OUTER RADIUS = 1.2700E+00

ENERGY DEFINITION

INPUT SPECTRUM

0.	0.	0.	8.3000E-03	1.6000E-02	3.7600E-02	1.0840E-01	7.6300E-02	2.5060E-01
1.6870E-01	1.4380E-01	7.2900E-02	3.4700E-02	3.4700E-02	2.3600E-02	1.6000E-02	5.6000E-03	1.4000E-03
7.0000E-04	7.0000E-04	0.	0.	0.	0.	0.	0.	0.
0.	0.	0.	0.	0.	0.	0.	0.	0.
0.	0.	0.	0.	0.	0.	0.	0.	0.

TIME DEFINITION

DELTA FUNCTION AT T= 0. SEC.

ANGULAR DEFINITION

ISOTROPIC - LIMITED ABOUT U= 0.

V= C.

h= 1.0000E+00 WITH PHI-MIN= 4.5000E+01

PHI-MAX= 9.0000E+01

INTERVAL NUMBER 4

NUMBER BORN IN THIS INTERVAL = 5.00000E-01
 RELATIVE IMPORTANCE = 2.00000E+00
 POSITION DEFINITION

SPHERE

POINT AT CENTER X= 0. Y= 0. Z= 0.

OUTER RADIUS = 1.2700E+00

ENERGY DEFINITION

INPUT SPECTRUM

0.	0.	0.	8.3000E-03	1.6000E-02	3.7600E-02	1.0840E-01	7.6300E-02	2.5060E-01
1.6870E-01	1.4380E-01	7.2900E-02	3.4700E-02	3.4700E-02	2.3600E-02	1.6000E-02	5.6000E-03	1.4000E-03
7.0000E-04	7.0000E-04	0.	0.	0.	0.	0.	0.	0.
0.	0.	0.	0.	0.	0.	0.	0.	0.
0.	0.	0.	0.	0.	0.	0.	0.	0.

TIME DEFINITION

Output (cont.)

-107-

MOR-6

1 DELTA FUNCTION AT T= 0. SEC.
ANGULAR DEFINITION
ISOTROPIC - LIMITED ABOUT U= 0.
PHI-MAX= 1.8000E+02

V= C.

W= 1.0000E+00 WITH PHI-MIN= 9.0000E+01

BANK HAS ROOM FOR 804 SECONDARY PARTICLES PER SOURCE PARTICLE

Output (cont.)

-108-

MOR-6

1
A. HANDY-DANDY MAP TO BLANK COMMON (IF YOU SHOULD BE SO UNLUCKY AS TO HAVE TO READ A CORE DUMP)

QUANTITY	POSITION IN COMMON (DECIMAL)	CORE LOCATION (CCTAL)
ENERGY, VELOCITY	1	0001420
DET. DEFIN.	91	0001552
RESPONSE FUNCT.	201	0001730
BIN DEFIN.	336	0002137
GEOMETRY	488	0002367
EQUIVALENCE	983	0003346
FISS. SPECTRA	998	0003365
SCATT. IMPORT.	1118	0003555
TOTAL CROSS SECT.	1343	0004116
PNABS, PFISS, PSEC	1568	0004457
GAMMA PROD	2168	0005607
SCATT. PRDB	4418	0012121
SCATT ANGLE DATA	5238	0013605
LEG. COEF.	7438	0020035
ALBEDO	13288	0033367
SPLT. STAND.	8428	0021773
SPLT. COUNTERS	10858	0026571
RR STAND.	15718	0040165
RR COUNTERS	19363	0047262
PATH STRETCH	24223	0060656
FISS PROD PARAM	25438	0063155
SEC GAMMA PARAM	25438	0063155
REAL SCATT COUNT	27868	0067753
ALBEDO SCATT COUNT	30298	0074551
FISS COUNT	30298	0074551
SEC PROD COUNT	30298	0074551
SCATT-MEDIA	35158	0106145
UNCOLLIDED RESPONSE	35163	0106152
TOTAL RESPONSE	35181	0106174
ENG FLUENCE	35199	0106216
TIME RESPONSE	35361	0106460
T, E FLUENCE	35631	0107076
ANGLE, E FLUENCE	38061	0113674
SOURCE PARAM.	39357	0116314
BATCH RESULTS	39742	0117115
BANK	40342	0120245
LAST POSITION	50000	0143137

Output (cont.)

-109-

MOR-6

TIME REQUIRED FOR INPUT = 2.906E+00 MIN.

1

SUMMARY OF BATCH RESULTS

BATCH NO.	WT	-----AVERAGE SOURCE PARAMETERS-----							---PARTICLES STARTED---				-----PARTICLES TERMINATED-----					TIME MIN.	
		X	Y	Z	T	E	U	V	W	SOURCE	SPLIT	FISS.	GAMMA	ESCAPE	ENER	TIME	R.R.		BANK
1	1.11+0	-6.28-2	-1.35-1	2.06-2	0.00+0	9.33				50	0	0	80	64	0	0	66	0	0.90
		-9.62-2	-7.71-2	-6.07-2															
2	1.07+0	1.39-1	-1.09-1	-4.15-2	0.00+0	11.33				50	0	0	411	243	0	0	218	0	3.30
		-1.16-1	-2.08-1	-1.04-1															
3	8.94-1	6.41-2	2.17-2	1.46-2	0.00+0	10.25				50	0	0	150	70	0	0	130	0	1.02
		-1.58-2	-8.60-2	8.11-2															
4	9.53-1	1.95-2	1.38-1	7.18-2	0.00+0	10.21				50	0	0	556	310	0	0	296	0	2.17
		1.15-1	-1.28-1	2.95-3															
5	1.10+0	9.93-2	-1.58-2	-1.30-1	0.00+0	10.17				50	0	0	266	164	0	0	152	0	1.31
		1.15-1	-3.77-2	-6.13-2															
6	1.01+0	2.08-3	6.04-2	8.33-2	0.00+0	9.26				50	0	0	131	66	0	0	115	0	0.97
		-1.11-1	-9.54-2	-5.40-2															
7	9.89-1	1.43-2	4.52-2	1.23-1	0.00+0	9.96				50	0	0	207	103	0	0	154	0	1.60
		-1.13-1	-2.00-1	1.79-2															
8	8.43-1	-1.17-1	-2.02-1	3.00-2	0.00+0	10.04				50	0	0	226	133	0	0	143	0	1.58
		-7.45-2	1.08-1	2.30-1															
9	9.53-1	1.43-1	5.23-2	1.03-1	0.00+0	9.86				50	0	0	101	51	0	0	100	0	0.83
		1.27-1	1.36-1	-8.67-2															
10	9.42-1	-1.69-2	-3.32-2	9.38-2	0.00+0	9.83				50	0	0	129	82	0	0	97	0	0.98
		-1.37-1	7.53-2	2.53-2															
11	8.32-1	-8.16-2	3.32-2	-1.85-1	0.00+0	9.82				50	0	0	306	142	0	0	214	0	1.41
		1.44-2	7.46-2	1.50-1															
12	1.08+0	-1.75-2	8.24-2	1.23-1	0.00+0	9.35				50	0	0	122	56	0	0	116	0	0.85
		1.25-1	-1.41-2	-4.07-2															
13	1.06+0	6.75-2	-6.66-2	5.01-4	0.00+0	10.50				50	0	0	117	67	0	0	100	0	1.15
		-3.54-1	-2.74-2	-6.62-2															
14	8.35-1	1.14-1	3.14-5	1.41-1	0.00+0	10.56				50	0	0	79	41	0	0	88	0	0.97
		4.79-2	4.13-2	1.50-1															
15	9.75-1	1.32-1	-2.51-1	-4.26-2	0.00+0	10.29				50	0	0	128	72	0	0	106	0	1.39
		5.78-2	-2.70-1	-5.73-3															

Output (cont.)

-110-

MOR-6

1
SUMMARY OF BATCH RESULTS

BATCH NO.	-----AVERAGE SOURCE PARAMETERS-----							---PARTICLES STARTED---				-----PARTICLES TERMINATED-----					TIME MIN.
	WT	X	Y	Z	T	E		SOURCE	SPLIT	FISS.	GAMMA	ESCP	ENER	TIME	R.R.	BANK	
		U	V	W													
16	9.89-1	1.26-2	4.87-2	2.27-1	0.00+0	9.31		50	0	0	95	48	0	0	97	0	0.89
		-1.08-1	9.98-2	2.28-3													
17	1.09+0	-1.55-1	-2.46-2	4.81-2	0.00+0	9.58		50	0	0	101	52	0	0	99	0	1.09
		1.40-1	2.69-2	-8.88-2													

PROBLEM TERMINATED BY MAXIMUM TIME LIMIT

Output (cont.)

-111-

MOR-6

1

FINAL SUMMARIES

EXAMPLE PROBLEM FOR MORSE-L REPORT

AVERAGE SOURCE PARAMETERS

WT 9.8327E-01
 X 2.1085E-02
 Y -2.1258E-02
 Z 3.9924E-02
 T 0.
 E 9.9700E+00
 U -2.3383E-02
 V -3.7863E-02
 W -2.1532E-03

PARTICLES STARTED

	NUMBER	WEIGHT
ORIGINAL SOURCE	850	8.3578E+02
DUE TO SPLITTING	0	
DUE TO FISSION PRODUCTION	0	
DUE TO SEC. GAMMA PRODUCTION	3205	

PARTICLES TERMINATED

	NUMBER	WEIGHT
ESCAPED FROM DEFINED GEOMETRY	1764	3.2110E+02
REACHED ENERGY CUTOFF	0	0.
KILLED BY RUSSIAN ROULETTE	2291	0.
REACHED TIME CUTOFF	0	0.
UNABLE TO BE ADDED TO BANK	0	

TOTAL NUMBER OF SCATTERINGS BY MATERIAL MEDIA

MEDIUM	NUMBER
1	222
2	526
3	1177
4	40527
5	301

REAL SCATTERING COUNTERS

ENERGY GROUP	REGION 1		REGION 2		REGION 3		REGION 4		REGION 5		REGION 6	
	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT
1	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
2	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
3	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
4	1	2.85E-04	3	4.70E-03	1	8.60E-04	1	8.11E-04	0	0.	0	0.
5	1	6.16E-04	6	5.87E-03	1	1.47E-03	2	1.56E-03	0	0.	0	0.
6	7	3.82E-03	15	1.19E-02	3	7.89E-03	2	1.55E-03	3	2.49E-03	3	6.24E-03
7	18	2.39E-02	40	5.56E-02	22	2.97E-02	16	2.34E-02	5	8.69E-03	5	8.95E-03
8	9	1.00E-02	33	4.99E-02	13	2.23E-02	4	2.72E-03	5	7.66E-03	4	4.99E-03
9	39	4.35E-02	120	1.72E-01	64	5.60E-02	25	5.25E-02	16	1.99E-02	8	8.53E-03
10	32	2.56E-02	93	1.30E-01	45	8.81E-02	32	4.47E-02	16	2.25E-02	14	1.09E-02
11	22	1.78E-02	116	2.06E-01	52	6.91E-02	25	3.34E-02	26	3.35E-02	17	1.49E-02
12	14	3.40E-02	79	1.28E-01	42	8.79E-02	33	5.64E-02	12	1.08E-02	7	2.14E-02

Output (cont.)

-112-

MOR-6

1 13	16	1.51E-02	39	5.45E-02	28	4.39E-02	25	3.58E-02	11	1.49E-02	8	1.53E-02
14	15	3.01E-02	40	5.52E-02	30	4.99E-02	26	4.81E-02	20	2.73E-02	12	1.18E-02
15	6	8.25E-03	43	6.29E-02	36	7.99E-02	23	2.93E-02	16	2.71E-02	10	1.38E-02
16	10	1.12E-02	43	6.14E-02	60	1.05E-01	24	4.47E-02	14	1.72E-02	17	1.52E-02
17	5	2.26E-03	22	4.15E-02	59	1.19E-01	24	3.13E-02	16	1.77E-02	13	1.26E-02
18	1	2.79E-04	17	2.26E-02	53	8.37E-02	32	5.56E-02	12	1.80E-02	1	3.45E-04
19	2	2.07E-03	20	3.15E-02	50	8.72E-02	32	4.22E-02	15	1.15E-02	3	4.04E-03
20	0	0.	6	7.60E-03	46	7.50E-02	21	3.17E-02	23	3.51E-02	8	1.12E-02
21	1	3.78E-04	5	7.68E-03	29	4.34E-02	25	4.49E-02	12	2.85E-02	13	1.53E-02
22	4	2.83E-03	54	7.33E-02	187	2.72E-01	114	1.85E-01	55	7.58E-02	27	2.11E-02
23	6	3.37E-03	25	2.83E-02	176	2.81E-01	95	1.51E-01	53	6.96E-02	39	3.73E-02
24	8	8.09E-03	29	4.69E-02	388	6.43E-01	246	4.16E-01	101	1.37E-01	97	9.53E-02
25	2	3.65E-03	41	6.06E-02	400	5.91E-01	307	6.19E-01	139	2.04E-01	89	1.12E-01
26	0	0.	34	3.61E-02	338	4.95E-01	287	4.58E-01	116	1.31E-01	91	9.18E-02
27	0	0.	32	3.89E-02	324	5.20E-01	320	5.00E-01	104	1.56E-01	75	9.35E-02
28	0	0.	16	2.65E-02	276	4.34E-01	322	5.09E-01	118	1.78E-01	126	1.65E-01
29	0	0.	13	1.78E-02	597	5.69E-01	564	1.01E+00	299	3.84E-01	192	2.45E-01
30	0	0.	12	9.43E-02	1671	1.33E+01	2336	2.65E+01	1195	1.06E+01	774	5.06E+00
31	0	0.	0	0.	0	0.	0	0.	1	1.36E-04	0	0.
32	0	0.	13	4.28E-03	1	7.71E-07	4	3.45E-03	6	9.24E-03	4	6.74E-04
33	0	0.	9	9.27E-03	3	3.62E-03	9	2.92E-03	16	1.52E-02	10	5.53E-03
34	0	0.	5	2.36E-02	2	6.38E-03	2	1.93E-03	1	9.84E-05	2	1.65E-03
35	0	0.	3	1.47E-03	1	3.76E-04	2	1.81E-04	5	3.85E-04	2	4.67E-04
36	0	0.	10	1.74E-02	3	5.56E-04	3	2.29E-05	7	4.39E-04	4	9.21E-05
37	0	0.	16	4.57E-02	8	4.69E-06	14	2.16E-03	13	9.59E-04	16	1.41E-03
38	1	4.50E-05	42	3.42E-02	65	3.40E-02	86	5.83E-02	111	7.50E-02	81	5.53E-02
39	0	0.	15	2.25E-02	12	1.39E-03	23	5.80E-03	21	3.30E-03	30	1.20E-02
40	0	0.	31	7.87E-02	10	6.48E-04	20	3.27E-03	16	5.46E-04	20	3.44E-03
41	0	0.	34	8.82E-02	18	1.70E-03	26	8.78E-03	28	1.19E-02	23	9.77E-03
42	1	8.25E-06	33	1.29E-01	8	2.64E-03	11	1.08E-02	18	7.50E-03	21	4.51E-03
43	0	0.	89	2.64E-01	23	5.69E-03	28	1.48E-02	32	6.17E-03	32	6.36E-03
44	1	1.33E-04	91	1.34E-01	21	6.48E-04	42	1.69E-02	45	7.34E-03	54	1.03E-02
45	0	0.	316	2.01E-01	35	5.55E-03	83	4.55E-02	87	1.93E-02	96	1.09E-02
SUM	222	2.47E-01	1703	2.58E+00	5201	1.87E+01	5316	3.11E+01	2809	1.24E+01	2048	6.22E+00

ENERGY GROUP	REGION 7 NUMBER WEIGHT	REGION 8 NUMBER WEIGHT	REGION 9 NUMBER WEIGHT	REGION 10 NUMBER WEIGHT	REGION 11 NUMBER WEIGHT	REGION 12 NUMBER WEIGHT
1	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
2	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
3	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
4	0 0.	0 0.	0 0.	0 0.	0 0.	3 1.31E-03
5	0 0.	1 4.16E-04	0 0.	0 0.	0 0.	1 7.60E-04
6	3 9.68E-04	1 4.74E-04	0 0.	0 0.	0 0.	12 9.52E-03
7	6 5.72E-03	1 2.32E-04	2 3.47E-03	2 3.35E-03	0 0.	7 3.85E-03
8	4 2.57E-03	0 0.	1 2.09E-04	0 0.	1 3.38E-04	4 1.60E-03
9	6 4.81E-03	7 3.27E-03	4 2.68E-03	0 0.	3 5.58E-04	9 6.16E-03
10	4 2.71E-03	5 2.75E-03	1 7.88E-04	0 0.	5 4.61E-06	11 1.27E-02
11	3 2.26E-03	4 1.86E-03	2 2.83E-03	0 0.	3 1.64E-03	22 1.90E-02
12	5 2.97E-03	2 3.43E-03	1 5.89E-05	1 2.72E-03	4 3.40E-04	12 1.20E-02
13	7 5.59E-03	2 1.63E-03	5 3.50E-03	0 0.	2 3.92E-06	6 6.78E-03
14	6 5.38E-03	2 4.42E-04	4 2.78E-03	2 3.85E-03	3 1.63E-03	16 1.66E-02
15	8 6.35E-03	4 2.69E-03	2 2.58E-04	0 0.	2 1.63E-03	17 2.23E-02
16	7 6.59E-03	5 3.96E-03	5 1.03E-02	0 0.	0 0.	14 3.00E-02
17	1 2.39E-03	5 4.42E-03	6 7.41E-04	0 0.	1 3.34E-04	19 4.48E-02
18	10 7.30E-03	5 3.18E-03	0 0.	3 1.55E-03	1 1.13E-03	13 1.18E-02
19	7 1.08E-02	9 7.44E-03	2 1.02E-03	2 2.92E-03	2 1.96E-03	11 2.99E-02
20	6 2.06E-02	4 1.58E-03	2 4.13E-03	2 9.10E-04	3 2.27E-03	12 1.31E-02
21	4 1.83E-03	8 5.50E-03	1 3.61E-03	0 0.	2 1.96E-03	6 8.56E-03
22	20 2.15E-02	25 3.30E-02	9 4.89E-03	7 4.42E-03	5 3.59E-03	29 3.31E-02
23	24 2.69E-02	15 1.15E-02	6 1.39E-02	10 5.70E-03	7 2.42E-03	31 3.21E-02

1 24	49	4.34E-02	27	1.83E-02	13	6.38E-03	16	9.78E-03	12	1.02E-02	74	1.21E-01
25	66	5.60E-02	39	4.69E-02	8	1.03E-02	24	2.01E-02	11	6.22E-03	91	1.10E-01
26	60	5.39E-02	35	8.56E-02	17	1.37E-02	14	2.31E-02	8	8.25E-03	98	1.07E-01
27	64	7.01E-02	35	3.51E-02	24	2.15E-02	11	1.48E-02	13	5.14E-03	63	6.49E-02
28	63	6.30E-02	53	6.68E-02	24	2.79E-02	10	9.19E-03	13	1.39E-02	84	1.19E-01
29	108	1.27E-01	51	6.36E-02	42	4.32E-02	15	2.92E-02	13	8.93E-03	165	1.94E-01
30	772	6.68E+00	173	6.17E-01	297	1.89E-01	232	2.89E-01	1016	3.87E-02	735	4.99E+00
31	1	1.35E-03	0	0.	0	0.	1	1.99E-05	1	8.76E-04	0	0.
32	2	9.25E-04	2	4.58E-04	4	5.17E-04	4	2.17E-03	6	1.92E-03	2	1.28E-03
33	10	6.19E-03	10	1.72E-03	4	9.07E-04	14	5.25E-03	24	1.54E-03	0	0.
34	3	1.60E-04	2	3.33E-04	0	0.	2	2.63E-04	7	3.63E-04	0	0.
35	3	8.77E-04	3	4.11E-04	4	1.10E-03	3	3.53E-03	4	3.80E-04	1	8.03E-07
36	8	2.32E-03	3	6.01E-05	0	0.	3	3.90E-04	8	2.70E-03	1	4.50E-05
37	14	6.73E-03	9	1.08E-03	5	2.10E-05	8	8.73E-04	26	2.60E-03	4	1.21E-03
38	57	3.12E-02	44	1.05E-02	42	1.92E-02	58	3.01E-02	113	1.06E-02	28	8.95E-03
39	24	1.35E-02	14	4.54E-03	13	2.20E-03	31	1.31E-02	50	6.07E-03	6	7.13E-04
40	21	6.45E-03	14	9.47E-03	13	1.71E-03	36	9.82E-03	46	1.08E-02	6	3.27E-03
41	35	3.97E-03	20	4.91E-03	17	6.32E-03	36	6.99E-03	68	1.09E-02	4	5.42E-03
42	13	4.42E-03	23	4.06E-03	17	7.13E-03	28	8.28E-03	66	8.93E-03	7	1.08E-03
43	24	1.15E-02	34	4.49E-03	36	4.79E-03	34	3.14E-03	88	8.71E-03	2	1.08E-03
44	52	5.80E-03	42	5.63E-03	42	7.76E-03	61	9.30E-03	164	2.07E-02	7	3.76E-05
45	118	2.07E-02	80	6.85E-03	80	4.17E-03	132	7.14E-03	512	1.39E-02	9	1.67E-04
SUM	1698	7.34E+00	818	1.08E+00	755	4.23E-01	802	5.21E-01	2313	2.12E-01	1642	6.05E+00

Output (cont.)

ENERGY GROUP	REGION 13 NUMBER WEIGHT	REGION 14 NUMBER WEIGHT	REGION 15 NUMBER WEIGHT	REGION 16 NUMBER WEIGHT	REGION 17 NUMBER WEIGHT	REGION 18 NUMBER WEIGHT
1	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
2	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
3	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
4	0 0.	1 6.05E-04	1 5.70E-04	0 0.	0 0.	0 0.
5	0 0.	1 8.58E-04	1 7.43E-04	1 5.37E-04	0 0.	0 0.
6	8 8.13E-03	3 1.38E-03	4 2.69E-03	2 1.11E-03	0 0.	2 5.61E-03
7	9 7.02E-03	6 1.81E-03	4 1.22E-03	1 1.14E-03	6 8.45E-04	1 2.92E-04
8	6 4.81E-03	4 1.88E-03	6 1.96E-03	8 2.71E-03	4 7.61E-04	1 1.86E-05
9	23 2.15E-02	16 7.29E-03	12 6.76E-03	11 3.39E-03	5 2.12E-03	6 2.81E-03
10	20 1.83E-02	16 1.15E-02	9 4.94E-03	11 3.13E-03	4 3.13E-03	2 7.56E-05
11	18 1.33E-02	24 1.18E-02	15 6.35E-03	7 2.25E-03	6 2.37E-03	4 9.88E-04
12	14 1.05E-02	12 6.90E-03	12 6.98E-03	13 5.16E-03	6 2.02E-03	3 8.81E-04
13	12 1.28E-02	17 1.18E-02	13 1.04E-02	11 4.82E-03	6 1.80E-03	2 3.10E-04
14	12 8.42E-03	18 1.49E-02	12 5.14E-03	8 1.82E-03	7 1.54E-03	0 0.
15	19 1.80E-02	19 1.26E-02	18 9.84E-03	11 8.62E-03	5 1.37E-03	4 1.23E-03
16	14 1.48E-02	10 8.64E-03	13 6.35E-03	16 7.57E-03	11 9.02E-03	2 3.51E-03
17	20 1.61E-02	23 1.53E-02	13 6.47E-03	6 3.04E-03	11 6.17E-03	7 1.76E-03
18	20 2.20E-02	11 6.08E-03	14 9.06E-03	10 2.46E-03	5 2.91E-03	1 2.29E-04
19	22 1.63E-02	17 7.32E-03	16 9.11E-03	3 5.64E-04	7 3.16E-03	2 9.36E-04
20	16 1.41E-02	12 7.20E-03	10 3.91E-03	13 3.85E-03	2 1.17E-03	1 2.98E-04
21	14 1.53E-02	8 4.87E-03	2 4.10E-04	7 6.03E-03	4 1.90E-03	4 2.03E-03
22	78 8.10E-02	42 3.17E-02	42 2.26E-02	45 1.64E-02	25 1.41E-02	15 6.94E-03
23	88 9.18E-02	48 3.38E-02	32 1.35E-02	32 1.24E-02	30 1.17E-02	24 1.87E-02
24	187 2.10E-01	152 1.29E-01	99 5.70E-02	82 3.82E-02	54 2.33E-02	50 2.60E-02
25	153 2.06E-01	162 1.11E-01	132 7.50E-02	98 3.44E-02	42 1.52E-02	53 3.29E-02
26	130 1.28E-01	181 1.74E-01	83 4.33E-02	83 2.62E-02	58 2.21E-02	53 3.42E-02
27	144 1.30E-01	176 1.43E-01	107 5.68E-02	112 5.94E-02	49 1.86E-02	52 3.51E-02
28	167 1.56E-01	196 2.04E-01	113 5.89E-02	66 3.04E-02	49 1.59E-02	66 3.16E-02
29	315 3.01E-01	297 2.59E-01	251 1.45E-01	152 6.45E-02	80 2.95E-02	68 3.56E-02
30	1106 5.22E+00	1311 1.20E+01	1249 6.14E+00	488 7.90E-01	538 2.54E+00	810 1.82E+00
31	1 2.78E-04	0 0.	0 0.	1 3.58E-05	1 5.19E-06	0 0.
32	2 1.75E-04	8 1.86E-03	1 1.51E-07	2 2.53E-05	5 2.84E-04	5 1.87E-04
33	7 5.15E-03	10 5.81E-03	14 3.59E-03	9 2.22E-03	15 3.64E-03	11 5.59E-03
34	0 0.	2 8.76E-04	3 3.10E-04	4 6.41E-04	3 1.70E-03	5 7.41E-04

-114-

MOR-6

1 35	4	2.28E-03	5	3.44E-03	0	C.	4	1.81E-03	5	1.04E-04	3	9.91E-05
36	4	4.23E-05	6	5.86E-03	6	7.17E-04	3	8.43E-04	4	5.72E-04	3	1.51E-04
37	6	1.15E-03	15	3.09E-03	14	2.47E-03	12	5.89E-04	11	1.24E-04	13	3.05E-03
38	55	1.61E-02	65	2.41E-02	87	2.30E-02	92	1.65E-02	91	1.83E-02	91	1.29E-02
39	18	6.06E-03	17	5.60E-03	19	1.91E-02	12	1.89E-03	24	2.55E-03	35	1.82E-03
40	8	1.00E-04	15	2.66E-03	11	1.28E-03	20	1.40E-02	23	7.22E-03	28	2.58E-03
41	14	3.61E-03	29	7.86E-03	30	5.06E-03	20	3.34E-03	30	4.97E-03	30	1.82E-03
42	9	2.09E-03	10	2.22E-03	20	3.08E-03	18	5.22E-04	30	2.19E-03	31	2.80E-03
43	11	3.73E-03	26	7.00E-03	18	5.95E-03	28	9.26E-03	22	3.05E-03	34	3.33E-03
44	13	5.42E-03	19	4.61E-03	40	6.03E-03	48	5.29E-03	62	2.30E-03	66	6.69E-03
45	23	3.16E-03	51	5.48E-03	78	9.73E-03	109	8.01E-03	116	9.56E-03	146	6.16E-03
SUM	2790	6.80E+00	3061	1.33E+01	2624	6.79E+00	1684	1.19E+00	1456	2.79E+00	1734	2.11E+00

ENERGY GROUP	REGION 19 NUMBER WEIGHT	REGION 20 NUMBER WEIGHT	REGION 21 NUMBER WEIGHT	REGION 22 NUMBER WEIGHT	REGION 23 NUMBER WEIGHT	REGION 24 NUMBER WEIGHT
1	0 0.	0 0.	0 C.	0 0.	0 0.	0 0.
2	0 0.	0 0.	0 C.	0 0.	0 0.	0 0.
3	0 0.	0 0.	0 C.	0 0.	0 0.	0 0.
4	0 0.	0 0.	0 C.	0 0.	0 0.	0 0.
5	0 0.	2 1.43E-03	0 C.	0 0.	0 0.	0 0.
6	2 3.69E-04	1 5.13E-05	1 1.32E-05	0 0.	4 1.98E-04	0 0.
7	1 2.61E-04	0 0.	2 2.93E-04	2 1.16E-05	0 0.	1 8.79E-04
8	0 0.	1 1.25E-04	0 C.	0 0.	2 9.49E-05	1 3.55E-04
9	1 1.84E-05	1 1.27E-04	0 C.	2 2.84E-04	0 0.	2 1.08E-03
10	5 5.76E-03	3 5.54E-03	1 3.86E-06	0 0.	0 0.	1 6.08E-04
11	5 6.07E-04	2 8.33E-04	0 C.	0 0.	0 0.	2 1.14E-03
12	5 4.34E-04	2 8.59E-04	2 1.05E-04	2 7.63E-06	1 2.59E-08	0 0.
13	0 0.	1 5.64E-05	0 C.	0 0.	2 2.61E-07	1 3.92E-04
14	1 1.82E-04	0 0.	0 C.	2 3.92E-05	1 2.35E-07	2 1.34E-03
15	1 1.96E-05	1 1.08E-04	0 C.	1 4.81E-06	3 4.83E-05	1 7.43E-04
16	5 1.86E-04	0 C.	0 C.	2 4.90E-06	1 7.94E-07	1 1.29E-03
17	2 1.17E-03	1 8.24E-04	0 C.	0 0.	3 1.04E-05	0 0.
18	2 3.57E-04	0 0.	2 1.83E-04	0 0.	3 2.38E-06	0 0.
19	4 9.68E-04	1 5.64E-05	0 C.	0 0.	3 1.05E-06	2 1.61E-03
20	3 1.87E-05	1 8.24E-04	1 8.24E-04	0 0.	1 4.81E-06	1 6.05E-04
21	0 0.	1 5.38E-03	2 2.60E-05	1 3.81E-06	0 0.	3 2.05E-03
22	11 8.33E-04	1 1.08E-04	1 8.24E-04	0 0.	6 9.51E-05	6 5.16E-03
23	5 5.36E-04	3 5.66E-04	0 C.	3 4.20E-05	1 7.94E-07	0 0.
24	11 4.77E-04	8 8.36E-04	7 2.96E-03	5 7.75E-05	8 5.23E-06	5 2.26E-03
25	15 3.09E-03	6 4.04E-04	7 2.96E-03	7 4.09E-04	4 2.62E-06	2 1.60E-03
26	14 1.42E-03	7 2.27E-04	3 8.50E-04	10 2.11E-04	10 4.21E-04	2 1.39E-03
27	23 2.03E-03	5 2.89E-04	3 1.07E-03	2 9.41E-05	11 3.58E-05	11 9.55E-03
28	18 6.37E-04	4 1.89E-04	11 6.23E-03	5 1.01E-04	3 5.43E-05	10 6.95E-03
29	47 7.64E-03	26 2.41E-03	9 4.08E-03	8 5.16E-04	17 2.43E-03	13 6.12E-03
30	267 5.55E-01	21 3.82E-03	112 5.32E-02	199 3.66E-02	179 9.62E-03	5 3.60E-03
31	0 0.	0 0.	0 C.	0 0.	0 0.	0 0.
32	1 1.87E-05	2 5.97E-05	3 3.11E-03	4 1.39E-04	7 8.15E-04	0 0.
33	8 4.17E-03	7 2.02E-03	6 1.09E-04	4 3.05E-04	12 2.31E-03	0 0.
34	4 1.02E-03	1 2.23E-08	1 6.99E-10	1 3.10E-03	8 1.52E-03	0 0.
35	4 2.41E-04	2 9.86E-05	2 2.15E-04	3 2.77E-03	5 4.52E-03	0 0.
36	5 4.74E-04	4 6.38E-05	0 C.	0 0.	9 1.82E-03	0 0.
37	12 1.37E-03	5 1.15E-03	5 8.32E-05	5 5.20E-06	22 1.22E-03	0 0.
38	84 1.30E-02	50 3.48E-03	48 3.62E-03	43 2.55E-03	79 1.73E-02	0 0.
39	28 2.38E-03	15 3.02E-03	13 1.29E-03	16 7.07E-04	39 8.95E-03	0 0.
40	15 1.29E-03	19 1.61E-03	10 3.38E-03	11 3.14E-03	32 5.50E-03	0 0.
41	35 6.62E-03	22 2.86E-03	26 4.28E-03	19 1.41E-03	65 5.59E-03	1 2.71E-08
42	23 1.27E-03	18 1.60E-03	16 2.27E-03	18 4.38E-03	70 6.96E-03	0 0.
43	25 3.00E-03	23 7.82E-04	27 1.74E-03	24 2.58E-03	95 1.11E-02	0 C.
44	51 2.36E-03	44 3.47E-03	46 7.95E-04	38 2.00E-03	170 4.62E-03	1 2.59E-05
45	115 4.16E-03	98 2.94E-03	140 3.98E-03	107 2.40E-03	582 1.10E-02	2 5.27E-05

Output (cont.)

-115-

MOR-6

1SUM	858	6.23E-01	409	4.83E-02	507	9.85E-02	544	6.39E-02	1458	9.63E-02	76	4.88E-02
ENERGY GROUP	REGION 25		REGION 26		REGION 27							
	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT						
1	0	0.	0	0.	0	0.						
2	0	0.	0	0.	0	0.						
3	0	0.	0	0.	0	0.						
4	0	0.	0	0.	0	0.						
5	0	0.	0	0.	0	0.						
6	1	8.57E-04	0	0.	0	0.						
7	1	3.92E-04	0	0.	0	0.						
8	0	0.	0	0.	0	0.						
9	2	7.29E-04	0	0.	0	0.						
10	2	5.91E-04	1	2.83E-04	1	3.34E-04						
11	2	1.61E-03	2	3.24E-03	1	4.26E-04						
12	2	1.12E-03	2	2.89E-03	0	0.						
13	0	0.	1	5.06E-04	0	0.						
14	0	0.	0	0.	0	0.						
15	2	1.04E-03	0	0.	0	0.						
16	3	9.65E-04	1	6.10E-04	1	3.62E-05						
17	0	0.	1	2.28E-04	0	0.						
18	0	0.	0	0.	0	0.						
19	0	0.	0	0.	1	3.62E-05						
20	1	9.11E-04	1	6.05E-04	0	0.						
21	0	0.	1	3.90E-04	0	0.						
22	3	1.61E-03	4	3.36E-03	1	3.62E-05						
23	3	1.30E-03	1	2.40E-03	1	2.40E-03						
24	6	2.73E-03	3	1.22E-03	0	0.						
25	7	3.06E-03	11	6.74E-03	0	0.						
26	3	6.30E-03	2	1.29E-03	2	7.14E-04						
27	8	7.10E-03	11	6.90E-03	1	8.78E-04						
28	11	3.11E-02	1	1.33E-03	1	3.89E-04						
29	7	9.02E-03	9	2.41E-02	0	0.						
30	19	5.76E-02	20	4.16E-02	6	2.29E-03						
31	0	0.	0	0.	0	0.						
32	0	0.	0	0.	0	0.						
33	2	2.07E-03	1	9.70E-08	0	0.						
34	0	0.	2	3.01E-05	0	0.						
35	0	0.	0	0.	0	0.						
36	0	0.	0	0.	0	0.						
37	0	0.	0	0.	0	0.						
38	4	3.43E-05	7	7.13E-04	3	5.32E-05						
39	1	3.13E-08	1	7.03E-08	0	0.						
40	0	0.	1	2.70E-08	0	0.						
41	0	0.	1	1.04E-07	0	0.						
42	1	4.66E-07	3	2.52E-05	0	0.						
43	0	0.	1	3.59E-06	1	4.83E-08						
44	3	9.27E-04	3	1.11E-04	0	0.						
45	8	1.62E-03	4	1.27E-04	7	2.30E-03						
SUM	102	1.33E-01	96	9.87E-02	27	9.89E-03						

Output (cont.)

-116-

MOR-6

SECONDARY PRODUCTION PROBABILITIES

ENERGY GROUP	REGION 1		REGION 2		REGION 3		REGION 4		REGION 5		REGION 6	
	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT
1	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
2	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.

1	3	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
4	1	5.13E-07	3	1.26E-02	1	1.78E-04	1	1.68E-04	0	0.	0	0.	
5	1	1.31E-06	6	1.20E-02	1	2.10E-04	2	2.23E-04	0	0.	0	0.	
6	7	9.39E-06	15	2.34E-02	3	6.22E-04	2	1.22E-04	3	1.96E-04	3	4.92E-04	
7	18	6.12E-05	40	9.30E-02	22	9.69E-04	16	7.63E-04	5	2.84E-04	5	2.92E-04	
8	9	2.55E-05	33	6.78E-02	13	1.28E-04	4	1.57E-05	5	4.41E-05	4	2.87E-05	
9	39	1.09E-04	120	1.91E-01	64	4.18E-04	25	2.29E-04	16	8.67E-05	8	3.71E-05	
10	32	6.41E-05	93	1.57E-01	45	3.30E-04	32	1.67E-04	16	8.43E-05	14	4.08E-05	
11	22	4.17E-05	116	1.63E-01	52	1.63E-04	25	7.89E-05	26	7.91E-05	17	3.53E-05	
12	14	6.25E-05	79	6.85E-02	42	1.55E-04	33	9.94E-05	12	1.91E-05	7	3.78E-05	
13	16	2.12E-05	39	2.89E-02	28	5.44E-05	25	4.43E-05	11	1.85E-05	8	1.90E-05	
14	15	6.92E-05	40	2.05E-02	30	4.19E-05	26	4.05E-05	20	2.29E-05	12	9.90E-06	
15	6	1.94E-05	43	1.65E-02	36	1.85E-05	23	6.78E-06	16	6.27E-06	10	3.20E-06	
16	10	2.00E-05	43	1.16E-02	60	7.15E-06	24	3.06E-06	14	1.18E-06	17	1.04E-06	
17	5	3.06E-06	22	4.00E-03	59	1.50E-06	24	3.95E-07	16	2.23E-07	13	1.58E-07	
18	1	3.33E-07	17	5.71E-04	53	5.07E-07	32	3.37E-07	12	1.09E-07	1	2.09E-09	
19	2	2.22E-06	20	3.74E-04	50	5.29E-07	32	2.56E-07	15	6.98E-08	3	2.45E-08	
20	0	0.	6	4.83E-05	46	4.08E-07	21	1.72E-07	23	1.91E-07	8	6.08E-08	
21	1	4.20E-07	5	2.57E-05	29	2.17E-07	25	2.25E-07	12	1.42E-07	13	7.67E-08	
22	4	2.83E-06	54	8.61E-05	187	1.41E-06	114	9.60E-07	55	3.93E-07	27	1.10E-07	
23	6	2.66E-06	25	2.43E-05	176	2.16E-06	95	1.16E-06	53	5.36E-07	39	2.87E-07	
24	8	5.45E-06	29	1.59E-05	388	1.15E-05	246	7.44E-06	101	2.46E-06	97	1.70E-06	
25	2	2.38E-06	41	3.65E-05	400	3.17E-05	307	3.32E-05	139	1.10E-05	89	5.99E-06	
26	0	0.	34	1.91E-05	338	8.33E-05	287	7.70E-05	116	2.20E-05	91	1.54E-05	
27	0	0.	32	7.02E-05	324	2.28E-04	320	2.19E-04	104	6.84E-05	75	4.09E-05	
28	0	0.	16	1.12E-04	276	6.27E-04	322	7.35E-04	118	2.58E-04	126	2.39E-04	
29	0	0.	13	6.87E-05	597	3.58E-03	564	3.73E-03	299	1.42E-03	192	9.07E-04	
30	0	0.	12	7.29E-03	1671	1.17E-01	2336	2.32E-01	1195	9.28E-02	774	4.44E-02	
31	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	
32	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	
33	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	
34	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	
35	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	
36	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	
37	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	
38	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	
39	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	
40	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	
41	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	
42	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	
43	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	
44	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	
45	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	
SUM	219	5.25E-04	996	8.79E-01	4991	1.25E-01	4963	2.39E-01	2402	9.54E-02	1653	4.66E-02	

Output (cont.)

-117-

ENERGY GROUP	REGION 7 NUMBER WEIGHT	REGION 8 NUMBER WEIGHT	REGION 9 NUMBER WEIGHT	REGION 10 NUMBER WEIGHT	REGION 11 NUMBER WEIGHT	REGION 12 NUMBER WEIGHT
1	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
2	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
3	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
4	0 0.	0 0.	0 0.	0 0.	0 0.	3 2.71E-04
5	0 0.	1 5.93E-05	0 0.	0 0.	0 0.	1 1.08E-04
6	3 7.64E-05	1 3.73E-05	0 0.	0 0.	0 0.	12 7.51E-04
7	6 1.87E-04	1 7.57E-06	2 1.13E-04	2 1.09E-04	0 0.	7 1.26E-04
8	4 1.48E-05	0 0.	1 1.20E-06	0 0.	1 1.94E-06	4 9.20E-06
9	6 2.09E-05	7 1.42E-05	4 1.17E-05	0 0.	3 2.43E-06	9 2.68E-05
10	4 1.02E-05	5 1.03E-05	1 2.95E-06	0 0.	5 1.73E-08	11 4.74E-05
11	3 5.34E-06	4 4.39E-06	2 6.68E-06	0 0.	3 3.87E-06	22 4.49E-05
12	5 5.23E-06	2 6.04E-06	1 1.74E-07	1 4.79E-06	4 5.98E-07	12 2.11E-05
13	7 6.93E-06	2 2.01E-06	5 4.34E-06	0 0.	2 4.86E-09	6 8.45E-06

MOR-6

1	14	6	4.52E-06	2	3.72E-07	4	2.34E-06	2	3.24E-06	3	1.37E-06	16	1.39E-05
15	8	1.47E-06	4	6.23E-07	2	5.97E-08	0	0.	2	3.76E-07	17	5.15E-06	
16	7	4.51E-07	5	2.71E-07	5	7.03E-07	0	0.	0	0.	14	2.05E-06	
17	1	3.01E-08	5	5.59E-08	6	9.35E-09	0	0.	1	4.22E-09	19	5.65E-07	
18	10	4.42E-08	5	1.93E-08	0	C.	3	9.38E-09	1	6.87E-09	13	7.14E-08	
19	7	6.57E-08	9	4.51E-08	2	6.17E-09	2	1.77E-08	2	1.19E-08	11	1.81E-07	
20	6	1.12E-07	4	8.62E-09	2	2.25E-08	2	4.95E-09	3	1.23E-08	12	7.11E-08	
21	4	9.18E-09	8	2.75E-08	1	1.81E-08	0	0.	2	9.81E-09	6	4.28E-08	
22	20	1.12E-07	25	1.71E-07	9	2.54E-08	7	2.29E-08	5	1.86E-08	29	1.72E-07	
23	24	2.07E-07	15	8.83E-08	6	1.07E-07	10	4.39E-08	7	1.86E-08	31	2.47E-07	
24	49	7.75E-07	27	3.28E-07	13	1.14E-07	16	1.75E-07	12	1.82E-07	74	2.17E-06	
25	66	3.00E-06	39	2.52E-06	8	5.54E-07	24	1.08E-06	11	3.33E-07	91	5.90E-06	
26	60	9.07E-06	35	1.43E-05	17	2.30E-06	14	3.88E-06	8	1.39E-06	98	1.80E-05	
27	64	3.07E-05	35	1.54E-05	24	9.41E-06	11	6.47E-06	13	2.25E-06	63	2.84E-05	
28	63	9.11E-05	53	9.66E-05	24	4.03E-05	10	1.33E-05	13	2.01E-05	84	1.71E-04	
29	108	4.70E-04	51	2.35E-04	42	1.60E-04	15	1.08E-04	13	3.30E-05	165	7.19E-04	
30	772	5.85E-02	173	5.41E-03	297	1.65E-03	232	2.54E-03	1016	3.40E-04	735	4.38E-02	
31	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.	
32	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.	
33	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.	
34	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.	
35	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.	
36	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.	
37	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	
38	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	
39	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.	
40	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.	
41	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.	
42	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.	
43	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.	
44	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.	
45	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.	
SUM	1313	5.95E-02	518	5.92E-03	478	2.01E-03	351	2.79E-03	1130	4.08E-04	1565	4.62E-02	

ENERGY GROUP	REGION 13 NUMBER WEIGHT	REGION 14 NUMBER WEIGHT	REGION 15 NUMBER WEIGHT	REGION 16 NUMBER WEIGHT	REGION 17 NUMBER WEIGHT	REGION 18 NUMBER WEIGHT
1	0 0.	0 C.	0 C.	0 0.	0 0.	0 0.
2	0 0.	0 0.	0 C.	0 0.	0 0.	0 0.
3	0 0.	0 0.	0 C.	0 0.	0 0.	0 0.
4	0 0.	1 1.25E-04	1 1.18E-04	0 0.	0 0.	0 0.
5	0 0.	1 1.22E-04	1 1.06E-04	1 7.65E-05	0 0.	0 0.
6	8 6.41E-04	3 1.09E-04	4 2.12E-04	2 8.79E-05	0 0.	2 4.42E-04
7	9 2.29E-04	6 5.92E-05	4 4.00E-05	6 3.71E-05	6 2.76E-05	1 9.52E-06
8	6 2.77E-05	4 1.08E-05	6 1.13E-05	8 1.56E-05	4 4.38E-06	1 1.07E-07
9	23 9.37E-05	16 3.17E-05	12 2.94E-05	11 1.47E-05	5 9.23E-06	6 1.22E-05
10	20 6.85E-05	16 4.30E-05	9 1.85E-05	11 1.17E-05	4 1.17E-05	2 2.83E-07
11	18 3.14E-05	24 2.79E-05	15 1.50E-05	7 5.31E-06	6 5.59E-06	4 2.34E-06
12	14 1.85E-05	12 1.22E-05	12 1.23E-05	13 9.09E-06	6 3.55E-06	3 1.55E-06
13	12 1.58E-05	17 1.46E-05	13 1.29E-05	11 5.97E-06	6 2.22E-06	2 3.84E-07
14	12 7.08E-06	18 1.25E-05	12 4.32E-06	8 1.53E-06	7 1.29E-06	0 0.
15	19 4.16E-06	19 2.91E-06	18 2.28E-06	11 1.99E-06	5 3.16E-07	4 2.78E-07
16	14 1.01E-06	10 5.91E-07	13 4.34E-07	16 5.18E-07	11 6.17E-07	2 2.40E-07
17	20 2.04E-07	23 1.93E-07	13 6.17E-08	6 3.84E-08	11 7.79E-08	7 2.22E-08
18	20 1.33E-07	11 3.68E-08	14 5.49E-08	10 1.49E-08	5 1.76E-08	1 1.39E-09
19	22 9.90E-08	17 4.44E-08	16 5.52E-08	3 3.42E-09	7 1.91E-08	2 5.68E-09
20	16 7.67E-08	12 3.91E-08	10 2.13E-08	13 2.09E-08	2 6.36E-09	1 1.62E-09
21	14 7.63E-08	8 2.44E-08	2 2.05E-08	7 3.02E-08	4 9.52E-09	4 1.01E-08
22	78 4.20E-07	42 1.65E-07	42 1.17E-07	45 8.49E-08	25 7.31E-08	15 3.60E-08
23	88 7.07E-07	48 2.60E-07	32 1.04E-07	32 9.53E-08	30 8.98E-08	24 1.44E-07
24	187 3.76E-06	152 2.31E-06	99 1.02E-06	82 6.82E-07	54 4.17E-07	50 4.65E-07

1 25	153	1.10E-05	162	5.95E-06	132	4.02E-06	98	1.85E-06	42	8.17E-07	53	1.77E-06
26	130	2.16E-05	181	2.92E-05	83	7.29E-06	83	4.40E-06	58	3.72E-06	53	5.75E-06
27	144	5.71E-05	176	6.24E-05	107	2.49E-05	112	2.60E-05	49	8.14E-06	52	1.53E-05
28	167	2.25E-04	196	2.95E-04	113	8.50E-05	66	4.40E-05	49	2.29E-05	66	4.57E-05
29	315	1.11E-03	297	9.58E-04	251	5.36E-04	152	2.39E-04	80	1.09E-04	68	1.32E-04
30	1106	4.58E-02	1311	1.05E-01	1249	5.39E-02	488	6.92E-03	538	2.23E-02	810	1.60E-02
31	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
32	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
33	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
34	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
35	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
36	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
37	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
38	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
39	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
40	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
41	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
42	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
43	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
44	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
45	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
SUM	2615	4.84E-02	2783	1.07E-01	2283	5.51E-02	1302	7.51E-03	1014	2.25E-02	1233	1.66E-02

Output (cont.)

-119-

MOR-6

ENERGY GROUP	REGION 19 NUMBER WEIGHT	REGION 20 NUMBER WEIGHT	REGION 21 NUMBER WEIGHT	REGION 22 NUMBER WEIGHT	REGION 23 NUMBER WEIGHT	REGION 24 NUMBER WEIGHT
1	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
2	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
3	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
4	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
5	0 0.	2 2.91E-05	2 2.03E-04	1 1.04E-06	0 0.	0 0.
6	1 8.50E-06	0 0.	1 7.40E-07	2 9.55E-06	2 3.79E-07	1 5.09E-05
7	0 0.	1 8.00E-08	1 5.54E-07	0 0.	0 0.	2 5.46E-07
8	1 8.00E-08	3 2.07E-05	1 1.45E-08	2 1.24E-06	0 0.	0 0.
9	5 2.16E-05	2 1.97E-06	0 0.	0 0.	0 0.	1 4.14E-07
10	5 1.43E-06	2 1.51E-06	2 1.85E-07	2 1.34E-08	1 4.56E-11	2 2.80E-07
11	5 7.65E-07	1 6.99E-08	0 0.	0 0.	2 3.24E-10	0 0.
12	0 0.	0 0.	0 0.	2 3.30E-08	1 1.98E-10	1 2.02E-08
13	1 1.53E-07	1 2.49E-08	0 0.	1 1.11E-09	3 1.12E-08	2 3.76E-08
14	1 4.52E-09	0 0.	0 0.	2 3.35E-10	1 5.43E-11	1 1.44E-08
15	5 1.27E-08	1 1.04E-08	0 0.	0 0.	3 1.31E-10	1 1.26E-08
16	2 1.47E-08	0 0.	2 1.11E-09	0 0.	3 1.44E-11	0 0.
17	2 2.16E-09	1 3.42E-10	0 0.	0 0.	3 6.40E-12	0 0.
18	4 5.87E-09	1 4.48E-09	1 4.48E-09	0 0.	1 2.62E-11	2 6.98E-09
19	3 1.02E-10	1 2.69E-08	2 1.30E-10	1 1.91E-11	0 0.	1 2.44E-09
20	0 0.	1 5.58E-10	1 4.27E-09	0 0.	6 4.93E-10	3 7.94E-09
21	11 4.32E-09	3 4.36E-09	0 0.	3 3.23E-10	1 6.11E-12	6 2.21E-08
22	5 4.12E-09	8 1.49E-08	7 5.28E-08	5 1.38E-09	8 9.35E-11	0 0.
23	11 8.53E-09	6 2.17E-08	7 1.59E-07	7 2.19E-08	4 1.40E-10	5 2.91E-08
24	15 1.66E-07	7 3.81E-08	3 1.43E-07	10 3.55E-08	10 7.08E-08	2 5.57E-08
25	14 2.39E-07	5 1.27E-07	3 4.66E-07	2 4.12E-08	11 1.57E-08	2 1.29E-07
26	23 8.88E-07	4 2.73E-07	11 9.00E-06	5 1.46E-07	3 7.84E-08	11 2.45E-06
27	18 9.21E-07	26 8.92E-06	9 1.51E-05	8 1.91E-06	17 8.98E-06	10 5.02E-06
28	47 2.83E-05	21 3.35E-05	112 4.67E-04	199 3.21E-04	17 8.44E-05	13 1.09E-05
29	267 4.87E-03	0 0.	0 0.	0 0.	0 0.	5 1.65E-05
30	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
31	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
32	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
33	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
34	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
35	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.

1 36	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
37	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
38	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
39	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
40	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
41	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
42	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
43	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
44	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
45	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
SUM	448	4.96E-03	99	2.76E-04	164	5.02E-04	251	3.25E-04	263	1.10E-04	72	1.17E-04

ENERGY GROUP	REGION 25		REGION 26		REGION 27	
	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT
1	0	0.	0	0.	0	0.
2	0	0.	0	0.	0	0.
3	0	0.	0	0.	0	0.
4	0	0.	0	0.	0	0.
5	0	0.	0	0.	0	0.
6	1	9.22E-05	0	0.	0	0.
7	1	2.28E-05	0	0.	0	0.
8	0	0.	0	0.	0	0.
9	2	6.59E-06	0	0.	0	0.
10	2	4.02E-07	1	1.92E-07	1	2.27E-07
11	2	3.97E-07	2	8.00E-07	1	1.05E-07
12	2	9.60E-08	2	2.48E-07	0	0.
13	0	0.	1	2.61E-08	0	0.
14	0	0.	0	0.	0	0.
15	2	2.03E-08	0	0.	0	0.
16	3	9.59E-09	1	6.07E-09	1	3.60E-10
17	0	0.	1	1.34E-09	0	0.
18	0	0.	0	0.	0	0.
19	0	0.	0	0.	1	1.57E-10
20	1	3.68E-09	1	2.44E-09	0	0.
21	0	0.	1	1.51E-09	0	0.
22	3	6.87E-09	4	1.44E-08	1	1.55E-10
23	3	7.74E-09	1	1.43E-08	1	1.43E-08
24	6	3.52E-08	3	1.57E-08	0	0.
25	7	1.06E-07	11	2.34E-07	0	0.
26	3	5.84E-07	2	1.20E-07	2	6.63E-08
27	8	1.83E-06	11	1.77E-06	1	2.26E-07
28	11	2.25E-05	1	9.62E-07	1	2.81E-07
29	7	1.60E-05	9	4.29E-05	0	0.
30	19	2.64E-04	20	1.90E-04	6	1.05E-05
31	0	0.	0	0.	0	0.
32	0	0.	0	0.	0	0.
33	0	0.	0	0.	0	0.
34	0	0.	0	0.	0	0.
35	0	0.	0	0.	0	0.
36	0	0.	0	0.	0	0.
37	0	0.	0	0.	0	0.
38	0	0.	0	0.	0	0.
39	0	0.	0	0.	0	0.
40	0	0.	0	0.	0	0.
41	0	0.	0	0.	0	0.
42	0	0.	0	0.	0	0.
43	0	0.	0	0.	0	0.
44	0	0.	0	0.	0	0.
45	0	0.	0	0.	0	0.
SUM	83	4.27E-04	72	2.38E-04	16	1.14E-05

Output (cont.)

-120-

MOR-6

SECONDARY PRODUCTION COUNTERS (BOTH THE GROUPS CAUSING PRODUCTION AND RESULTING FROM PRODUCTION)

ENERGY GROUP	REGION 1		REGION 2		REGION 3		REGION 4		REGION 5		REGION 6	
	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT
1	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
2	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
3	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
4	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
5	0	0.	1	8.40E-03	0	0.	0	0.	0	0.	0	0.
6	1	8.25E-06	2	1.81E-02	0	0.	1	2.88E-04	0	0.	4	4.55E-04
7	1	1.50E-05	5	9.27E-02	3	9.50E-04	0	0.	2	1.90E-03	1	9.25E-04
8	1	7.63E-06	4	8.98E-02	1	2.91E-05	1	1.94E-05	1	2.61E-05	3	2.69E-05
9	2	3.22E-05	11	1.12E-01	6	3.68E-04	3	1.19E-04	1	1.24E-05	0	0.
10	4	5.72E-05	8	9.32E-02	4	2.56E-04	5	4.37E-04	2	1.59E-04	1	1.08E-05
11	4	5.12E-05	11	1.15E-01	3	7.46E-05	4	1.22E-04	2	3.53E-05	2	2.03E-05
12	1	1.49E-05	8	5.23E-02	6	1.20E-04	3	4.42E-05	1	6.87E-06	1	3.25E-06
13	2	1.45E-05	4	2.23E-02	3	3.66E-05	2	8.68E-05	1	1.34E-05	1	2.58E-06
14	3	2.33E-04	4	2.02E-02	5	7.39E-05	4	1.62E-04	1	7.73E-06	3	2.18E-05
15	1	5.29E-05	4	9.72E-03	4	1.05E-05	3	4.26E-06	2	2.98E-06	1	7.64E-07
16	3	8.81E-05	3	3.94E-03	6	5.39E-06	2	1.67E-06	1	2.69E-07	3	1.24E-06
17	1	3.29E-06	3	4.48E-03	8	2.24E-06	3	5.03E-07	3	7.07E-07	2	1.77E-07
18	0	0.	2	6.76E-04	5	4.03E-07	3	1.88E-07	1	3.82E-08	0	0.
19	1	1.73E-06	2	2.18E-04	7	8.56E-07	4	2.66E-07	2	8.16E-08	0	0.
20	0	0.	1	4.93E-05	5	3.75E-07	1	5.08E-08	3	2.63E-07	1	5.04E-08
21	0	0.	1	1.33E-05	5	3.37E-07	3	1.14E-07	2	2.59E-07	2	4.38E-08
22	0	0.	8	1.05E-04	20	1.39E-06	11	1.11E-06	4	2.32E-07	2	6.97E-08
23	1	2.97E-06	4	3.85E-05	17	1.70E-06	9	7.37E-07	4	3.93E-07	5	5.19E-07
24	1	9.62E-06	6	2.08E-05	33	8.69E-06	21	7.75E-06	12	2.35E-06	13	2.34E-06
25	0	0.	14	1.11E-04	41	2.75E-05	30	3.69E-05	10	9.28E-06	10	6.40E-06
26	0	0.	3	2.91E-05	11	8.70E-05	10	4.59E-05	4	1.70E-05	5	2.24E-05
27	0	0.	1	2.88E-05	10	1.56E-04	9	1.72E-04	4	6.81E-05	2	2.82E-05
28	0	0.	2	6.55E-05	10	4.80E-04	13	7.87E-04	3	1.04E-04	5	2.51E-04
29	0	0.	0	0.	25	6.04E-03	23	5.23E-03	9	1.07E-03	5	3.71E-04
30	0	0.	4	7.01E-03	84	9.75E-02	117	2.47E-01	67	1.06E-01	50	3.81E-02
31	0	0.	0	0.	0	0.	3	7.07E-03	2	3.34E-03	0	0.
32	0	0.	14	3.62E-03	8	3.96E-03	10	1.77E-02	4	1.80E-03	1	1.81E-03
33	1	1.52E-05	3	2.74E-05	24	1.78E-02	21	2.55E-02	18	1.83E-02	15	7.29E-03
34	1	7.21E-06	2	1.99E-02	8	7.56E-03	1	1.56E-03	1	9.84E-05	1	2.00E-07
35	0	0.	0	0.	10	9.72E-04	4	7.32E-03	3	2.93E-04	2	2.22E-04
36	0	0.	12	2.03E-02	6	1.00E-04	6	1.01E-03	2	1.02E-06	5	1.02E-03
37	1	1.49E-05	4	2.78E-02	36	1.52E-03	19	3.82E-03	12	8.80E-04	10	7.16E-04
38	0	0.	2	1.64E-02	167	6.39E-02	168	1.64E-01	71	6.87E-02	57	2.32E-02
39	1	7.85E-05	8	1.88E-02	18	3.69E-03	11	4.91E-03	15	8.28E-03	13	2.04E-03
40	3	4.22E-05	8	5.44E-02	13	6.30E-04	10	9.57E-04	3	7.31E-06	3	2.03E-03
41	6	1.28E-04	7	5.29E-02	19	2.42E-03	19	1.60E-02	6	6.96E-03	9	1.92E-03
42	7	2.36E-04	6	9.74E-02	1	3.04E-03	2	3.75E-03	1	4.38E-04	0	0.
43	1	9.62E-06	41	2.19E-01	0	0.	0	0.	0	0.	0	0.
44	2	1.97E-05	4	5.52E-02	12	5.53E-04	11	3.45E-04	4	3.05E-05	6	3.71E-05
45	4	4.14E-05	5	6.41E-02	0	0.	0	0.	0	0.	0	0.
SUM	54	1.19E-03	232	1.30E+00	644	2.12E-01	570	5.09E-01	284	2.18E-01	244	8.05E-02

ENERGY GROUP	REGION 7		REGION 8		REGION 9		REGION 10		REGION 11		REGION 12	
	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT
1	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
2	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
3	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.

Output (cont.)

-121-

MOR-6

Output (cont.)

-122-

MOR-6

1	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.	0	0.
5	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.	0	0.
6	0	0.	1	3.73E-04	0	C.	0	0.	0	0.	0	0.	3	3.12E-03
7	1	1.74E-04	1	7.57E-05	0	C.	0	0.	0	0.	0	0.	1	1.27E-04
8	0	0.	0	0.	1	1.20E-05	0	0.	0	0.	0	0.	1	2.12E-05
9	3	1.49E-05	2	4.19E-05	0	0.	0	0.	0	0.	0	0.	1	1.69E-05
10	0	0.	0	0.	0	C.	0	0.	2	5.04E-08	1	1.56E-05	1	1.56E-05
11	1	3.29E-05	2	2.11E-06	0	C.	0	0.	5	3.84E-06	3	5.92E-05	3	5.92E-05
12	0	0.	5	5.61E-06	0	0.	0	0.	6	5.89E-07	2	5.10E-05	2	5.10E-05
13	1	4.68E-06	0	0.	0	C.	0	0.	0	0.	2	9.46E-06	2	9.46E-06
14	1	6.88E-06	2	3.15E-07	0	C.	1	2.28E-05	5	1.36E-06	2	1.12E-05	2	1.12E-05
15	2	4.49E-07	0	0.	0	C.	0	0.	5	3.76E-07	2	3.01E-06	2	3.01E-06
16	1	1.71E-07	0	0.	1	5.29E-07	0	0.	0	0.	4	5.37E-06	4	5.37E-06
17	1	3.01E-07	5	4.27E-08	1	1.39E-08	0	0.	0	0.	3	6.33E-07	3	6.33E-07
18	1	6.34E-08	1	1.10E-08	0	C.	0	0.	0	0.	0	0.	0	0.
19	1	2.08E-08	1	2.04E-08	0	C.	0	0.	1	1.01E-08	4	1.45E-07	4	1.45E-07
20	3	3.91E-07	1	2.37E-08	0	C.	0	0.	11	1.22E-08	2	6.76E-08	2	6.76E-08
21	1	2.57E-09	1	1.86E-08	0	C.	0	0.	1	8.36E-09	2	3.84E-08	2	3.84E-08
22	4	2.77E-07	3	2.03E-07	1	2.41E-08	5	1.15E-08	5	1.70E-09	4	2.61E-07	4	2.61E-07
23	3	1.46E-07	1	3.00E-08	1	5.65E-08	3	2.35E-08	5	2.07E-09	5	1.75E-07	5	1.75E-07
24	6	7.28E-07	11	1.13E-06	2	1.46E-07	2	8.47E-08	5	4.80E-09	8	1.45E-06	8	1.45E-06
25	6	1.35E-06	9	4.76E-06	0	C.	14	8.49E-07	15	4.32E-08	11	6.33E-06	11	6.33E-06
26	5	2.69E-05	2	1.61E-05	4	6.17E-07	4	1.89E-06	5	4.31E-08	3	1.18E-05	3	1.18E-05
27	2	1.12E-05	2	1.20E-05	2	5.70E-05	1	1.38E-06	26	2.19E-04	4	4.24E-05	4	4.24E-05
28	2	7.81E-05	4	1.73E-04	0	C.	2	9.10E-06	5	3.69E-07	5	1.49E-04	5	1.49E-04
29	4	2.94E-04	5	4.15E-04	0	C.	0	0.	5	9.45E-07	7	8.16E-04	7	8.16E-04
30	81	6.36E-02	13	6.33E-03	49	1.90E-03	43	2.33E-03	42	3.07E-04	49	4.12E-02	49	4.12E-02
31	0	0.	0	0.	1	1.99E-05	0	0.	0	0.	0	0.	0	0.
32	2	6.64E-04	3	2.42E-03	4	7.98E-05	3	1.09E-04	7	6.69E-05	3	2.58E-03	3	2.58E-03
33	10	2.76E-03	12	7.16E-04	7	1.38E-04	7	2.72E-04	19	8.86E-05	9	3.10E-03	9	3.10E-03
34	5	3.28E-03	2	2.16E-04	0	C.	2	1.09E-04	5	1.12E-07	1	1.25E-06	1	1.25E-06
35	1	1.93E-07	1	1.98E-04	0	C.	1	5.43E-05	1	4.89E-07	4	3.87E-03	4	3.87E-03
36	3	3.53E-05	1	9.71E-05	1	1.99E-05	1	5.43E-05	0	0.	4	9.06E-05	4	9.06E-05
37	11	6.28E-03	6	1.05E-03	5	7.98E-05	2	1.09E-04	20	1.86E-06	11	3.74E-03	11	3.74E-03
38	65	3.94E-02	33	2.59E-03	30	9.72E-04	45	1.10E-03	65	2.99E-04	61	2.69E-02	61	2.69E-02
39	7	5.74E-03	3	3.70E-06	4	5.43E-04	5	1.09E-04	7	8.59E-07	17	3.92E-03	17	3.92E-03
40	9	9.39E-04	5	4.27E-08	1	1.54E-07	1	5.43E-05	2	1.39E-05	6	8.96E-05	6	8.96E-05
41	11	4.93E-03	4	1.09E-04	8	1.20E-04	8	4.03E-04	10	2.25E-05	4	1.29E-03	4	1.29E-03
42	1	1.29E-04	0	0.	0	C.	0	0.	2	3.53E-05	0	0.	0	0.
43	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.	0	0.
44	5	4.49E-05	2	4.19E-05	1	5.29E-07	0	0.	11	4.23E-06	9	8.36E-05	9	8.36E-05
45	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.	0	0.
SUM	260	1.28E-01	144	1.49E-02	124	3.95E-03	150	4.74E-03	298	1.07E-03	258	9.13E-02	258	9.13E-02

ENERGY GROUP	REGION 13	REGION 14	REGION 15	REGION 16	REGION 17	REGION 18
GROUP	NUMBER WEIGHT	NUMBER WEIGHT	NUMBER WEIGHT	NUMBER WEIGHT	NUMBER WEIGHT	NUMBER WEIGHT
1	0 0.	0 0.	0 C.	0 0.	0 0.	0 0.
2	0 0.	0 0.	0 C.	0 0.	0 0.	0 0.
3	0 0.	0 0.	0 C.	0 0.	0 0.	0 0.
4	0 0.	0 0.	0 C.	0 0.	0 0.	0 0.
5	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
6	0 0.	0 0.	1 2.84E-04	0 0.	0 0.	5 4.30E-04
7	4 1.71E-04	1 4.14E-05	0 C.	0 0.	1 1.26E-05	0 0.
8	2 8.51E-05	1 1.08E-05	1 8.79E-06	1 5.25E-06	1 2.20E-05	0 0.
9	3 1.40E-04	2 2.77E-05	1 1.13E-05	1 4.16E-06	1 3.47E-06	1 3.73E-05
10	3 1.37E-04	1 1.17E-05	1 1.13E-05	2 2.83E-06	0 0.	0 0.
11	3 3.58E-05	2 1.05E-05	2 2.43E-05	2 2.86E-05	6 3.89E-06	2 2.93E-06
12	2 2.34E-05	1 5.71E-06	1 3.14E-06	1 8.92E-06	2 6.79E-06	3 1.27E-06
13	2 4.68E-05	3 4.33E-05	3 2.05E-05	1 2.03E-06	1 4.94E-07	0 0.
14	1 2.85E-06	2 9.31E-06	1 1.43E-06	2 4.89E-06	2 1.72E-06	0 0.

Output (cont.)

-123-

MOR-6

15	4	9.09E-06	4	3.03E-06	2	1.62E-06	0	0.	0	0.	1	9.23E-08
16	1	3.29E-07	2	7.15E-07	2	1.60E-06	2	4.77E-07	4	8.93E-07	3	2.34E-07
17	3	2.76E-07	3	3.13E-07	2	8.37E-08	2	1.43E-07	7	3.43E-08	0	0.
18	2	6.91E-08	1	1.37E-08	2	3.90E-08	0	0.	4	1.22E-08	0	0.
19	3	1.40E-07	1	1.23E-08	2	3.38E-08	1	2.72E-09	2	1.28E-08	1	5.03E-08
20	0	0.	1	1.95E-08	2	4.76E-08	3	5.67E-08	0	0.	0	0.
21	4	1.87E-07	1	7.83E-09	0	C.	0	0.	2	7.38E-08	0	0.
22	6	2.95E-07	4	1.23E-07	6	1.50E-07	5	4.33E-08	3	1.25E-07	1	1.27E-08
23	11	8.32E-07	4	1.93E-07	4	1.03E-07	4	9.06E-08	8	2.80E-07	3	1.17E-07
24	20	3.66E-06	20	2.99E-06	10	8.26E-07	8	5.57E-07	7	5.91E-07	4	2.77E-07
25	19	1.21E-05	15	5.14E-06	11	3.07E-06	10	1.83E-06	7	1.13E-07	6	1.14E-06
26	6	2.04E-05	7	3.31E-05	4	7.92E-06	4	3.50E-06	4	6.93E-06	2	3.65E-06
27	6	4.78E-05	5	3.80E-05	3	1.14E-05	7	2.37E-05	3	1.28E-05	3	1.14E-05
28	8	3.31E-04	7	2.90E-04	7	1.19E-04	3	2.08E-05	5	1.06E-04	2	2.37E-05
29	10	9.03E-04	12	1.43E-03	6	2.32E-04	7	5.13E-04	9	2.47E-04	4	7.27E-05
30	115	4.14E-02	141	1.14E-01	124	4.37E-02	25	5.13E-03	237	2.92E-02	68	1.58E-02
31	1	2.78E-04	1	8.76E-04	1	4.83E-05	1	1.36E-04	1	5.19E-06	0	0.
32	8	8.46E-04	10	5.73E-03	6	2.32E-03	1	3.44E-07	16	3.63E-04	10	7.53E-04
33	18	9.36E-03	24	1.24E-02	14	4.25E-03	9	7.53E-04	25	4.13E-04	8	8.90E-04
34	6	1.39E-03	7	4.37E-03	3	1.01E-03	1	2.29E-05	4	1.00E-04	0	0.
35	4	5.56E-04	5	2.63E-03	8	4.98E-03	1	1.06E-06	5	1.32E-04	0	0.
36	9	4.56E-03	6	4.38E-03	6	7.71E-04	1	1.49E-04	3	8.44E-05	2	6.22E-05
37	22	1.43E-03	17	7.03E-03	14	3.01E-03	9	2.76E-04	26	5.65E-04	4	1.02E-04
38	131	1.94E-02	121	5.69E-02	103	2.46E-02	50	3.91E-03	174	1.21E-02	64	1.12E-02
39	9	1.45E-03	19	1.03E-02	17	7.62E-04	8	1.11E-04	23	1.49E-02	9	2.54E-03
40	7	1.11E-03	7	1.78E-03	3	6.05E-05	1	3.72E-07	8	1.97E-04	1	1.54E-04
41	19	2.98E-03	21	9.37E-03	15	1.32E-03	6	3.85E-04	24	6.69E-04	4	6.88E-04
42	0	0.	0	0.	2	4.83E-05	0	0.	2	5.01E-05	0	0.
43	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
44	4	8.27E-06	3	8.51E-06	6	2.27E-05	3	2.94E-06	5	4.36E-06	7	4.05E-05
45	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
SUM	476	8.67E-02	482	2.32E-01	396	8.88E-02	182	1.15E-02	632	5.92E-02	218	3.28E-02

ENERGY GROUP	REGION 19 NUMBER WEIGHT	REGION 20 NUMBER WEIGHT	REGION 21 NUMBER WEIGHT	REGION 22 NUMBER WEIGHT	REGION 23 NUMBER WEIGHT	REGION 24 NUMBER WEIGHT
1	0 0.	0 0.	0 C.	0 0.	0 0.	0 0.
2	0 0.	0 0.	0 C.	0 0.	0 0.	0 0.
3	0 0.	0 0.	0 C.	0 0.	0 0.	0 0.
4	0 0.	0 0.	0 C.	0 0.	0 0.	0 0.
5	0 0.	0 0.	0 C.	0 0.	0 0.	0 0.
6	0 0.	0 0.	0 C.	0 0.	0 0.	0 0.
7	1 8.50E-05	0 0.	2 2.14E-05	0 0.	0 0.	1 5.09E-04
8	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
9	0 0.	0 0.	0 C.	0 0.	0 0.	0 0.
10	5 1.88E-05	5 1.95E-05	0 C.	0 0.	0 0.	0 0.
11	0 0.	5 1.90E-06	0 C.	0 0.	0 0.	0 0.
12	1 5.20E-07	5 1.45E-06	0 C.	0 0.	0 0.	0 0.
13	0 0.	0 0.	0 C.	0 0.	2 3.21E-10	0 0.
14	0 0.	0 0.	0 C.	2 3.30E-07	0 0.	0 0.
15	0 0.	0 0.	0 C.	0 0.	0 0.	0 0.
16	0 0.	0 0.	0 C.	2 3.35E-09	0 0.	0 0.
17	1 1.04E-07	0 0.	0 C.	0 0.	0 0.	0 0.
18	0 0.	0 0.	1 5.55E-09	0 0.	0 0.	0 0.
19	0 0.	0 0.	0 C.	0 0.	5 4.03E-12	0 0.
20	0 0.	0 0.	0 C.	0 0.	0 0.	1 2.44E-08
21	0 0.	0 0.	0 C.	0 0.	0 0.	1 1.16E-08
22	4 3.25E-09	0 0.	0 C.	0 0.	11 4.72E-10	1 1.44E-08
23	1 4.65E-09	1 4.14E-09	0 C.	0 0.	0 0.	0 0.
24	3 2.10E-09	1 8.85E-09	15 4.07E-08	6 1.31E-09	0 0.	1 2.35E-08
25	1 4.45E-07	3 4.54E-08	15 1.22E-07	1 4.92E-08	0 0.	0 0.

1 26	1	3.29E-07	0	0.	1	6.25E-08	1	1.18E-08	0	0.	0	0.
27	1	8.60E-07	0	0.	1	1.63E-07	0	0.	0	0.	1	7.37E-07
28	2	3.22E-07	0	0.	28	7.51E-06	1	1.01E-07	0	0.	2	1.40E-05
29	2	8.12E-07	1	3.87E-06	23	1.44E-05	1	9.67E-06	0	0.	0	0.
30	102	4.98E-03	5	3.46E-05	42	4.69E-04	30	2.81E-04	5	1.31E-04	0	0.
31	1	4.93E-05	0	0.	0	0.	0	0.	0	0.	0	0.
32	3	1.48E-04	0	0.	8	4.81E-05	0	0.	0	0.	0	0.
33	10	5.29E-04	1	6.91E-06	23	8.73E-05	3	1.07E-05	1	6.07E-06	0	0.
34	7	1.97E-04	0	0.	1	1.14E-05	0	0.	1	1.15E-05	0	0.
35	6	2.96E-04	0	0.	4	1.07E-06	0	0.	0	0.	1	5.09E-04
36	5	1.49E-04	0	0.	0	0.	2	2.11E-05	0	0.	0	0.
37	6	1.97E-04	0	0.	2	1.68E-07	6	5.69E-05	5	4.03E-12	2	3.60E-08
38	68	2.96E-03	9	2.77E-05	69	2.57E-04	28	1.92E-04	14	1.14E-04	5	1.48E-05
39	5	2.47E-04	10	3.35E-06	6	6.81E-05	3	1.05E-05	2	3.21E-10	0	0.
40	3	9.87E-05	1	3.87E-06	0	0.	0	0.	0	0.	0	0.
41	5	1.98E-04	5	1.95E-05	15	3.89E-05	1	4.04E-08	0	0.	0	0.
42	1	4.06E-07	0	0.	0	0.	0	0.	0	0.	0	0.
43	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
44	5	1.88E-05	0	0.	0	0.	1	2.89E-07	0	0.	0	0.
45	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
SUM	250	1.02E-02	52	1.23E-04	256	1.02E-03	88	5.83E-04	46	2.63E-04	16	1.05E-03

ENERGY GROUP	REGION 25 NUMBER WEIGHT	REGION 26 NUMBER WEIGHT	REGION 27 NUMBER WEIGHT
1	0 0.	0 0.	0 0.
2	0 0.	0 0.	0 0.
3	0 0.	0 0.	0 0.
4	0 0.	0 0.	0 0.
5	0 0.	0 0.	0 0.
6	0 0.	0 0.	0 0.
7	0 0.	0 0.	0 0.
8	0 0.	0 0.	0 0.
9	0 0.	0 0.	0 0.
10	0 0.	0 0.	0 0.
11	1 1.98E-06	0 0.	0 0.
12	0 0.	1 2.10E-07	0 0.
13	0 0.	0 0.	0 0.
14	0 0.	0 0.	0 0.
15	0 0.	0 0.	0 0.
16	0 0.	0 0.	0 0.
17	0 0.	0 0.	0 0.
18	0 0.	0 0.	0 0.
19	0 0.	0 0.	0 0.
20	0 0.	1 2.44E-08	0 0.
21	0 0.	0 0.	0 0.
22	0 0.	0 0.	1 1.55E-09
23	1 1.03E-08	0 0.	0 0.
24	0 0.	0 0.	0 0.
25	1 8.78E-08	2 1.50E-07	0 0.
26	2 6.70E-07	0 0.	0 0.
27	1 1.68E-07	1 1.68E-07	0 0.
28	1 1.91E-05	0 0.	0 0.
29	0 0.	4 2.87E-05	0 0.
30	1 1.74E-04	9 1.70E-04	0 0.
31	0 0.	0 0.	0 0.
32	0 0.	0 0.	0 0.
33	1 1.98E-06	0 0.	0 0.
34	0 0.	0 0.	0 0.
35	0 0.	1 2.10E-07	1 1.55E-09
36	0 0.	0 0.	0 0.

Output (cont.)

-124-

MOR-6

1 37	0	0.	1	2.44E-08	0	C.
38	7	1.94E-04	16	1.99E-04	0	C.
39	0	C.	0	0.	0	C.
40	0	C.	0	0.	0	C.
41	0	0.	0	0.	0	C.
42	0	0.	0	0.	0	0.
43	0	0.	0	0.	0	C.
44	0	0.	0	0.	0	C.
45	0	0.	0	0.	0	C.
SUM	16	3.92E-04	36	3.98E-04	2	3.10E-09

NUMBER OF PARTICLES PRODUCED BY SCATTERINGS

ENERGY GRUP	REGION 1		REGION 2		REGION 3		REGION 4		REGION 5		REGION 6	
	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT
1	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
2	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
3	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
4	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
5	0	0.	2	1.91E-03	0	C.	2	1.51E-03	0	0.	0	0.
6	5	4.38E-03	5	3.65E-03	2	7.10E-03	1	7.20E-04	1	3.53E-04	2	5.93E-03
7	8	1.45E-02	24	2.75E-02	12	1.36E-02	4	6.82E-03	4	7.62E-03	3	5.74E-03
8	4	2.85E-03	18	2.56E-02	5	7.05E-03	7	8.67E-03	4	6.19E-03	2	6.24E-04
9	14	2.28E-02	72	1.07E-01	24	2.77E-02	13	2.51E-02	7	9.53E-03	1	5.02E-04
10	18	2.12E-02	71	8.36E-02	31	6.65E-02	17	2.90E-02	6	3.23E-03	5	5.30E-03
11	10	1.08E-02	84	1.35E-01	33	4.84E-02	21	2.67E-02	14	1.78E-02	11	1.08E-02
12	11	1.52E-02	70	1.29E-01	39	7.37E-02	16	2.93E-02	12	1.49E-02	10	1.84E-02
13	28	3.32E-02	35	5.42E-02	26	4.52E-02	15	2.56E-02	10	1.12E-02	7	1.35E-02
14	24	4.89E-02	53	7.55E-02	17	2.82E-02	29	4.11E-02	13	1.61E-02	7	5.89E-03
15	17	1.94E-02	58	9.24E-02	21	4.86E-02	23	3.61E-02	8	8.35E-03	10	8.62E-03
16	13	1.71E-02	69	1.01E-01	42	7.22E-02	15	2.45E-02	15	2.99E-02	15	1.32E-02
17	13	1.28E-02	41	8.71E-02	46	8.22E-02	24	3.04E-02	14	1.44E-02	12	1.22E-02
18	2	8.75E-04	40	4.84E-02	47	8.42E-02	22	4.52E-02	14	1.78E-02	4	2.39E-03
19	6	1.14E-02	41	5.54E-02	44	7.86E-02	22	2.48E-02	11	1.16E-02	4	6.64E-03
20	1	3.21E-04	14	1.84E-02	47	8.36E-02	22	3.13E-02	18	2.50E-02	7	1.14E-02
21	0	0.	12	1.69E-02	32	5.54E-02	22	3.97E-02	15	2.42E-02	11	1.36E-02
22	11	1.28E-02	77	1.08E-01	173	2.59E-01	107	1.62E-01	55	7.57E-02	26	2.22E-02
23	17	1.18E-02	32	3.46E-02	176	2.93E-01	90	1.39E-01	57	7.46E-02	34	2.90E-02
24	12	1.67E-02	30	4.93E-02	397	6.38E-01	239	4.02E-01	100	1.41E-01	95	9.43E-02
25	5	7.70E-03	41	6.06E-02	413	6.25E-01	298	5.99E-01	136	2.03E-01	89	1.11E-01
26	0	0.	33	3.53E-02	341	4.85E-01	282	4.63E-01	117	1.26E-01	88	9.43E-02
27	0	0.	33	3.97E-02	339	5.38E-01	316	4.96E-01	105	1.50E-01	75	9.56E-02
28	0	0.	16	2.64E-02	280	4.33E-01	319	5.13E-01	116	1.88E-01	126	1.55E-01
29	0	0.	13	1.77E-02	601	9.79E-01	565	1.00E+00	294	3.78E-01	196	2.50E-01
30	0	0.	12	8.93E-02	1803	1.35E+01	2472	2.65E+01	1256	1.06E+01	813	5.07E+00
31	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
32	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
33	0	0.	0	0.	0	0.	0	0.	1	3.11E-06	2	4.59E-04
34	0	0.	0	0.	0	C.	0	0.	4	5.83E-03	2	2.91E-04
35	0	0.	0	0.	0	C.	1	3.35E-04	3	9.54E-04	0	0.
36	0	0.	1	3.46E-04	1	7.70E-07	0	0.	1	1.47E-03	0	C.
37	0	0.	4	1.65E-02	4	3.23E-05	2	5.48E-04	3	7.72E-07	2	1.59E-07
38	0	0.	6	9.71E-03	8	2.89E-03	12	3.30E-03	8	2.63E-03	14	6.36E-03
39	0	0.	4	2.01E-04	11	6.17E-03	21	6.94E-03	20	8.19E-03	23	9.06E-03
40	0	0.	16	3.13E-02	14	2.02E-03	17	3.43E-03	36	1.29E-02	20	4.86E-03
41	0	0.	18	2.87E-02	11	5.74E-03	31	7.86E-03	31	1.35E-02	29	1.31E-02
42	0	0.	25	3.18E-02	15	4.57E-03	27	1.00E-02	29	1.11E-02	28	9.89E-03

Output (cont.)

-125-

MOR-6

1 43	0	0.	59	7.29E-02	35	5.27E-03	36	1.54E-02	45	6.70E-03	45	1.12E-02
44	3	8.31E-05	96	8.94E-02	31	4.92E-03	49	1.27E-02	63	1.27E-02	57	9.10E-03
45	0	0.	478	1.62E-01	60	1.05E-02	157	2.83E-02	163	2.57E-02	173	1.17E-02
SUM	222	2.85E-01	1703	1.97E+00	5201	1.86E+01	5316	3.08E+01	2809	1.22E+01	2048	6.13E+00

ENERGY GROUP	REGION 7		REGION 8		REGION 9		REGION 10		REGION 11		REGION 12	
	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT
1	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
2	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
3	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
4	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
5	0	0.	0	0.	0	0.	0	0.	0	0.	1	4.16E-04
6	3	9.54E-04	0	0.	0	0.	0	0.	0	0.	8	5.78E-03
7	2	2.28E-03	0	0.	2	2.41E-03	1	1.66E-03	0	0.	5	3.25E-03
8	0	0.	1	4.67E-04	0	0.	0	0.	0	0.	2	8.35E-04
9	4	1.95E-03	2	1.67E-03	2	1.64E-03	0	0.	1	2.77E-04	4	2.19E-03
10	4	2.22E-03	3	1.78E-03	0	0.	0	0.	4	3.78E-06	8	9.77E-03
11	2	6.25E-04	2	9.54E-04	0	0.	1	1.63E-03	2	2.66E-06	6	5.03E-03
12	3	4.20E-03	1	8.61E-04	1	9.69E-05	0	0.	3	3.37E-04	9	8.68E-03
13	4	3.87E-03	3	1.37E-03	2	3.04E-04	0	0.	2	3.92E-06	8	5.10E-03
14	6	4.27E-03	3	5.06E-04	3	2.72E-03	1	2.72E-03	2	1.63E-03	12	1.24E-02
15	4	3.49E-03	3	1.77E-03	1	5.19E-04	0	0.	3	1.63E-03	15	1.97E-02
16	7	3.79E-03	3	1.56E-03	4	7.74E-03	0	0.	0	0.	11	1.08E-02
17	0	0.	6	4.25E-03	4	5.84E-04	0	0.	2	3.37E-04	12	3.44E-02
18	7	5.26E-03	3	2.30E-03	2	4.12E-04	3	2.48E-03	0	0.	13	7.03E-03
19	6	6.85E-03	9	8.14E-03	1	7.77E-05	2	2.92E-03	2	1.96E-03	14	3.05E-02
20	8	1.77E-02	1	4.36E-04	3	1.43E-03	0	0.	3	2.27E-03	13	1.48E-02
21	1	7.71E-04	7	4.98E-03	2	4.13E-03	0	0.	2	1.96E-03	10	1.16E-02
22	21	2.30E-02	25	2.85E-02	11	1.01E-02	6	3.64E-03	5	3.59E-03	34	3.74E-02
23	24	2.90E-02	14	1.21E-02	6	1.03E-02	9	5.48E-03	8	2.42E-03	31	3.40E-02
24	46	4.10E-02	28	1.84E-02	15	6.94E-03	15	9.74E-03	12	1.02E-02	73	1.31E-01
25	65	6.13E-02	38	3.91E-02	7	1.05E-02	25	2.01E-02	11	6.22E-03	85	1.06E-01
26	61	5.23E-02	36	8.35E-02	18	1.89E-02	13	1.97E-02	8	8.25E-03	103	1.18E-01
27	65	6.74E-02	37	4.75E-02	21	1.88E-02	13	1.83E-02	13	5.14E-03	64	6.46E-02
28	66	6.66E-02	55	6.96E-02	24	2.79E-02	9	8.07E-03	14	1.50E-02	88	1.21E-01
29	108	1.28E-01	52	6.24E-02	42	4.32E-02	15	2.92E-02	14	9.26E-03	163	1.88E-01
30	796	6.65E+00	186	6.23E-01	307	1.55E-01	238	2.93E-01	1019	4.03E-02	773	5.03E+00
31	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
32	0	0.	0	0.	0	0.	1	2.13E-05	0	0.	0	0.
33	0	0.	3	2.47E-05	1	2.36E-05	0	0.	4	3.75E-06	0	0.
34	0	0.	0	0.	0	0.	2	1.07E-04	5	4.00E-05	0	0.
35	2	3.25E-04	1	5.45E-07	0	0.	0	0.	3	3.26E-04	0	0.
36	1	7.39E-04	1	2.96E-04	2	1.70E-03	5	5.77E-04	3	3.56E-05	0	0.
37	6	1.08E-03	1	3.67E-05	1	1.59E-05	2	3.26E-04	4	2.34E-04	0	0.
38	10	4.82E-03	2	3.97E-05	2	1.67E-07	9	4.33E-03	18	1.37E-03	3	1.46E-03
39	14	3.41E-03	13	2.11E-03	14	6.09E-03	16	8.30E-03	37	7.46E-04	8	8.61E-04
40	17	6.35E-03	14	9.80E-04	19	6.06E-03	27	1.01E-02	35	2.25E-03	12	4.78E-03
41	33	6.96E-03	18	6.11E-03	7	8.39E-05	33	4.40E-03	66	6.56E-03	5	3.41E-03
42	23	2.94E-03	24	8.15E-03	19	5.59E-03	30	8.97E-03	69	4.20E-03	8	2.06E-03
43	39	1.17E-02	39	2.27E-03	37	2.92E-03	50	6.69E-03	79	6.16E-03	7	7.99E-04
44	58	8.79E-03	50	6.90E-03	51	5.55E-03	66	9.44E-03	146	1.63E-02	9	8.10E-04
45	182	2.02E-02	134	3.78E-03	124	4.08E-03	210	9.70E-03	714	1.44E-02	25	1.55E-03
SUM	1698	7.24E+00	818	1.05E+00	755	3.97E-01	802	4.81E-01	2313	1.63E-01	1642	6.00E+00

ENERGY GROUP	REGION 13		REGION 14		REGION 15		REGION 16		REGION 17		REGION 18	
	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT
1	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
2	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
3	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
4	0	0.	1	5.70E-04	0	0.	0	0.	0	0.	0	0.

Output (cont.)

-126-

MOR-6

1	5	0	0.	0	0.	2	1.26E-03	0	0.	0	0.	0	0.
6	2	1.14E-03	2	1.34E-03	2	1.63E-03	0	0.	0	0.	1	2.61E-05	
7	4	2.56E-03	1	4.22E-04	2	5.53E-04	3	7.28E-04	3	5.89E-04	1	2.87E-04	
8	2	1.43E-03	3	7.45E-04	3	9.35E-04	2	1.06E-03	2	2.51E-04	0	0.	
9	13	1.13E-02	5	2.60E-03	7	3.14E-03	6	2.60E-03	4	9.56E-04	2	8.68E-04	
10	15	1.57E-02	8	3.24E-03	6	2.83E-03	7	2.11E-03	3	2.01E-03	2	6.49E-03	
11	15	9.37E-03	14	6.24E-03	6	4.37E-03	6	1.54E-03	2	4.88E-04	4	1.00E-03	
12	7	4.71E-03	8	5.00E-03	3	8.59E-04	14	6.10E-03	3	1.47E-03	4	1.71E-04	
13	6	5.07E-03	13	7.63E-03	13	7.55E-03	7	3.54E-03	3	1.00E-03	1	5.64E-05	
14	11	9.73E-03	11	8.90E-03	6	3.92E-03	8	1.77E-03	4	5.20E-04	1	1.14E-05	
15	11	9.06E-03	24	1.46E-02	13	8.99E-03	8	3.94E-03	5	9.03E-04	1	1.96E-05	
16	12	1.23E-02	8	1.05E-02	15	5.72E-03	14	5.56E-03	8	7.94E-03	2	9.32E-04	
17	21	1.80E-02	16	9.97E-03	14	6.29E-03	9	4.76E-03	12	5.32E-03	4	1.44E-03	
18	12	1.09E-02	14	8.27E-03	8	5.62E-03	10	2.58E-03	5	3.11E-03	2	2.42E-04	
19	16	1.33E-02	20	8.78E-03	12	8.15E-03	6	1.43E-03	5	2.86E-03	0	0.	
20	12	8.42E-03	11	7.59E-03	13	8.36E-03	12	4.07E-03	3	1.32E-03	1	2.98E-04	
21	11	7.78E-03	5	1.44E-03	2	1.10E-03	8	6.62E-03	2	4.29E-04	4	2.03E-03	
22	73	7.75E-02	38	2.67E-02	48	2.24E-02	34	1.22E-02	27	1.49E-02	10	4.11E-03	
23	88	8.51E-02	40	2.63E-02	28	1.24E-02	33	1.18E-02	32	1.32E-02	22	1.74E-02	
24	192	2.24E-01	151	1.24E-01	98	5.36E-02	82	3.96E-02	53	2.27E-02	49	2.52E-02	
25	163	2.08E-01	153	9.85E-02	129	7.32E-02	102	3.61E-02	46	1.74E-02	51	3.26E-02	
26	137	1.41E-01	174	1.67E-01	90	4.60E-02	79	2.53E-02	57	2.04E-02	51	3.38E-02	
27	138	1.28E-01	177	1.45E-01	105	5.60E-02	110	5.63E-02	51	1.94E-02	50	3.44E-02	
28	163	1.53E-01	208	2.10E-01	110	5.57E-02	65	2.95E-02	44	1.42E-02	66	3.11E-02	
29	311	3.03E-01	300	2.63E-01	250	1.45E-01	149	6.24E-02	83	2.92E-02	68	3.68E-02	
30	1180	5.25E+00	1378	1.20E+01	1298	6.12E+00	528	8.01E-01	557	2.53E+00	836	1.82E+00	
31	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	
32	0	0.	0	0.	0	0.	1	3.82E-05	0	0.	0	0.	
33	0	0.	3	3.84E-03	1	1.49E-03	0	0.	0	0.	1	2.36E-05	
34	0	0.	0	0.	1	7.53E-06	0	0.	1	5.17E-05	2	9.01E-05	
35	2	4.29E-04	3	9.44E-04	1	1.85E-05	2	6.95E-05	5	2.87E-04	1	2.87E-03	
36	2	4.28E-05	4	9.73E-04	3	8.55E-04	3	3.23E-04	4	8.02E-04	2	7.09E-05	
37	3	2.56E-04	3	2.04E-03	2	1.29E-05	2	2.62E-04	3	1.96E-05	4	8.46E-05	
38	4	1.21E-03	10	2.52E-03	15	9.79E-04	10	1.49E-04	12	6.79E-04	19	3.26E-03	
39	19	3.81E-03	12	1.86E-03	23	2.35E-03	24	2.55E-03	25	1.01E-03	25	4.45E-03	
40	11	9.00E-04	12	8.21E-03	25	8.11E-03	18	8.42E-03	34	1.02E-02	20	4.24E-04	
41	16	2.34E-03	30	7.65E-03	20	9.93E-04	27	2.50E-03	23	1.86E-03	28	4.69E-03	
42	16	1.32E-03	22	6.60E-03	28	2.79E-03	29	4.51E-03	40	1.01E-03	42	2.23E-03	
43	20	3.85E-03	36	3.70E-03	32	4.82E-03	37	5.96E-03	31	3.18E-03	42	1.55E-03	
44	22	7.38E-03	36	6.94E-03	56	1.77E-02	55	6.98E-03	69	3.83E-03	73	3.30E-03	
45	60	9.93E-03	107	7.47E-03	134	7.60E-03	174	5.61E-03	195	1.05E-02	242	5.26E-03	
SUM	2790	6.74E+00	3061	1.32E+01	2624	6.71E+00	1684	1.16E+00	1456	2.74E+00	1734	2.08E+00	

ENERGY GROUP	REGION 19 NUMBER WEIGHT	REGION 20 NUMBER WEIGHT	REGION 21 NUMBER WEIGHT	REGION 22 NUMBER WEIGHT	REGION 23 NUMBER WEIGHT	REGION 24 NUMBER WEIGHT
1	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
2	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
3	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
4	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
5	0 0.	2 1.39E-03	0 0.	0 0.	0 0.	0 0.
6	0 0.	1 5.05E-05	0 0.	0 0.	3 1.47E-04	0 0.
7	1 2.57E-05	0 0.	1 5.86E-06	2 1.14E-05	0 0.	0 0.
8	1 3.38E-04	0 0.	0 0.	0 0.	2 9.49E-05	0 0.
9	0 0.	1 1.27E-04	1 2.82E-04	1 2.80E-04	0 0.	1 4.29E-04
10	4 5.64E-03	1 3.86E-06	0 0.	0 0.	0 0.	1 3.53E-04
11	2 3.11E-04	2 1.31E-04	0 0.	0 0.	0 0.	1 6.46E-04
12	4 4.32E-04	2 9.16E-04	2 1.68E-05	1 3.82E-06	0 0.	3 2.00E-03
13	0 0.	0 0.	0 0.	0 0.	1 2.59E-08	0 0.
14	0 0.	1 3.44E-05	0 0.	0 0.	1 2.35E-07	1 3.92E-04
15	2 2.90E-04	0 0.	0 0.	1 4.81E-06	2 4.75E-05	1 7.40E-04

1 16	5	1.86E-04	0	0.	0	C.	2	4.90E-06	1	7.94E-07	1	6.05E-04
17	0	0.	2	1.65E-03	0	C.	1	4.81E-06	2	5.60E-06	0	0.
18	1	3.44E-04	0	0.	2	1.83E-04	0	0.	3	2.38E-06	0	0.
19	4	9.64E-04	1	5.64E-05	0	C.	0	0.	3	1.05E-06	0	0.
20	4	8.43E-04	1	8.24E-04	0	C.	0	0.	2	9.62E-06	2	1.65E-03
21	0	0.	2	1.08E-02	2	2.60E-05	1	3.81E-06	0	0.	3	1.79E-03
22	12	1.18E-03	1	1.08E-04	1	8.24E-04	0	0.	6	9.51E-05	6	5.19E-03
23	5	5.36E-04	2	3.37E-04	0	0.	3	4.20E-05	2	8.20E-07	3	3.17E-03
24	12	4.90E-04	8	1.05E-03	6	2.73E-03	5	7.75E-05	8	5.23E-06	4	1.46E-03
25	15	2.52E-03	6	4.04E-04	8	3.05E-03	6	3.17E-04	4	2.62E-06	4	2.66E-03
26	14	1.42E-03	7	2.27E-04	3	8.50E-04	10	2.11E-04	11	4.21E-04	1	2.53E-04
27	23	2.01E-03	5	2.89E-04	3	1.07E-03	3	9.79E-05	10	3.20E-05	10	8.54E-03
28	18	6.37E-04	4	1.89E-04	11	6.23E-03	5	1.01E-04	3	5.43E-05	8	6.83E-03
29	45	6.17E-03	25	2.27E-03	10	4.31E-03	8	5.20E-04	16	2.09E-03	14	6.65E-03
30	276	5.53E-01	25	4.09E-03	114	5.36E-02	202	3.64E-02	183	9.92E-03	8	5.27E-03
31	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
32	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
33	0	0.	1	6.82E-05	0	C.	0	0.	0	0.	0	0.
34	0	0.	0	0.	1	3.10E-03	0	0.	2	1.39E-03	0	0.
35	0	0.	0	0.	1	1.36E-04	2	3.03E-03	7	8.42E-04	0	0.
36	5	1.46E-04	2	2.36E-05	0	C.	0	0.	4	8.38E-04	0	0.
37	5	8.04E-04	0	0.	1	1.47E-08	4	4.19E-06	6	2.88E-04	0	0.
38	16	5.90E-03	7	1.04E-04	4	3.46E-05	5	2.34E-03	12	7.05E-04	0	0.
39	18	2.97E-04	16	9.56E-04	13	1.62E-04	10	1.68E-04	16	6.85E-03	0	0.
40	26	1.98E-03	18	8.21E-04	13	3.62E-04	14	2.46E-04	31	5.39E-03	0	0.
41	29	2.54E-03	21	5.64E-03	20	2.12E-03	12	1.71E-03	37	3.90E-03	0	0.
42	38	5.81E-03	20	2.21E-03	18	2.80E-03	16	1.39E-03	53	5.84E-03	1	1.63E-08
43	33	2.70E-03	26	9.71E-04	23	1.35E-03	26	3.06E-03	89	9.06E-03	0	0.
44	54	2.87E-03	51	1.27E-03	46	5.90E-04	51	1.53E-03	157	4.88E-03	0	0.
45	186	2.84E-03	148	3.19E-03	203	3.97E-03	153	1.91E-03	781	8.43E-03	3	1.67E-05
SUM	858	6.04E-01	409	3.82E-02	507	8.78E-02	544	5.35E-02	1458	6.13E-02	76	4.87E-02

ENERGY GROUP	REGION 25 NUMBER WEIGHT	REGION 26 NUMBER WEIGHT	REGION 27 NUMBER WEIGHT
1	0 0.	0 0.	0 C.
2	0 0.	0 0.	0 C.
3	0 0.	0 0.	0 C.
4	0 0.	0 0.	0 C.
5	0 0.	0 0.	0 C.
6	0 0.	0 0.	0 C.
7	0 0.	0 0.	0 C.
8	1 3.87E-04	0 0.	0 C.
9	0 0.	0 0.	0 C.
10	2 6.70E-04	0 0.	1 3.32E-04
11	2 1.65E-03	0 0.	0 C.
12	1 2.53E-04	2 2.68E-03	0 C.
13	1 8.03E-04	1 4.90E-04	0 C.
14	0 0.	1 5.06E-04	0 C.
15	2 1.04E-03	0 0.	0 C.
16	1 3.90E-04	0 0.	1 4.25E-04
17	1 2.28E-04	2 1.45E-03	0 C.
18	1 8.65E-04	0 0.	0 C.
19	0 0.	1 2.28E-04	1 3.62E-05
20	0 0.	0 0.	0 C.
21	1 3.90E-04	0 0.	0 C.
22	4 1.86E-03	5 3.97E-03	1 3.62E-05
23	3 1.30E-03	2 4.79E-03	1 3.62E-05
24	5 2.41E-03	3 1.22E-03	1 2.40E-03
25	8 3.97E-03	10 5.86E-03	0 C.
26	4 1.33E-03	1 6.80E-04	2 7.14E-04

Output (cont.)

-128-

MOR-6

1 27	7	7.01E-03	13	8.19E-03	0	C.
28	7	2.70E-02	2	1.72E-03	1	8.78E-04
29	10	1.61E-02	7	1.82E-02	0	C.
30	22	5.99E-02	22	4.71E-02	7	2.66E-03
31	0	0.	0	0.	0	C.
32	0	0.	0	0.	0	C.
33	0	0.	0	0.	0	C.
34	0	0.	1	6.37E-06	0	C.
35	1	1.11E-03	0	0.	0	0.
36	0	0.	0	0.	0	0.
37	0	0.	0	0.	0	C.
38	1	1.37E-05	0	0.	1	2.72E-06
39	0	0.	3	2.56E-05	0	C.
40	0	0.	0	0.	0	C.
41	0	0.	1	1.75E-08	0	C.
42	3	4.84E-07	0	0.	0	0.
43	0	0.	4	2.72E-04	1	1.21E-07
44	3	1.47E-05	5	2.62E-04	1	3.57E-05
45	11	1.37E-03	10	4.95E-05	8	3.39E-04
SUM	102	1.30E-01	96	9.80E-02	27	7.89E-03

Output (cont.)

NUMBER OF RUSSIAN ROULETTE KILLS

ENERGY GROUP	REGION 1		REGION 2		REGION 3		REGION 4		REGION 5		REGION 6	
	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT
1	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
2	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
3	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
4	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
5	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
6	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
7	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
8	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
9	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
10	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
11	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
12	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
13	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
14	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
15	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
16	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
17	0	0.	0	C.	0	C.	0	0.	0	0.	0	0.
18	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
19	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
20	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
21	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
22	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
23	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
24	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
25	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
26	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
27	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
28	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
29	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
30	0	0.	2	1.32E-02	118	3.63E-01	148	6.01E-01	56	2.69E-01	42	1.36E-01
31	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
32	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.

-129-

MOR-6

1 33	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
34	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
35	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
36	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
37	0	0.	0	0.	1	3.72E-08	0	0.	0	0.	0	0.
38	0	0.	1	8.22E-08	1	4.27E-07	1	8.37E-08	1	5.60E-08	1	1.56E-08
39	0	0.	1	2.67E-08	0	0.	1	6.28E-07	0	0.	2	3.62E-07
40	0	0.	2	9.78E-06	1	1.09E-07	0	0.	2	1.45E-07	1	2.89E-07
41	0	0.	2	7.41E-06	1	4.14E-08	1	1.67E-07	2	2.38E-07	0	0.
42	0	0.	2	2.01E-06	0	0.	1	5.89E-08	2	2.77E-07	1	4.14E-08
43	0	0.	2	1.12E-07	1	2.34E-08	2	7.07E-08	2	4.69E-07	3	1.55E-08
44	0	0.	5	6.14E-06	2	7.01E-08	1	1.20E-08	3	4.73E-07	0	0.
45	0	0.	134	3.69E-04	23	4.73E-05	45	1.36E-04	53	8.31E-05	39	4.70E-05
SUM	0	0.	151	1.36E-02	148	3.63E-01	200	6.01E-01	121	2.69E-01	89	1.36E-01

ENERGY GROUP	REGION 7		REGION 8		REGION 9		REGION 10		REGION 11		REGION 12	
	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT
1	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
2	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
3	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
4	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
5	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
6	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
7	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
8	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
9	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
10	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
11	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
12	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
13	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
14	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
15	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
16	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
17	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
18	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
19	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
20	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
21	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
22	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
23	0	0.	0	0.	0	0.	0	0.	1	1.30E-07	0	0.
24	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
25	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
26	0	0.	0	0.	0	0.	0	0.	0	0.	1	4.02E-04
27	1	8.18E-04	0	0.	0	0.	0	0.	0	0.	0	0.
28	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
29	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
30	25	7.95E-02	9	8.79E-03	11	9.53E-03	5	8.15E-03	3	3.37E-03	32	6.25E-02
31	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
32	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
33	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
34	0	0.	0	0.	0	0.	0	0.	2	7.25E-08	0	0.
35	0	0.	0	0.	0	0.	0	0.	1	8.24E-09	0	0.
36	0	0.	0	0.	1	8.76E-04	0	0.	0	0.	0	0.
37	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
38	1	1.77E-07	0	0.	0	0.	0	0.	5	8.58E-08	1	4.95E-07
39	1	1.31E-06	1	6.28E-07	1	1.59E-08	0	0.	2	8.12E-08	1	1.05E-07
40	1	7.55E-08	1	3.38E-09	1	4.74E-09	3	1.27E-06	2	3.11E-10	0	0.
41	0	0.	1	1.97E-08	1	2.48E-11	2	2.53E-08	6	9.16E-08	0	0.
42	1	3.22E-07	1	1.55E-09	2	7.00E-09	2	5.61E-08	5	9.54E-07	1	3.97E-08
43	2	1.15E-08	1	2.28E-07	1	1.17E-08	4	1.37E-07	5	8.22E-08	1	6.17E-08

Output (cont.)

-130-

MOR-6

1 44	0	0.	3	3.78E-08	3	1.60E-08	3	3.82E-08	8	3.32E-08	1	1.49E-07
45	43	1.08E-04	31	1.22E-05	31	2.10E-05	65	2.17E-05	183	3.30E-05	12	1.52E-05
SUM	75	8.04E-02	48	8.80E-03	52	1.04E-02	84	8.17E-03	223	3.41E-03	50	6.29E-02

ENERGY GROUP	REGION 13 NUMBER WEIGHT	REGION 14 NUMBER WEIGHT	REGION 15 NUMBER WEIGHT	REGION 16 NUMBER WEIGHT	REGION 17 NUMBER WEIGHT	REGION 18 NUMBER WEIGHT
1	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
2	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
3	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
4	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
5	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
6	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
7	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
8	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
9	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
10	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
11	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
12	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
13	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
14	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
15	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
16	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
17	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
18	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
19	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
20	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
21	0 0.	0 0.	1 2.21E-04	0 0.	0 0.	0 0.
22	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
23	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
24	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
25	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
26	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
27	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
28	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
29	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
30	78 1.98E-01	75 1.23E-01	49 2.21E-01	34 2.51E-02	23 6.58E-02	27 2.86E-02
31	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
32	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
33	0 0.	1 1.15E-05	0 0.	0 0.	0 0.	0 0.
34	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
35	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
36	0 0.	1 1.85E-07	0 0.	1 7.77E-09	1 6.40E-07	0 0.
37	0 0.	0 0.	0 0.	1 1.71E-08	0 0.	1 3.45E-08
38	1 1.39E-07	1 2.48E-07	2 1.82E-07	2 7.25E-09	2 1.98E-08	1 7.06E-09
39	2 1.58E-07	1 5.14E-08	1 1.23E-07	0 0.	0 0.	1 6.66E-08
40	0 0.	0 0.	0 0.	0 0.	2 6.38E-09	1 7.03E-08
41	1 9.91E-09	1 5.17E-09	1 3.00E-09	1 8.25E-09	2 2.00E-08	0 0.
42	0 0.	1 3.75E-08	1 2.43E-07	1 4.48E-08	1 4.22E-08	2 1.57E-07
43	1 5.60E-09	0 0.	2 2.56E-08	0 0.	3 2.15E-07	2 2.20E-07
44	1 3.78E-08	1 1.37E-08	4 2.62E-07	3 2.91E-07	2 2.21E-08	3 2.62E-08
45	12 1.41E-05	25 4.60E-05	35 1.11E-04	39 3.45E-05	44 2.78E-05	71 2.28E-05
SUM	96 1.98E-01	107 1.23E-01	96 2.21E-01	82 2.51E-02	80 6.58E-02	109 2.87E-02

ENERGY GROUP	REGION 19 NUMBER WEIGHT	REGION 20 NUMBER WEIGHT	REGION 21 NUMBER WEIGHT	REGION 22 NUMBER WEIGHT	REGION 23 NUMBER WEIGHT	REGION 24 NUMBER WEIGHT
1	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
2	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
3	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
4	0 0.	0 0.	0 0.	0 0.	0 0.	0 0.
5	0 0.	1 6.84E-04	0 0.	0 0.	0 0.	0 0.

Output (cont.)

-131-

MOR-6

1	6	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	7	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	8	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	9	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	10	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	11	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	12	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	13	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	14	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	15	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	16	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	17	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	18	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	19	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	20	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	21	0	0.	1	5.38E-03	0	0.	0	0.	0	0.	0	0.	0	0.
	22	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	23	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	24	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	25	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	26	0	0.	0	0.	0	0.	0	0.	1	2.35E-07	0	0.	0	0.
	27	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	28	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	29	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	30	10	2.04E-02	3	8.45E-05	2	7.56E-04	2	1.72E-04	6	8.92E-04	1	4.37E-04	0	0.
	31	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	32	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	33	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	34	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
	35	0	0.	0	0.	0	0.	0	0.	2	7.80E-08	0	0.	0	0.
	36	0	0.	1	1.99E-08	0	0.	0	0.	0	0.	0	0.	0	0.
	37	0	0.	0	0.	0	0.	1	7.23E-10	0	0.	0	0.	0	0.
	38	0	0.	1	1.10E-08	0	0.	0	0.	1	1.59E-10	0	0.	0	0.
	39	1	2.24E-07	1	1.09E-08	0	0.	2	3.37E-09	2	5.59E-09	0	0.	0	0.
	40	1	2.18E-09	1	5.32E-08	4	3.87E-07	1	1.34E-07	4	1.05E-05	0	0.	0	0.
	41	1	5.72E-08	1	9.80E-07	0	0.	2	2.27E-08	2	3.25E-07	0	0.	0	0.
	42	2	7.57E-07	2	5.39E-07	2	3.68E-09	1	2.62E-10	1	3.50E-10	0	0.	0	0.
	43	1	8.75E-07	1	3.00E-09	1	4.81E-08	0	0.	5	1.11E-08	0	0.	0	0.
	44	2	3.97E-08	0	0.	1	2.53E-09	2	6.23E-09	8	1.43E-08	0	0.	0	0.
	45	44	1.86E-05	41	1.87E-05	53	1.14E-05	39	7.22E-06	211	1.72E-05	0	0.	0	0.
	SUM	62	2.04E-02	54	6.17E-03	63	7.68E-04	50	1.80E-04	243	9.21E-04	1	4.37E-04	0	0.

ENERGY GROUP	REGION 25 NUMBER WEIGHT	REGION 26 NUMBER WEIGHT	REGION 27 NUMBER WEIGHT
1	0 0.	0 0.	0 0.
2	0 0.	0 0.	0 0.
3	0 0.	0 0.	0 0.
4	0 0.	0 0.	0 0.
5	0 0.	0 0.	0 0.
6	0 0.	0 0.	0 0.
7	0 0.	0 0.	0 0.
8	0 0.	0 0.	0 0.
9	0 0.	0 0.	0 0.
10	0 0.	0 0.	0 0.
11	0 0.	0 0.	0 0.
12	0 0.	0 0.	0 0.
13	0 0.	0 0.	0 0.
14	0 0.	0 0.	0 0.
15	0 0.	0 0.	0 0.
16	0 0.	0 0.	0 0.

Output (cont.)

-132-

MOR-6

1 17	0	0.	0	0.	0	0.
18	0	0.	0	0.	0	0.
19	0	0.	0	0.	0	0.
20	0	0.	0	0.	0	0.
21	0	0.	0	0.	0	0.
22	0	0.	0	0.	0	0.
23	0	0.	0	0.	0	0.
24	0	0.	0	0.	0	0.
25	0	0.	0	0.	0	0.
26	0	0.	0	0.	0	0.
27	0	0.	0	0.	0	0.
28	0	0.	0	0.	0	0.
29	0	0.	0	0.	0	0.
30	3	3.44E-03	0	0.	0	0.
31	0	0.	0	0.	0	0.
32	0	0.	0	0.	0	0.
33	0	0.	0	0.	0	0.
34	0	0.	0	0.	0	0.
35	0	0.	0	0.	0	0.
36	0	0.	0	0.	0	0.
37	0	0.	0	0.	0	0.
38	0	0.	0	0.	0	0.
39	0	0.	0	0.	0	0.
40	0	0.	0	0.	0	0.
41	0	0.	0	0.	0	0.
42	0	0.	0	0.	0	0.
43	0	0.	0	0.	0	0.
44	0	0.	0	0.	0	0.
45	3	5.71E-06	1	9.02E-08	0	0.
SUM	6	3.45E-03	1	9.02E-08	0	0.

Output (cont.)

-133-

NUMBER OF RUSSIAN ROULETTE SURVIVALS

ENERGY GROUP	REGION 1		REGION 2		REGION 3		REGION 4		REGION 5		REGION 6	
	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT
1	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
2	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
3	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
4	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
5	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
6	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
7	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
8	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
9	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
10	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
11	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
12	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
13	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
14	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
15	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
16	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
17	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
18	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
19	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
20	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
21	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
22	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.

MOR-6

1 23	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
24	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
25	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
26	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
27	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
28	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
29	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
30	0	0.	0	0.	130	3.89E-01	161	5.08E-01	76	3.12E-01	36	7.69E-02
31	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
32	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
33	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
34	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
35	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
36	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
37	0	0.	1	5.65E-06	0	C.	0	0.	0	0.	0	0.
38	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
39	0	0.	0	0.	1	2.50E-07	0	0.	1	1.98E-08	0	0.
40	0	0.	0	0.	0	C.	1	8.30E-07	0	0.	0	0.
41	0	0.	0	0.	0	C.	0	0.	0	0.	1	2.68E-07
42	0	0.	0	0.	1	1.60E-06	1	2.90E-08	0	0.	0	0.
43	0	0.	2	8.66E-06	0	C.	1	7.70E-08	0	0.	1	3.65E-08
44	0	0.	1	4.12E-08	0	C.	0	0.	0	0.	3	1.20E-06
45	0	0.	151	5.14E-04	22	1.26E-04	30	5.78E-05	41	5.64E-05	47	4.98E-05
SUM	0	0.	155	5.28E-04	154	3.89E-01	194	5.08E-01	118	3.12E-01	88	7.69E-02

ENERGY GROUP	REGION 7		REGION 8		REGION 9		REGION 10		REGION 11		REGION 12	
	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT
1	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
2	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
3	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
4	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
5	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
6	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
7	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
8	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
9	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
10	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
11	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
12	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
13	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
14	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
15	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
16	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
17	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
18	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
19	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
20	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
21	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
22	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
23	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
24	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
25	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
26	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
27	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
28	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
29	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
30	32	1.22E-01	11	9.38E-03	6	1.85E-03	6	5.12E-03	2	1.40E-03	43	1.09E-01
31	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
32	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.
33	0	0.	0	0.	0	C.	0	0.	0	0.	0	0.

Output (cont.)

-134-

MOR-6

1 34	0	0.	0	0.	0	0.	0	0.	1	7.36E-09	0	0.
35	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
36	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
37	0	0.	0	0.	0	0.	0	0.	1	5.90E-09	0	0.
38	0	0.	0	0.	0	0.	1	1.42E-08	2	6.24E-09	0	0.
39	1	6.28E-07	0	0.	0	0.	1	3.40E-06	2	2.90E-09	0	0.
40	0	0.	0	0.	0	0.	1	4.08E-08	3	2.89E-08	1	9.76E-08
41	1	3.58E-07	0	0.	0	0.	0	0.	4	1.50E-09	0	0.
42	1	1.27E-03	0	0.	0	0.	0	0.	3	9.99E-10	0	0.
43	1	1.31E-03	0	0.	0	0.	1	1.62E-08	2	3.35E-10	0	0.
44	3	4.15E-08	1	1.44E-08	0	0.	1	2.07E-08	7	1.37E-08	0	0.
45	57	3.62E-04	36	1.33E-05	27	1.31E-05	47	2.36E-05	187	3.27E-05	4	3.14E-06
SUM	96	1.23E-01	48	9.40E-03	33	1.86E-03	58	5.15E-03	214	1.44E-03	48	1.09E-01

ENERGY GROUP	REGION 13		REGION 14		REGION 15		REGION 16		REGION 17		REGION 18	
	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT
1	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
2	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
3	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
4	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
5	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
6	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
7	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
8	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
9	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
10	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
11	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
12	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
13	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
14	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
15	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
16	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
17	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
18	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
19	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
20	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
21	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
22	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
23	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
24	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
25	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
26	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
27	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
28	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
29	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
30	63	1.43E-01	70	8.52E-02	61	2.26E-01	43	2.78E-02	38	6.79E-02	43	4.22E-02
31	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
32	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
33	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
34	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
35	0	0.	1	1.65E-07	0	0.	0	0.	0	0.	0	0.
36	1	1.11E-07	0	0.	0	0.	0	0.	0	0.	0	0.
37	1	3.45E-08	0	0.	0	0.	0	0.	0	0.	0	0.
38	0	0.	0	0.	0	0.	0	0.	0	0.	1	7.22E-09
39	1	2.81E-08	0	0.	0	0.	1	4.70E-07	1	2.95E-07	0	0.
40	1	1.62E-07	0	0.	1	1.10E-07	1	1.17E-08	1	1.83E-09	1	1.86E-08
41	0	0.	1	3.13E-08	0	0.	0	0.	0	0.	1	2.95E-07
42	1	5.60E-09	1	1.17E-08	1	3.51E-09	0	0.	0	0.	0	0.
43	0	0.	1	1.17E-08	0	0.	1	3.79E-08	0	0.	0	0.
44	0	0.	1	6.79E-08	0	0.	0	0.	1	8.77E-10	1	1.28E-08

Output (cont.)

-135-

MOR-6

1 45	18	2.99E-05	22	1.63E-05	36	6.53E-05	35	4.91E-05	43	1.95E-05	47	1.89E-05
SUM	86	1.43E-01	97	8.52E-02	99	2.26E-01	81	2.79E-02	84	6.79E-02	94	4.22E-02

ENERGY GROUP	REGION 19		REGION 20		REGION 21		REGION 22		REGION 23		REGION 24	
	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT
1	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
2	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
3	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
4	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
5	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
6	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
7	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
8	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
9	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
10	1	1.82E-05	0	0.	0	0.	0	0.	0	0.	0	0.
11	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
12	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
13	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
14	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
15	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
16	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
17	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
18	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
19	1	1.79E-06	0	0.	0	0.	0	0.	0	0.	0	0.
20	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
21	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
22	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
23	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
24	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
25	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
26	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
27	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
28	0	0.	0	0.	0	0.	0	0.	1	7.93E-07	0	0.
29	0	0.	0	0.	0	0.	3	1.21E-04	3	4.07E-04	2	8.17E-04
30	9	6.05E-03	0	0.	3	5.69E-04	0	0.	0	0.	0	0.
31	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
32	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
33	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
34	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
35	0	0.	0	0.	0	0.	0	0.	0	0.	0	0.
36	0	0.	0	0.	0	0.	0	0.	1	4.71E-07	0	0.
37	1	2.26E-07	0	0.	0	0.	0	0.	0	0.	0	0.
38	2	1.24E-07	0	0.	1	8.43E-10	2	4.99E-07	0	0.	0	0.
39	0	0.	0	0.	3	1.96E-07	0	0.	2	1.20E-10	0	0.
40	1	5.37E-07	0	0.	1	1.30E-07	0	0.	1	1.59E-10	0	0.
41	0	0.	1	1.59E-10	0	0.	1	1.59E-10	3	4.53E-08	0	0.
42	2	2.38E-07	0	0.	0	0.	2	2.99E-08	2	3.83E-10	0	0.
43	0	0.	0	0.	0	0.	0	0.	3	1.00E-08	0	0.
44	0	0.	2	4.06E-09	1	4.87E-12	0	0.	190	1.60E-05	0	0.
45	44	2.35E-05	40	1.41E-05	52	1.52E-05	34	1.02E-05	206	4.24E-04	2	8.17E-04
SUM	61	6.09E-03	43	1.41E-05	61	5.85E-04	42	1.32E-04				

ENERGY GROUP	REGION 25		REGION 26		REGION 27	
	NUMBER	WEIGHT	NUMBER	WEIGHT	NUMBER	WEIGHT
1	0	0.	0	0.	0	0.
2	0	0.	0	0.	0	0.
3	0	0.	0	0.	0	0.
4	0	0.	0	0.	0	0.
5	0	0.	0	0.	0	0.
6	0	0.	0	0.	0	0.

Output (cont.)

-136-

MOR-6

1	7	0	0.	0	0.	0	0.
	8	0	0.	0	0.	0	0.
	9	0	0.	0	0.	0	0.
	10	0	0.	0	0.	0	0.
	11	0	0.	0	0.	0	0.
	12	0	0.	0	0.	0	0.
	13	0	0.	0	0.	0	0.
	14	0	0.	0	0.	0	0.
	15	0	0.	0	0.	0	0.
	16	0	0.	0	0.	0	0.
	17	0	0.	0	0.	0	0.
	18	0	0.	0	0.	0	0.
	19	0	0.	0	0.	0	0.
	20	0	0.	0	0.	0	0.
	21	0	0.	0	0.	0	0.
	22	0	0.	0	0.	0	0.
	23	0	0.	0	0.	0	0.
	24	0	0.	0	0.	0	0.
	25	0	0.	0	0.	0	0.
	26	0	0.	0	0.	0	0.
	27	0	0.	0	0.	0	0.
	28	0	0.	0	0.	0	0.
	29	0	0.	0	0.	0	0.
	30	1	6.70E-04	0	0.	0	0.
	31	0	0.	0	0.	0	0.
	32	0	0.	0	0.	0	0.
	33	0	0.	0	0.	0	0.
	34	0	0.	0	0.	0	0.
	35	0	0.	0	0.	0	0.
	36	0	0.	0	0.	0	0.
	37	0	0.	0	0.	0	0.
	38	0	0.	0	0.	0	0.
	39	0	0.	0	0.	0	0.
	40	0	0.	0	0.	0	0.
	41	0	0.	0	0.	0	0.
	42	0	0.	0	0.	0	0.
	43	0	0.	1	6.26E-08	0	0.
	44	0	0.	0	0.	0	0.
	45	1	1.32E-06	3	5.75E-06	2	1.17E-07
SUM		2	6.72E-04	4	5.81E-06	2	1.17E-07

Output (cont.)

-137-

MOR-6

¹ DETECTOR RESPONSES

EXAMPLE PROBLEM FOR MORSE-L REPORT

DETECTOR NUMBER	RESPONSE NUMBER	UNCOLLIDED RESPONSE	FSD	TOTAL RESPONSE	FSD
1	1	1.9466E+02	0.0722	1.0705E+03	0.3912
1	2	0.	0.	5.3588E+02	0.2287
1	3	0.	0.	1.3915E+03	0.2349
2	1	1.4633E+00	0.1618	2.2097E+01	0.2687
2	2	0.	0.	2.9453E+02	0.2516
2	3	0.	0.	7.0566E+02	0.2429

Output (cont.)

-138-

MOR-6

1
STATISTICAL SUMMARY OF DETECTOR RESPONSE RESULTS

DETECTOR RESPONSE	1 1	1 2	1 3	2 1	2 2	2 3
BATCH						
1	3.41E+02	9.27E+01	3.75E+02	7.00E+00	2.64E+01	1.46E+02
2	8.29E+02	6.41E+02	1.66E+03	1.85E+01	3.45E+02	8.84E+02
3	7.08E+02	2.21E+02	4.64E+02	9.99E+00	9.99E+01	2.20E+02
4	1.08E+03	1.59E+03	4.19E+03	3.11E+01	1.14E+03	2.56E+03
5	4.23E+02	8.58E+02	2.12E+03	1.12E+01	6.49E+02	1.05E+03
6	6.35E+02	9.65E+02	2.13E+03	1.44E+01	3.76E+02	1.10E+03
7	7.67E+03	4.35E+02	1.48E+03	1.08E+02	2.54E+02	8.33E+02
8	5.96E+02	1.78E+03	4.95E+03	2.61E+01	7.37E+02	2.14E+03
9	5.48E+02	2.62E+02	4.76E+02	1.12E+01	6.76E+01	1.72E+02
10	5.57E+02	2.85E+02	7.95E+02	1.86E+01	1.40E+02	3.46E+02
11	6.13E+02	9.53E+01	3.78E+02	1.62E+01	1.35E+01	3.19E+01
12	3.52E+02	7.01E+01	1.69E+02	8.52E+00	2.26E+01	8.59E+01
13	5.82E+02	4.29E+02	8.33E+02	1.85E+01	2.40E+02	4.52E+02
14	5.31E+02	1.37E+02	3.96E+02	4.57E+01	1.04E+02	2.80E+02
15	6.32E+02	4.84E+02	1.25E+03	6.06E+00	4.60E+02	7.23E+02
16	1.60E+03	2.34E+02	7.25E+02	1.86E+01	1.39E+02	3.56E+02
17	4.96E+02	5.28E+02	1.26E+03	5.41E+00	1.90E+02	6.21E+02
AVERAGE	1.07E+03	5.36E+02	1.39E+03	2.21E+01	2.95E+02	7.06E+02
SD-RESULT	4.19E+02	1.23E+02	3.27E+02	5.94E+00	7.41E+01	1.71E+02
SD-DIST	1.73E+03	5.05E+02	1.35E+03	2.45E+01	3.06E+02	7.07E+02
W-TEST	0.	0.	0.	0.	0.	0.

Output (cont.)

-139-

MOR-6

1

ENERGY DEPENDENT FLUENCE (PARTICLES/CM**2-MEV)

DETECTOR NO. ENERGIES	1	2
1.800E+01	0.	0.
1.175E+01	0.	0.
7.660E+00	9.424E+00 0.237	3.530E-01 0.250
5.770E+00	4.116E+01 0.144	1.054E+00 0.247
4.210E+00	9.183E+01 0.114	1.831E+00 0.185
2.970E+00	1.486E+02 0.344	2.370E+00 0.216
1.990E+00	1.020E+02 0.300	3.169E+00 0.264
1.260E+00	8.514E+01 0.092	3.029E+00 0.206
8.420E-01	6.347E+01 0.205	1.725E+00 0.242
5.900E-01	4.724E+01 0.176	1.379E+00 0.251
1.261E-02	6.644E+02 0.842	8.185E+00 0.913
2.000E-04	1.064E+03 0.585	7.449E+01 0.927
1.000E-10 ENERGIES	1.464E+05 0.379	4.150E+03 0.893
1.000E+01	2.913E+00 0.368	1.993E+00 0.381
8.190E+00	1.508E+01 0.271	8.423E+00 0.268
6.707E+00	3.969E+01 0.271	2.064E+01 0.269
5.493E+00	1.296E+01 0.299	5.738E+00 0.292
4.498E+00	2.403E+01 0.429	6.874E+00 0.433
3.684E+00		

Output (cont.)

-140-

MOR-6

1
ENERGY DEPENDENT FLUENCE (PARTICLES/CM**2-MEV)

DETECTOR NO. ENERGIES	1	2
3.684E+00	1.825E+01 0.372	7.022E+00 0.408
3.017E+00	4.210E+01 0.343	1.326E+01 0.368
2.471E+00	3.790E+02 0.250	2.169E+02 0.282
2.024E+00	9.671E+01 0.413	3.998E+01 0.378
1.657E+00	1.333E+02 0.370	1.293E+01 0.431
1.357E+00	1.026E+02 0.350	5.145E+01 0.447
1.112E+00	1.831E+02 0.402	1.107E+02 0.816
9.103E-01	1.950E+02 0.390	4.976E+01 0.292
7.455E-01	1.854E+02 0.327	2.470E+02 0.699
6.105E-01	2.559E+02 0.311	3.450E+02 0.454
5.000E-01		

Output (cont.)

-141-

MOR-6

1
TIME DEPENDENT RESPONSE (RESPONSE/SEC)

DETECTOR NUMBER 1 RESPONSE TIMES	1	2	3
1.243E-09	0.	4.812E+10	1.115E+11
	0.	0.551	0.572
1.500E-09	0.	5.901E+10	8.980E+10
	0.	0.478	0.411
2.000E-09	0.	1.272E+10	2.180E+10
	0.	0.456	0.467
5.000E-09	7.522E+09	1.306E+09	4.381E+09
	0.236	0.437	0.479
1.000E-08	2.962E+10	2.521E+07	1.145E+08
	0.176	0.324	0.502
3.000E-08	1.088E+10	3.063E+06	7.420E+06
	0.875	0.235	0.210
5.000E-08	6.758E+09	3.192E+06	9.252E+06
	0.979	0.309	0.326
7.000E-08	5.406E+07	3.489E+06	5.910E+06
	0.244	0.569	0.464
1.000E-07	2.486E+08	2.465E+06	6.129E+06
	0.922	0.327	0.230
3.000E-07	8.660E+06	3.852E+06	1.254E+07
	0.741	0.226	0.316
7.000E-07	3.752E+05	3.609E+06	9.833E+06
	0.589	0.284	0.262
1.000E-06	3.149E+06	4.183E+06	1.232E+07
	0.418	0.245	0.312
1.000E-05	4.911E+04	2.597E+06	7.140E+06
	0.513	0.226	0.214
1.000E-04	1.148E+02	1.935E+05	5.168E+05
	0.626	0.392	0.381
1.000E-03	6.137E-90	0.	0.
	1.000	0.	0.
1.000E-02			

Output (cont.)

-142-

MOR-6

1
 TIME DEPENDENT RESPONSE (RESPONSE/SEC)

DETECTOR NUMBER 2 RESPONSE TIMES	1	2	3
1.440E-09	0.	1.118E+10	2.196E+10
	0.	0.703	0.774
1.500E-09	0.	5.639E+10	5.281E+10
	0.	0.824	0.615
2.000E-09	0.	3.037E+09	8.092E+09
	0.	0.407	0.447
5.000E-09	8.324E+07	4.027E+08	1.411E+09
	0.564	0.342	0.458
1.000E-08	6.866E+08	3.885E+07	2.210E+08
	0.173	0.636	0.693
3.000E-08	9.968E+07	1.425E+06	3.491E+06
	0.327	0.255	0.219
5.000E-08	1.622E+07	1.453E+06	4.208E+06
	0.420	0.292	0.300
7.000E-08	2.703E+06	9.664E+05	2.093E+06
	0.803	0.398	0.383
1.000E-07	2.310E+07	1.325E+06	3.370E+06
	0.984	0.239	0.189
3.000E-07	1.699E+04	1.883E+06	6.127E+06
	0.630	0.226	0.308
7.000E-07	3.154E+05	2.524E+06	7.207E+06
	0.939	0.473	0.423
1.000E-06	8.564E+04	2.031E+06	5.806E+06
	0.940	0.238	0.292
1.000E-05	3.094E+02	1.254E+06	3.329E+06
	0.688	0.243	0.205
1.000E-04	3.108E+01	1.342E+05	3.165E+05
	0.997	0.446	0.406
1.000E-03	3.632E-86	0.	0.
	1.000	0.	0.
1.000E-02			

Output (cont.)

-143-

MOR-6

1
TIME AND ENERGY DEPENDENT FLUENCE (PARTICLES/CM**2-SEC-MEV)

DETECTOR NUMBER 1

ENERGIES TIMES	1.800E+01	1.175E+01	7.660E+00	5.770E+00	4.210E+00	2.970E+00	1.990E+00	1.260E+00	8.420E-01	5.900E-01
	1.175E+01	7.660E+00	5.770E+00	4.210E+00	2.970E+00	1.990E+00	1.260E+00	8.420E-01	5.900E-01	1.261E-02
1.243E-09	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
1.500E-09	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
2.000E-09	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
5.000E-09	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
1.000E-08	0.	1.838E+09	1.754E+06	0.	0.	0.	0.	0.	0.	0.
3.000E-08	0.	0.236	1.000	0.	0.	0.	0.	0.	0.	0.
5.000E-08	0.	1.162E+07	2.058E+09	4.591E+09	7.428E+09	5.066E+09	4.221E+09	2.634E+09	4.614E+08	7.393E+07
7.000E-08	0.	0.470	0.144	0.114	0.344	0.303	0.093	0.170	0.215	0.453
1.000E-07	0.	1.784E+00	2.991E+02	7.046E+03	1.782E+05	3.648E+07	3.627E+07	5.396E+08	1.901E+09	1.752E+10
3.000E-07	0.	1.000	0.985	0.503	0.416	0.908	0.591	0.486	0.215	0.941
5.000E-07	0.	0.	0.	1.145E-01	6.962E-02	1.188E+02	2.818E+02	9.265E+02	7.046E+04	1.170E+10
7.000E-07	0.	0.	0.	1.000	0.643	0.924	0.811	0.522	0.638	0.979
1.000E-06	0.	0.	0.	0.	0.	0.	6.019E-05	5.440E-03	7.695E-01	7.670E+07
3.000E-06	0.	0.	0.	0.	0.	0.	0.771	0.620	0.705	0.226
5.000E-06	0.	0.	0.	0.	0.	0.	9.780E-12	2.014E-15	9.459E-15	3.808E+08
7.000E-06	0.	0.	0.	0.	0.	0.	1.000	1.000	1.000	0.923
1.000E-05	0.	0.	0.	0.	0.	0.	0.	0.	0.	8.552E-23
3.000E-05	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.999
5.000E-05	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
7.000E-05	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
1.000E-04	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
3.000E-04	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
5.000E-04	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
7.000E-04	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
1.000E-03	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
3.000E-03	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
5.000E-03	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
7.000E-03	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
1.000E-02	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.

Output (cont.)

-144-

MOR-6

1
TIME AND ENERGY DEPENDENT FLUENCE (PARTICLES/CM**2-SEC-MEV)

DETECTOR NUMBER 1

ENERGIES TIMES	1.261E-02	2.000E-04	1.000E+01	8.190E+00	6.707E+00	5.493E+00	4.498E+00	3.684E+00	3.017E+00	2.471E+00
1.243E-09	2.000E-04	1.000E-10	8.190E+00	6.707E+00	5.493E+00	4.498E+00	3.684E+00	3.017E+00	2.471E+00	2.024E+00
1.500E-09	0.	0.	0.	0.	7.510E+06	1.142E+10	0.	6.099E+09	1.516E+07	1.736E+10
2.000E-09	0.	0.	0.	0.	1.000	1.000	0.	0.987	1.000	1.000
5.000E-09	0.	0.	0.	0.	0.	2.406E+06	4.133E+09	5.139E+09	6.821E+09	0.
1.000E-08	0.	0.	0.	0.	0.	1.000	1.000	0.751	1.000	0.
3.000E-08	0.	0.	0.	4.197E+08	2.694E+08	5.493E+06	8.853E+08	7.401E+07	2.719E+09	7.493E+07
5.000E-08	0.	0.	0.	0.975	0.552	1.000	0.691	0.780	1.000	0.601
1.000E-07	0.	0.	0.	1.954E+07	2.868E+08	0.	4.165E+08	1.709E+06	3.461E+06	6.359E+07
3.000E-07	0.	0.	0.	0.701	0.610	0.	1.000	0.667	0.458	0.970
5.000E-07	0.	0.	0.	5.138E+06	5.336E+06	1.680E+04	2.944E+05	6.703E+04	1.514E+06	7.167E+06
7.000E-07	0.	0.	0.	0.907	0.807	0.583	0.528	0.498	0.789	0.445
1.000E-06	0.	0.	0.	2.236E+02	3.910E+05	6.196E+02	5.636E+03	2.207E+05	1.262E+05	2.588E+06
3.000E-06	0.	0.	0.	0.720	0.465	1.000	0.731	0.594	0.413	0.229
5.000E-06	0.	0.	0.	0.	4.879E+05	2.806E+04	3.010E+03	5.036E+04	7.372E+05	3.480E+06
7.000E-06	0.	0.	0.	0.	0.564	1.000	0.921	0.686	0.607	0.387
1.000E-05	7.878E+08	0.	0.	7.699E+02	5.777E+04	0.	2.452E+04	1.864E+04	8.561E+04	3.026E+06
3.000E-05	1.000	0.	0.	1.000	0.549	0.	1.000	0.685	0.644	0.535
5.000E-05	2.318E+09	0.	3.028E+04	2.046E+04	1.133E+05	9.799E+04	1.595E+05	5.384E+04	1.855E+04	1.827E+06
7.000E-05	0.920	0.	1.000	0.735	0.505	0.952	0.697	0.541	0.962	0.268
1.000E-04	6.978E+08	0.	0.	3.692E+05	4.705E+05	0.	4.166E+03	5.393E+04	2.705E+05	3.000E+06
3.000E-04	0.741	0.	0.	0.565	0.588	0.	0.848	0.683	0.687	0.221
5.000E-04	3.004E+07	1.182E+07	0.	2.192E+05	2.061E+05	2.142E+05	0.	2.951E+04	1.522E+04	3.590E+06
7.000E-04	0.593	0.837	0.	0.814	0.550	0.935	0.	1.000	1.000	0.311
1.000E-03	3.205E+07	1.376E+10	3.334E+03	1.593E+05	4.870E+05	8.195E+04	3.339E+04	4.629E+05	2.168E+05	4.059E+06
3.000E-03	0.958	0.440	0.869	0.770	0.495	0.893	0.889	0.936	0.404	0.310
5.000E-03	0.	2.455E+08	2.009E+04	9.088E+04	1.879E+05	5.023E+04	1.448E+05	5.518E+04	1.833E+05	2.095E+06
7.000E-03	0.	0.513	0.509	0.308	0.298	0.411	0.525	0.621	0.507	0.223
1.000E-02	0.	5.738E+05	1.188E+03	4.213E+03	1.750E+04	5.184E+03	4.278E+03	5.222E+03	1.322E+04	1.622E+05
3.000E-02	0.	0.626	0.670	0.463	0.347	0.468	0.634	0.658	0.551	0.379
5.000E-02	0.	3.068E-86	0.	0.	0.	0.	0.	0.	0.	0.
7.000E-02	0.	1.000	0.	0.	0.	0.	0.	0.	0.	0.

Output (cont.)

-145-

MOR-6

1
TIME AND ENERGY DEPENDENT FLUENCE (PARTICLES/CM**2-SEC-MEV)

DETECTOR NUMBER 1

ENERGIES TIMES	2.024E+00	1.657E+00	1.357E+00	1.112E+00	9.103E-01	7.455E-01	6.105E-01
1.243E-09	1.657E+00	1.357E+00	1.112E+00	9.103E-01	7.455E-01	6.105E-01	5.000E-01
	0.	1.595E+10	1.575E+07	1.168E+10	8.95CE+10	2.472E+09	2.439E+10
	0.	0.999	0.695	0.990	0.903	1.000	0.889
1.500E-09	1.346E+10	1.705E+10	5.240E+09	1.595E+11	1.295E+10	7.406E+09	1.738E+10
	1.000	0.894	0.687	0.788	0.454	0.513	0.543
2.000E-09	5.317E+07	1.293E+09	1.857E+09	3.664E+08	3.522E+10	1.682E+10	4.197E+09
	0.456	0.941	0.695	0.684	0.671	0.684	0.349
5.000E-09	3.581E+08	1.683E+07	1.099E+08	7.112E+08	1.555E+08	3.341E+08	1.641E+09
	0.531	0.404	0.402	1.000	0.469	0.410	0.639
1.000E-08	1.749E+06	3.162E+06	1.041E+07	5.574E+05	3.390E+06	6.354E+06	9.976E+06
	0.397	0.459	0.554	0.322	0.653	0.354	0.360
3.000E-08	6.049E+05	5.559E+05	1.566E+05	1.119E+05	4.306E+05	7.131E+05	5.249E+06
	0.677	0.688	0.569	0.913	0.623	0.631	0.832
5.000E-08	7.106E+05	1.808E+05	5.778E+04	2.216E+05	6.711E+05	2.557E+05	5.246E+05
	0.696	0.735	1.000	0.693	0.720	0.888	0.520
7.000E-08	1.890E+06	0.	1.239E+05	0.	5.833E+05	8.169E+06	5.710E+05
	0.994	0.	0.688	0.	0.977	1.000	0.670
1.000E-07	1.733E+06	5.416E+04	3.051E+05	1.682E+04	1.070E+05	1.868E+06	1.373E+06
	0.799	0.769	0.421	0.998	0.959	0.901	0.345
3.000E-07	1.630E+05	1.697E+06	3.555E+05	1.036E+06	5.388E+05	6.722E+05	1.452E+06
	0.625	0.687	0.617	0.475	0.959	0.954	0.482
7.000E-07	0.	0.	8.127E+05	3.148E+06	1.565E+05	1.708E+06	8.795E+05
	0.	0.	0.579	1.000	0.959	0.898	0.523
1.000E-06	4.421E+05	2.583E+04	3.906E+05	6.488E+05	4.728E+05	1.453E+06	2.964E+06
	0.689	0.601	0.441	0.651	0.572	0.610	0.420
1.000E-05	5.137E+05	8.371E+05	5.106E+05	5.742E+05	2.574E+05	8.396E+05	1.083E+06
	0.388	0.606	0.342	0.756	0.484	0.576	0.349
1.000E-04	4.142E+04	4.483E+04	4.862E+04	4.081E+04	3.472E+04	4.302E+04	1.051E+05
	0.556	0.549	0.481	0.486	0.454	0.516	0.490
1.000E-03	0.	0.	0.	0.	0.	0.	0.
	0.	0.	0.	0.	0.	0.	0.
1.000E-02							

Output (cont.)

-146-

MOR-6

DEPENDENT FUNCTION (PARTICLES/CM**2-SEC-MEV)

ENERGIES TIMES	1.800E+01	1.175E+01	7.660E+00	5.770E+00	4.210E+00	2.970E+00	1.990E+00	1.260E+00	8.420E-01	5.900E-01	1.261E-02
1.440E-09	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
1.500E-09	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
2.000E-09	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
5.000E-09	0.	2.035E+07	0.	0.	0.	0.	0.	0.	0.	0.	0.
1.000E-08	0.	0.564	0.	0.	0.	0.	0.	0.	0.	0.	0.
3.000E-08	0.	1.256E+07	5.272E+07	9.150E+07	1.155E+08	1.407E+08	1.236E+08	4.216E+07	1.216E+07	5.503E+05	0.923
5.000E-08	0.	0.323	0.247	0.185	0.221	0.274	0.250	0.372	0.533	0.923	0.923
7.000E-08	0.	4.380E+00	2.157E+02	5.507E+04	2.546E+06	1.775E+07	2.780E+07	4.410E+07	5.376E+07	4.635E+07	0.726
1.000E-07	0.	1.000	0.680	0.731	0.938	0.664	0.302	0.289	0.301	0.726	0.726
3.000E-07	0.	0.	4.846E-01	1.104E-01	3.665E-02	3.219E-02	6.440E-02	1.191E-04	3.023E+06	2.677E+07	0.445
5.000E-07	0.	0.	1.000	1.000	0.615	0.984	0.467	0.487	0.856	0.445	0.445
7.000E-07	0.	0.	0.	0.	0.	5.085E-03	5.717E-04	1.145E-02	2.832E+00	4.681E+06	0.803
1.000E-06	0.	0.	0.	0.	0.	1.000	0.991	0.866	0.561	0.803	0.803
3.000E-06	0.	0.	0.	0.	0.	0.	0.	0.	9.472E-10	3.285E+07	0.996
5.000E-06	0.	0.	0.	0.	0.	0.	0.	0.	0.933	0.996	0.996
7.000E-06	0.	0.	0.	0.	0.	0.	0.	0.	0.	4.250E-17	0.850
1.000E-05	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.850	0.850
3.000E-05	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
5.000E-05	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
7.000E-05	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
1.000E-04	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
3.000E-04	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
5.000E-04	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
7.000E-04	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
1.000E-03	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
3.000E-03	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
5.000E-03	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
7.000E-03	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
1.000E-02	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.

Output (cont.)

-147-

MOR-6

TIME AND ENERGY DEPENDENT FLUENCE (PARTICLES/CM**2-SEC-MEV)

DETECTOR NUMBER 2

ENERGIES TIMES	1.261E-02	2.000E-04	1.000E+01	8.190E+00	6.707E+00	5.493E+00	4.498E+00	3.684E+00	3.017E+00	2.471E+00	2.024E+00
1.440E-09	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	1.652E+10
1.500E-09	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	1.000
2.000E-09	0.	0.	0.	0.	0.	1.419E+06	1.899E+09	0.	1.322E+09	2.036E+09	0.
5.000E-09	0.	0.	0.	0.	0.	1.000	1.000	0.	0.705	0.999	0.
1.000E-08	0.	0.	0.	0.	2.348E+08	1.485E+08	3.249E+05	3.826E+08	1.932E+08	8.535E+08	2.132E+07
3.000E-08	0.	0.	0.	0.	0.933	0.572	1.000	0.690	0.890	1.000	0.477
5.000E-08	0.	0.	0.	0.	1.013E+07	1.496E+08	0.	1.889E+04	6.243E+05	1.370E+06	2.842E+05
1.000E-07	0.	0.	0.	0.	0.684	0.570	0.	0.576	0.710	0.518	0.329
3.000E-07	0.	0.	0.	0.	5.167E+06	2.086E+07	8.388E+03	1.437E+05	3.058E+04	6.571E+05	3.793E+06
5.000E-07	0.	0.	0.	0.	0.959	0.949	0.555	0.596	0.745	0.756	0.325
7.000E-07	0.	0.	0.	0.	1.060E+03	1.710E+05	3.120E+02	2.969E+03	1.459E+05	5.455E+04	1.185E+06
1.000E-06	0.	0.	0.	0.	0.692	0.457	1.000	0.706	0.608	0.423	0.262
3.000E-06	0.	0.	0.	0.	0.	2.076E+05	1.359E+04	3.947E+03	2.110E+04	3.748E+05	1.744E+06
5.000E-06	0.	0.	0.	0.	0.	0.566	1.000	0.727	0.692	0.637	0.381
7.000E-06	0.	0.	0.	0.	3.822E+02	2.609E+04	0.	1.171E+04	7.298E+03	3.331E+04	1.219E+06
1.000E-05	0.	0.	0.	0.	1.000	0.558	0.	1.000	0.685	0.629	0.505
3.000E-05	3.330E+08	0.	1.852E+04	1.181E+04	7.903E+04	4.814E+04	9.754E+04	2.253E+04	7.555E+03	9.541E+05	0.296
5.000E-05	0.930	0.	1.000	0.771	0.510	0.951	0.709	0.540	0.822	0.296	0.296
7.000E-05	1.369E+06	0.	0.	1.843E+05	2.398E+05	0.	6.725E+03	4.139E+04	1.187E+05	1.285E+06	0.232
1.000E-04	0.630	0.	0.	0.571	0.591	0.	0.851	0.681	0.686	0.232	0.232
3.000E-04	2.419E+07	7.556E+07	0.	1.474E+05	9.495E+04	5.355E+04	0.	1.498E+04	0.	4.316E+06	0.593
5.000E-04	0.938	1.000	0.	0.871	0.538	0.898	0.	1.000	0.	0.593	0.593
7.000E-04	9.973E+03	4.276E+08	2.263E+03	7.964E+04	2.382E+05	3.468E+04	1.663E+04	2.683E+05	1.056E+05	1.608E+06	0.308
1.000E-03	0.762	0.941	0.704	0.758	0.481	0.856	0.900	0.956	0.435	0.308	0.308
3.000E-03	0.	1.547E+06	1.433E+04	5.079E+04	8.940E+04	2.475E+04	4.996E+04	1.113E+04	4.216E+04	1.123E+06	0.234
5.000E-03	0.	0.688	0.523	0.290	0.342	0.414	0.463	0.449	0.546	0.234	0.234
7.000E-03	0.	1.554E+05	7.546E+02	2.397E+03	9.655E+03	2.469E+03	1.172E+03	2.590E+03	5.400E+03	1.091E+05	0.492
1.000E-02	0.	0.997	0.690	0.451	0.332	0.465	0.601	0.658	0.529	0.492	0.492
3.000E-02	0.	1.816E-82	0.	0.	0.	0.	0.	0.	0.	0.	0.
5.000E-02	0.	1.000	0.	0.	0.	0.	0.	0.	0.	0.	0.

Output (cont.)

-148-

MOR-6

1
TIME AND ENERGY DEPENDENT FLUENCE (PARTICLES/CM**2-SEC-MEV)

DETECTOR NUMBER 2

ENERGIES TIMES	2.024E+00	1.657E+00	1.357E+00	1.112E+00	9.103E-01	7.455E-01	6.105E-01
1.440E-09	1.657E+00	1.357E+00	1.112E+00	9.103E-01	7.455E-01	6.105E-01	5.000E-01
1.500E-09	0.	1.073E+10	3.941E+06	0.	3.296E+09	0.	2.449E+08
2.000E-09	0.977	0.882	0.661	0.551	0.894	0.998	0.876
5.000E-09	1.881E+08	5.995E+08	2.429E+08	5.560E+08	2.267E+09	3.130E+09	3.396E+09
1.000E-08	0.390	0.624	0.471	0.808	0.628	0.259	0.440
3.000E-08	9.345E+05	2.369E+06	4.013E+06	2.374E+05	2.045E+06	4.460E+06	5.712E+06
5.000E-08	0.629	0.642	0.920	0.877	0.937	0.607	0.834
7.000E-08	7.047E+00	3.599E+05	5.086E+04	4.672E+04	1.244E+05	1.714E+05	1.046E+05
1.000E-07	0.997	0.975	1.000	0.	1.000	0.788	0.758
3.000E-07	6.718E+05	2.375E+05	1.005E+05	7.077E+03	3.722E+05	4.749E+05	1.231E+06
7.000E-07	1.341E+05	4.869E+05	3.039E+05	8.051E+05	9.012E+05	1.953E+05	3.505E+05
1.000E-06	1.182E+05	0.	3.597E+05	9.690E+01	1.563E+05	6.146E+01	3.507E+05
1.000E-05	1.314E+05	1.796E+04	4.149E+05	2.539E+05	1.289E+05	7.703E+05	2.563E+06
1.000E-04	1.369E+05	1.437E+04	9.702E+04	1.543E+05	2.427E+05	2.219E+05	2.411E+06
1.000E-03	2.717E+04	8.134E+03	4.052E+04	1.006E+05	1.506E+04	4.756E+04	8.333E+04
1.000E-02	0.	0.	0.	0.	0.	0.	0.

Output (cont.)

-149-

MOR-6

1
ANGLE AND ENERGY DEPENDENT FLUENCE (PARTICLES/CM**2-MEV-STERADIAN)

DETECTOR NUMBER 1

ENERGIES	1.800E+01	1.175E+01	7.660E+00	5.770E+00	4.210E+00	2.970E+00	1.990E+00	1.260E+00	8.420E-01	5.900E-01	
COSINES	1.175E+01	7.660E+00	5.770E+00	4.210E+00	2.970E+00	1.990E+00	1.260E+00	8.420E-01	5.900E-01	1.261E-02	
-1.000E+00	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	
0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	
	0.	1.358E-03	2.452E-03	3.406E-03	1.125E-02	1.673E-03	9.349E-03	7.892E-03	8.343E-03	3.497E-03	
	0.	1.000	0.698	0.752	0.851	0.782	0.792	0.927	0.939	0.978	
2.000E-01	0.	4.115E-04	6.239E-03	2.376E-01	1.143E+00	4.003E-02	1.360E-01	4.519E-01	3.934E-01	5.639E-01	
	0.	1.000	0.836	0.904	0.683	0.668	0.556	0.606	0.760	0.815	
4.000E-01	0.	3.240E-04	5.029E-04	2.094E-02	9.613E-03	6.735E-02	2.612E-01	5.665E-01	1.486E-01	4.442E+02	
	0.	0.996	0.641	0.808	0.517	0.586	0.646	0.963	0.886	0.996	
6.000E-01	0.	1.090E-03	3.651E-02	8.936E-02	5.046E-01	1.119E+00	2.098E+00	1.254E+00	1.672E+00	2.335E+00	
	0.	0.615	0.354	0.290	0.537	0.406	0.493	0.490	0.435	0.353	
8.000E-01	0.	1.287E-01	1.332E-01	2.796E-01	2.185E+00	1.789E+01	3.155E+00	5.109E+00	4.481E+00	4.182E+00	
	0.	0.932	0.506	0.417	0.577	0.897	0.454	0.573	0.532	0.806	
9.000E-01	C.	2.253E-01	6.023E+00	2.156E+00	1.515E+02	6.909E+01	3.678E+01	1.847E+01	1.191E+01	7.597E+00	
	0.	0.662	0.910	0.557	0.981	0.766	0.645	0.576	0.477	0.621	
9.500E-01	0.	2.950E+01	1.246E+02	2.882E+02	3.103E+02	2.150E+02	2.179E+02	1.642E+02	1.206E+02	3.106E+02	
	0.	0.236	0.142	0.113	0.141	0.121	0.091	0.259	0.198	0.729	
1.000E+00											

Output (cont.)

-150-

MOR-6

ANGLE AND ENERGY DEPENDENT FLUENCE (PARTICLES/CM**2-MEV-STERADIAN)

DETECTOR NUMBER 1

ENERGIES	1.261E-02	2.000E-04	1.000E+01	8.190E+00	6.707E+00	5.493E+00	4.498E+00	3.684E+00	3.017E+00	2.471E+00
COSINES	2.000E-04	1.000E-10	8.190E+00	6.707E+00	5.493E+00	4.498E+00	3.684E+00	3.017E+00	2.471E+00	2.024E+00
-1.000E+00	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
2.000E-01	2.912E-04	3.744E+01	3.613E-02	1.231E-01	3.919E-01	0.	2.740E-01	1.689E-01	2.044E-01	4.270E+00
4.000E-01	0.879	1.000	1.000	1.000	0.999	0.	1.000	1.000	0.991	1.000
6.000E-01	3.273E+00	4.697E+04	0.	2.010E-01	4.366E-01	2.487E-01	1.125E-01	8.389E-02	1.478E-01	1.007E+01
8.000E-01	0.546	0.822	0.	0.869	0.828	0.994	0.992	0.972	0.966	0.678
9.000E-01	5.634E+01	1.126E+03	3.166E-03	1.393E-01	1.687E-01	3.159E-02	4.875E-02	6.738E-02	1.941E-01	3.253E+00
9.500E-01	0.531	0.660	1.000	0.812	0.962	1.000	1.000	0.997	0.999	0.789
1.000E+00	3.514E+00	1.299E+03	2.072E-02	2.267E-01	1.021E+00	7.303E-01	1.003E+00	8.413E-01	1.312E+00	2.221E+01
	0.913	0.558	1.000	0.459	0.707	0.838	0.934	0.649	0.745	0.410
	1.126E+01	3.188E+04	5.824E-01	7.500E+00	1.566E+01	3.644E+00	4.786E+00	6.554E+00	1.420E+01	1.492E+02
	0.681	0.974	0.924	0.600	0.584	0.567	0.973	0.928	0.824	0.703
	5.487E+00	1.330E+04	4.128E+00	5.979E+00	3.036E+01	4.562E+00	1.984E+01	1.341E+01	2.823E+01	2.261E+02
	0.667	0.970	0.682	0.589	0.350	0.782	0.548	0.920	0.712	0.309
	3.106E+03	1.913E+05	3.738E+00	2.427E+01	5.660E+01	2.536E+01	4.132E+01	2.692E+01	6.994E+01	5.226E+02
	0.642	0.459	0.624	0.343	0.309	0.439	0.610	0.585	0.528	0.361

Output (cont.)

-151-

MOR-6

1
ANGLE AND ENERGY DEPENDENT FLUENCE (PARTICLES/CM**2-MEV-STERADIAN)

DETECTOR NUMBER 1

ENERGIES COSINES -1.000E+00	2.024E+00 1.657E+00 0.	1.657E+00 1.357E+00 0.	1.357E+00 1.112E+00 0.	1.112E+00 9.103E-01 0.	9.103E-01 7.455E-01 0.	7.455E-01 6.105E-01 0.	6.105E-01 5.000E-01 0.
0.	4.753E-01 1.000	2.817E-01 1.000	1.537E-01 1.000	8.295E-01 1.000	3.802E-03 1.000	2.074E-01 0.999	1.524E+01 0.672
2.000E-01	6.878E+00 0.998	5.148E-01 0.939	1.545E+00 0.669	2.952E-01 0.977	6.829E-03 1.000	1.372E+00 0.925	1.197E+01 0.519
4.000E-01	7.143E+00 0.632	1.139E+01 0.942	1.132E+00 0.870	2.797E-01 0.667	5.727E+00 0.678	4.479E+00 0.613	1.750E+01 0.555
6.000E-01	5.129E+00 0.837	3.581E+01 0.993	3.128E+00 0.592	4.513E+01 0.710	3.241E+00 0.890	8.793E+00 0.538	4.269E+01 0.368
8.000E-01	3.701E+01 0.791	4.093E+01 0.761	4.989E+01 0.752	1.017E+01 0.712	3.184E+01 0.643	1.038E+02 0.650	8.149E+01 0.515
9.000E-01	2.414E+01 0.562	5.109E+01 0.572	9.738E+01 0.414	1.679E+01 0.615	1.482E+01 0.925	7.464E+01 0.573	7.652E+01 0.583
9.500E-01	1.312E+02 0.709	9.927E+01 0.485	1.041E+02 0.432	3.594E+02 0.596	5.062E+02 0.474	2.483E+02 0.529	2.256E+02 0.266
1.000E+00							

Output (cont.)

-152-

MOR-6

1
ANGLE AND ENERGY DEPENDENT FLUENCE (PARTICLES/CM**2-MEV-STERADIAN)

DETECTOR NUMBER 2

ENERGIES	1.800E+01	1.175E+01	7.660E+00	5.770E+00	4.210E+00	2.970E+00	1.990E+00	1.260E+00	8.420E-01	5.900E-01
CGSINES	1.175E+01	7.660E+00	5.770E+00	4.210E+00	2.970E+00	1.990E+00	1.260E+00	8.420E-01	5.900E-01	1.261E-02
-1.000E+00	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
2.000E-01	0.	2.602E-04	9.383E-04	3.172E-02	1.290E-01	3.062E-03	2.869E-02	4.699E-02	6.050E-02	5.377E+00
4.000E-01	0.	1.000	0.548	0.909	0.673	0.649	0.956	0.972	0.909	0.984
6.000E-01	0.	1.641E-04	8.741E-04	2.372E-04	1.456E-01	7.779E-02	1.931E-01	1.547E-01	1.262E-01	8.762E-02
8.000E-01	0.	0.809	0.668	0.667	0.891	0.436	0.590	0.664	0.718	0.420
1.000E+00	0.	1.999E-02	1.840E-01	1.218E-01	3.717E-01	6.868E-01	7.851E-01	5.501E-01	4.580E-01	8.470E-01
1.250E+00	0.	1.000	0.611	0.473	0.439	0.397	0.361	0.395	0.385	0.738
1.500E+00	0.	1.055E-02	1.003E-01	3.435E-01	4.635E-01	8.109E-01	1.076E+00	5.528E-01	3.696E-01	1.784E-01
1.750E+00	0.	0.666	0.382	0.310	0.243	0.250	0.390	0.425	0.219	0.513
2.000E+00	0.	4.458E-01	1.068E+00	1.841E+00	1.478E+00	1.658E+00	5.932E-01	1.322E-01	1.617E-01	4.476E-02
2.250E+00	0.	0.264	0.184	0.238	0.335	0.249	0.175	0.214	0.397	0.567
2.500E+00	0.	6.770E-02	4.435E-02	8.546E-02	8.779E-02	1.657E-01	2.942E-02	2.458E-03	5.305E-03	3.164E-03
2.750E+00	0.	0.862	0.633	0.270	0.402	0.348	0.265	0.426	0.838	0.995
3.000E+00	0.	4.070E-02	3.199E-02	7.115E-02	6.069E-02	2.905E-01	9.271E-02	6.999E-03	2.949E-03	1.803E-04
3.250E+00	0.	0.793	0.720	0.436	0.533	0.521	0.518	0.611	0.621	0.791
3.500E+00	0.									
3.750E+00	0.									
4.000E+00	0.									
4.250E+00	0.									
4.500E+00	0.									
4.750E+00	0.									
5.000E+00	0.									
5.250E+00	0.									
5.500E+00	0.									
5.750E+00	0.									
6.000E+00	0.									
6.250E+00	0.									
6.500E+00	0.									
6.750E+00	0.									
7.000E+00	0.									
7.250E+00	0.									
7.500E+00	0.									
7.750E+00	0.									
8.000E+00	0.									
8.250E+00	0.									
8.500E+00	0.									
8.750E+00	0.									
9.000E+00	0.									
9.250E+00	0.									
9.500E+00	0.									
9.750E+00	0.									
1.000E+00	0.									

Output (cont.)

-153-

MOR-6

1

ANGLE AND ENERGY DEPENDENT FLUENCE (PARTICLES/CM**2-MEV-STERADIAN)

DETECTOR NUMBER 2

ENERGIES	1.261E-02	2.000E-04	1.000E+01	8.190E+00	6.707E+00	5.493E+00	4.498E+00	3.684E+00	3.017E+00	2.471E+00
COSINES	2.000E-04	1.000E-10	8.190E+00	6.707E+00	5.493E+00	4.498E+00	3.684E+00	3.017E+00	2.471E+00	2.024E+00
-1.000E+00	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
0.	0.	0.	0.	0.	0.	0.	0.	0.	0.	0.
2.000E-01	5.522E+01	3.220E+03	1.434E-02	1.106E-01	1.794E-01	8.806E-02	1.537E-01	9.443E-02	1.413E-01	3.088E+00
	0.998	0.918	1.000	1.000	0.993	1.000	1.000	1.000	0.994	0.998
4.000E-01	1.736E-01	2.057E+01	0.	4.477E-02	1.530E-01	2.365E-02	1.872E-02	2.710E-02	6.300E-02	2.840E+00
	0.744	0.854	0.	0.573	0.721	0.662	0.997	0.961	0.962	0.618
6.000E-01	3.845E+00	4.817E+01	1.823E-02	7.784E-01	9.093E-01	2.228E-01	2.465E-02	8.951E-02	1.833E-01	6.057E+00
	0.993	0.688	0.688	0.910	0.443	0.953	0.780	0.715	0.586	0.377
8.000E-01	4.373E-02	8.609E+00	6.604E-01	2.181E+00	6.826E+00	1.290E+00	2.861E+00	1.111E+00	2.505E+00	6.399E+01
	0.599	0.686	0.678	0.442	0.517	0.657	0.648	0.669	0.507	0.312
9.000E-01	1.851E-04	9.234E+00	5.080E-01	5.396E+00	9.920E+00	3.755E+00	4.285E+00	7.571E+00	1.273E+01	1.019E+02
	0.636	0.932	0.741	0.341	0.366	0.499	0.568	0.504	0.419	0.329
9.500E-01	1.182E-03	8.333E-03	8.110E-01	5.157E-01	8.630E+00	4.260E+00	1.041E+00	1.907E+00	4.613E+00	1.424E+02
	1.000	1.000	1.000	0.705	0.433	0.617	0.675	0.993	0.992	0.891
1.000E+00	2.095E-08	3.277E-03	1.744E+00	3.046E+00	4.956E+00	0.	4.047E-02	1.289E-02	5.630E-01	4.035E+01
	0.660	0.999	0.997	0.695	0.531	0.	1.000	0.625	0.940	0.522

Output (cont.)

-154-

MOR-6

1
ANGLE AND ENERGY DEPENDENT FLUENCE (PARTICLES/CM**2-MEV-STERADIAN)

DETECTOR NUMBER 2

ENERGIES COSINES -1.000E+00	2.024E+00	1.657E+00	1.357E+00	1.112E+00	9.103E-01	7.455E-01	6.105E-01
0.	0.	0.	0.	0.	0.	0.	0.
0.	0.	0.	0.	0.	0.	0.	0.
2.000E-01	3.991E-01	2.460E-01	2.062E-01	4.566E-02	3.799E-03	1.745E+00	2.623E+01
	1.000	0.997	1.000	0.971	1.000	0.683	0.632
4.000E-01	7.343E-01	1.518E-01	3.277E-01	2.243E-01	3.256E+00	2.108E+01	1.553E+02
	0.746	0.995	0.606	0.967	0.608	0.665	0.797
6.000E-01	4.354E-01	8.791E-02	2.086E+00	6.154E-01	9.951E-01	6.103E+00	2.388E+01
	0.445	0.844	0.645	0.782	0.604	0.538	0.668
8.000E-01	7.806E+00	3.987E+00	2.509E+01	1.136E+01	1.695E+01	1.035E+01	2.356E+01
	0.465	0.655	0.569	0.700	0.455	0.370	0.340
9.000E-01	1.700E+01	5.810E+00	2.081E+01	1.173E+01	2.795E+01	3.703E+01	4.443E+01
	0.487	0.448	0.478	0.435	0.255	0.494	0.370
9.500E-01	5.331E+01	1.080E+01	5.356E+00	2.789E+02	9.730E+00	5.386E+02	5.721E+01
	0.665	0.631	0.718	0.988	0.841	0.990	0.500
1.000E+00	2.453E+00	8.627E-01	5.977E+00	9.179E-01	7.740E+00	1.646E+01	3.641E+01
	0.737	0.736	0.585	0.775	0.962	0.764	0.640

TIME FOR OUTPUT = 2.308E+00
TOTAL PROBLEM TIME = 2.762E+01

Output (cont.)

-155-

MOR-6

BOX 1 1 1

LENGTHS OF SIDES

X 2.000E+02

Y 2.000E+02

Z 5.531E+01

EXAMPLE PROBLEM FOR MORSE-L REPORT

EXAMPLE PROBLEM FOR MORSE-L REPORT

EXAMPLE PROBLEM FOR MORSE-L REPORT

BOX 1 1 1
 BLOCK 1 1 2
 LENGTHS OF SIDES
 X 2.000E+02
 Y 2.000E+02
 Z 3.031E+01

EXAMPLE PROBLEM FOR MORSE-L REPORT
ENERGY DEPENDENT FLUENCE FOR DETECTOR NUMBER 1

EXAMPLE PROBLEM FOR MORSE-L REPORT
ENERGY DEPENDENT FLUENCE FOR DETECTOR NUMBER 1

EXAMPLE PROBLEM FOR MORSE-L REPORT
ENERGY DEPENDENT FLUENCE FOR DETECTOR NUMBER 2

EXAMPLE PROBLEM FOR MORSE-L REPORT
ENERGY DEPENDENT FLUENCE FOR DETECTOR NUMBER 2

EXAMPLE PROBLEM FOR MORSE-L REPORT
TIME DEPENDENT RESPONSE FOR DETECTOR 1 AND RESPONSE FUNCTION 1

EXAMPLE PROBLEM FOR MORSE-L REPORT
TIME DEPENDENT RESPONSE FOR DETECTOR 1 AND RESPONSE FUNCTION 2

EXAMPLE PROBLEM FOR MORSE-L REPORT
TIME DEPENDENT RESPONSE FOR DETECTOR 1 AND RESPONSE FUNCTION 3

EXAMPLE PROBLEM FOR MORSE-L REPORT
TIME DEPENDENT RESPONSE FOR DETECTOR 2 AND RESPONSE FUNCTION 1

EXAMPLE PROBLEM FOR MORSE-L REPORT
TIME DEPENDENT RESPONSE FOR DETECTOR 2 AND RESPONSE FUNCTION 2

EXAMPLE PROBLEM FOR MORSE-L REPORT
TIME DEPENDENT RESPONSE FOR DETECTOR 2 AND RESPONSE FUNCTION 3

EXAMPLE PROBLEM FOR MORSE-L REPORT
TIME AND ENERGY DEPENDENT FLUENCE FOR DETECTOR NUMBER 1
(EACH ENERGY PLOT OF FLUENCE IS SCALED INDEPENDENTLY)

EXAMPLE PROBLEM FOR MORSE-L REPORT
TIME AND ENERGY DEPENDENT FLUENCE FOR DETECTOR NUMBER 2
(EACH ENERGY PLOT OF FLUENCE IS SCALED INDEPENDENTLY)

EXAMPLE PROBLEM FOR MORSE-L REPORT
ANGLE AND ENERGY DEPENDENT FLUENCE FOR DETECTOR NUMBER 1
(EACH ENERGY PLOT OF FLUENCE IS SCALED INDEPENDENTLY)

EXAMPLE PROBLEM FOR MORSE-L REPORT
ANGLE AND ENERGY DEPENDENT FLUENCE FOR DETECTOR NUMBER 2
(EACH ENERGY PLOT OF FLUENCE IS SCALED INDEPENDENTLY)

MORSE - 1

1.90492E+02	7.29448E-02	0.	0.	0.	0.	MORSE- 3
1.41305E+00	1.61894E-01	0.	0.	0.	0.	MORSE- 4
TOTAL RESPONSE						MORSE- 5
1.02931E+03	3.85627E-01	5.25011E+02	2.21068E-01	1.36507E+03	2.26573E-01	MORSE- 6
2.12074E+01	2.67224E-01	2.87948E+02	2.43721E-01	6.89132E+02	2.35697E-01	MORSE- 7
ENERGY DEPENDENT FLUENCE						MORSE- 8
0.	0.	8.90415E+00	2.43639E-01	4.05122E+01	1.38726E-01	MORSE- 9
9.01228E+01	1.11049E-01	1.44473E+02	3.34502E-01	9.82988E+01	2.96345E-01	MORSE-10
8.28310E+01	9.35057E-02	6.14993E+01	2.01553E-01	4.53462E+01	1.73113E-01	MORSE-11
6.27836E+02	8.42163E-01	1.00483E+03	5.86533E-01	1.38362E+05	3.82969E-01	MORSE-12
2.75079E+00	3.72250E-01	1.47073E+01	2.63642E-01	3.95117E+01	2.65408E-01	MORSE-13
1.27960E+01	2.86242E-01	2.27927E+01	4.29477E-01	2.24727E+01	3.41026E-01	MORSE-14
4.19629E+01	3.24076E-01	3.72489E+02	2.40397E-01	9.38095E+01	4.02811E-01	MORSE-15
1.25922E+02	3.73831E-01	1.00817E+02	3.46047E-01	1.78480E+02	3.89816E-01	MORSE-16
1.89414E+02	3.79895E-01	1.75361E+02	3.31285E-01	2.52821E+02	2.96895E-01	MORSE-17
0.	0.	3.33864E-01	2.55393E-01	1.02585E+00	2.41100E-01	MORSE-18
1.79521E+00	1.78714E-01	2.29114E+00	2.12981E-01	3.07233E+00	2.58304E-01	MORSE-19
2.89668E+00	2.08536E-01	1.64072E+00	2.45327E-01	1.30849E+00	2.54891E-01	MORSE-20
7.73045E+00	9.13001E-01	7.03566E+01	9.27635E-01	3.91943E+03	8.93806E-01	MORSE-21
1.88213E+00	3.85120E-01	8.19651E+00	2.60888E-01	2.00232E+01	2.63143E-01	MORSE-22
5.68542E+00	2.78038E-01	6.55327E+00	4.31448E-01	8.01019E+00	3.59129E-01	MORSE-23
1.35615E+01	3.39546E-01	2.10634E+02	2.75276E-01	3.87901E+01	3.68406E-01	MORSE-24
1.46032E+01	3.77456E-01	4.91086E+01	4.44277E-01	1.08859E+02	7.81947E-01	MORSE-25
4.70444E+01	2.96508E-01	2.34000E+02	6.97456E-01	3.45812E+02	4.27541E-01	MORSE-26
TIME DEPENDENT RESPONSE						MORSE-27
0.	0.	4.54467E+10	5.52922E-01	1.05330E+11	5.74246E-01	MORSE-28
0.	0.	6.60329E+10	4.16695E-01	1.13861E+11	3.71692E-01	MORSE-29
0.	0.	1.26238E+10	4.40694E-01	2.09883E+10	4.58590E-01	MORSE-30
7.10424E+09	2.43190E-01	1.24589E+09	4.35090E-01	4.15367E+09	4.79271E-01	MORSE-31
2.88628E+10	1.72552E-01	2.52028E+07	3.05704E-01	1.09183E+08	4.98240E-01	MORSE-32
1.02958E+10	8.74225E-01	2.93915E+06	2.35130E-01	7.11070E+06	2.11548E-01	MORSE-33
6.38312E+09	9.78770E-01	3.06795E+06	3.05972E-01	8.81779E+06	3.25974E-01	MORSE-34
5.17112E+07	2.44830E-01	3.46032E+06	5.41185E-01	5.93060E+06	4.36247E-01	MORSE-35
2.34837E+08	9.22396E-01	2.42778E+06	3.13354E-01	6.17822E+06	2.15011E-01	MORSE-36
8.18434E+06	7.41751E-01	3.87581E+06	2.12305E-01	1.22286E+07	3.07009E-01	MORSE-37
3.54386E+05	5.90953E-01	3.40834E+06	2.89409E-01	9.28681E+06	2.68454E-01	MORSE-38
2.97443E+06	4.20935E-01	4.16886E+06	2.32068E-01	1.20887E+07	3.00615E-01	MORSE-39
4.64986E+04	5.14231E-01	2.54407E+06	2.18250E-01	7.03263E+06	2.05716E-01	MORSE-40
1.08389E+02	6.28077E-01	1.85055E+05	3.88769E-01	4.93358E+05	3.79345E-01	MORSE-41
5.79597E-90	1.00000E+00	0.	0.	0.	0.	MORSE-42
0.	0.	1.05596E+10	7.03965E-01	2.07369E+10	7.75343E-01	

Punched Card Output

-173-

MOR-6

8.08825E+04	9.40045E-01	1.97635E+06	2.32420E-01	5.65617E+06	2.83497E-01	MORSE-54
2.92185E+02	6.88893E-01	1.22177E+06	2.36207E-01	3.27903E+06	1.96534E-01	MORSE-55
2.93557E+01	9.97003E-01	1.27812E+05	4.43942E-01	3.01270E+05	4.05031E-01	MORSE-56
3.43012E-86	1.00000E+00	0.	0.	0.	0.	MORSE-57
TIME AND ENERGY DEPENDENT FLUENCE						MORSE-58
0.	0.	0.	0.	0.	0.	MORSE-59
0.	0.	0.	0.	0.	0.	MORSE-60
0.	0.	0.	0.	0.	0.	MORSE-61
0.	0.	0.	0.	0.	0.	MORSE-62
0.	0.	0.	0.	0.	0.	MORSE-63
0.	0.	0.	0.	0.	0.	MORSE-64
1.73621E+09	2.43155E-01	1.11541E+07	4.63239E-01	1.68523E+00	1.00000E+00	MORSE-65
0.	0.	0.	0.	0.	0.	MORSE-66
0.	0.	0.	0.	0.	0.	MORSE-67
0.	0.	0.	0.	0.	0.	MORSE-68
0.	0.	0.	0.	0.	0.	MORSE-69
1.65668E+06	1.00000E+00	2.02520E+09	1.38742E-01	2.90076E+02	9.57806E-01	MORSE-70
0.	0.	0.	0.	0.	0.	MORSE-71

ANGLE AND ENERGY DEPENDENT FLUENCE						MORSE329
0.	0.	0.	0.	0.	0.	MORSE330
0.	0.	0.	0.	0.	0.	MORSE331
0.	0.	0.	0.	0.	0.	MORSE332
1.28252E-03	1.00000E+00	3.88628E-04	9.99927E-01	3.06021E-04	9.96469E-01	MORSE333
1.02960E-03	1.16355E-01	1.21561E-01	9.32323E-01	2.12740E-01	6.63346E-01	MORSE334
2.78748E+01	2.42189E-01	0.	0.	2.31602E-03	6.98953E-01	MORSE335
5.89280E-03	8.36239E-01	1.58706E-03	7.09458E-01	3.49908E-02	3.51098E-01	MORSE336
1.26334E-01	5.06244E-01	5.70073E+00	9.08566E-01	1.22822E+02	1.36890E-01	MORSE337
0.	0.	3.21701E-03	7.52656E-01	2.24357E-01	9.04031E-01	MORSE338
2.05248E-02	7.77372E-01	8.60094E-02	2.86707E-01	2.65715E-01	4.16638E-01	MORSE339
2.04874E+00	5.54561E-01	2.82953E+02	1.10376E-01	0.	0.	MORSE340
1.06253E-02	8.52041E-01	1.07993E+00	6.84270E-01	9.12008E-03	5.16281E-01	MORSE341
4.77429E-01	5.38159E-01	2.06622E+00	5.78327E-01	1.43282E+02	9.80418E-01	MORSE342
3.06149E+02	1.35351E-01	0.	0.	1.57984E-03	7.82552E-01	MORSE343
3.78462E-02	6.68471E-01	6.42108E-02	5.81628E-01	1.06038E+00	4.07816E-01	MORSE344
1.69083E+01	8.97392E-01	6.55286E+01	7.63447E-01	2.08893E+02	1.20825E-01	MORSE345
0.	0.	8.82968E-03	7.92607E-01	1.28472E-01	5.58079E-01	MORSE346
2.46856E-01	6.46812E-01	1.98399E+00	4.94298E-01	2.99654E+00	4.54201E-01	MORSE347
7.25185E+01	4.42419E-01	5.43027E+01	4.99087E-01	3.52321E+01	6.24240E-01	MORSE473

Card Output (cont.)

-174-

MOR-6

References:

1. E. A. Straker, et al, "The MORSE Code - A Multigroup Neutron and Gamma-ray Monte Carlo Transport Code"; ORNL-4585, September, 1970.
2. V. R. Cain, "Sambo, A Collision Analysis Package for Monte Carlo Codes"; ORNL-TM-3203, September, 1970.
3. T. P. Wilcox, "MORSE-C, A Special Version of the MORSE Program Designed to Solve Criticality Problems"; MOR-2, April 27, 1971.
4. B. F. Maskewitz, "A Review of the Monte Carlo Method for Radiation Transport Calculations (Collected Papers of a Seminar, October 5-7, 1970)"; ORNL-RSIC-29, February, 1971, p.113-123.
5. F. M. Clark, "The Exponential Transform as an Importance Sampling Device - A Review"; ORNL-RSIC-14, January, 1966.
6. E. D. Cashwell, C. J. Everett, "A Practical Manual on the Monte Carlo Method for Random Walk Problems"; LA-2120, January, 1957 (Also published as a book).
7. G. L. Burrown, D. B. MacMillan, "Confidence Limits for Monte Carlo Calculations"; Nuclear Science and Engineering, 22, 384-394 (1965).
8. S. S. Shapiro, M. B. Wilk, "An Analysis of Variance Test for Normality (complete samples)", Biometrika (1965), 52, 3 and 4, p 591.

Distribution:

C. Anderson
D. Buchla
P. Brown
G. Canfield
J. Carothers
W. Collins
W. Cooper
R. DaRoza
N. Davies
W. Dickinson
R. Doyas
S. Eccles
R. Ellis
E. Farley
J. Ferguson
J. Fleck, Jr.
H. Francis
R. Geil
P. Giles
W. Grayson
C. Groseclose
D. Hanner
T. Harper
L. Hilton
R. Howe
R. Howerton
J. Hudson
R. Jones

B. Koponen
J. Lee
W. Loewe
G. Maenchen
J. Mallett
S. Matthews
W. McMaster
E. Mendelsohn
G. Miller, Sandia, Liv.
J. Mogford, Sandia, Liv.
L. Moon
J. Morton
E. McCauley
R. Neifert
N. Parker
S. Perkins
E. Plechaty
C. Prevo
A. Profio
C. Reinhardt, EG&G, LV
L. Richards
J. Ruminer
J. Shearer
D. Smith
G. Tiresill
A. Toor
J. Watson
T. Wilcox
TID File, L-9 (2)

NOTICE

"This report was prepared as an account of work sponsored by the United States Government. Neither the United States nor the United States Atomic Energy Commission, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness or usefulness of any information, apparatus, product or process disclosed, or represents that its use would not infringe privately-owned rights."