ARMOUR RESEARCH FOUNDATION
of
ILLINOIS INSTITUTE OF TECHNOLOGY
Technology Center
Chicago 16, Illinois

ARF Project No. K6018
Contract No. AT(11-1)-578
Project Agreement 21

STUDIES OF REACTOR CONTAINMENT

ARF Report No. K6018-3
(Bi-Monthly Progress Report)

Contributors: L. E. Anfinson, J. E. Ash, L. H. Botten,
J. B. Eichler, E. V. Gallagher
P. Lieberman, M. Malloy, D. Messmer,
E. J. Murry, L. Slugodski, M. Terra,
and T. A. Zaker

for
THE UNITED STATES ATOMIC ENERGY COMMISSION
Reactor Development Branch
Germantown, Maryland

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency Thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

DISTRIBUTION LIST

Mr. Fred C. Mattmueller, Director
Contracts Division (4)
U. S. Atomic Energy Commission
Chicago Operations Office
9800 S. Cass Ave.
Argonne, Ill.

Mr. S. A. Szawlewicz, Chief
Reactor Safety Branch (4)
Division of Reactor Development
U. S. Atomic Energy Commission
Washington 25, D. C.

Mr. O. T. Brittan (2)
Reactor Engineering Division
Argonne National Laboratory
9700 S. Cass Ave.
Argonne, Ill.

Mr. Donald M. Gardiner, Director
Health and Safety Division
Chicago Operations Office
U. S. Atomic Energy Commission
9800 S. Cass Ave.

Dr. David B. Langmuir, Director
Thompson-Ramo Wooldridge Corp.
P. O. Box 45144, Airport Station
Los Angeles 45, California

Mr. James E. McLaughlin
Radiation Branch
Environmental Sciences Division
New York Operations Office
U. S. Atomic Energy Commission
New York 14, New York

Mr. Warren E. Nyer, Manager
Reactor Projects Branch (SPERT)
Phillips Petroleum Company
P. O. Box 1259
Idaho Falls, Idaho

Dr. Walter R. Wise, Jr.
Air-Ground Ordnance Laboratory
White Oak
Silver Spring, Maryland

Mr. N. B. Botsford
Poulter Laboratories
Stanford Research Institute
Menlo Park, California

Mr. William B. Cottrell
Reactor Division
Oak Ridge National Laboratories
Oak Ridge, Tennessee.

ARMOUR RESEARCH FOUNDATION

Main Files

Report Library

THS/AHW/K files (2)

TAZ, K (6)

NAW, K (8)

TABLE OF CONTENTS

<u>Section</u>	<u>Title</u>	<u>Page</u>
I	INTRODUCTION	1
A	Task No. 1: Crushable Shield Analysis and Design	3
	1. Introduction	3
	2. Computer Program	3
	a. Boundary Conditions	4
	b. Initial Conditions	5
	c. Stress-Volume Relations	5
	d. Stress-Volume Matrix	6
	e. Stress Field	6
	3. Future Plans	10
B	Task No. 2: Shock Impingement Experiments on Crushable Shields	11
	1. Introduction	11
	2. Stress Sensor	11
	3. Unloading Curves	14
	4. Future Plans	15
C	Task No. 3: Coolant Decompression Experiments and Analysis	17
	1. Introduction	17
	2. Summary of Previous Activities	17
	3. Activities During This Report Period	19
	a. Three-Dimensional Driven Chamber	19
	b. Driver Chamber Modification	22
	c. Capacitance Type Spallation Gage	22
	4. Future Plans	25

STUDIES OF REACTOR CONTAINMENT

I. INTRODUCTION

This Bi-Monthly Technical Progress Report is issued by Armour Research Foundation in response to the requirements of Contract No. AT(11-1)-578, Project Agreement 21, under which the work reported herein is conducted .

Work under this project agreement is generally directed toward development of criteria for assessing the safety of nuclear reactors in the event of maloperation of the reactor system. Project Agreement 21 covers problems on the generation of transient loads on containment structures in the event of a violent system excursion or a loss-of-coolant accident, and on the transmission and attenuation of disturbances through configurations of material surrounding the source. Under a concurrent program, covered by Project Agreement 22, other aspects of the reactor safety problem are being studied. These include the properties and responses of containment structures subjected to transient loads from system maloperation. The two programs are complementary, and work performed under the latter is reported concurrently in a separate series of bi-monthly progress reports.

The work covered by Project Agreement 21 is divided into three tasks, the titles and specific objectives of which are given as follows:

Task No. 1: Crushable Shield Analysis and Design

1. Preparation of digital computer codes for calculation of wave transmission in layered composites of materials, and performance of calculations for representative systems.

2. Code optimization and modification to include the effect of support structure response.

Task No. 2: Shock Impingement Experiments on Crushable Shields

1. Performance of gas shock impingement experiments on six basic crushable materials to obtain relevant stress-density relations in uniaxial strain.

2. Performance of experiments on artificial materials and layered systems in connection with the work of Task No. 1.

Task No. 3: Coolant Decompression Experiments and Analysis

1. Analysis of previously obtained experimental data using a liquid-driven shock tube.

ARMOUR RESEARCH FOUNDATION OF ILLINOIS INSTITUTE OF TECHNOLOGY

2. Extension of capabilities to simulate coolant conditions of 600°F and 1500 psi, and with increased driven chamber dimensions for the study of three-dimensional effects.

3. Investigation of the phenomena of close-in shock and jet impingement on a containment wall.

A. Task No. 1: Crushable Shield Analysis and Design

1. Introduction

During this report period, emphasis was placed on the completion of a computer program for the solution to propagation of stress waves generated in a one-dimensional, homogeneous material subjected to an impulse loading. This computer program can handle a limited number of blast wave forms and only a single layered material where the material is characterized by a simple, linear piece-wise equation of state. This program, known as the "preliminary" program, is capable of treating problems that occur in the shock tube tests of Task 2, and will be able to establish preliminary trends for the design of blast shields.

The computer program for the solution to propagation of stress waves in a one-dimensional, multi-layered material subjected to complex pressure-time inputs will be used to obtain detail design criteria for the design of blast shields. This computer program, known as the "generalized" program, was placed on a lesser priority basis until the "preliminary" program is completed in its entirety.

2. Computer Program

The last two bi-monthly progress reports described the basic flow diagram of the "preliminary" program, and the test cases designed to be used in the checking out of this program. This progress report will describe in detail the logic used in the solution of the stress field in the interior of the impacted solid. The detail discussion is necessary since persons skilled in wave interaction solutions often treat interior interaction problems with ease because of intuitive judgements whereas a computer must be constantly directed by decisions based upon comparisons with input data

and/or results as they become available from various computations. Consequently, many decision making comparisons had to be devised in order to have the computer solve wave interaction problems. The following section will show how the computer will solve a typical wave interaction problem. The solution can be described in terms of the given boundary conditions, initial conditions; and equation of state of the impacted material. The solution required the determination of the stress field in the media at each instant of time.

a. Boundary Conditions

The one-dimensional but finite length impacted solid, contains two boundary conditions. First is the boundary at the end of the impacted solid where the loading is applied. Second is the boundary at the other end of the impacted solid where the solid is supported.

At the loading end, the pressure-time history is specified. Actually, the stress wave oscillations within the solid interact with the boundary condition, but the interaction is too weak to modify the given boundary condition. This assumption is especially true of the usual physical arrangement of the applied loading boundary which is an air/solid interface with a very high mechanical impedance mismatch that does not permit the transmission to wave motion.

At the support end, the particle velocity versus time history is specified for certain conditions, and stress versus time history is specified for the remainder of the conditions. This mixed boundary condition is introduced to permit spallation. The zero particle velocity is required at the support because it is given that the support is rigid. The negative particle velocity appears when the junction between the impacted solid and the support tends

toward a tensile load, so that under these conditions a zero stress condition is established as the impacted solid separates from the support. Thus the boundary condition is specified as being $U = 0$ for $\sigma > 0$, or $U \leq 0$ for $\sigma = 0$.

b. Initial Conditions

The given initial conditions are the equations of state of the propagating medium, the length of the medium, and the density of the medium.

The magnitude of the peak pressure of the applied loading compared to the Hugoniot elastic limit determines the types of wave motion excited at impact. The length of the medium as compared to the wave length of the transmitted blast wave determines the attenuation or magnification of the magnitude of the peak reflected stress at the rigid support.

c. Stress-Volume Relations

The stress-volume relation for any material can be approximated by a continuous series of straight line segments. For an elastic material there is a single straight line segment for both the loading and unloading paths. For a plastic material, there are different straight line segments for the loading and unloading paths. The preliminary program accepts a stress-volume relation consisting of ten lines segments.

For elastic materials the solution to wave propagation problems is considerably simplified because of the maximum of one left-running and a maximum of one right-running wave are produced after each interaction. This is true since in the Lagrangian wave diagram, the incident waves continue without refraction after passage through the interaction point. The reason for this is that all the "jump" condition equations across the wave fronts simplify in a manner such that the stress in the newly formed regions can be calculated directly from the known stresses, and the particle

velocity in the newly formed regions can be independently calculated directly from the known particle velocities.

For plastic materials, the complexity of the solution to wave propagation problem appears in (a) the possibility of multiple left-running waves radiating from the point of interaction in the wave-diagram, (b) in the possibility of refraction of the incident waves after passage through the interaction point, and (c) in the cumbersome solution for the stress and particle velocity for a newly formed region in the wave diagram.

d. Stress-Volume Matrix

A scheme was developed for the use of the stress-volume relation in wave interaction problems so that the logic section of the program, the bookkeeping, and flow charting of the computer logic would be simplified. The scheme is a system of listing the stress and associated volume states along the Hugoniot in a matrix notation. The listed stress-volume points are the end points of each straight line segments of the segmented stress-volume relation and those points which are formed by the intersection of the projected line segments and the stress-volume relation. The listing is in order of the stress magnitudes where the listing contains both "points" and "intercepts". For an example of a stress-volume diagram which produces a 16 x 16 matrix, see Fig. A-1 of Progress Report No. 2.

e. Stress Field

The stress field in the interior of an impacted solid is a result of separate interactions, where each interaction is treated by the same calculation scheme. The stress field shows these interactions in their proper position and time sequence so that the correct wave combinations are treated together.

The over-all solution is obtained by the interaction of pairs of waves, and by the consideration of their separate resultant stresses and particle velocities. Hence, let us consider the detailed treatment of an interaction between a pair of compression waves, and show the solution process in the form of the computer solution process. The pair of compression waves are taken to be composed of one left-running and one right-running wave, as shown below:

The constant state region on the left is designated as -1 ; on the right by $+1$. The region in the middle disappears after the interaction, and it is designated by 0 . Parameters associated with each region are designated by $+1$, -1 , or 0 where these symbols appear as subscripts.

The given stress-volume relation for the sample problem is given in Fig. A-1. Note that the stress-volume matrix would contain the points 0 through 7 and the intercepts A and B . Also given are the values of P_{+1} , P_{-1} , U_{+1} , and U_{-1} ; with these given states shown in Fig. A-1. The problem is to find the value of the resultant stress, P_R , of the newly formed constant state region.

An estimate of the stress magnitude of the newly formed region, R , is obtained by first noting that for different ranges of the estimate stress P_R , different calculations schemes will be required. Thus it is

ARMOUR RESEARCH FOUNDATION OF ILLINOIS INSTITUTE OF TECHNOLOGY

necessary to establish the stress bounds for P_R for which the calculation scheme changes. Referring to Fig. A-1, the four bounds of P_R would be $P_R < 0$, $P_R \leq P_{+1}$, $P_{+1} < P_R \leq P_{-1}$, and $P_R > P_{-1}$.

The first boundary tests for $P_R < 0$. Assuming that the material can not withstand a tensile load, if $P_R < 0$ a spall occurs. In the preliminary computer program, the program is brought to a halt if $P_R < 0$. In the generalized computer program, the computer keeps track of the wave motion in the main body of the material as well as the spalled section.

The second boundary tests for $P_R \leq P_{+1}$. Since linear and parallel unloading lines are assumed for the hysteresis zone under the Hugoniot in the stress-volume relation, the second boundary shows that a simple computational scheme can be used. Namely, a single leftward moving unloading wave and a single rightward moving unloading wave is generated. The value of the stress in the newly formed region is determined just as is done in the simple case of the wave motion in elastic substances.

The third boundary tests for $P_{+1} < P_R \leq P_{-1}$. In this case a single leftward moving unloading wave moves into region +1, because of the assumed linear unloading paths in the hysteresis zone of the stress-volume relation. However, the stress-volume matrix must be consulted in order to determine the number of rightward moving loading waves. The first estimate of P_R is such that $P_R = P_1$. Such that there would be a single left and a single right running wave. Across these two waves, the particle velocity U_{R_LEFT} is compared to U_{R_RIGHT} . A mismatch of U_{R_L} and U_{R_R} would require a second estimate of $P_R = P_2$, and that there be two right running waves with a constant state region associated with the properties of state point 1.

The mismatch of U_{R_L} across $0 - (-1)$, and $(-1) - (R)$ with U_{R_R} across $0 - (+1)$, $(+1) - (1)$, and $(1) - (R)$, is again compared. If the mismatch is in the same direction as before then P_R is assumed equal to P_{-1} , and three right-running waves need be formed. But if the mismatch in U_{R_L} and U_{R_R} is in a different direction, the value of P_R must lie between P_1 , and P_2 , and where P_R lies on a linear stress-volume relation connecting P_1 and P_2 .

It may be noted here that as constant state regions are introduced at P_1 and P_2 , tests are made on the intercept points A and B respectively to insure that the constant state regions do actually exist. If, however, P_R is found to be $> P_A$, it can be shown that no constant state regions at P_1 can be introduced.

The fourth boundary tests for $P_R > P_{-1}$. In this case there is the possibility of multiple left- and rightward moving waves. In this case the estimate of P_R is taken as P_3 . Point 3 is used because it permits a convenient test of the magnitude of P_R from a known point on the stress volume diagram. The wave motion for such a case is shown below. Next, point 4 is used as an estimate for P_R , and the stress-volume matrix indicates the leftward moving wave and three rightward moving waves.

This process continues with the testing of point 5 where the comparison between U_{R_L} and U_{R_R} reverses its trend. The value of P_R is then determined by iteration since $P_4 < P_R < P_5$ where P_5 and P_4 are connected by a linear stress-volume relation.

Note that the first three boundary tests include the automatic introduction of a strain discontinuity which radiates vertically from the interaction point in the Lagrangian wave diagram, while the fourth boundary test does not introduce any strain discontinuity.

To date, the Univac 1105 has been very successful with the preliminary program. To date approximately seven various types of interactions have been completed on the machine including both boundary condition problems and interior waves interaction problems. In addition, the complete series of flow diagrams have been made of the program as it now stands enabling quick location of any particular trouble spots.

3. Future Plans

Sample problems such as those described in previous bi-monthly progress reports will now be used in the debugging procedure. At the same time actual shock tube data from Task 2 will be fed to the computer for actual-case problems.

In addition, during the next report period it is expected to complete or nearly complete the writing of the final report covering activities of Task 1 during the year covering 1962 which will deal mainly with the preliminary computer program.

B. Task No. 2: Shock Impingement Experiments on Crushable Shields

1. Introduction

During this report period, the experimental effort has been devoted to the development of the stress sensor; and the analytical effort to the development of a data reduction technique for the determination of unloading isentropes. The development of the stress sensor consisted of investigating the influence of sensor mechanical composition on sensor electrical performance. The electrical performance consisted of designing the mechanical mixture of the sensor constituents so as to obtain a given initial electrical resistance, and also to obtain a piezo-resistive effect which is useful for the expected pressure range of an impact test. The selection of mechanical properties of the sensor constituents in order to obtain a given initial electrical has been completed; however, the dynamic and quantitative evaluation of the piezo-resistive effect has not been completed. The main reason for the slow calibration of the dynamic piezo-resistive effect is that the sensor performance is not completely reproducible from one impact test to the next. The slow calibration process has been the cause for the delay in the determination of the complete pressure-volume relations for balsa wood.

An analysis was undertaken for the determination of the type of data and experimental arrangement required for balsa wood in order to specify the unloading paths from different points on its Hugoniot in the pressure-volume plane.

2. Stress Sensor

The wafer-type sensor, used for the determination of the unloading isentropes of balsa, consisted of a homogeneous suspension of tellurium particles in a matrix of bakelite pressed into a thin disk, both faces of which

were subsequently coated with a silver film by vapor deposition in a vacuum chamber. The initial electrical resistance of the wafer was an important variable which was dictated by the circuit design and the terminal resistor associated with the electrical transmission line impedance. Usually, the wafer was required to have an initial resistance in the neighborhood of 50 ohms. The initial resistance of the sensors was strongly dependent upon the particle size of the tellurium, the particle size of the bakelite before it was thermally set in a press, and the relative weights of tellurium and bakelite. Using Fig. B-1 it was possible to select these three variables to meet the specifications of the required initial electrical resistance of the wafer. The reproducibility of the initial electrical resistance of the wafers are shown in Fig. B-2, where the variations were probably due to the inhomogeneity of the mixture caused by insufficient mixing of the two constituents.

The effects of tellurium particle size, bakelite particle size and weight ratio upon the $\Delta R_G / R_{G_0}$ versus p plot has not yet been determined at this time. These three variables need to be adjusted so that the maximum sensor sensitivity, $\left(\frac{\Delta R_G / R_{G_0}}{P} \right)_{\text{maximum}}$, should be obtained in the test pressure range of interest.

In Fig. B-3 of the bi-monthly Progress Report No. 2, the tellurium-bakelite sensor loading and unloading paths in the pressure-voltage chart were shown. The unloading and reloading paths were coincident in the sensor reported in the Progress Report No. 2. However, in this report period, the sensor performed so that the unloading and reloading paths did not coincide for a given impact. Furthermore, if the impact was exactly duplicated, the unloading and reloading paths translated as a group, away from the results obtained from the early impact data results. But in spite of this inadequacy.

the waveform and associated time differences were accurate, as can be seen from the initial and repeated runs in Fig. B-3. Some of this amplitude change would seem to be caused by the plastic set and creep characteristics of the wafer whose matrix contained bakelite, as evidenced by the change in wafer initial electrical resistance after each shock loading.

A detailed discussion of the stress sensor performance in terms of responding to the stress wave forms as they were generated within a shock tube, can be treated according to whether fast transients or slow transients are being considered. The fast transients are associated with the stress waves that reverberated within the bakelite holder as shown in Fig. B-4. The stress sensor close to the gas was exposed to short duration stress spikes which were too short in duration to appear in the data records of station S-2, while a stress sensor located at a distance from the gas was exposed to longer duration stress spikes which did appear in the data records of station KE.

The slow transient effects are associated with the long period pressure waves which reverberated within the shock tube as shown in Fig. B-5. The pressure-time history at the end of the shock tube had wave forms which had a sharp rise to constant pressure magnitude and then a slow decay in pressure magnitude thereafter. The process was periodic but affected by attenuation. Each sharp rise in gas pressure resulted in a jump to a shock compression state in the sensor; while each slow decay in gas pressure resulted in an isentropic unloading path in the sensor pressure-voltage chart. The piezo-resistive performance during the repeated impacts on the sensor by shock waves of progressively smaller pressure magnitudes is shown in the pressure-voltage chart of Fig. B-6. The loading lines are shown solid

and the unloading lines as dashed. Note that loading lines are parallel to reloading lines, and unloading lines are parallel to subsequent unloading lines in a pressure-voltage chart which has linear scales. Thus, for a wide range of impact pressures, the respective loading and unloading sensor sensitivities $\left(\frac{\Delta R_G}{R_{G_0}} / P\right)$ remain approximately constant. Thus, if a peak pressure data point was available from a conventional type of gage located in the adjacent gas, the developed sensor would have been able to give complete quantitative stress magnitudes throughout the entire stress wave form in the interior of the solid.

Analysis of the sensor data reduction process for the determination of the unloading isentrope showed that the exact arrival times of various waves and only approximate waveforms are adequate, if the initial stresses of the specimen are known accurately from the shock tube instrumentation; thus, with the determination of the sensitivities and sufficient other data, the unloading isentropes can be determined.

One serious problem encountered in the use of the sensor in the shock tube has been the shearing of electrical lead wires caused by the relative movement of the particles of wood with reference to the stationary steel container walls of the shock tube, since the wires must be fed from the wood through the shock tube walls. Because the data of the sensor was required throughout the movement of the shock-compressed wood, the breakage of leads imposed a handicap which must be overcome.

3. Unloading Curves

The determination of the unloading curves from different points on the Hugoniot as shown in the following diagram, requires the measurement of several quantities. A method of computation has been devised for the

UNIVAC 1105 rapid determination of the pressure, specific volume ratio, shock velocity, particle velocity and the other pertinent quantities required for the determination of the unloading curve in the p-v diagram.

The character of the unloading portion of the stress-time history obtained experimentally at some point in the solid determines qualitatively whether the unloading isentrope is convex ($AB'C$) or concave ($AB''C$) to the pressure axis. Computations based on the measured values of unloading wave velocity and pressure determine the specific volumes at points B and C on the assumption of straight line segments joining A and B , and B and C . Comparing the qualitative character of the unloading history with the computed results provides a check on this point.

4. Future Plans

The tests for the reproducibility of the sensor piezo-resistive properties will be concluded during the next report period and these tests will be performed more rapidly than in the past because of the introduction of a new sensor holder which will permit the simultaneous testing of three sensors as compared to the existing holder which permitted the testing of one sensor at a time. The tests on the complete equation of state of balsa will start during the next report period.

Sensor charts of pressure versus electrical-resistance will be accumulated from a multitude of tests, and then a sensor design will be selected during the next report period. A large group of sensors will be manufactured according to the selected design, and they will furnish the supply of sensors that will be used in the forthcoming balsa tests.

In the final report period final dynamic pressure-volume relations will be developed for balsa wood based on the experiments which have been performed. Test series have been designed for redwood, sugar pine, celotex, styrofoam, and foamglass for the determinations of complete dynamic pressure-volume data for these materials with instrumentation as described in this and preceding reports of this series.

Sensor behavior will be investigated in somewhat greater detail to ascertain the cause of the sensitivity of electrical properties to variations in composition. The calibrations described herein will be used to reduce data from the forthcoming shock tube experiments for the determination of Hugoniot curves and unloading characteristics.

C. Task No. 3: Coolant Decompression Experiments and Analysis

1. Introduction

This task is concerned with obtaining experimental data on the decompression of pressurized heated water.

The problem of explosive decompression of water has arisen in connection with the safety aspects of water cooled reactors. Coolant water, under high temperature and pressure, will undergo a sudden drop in pressure, and temperature after rupture of a pipe line or a portion of the reactor vessel wall. The rate of change of pressure and temperature will depend on the size of the rupture and the volume of the vessel. The aim of Task 3 is to study the phenomena associated with the transient phase of decompression and external flow where pressure, temperature, velocity, etc., may change very rapidly and have sizeable gradients, such that localized conditions can be significantly different from the average conditions. For these conditions the detailed phenomenon is not necessarily explainable in terms of equilibrium or steady state behavior since it represents a dynamic disturbance from an initial equilibrium state. The purpose of this task is to gain an understanding of the transient phenomena sufficient to predict corresponding effects in prototype reactor systems.

2. Summary of Previous Activities

The aims of work on Task 3 during the current contract period were outlined in ARF Proposal No. 62-616D. Very briefly these aims consist of:

- (a) analysis of previously obtained data
- (b) construction of analytical models, and
- (c) development of additional experiments which would:

- (i) extend the range of initial conditions to about 635°F,
- (ii) treat three dimensional effects in the driven chamber, and
- (iii) study close-in jet impingement.

During the first two months of the current contract period the analysis of previously obtained data was completed but it became clear that the formulation of analytical models could not be completed until additional experimental data was obtained and analyzed. The results were expressed in the form of a graphical relationship between first maximum pressure rise and the temperature (which is effectively a measure of the energy) in the driver chamber. In order to satisfy the additional aims it was necessary to design and construct a new test apparatus.

A new driven chamber capable of withstanding uniform pressures in excess of 2000 psi was designed and fabricated. An enlarged receiver vessel having a diameter of three feet and a length of about four feet was designed and submitted to several pressure vessel fabricators for cost estimates. The vessel design included allowances for a 500 psi shock of 5 milliseconds duration, a movable plate for studying impingement of shocks or water jet, and a porthole for the intended purpose of observing the contact surface by means of either high speed photography or x-ray attenuation. Some initial design work had been done on a gage to study spallation of water which is believed to have occurred at the closed end of the driver chamber in some previous experiments. Various methods (including the use of glass wool packing) had been considered for decreasing the strength of the reflected rarefaction wave. The activity on both the detailed design of experiments and modification of apparatus was interrupted temporarily to facilitate increased personnel commitment to Task 2 and simultaneously

permit more detailed investigation of the apparatus design requirements in terms of anticipated performance limitations and degree of simulation of prototype conditions.

3. Activities During This Report Period

The activities performed during this report period include an investigation of the apparatus design which resulted in a number of modifications. Included in these modifications were the addition of a porthole just upstream of the diaphragm flange in the driver chamber, and selection of a different, less costly, vessel design for the driven chamber. Consideration of the capacitance type spallation gage was continued, and a new commercially available pressure sensor, which appears to withstand high temperatures better than the Kistler piezoelectric sensor has been located. The use of several variations in length and diameter of the driven chamber for the purpose of studying three-dimensional effects has been abandoned for the time being, in favor of studying only a single large diameter. No experiments were conducted during this period.

a. Three-Dimensional Driven Chamber

Bids were received from a few vessel fabricators for the previously designed three-dimensional driven chamber. The bids ranged from \$2,980 to \$3,254. The main expense in these bids was associated with the design requirement for possible short-duration shock waves of up to 500 psi. Since the resultant static equilibrium pressure will always be well below 50 psi for the intended initial driver conditions, and since the 500 psi shock waves will probably not occur in the three-dimensional vessel for any of the experiments planned, it has been decided to modify a 150 psi vessel which is locally available from stock at a cost of about \$300. The estimate of 500 psi shock waves was based on an extrapolation of one-

ARMOUR RESEARCH FOUNDATION OF ILLINOIS INSTITUTE OF TECHNOLOGY

dimensional data to a higher temperature; however, since three-dimensional expansion of the shock wave will occur in this case, and since we will run initial experiments with relatively low initial driver conditions, we will be able to safely avoid the possibility of developing unduly high shock wave pressures within the tank. The necessary vessel modifications will be made in the ARF machine shop.

The vessel will provide a means of checking the magnitude of possible shock waves after a three-dimensional expansion. Earlier plans called for a detailed determination of effects on shock wave magnitude of variations of both length and diameter of the driven chamber. Now, after reviewing the apparatus design requirements, with consideration of the application of the results to prototype reactors, it appears that a thorough understanding of shock wave strength versus diameter or length of the driven chamber will not be too important especially if it should later be found that only negligible shock wave effects are observed in the current study only a few feet away from the end of the driver outlet. For this reason it is more desirable simply to determine the magnitude of the shock wave in a single vessel of relatively large size, as a function of distance from the source. This can then be compared to existing data on expansion-weakening of a diverging shock wave produced by other sources, such as explosives or compressed gas. However, if the shock wave in the driven chamber, although reduced in strength due to its divergence in the vessel, is not of negligible strength, then, considering practical application of the results, a detailed understanding of the relationship between shock wave strength and the variations in dimensions of the expansion chamber would probably be necessary. The dimension-dependent experiments can easily and quickly be done with very little modification of the present apparatus.

ARMOUR RESEARCH FOUNDATION OF ILLINOIS INSTITUTE OF TECHNOLOGY

One of the primary reasons that the prior apparatus was not designed for the higher temperature and pressure working conditions for which we are now building apparatus is the inability of piezoelectric pressure transducers to withstand a sustained high-temperature environment. After an exhaustive search we have located a bonded strain gage pressure transducer manufactured by Advanced Technology Laboratories. This transducer isolates the working fluid from the active gage elements by means of a catenary diaphragm and provides for either air or water cooling. The temperatures we will be using are well within the design range of this gage. We have ordered one transducer on a trial basis in order to evaluate response time and pressure sensitivity under our experimental conditions.

One of the primary purposes of the plate impingement study is to find the mechanical loading effects of the ejected water column on a shell or very large plate. Any backloading due to flow around the plate, as shown in (a), will reduce the magnitude of the experimental loading.

We will attach baffle plates as shown in (b) in one of the very early experiments in order to determine whether study of the small plate alone could cause us to seriously underestimate the magnitude of the mechanical loading effect.

The layout of the new driven chamber is shown in Fig. C-1.

b. Driver Chamber Modification

The design of a porthole to accommodate high-speed photographic viewing in the region just upstream of the diaphragm has been completed. Actually two ports are provided, one for the camera and one for a light source. The shop modifications for this design should be completed shortly. A diagram of the design of this porthole is shown in Fig. C-2. For test runs which will use no photographic instrumentation in the driver chamber, the portholes will be fitted with contoured plugs.

A review of the design of the driver chamber indicated that high longitudinal thermal gradients and the associated thermal stresses might be developed. To avoid this condition, while still allowing for rapid heating of the water, a special heat conductive layer of material will be placed between the external heating coils and the outside surface of the driver chamber.

c. Capacitance Type Spallation Gage

Early in the present contract period, some attention was given to the feasibility of using a variable capacitance gage, with the fluid in the driver section used as a variable dielectric, to measure the extent of spallation which occurs at the closed end of the driver section upon the arrival of the initial expansion wave. The occurrence of spallation has been indicated by theory and tentatively confirmed by previous pressure-time

measurements. However, the actual distance through which the liquid contact surface moves is not presently known. During the current report period some additional consideration has been given to the measurement of spallation distance in terms of change in the dielectric constant of the fluid in the region near the closed end of the driver section. Although this effort has been very limited, it still appears that the simple technique described below is feasible.

Gage operation is dependent on the fundamental relationship between the charge on a capacitor, q ; the capacitance, c ; and the voltage appearing across the capacitor, v ; given by the equation:

$$q = cv.$$

If a capacitor is constructed of short thin-walled concentric cylinders and mounted rigidly to the end of the driver section, then when spallation occurs the average dielectric constant of the capacitor dielectric will decrease (the dielectric, initially pure water, becomes a mixture of low pressure water vapor and pure water) causing a decrease in capacitance. If the capacitor is part of the circuit shown below, then at any time a sudden decrease in capacitance occurs, an increase of voltage will be detected by the oscilloscope.

By making the time constant of the whole circuit very long the charge on the capacitor is effectively constant, a voltage record, such as the one shown below, may be used to establish the magnitude of spallation.

We assume that the mixture mentioned above has a distinct interface which is maintained throughout the time of interest. We further must assume that this interface remains approximately plane parallel to the end of the driver section. We are interested in finding the average length of the vapor region produced by spallation. By using well-known equations we may derive the following relation from which the length of the spallation region, λ , is easily found:

$$\lambda = \frac{(\Delta V) L K_w}{(K_w - 1)(V_i + \Delta V)},$$

where,

ΔV is the change in voltage recorded on the oscilloscope record,

V_i is the initial known voltage across the gage,

L is the length of the cylinders making up the capacitor, and

K_w is the dielectric constant of water under initial driver conditions.

The value of the dielectric constant of water, K_w , is a function of temperature and may be calculated from the formula below for any particular temperature, $T(^{\circ}\text{C})$:

$$K_w = (5.321 \times 10^3) T^{-1} + 2.3376 \times 10^2 - (9.297 \times 10^{-1}) T + (1.417 \times 10^{-3}) T^2 - (8.292 \times 10^{-7}) T^3,$$

for any temperature between 100°C and 370°C (i. e. , 212°F and 698°F). In the present design the length of each cylinder is 1.5 centimeters, and the initial voltage across the gage is 45 volts.

Some limited future work will be needed before the gage can be used in experiments. A satisfactory method of calibration must be developed (X-ray photography may be adequate). The gage should at least detect the presence of, and the approximate length of, the region of spallation. Furthermore, the actual time variation of the spallation distance may be obtained by making the time constant of the system sufficiently large. If for any reason the circuit cannot be built with a large enough time constant, then the time variation may still be obtained from transient analysis of the circuit.

4. Future Plans

We expect to have our complete experimental apparatus in operation within the next report period. It is also expected that we will have begun the series of experiments and finished analysis of completed trials.

Respectfully submitted,

P. Lieberman
Project Engineer

Fig. A-1. STRESS VERSUS SPECIFIC VOLUME

Fig. B-1a. EFFECT OF TELLURIUM PARTICLE SIZE UPON THE RESISTANCE OF THE TELLURIUM BAKELITE SENSOR

Fig. B-2a. THE REPRODUCIBILITY OF INITIAL RESISTANCE FOR IDENTICALLY CONSTRUCTED TELLURIUM-BAKELITE SENSORS

Fig. B-3, a1: Initial Run

Fig. B-3, a2: Repeated Run

Fig. B-3a. THE REPRODUCIBILITY OF THE SENSOR WAVEFORM

Fig. B-1b. EFFECT OF BAKELITE PARTICLE SIZE UPON THE
RENSTANCE OF THE TELLURIUM-BAKELITE SENSOR

Fig. B-2b. THE REPRODUCIBILITY OF INITIAL RESISTANCE FOR IDENTICALLY CONSTRUCTED TELLURIUM-BAKELITE SENSORS

Fig. B-3, b1: Initial Run

Fig. B-3, b2: Repeated Run

Fig. B-3b. THE REPRODUCIBILITY OF THE SENSOR WAVEFORM

Fig. B-4. THE EFFECTS OF THE FAST TRANSIENTS IN THE BAKELITE HOLDER

a) Physical Setup and Wave Diagram of Shock Tube

b) Theoretical Pressure-Time Histories

Fig. B-5. THE EFFECTS OF THE SLOW TRANSIENTS OF THE SHOCK TUBE

Fig. B-6. LOADING AND SLOW TRANSIENT UNLOADING PATHS
OF STRESS SENSOR IN THE PRESSURE-VOLTAGE PLANE

Fig. C-1. THREE-DIMENSIONAL CASE DRIVEN SECTION

Fig. C-2. CAMERA AND LIGHT PORT DETAIL

Fig. C-3. IMPINGEMENT PLATE HOLDER