40

9-25-64

UNCLASSIFIED

DEFENSE INFORMATION

~~CONFIDENTIAL~~

This document contains information affecting the National Defense of the United States within the meaning of the Espionage Laws, Title 18, U.S.C., Sections 793 and 794, the transmission or revelation of which in any manner to an unauthorized person is prohibited by law.

WASH

MARTIN COMPANY
NUCLEAR DIVISION

MARTIN
MARIETTA

UNCLASSIFIED

~~CONFIDENTIAL~~

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency Thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

~~CONFIDENTIAL~~

0000000000
UNCLASSIFIED

SPECIAL REVIEW FINAL DETERMINATION	Reviewed	Class.	Date
	TR	U	12-21-81
Class: <u>U</u>			

Distribution:
C92A

ADVANCED SR-90
SPACE POWER SUPPLY
STUDY

August 1964

MND-3393

UNCLASSIFIED

OK CH:

BY AUTHORITY OF D.O.C

BY L. Tomper DATE 11/2/71

Approved by:

Martin R. Scheve
Program Manager

EXCLUDED FROM AUTOMATIC RE-
GRADING: DOD DIR 5200.10 DOES
NOT APPLY

NOTICE

This report was prepared as an account of work sponsored by the United States Government. Neither the United States nor the United States Atomic Energy Commission, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness or usefulness of any information, apparatus, product or process disclosed, or represents that its use would not infringe privately owned rights.

~~DEFENSE
INFORMATION~~

This document contains information affecting the National Defense of the United States within the meaning of the Espionage Laws, Title 18, U.S.C., Sections 793 and 794, the transmission or revelation of which in any manner to an unauthorized person is prohibited by law.

MARTIN **MARTIN**
MARIETTA

NUCLEAR DIVISION Baltimore 3, Maryland

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

~~CONFIDENTIAL~~

UNCLASSIFIED

GG

DECLASSIFIED

LEGAL NOTICE

This report was prepared as an account of Government sponsored work. Neither the United States, nor the Commission, nor any person acting on behalf of the Commission:

A. Makes any warranty or representation, expressed or implied, with respect to the accuracy, completeness, or usefulness of the information contained in this report, or that the use of any information, apparatus, method, or process disclosed in this report may not infringe privately owned rights; or

B. Assumes any liabilities with respect to the use of, or for damages resulting from the use of any information, apparatus, method, or process disclosed in this report.

As used in the above, "person acting on behalf of the Commission" includes any employee or contractor of the Commission, or employee of such contractor, to the extent that such employee or contractor of the Commission, or employee of such contractor prepares, disseminates, or provides access to, any information pursuant to his employment or contract with the Commission, or his employment with such contractor.

DECLASSIFIED
MIN 3393

FOREWORD

The results of a study on two Advanced (250-watt) Strontium-90 Space Power Supplies are presented in this series of reports. The study was performed for the U.S. Atomic Energy Commission by the Nuclear Division of the Martin Company under Contract AT(30-1)-3393. The work was sponsored by the Division of Reactor Development, Isotopic Power Branch in keeping with its responsibility for the development of isotopic power systems for space missions of established or possible interest to the National Aeronautics and Space Administration, (NASA) and the Department of Defense (DOD).

The complete results of the systems studied are presented in three volumes, as follows:

MND-3393--Advanced Sr-90 Space Power Supply Study

MND-3393-1--Development Program, Advanced Sr-90 Space
Power Supply--Dynamic System

MND-3393-2--Development Program, Advanced Sr-90 Space
Power Supply--Static System

~~DECLASSIFIED~~

~~CONFIDENTIAL~~

BLANK

~~CONFIDENTIAL~~

~~DECLASSIFIED~~

MND 3393

CONFIDENTIAL

v

CONTENTS

	Page
Legal Notice	ii
Foreword	iii
Contents	v
I. Introduction and Summary	I-1
II. Applications and Design Criteria	II-1
A. System Application Criteria	II-1
B. Power System Design Criteria	II-2
III. Dynamic System	III-1
A. General	III-1
B. Description of Components	III-3
C. System Performance and Optimization	III-31
D. Dynamic System Reliability	III-45
E. References	III-65
IV. Static Generator System	IV-1
A. General	IV-1
B. Description of Components	IV-1
C. System Performance and Optimization	IV-11
D. Static System Reliability	IV-27
V. Shielding	V-1
A. Shielding Philosophy and Design Criteria	V-1
B. Shielding Requirements	V-2
C. Shielding Analysis Method	V-2

CONFIDENTIAL

MND-3393

~~CONFIDENTIAL~~
CONFIDENTIAL

CONTENTS (continued)

	Page
VI. Ground Handling Equipment	VI-1
A. General	VI-1
B. System Criteria	VI-2
C. Selected System	VI-7
Appendix A--Thermoelectric Analysis	A-1
Appendix B--Dynamic System Radiator Area and Temperature Parametric Study	B-1
Appendix C--Radiator Parametric Study Coolant Comparison	C-1
Appendix D--Coolant System Parametric Study	D-1
Appendix E--Dynamic System Radiator Armor Requirements	E-1
Appendix F--Dynamic System Temperature Distribution and Thermal Loss	F-1
Appendix G--Dynamic System Performance Calculations	G-1
Appendix H--Dynamic System Temperature Distributions After Cooling System Failure on the Launch Pad	H-1
Appendix I--Static System Radiator Optimization	I-1
Appendix J--Static System Temperature Distributions	J-1
Appendix K--Static System Thermal Losses	K-1
Appendix L--Static System Performance Calculations	L-1
Appendix M--Fuel Handling System Interface and Equipment Specifications	M-1
Appendix N--SNAP 17A Impact Test Program	N-1

~~CONFIDENTIAL~~
CONFIDENTIAL

MND-8393

~~CONFIDENTIAL~~
CONFIDENTIAL

CONTENTS (continued)

	Page
Appendix O--Shock Overpressure and Thermal Effects of Fireball	O-1
Appendix P--Description of Vehicle and Assumed Trajec- tory	P-1
Appendix Q--General Safety	Q-1

DECLASSIFIED

~~CONFIDENTIAL~~

BLANK

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

~~CONFIDENTIAL~~

0115087030

I-1

I. INTRODUCTION AND SUMMARY

The Martin Company has studied two different systems, for the Advanced Sr-90 Space Power Supply, each of which offers significant advantages with respect to weight, size and potential depending upon the particular spacecraft application. These advantages are available without sacrificing either reliability or safety--two features which have always been essential in the AEC SNAP programs.

Both power systems, while major advances in themselves, will not require major development expenditures. All development objectives are clearly attainable at a modest cost within a suggested 30-month span. Each technological advance required is a logical progression in isotopic power system design, and has, as a solid base, the knowledge gained by the Martin Company from prior SNAP programs of the AEC.

The two systems are the dynamic and static systems, respectively, as referenced to their waste heat rejection subsystems. One system rejects its waste heat to space by means of a dynamic coolant loop transferring heat to the vehicle skin as depicted in Fig. I-1. The other system, Fig. I-2, uses a static radiator configuration utilizing the surface of the power supply itself and auxiliary fins to reject its waste heat by radiation to space.

In both systems, heat is produced by decay of the radioisotope Sr-90 in the fluoride form. The fuel is encapsulated into hemispherically ended cylinders. These capsules are placed in pairs, forming a rectangular parallelepiped heat source. By placing two thermoelectric modules adjacent to the two major surface areas of the heat source, the heat is converted directly to electricity by solid state thermoelectric elements.

Each module contains thermoelectric couples paired in parallel, which, in turn, form series connections. The parallel pairs provide the redundancy required for high reliability, and the series connections enable a single module to produce seven volts dc. The two modules in each generator are then connected in series with a converter-regulator to produce 250 watts(e) net at 28 volts dc.

The dynamic system utilizes a sealed, thermoelectric module with segmented telluride thermoelements, operating between 1000° to 240° F, and a coolant chamber at the cold end. The unconverted heat is transferred from the module by means of water, propelled by redundant pumps, circulating through the coolant loop to the remote radiator. The radiator consists of tubes brazed to the skin of the vehicle.

The static system utilizes silicon germanium alloy thermocouples brazed to a module base plate which serves as the basic waste heat

~~CONFIDENTIAL~~

MND-3893

0115087030

Fig. I-1. Artists' Concept of Dynamic System

~~CONFIDENTIAL~~DECLASSIFIED
MND-3393

Fig. I-2. Artists' Concept of Static System

~~CONFIDENTIAL~~
~~CONFIDENTIAL~~
~~CONFIDENTIAL~~

rejection system. Attached to the edges of each module plate are fins which provide the additional necessary radiator area.

A summary of the performance of the two systems is presented in Table I-1.

TABLE I-1
 Performance Summary
 (all values for five-year design point except as noted)

	<u>Generators</u>	
	<u>Dynamic</u>	<u>Static</u>
Power (watts(e))		
Net	250	250
Gross	297	278
Junction temperature (°F)		
Hot	925	1500
Cold	240	610
T/E efficiency (%)	8.90	6.13
Total heat input (watts(t))	3980	4990
System net efficiency (%)	6.28	5.01
Fuel loading at beginning of life (watts(t))	4505	5648
Weight (lb)		
Total generator	145.6	184.0
Typical converter	12.0	10.0
Total unshielded system	157.6	194.0

The systems presented have been designed to allow a maximum of flexibility to the spacecraft designer. By including d-c converters in the systems, almost any voltage is readily available to the payload by simply placing a center tap on the output of the converter. However, if

~~CONFIDENTIAL~~

~~CONFIDENTIAL~~
 MND-3393

~~CONFIDENTIAL~~

0000000000

I-5

the only voltage required is 28 volts $\pm 10\%$, the system weight can be reduced 10% by replacing the converter with a simple overvoltage limiter and by designing the thermoelectric system to produce 28 volts. The inefficiency of the d-c converter is eliminated since the simple regulator is virtually 100% efficient at the design point. Thus, a 10% saving in fuel weight (approximately one to two capsules) can be effected. The overall size of the generator and radiator is accordingly reduced. A static generator so designed will weigh approximately 170 pounds and will not have a converter. The dynamic generator will weigh approximately 141 pounds and will have only an inverter for the pumps.

~~CONFIDENTIAL~~

MND-3393

0000000000

~~DECLASSIFIED~~
~~CONFIDENTIAL~~

BLANK

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

II. APPLICATIONS AND DESIGN CRITERIA

A. SYSTEM APPLICATION CRITERIA

The static and dynamic system designs developed during this study are intended for use with different types of spacecraft and consideration must therefore be given to the basic payload configurations to which each is applicable before the designs are discussed in detail.

1. Dynamic System

The dynamic system, with its large, low temperature, radiator is intended for use on those missions where the payload has a skin or in which the last boost stage or a transition section is orbited with the payload. In these cases, there are large areas of vehicle skin which may be available for power system waste heat rejection. Since the metallic skin is in orbit whether or not a radioisotope power supply is on board, a large radiator area can be made available to the radioisotope power system for a comparatively small weight increase. The radiator weight accruing to the radioisotope power supply consists of the pumps, manifolds, and lines necessary to conduct the cooling fluid out to the proper skin location, and the heat transfer tubes on the skin, including any meteoroid protection armor that may be required.

The dynamic system generator will also be easier to locate in the vehicle since provision need not be made to expose any generator thermal radiative surfaces to space. Thus, the generator has considerable installation flexibility since coolant line routing may be accomplished with minimal weight and complexity.

On the other hand, if the vehicle has no available skin, the weight of a large radiator would make the dynamic system much heavier. It has been estimated that the weight of skin and tubes amounts to approximately $75 \text{ lb}/100 \text{ ft}^2$ of radiator area. Most of this weight is attributable to the skin. Since additional structure would probably be needed to support the skin and tubes during launch, it can be seen that the static system will provide a lighter system for vehicles without available skin area.

2. Static System

The static system is entirely self-contained, using the surface of the generator itself for high temperature waste heat rejection. It is somewhat heavier than the dynamic system because of the surface requirements for heat rejection. The static system should be considered for those vehicles which have no skin available for a large low temperature radiator.

RECORDED
~~CONFIDENTIAL~~

The space vehicle designer should also remember that the static system has to be exposed to space on all possible sides so that it may reject its waste heat with a minimum weight radiator configuration. Generally, this means that the static system can be used on any vehicle but must be installed on the outside of the spacecraft or better, deployed on a boom away from the spacecraft. Boom deployment serves to reduce or eliminate both the thermal input to the vehicle and the amount of nuclear radiation shielding required.

3. Common Features

There are several features that are common to Sr-90 radioisotope thermoelectric power supplies that the user should consider. Full advantage of a Sr-90 power system can only be obtained in long life missions. This is due to the long half life of the fuel (28 years). For short term missions of less than a year, other radioisotopes give much higher power capability for a given weight.

Another important feature of a Sr-90 thermoelectric power system is that it has very light weight per kilowatt-hour of power (1.3 watts(net) per pound for the static system; 1.6 watts(net) per pound for the dynamic system). Along with long life and light weight, this type of system has extremely high reliability.

Along with these advantages, there is an important disadvantage that must be considered. Strontium-90, being a radioisotope, is a source of nuclear radiation. This radiation, produced by the natural decay of the isotope, requires either shielding or distance between the power supply and electronic equipment and personnel to prevent permanent damage.

B. POWER SYSTEM DESIGN CRITERIA

There are several design requirements, criteria and assumptions that have been established for the design of the 250-watt Sr-90 space generator. These requirements and criteria fall into two general categories: those established by the contracting agency and those assumed in order to develop the generator and ground handling equipment designs. These requirements and criteria are discussed.

1. Performance

a. Power output

The power system will deliver 250 watts to the load at the end of a five-year mission. Any excess power available at the beginning of the mission will be consumed by regulatory circuits in the power system.

CONFIDENTIAL

MND-3393

RECORDED

CONFIDENTIAL

II-3

b. Voltage

The power system output voltage will be 28 volts $\pm 10\%$.

c. Load

It has been assumed that the load appears to the power system to be resistive only, and time invariant.

2. Environmental Conditions and Mission Parameters

a. Launch site

The generator will be launched from the Pacific Missile Range (PMR) and it is assumed the launch will occur from PALC 1 for purposes of discussing typical launch pad environments.

b. Launch vehicle and payload

The launch vehicle is the Atlas/Agena, however, the payload is unspecified. It has been assumed that the mission variable transition section between the Agena and payload can be adapted to accept the generator, and that the skin of this transition piece will be available for use as the dynamic system radiator.

c. Launch trajectory and orbit

The launch trajectory has been assumed to be 182 degrees from true north, to obtain the best possible polar orbit. The high altitude orbit has been assumed to be 10,000 nautical miles.

d. Ambient vehicle temperatures

It is assumed that a location in the payload electronics bay that has a regulated ambient temperature between $+30^{\circ}$ and $+130^{\circ}$ F for the duration of the mission, will be available for the power supply, voltage converter and regulator.

e. Shock and vibration

The structural design dynamic load criteria has been assumed to be equivalent to a static load design criteria of 100 g.

f. Ambient pressure

It has been assumed that the ambient pressure in the 10,000-nautical mile orbit is 10^{-10} mm Hg for the purposes of investigating the sublimation rates of materials.

CONFIDENTIAL

MND-3393

03772291030

DECLASSIFIED
CONFIDENTIAL

g. Mission life

The mission life is five years from the time of launch.

h. Nuclear radiation

The total integrated dose from ambient nuclear radiation has been conservatively assumed to be 10^7 rad for the five-year mission at a 10,000-nautical mile orbit. Based on typical transistor tolerance levels, it has been assumed that the payload for a five-year life can tolerate 10^6 rad of gamma radiation and 10^{12} neutrons/cm² from the radioisotope power supply.

3. Fuel

The fuel will be Sr-90 in the fluoride form. Fuel characteristics are per AEC Specification "Strontium-90 Fuel Properties," April 15, 1964 (Confidential).

4. Reliability

A design goal of 80% probability of no system failure during the five-year mission life has been assumed.

5. Safety

The basic safety philosophy governing design of the 250-watt Radioisotopic Thermoelectric Generator (RTG) requires that the general public not be exposed to undue hazards resulting from normal use of the generator or from any credible accident attendant to its use.

The safety design criteria governing the life of the generator system are as follows:

a. Shipment

Shipment of the radioisotopic fuel shall be in accordance with applicable Federal, State and local regulations.

b. Containment

The design will provide absolute containment or confinement of the fuel under all credible missile abort induced conditions.

c. Impact

The fuel capsule shall maintain structural integrity when subjected to terminal velocity impact upon a rigid medium.

CONFIDENTIAL

DECLASSIFIED

MND-3393

CONFIDENTIAL

03145587030

II-5

d. Re-entry burnup

The generator system shall be designed to permit exposure and dispersal of the radioactive fuel above 100,000 feet, following re-entry from orbit.

e. Partial burnup zone

The partial burnup zone associated with high velocity, preorbital re-entry shall be over deep sea ocean areas or isolated, uninhabited land areas.

f. Corrosion resistance

The fuel capsule shall maintain integrity (corrosion resistance) to permit adequate time for sea recovery operations in the event the capsule is impacted within recoverable sea depths.

The capsule shall be resistant to the corrosive action of missile propellants and their byproducts and be chemically compatible with the isotopic fuel form.

The capsule shall also exhibit high corrosion and sublimation resistance at high operating temperatures.

CONFIDENTIAL

MND-3393

031712291030

II-6: ~~DECLASSIFIED~~ ~~CONFIDENTIAL~~

BLANK

~~CONFIDENTIAL~~
MND-3393

DECLASSIFIED

III. DYNAMIC SYSTEM

A. GENERAL

1. System Description

The dynamic generator system is shown schematically in Fig. III-1. It consists of a heat source radiating energy to thermoelectric packages, which in turn convert part of the thermal energy to electrical power and reject the remaining thermal energy at the cold junction to a fluid coolant. This waste energy is then transported, via the coolant, through tubes to the radiator panel and radiated to space.

Depending on reliability requirements, two or more redundant pumps propel the fluid through the coolant loop. In the event of pump failure, which will be detected by suitable temperature-sensing elements, a control circuit will shut down the defective pump and initiate operation of an alternate pump. Check valves in the system automatically prevent fluid recirculation through the dormant pump(s). Power is supplied to the pumps and control circuit from the generator electrical output.

A dc-to-dc converter conditions the 14-volt generator output to a regulated 28 volts (dc). The voltage regulation included in the converter serves two purposes: it limits the load voltage to the prescribed value and acts to minimize the hot junction temperature during the beginning-of-life fuel overload.

The primary heat rejection system is a cylindrical radiator composed of the aluminum skin of the space vehicle to which stainless steel lined aluminum tubes are brazed. Coolant carrying the waste heat from the thermoelectric modules is circulated through the tubes, transferring its heat to the vehicle skin. The heat is then dissipated by radiation to space. The radiator tubes are protected from meteoroid damage by the vehicle skin and aluminum shields sandwiched between the skin and tubes.

The basic components of the generator consist of the beryllium hot and cold plates, fuel capsules and assembly, two segmented telluride fluid-cooled thermoelectric modules, radiator system and the structure required to support the subassemblies relative to each other.

The generator assembly will automatically break up on re-entry, or can be separated by explosive couplings on command, to expose the fuel capsules for burnup.

2. Performance Summary

The two thermoelectric modules of the generator produce a gross output power of 297 watts(e) at end of life. The pump and control circuit

SECRET

MND-3393

CONFIDENTIAL

Fig. III-1. Thermohydraulic Schematic

III-2

SECRET

CONFIDENTIAL

~~CONFIDENTIAL~~

III-3

require a total of 17 watts out of a 90% efficient dc-to-ac inverter. The net output power supplied by the generator out of the 90% efficient dc-to-dc converter is 250 watts at $28 \pm 1\%$ volts. A 8.9% thermoelectric efficiency is obtained at end of life with hot and cold junction temperatures of 925° and 240° F, respectively. The overall system efficiency is 6.28%. The unshielded weight of the generator is 146 pounds, plus 12 pounds for a typical converter and inverter.

B. DESCRIPTION OF COMPONENTS

The dynamic generator (see Fig. III-2) is designed such that it is a rigid assembly during all ground, launch and orbiting conditions; but, upon re-entry, the generator will break up into sections, allowing the fuel capsules to fall free. This approach is used to expose the fuel capsules as soon as possible to assure complete capsule burnup and fuel particle dispersion. The release is initiated by aerodynamic heating of V-band clamps which will burn through rapidly because of very high local heating in the thin band sections between supports. The cold junction plates are then free to fall apart, complete with the thermoelectric modules and the hot plates. Each hot plate is tied to one of the cold junction plates with a thermoelectric module sandwiched between them. Once the hot plates separate, the fuel capsule assembly will fall apart since the hot plates supply the only fuel assembly retention. The generator and fuel assembly separation forces are supplied by aerodynamic pressure and the weight of the components.

1. Fuel Capsules

The fuel capsule (see Fig. III-3) will be exposed to both air and high vacuum environments, and may be subjected to salt water corrosion and impact conditions. In addition, the capsule must also be designed to assure burnup during re-entry. This design criteria is discussed in greater detail in the section dealing with nuclear safety.

Haynes-25 was selected for the fuel capsule material based on its properties at 1800° F and prior tests conducted for the SNAP 17A and other programs. Impact strength was a predominate consideration, but salt water corrosion, oxidation and sublimation characteristics were also evaluated. Hastelloy C appears to be an acceptable alternate material. The Haynes-25 alloy is slightly better for impact, while the Hastelloy is somewhat better for salt water corrosion. Hastelloy C salt water corrosion rates were evaluated under the SNAP 7 program, and Haynes-25 corrosion has been evaluated under the SNAP 17A program. Final selection should be based on capsule impact tests. The fuel capsule is a cylindrical shell with hemispherical ends. The thickness of the ends is 0.20 inch while the thickness of the cylindrical walls is 0.10 inch. It has been observed (based on a number of impact tests

~~CONFIDENTIAL~~

MND-3393

031712281030

DECLASSIFIED

031712281030

DECLASSIFIED

031712281030

DECLASSIFIED

0315587030

CONFIDENTIAL

DECLASSIFIED

III-4

Fig. III-2. Dynamic Generator

CONFIDENTIAL

MND-3393

DECLASSIFIED

03172291030

DECLASSIFIED

Fig. III-3. Fuel Capsule, Dynamic System

CONFIDENTIAL

MINI-3393

000000

CONFIDENTIAL

0310507030
~~CONFIDENTIAL~~

III-7

on the SNAP 9A and 17A programs) that this ratio of end cap thickness to wall thickness yields optimum impact resistance in that it distributes the deformations and stresses in both the end and the wall. If one member is too strong, it resists deformation and tends to load up the other member, causing it to fail. The worst impact condition occurs when the capsule strikes at approximately 45 degrees to the longitudinal axis. The hemispherical end also avoids any edges subject to tearing and provides sufficient thickness to take care of the abrasion that usually occurs in an inclined impact.

The capsule is fabricated in two separate sections, and the fuel is compacted directly into each piece. The pieces are then fitted together, and a single circumferential weld is made using filler rod. A small lip is provided in one section which mates with a machined surface on the other section to assure proper alignment of the capsule for welding. The lip is kept small enough so that it will become part of the welded joint, thus eliminating any crevices which might cause a failure when the capsule is subjected to high stresses. The weld joint has been moved to the quarter length point in this design. This places the weld far enough from the end to avoid the severe deformations and the high stresses that accompany the deformations.

The size of the capsule was determined by a number of considerations. The frictional heating during re-entry is much greater than the fuel heating. Therefore, a small capsule diameter is preferred since it will achieve a higher terminal velocity and thus receive a higher heat flux. Since the smaller capsule has less heat capacity, it will reach the melting temperature much sooner. The diameter and wall thickness selected in this design are a result of a burnup analysis balanced against the structural requirements for impact. Although a weight penalty is paid with this multiple capsule arrangement, it has been shown that a larger diameter capsule would not burn up at an acceptable altitude. The length of the capsule is somewhat more arbitrary. It is desirable to hold the ratio of capsule length-to-diameter to some small number, approximately 4 to 5, to avoid buckling of the capsule during impact. The combination of these considerations plus the overall generator assembly problems lead to this design.

2. Fuel Capsule Assembly

The fuel capsule assembly (see Figs. III-2 and III-4) for the dynamic system consists of 14 fuel capsules. The design provides for capsule retention during ground handling, launch, and system operation; but it permits rapid release of the individual capsules when the generator structure breaks up upon re-entry. This is done to ensure complete capsule burnup although it makes the assembly more complex.

CONFIDENTIAL

MND-3393

0310507030

DECLASSIFIED

~~CONFIDENTIAL~~

The capsules are assembled as seven pairs. A temporary holding fixture is required during the assembly. Two capsules are placed side by side in each of seven sheet metal slings. The sling restrains one end of the capsule in the axial and radial directions. A sheet metal cap is placed over the other end of the capsules, completing the capsule restraint once the pieces have been properly locked in place. The locking is accomplished by letting the two ends of each sling protrude through the cap. A triangular sheet metal beam is brought in from each side so that it catches under the holding bars welded to each tip of the slings. This action causes the sling and cap to grip the capsules snugly. The triangular beams are locked in place by an H section which prevents the beams from backing out and also locks the capsule package against longitudinal motion with respect to the H section.

A fuel assembly latching mechanism is attached to the H section and serves to lock the fuel capsule assembly to the hot plate. Two parallel latch bars are aligned with the outer edges of the door. On the outboard side of each bar are two wedge-shaped protrusions. The bars are driven apart by cams located at either end, and the wedges engage fittings in the hot plate, forcing the fuel capsule assembly back against stops in the hot plate, and at the same time restraining the assembly against lateral movement. The cams and latch bars are locked against reverse rotation by sawtooth splines. The fuel capsule assembly may be removed by depressing the cams against Belleville springs which disengage the splines and allow the cams to be reversed. A pin in the latch bar rides in a groove in the cam to force the wedges to retract, assuring release.

The fuel capsule assembly retension and latching parts are made of Hastelloy C which was selected for its mechanical properties at the operating temperature, which is close to the hot plate temperature. The Belleville springs will be made of Inconel X, chosen for its ability to maintain spring characteristics at high temperatures. Actually, the high stresses will occur only during the launch phase, but the design must allow for a temperature soak between the time of fueling and the time of launch.

Under certain conditions it is possible for metals to weld themselves together. This phenomena is known as vacuum welding and requires that the metals in contact have mutual solubility. It is further dependent on temperature, pressure, time, grain size and cleanliness of the interface. An interface which is not clean will not weld. The critical joints that are required to separate to assure fuel core or generator breakup will be protected from vacuum welding by use of a ceramic interface or the selection of mating materials which do not have mutual solubility.

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

3. Thermoelectric Module

The energy conversion portion of the generator consists of two thermoelectric modules connected in series. Each module contains 150 couples. The couples are connected in a series-parallel arrangement such that the failure of a single couple will only effect that couple. Since each couple is in parallel with one other couple and that pair is in series with the next pair, the loss of one couple would cause an almost negligible power drop (i.e., 1/300 of the total power).

The individual couples (Fig. III-5) consist of a hot shoe, a P-type element, an N-type element, and FerroVacE high purity iron diffusion barriers at either end of the elements. The hot shoe is a flexible strap made of 0.005 inch copper. Copper is used because of its low electrical resistance and flexibility. A small iron cup is ultrasonically spotwelded or brazed to both ends of the hot shoe. The cup is used to prevent diffusion of the copper into the thermoelement. It has been found that high purity iron is the best barrier material since it does not poison the thermoelements and reasonable bonds may be obtained. The cup shape is used to prevent the bonding flash from spreading to the copper shoe. The thermoelements are bonded directly to these cups. The P-type element is a segmented PbTe-BiSbTe design which is selected to match given temperature ranges with the most efficient thermoelectric material for that range. Thus, the hot end of the element is lead telluride; the cold end is bismuth telluride. Adding additional segments of other materials does not appear desirable when the cost and complexity involved is weighed against the small gain over the PbTe-BiSbTe construction.

The N-type element is a graded lead telluride material. A graded material is one in which the doping is changed along the length of the element to provide the maximum thermoelectric efficiency for the temperature in a given section of the element. The hot junction operates at 925° F (end-of-life temperature) while the cold junction is at 240° F, thus there is a gradient across an element of 685° F. By grading or segmenting the element, this gradient can in essence be broken up into sections, each matched to the most efficient material, or doping, for that range. An iron disc is bonded to the cold end of the element to provide a barrier to prevent the copper connecting straps from poisoning the elements.

Thermal insulation is required around the elements. This is accomplished by using Min-K sheet insulation which has been preformed to receive the couples. Assembly is accomplished by simply inserting the element legs through holes in the insulation. The Min-K sheet may be large enough to satisfy the whole module, or it may be divided up into sections to facilitate assembly and repair. Min-K has the lowest thermal conductivity of any of the available insulations. Copper connector straps

DECLASSIFIED

CONFIDENTIAL

Fig. III-5. Thermoelectric Module Section Dynamic System

DECLASSIFIED

CONFIDENTIAL

MND-3393

CONFIDENTIAL

III-11

are soldered to the iron discs on the cold end of the thermoelements to complete the series-parallel couple connections for the module.

The heat sink at the cold junction of the thermoelements is formed by a water-cooled diaphragm which is brazed to a cold plate for structural strength and to complete the water passage. The water pressure acting on the diaphragm provides the necessary force (approximately 30 psi) on the thermoelements to maintain good thermal conduction through the elements and to prevent the elements from breaking when subjected to dynamic loads. The diaphragm is made of stainless steel to satisfy the requirement for a thin flexible material which is not appreciably effected by the coolant fluid or radiation. The cold junction plates are made of beryllium because of its high strength-to-weight ratio. The plates are of a ribbed design to provide the required stiffness at a minimum weight. All of the structural loads of the generator are carried through these plates. The loads from the hot plate normal to the cold plate are carried through a ring of insulation surrounding the module. The loads in the other two axis are carried through shear tubes which are thermally insulated to reduce the heat losses through the mount. Aluminum oxide is used as the insulator in the areas since it has sufficient strength to carry the loads, can be formed into the required close tolerance parts, and has reasonable low thermal conductivity.

The thermoelectric module must be operated in an inert gas atmosphere for sustained service. Therefore, a rectangular stainless steel bellows surrounds the thermoelectric module. The bellows provides a high thermal resistance path to reduce heat loss. It is brazed to both the hot plate and the cold junction plate to form a sealed chamber. The chamber is evacuated and backfilled at assembly with an inert gas such as argon at six to eight inches of Hg absolute pressure when cold. The gas pressure increases to approximately 7 psia at operating temperature. The electrical leads from the module are brought through the cold junction plate by use of hermetically sealed connectors.

To keep the thermoelectric module from shorting out, it must be electrically insulated. This is accomplished on the hot side by coating the face of the hot plate with aluminum oxide and inserting a sheet of mica between the oxide and the hot shoes for a second barrier. The mica will also permit the hot shoes to slide during thermal expansion and contraction with a minimum bending and shearing stress in the thermoelement. The cold end is insulated with a sheet of mica inserted between the connecting straps and the stainless steel diaphragm. Electrical insulation of the cold junction is not as difficult due to the lower temperature and the mica is sufficient.

CONFIDENTIAL

MND-3393

037028.030

DECLASSIFIED
~~CONFIDENTIAL~~

Aluminum oxide and mica have been used for electrical insulation of thermoelements in other generators, and were used together in both the SNAP 7 and the SNAP 9A generators. A variation of the module pressure loading system has been used successfully on a chemically fueled generator currently under development at Martin. There the module pressure was held at half the external air pressure, providing a differential pressure of approximately 7 psi.

4. Thermal Insulation

To achieve a reasonable conversion efficiency, it is necessary to thoroughly insulate the fuel core. This forces approximately 90% of the thermal energy to flow through the elements. The module insulation has been covered in the thermoelectric module discussion. The area around the modules and on each of the four remaining sides is also insulated with Johns Manville Min-K (chosen for its excellent insulation properties) under the conditions experienced in the dynamic generator. Min-K can be molded or machined to a desired section, and can carry fairly substantial loads (as high as 200 psi), provided they are distributed over a large area and the operating temperature is under 1000° F. The insulation on the front face of the generator is attached directly to the front of the fuel core and protected by a thin sheet of metal. Sheet metal panels form the remainder of the enclosure on the back, top and bottom. These sheet metal panels form a tension tie between the cold junction plates, and they are held to the plates by V-band clamps. It is the release of these clamps that permits the generator to break up on re-entry.

5. Cooling System

The cold junction temperature of the generator is maintained by pumping water through the passage formed between the stainless steel diaphragm and the cold junction plates. Water was chosen because it is the most efficient cooling fluid, and it is not severely affected by radiation. A pump is required to maintain the required flow of approximately 7 gpm at a 3-psi pressure rise across the pump. The design life for the system is five years which is longer than any single pump can be expected to operate on a continuous basis with the reliability desired. Therefore, it is necessary to place a number of pumps in parallel to assure that the reliability requirements of the system will be attained. Only one pump will operate at any given time. When that pump fails to deliver the required flow, which is sensed by the corresponding temperature increase, the next pump is automatically started. Based upon current reliability test data, it will be necessary to use four pumps of the model chosen to give a system reliability of 96%. An a-c power supply will be used to keep the motor efficiency as high as possible and to permit a completely sealed (canned) system. The following summarizes the coolant pump characteristics:

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

Flow (gpm)	7
Rated pressure (psi)	3
Voltage supply (volts, ac)	28 400 cycle, single phase
Required power (watts)	7
Weight (lb)	2.5
Life expectancy (hr)	12,500

The pressure supplied by the pumps is only that pressure required to maintain the 7-gpm coolant flow. An additional 35 psia will be superimposed on the coolant system by a small accumulator. It is this pressure that supplies the mechanical loading on the thermoelements. The pressure is sufficiently high to surpress the water vapor pressure at operating temperature. The accumulator uses a spring to supply the required force on a small piston-bellows arrangement to obtain the required pressure on the coolant. The accumulator also compensates for small volumetric changes in the coolant system caused by thermal expansion or contraction.

The radiator (see Fig. III-6) will utilize the skin of the vehicle, and the skin thickness has been estimated at 0.050 inch for purposes of thermal and meteoroid armor calculations. It would have been desirable to use aluminum tubing to construct the radiator for heat rejection and fabrication reasons, but aluminum would be dissolved by the water at a prohibitive rate. Therefore, a very thin stainless steel tube is used to carry the water, and a thin jacket of aluminum has been extruded over the stainless steel tube to permit brazing the tube to the aluminum skin. This type of fabrication is currently being done by the Uniform Tube Company, Collegeville, Pa. To facilitate assembly and heat transfer, the tube will be swaged into a D shape with the flat side against a 0.025-inch thick meteorite shield which in turn is brazed to the vehicle skin.

a. Pump control system

The pump control circuit is shown in Fig. III-7.

DECLASSIFIED
CONFIDENTIAL

Section A-A
(scale 4/1)

Fig. III-6. Dynamic System Radiator

DECLASSIFIED

CONFIDENTIAL

MND-3393

CONFIDENTIAL

III-15

Fig. III-7. Pump Control Circuits

The circuit operates as follows: Pump 1 is operating; if a failure occurs in the pump or cooling system, the temperature of the coolant and the generator cold plate rise. The thermostats are mounted on the generator cold plate. When the cold plate reads 300° F, the first thermostat switches, causing Pump 1 to shut down and Pump 2 to start.

The process is repeated until the temperature ceases to rise (the coolant is flowing) or all the thermostats have switched, which will happen if the cooling fluid has been lost due to tube puncture. Thermostat contacts will be equipped with latches so the switch will throw once and remain in the thrown position.

Design tests will undoubtedly allow a closer temperature spacing of the thermostats which will reduce the danger of over temperature damage to the thermocouple hot junctions.

6. Installation

The generator may be mounted in either a horizontal or vertical position depending on the suitability for a given installation. The coolant pumps may be mounted on the vehicle radiator section. The generator should be located as close to the pumps and radiator as practical to keep the system weight and the coolant pumping pressure losses to a minimum. The generator should be mounted near the surface of the vehicle to facilitate remote fueling of the generator in the gantry. External generator supports attached to the vehicle are recommended during the launch. These supports are to be discarded with the Agena aft sections after launch, and will provide a lighter overall system than if the generators were cantilevered off the vehicle without external supports.

CONFIDENTIAL

MND-3393

037028.030

Fig. III-8. Electrical System Schematic

The separation of the generator during re-entry is dependent upon the destruction of the V-band clamps due to aerodynamic heating. Therefore, it is necessary that the generator position on re-entry be such that it is not shielded from aerodynamic heating.

The generator and radiator assembly may be separated with respect to other equipment if radiation or radiation shield weight becomes a problem. This may be done after launch by using extension devices such as the DeHavilland STEM (Self-storing Tubular Extensible Member).

The couplings that retain the V-band clamps on the generator may be replaced with standard explosive coupling units. These may be detonated on command, and would permit generator destruction if deemed desirable either during the launch phase or for some time afterward.

7. DC-to-DC Converter and DC-to-AC Inverter

This section describes the technical approach which will be used to provide a power conditioning system that can convert the electrical output of the thermoelectric generator to a usable voltage level and also provide a fixed frequency alternating current for pump motor drive power. An electrical schematic of the power system may be found in Fig. III-8.

The power conditioning subsystem must meet the following requirements:

Output 1

Voltage (volts)	$28 \pm 10\%$, dc
Power (watts)	250
Load	Resistive

Output 2

Voltage (volts)	$115 \pm 10\%$ rms, ac
Power (watts)	17
Frequency (cps)	$400 \pm 10\%$
Load	Pump motor and controls

DECLASSIFIED
CONFIDENTIAL

Input

Voltage (volts)	$14 \pm 1\%$ dc
Power (watts)	297

Environment

Temperature, ambient (F)	+30 to +130
------------------------------	-------------

a. Converter types

There are various methods of converting electrical energy from one voltage level to another. The various methods are distinctive with respect to efficiency, size, complexity, application and performance in various environments. To increase a voltage level, it is necessary to use a transformer and since a transformer is an alternating current device, it is necessary to convert the dc input voltage to ac by a switching device. Various devices and techniques are available for switching purposes and the most common are shown in Fig. III-9.

- (1) Systems using tunnel diodes as switching elements where maximum theoretical efficiencies are 65% for germanium and 45% for silicon.
- (2) Single-ended and flyback-type systems for switching using germanium or silicon transistors where efficiencies obtainable are on the order of 70%.
- (3) Push-pull type systems using silicon or germanium transistors as switching elements where efficiencies obtainable are in the order of 80 and 90%, respectively.

The same discussion for converters is applicable to inverters for the power level required. Inverters do not require rectification but may require harmonic filtering and frequency stabilization.

The system concept selected to meet the requirements consists of a converter and an inverter as separate circuits each being powered by the thermoelectric generator.

b. Converter

The converter circuit concept selected consists of a push-pull system using germanium transistors, plus a closed loop regulation system. A block diagram of the converter circuit is shown in Fig. III-10.

CONFIDENTIAL

MND-3393

DECLASSIFIED

Tunnel diode static converter

Transistor single ended converter

Transistor push-pull static converter

Fig. III-9. Converter Schematics

DECLASSIFIED

~~CONFIDENTIAL~~

Fig. III-10. Converter Schematic

DECLASSIFIED

~~CONFIDENTIAL~~

MND-3393

Selection of an oscillator driver-power stage concept allows operation of the power (output) transformer out of saturation for minimum losses. The oscillator is of the overdriven, push-pull transformer coupled type and its function is to supply base drive switching current to the power stage. A circuit for the oscillator-driver is shown in Fig. III-11.

Fig. III-11. Oscillator-Driver Circuit

In the circuit of Fig. III-11, Q_1 and Q_2 are used to alternately switch the input d-c voltage (E_1) across P_1 and P_2 , primary windings of T_1 . This voltage is changed by transformer action to S_1 or S_2 and is used to supply base drive power for the power transistors in the power stage. R_1 and R_2 forward bias Q_1 and Q_2 into conduction and effectively make the oscillator self-starting. Q_1 and Q_2 are operated in a switching (saturation) mode for minimum losses. T_1 is a saturating transformer using a square hysteresis loop type of magnetic material. The parameters of T_1 establish the frequency of oscillation. It can be

shown from Faraday's law that $f = \frac{E_1}{4N\Phi_s}$ where E_1 (input voltage) is constant and f (frequency) is inversely proportional to the number of turns on T_1 and the saturation flux level of the magnetic material used.

DECLASSIFIED

CONFIDENTIAL

The power stage and output transformer is shown in Fig. III-12.

Fig. III-12. Power Stage and Transformer Circuit

Q_3 and Q_4 in the power stage are alternately driven into conduction and supply square wave power to T_2 . This voltage is stepped up by transformer action and after rectification is applied to the load (R_L). Allowing a common connection between input (E_1) and output (E_0) offers the advantage of increased efficiency and reduced size. This is so because the circuit of Fig. III-12 can be considered as two equivalent generators in series where one generator supplies $\frac{E_1}{E_0} P_0$ power to the

load and the second generator supplies $\frac{(E_0 - E_1)}{E_0} P_0$ power to the load.

The first equivalent generator supplies its power directly to the load through the rectifier. Since the practicality of this system depends on the ratio of E_1/E_0 , selection of this concept for the required application appears reasonable, since E_1/E_0 is $1/2$. The selected concept requires a converter capability of only $\frac{(E_0 - E_1)}{E_0} P_0$ watts or 125 watts versus a 250-watt capability for an isolated input-output converter.

T_2 is operated at a flux level below saturation for minimum losses. For high efficiency low voltage power conversion, tape wound super-malloy toroidal cores are used.

CONFIDENTIAL

MND-3393

DECLASSIFIED

The rectifier output of the power stage can be connected as shown in Figs. III-12 or III-13 or if an isolated output is desired, then the circuit will appear as shown in Fig. III-14. The third winding (d-e) on T_2 is used for regulation purposes which will be explained in the appropriate sections.

Fig. III-13. Output Circuit

Design considerations for transistors. A graph of P_C (total conduction power loss) versus I_B (base drive current) with I_C (collector current) as a parameter for a transistor as a closed switch is shown in Fig. III-15. $P_C = I_B V_{BE} + I_C V_{CE}$ where V_{BE} is the base-emitter voltage and V_{CE} is the collector-emitter voltage and I_C is the collector current. OA is the locus of minimum losses for various values of I_C . Data of this nature exist for various power transistors so that power converters can be easily optimized.

Fig. III-14. Isolated Output Circuit

DECLASSIFIED

CONFIDENTIAL

Fig. III-15. Transistor Power Loss versus Base Drive Current

Fig. III-16. Power Loss versus Frequency

Fig. III-17. Germanium Transistor Rectifier Circuit

DECLASSIFIED

CONFIDENTIAL

Frequency considerations. To achieve a minimum loss converter, consideration must be given to the relationships depicted in Fig. III-16.

- A = total loss
- B = transistor loss
- C = transformer loss
- f_0 = optimum frequency.

Optimum frequency of oscillation occurs when power transistor losses equal power transformer losses.

Rectifiers considerations. Consideration must also be given to the losses in the power rectifiers. These losses can be minimized by using germanium transistors as rectifiers as shown in Fig. III-17.

c. Regulation

If the load is an invariant resistance, as has been assumed, designing the system to deliver 28 volts at the end of life will permit the use of a simple regulatory device. Since the lead is constant and the generator will deliver a higher voltage at all times prior to the design point, then the only regulation required will be over-voltage protection. This may be provided by a zener diode at the output (load) terminals (see Fig. III-18).

Fig. III-18. Zener Diode Regulator Circuit

DECLASSIFIED

CONFIDENTIAL

Fig. III-19. Closed Loop Regulator Circuit

DECLASSIFIED

CONFIDENTIAL

MND-3393

This regulator will have inherently higher reliability than the more complicated one discussed later. The simple overvoltage protection regulator has been used in the reliability analysis. If it is assumed that the load varied, then a more complicated regulator is needed to maintain the output voltage at $28 \pm 10\%$ volts dc. It is also used to maintain the operating point of the generator constant with respect to its EI load line characteristic for any load variation. Figure III-19 illustrates a closed loop regulator circuit which will meet these requirements.

The circuit operation is as follows: differential amplifier Q_5 , Q_6 will detect any voltage variation across d-e which is proportional to load variations. V_d (differential amplifier output voltage) is converted to a current proportional to V_d by Q_7 and proportionately biases Q_8 and Q_9 . Q_9 is designed to handle full-load current. This type of regulator maintains the operating point of the generator constant and will also maintain the converter output voltage within specifications. The generator operating characteristics plus an equivalent circuit of the generator, regulator and load reflected to the input is shown in Fig. III-20. The complete d-c power conditioner, with the more complex regulator, is shown in Fig. III-21.

Fig. III-20. Power System Equivalent Circuit

E_{oc} = generator open circuit voltage

R_i = generator internal impedance

SECRET
CONFIDENTIAL

Fig. III-21. DG-to-DC Converter Schematic

SECRET

CONFIDENTIAL

MND-3393

R_L = reflected load

R_{reg} = equivalent regulator resistance

$$E_1 = \frac{E_{oc} R_K}{R_i + R_K} = \text{constant since } R_K \text{ is constant and}$$

$$R_K = \frac{R_{reg} R_L}{R_{reg} + R_L}$$

d. Inverter

To provide 400 cps power for a pump motor, an inverter is required. Various inverter techniques were investigated.

- (1) Using the square wave a-c output of the power transformer (T_2) of the converter through an additional winding. Since maximum efficiency is required of the dc-to-dc converter, it is necessary to operate the converter at an optimum frequency which will be different than the inverter requirement. Therefore, a separate inverter is justified.
- (2) Sine wave transistorized oscillator driving a Class B push-pull power stage. The oscillator can be frequency controlled by either R-C or L-C networks.
- (3) Square wave oscillator driving a push-pull power stage. Frequency controlled by R-C network. Since a motor is sensitive to the average value of current, it should operate satisfactorily with a square wave and since a square wave oscillator would have less parts than a sine wave oscillator, this technique was selected.

The inverter circuit is shown in Fig. III-22. The frequency of oscillation is determined by the $R_4 C_1$ time constant and is independent of input voltage. The frequency can be stabilized to within 2% and if necessary can be temperature stabilized. Since E_1 is the generator-loaded terminal voltage and is constant due to the dc-to-dc converter regulator, it would not be necessary to regulate the inverter output voltage. It may be necessary to install a capacitor at a-b on Fig. III-22 to counteract the motor winding inductance. Power factor correction of this nature would allow the switching currents of Q_3 and Q_4 to be in phase with the switching voltage.

CONFIDENTIAL

Fig. III-22. DC-to-AC Inverter Schematic

CONFIDENTIAL

MND-3393

CONFIDENTIAL

e. Electromagnetic compatibility

Electromagnetic interference reduction techniques will be incorporated in the design of the dc-to-dc converter. Consideration will be given to shielding and isolation of the oscillator driver from the power stage, and shielding and isolation of the power stage from the output. Feedthrough capacitors will be used to shunt undesired interference signals, and power input will be isolated through R, L, C, networks. Switching transistor and rectifier spikes will be suppressed with appropriate despiking networks. Conductors carrying forward and reverse currents of switching circuits will be placed adjacent to each other. Single point grounding techniques will be utilized. A conducted interference test will be performed on the breadboard converter to assure design adequacy. Radiated and conducted interference tests will be performed on the packaged unit. The precautionary steps taken during the design phase should reduce to a minimum RFI fixes after packaging.

f. Efficiency

It is estimated that the converter efficiency as proposed would be in the order of 90% and the inverter efficiency would be 85 to 90% for a square wave and 70% for a sine wave. Since it is expected a square wave inverter will be used, the generator power requirement would be 297 watts in order to provide 250 watts of d-c power at 28 volts and 17 watts of power at 115 volts RMS 400 cps.

g. Weight and size

The converter-inverter system would weigh approximately 12 pounds and the volume would be approximately 160 cubic inches.

It should be noted that almost any voltage can be made available to the payload by changing transformer ratios or by placing a center tap on the output of Transformer T2. Thus, any payload voltage requirement can be accommodated within the system design using this d-c converter. If 28 volts is the only voltage required, then the generator could be made lighter by eliminating the converter entirely and designing the thermoelectric system to produce 28 volts. The inverter would still be required for the pumps.

C. SYSTEM PERFORMANCE AND OPTIMIZATION

1. Thermoelectric Parametric Study

The dynamic system power conversion modules consist of segmented couples composed of variably doped lead tin telluride on the N leg and

~~CONFIDENTIAL~~

a lead telluride-bismuth telluride combination on the P leg. These materials are employed so as to maximize the efficiency obtained from each element by utilizing each material in its optimum temperature range. The segmented couple arrangement is shown in Fig. III-23.

Fig. III-23. Segmented Couple Configuration

A thermoelectric parametric study was performed for cold junction temperatures of 900°, 950° and 1000° F, and contact resistivities of 21.7, 79.0 and 158.1 $\mu\Omega$ in.². The Vince-Tom thermoelectric optimization code for the IBM 709 (Ref. III-1) was used in this study. The results are presented in Appendix A. The segmented couple design and materials properties are taken from the SNAP 21A program and are those currently in use on that program as of May 15, 1964.

An end-of-life hot junction temperature of 925° F was used for design purposes. This gives a reasonable beginning-of-life value of 1000° F. Cooling system studies (Appendix D) indicate the optimum cold junction temperature is 240° F. Of the three contact resistivity values used in the thermoelectric study, 79.0 $\mu\Omega$ in.² was chosen as the most realistic value (for design purposes) to account for thermoelectric degradation over the five-year mission. For these hot and cold junction temperatures, and contact resistivity, the design value thermoelectric efficiency was determined to be 8.9% (see Fig. III-24).

2. Radiator Parametric Study

A parametric study of radiator temperatures and areas required to reject the waste heat was performed. The variables were radiator temperature, radiator area, waste heat to be rejected, orbital altitude

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

Fig. III-24. Thermoelectric Efficiencies for PbSnTe-BiSbTe Segmented Elements

~~CONFIDENTIAL~~

Fig. III-25. Radiator Area Required for Orbiting Vehicle

~~CONFIDENTIAL~~~~CONFIDENTIAL~~

MND-3393

and vehicle position in the orbit (see Appendix D). A polar orbit was considered for the space vehicle and for altitudes of 100, 1000, 10,000 and 20,000 nautical miles, an effective sink temperature was calculated for each of four positions (at 90-degree angles to each other) around the earth. These effective sink temperatures were determined on the bases of direct solar radiation, reflected solar radiation from the earth, and thermal radiation from the earth, as thermal inputs to the surface of the space vehicle. The effective sink temperature for each orbital position was a function of the altitude and the view factors of the space vehicle to the earth and sun. The results are presented in Table III-1.

TABLE III-1
Effective Sink Temperature

Altitude (naut mi)	Average Effective Sink Temperature (°F)
100	337
1,000	314
10,000	233
20,000	193

The interrelation between radiator area, radiator temperature and heat to be rejected was then calculated using the relation

$$q = \sigma \epsilon \eta_f A (T_R^4 - \theta^4)$$

where

q = heat to be rejected

ϵ = emissivity of the surface

η_f = area efficiency of the surface due to tube spacing

A = area of radiator

T_R = radiator temperature

θ = effective sink temperature

The results for a 10,000-nautical mile orbit are presented in Fig. III-25. The design point is 180° F and approximately 3200 watts of heat rejected as determined by the cooling system optimization study.

~~CONFIDENTIAL~~

3. Coolant Comparison

Eight synthetic coolants and water were investigated for use in the cooling system. The bases of the investigation were nuclear radiation stability of the coolant properties and thermal characteristics of the various coolants. The coolants were considered unsuitable for use if any of the properties are changed by 10% by a dose of 7×10^7 rad (H_2O). Heat transfer characteristics of the coolants were determined by calculating the difference between the diaphragm surface and bulk fluid temperatures in the module coolant chamber. The results are presented in Table III-2.

TABLE III-2
Coolant Comparison

<u>Coolant</u>	<u>Acceptable Radiation Stability</u>	<u>$T_{\text{diaphragm}} - T_{\text{bulk}}$ (°F)</u>
Water	Yes	43
Freon-21	No	225
FC-75	Yes	432
OS-59	No	383
Coolanol-45	No	502
Coolanol-35	No	256
Dowtherm-A	Yes	309
Dowtherm-E	No	--
Oronite-8515	No	--

From a nuclear radiation stability point of view, water, FC-75 and Dowtherm-A are considered acceptable for use as coolants. However, it is evident from Table III-2 that water exhibits the best heat transfer characteristics, and it, therefore, was chosen as the coolant to be used in the dynamic system.

4. Cooling System Parametric Study

This study was aimed primarily at determining the tradeoff between thermal inventory and weight as a function of radiator tube size and coolant flow rate (see Appendix D). The basic approach in determining the optimum tube diameter and flow rate was to investigate the fuel thermal inventory as a function of coolant flow rate and radiator tube diameter. The optimum flow rate which minimizes the thermal inventory was determined by examining the behavior of the system. For example, the thermal inventory is dependent on the cold junction temperature (for a constant hot junction temperature) through the thermoelectric efficiency, and pumping power. These in turn are dependent

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

2

on the flow rate. For a fixed heat rejection temperature, T_R , the cold junction temperature decreases as flow increases. This results in an increased thermoelectric efficiency and hence a decrease in fuel thermal inventory. However, at some flow rate, the pumping power begins to become significant and the thermal inventory goes through a minimum value after which it increases rapidly as the flow increases. This minimum value point was determined for a range of D tube diameters from 0.375 to 0.75 inch (see Fig. III-26) utilizing the minimum thermal inventory corresponding to an optimum flow rate for each diameter; the fuel assembly weight was calculated assuming a constant power density. To this was added the tube weight including meteoroid bumper and the contained water coolant. Finally, a system weight composed of these items was plotted versus diameter as shown in Fig. III-27. By cross plotting, a plot of system weight versus thermal inventory was developed as shown in Fig. III-28.

It is evident that the changes in system weight (69 to 75 pounds) and thermal inventory (4200 to 3900) are not relatively large (<10%) for the range of tube sizes considered; therefore, the system parameters are relatively insensitive to the D tube diameters. However, this is only true for an optimized flow rate for each tube size. For other than an optimized flow rate, the changes in these parameters are very sensitive to flow rate as indicated in Fig. III-26. Since the system parameters are relatively insensitive to D tube diameters for optimized flow rate, any value within the range considered could be used as a reasonable design point. Based on this evaluation, a typical D tube diameter of 0.5 inch was selected as the design point. The optimum system parameters for this tube size are given in Table III-3, and comprise the generator cooling system design point.

TABLE III-3

Tube Diameter Design Point

	<u>0.5-Inch D Tubes</u>
Thermal inventory, end of life (watts)	3980
Weight (lb)	
Tubes	5.62
Bumper	1.20
Coolant	3.54
Fuel capsules	59.20
Total	69.54

CONFIDENTIAL

MND-3393

CONFIDENTIAL

Fig. III-26. Thermal Inventory versus System Flow Rate

CONFIDENTIAL

CONFIDENTIAL

Fig. III-27. System Weight versus Tube Diameter

DECLASSIFIED

CONFIDENTIAL

Fig. III-28. System Weight versus Thermal Inventory at Optimum Flowrate

R = reliability objective of each thermocouple = 0.9947

R_C = reliability objective of entire thermocouple functional block = 0.999

Fig. III-29. Thermoelectric Generator Thermocouple Arrangement

DECLASSIFIED

CONFIDENTIAL

TABLE III-3 (continued)

	<u>0.5-Inch D Tubes</u>
Optimum flow rate (lb/in.)	3000
Pumping power (watts)	7
Radiator fin root temperature (°F)	180
Number of radiator tubes	7
Radiator surface area (ft ²)	45.4
Radiator effectiveness (%)	95
Cold junction temperature (°F)	240
Heat rejected at radiator (watts)	3215

5. Temperature Distribution

The design point (end of five-year mission life) temperatures and their respective positions are presented in Table III-4. To verify material temperature limitation compatibility, the hot side temperatures were determined for beginning-of-life conditions.

TABLE III-4
Dynamic System Temperature Distribution

	<u>End of Life (°F)</u>	<u>Beginning of Life (°F)</u>
Radiator fin root	180	
Average bulk fluid	180	
Diaphragm surface	200	
Cold junction	240	
Hot junction	925	1000
Fuel block surface	975	1050
Fuel capsule front wall	1445	1517
Fuel capsule back wall	1690	1796
Maximum fuel		1835

DECLASSIFIED

~~CONFIDENTIAL~~

The most critical calculation, the beginning-of-life fuel capsule temperature distribution, was performed by numerical techniques using an IBM 7094 IBM Code TIGAMM. A brief description of the code may be found in Appendix J. The results of this calculation indicate that the fuel capsules material (Haynes-25) will be satisfactory under the worst temperature conditions, since they are about the same as the temperatures in the SNAP 17A generator.

The calculations may be found in Appendix F.

6. Thermal Losses

The parasitic thermal losses in the dynamic system occur in five components. These are the module insulation, the module bellows, the insulation surrounding the module bellows, the hot plate support structures, and the insulation surrounding the fuel assembly--the four sides not occupied by the modules.

The module insulation consist of Johns Manville Min-K 1301 filled with argon gas. The insulation surrounding the module bellows and fuel assembly is Johns Manville Min-K 1301 under vacuum conditions. The module stainless steel bellows are designed to provide an extended heat path to minimize thermal loss while sealing the thermoelectric package. The hot plate support structure consists of stainless steel rods surrounded by ceramic insulator sleeves to reduce conduction losses out of the rods while maintaining a compressive load-carrying capability.

The parasitic heat losses are summarized in Table III-5 for end-of-life conditions. The calculations may be found in detail in Appendix F.

TABLE III-5

Parasitic Thermal Losses (watts)

Module insulation	181
Module bellows	102
Bellows insulation	63
Hot plates support structure	267
Fuel assembly insulation	37
Total Parasitic losses	650

7. Weight Summary

The weights of the dynamic generator components are presented in Table III-6. Each structural member of the dynamic system components has been conservatively stress analyzed to assure it has sufficient size to meet the 100-g loading criteria.

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

TABLE III-6
Dynamic System Weight

<u>Item</u>	<u>Weight (lb)</u>	<u>Item</u>	<u>Weight (lb)</u>
Cold plate (2)	17.2	Pumps (4)	10.0
Hot plate (2)	10.3	Latches	1.3
Bellows (2)	0.9	Capsule slings (7)	0.9
Couples	7.6	Capsule cap structure	1.1
Module insulation	1.0	Wedge beams (2)	1.1
Mica and Al ₂ O ₃ sheets	0.5	H beam	2.9
Pressure diaphragm	0.3	Back closure structure (1)	1.4
Fuel + capsule (14)	59.2	Side closure structures (2)	1.4
Min-K insulation	10.5	Door closure structures (2)	0.5
Radiator tubes + headers + water	15.5	Generator Total	145.6
V-band clamps	2.0	Typical converter and inverter	12.0
		Typical system	157.6

The system presented herein has been designed to allow a maximum of flexibility to the spacecraft designer. By including a d-c converter in the system, almost any voltage is readily available to the payload by simply placing a center tap on the output of the converter. However, if the only voltage required is 28 volts $\pm$ 10%, the system weight can be reduced 10% by replacing the converter with a simple overvoltage limiter as discussed previously and by designing the thermoelectric system to produce 28 volts. The inefficiency of the d-c converter is eliminated since the simple regulator is virtually 100% efficient at the design point. Thus, a 10% saving in fuel weight (approximately one capsule) can be effected. The overall size of the generator and radiator is accordingly reduced. A generator so designed will weigh approximately 141 pounds and there will be no converter, only the dc-to-ac inverter for the pumps.

DECLASSIFIED

~~CONFIDENTIAL~~8. Performance Summary

The performance of the dynamic system is summarized in Table III-7. The calculations of the various parameters may be found in the appropriate appendices.

TABLE III-7

Dynamic System Performance Summary
(all values for five-year design points, except as noted)

Power (watts (e))	
Net to load	250
Pump, ac	7
Control system, ac	10
Efficiency (%)	
DC-to-AC inverter	90
DC-to-DC converter	90
Gross power from generator (watts (e))	297
Junction temperatures (°F)	
Hot	925
Cold	240
Thermoelectric efficiency (%)	8.9
Heat to thermoelements (watts (t))	3330
Parasitic heat losses (watts (t))	650
Total thermal inventory (watts (t))	3980
System net efficiency (%)	6.28
Fuel loading, beginning of mission (watts (t))	4505
(curies)	715,136
Electrical characteristics	
Generator output voltage (volts)	14.0
Generator output current (amp)	21.2
Optimum generator load (ohms)	0.660
Generator internal resistance (ohms)	0.482
Converter output voltage (volts)	28 ± 2.8

9. Cooling System Failure on Launch Pad

If the dynamic cooling system should fail while the fueled generator is on the launch pad, the possibility of overheating and perhaps melting the fuel capsule arises. The situation has been analyzed in detail (see

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

III-45

Appendix H) and, based on an extremely conservative analysis, the fuel capsule wall temperature might reach the melting range of Haynes-25, the fuel capsule material. Since the analysis was very conservative, it is unlikely that the temperature will get this high. However, as a precaution, it is suggested that extra cooling for the generator be provided in the event of cooling system failure by passing ambient air (assumed to be at 100° F) over the surface of the generator. The required velocity of the air is approximately 70 fps. If it is passed through a duct with the same cross-sectional area as that of the generator cold plates, the required mass flow is approximately 6400 ft³ / min. This air flow will maintain the fuel capsule wall at a maximum temperature of approximately 2100° F, or 300° F below the melting range of Haynes-25.

D. DYNAMIC SYSTEM RELIABILITY

The dynamic power supply has a reliability design objective of 80% probability of failure-free operation for a period of five years, with a confidence of 50%. It is further assumed that the failure distribution will be exponential, i.e., random.

The operational reliability experience of the power supply involves two phases: the launch-boost phase; and, the orbital phase. During the orbital phase, the mechanical stress will be low, and a constant radiation and thermal environment will be experienced throughout the five-year mission.

Basically, the reliability of the dynamic system depends on the individual reliabilities of the generator, the converter, the inverter and the cooling system.

1. Generator Reliability

a. Failure modes, causes and effects

The primary mode of failure for nuclear generators operating in a hard vacuum has been leakage, i.e., loss of internal pressure due to the inability to maintain adequate seals. The result has caused the telluride-type elements to sublime which in turn causes a continuous decrease in power. Although segmented telluride-type thermocouples are to be used in the dynamic system, adequate sealing will be afforded by brazing the seals to the thermocouple hot and cold plates, which are very rigid members. Tests should be run on these brazed seals during development and acceptance testing to assure that the leakage rates are within a very low tolerance.

~~CONFIDENTIAL~~

MND-3393

037029.030

DECLASSIFIED

~~CONFIDENTIAL~~

Table III-8 lists the other most likely failure modes and gives the most probable cause and effect of each. The probability of occurrence of these modes is estimated for some modes but exact determination thereof is not planned because of the time that would be required for life testing. However, an indication that designed margins of safety are high can be obtained from relatively inexpensive testing, since the primary cause of failure is vibration during launch boost. Exploratory testing involving the 150-thermocouple module should be initiated during development to determine environmental limits in vibration, shock and temperature. Additional tests should be planned to determine thermocouple material strengths at operational temperature ranges in shear, compression, tension, etc.

TABLE III-8
Failure Modes

<u>Failure Mode</u>	<u>Cause</u>	<u>Probability of Failure</u>	<u>Effect</u>
Bond separation	Vibrations during launch-boost	0.02	Lose one element
Element breakage	Vibrations during launch-boost	0.90	
Electrical connectors	Vibrations during launch-boost	0.05	Lose a module or generator
Wire breakage	Vibrations during launch-boost	0.00	
Short circuit	Insulation breakdown Long time buildup of metallic crystals due to sublimation (static system only)	0.03	
		<hr/> 1.00	

b. Reliability model

The mean failure rate for the thermocouple used in the dynamic system is 0.012%/1000 hours and is based on a history of thermocouple performances in similar generators. This failure rate is based on the thermocouple failure rate data from Ref. 6. Briefly, over 14 million thermocouple hours were recorded with only one failure occurring; the best estimate of the failure rate is 0.007%/1000 hours; the mean value is 0.012%/1000 hours.

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

Three hundred thermocouples are arranged in two modules and each module contains 150 thermocouples. The two modules are arranged so that all of the thermocouple pairs are arranged in series-parallel; a block diagram is given in Fig. III-29. Any seven thermocouples can fail without disrupting the electrical output or reducing power below requirements provided that the two failures do not occur in the same redundant pair. The reliability of one thermocouple functioning for five years is 0.9947, based on a failure rate of 0.012%/hours and an operating time of 43,800 hours. The corresponding MTBF is 8,333,300 hours. The reliability for the series-parallel arrangement of the 300 thermocouples is 0.999 and is based on the reliability model that follows (see Ref. 6).

$$R_C = \sum_{i=0}^k 2^i \binom{n}{i} R^{2n-i} Q$$

where

R_C = reliability of the entire thermocouple series-parallel unit

R = reliability of an individual thermocouple

Q = $1 - R$

$2n$ = total number of thermocouples

i = i th failure

k = number of allowable failures

c. Fuel core assembly design reliability

The fuel capsule assembly is a structural subsystem of the thermoelectric generator. Structural reliability is achieved by applying a standard margin of safety, namely 2/3 yield strength. This is not a sophisticated approach to the design of a highly reliable structure; however, it has proven adequate for previous similar designs and is considered qualitatively adequate.

After insertion into orbit, structural loads decrease substantially, and there appears to be no reason for doubting that structural integrity will be maintained indefinitely. The critical period, therefore, is launch-boost. To assure the ability of the structure to withstand this environment, a complete generator system (fuel assembly simulated) should be subjected to a launch-boost environmental test that will closely

CONFIDENTIAL

Functional block diagram

Fig. III-30. Circuit Diagram for 250-Watt DC-to-DC Converter

CONFIDENTIAL

CONFIDENTIAL

MND-3393

simulate the launch-boost environment of temperature, vibration and shock, in duration with cyclical incremental increases in intensity until three times the maximum anticipated is reached or failure occurs. Any failures that occur should be analyzed until the basic cause is determined. Design changes and test reruns should be accomplished, based on these analyses. This process should be continued until failure-free operation is achieved.

d. Analysis and conclusions

Investigation indicates that the thermoelectric generator design is capable of achieving its reliability objective. This opportunity for success is largely due to adequate sealing afforded by brazing the seals to the thermocouple housing as explained. Since inadequate sealing has been the source and primary mode of failure of the telluride-type thermoelectric generator, this inadequacy is to be eliminated by design.

The reliability of the generator will also be 0.999 based on the following considerations:

- (1) Reliability of the heat source approaches 1.0.
- (2) Mechanical reliability of the generator approaches 1.0; there are no moving functional parts.
- (3) Structural reliability of the generator approaches 1.0 since adequate design measures are to be taken to assure failure-free operation at launch-boost.

2. Converter Reliability

A reliability study has been made on the dc-to-dc converter unit. At the present time a tentative circuit configuration is complete. Parts selection should be based on the use of military standard part types, which have been found to meet all design requirements, including reliability, procured from vendors of known performance capability. The transformers, T_1 and T_2 of Fig. III-30, require customization to match the characteristics of the thermocouple input. Any part of in-house construction should be composed of MIL standard materials; all materials should be qualified and thoroughly tested to meet, if not better, requirements of comparable standard parts.

Quantitative data presented here is based upon usage of denoted parts, their parameters and stresses. Quantitative information encompasses failure modes and effects and the effects of radiation.

DECLASSIFIED

~~CONFIDENTIAL~~

a. Failure rate determination

Failure rate data is based on MIL-HDBK-217 (Ref. 1). In comparison, Minuteman parts data are used as a reliable limit. In this way, failure rates become more realistic, since Ref. 1 data are quite conservative, compared to that of Minuteman. Other ultrahigh reliability programs are not considered here since order of magnitude failure-rate reductions beyond Minuteman rates do not create significant reliability improvements in this system.

b. Reliability model

The reliability model is a simple series-type where the failure rate of the dc-to-dc converter (λ_c) is given by:

$$\lambda_c = \sum_{i=1}^n \lambda_i$$

where

λ_i = failure rate of each component

λ_c (MIL-HDBK-217) = 0.3045%/1000 hours

λ_c (Minuteman) = 0.1717%/1000 hours

The converter MTBF is given by the expression

$$MTBF_c = \frac{1}{\lambda_c}$$

$MTBF_c$ (MIL-HDBK-217) = 328,400 hours

$MTBF_c$ (Minuteman) = 582,400 hours

Figure of Merit

$$R(t) = e^{-\lambda_c t}$$

$R(t)$, MIL-HDBK-217 = 0.875

$R(t)$, Minuteman = 0.927

where t = mission time of five years or 43,800 hours.

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

CONFIDENTIAL

III-51

c. Failure modes

There are three ways that a part to fail may be defined to encompass all the possible failure modes. These are the mechanisms of drift, shorts and opens--the latter two being classified as catastrophic modes.

Drift shall be designated here as the change of critical part parameters from their initial values to values outside their acceptable tolerance limits. The drift characteristics of the parts should be tested under severe effects of temperature, stress levels, thermal shock, aging, etc.; and this will determine if the drift characteristics of the unit are within tolerance.

A qualitative study of the two remaining catastrophic failure modes is shown in Table III-9. Data from Ref. 2 provided the failure mode probability inputs.

3. Inverter Reliability

a. Failure rate determination

The failure rate determination for the inverter shall be the same as the converter unit.

b. Reliability model

A reliability study of the inverter unit has been made; at the present time the tentative circuit configuration is essentially complete. The parts selection should be done the same way as the converter parts and the operating stresses for these parts shall not exceed those stress objectives outlined in Table III-10. Basically, the inverter will consist of the converter circuit minus the filtering network to the right of T₂ in Fig. III-30.

The reliability model is a simple series-type where the failure rate of the inverter is given by

$$\lambda_I = \sum_{i=1}^n \lambda_i$$

where λ_i = failure rate of each component

$$\lambda_I \text{ (MIL-HDBK-217)} = 0.197\%/1000 \text{ hours}$$

$$\lambda_I \text{ (Minuteman)} = 0.1272\%/1000 \text{ hours}$$

CONFIDENTIAL

MND-3393

TABLE III-9
Failure Modes and Effects

<u>Part No.</u>	<u>Failure Mode</u>			<u>Probability of Fail. in Mode</u>	<u>General Effects On-</u>		
	<u>Short</u>	<u>Open</u>	<u>Drift</u>		<u>Input</u>	<u>Output</u>	<u>Internal Parts</u>
Source CR1	X				0 volts	0 volts	Converter off. No harm to generator.
Source		X			0 volts	0 volts	Converter off. No harm to generator.
Load CR1	X				Generator voltage reduced due to increased current demand.	0 volts	T ₂ windings draw higher currents. Oscillator may quit due to power drawn to supply load, and to reduced input voltage.
Load		X			Generator voltage greatly increased.	Voltage greatly increased. (>2 times)	C ₁ has higher voltage across terminals.
C ₁	X			5%	Generator voltage reduced due to increased current demand.	0 volts	T ₂ windings draw higher currents. Oscillator may quit due to power drawn to supply load, and to reduced input voltage.

MND-3393

CONFIDENTIAL

TABLE III-9 (continued)

Part No.	Failure Mode			Probability of Fail. in Mode	Input	General Effects On-	
	Short	Open	Drift			Output	Internal Parts
C ₁		X		5%	No effect	Normal voltage and power levels. Loss of filtering. Ripple and transients on load.	Turn-on and pulse transients may be harmful (when not connected to system load).
Q ₅ , Q ₆ collector base		X		2.5%	Generator voltage increased due to lighter loading.	Less power delivered to load. Increased ripple.	No harm to other parts.
T ₂ secondary		X		10%	Generator voltage increased due to lighter loading.	Less power delivered to load. Increased ripple.	No harm to other parts.
Primary T ₂		X		10%	Generator voltage increased due to lighter loading. Oscillations may be nonsymmetrical due to unequal input Z of Q ₃ and Q ₄ .	Less power delivered to load. Voltage should have more ripple content than normal.	No harm to other parts.
Q ₃ , Q ₄ base-emitter junction		X		2.5%	Generator voltage increased due to lighter loading. Only 1/2 of power amplifier is operational.	Less power delivered to load. Voltage should have more ripple content than normal.	No harm to other parts.

CONFIDENTIAL
MIND-3393

CONFIDENTIAL

III-53

TABLE III-9 (continued)

Part No.	Failure Mode			Probability of Fail in Mode	General Effects On-		
	Short	Open	Drift		Input	Output	Internal Parts
Q ₃ , Q ₄ base- collector junction		X		2.5%	Generator voltage increased due to lighter loading. Oscillations may be nonsymmetrical due to unequal input Z of Q ₃ and Q ₄ .	Less power delivered to load. Voltage should have more ripple content than normal.	No harm to other parts.
Q ₃ , Q ₄ collector emitter		X		10%	Generator voltage increased due to lighter loading. Oscillations may be nonsymmetrical due to unequal input Z of Q ₃ and Q ₄ .	Less power delivered to load. Voltage should have more ripple content than normal.	No harm to other parts.
T ₁ secondary		X		10%	Generator voltage increased due to lighter loading. Only 1/2 of power amplifier is operational.	Less power delivered to lead. Voltage should have more ripple content than normal.	Open base of Q ₂ or Q ₃ may destroy transistor due to thermal run-away.
T ₁ feedback winding		X		10%	Oscillations cease. Generator voltage greatly increased due to light loading.	0 volts	Open base of Q ₁ (or Q ₂) may destroy transistor due to thermal run-away. Q ₁ (or Q ₂) on steadily.

MND-3393

CONFIDENTIAL

CONFIDENTIAL

TABLE III-9 (continued)

Part No.	Failure Mode			Probability of Fail in Mode	Input	General Effects On-	
	Short	Open	Drift			Output	Internal Parts
T ₁ primary		X		10%	Oscillations cease. Generator voltage greatly increased due to light loading.	0 volt	No harm to other parts.
Q ₁ , Q ₂ base to emitter junction	X			5%	Oscillations cease. Generator voltage greatly increased due to light loading.	0 volt	No harm to other parts.
Q ₁ , Q ₂ base to collector junction	X			5%	Oscillations cease.	0 volt	No harm to other parts.
R ₁		X		95%	Oscillations may not start. Pulse shapes may be poor.	0 volt if there are no oscillations. Normal output at slightly reduced efficiency when oscillations are started.	No harm to other parts.

CONFIDENTIAL

MND-3393

CONFIDENTIAL

III-55

TABLE III-9 (continued)

Part No.	Failure Mode			Probability of Fail in Mode	Input	General Effects On-	
	Short	Open	Drift			Output	Internal Parts
R ₂		X		95%	Oscillations may not start. Pulse shapes may be poor.	0 volt if there are no oscillations. Normal output at slightly reduced efficiency when oscillations are started.	No harm to other parts.
C ₂ , C ₃	X			0.95	Generator voltage reduced due to short circuit of output on 1/2 cycle.	Discharge load on 1/2 cycle.	May harm Q ₅ (or Q ₆) due to 1/2 cycle current surges.
C ₂ , C ₃		X		0.05	No effect.	No noticeable effect, although not quite as clean filtering.	No effect.
L ₁		X		1.0	Generator voltage greatly increased due to no load.	0 volt	No harmful effects. Slightly greater stress on voltage sensitive part parameters.
CR ₁	X				Generator voltage reduced to increased current demand.	0 volt	T ₂ windings draw higher currents. Oscillator may quit due to power drawn to supply load, and to reduced input voltage.

CONFIDENTIAL

MND-3393

CONFIDENTIAL

CONFIDENTIAL

TABLE III-10

Failure Rate Estimation for 250-Watt Power Supply Converter

1	2	3	4	5	6	7	8	9	
No. of Parts	Parts Symbol	Description	Type	Operating	Stress Rated	Ratio	λ 217	λ Minuteman	
1	CR ₁	Diode	Si (-Pow) zener			≤ 0.1	0.010	0.002	MIL-HDBK-217
1	C ₁	Capacitor	#Solid tantalum			≤ 0.8	#0.0075	0.0035	$R_C = e^{-\lambda t}$
1	C ₂	Capacitor	Paper Hi-Rel			≤ 0.6	0.010	0.0015	$\lambda = 0.3045 f / 10^5$ hours
1	C ₃	Capacitor	Paper Hi-Rel			≤ 0.6	0.010	0.0015	$t = 43,800$ hours
1	Q ₁	Transistor	SiI (25 to 150)°C			≤ 0.1	0.020	0.0030	$R_C = e^{-0.1334}$
1	Q ₂	Transistor	SiI (25 to 150)°C			≤ 0.1	0.020	0.0030	> 0.8751
1	Q ₃	Transistor	SiI (25 to 150)°C			≤ 0.1	0.020	0.0030	
1	Q ₄	Transistor	SiI (25 to 150)°C			≤ 0.1	0.020	0.0030	
1	Q ₅	Transistor	SiI (25 to 150)°C			≤ 0.1	0.020	0.0030	Minuteman
1	Q ₆	Transistor	SiI (25 to 150)°C			≤ 0.1	0.020	0.0030	$R_C = e^{-\lambda t}$
1	R ₁	Resistor	RC			≤ 0.1	0.001	0.0001	$\lambda = 0.1717 f / 10^5$ hours
1	R ₂	Resistor	RC			≤ 0.1	0.001	0.0001	$t = 43,800$ hours
1	T ₁	**Transformer	Saturated core		--	--	0.050	0.0500	$R_C = e^{-0.0752}$
1	T ₂	**Transformer	Power		--	--	0.050	0.0500	$= 0.9275$
1	L ₁	**Inductor	Choke		--	--	0.025	0.0250	
27	--	*Solder joints	--		--	--	0.020	0.0200	
							0.3045	0.1717	
Reliability Estimation for 250-Watt Power Supply Inverter									
1	***Q ₁	Transistor	SiI (25 to 150)°C				0.020	0.003	MIL-HDBK-217
1	***Q ₂	Transistor	SiI (25 to 150)°C				0.020	0.003	$R_C = e^{-\lambda t}$
1	***Q ₃	Transistor	SiI (25 to 150)°C				0.020	0.003	$\lambda = 0.197 f / 10^5$ hours
1	***Q ₄	Transistor	SiI (25 to 150)°C				0.020	0.003	$t = 43,800$ hours
									$R = e^{-197 \times 10^{-5} \times 4.38 \times 10^{-4}}$
									$= e^{-0.0862} = 0.174$
1	R ₁	Resistor	RC				0.001	0.0001	Minuteman
1	R ₂	Resistor	RC				0.001	0.0001	$R_C = e^{-\lambda t}$
1	**T ₁	Transformer	Saturated core				0.050	0.050	$\lambda = 0.1272 f / 10^5$ hours
1	**T ₂	Transformer	Power				0.050	0.050	$t = 43,800$ hours
18	--	Solder joints	--				0.015	0.015	$R_C = e^{-0.0557} = 0.9458$
							0.197	0.1272	

Ambient temperature = 60°C.

*Solder joints based on 2/3 total leads $\approx$ number of junctions; all parts mounted on printed circuit board.

**Construction to conform with MIL-T/27A as a minimum requirement.

***Transistor and diode normalized temperature (T_N) is 0.28.

#Computed based on Ref. 5.

CONFIDENTIAL
MIND-3393

CONFIDENTIAL

~~CONFIDENTIAL~~

The inverter MTBF is given by

$$MTBF_I = \frac{1}{\lambda_I}$$

$$MTBF_I \text{ (MIL-HDBK-217)} = 507,600 \text{ hours}$$

$$MTBF_I \text{ (Minuteman)} = 786,100 \text{ hours}$$

Figure of Merit

$$R(t) = e^{-\lambda_I t}$$

where t = mission time of five years or 43,800 hours

$$R(t), \text{ MIL-HDBK-217} = 0.917$$

$$R(t), \text{ Minuteman} = 0.945$$

c. Radiation effects

Both the converter and the inverter units are the most susceptible to radiation; some precautions that should be taken are given.

A radiation environment may be instrumental in causing drift and catastrophic failures. A detailed and descriptive explanation of radiation effects on the parts may be found in Refs. 3 and 4. A special effort should be made to select materials and parts least affected by a radiation environment. Parts each have characteristic damage thresholds, therefore; a predicted safe gamma ray dosage and neutron dosages should be determined. In designing the system layout, the best combination of spacing and shielding should be chosen to assure safe gamma ray and neutron dosages. Since axial distance of the converter from the generator has been kept open in the mechanical design, for both the extended and unextended modes, a mounting distance in each mode should be selected with respect to safe dosage. Shielding should be implemented only if necessary.

Converter irradiation may be best described by the following diagram (Fig. III-31), and may be classified as originating within the vehicle or externally. The significant internal radiation is the bremsstrahlung gamma ray. Dose rates as a function of generator distance are described in Ref. 4.

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

Fig. III-31. Sources of Converter Irradiation

Gamma ray exposure creates a transient effect on parts, although permanent set may occur due to secondary effects, such as the heating of metal parts (Ref. 5).

External radiation is manifested by proton and electron levels, and is especially significant in the Van Allen belt. Parts may experience deterioration when exposed to external radiation, also converter exposure may be described in terms of an extended or an unextended housing with respect to axial distance from the nuclear generator, a much larger dose being experienced in the latter case. Figure III-32 depicts conservatively estimated exposure times in the unextended mode.

The system should be designed to function satisfactorily after the converter unit has been exposed to the radiation level in the unextended position five times.

4. Overall Limitations of Reliability Estimate--Converter and Inverter

The reliability estimate was based on the assumption that the regulating means in the converter unit would be a zener diode. However, if a more complex regulating circuit is needed, the reliability of each power supply considered would range between 0.779 and 0.738 based on the following reasoning.

Table III-11 lists the description of parts in the regulator, the quantity of each kind of part, assumed stress ratio and conservative estimates of the Minuteman failure rates as listed in MIL-HDBK-217; as a more conservative estimate, another assessment is given based on MIL-HDBK-217 high reliability parts.

DECLASSIFIED
CONFIDENTIAL

Fig. III-32. Converter Housing Unextended--Proximity to Intense Radiation

TABLE III-11
Regulator Parts Description

Kind of Part	Minuteman Estimate				MIL-HDBK-217 Estimate	
	Quantity	Stress Ratio	λ_i	λ_i	λ_i	λ_i
			(%/1000 hr)	(%/1000 hr)	(%/1000 hr)	(%/1000 hr)
Capacitor	1	0.8	0.004	0.004	0.025	0.025
Diode	5	0.1	0.007	0.035	0.010	0.050
Resistor	9	0.1	0.0007	0.0063	0.001	0.009
Transistor	5	0.1	0.003	0.015	0.020	0.100
Total				0.0603%/1000 hr		0.184%/1000 hr

CONFIDENTIAL

MND-3393

DECLASSIFIED

The failure rate model is as follows:

$$\lambda_R = \sum_i \lambda_i$$

where

λ_R = failure rate of the regulator circuit

λ_i = failure rate of each part.

A comparison of the two failure rates for the regulator circuit is:

$$\lambda_R^* \text{ (Minuteman)} = 0.0603\% / 1000 \text{ hours}$$

$$\lambda_R \text{ (MIL-HDBK-217)} = 0.184\% / 1000 \text{ hours.}$$

The reliability model for the regulator circuit is

$$R_R(t) = e^{-\lambda_R t}$$

where

$R_R(t)$ = reliability of the regulator circuit

λ_R = failure rate of the regulator circuit

t = mission time of five years or 43,800 hours.

A comparison of the two reliability figures for the regulator circuit is:

$$R_R^*(t) \text{ Minuteman} = 0.9738$$

$$R_R(t) \text{ MIL-HDBK-217} = 0.9225.$$

Since the reliability of each power supply is 0.80, and since a regulator may be added, the reliability may vary between two limits

DECLASSIFIED

~~CONFIDENTIAL~~

$$R_P R_R < R < R_P R_R^*$$

where

R_P = reliability of each power supply

R_R = reliability of regulator circuit (MIL-HDBK-217)

R_R^* = reliability of regulator circuit (Minuteman).

Specifically, the model becomes

$$(0.80) (0.9225) < R < (0.80) (0.9738)$$

$$0.738 < R < 0.779.$$

This last inequality means that the reliability of each power supply may range between 0.738 and 0.779, depending on whether or not the regulator parts can approach Minuteman failure rates.

5. Cooling System

The cooling system is composed basically of radiator piping, a redundant pump network operating in parallel standby, a control unit consisting of thermostatic switching for the pumps, and a pressure accumulator which maintains constant water pressure throughout the cooling system. The nature of the pressure accumulator is such that it is fundamentally a very reliable unit; the reliability of the pressure accumulator approaches 1.0. Similarly, the reliability of the thermostatic switching controls for the pumps also approaches 1.0, since a thermostat is fundamentally a very reliable part and each thermostat will be called upon to act only once during its five-year mission. Therefore, the reliability of the cooling system reduces to a function of the reliability of the pumps and the probability that the radiator tubing will not experience meteoroid puncture.

a. Failure modes

A primary mode of failure is coolant leakage. Tests should be run to assure a leakproof cooling system which will involve functional performance of a complete cooling system in an environment of temperature cycling, vibration and shock in excess of that which the cooling system will experience in actual use. In addition, the radiator tubing

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

0315087030

III-63

which is brazed against the skin of the missile has a possibility of failure due to meteorite puncture. The design of the radiator tubing will be such so as to make this probability very small. The pumps which circulate the coolant throughout the system also may fail--the primary mode of failure will be bearing wear in the pumps due to the extreme shock and vibration environment at launch-boost coupled with the normal thrust loading during pump operation. The pumps should be qualified by testing to environmental stresses of shock and vibration in excess of launch levels, followed by endurance testing at pump loads much higher than mission loads. Thus, by proper design selection and testing, there will be a high probability that the redundant pump network will have failure-free operation during its five-year mission. To date, the number of pumps that will be required to achieve the reliability objective for the redundant pump network is not specified, but, based on existing data, it appears that either three or four will be sufficient.

b. Failure rate determination

Failure rate determination for the puncture of the radiator tubing by a meteoroid is based on the armor thickness required in Appendix E, the 2.5 mils of armor strip placed in front of the tube gives approximately a 0.956 probability of no meteoroid puncture of the radiator tubes during its five-year mission. To date, failure rate data on the pumps are incomplete; however, based on data from Ref. 6 and from pump manufacturers and by adequate testing, it is felt that a failure rate that will meet the reliability objective of 0.80 can be achieved.

c. Reliability model

To achieve the reliability objective of the dynamic system, the reliability of the cooling system should be approximately 0.9177.

The reliability model for the cooling system is a simple series-type where:

$$R_{CO}(t) = R_R(t) \cdot R_P(t)$$

where

$R_{CO}(t)$ = reliability of the cooling system

$R_R(t)$ = probability of no meteoroid puncture of radiator tubing

$R_P(t)$ = reliability of the redundant pump network

t = mission time of five years or 43,800 hours.

~~CONFIDENTIAL~~

MND-3393

031720A030

DECLASSIFIED

III-64

~~CONFIDENTIAL~~

Figure of Merit

$$R_{CO}(t) = R_R(t) \cdot R_P(t)$$

$$R_R(t) = 0.956$$

$$R_P(t) = 0.960$$

$$R_{CO}(t) = 0.9177.$$

The reliability of the pump network was obtained by dividing the reliability of the cooling system by the probability of the meteoroid puncture.

6. Overall Dynamic System Reliability

a. Estimate of system reliability

The operational reliability of the 250-watt dynamic power system is the product of the reliabilities of the generator, the converter, the inverter, and the cooling system. The estimated reliabilities of the generator, the converter, the inverter and the cooling system are 0.999, 0.927 (Minuteman parts), 0.945 and 0.917, respectively. System reliability, therefore, is estimated at greater than 0.80.

b. Limitations and quality of estimate

Stress and failure rate data for the converter and inverter were derived from MIL-HDBK-217 which is reasonably authoritative. All components and parts except two, which have demonstrated a high reliability in previous space applications, are military standard parts, and the specifications to which they were tested should be checked to assure that they have been tested to environmental levels equal to or greater than those to be experienced by the 250-watt power system. These data form the basis for the reliability estimate which is believed to be conservative.

Generator reliability is primarily a question of thermocouple reliability, and currently available test data allows for a mean estimate of the thermocouple failure rate to be made. Moreover, analysis of the segmented telluride-type thermocouples indicates that they should function in the operational environment indefinitely, far beyond the required five-year period.

The cooling system reliability is mainly a question of the redundant pump network reliability: the test data that are available along with the

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

0313587030

11-65

fact that these pumps should be stringently qualified indicate that the reliability objective of failure-free operation for a period of five years is within reach.

7. Recommendations for Critical Reliability Testing

The following are the recommendations made for critical reliability testing.

- (1) Exploratory tests of thermocouple assemblies to determine environmental limits in vibration, shock and temperature.
- (2) Exploratory tests of thermocouple material to determine strengths at operational temperature ranges in shear, compression, tension, etc.
- (3) Detailed structural analysis of fuel capsule assembly to determine load distributions at critical points.
- (4) Qualification tests for the pumps which will assure a high probability of the design meeting the vibrational limits at launch-boost, and the wearout limits due to normal thrust loading.
- (5) Environmental tests of the cooling system to assure design adequacy of the coolant system for leakage.
- (6) Exploratory tests to determine the adequacy of the seal design in the thermoelectric generator.
- (7) Environmental and exploratory tests on the converter and inverter to determine whether failure rates were increased above that which was predicted.
- (8) Environmental testing of the control system to determine that the unit will function as reliably as predicted.

E. REFERENCES

1. "Reliability Stress and Failure-Rate Data for Electronic Equipment," MIL-HDBK-217, 8/8/62.
2. "Advent Program Reliability Handbook," TRA-873-74, General Electric, 7/1/61.
3. "The Effect of Nuclear Radiation on Electronic Components and Systems," REIC Report No. 2, Radiation Effects Information Center, Battelle Memorial Institute, 12/31/57.

~~CONFIDENTIAL~~

MND-3393

03172281030

DECLASSIFIED

~~CONFIDENTIAL~~

4. "Space-Radiation Damage to Electronic Components and Materials," REIC Report No. 32, Radiation Effects Information Center, Battelle Memorial Institute, 10/30/63.
5. Malanga, M. and Moynihan, J., "Failure-Rate Determination for Type 350D Hydrel St Solid Tantalum Capacitors," Sprague Technical Paper No. 62-15, 1962.
6. "Feasibility of Isotopic Power for Manned Lunar Missions," MND-3296-3, Martin Company. ~~CONFIDENTIAL~~

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

~~CONFIDENTIAL~~

031507030

IV-1

IV. STATIC GENERATOR SYSTEM

A. GENERAL

1. System Description

The static generator system consists of a heat source radiating energy to the thermoelectric packages, which in turn convert part of the thermal energy to electrical power and reject the remaining thermal energy at the cold junction to heat rejection fins. This waste energy is then radiated to space.

A dc-to-dc converter conditions the 14-volt generator output to a regulated 28 volts (dc). The voltage regulation included in the converter serves two purposes: it limits the load voltage to the prescribed value and acts to minimize the hot junction temperature during the beginning-of-life fuel overload.

The basic components of the generator consist of the beryllium radiator plates, fuel capsules and assembly, SiGe alloy thermoelectric modules, heat rejection fins and the structure required to support the subassemblies relative to each other.

The generator assembly will automatically break up on re-entry, or can be separated by explosive couplings on command, to expose the fuel capsules for burnup.

2. Performance Summary

The two thermoelectric modules of the generator produce a gross output power of 278 watts(e) at end of life. The net output power supplied by the generator out of the 90% efficient dc-to-dc converter is 250 watts at $28 \pm 1\%$ volts. A 6.13% thermoelectric efficiency is obtained at end of life with hot and cold junction temperatures of 1500 and 610°F, respectively. The overall system net efficiency is 5.01%. The unshielded weight of the generator is 184 pounds, plus 10 pounds for a typical converter.

B. DESCRIPTION OF COMPONENTS

The static generator (Fig. IV-1), like the dynamic system, is designed as a rigid assembly for ground, launch, and orbiting conditions; but it will break up into sections upon re-entry. The breakup is initiated by the release of V-band clamps which will readily burn through because of very high local heating in the thin band sections between supports. Once the bands are released, the two radiator

~~CONFIDENTIAL~~

MND-3393

037228030

Fig. IV-1. Static Generator

~~CONFIDENTIAL~~

0315087030

IV-3

plates with the thermoelectric modules attached are free to fall away, releasing the front and rear supports of the fuel capsule assembly. The fuel assembly will then fall apart, allowing each capsule to fall free. Aerodynamic pressures are sufficient to supply the required forces for generator breakup. The purpose of the breakup feature is to assure that the capsules will burnup completely at an altitude sufficiently high to allow adequate fuel particle dispersion.

1. Fuel Capsules

The fuel capsule design for the static system as shown in Fig. IV-2 is similar in appearance to the capsule used in the dynamic system in that both are cylinders with hemispherical ends and have the same external dimensions. The major difference is in the material selection necessitated by the extremely high temperature of the static system fuel capsule (2000° F). This temperature prohibits the use of Haynes-25 or the Hastelloy alloys which show a rapid decrease in mechanical properties above 1800° F. A materials search has indicated that thoria-dispersed (TD) nickel is the best available choice. The choice is not based on the mechanical properties at temperature alone, but also on the oxidation, sublimation, and melting point considerations. Other alloys have superior strength at this temperature, but their melting points are so high that it is very doubtful that the fuel capsule would burn as required by the safety criteria.

The oxidation rate of TD nickel is satisfactory, but sublimation is a problem at 2000° F in a hard vacuum. To overcome this, a 0.010 inch platinum sheath is placed over the capsule to provide the required protection. The capsule strength is in the 0.090-inch cylindrical wall and the 0.190-inch thick hemispherical end cap of TD nickel.

The capsule is made in two sections as is the capsule for the dynamic system. However, after making the capsule closure weld it will be necessary to make a seal weld in the platinum sheath over the capsule. The weld joint is located at the quarter length point, as in the dynamic system capsule, so that it does not receive the high impact stresses felt at the end of the capsule. Due to the change of thoria dispersion in a weld zone in TD nickel, it is necessary to use 80% of the normal allowables in the weld zone.

Arranged axially along the central region of the capsule are beryllium metal disks. These disks are compacted with the fuel during fuel loading of each capsule section and take up approximately 11% of the total volume of the capsule. The use of the beryllium disks reduces the large temperature gradient that would normally be present at operating temperatures with this generator.

~~CONFIDENTIAL~~

MND-3393

0315087030

CONFIDENTIAL

CONFIDENTIAL

Fig. IV-2. Fuel Capsule Static System

CONFIDENTIAL
MND-3393

~~CONFIDENTIAL~~

IV-5

2. Fuel Capsule Assembly

The fuel capsule assembly of the static generator system (Figs. IV-1 and IV-3) contains 18 fuel capsules. As discussed in the section dealing with the dynamic system fuel capsule, the capsule diameter and wall thickness were determined by capsule burnup and impact requirements, and the length was kept sufficiently short to prevent buckling. The problem then reduced to that of dividing the total capsule fuel volume required by the available volume per capsule with an even number of capsules as a prerequisite to fill the double row of fuel capsules. The projected area of the fuel capsules also had to be approximately equal to the thermoelectric module area for optimum radiant heat transfer to the thermoelements.

Since silicon-germanium elements may be operated in air or in a vacuum, a sealed module chamber is not required in the static system. It is therefore possible to radiate the heat from the fuel capsules directly to the hot shoes of the thermoelements.

The ends of the fuel capsules are nested into chamfered holes of the capsule support plates located at both ends of the capsules (see Fig. IV-3). These plates are then clamped together by two fueling machine handling rods with a ball lock arrangement which will hold the plates tightly against the capsules and in proper alignment during fueling or defueling. The door and door insulation are also supported on these same rods.

The installation of the fuel capsule assembly is accomplished by inserting the fuel assembly and rods into the generator. The fueling machine handling rods also serve to guide the assembly into proper position. The fuel capsule support plates (Fig. IV-3) are now supported in the generator by ball and socket joints. The balls are part of the capsule support plates while the sockets are of aluminum oxide and supported by thin-wall conical sections. Two of these supports are mounted on base plates on the back wall of the generator and two on the base plates of the fuel assembly door. When the ball and socket joints on the back wall of the generator are mated, the fuel assembly is sealed and locked into the generator. After the assembly is locked, the handling rods are removed.

The door latch is identical to that used on the dynamic system. Two parallel latch bars are aligned with the outer edges of the door. On the outboard side of each bar are two wedge shape protrusions. The bars are driven apart by cams located at either end, and the wedges engage fittings in the radiator plates, forcing the fuel capsule assembly to seat securely in the ball and socket joints, and at the same time restraining the door fuel capsule assembly from lateral motion. The cams and latch bars are locked against reverse rotation by sawtooth splines. The fuel capsule assembly may be removed

~~CONFIDENTIAL~~

MND-3393

~~CONFIDENTIAL~~

Fig. IV-3. Static Generator Layout

~~CONFIDENTIAL~~

MNS-3293

~~CONFIDENTIAL~~

0315587030

IV-7

by inserting the fueling machine handling rods and depressing the cams against Belleville springs which disengage the splines allowing the cams to be reversed. A pin in the latch bar rides in a groove in the cam to force the wedges to retract, assuring release.

The fuel capsule support plates, ball joints, and conical supports are made of Hastelloy C, selected for its strength at temperature and its low thermal conductivity which keeps heat losses through the conical support to a minimum. The Belleville springs will be made of Inconel-X, chosen for its ability to maintain spring characteristics at high temperature. Beryllium was selected for the base plate material because of its good strength-to-weight ratio. The latch will be made of steel for strength. Critical points will be protected against vacuum welding by material selection or the use of an interface material.

3. Thermoelectric Module

Silicon-germanium thermoelements are used in the static system generator. The silicon-germanium elements can operate at a high cold junction temperature which keeps the radiator size down. They can be operated in air or in a vacuum which eliminates the need for a sealed module chamber.

The basic SiGe thermocouple (see Fig. IV-4) is a one-piece, metallurgically bonded, rigid assembly constructed from a silicon alloy heat acceptor plate, and N-type and P-type SiGe alloy half cylinder legs. These are terminated at the cold junction by tungsten metal contacts suitable for brazing to an insulator stack which in turn is brazed to a beryllium heat sink. All joints in the basic thermocouple are formed at temperatures substantially in excess of the maximum operating temperature and have been shown by tests on the SNAP 10A and SNAP 17A programs to be stable during prolonged thermocouple operation at temperatures in excess of 1870° F. The silicon alloy hot junction plate, the SiGe legs and the tungsten shoes are closely matched in thermal expansion to assure that the joints remain essentially stress-free under all conditions. Because continuous metallurgical joints are employed in the thermocouple construction, contact resistances remain at low levels. Typical values of contact resistance measured in bonded thermoelements are equivalent to 2% of the resistance of a one centimeter SiGe cube per contact for P-type material and 3% of the resistance of a one centimeter SiGe cube per contact for N-type material. Due to the light weight of the thermocouple unit and the strong bonds, the thermocouples are able to withstand high g loadings.

Each thermoelectric couple is mounted on an oversized brazed insulator stack assembly containing a 0.020-inch thick ceramic insulator to provide electrical isolation from the connecting assembly. One hundred couples are connected in a series-parallel arrangement by

~~CONFIDENTIAL~~

MND-3393

03170041030

DECLASSIFIED

IV-8

CONFIDENTIAL

Fig. IV-4. Thermoelectric Couple Static System

CONFIDENTIAL

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

0315087030
IV-9

copper straps running between the insulator stacks to which the thermocouples are bonded. The compensated insulator stack is free from warpage at temperature due to matched thermal expansions. Since two modules of 100 couples are used in the generator, the loss of a single couple only causes a power loss of approximately 1/200 of the total.

4. Thermal Insulation

Foil-type insulation is used in this generator, since it is far more efficient than fibrous insulations at the higher temperatures of the static system generator. The foil insulation is composed of 100 titanium foils 0.0025 inch thick separated by layers of quartz fiber. In the thermoelectric module area, it is necessary to place a quartz fiber sleeve around the thermoelements to prevent electrical shorting between the elements and the insulation foils. Min-K insulation is used on the front and rear panels within the four conical fuel core supports because it can be readily fabricated to the required shape. The insulation is held in place by the radiator plates on the sides, and thin sheet metal panels on the other four sides. In the front the insulation forms part of the door assembly.

5. Radiator

The radiator in the static system must be operated at a relatively high temperature to keep the required radiator size to a minimum. Beryllium plate is used to provide structural strength at the design temperature and have minimum weight. As previously stated, the radiator plates are an integral part of the thermoelectric modules, but they are also the primary structural members of the generator since all of the generator loads will pass through them. The radiator plates are held in position by the sheet metal side panels which are attached by means of V-band clamps. When these bands are released, the generator is free to separate.

One continuous fin runs around the periphery of each radiator plate forming a 135-degree angle to the normal. This design was used in lieu of more conventional type fins to improve the fin view factor for radiant heat rejection. It resulted in a weight saving over the conventional fin concept.

The radiator configuration is omnidirectional in that it rejects heat along the six major axes. This gives a minimum radiator weight, but it may be undesirable from the standpoint of thermal input to other structures. If this should be a problem, the side of the fins facing the problem area can be silvered; and the fin root to tip dimension increased slightly to compensate for the ineffective radiator area.

~~CONFIDENTIAL~~

MND-3393

037228030

Fig. IV-5. Silicon Germanium Alloy Thermoelectric Efficiency Versus Temperature

~~CONFIDENTIAL~~

03115087030

IV-11

6. DC-to-DC Converter

The dc-to-dc voltage stepup converter and regulator for the static system will be similar in all respects to that of the dynamic system discussed in Chapter III. The only difference is that the generator will deliver only 278 watts to the converter input terminals, since no a-c power is required. This converter is estimated to weigh approximately 10 pounds.

It should be noted that almost any voltage can be made available to the payload by changing transformer ratios, or by placing a center tap on the output of the transformer, T2. Thus, any payload voltage requirement can be accommodated within the system design using this d-c converter. If 28 volts is the only voltage required, then the generator could be made lighter by eliminating the converter entirely and designing the thermoelectric system to produce 28 volts.

7. Installation

Several variations in system installation are possible. The generator should be mounted near the surface of the vehicle to facilitate remote fueling of the generator in the gantry. The generator may be mounted in either a vertical or horizontal position. To keep the generator structure weight down, external supports attached to the vehicle should be used on the generator during launch. These supports should then be discarded with the Agena vehicle so as to permit generator breakup during re-entry. The generator must be installed on the satellite in a location such that it is not shielded from aerodynamic heating during re-entry to assure its breaking up. The generator may be separated from the other satellite equipment if radiation or radiation shield weight becomes a problem. This may be done after launch by the use of extension devices such as the DeHavilland STEM (Self-storing Tubular Extendible Member).

C. SYSTEM PERFORMANCE AND OPTIMIZATION

1. Thermoelectric Efficiency

The thermoelectric efficiency for the silicon germanium alloy thermoelectric system as a function of hot and cold junction temperatures are presented in Fig. IV-5. These efficiencies were computed with the Martin IBM 7094 Code VINCE-TOM, Thermoelement Optimization Code. Data used are those in use on the SNAP 17A program as of May 15, 1964. The pertinent materials properties and details of the calculations are presented in Appendix L.

~~CONFIDENTIAL~~

MND-3393

031710291030

DECLASSIFIED

IV-12

~~CONFIDENTIAL~~

Configuration A

Configuration B

Configuration C

Configuration D

Configuration E

Fig. IV-6. Radiator Configurations

DECLASSIFIED

~~CONFIDENTIAL~~

MND-3393

The design points selected for the 250-watt static system are a hot junction temperature of 1500° F and a cold junction temperature of 610° F. For these temperatures, the thermoelectric efficiency is 6.13%.

From previous studies, it was known that fuel capsule temperature limitations would limit the hot junction temperature at the design point to 1500° F or less. It was also known that for a given hot junction temperature, thermoelectric conversion material and fuel and power levels, there is a cold junction temperature for which generator weight will be a minimum. Previous studies (MND-2994, June 1963) indicated that this optimum cold junction temperature would be over 600° F for a Sr-90 fueled, SiGe, 250-watt generator if shield weight were not included in the generator optimization. Since any Sr-90 system design must consider shielding, 610° F was selected as the approximate cold junction temperature to make the generator more closely resemble the generator for an optimum system, rather than an artificially minimum weight generator. Calculations based on the selected system indicate that the minimum generator weight occurs at a cold junction temperature of 700° F, the generator being eight pounds lighter than the selected design.

2. Radiator Optimization

Extensive design studies have been conducted on both radiator configuration and minimization of radiator weight for the selected configuration. The study consisted of two parts: selection of the lowest weight fin arrangement for the rectangular generator with large plate modules; and minimization of fin and module base plate weights for the best configuration.

a. Radiator configuration study

The many possible radiator configurations were analyzed and compared using simple techniques. A required radiator area was determined for an effective radiator temperature of 600° F and a heat rejection rate of 2500 watts. The approximate effective radiating area of the various configurations was determined using the string method and an assumed fin efficiency. Fin dimensions (root-to-tip and root thickness) were adjusted to give the required area and assumed efficiency. The weight of the fin material was then calculated. The configurations were compared on the basis of the weight of required fin material. The five most interesting configurations studied are illustrated in Fig. IV-6. The results are summarized in Table IV-1. Details of the calculations may be found in Appendix H. The configurations are compared in Table IV-1 on the basis of normalized weight where the normalized value is

$$\text{Weight (nom)} = \frac{\text{value for configuration under consideration}}{\text{value for Configuration E}}$$

Configuration F

Configuration G

Fig. IV-7. Cylindrical Generator Configurations

~~CONFIDENTIAL~~

03115087030

IV-15

TABLE IV-1

Static System Radiator Configuration Comparison

Conditions of comparison: Root temperature = 600° F
Fin-efficiency = 80%
Emissivity = 0.8
Heat to be rejected = 2500 watts
Density of fin material = 0.067 lb/in.³ (Be)
Thermal conductivity of fin = 79 Btu/hr-
°F (Be)
Length and width of base plate = 12.25 in.

<u>Configuration</u>	<u>A</u>	<u>B</u>	<u>C</u>	<u>D</u>	<u>E</u>
Fin root-to-tip dimension*	0.706	1.06	-	1.24	1.0
Fin root thickness*	1.41	1.41	-	1.41	1.0
Fin weight*	1.21	1.07	2.09	1.76	1.0

*All values normalized to Configuration E.

This was done because the initial study was performed with other than the final generator dimensions and for nonoptimum fin efficiencies. The two most attractive Configurations, B and E, were both investigated in detail for all fin efficiencies and for the actual generator dimensions. They retained the same relative positions as presented in Table IV-1. Configuration E was the lightest configuration and was selected for the static generator.

b. Other generator configurations

A cylindrical generator, similar in appearance to SNAP 17A was also investigated. Two configurations are shown in Fig. IV-7. Configuration F, the generator with conical end fins, is the superior configuration with respect to both weight and volume.

To keep the fuel capsule temperatures at reasonable levels due to the large quantity of fuel, it is necessary to arrange them in a single circle within the generator so that interior capsules view of the hot shoes is not obstructed by other capsules. Also, they should be arranged in a single tier in the vertical direction to avoid as much as possible serious structural problems in supporting the fuel capsules and holding them together during fueling. The resulting single ring of capsules

~~CONFIDENTIAL~~

MND-3393

03172081030

~~CONFIDENTIAL~~

yields a generator with a very large diameter-to-length ratio, and with a considerable amount of waste volume in the center of the generator. The two cylindrical generators are compared in Table IV-2. It can be seen that the overall weight and size of Configuration F will be considerably smaller than those of Configuration G.

Comparing all configurations, the rectangular generator occupies a much smaller volume. That is, it will fit into a 25% smaller box (14,500 in.³ for the rectangular generator versus 18,000 in.³ for the cylindrical generator).

TABLE IV-2
Cylindrical Generator Comparison

$$T_R = 600^\circ \text{ F}, \eta_f = 60\%$$

	<u>Configurations</u>	
	<u>Configuration F</u>	<u>Configuration G</u>
Central core (in.)		
Height	9	9
Diameter	18	18
Fins		
Root-to-tip width (in.)	7.67	44
Root thickness (in.)	1.15	7.7
Weight (lb)	30	68
Overall dimensions (in.)		
Height	19.8	9
Diameter	28.8	106

With the increase in overall volume which necessitates increasing the structural and fuel assembly members, the cylindrical configuration will weigh more than the selected rectangular configuration. Also, with the larger configuration, vehicle mounting and generator fueling becomes more difficult.

Based on these considerations the rectangular configuration was selected as the generator design for the static system.

~~CONFIDENTIAL~~

0110507030

IV-17

c. Fin and module plate optimization

Using the fin arrangement selected (Configuration E) in the configuration study, a careful analysis was made of the fin size and weight needed to reject the heat. Expressions were developed for the fin root-to-tip dimension, the fin root thickness, and the weight of fin material as functions of fin efficiency. The fin weight was then computed as a function of efficiency. The derivations and calculations may be found in Appendix I, Part 2. The results are presented in Fig. IV-8. From Fig. IV-8, it can be seen that the minimum weight fin is 60% efficient. For this efficiency, the fin root-to-tip dimension is 7.25 inches and the fin root thickness is 0.42 inch.

To verify this approximate calculation, a detail calculation of the temperature distribution in the module base plate and the fins was made with an IBM computer code. This calculation is discussed. It shows that the heat can indeed be rejected with a fin of the calculated size if the module base plate is approximately 0.75 inch thick at the edge of the thermocouple area.

The minimum weight radiator is provided by a plate tapered so that it is thinner at the center and thickest at the edge of the thermocouple area because the quantity of heat conducted through the plate to the fins increases as the edge of the thermocouple area is approached.

Considering the small difference in fin weight (~7%) indicated by the configuration study, a smaller weight module and fin configuration may be provided by Configuration B since the fins are centered on the plate and a smaller plate thickness will also give the proper temperatures at the couple cold junctions.

A detailed investigation of the structural properties and resonant frequencies of the two-plate configurations, based on a specific vehicle mounting configuration may indicate Configuration B to be a better structural configuration and thus lighter in weight.

3. Generator Temperature Distributions

The static generator temperature distributions have been calculated for both the design point and the beginning-of-life. The important system temperatures are those of the radiator, thermocouple cold junction, thermocouple hot junction, fuel capsule wall and the maximum fuel temperature. In addition to these, detailed calculation of the temperature distribution within the radiator (module base plate and fins) was made to verify that the approximate radiator design techniques used to size the fins in fact gave an adequate radiator. The design point and beginning-of-life temperature distributions are summarized in Table IV-3. The calculations may be found in Appendix J.

~~CONFIDENTIAL~~

MND-3393

0110507030

DECLASSIFIED

IV-18

CONFIDENTIAL

Fig. IV-8. Fin Weight Versus Fin Efficiency

CONFIDENTIAL

DECLASSIFIED

MND-3393

CONFIDENTIAL

0315087030

IV-19

TABLE IV-3

Static System Temperature Distributions

	Radiator Temperature (°F)	Junction Temperatures		Fuel Capsule Wall Temperatures		Maximum Fuel Temperature (°F)
		Cold (°F)	Hot (°F)	Front (°F)	Back (°F)	
Design point	600	610	1500	1740	1849	1878
Begin- ning of five- year life	631	642	1650	1884	2008	2040

The two most difficult and perhaps most critical calculations, the beginning-of-life fuel capsule temperature and design point radiator temperature distributions were performed by numerical techniques using an IBM 7094 Code T1GAAM. A brief description of the code may be found in Appendix J. The code verified the adequacy of radiator design. The calculated temperature distribution in the radiator at the design point is shown in Table IV-4.

The beginning-of-life fuel capsule temperatures were calculated for two different temperatures and for a capsule containing only fuel as well as the selected capsule design containing metal disks between cylindrical fuel pellets. The selected configuration greatly reduces the maximum fuel capsule wall temperature, thus easing somewhat the fuel capsule material problem. A summary of the fuel capsule temperature distributions is presented in Table IV-5.

4. Thermal Losses

The parasitic thermal losses in the static system occur in three components. They are the module thermal insulation, the thermal insulation on the four sides of the generator not occupied by the modules, and the fuel core support structure.

The module thermal insulation consists of 100 thin foils of titanium separated by thin mats of quartz fiber or by coating the foil on one side with ThO₂. In addition, the thermocouples are surrounded by sleeves of electrically insulating Johns Manville Dyna Quartz thermal insula-

CONFIDENTIAL

MND-3393

0312291030

CONFIDENTIAL

TABLE IV-4

Temperature Distribution in 3/4-inch Plate

506	507			497			483			467			456			$q_R = 622 \text{ watts}$ Material: Be $k = 80 \text{ Btu/hr-ft-}^\circ\text{F}$				
516	515			505			490			473			461							
527	525			514			498			479			466							
540	536			524			506			486			471							
555	555	547	551	547	535	536	529	516	513	506	493	490	484	475	474					
570	570	566	564	559	553	547	540	530	522	513	504	496	488	481	476	470	463	457	450	443
586	585	582	579	574	568	561	552	543	532	522	511	501	493	485	478	471	464	457	451	444
604	603	601	597	592	585	577	567	556	544	531	518	507	497	489	481	474	466	459	453	448
626	624	622	618	612	605	596	585	573	558	541	526	513	502	492	483	473				
643	641	638	634	628	620	611	599	585	569	549	532	518	505	495	486	479				
655	654	651	646	640	632	621	609	594	576	555	537	521	508	497	488	480	469	462	456	450
663	662	659	654	647	639	629	616	600	582	559	540	524	510	499	489	477				
667	666	663	658	651	643	632	619	603	584	561	542	526	512	500	490	482				

 $q_R = 622$ watts

Material: Be

 $k = 80$ Btu/hr-ft-°F

CONFIDENTIAL

MND-3393

CONFIDENTIAL

TABLE IV-5

Fuel Capsule Temperature Distributions--Beginning of Mission

	Beginning of Life Hot Junction Temperature (°F)	Capsule Wall Temperatures		Maximum Fuel Temperature (°F)
		Front (°F)	Back (°F)	
Configuration A (no metal in capsule)				
Design point hot junction temperature (°F)				
1400	1550	1800	2068	2132
1500	1650	1870	2136	2200
Configuration B (metal disks in capsule)				
Design point hot junction temperature (°F)				
1400	1550	1813	1936	1969
1500	1650	1884	2008	2040

~~CONFIDENTIAL~~

MND-3393

~~CONFIDENTIAL~~

tion to prevent electrical shorting of couples through the foils. Based on heat loss measurements made on similar insulations in the SNAP 13 program, this insulation system provides the minimum thermal loss in the module, consistent with reliable operation.

The insulation on the other four sides of the generator is provided exclusively by reflective foils.

The fuel core support structure, for the purposes of thermal loss calculations, was considered to be the conical member between the ball and socket support joint and the outside of the generator. The hot end of the cone will be at or below the thermocouple hot junction temperature, since there are two radiation groups between the fuel capsules and the cone. Therefore, the loss through the conical section was conservatively based on a hot end of 1500° and a cold end of 600° F.

The calculations may be found in Appendix K. The results are summarized in Table IV-6.

TABLE IV-6
Static System Thermal Losses

<u>Item</u>	<u>Loss (watts (t))</u>
Module insulation	
Sleeves	68
Foil	166
Side insulation	161
Fuel core support structure	<u>64</u>
Total	459

5. Weight Summary

The weights of various components and subsystems are presented in Table IV-7. Each structural member of the static system components has been conservatively stress analyzed to assure it has sufficient size to meet the 100 g loading criteria.

~~CONFIDENTIAL~~

03115507030

IV-23

TABLE IV-7
Static Generator Weight

	<u>Weight (lb)</u>
Fuel and fuel capsules (18)	75.6
Capsule support (2)	14.5
Ball, socket and cones (4)	3.9
Min-K insulation	0.6
Foil insulation	13.2
Thermocouples	10.0
Radiator plates (2)	57.6
Door assembly and latches	3.1
Back panel	1.1
End panels (2)	0.5
Clamp adaptor sections (4)	1.9
V-band clamps (2)	<u>2.0</u>
Generator total	184.0
Typical converter	<u>10.0</u>
Typical system	194.0

The system presented has been designed to allow a maximum of flexibility to the spacecraft designer. By including a d-c converter, almost any voltage is readily available to the payload by simply placing a center tap on the output of the converter. However, if the only voltage required is 28 volts $\pm 10\%$, the system weight can be reduced 10% by replacing the converter with a simple over-voltage limiter as discussed previously and by designing the thermoelectric system to produce 28 volts. The inefficiency of the d-c converter is eliminated since the simple regulator is virtually 100% efficient at the design point. Thus, a 10% saving in fuel weight (approximately two capsules) can be

~~CONFIDENTIAL~~

MND-3393

031712281030

6. Performance Summary

TABLE IV-8

(all values for five-year design point unless otherwise noted)

~~CONFIDENTIAL~~

7. Effect of Radiator Temperature on Generator Weight

There is, for a given hot junction temperature, fuel and power level, a cold junction temperature for which the weight of a radioisotope thermoelectric generator is minimum. This minimum exists since, as the cold junction and radiator temperature are increased, the generator efficiency decreases. Thus, the weight of fuel and fuel hardware increases while the radiator area and weight decreases. As cold junction temperature decreases, the opposite effects occur. This is illustrated graphically in Fig. IV-9. For this design, the radiator weight reaches a lower limit when the required radiator area approaches the module base plate area.

Fig. IV-9. Weight Optimization

For the static system, the weights of the generator for various cold junction temperatures have been estimated by calculating the fuel, fuel capsule and radiator weight for the several cold junction temperatures. The generator weight has then been estimated by adding these weights to a constant weight representing the balance of items in the generator system, which remain relatively unchanged by alterations in cold junction temperature. The results are presented in Fig. IV-10. Figure IV-10 indicates that the optimum cold junction temperature is approximately 700° F. The weight of the generator is increased by approximately eight pounds by reducing the cold junction 100° F to the selected design point of approximately 600° F.

*Generator weight equals fuel weight plus radiator weight plus a constant weight.

DECLASSIFIED

IV-26

~~CONFIDENTIAL~~

Fig. IV-10. Generator Weight Versus Cold Junction Temperature--Static System

DECLASSIFIED ~~CONFIDENTIAL~~

MND-3393

~~CONFIDENTIAL~~

03115507030

IV-27

Since the calculations did not include shielding weight, the optimum system weight will occur at a lower temperature (lower system efficiency) than that indicated by the curve because shield weight will vary as the required thermal inventory. Since shield weight cannot be calculated in any generally meaningful way without being specific about payload configuration, the nominal design cold junction temperature of 610° F was selected as a more realistic value for optimum overall system weight, although no specific shield weight comparisons could be made.

D. STATIC SYSTEM RELIABILITY

The static power supply has a reliability objective of 80% probability of failure-free operation for a period of five years, with a confidence of 50%. It is assumed that the failure distribution is exponential. The static system has two major components, the generator and the converter.

The operational reliability experience of the power system involves two phases: the launch-boost phase; and the orbital phase. During the launch-boost phase, a relatively severe mechanical environment will be experienced for a short time. During the orbital phase, the mechanical stress will be very low, and a constant radiation and thermal environment will be experienced throughout the entire five-year mission.

1. Generator Reliability

a. Failure modes, causes and effects

A major mode of failure for nuclear generators operating in a hard vacuum has been seal leakage, which causes a continuous decrease in power. However, silicon-germanium elements which will not sublime in a hard vacuum or oxidize in the earth's atmosphere, will be used in the static system. Consequently, pressurization of the thermoelectric generator is unnecessary.

Most probable failure modes, probable causes and the effects of each of these failures are the same for this generator as for the dynamic system generator (see Chapter III). Exploratory testing of SiGe modules has been conducted at RCA during the SNAP 17A program to verify failure modes and obtain an indication of the environmental limits of the equipment. Failures were induced in both mechanical shock and vibration at approximately 200% of launch specification environmental levels.

In the SNAP 17A project, modules of six thermocouples each will be subjected to combined temperature and vibration environments in tests at Martin-Baltimore. The temperature will be 1500° F at the hot

~~CONFIDENTIAL~~

MND-3393

031712081030

DECLASSIFIED

~~CONFIDENTIAL~~

junction and 450°F at the cold junction. Vibration, including both sinusoidal and Gaussian random will be in accordance with SNAP 17A specifications. Similar exploratory testing involving the 100-thermocouple module for the 250-watt generator should be initiated during the development phase.

b. Reliability model

The 200 thermocouples are arranged in two modules, each module containing 100 thermocouples. The two modules are arranged so that all of the thermocouples are in series-parallel as in the dynamic system. Any four thermocouples can fail without disrupting electrical output or reducing power below requirements, provided that two failures do not occur in the same redundant pair. The failure rates for the thermocouples that are to be used in the static system are based on the thermocouple failure rate data obtained from Ref. 6, Chapter III. Since the static system thermocouples are not composed of the same materials as those thermocouples which participated in the failure rate determination, a conservative estimate of this failure rate will be assumed. It is assumed that the developmental testing of these SiGe thermocouples, which will be carried on in the SNAP 17A and the 250-watt programs, will enable the failure rate of the SiGe thermocouples to approach the failure rate of the PbTe thermocouples. As stated before, the best estimate of the telluride-type thermocouples was 0.007%/1000 hours; however, a more conservative failure rate of 0.0276%/1000 hours will be assumed for the SiGe thermocouples. The reliability of each thermocouple is 0.9878 based on an operating time of 43,800 hours. The corresponding MTBF of the thermocouple is 3,623,000 hours; the reliability model of the series-parallel arrangement of the 200 thermocouples is the same model which was used in Chapter III. The reliability of the thermocouples for the five-year mission was calculated to be 0.889.

The reliability for the generator is also 0.889 for the same reasons as explained in Chapter III.

c. Fuel core assembly design reliability

The fuel core assembly for the static system is very similar to that of the dynamic system. Structural reliability design techniques which were specified for the dynamic system will also be used in designing this system.

d. Analysis and conclusions

Investigations thus far indicate that the thermoelectric generator design is potentially capable of achieving its reliability objective. This opportunity for success is largely due to the use of silicon-germanium

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

030507030

IV-29

thermocouple elements, which are not prone to sublimation in a hard vacuum and oxidation in the earth's atmosphere. In the light of past experience with thermoelectric generators operating in hard vacuum, this approach enjoys a much greater likelihood of successful operation for five years than does a lead telluride generator. The exploratory tests that have been conducted to date by RCA and by Martin tend to confirm this optimism.

2. Converter Reliability

This converter is the same one used for the dynamic system. Therefore studies involving failure mode analyses, failure rate determination, reliability and radiation effects will also apply. Again, the reliability of the converter is 0.927.

3. Overall System Reliability

a. Estimate of system reliability

The operational reliability of the static 250-watt generator system is the product of the reliabilities of the generator and the converter. The estimated reliability of the converter is 0.927. The estimate of generator reliability is 0.889. The system reliability, therefore, is estimated at not less than 0.80.

b. Limitations and quality of estimate

Stress and failure rate data for the converter were derived from MIL-HDBK-217 which is reasonably authoritative. All components and parts, except two, are military standard parts, and the specifications to which they were tested should be checked to assure that they have been tested to environmental levels equal to or greater than those to be experienced by the 250-power supply system. These data form the basis for the reliability estimate, which is believed to be conservative.

Generator reliability is primarily a question of thermocouple reliability, and test data currently available allows for a conservative estimate of the thermocouple failure rate to be made. Furthermore, analysis of the silicon-germanium thermocouples indicates that they should function in the operational environment indefinitely, far beyond the required five-year period.

c. Recommendations for critical reliability testing

The following recommendations are made for the static system:

- (1) Exploratory tests of thermocouple assemblies to determine environmental limits in vibration, shock and temperature.

~~CONFIDENTIAL~~

MND-3393

030507030

DECLASSIFIED

~~CONFIDENTIAL~~

- (2) Exploratory test programs for thermocouple material to determine strengths at operational temperature ranges in shear, compression, tension and performance reproducibility versus material composition.
- (3) Detailed structural analysis of the fuel assembly to determine load distributions at critical points.
- (4) Environmental and exploratory tests on the converter to determine whether failure rates were increased above those predicted.

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

03:58:030

V-1

V. SHIELDING

A. SHIELDING PHILOSOPHY AND DESIGN CRITERIA

Shielding is designed to meet various radiation criteria. For the payload, the total integrated dose criterion is 10^6 rads from the generator for the five-year mission. This was the criteria for the SNAP 17A electronics payload which also has a five-year mission and was based on the doses that components such as resistors, capacitors, and tubes can receive without being seriously damaged. The dose is due to bremsstrahlung gammas from the strontium fluoride fuel and neutrons from the photoneutron reaction

which occurs when the gammas strike the beryllium contained in the generator. This dose from the generator is in addition to the ambient space radiation. The dose received from space radiation depends on the altitude and inclination of orbit, and, of course, on the length of mission. For a five-year flight at 10,000 nautical miles and a circular, polar orbit, a total integrated dose of approximately 10^7 rads will be received by the equipment.

In addition to contributing to the dose via ionizations, the neutrons also cause atomic displacements in payload equipment. To gauge the damage from these displacements, criteria in units of flux (neutrons/cm²) have been set up. The component which can take the least neutron flux while maintaining satisfactory operation is the transistor. Depending on the type and thickness of the base material, transistors can receive from 10^{11} to 10^{13} neutrons/cm². Resistors, capacitors, diodes and vacuum tubes all have criteria which are equal to or higher than those mentioned for transistors. As the electronics system itself (the type of components used, the circuits, etc.) is uncertain at this point, no definite criterion can be set for the neutron flux. Instead several criteria were compared (Table V-1).

TABLE V-1
Shielding Criteria

Neutron Flux Criterion (n/cm ²)	Separation Distance (ft)		Uranium Shielding (in.)	
	Dynamic	Static	Dynamic	Static
10^{11}	14.7	16.7	0.000	0.00
10^{12}	4.3	4.9	0.46	0.43
10^{13}	0.7	1.0	1.25	1.18

~~CONFIDENTIAL~~

MND-3393

03:58:030

DECLASSIFIED

~~CONFIDENTIAL~~

B. SHIELDING REQUIREMENTS

With the unshielded gamma radiation, a separation distance between the generator surface and payload of 12.4 feet for the dynamic system (Fig. V-1) and 13 feet (Fig. V-2) for the static system is required to meet the specified criterion of 10^6 rads for five-years (22.8 rads/hr). For the purpose of estimating shield requirements, the front or broad face of the generator is assumed to be the one turned in the direction of the payload. In this case, the neutron contribution to the total dose is negligible (Fig. V-3) compared to that from the gammas.

Using depleted uranium as shielding, the separation distance between the generator and payload can be greatly reduced. Gamma dose rates toward the payload from the generator were determined for various thicknesses of uranium shielding for both the dynamic and static systems (Figs. V-4 and V-5). The neutron dose rate will be increased slightly due to fast fissioning within the uranium; however, the neutron contribution to the dose is still negligible compared to that of the gammas.

The separation distance required for various neutron flux criteria can be determined from Fig. V-6. In Table V-1, the separation distance for the listed criteria are given for both the dynamic and static systems. Also, the uranium shielding necessary to meet the dose criterion of 10^6 rads at these separation distances is shown.

C. SHIELDING ANALYSIS METHOD

Thermal wattages of 4000 for the dynamic system and 5000 for the static system were used in all dose and flux calculations. Gamma dose rates were found by using the Martin Generalized Shielding code. This code integrates dose rates from an array of point sources and uses buildup factors to approximate the contribution of scattered radiation to total dose rate. Gamma dose rates from the generator with various thicknesses of uranium shielding were also determined by using this code.

Neutron fluxes were found by using flux equations (Ref. 1) with bremsstrahlung gammas above the photoneutron reaction threshold of 1.666 Mev. To convert neutron flux to dose, the neutron energy (Ref. 2) for each particular gamma energy is used to find the appropriate flux-to-dose conversion factor (Ref. 3). As mentioned previously, the neutron dose is negligible compared to the gamma dose.

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

03115507030

V-3

Fig. V-1. Dynamic System--Gamma Dose Rate Above, to Side, and in Front of Generator as Function of Distance from the Generator Center

~~CONFIDENTIAL~~

MND-3393

031712281030

DECLASSIFIED

~~CONFIDENTIAL~~

V-4

Fig. V-2. Static System--Gamma Dose Rate Above, to Side, and in Front of Generator as Function of Distance from the Generator Center

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

3

Fig. V-3. Neutron Dose Rate as Function of Distance from Surface of Generator

DECLASSIFIED

V-6

CONFIDENTIAL

Fig. V-4. Dynamic System--Gamma Dose Rate as Function of Distance from Center of Generator for Various Thicknesses of Uranium Shielding Shown

CONFIDENTIAL

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

03115587030

V-7

Fig. V-5. Static System--Gamma Dose Rate as a Function of Distance from Center of Generator for Various Thicknesses of Uranium Shielding Shown

~~CONFIDENTIAL~~

MND-3393

03115587030

DECLASSIFIED

~~CONFIDENTIAL~~

V-8

Fig. V-6. Neutron Flux as a Function of Distance from Surface of Generator

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

~~CONFIDENTIAL~~

0315087030

V-9

REFERENCES

1. Rockwell, J., Reactor Shielding Design Manual, First Edition.
2. Reactor Physics Constants, Argonne National Laboratory.
3. Henderson, B. J., "Conversion of Neutron or Gamma Ray Flux to Absorbed Dose Rate," XDC 59-8-179, August 1959.

~~CONFIDENTIAL~~

MND-3393

031712291030

DECLASSIFIED

~~CONFIDENTIAL~~

BLANK

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

~~CONFIDENTIAL~~

13587030

VI-1

VI. GROUND HANDLING EQUIPMENT

The purpose of this study was to define the ground handling procedures and equipment necessary to support the use of an advanced Sr-90 space power supply in a hypothetical space mission. To identify the system criteria, it was appropriate to postulate the use of a particular launch site, a specific launch vehicle and a compatible payload configuration. From this premise, an analysis of the overall problem, a review of feasible solutions, and a system concept selection were made.*

A. GENERAL

The fuel handling portion of the Advanced Space Power Supply program requires the development of an equipment system which fulfills all the critical functional requirements inherent in the handling of highly radioactive fuel and is fully integrated into the numerous interface areas of a space program. The basic problem is handling a multikilocurie strontium-90 fuel assembly from arrival time at a launch site to its installation into the power generator of a space mission payload late in the prelaunch countdown. The generator is assumed to be assembled in the payload of a launch vehicle on the launching pad and approximately 100 feet above ground level.

Since the introduction of this fuel adds a radiation hazard to an already hazardous area, careful consideration must be given to maintaining complete nuclear safety at all times. All possibilities of equipment or system malfunction or failure must be analyzed and steps taken to ensure utmost system reliability at all times.

1. Approaches

The solution technique employed was to perform a generalized operation analysis of the site-oriented activity first. A safety and malfunction recovery philosophy was evolved, and functional requirements for any generalized system were outlined. From this broad view, a pattern of system capabilities was extracted, and several concepts generally conforming to this pattern were schematically delineated.

A set of design criteria was established, and these criteria applied to the several system concepts for evaluation and selection of practicable solutions. This work was, in large part, organized and performed during the Phase I engineering on the SNAP 17A program by AMF Atomics for Martin.

*Worked performed by AMF Atomics under subcontract to Martin.

~~CONFIDENTIAL~~

MND-3393

03712281030

~~CONFIDENTIAL~~
DECLASSIFIED

a. General concept

The concept, evolved as a result of the SNAP 17A effort and modified in the light of the 250-watt program requirements, is a site-oriented system utilizing the launch pad service tower to place the fuel handling equipment at the payload location.

This equipment consists basically of a semiautomatic, remote controlled fueling machine, a storage rack for the fuel shipping cask, a closed circuit television system and a control system. The system provides for the storage of the fuel assembly at the payload elevation, and transport and installation of the fuel assembly into the generator in an expeditious, yet highly reliable manner.

B. SYSTEM CRITERIA

The general attributes established for the system concept were simplicity, ease of operation and maintenance, flexibility or adaptability to varying interface requirements of vehicle and launch site, reliability, and safety of operations.

Machine motions, methods of drive, interlock requirements and procedural concepts were all subjected to examination in their conformance with these system attributes, and strong efforts were made to optimize the design in these areas.

1. Design Criteria and Capabilities

The system design was evolved so as to meet the following requirements:

- (1) Engage, transport and install a fuel assembly in a fail-safe manner, so the fuel assembly is continuously in mechanical captivity, either in the machine loader, or in the appropriate receptacle.
- (2) Provide attenuation of transient wind-induced relative motion between the launch vehicle and the fueling machine.
- (3) Open and close a fairing door at appropriate points in the fueling cycle.
- (4) Provide alignment of the fuel assembly with the storage cask or generator, and accomplish the insertion, preloading and locking of the fuel assembly into the receptacle.
- (5) Furnish biological shielding for the personnel needed to complete fueling operations and who must enter the radiation hazard area during fuel assembly exposure.

~~CONFIDENTIAL~~
DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

VI-3

- (6) Accomplish fueling operations by remote control where biological shielding techniques are insufficient to secure personnel safety during fueling.
- (7) Provide position sensing devices for relative location of machine and payload.
- (8) Provide visual and audible indication and alarm of gamma radiation levels to ensure personnel safety.

a. Mission interface assumptions

The scope of study was predicated on the assumption that the resultant system concept would be independent of a particular space mission. To conveniently circumscribe the interface areas, certain hypotheses were made.

The first assumption was that the mission would originate from PALC 1 at PMR, with the handling equipment erected on the service tower. From this point, further assumptions were made that the launch vehicle would be an Atlas/Agena D, and that the payload would be mounted within a Nimbus/Eogo type fairing (see Fig. VI-1). Welding these assumptions together, an optimum arrangement was generated. From generator/fuel assembly layouts, a payload/fairing interface drawing was delineated (see Fig. VI-2).

Further mission constraints were generated to establish logical and practicable ground rules for the handling operation and system design. These were defined in an Interface Specification (see Appendix M).

b. Safety requirements

A detailed analysis of safety requirements for the handling system was accomplished during the Phase I efforts of the SNAP 17A program. In the present study, a review of the results indicated that essentially all of the considerations were applicable to the 250-watt program. Inputs from this safety analysis are incorporated in the Equipment Specification (see Appendix M). Particular attention was given to the conditions surrounding a single 5000-watt source.

c. Reliability requirements

The reliability studies conducted during Phase I of the SNAP 17A program were particularly applicable to the handling system for the 250-watt program. An evaluation of the relative complexity factors in the control system, number of components, and characteristics of the machine elements indicates that reliability factors of 0.999 for single operation, and 0.99999 for malfunction recovery are entirely

~~CONFIDENTIAL~~

MND-3393

0371229.0330

0 2 4 6 8 10
SCALE FEET

Fig. VI-1. Service Tower Interface, PMR, PALC 1

MND-3393

~~CONFIDENTIAL~~

Fig. VI-2. Payload and Fairing Interface

~~CONFIDENTIAL~~

VI-5

DECLASSIFIED
CONFIDENTIAL

Fig. VI-3. Artist's Concept of Fueling Machine

DECLASSIFIED

CONFIDENTIAL

MND-3393

~~CONFIDENTIAL~~

015087030

VI-7

within the capability of the basic machine concept. Design parameters consistent with these requirements are incorporated in the equipment specification (Appendix M).

C. SELECTED SYSTEM

The selected fuel handling system, as shown in Fig. VI-3, consists of four basic subsystems, a fueling machine, a shipping cask-storage rack, a closed circuit television system and a control system. In essence, the fueling machine removes the fuel assembly from the shipping cask mounted on the storage rack at payload elevation and loads the generator in the launch vehicle according to operator commands over the control system. The entire operation is performed under the close surveillance of the operator utilizing the television monitors.

Both the fueling machine and the shipping cask storage rack are mounted on the service tower. This mounting consists of structural members attached to the tower framework. The fueling machine support bracketry is arranged to permit the machine to be positioned at either the launch vehicle or the shipping cask. The shipping cask storage rack is arranged to hold the cask in a position corresponding to the generator location. A door actuator for the cask is incorporated in the storage rack, and is operated through the main control system.

The fueling machine consists of a fuel assembly loader mounted on a machine carriage. The machine carriage provides the loader with four degrees of freedom of motion. Electromechanical drives position the machine in the three coordinate axes and in azimuth. The function of these drives is to transport the loader between the cask location and payload position, with the capability of introducing corrective motions in elevation, lateral position, and azimuth or angle of approach (see Fig. VI-3).

To overcome static and dynamic positional errors in the relative positions of the machine and launch vehicle, two auxiliary subsystems are incorporated in the fueling machine.

The first is a sway-restraint assembly mounted on the machine support (see Fig. VI-4). The sway restrainer encircles the launch vehicle and reduces any transient relative motions to a value consistent with the machine's capability to adapt to residual motions. This capability to tolerate residual motion is attained by means of gimbal mounts between the loaders and the machine carriage.

Any static positional errors encountered at the fueling machine-to-payload interface are sensed by a mechanical probe system referenced to the loader location. Two probes, each sensing lateral and vertical

~~CONFIDENTIAL~~

MND-3393

015087030

NOTES
1. STRUCTURE TO BE ALUMINUM, WELDED.

TOTAL WEIGHT APPROX. 250 LBS.

Fig. VI-4. Sway Restrainer

~~CONFIDENTIAL~~

03507030

VI-9

displacement of the loader to a fixed reference station on the payload fairing, are used to prevent ambiguity between lateral and azimuth position errors (see Fig. VI-5).

To permit access to the generator within the payload fairing, the loader assembly is provided with a fairing door opener and a door closer. The opener advances to the fairing with the machine carriage and depresses a latch release mechanism, allowing the fairing door to spring open. On completion of the loading operation, the closer mechanism swings the door shut to engage an automatic latching device (see Fig. VI-6).

The control system consists of two control stations. A console, provided with a complete set of machine drive controls, indicators, interlock overrides, permissive switches and TV monitors, is located in the control blockhouse. A second station, containing only those controls necessary for normal operation of the machine drives, is located in the service tower along side the machine to permit setup, alignment and checkout operations under close operator scrutiny (see Fig. VI-7).

The fuel assembly loader (see Fig. VI-8) is basically a pneumatic ram which applies the insertion and preload forces. Fitted with lockable guide rods which restrain the preload from application into the vehicle, the loader can develop a preset maximum load in the fuel assembly and generator. Rotary actuators operate pairs of fuel assembly pickup pins and lock finger positioning cams. A protective shield surrounds the fuel assembly and actuating mechanism.

The entire sequence of loader operations is remotely controlled by push buttons at the blockhouse console. Interlocks are provided in both mechanical and electrical modes to eliminate the possibility of inadvertent release of the fuel assembly. All operations are completely reversible in sequence, and may be stopped in a fail-safe manner at any point in the fueling cycle.

A pneumatic power package, mounted to the machine support, furnishes the air required for operation of the sway restrainer and the various air actuators incorporated in the machine (see Fig. VI-9).

The closed circuit television system consists of two remotely controlled area surveillance cameras with pan and tilt capabilities. These are continuously displayed at the control console on separate monitors. In addition, the loader assembly has a collimated TV camera which is registered on a visual reference mark on the fairing.

To monitor possible radiation hazards, four gamma-radiation detectors are appropriately located to give visual and audible alarms if radiation exceeds normal anticipated conditions, or where inadvertent or accidental exposure is encountered.

~~CONFIDENTIAL~~

MND-3393

0370201030

DECLASSIFIED

031507030

CONFIDENTIAL

DECLASSIFIED

Fig. VI-5. Probe Assembly

DECLASSIFIED

03712091030

CONFIDENTIAL

MND-3393

DECLASSIFIED

Fig. VI-6. Fairing Door Actuator

DECLASSIFIED

DECLASSIFIED

CONFIDENTIAL

DECLASSIFIED

Fig. VI-7. Control System for Fuel Handling Machine

DECLASSIFIED

DECLASSIFIED

CONFIDENTIAL

MND-3393

DECLASSIFIED

0315587030

CONFIDENTIAL

REF ID: A607031ED

0315587030 VI-13

Fig. VI-8. Fuel Assembly Loader

03172281030

CONFIDENTIAL

MND-3393

DECLASSIFIED

03172281030

Fig. VI-9. Sway Restrainer Pneumatic Diagram

~~CONFIDENTIAL~~

0315087030

VI-15

Biological shielding is provided at the service tower drive control station to permit two operators to reposition the tower when the fuel source is unshielded.

1. Evaluation Analysis

In the Phase I effort on the SNAP 17A program, a detailed and comprehensive evaluation technique was prepared for selecting the optimum handling system. The results of this analysis were particularly applicable to the 250-watt program. Using the SNAP 17A conclusions as a starting point, the present study investigated refinements in machine drive techniques, fuel grappling devices and operational modes. A major distinction in the program requirements tending toward the present scheme was the limitation of handling requirements to one fuel assembly of approximately 5000 thermal watts capacity.

An engineering decision was made to follow the basic machine drive system, but not to attempt to extrapolate the loader design from the prior program, due to the large scale factors on size, weights and thermal output.

In the design of a fuel assembly loader for the 250-watt program, an extensive review was conducted of the SNAP 17A work in this area. In the prior effort, design analyses were conducted on different methods of applying the necessary preload and locking forces into a fuel assembly. Each of these designs was re-evaluated for its applicability to the 250-watt problems. After this evaluation was made, it appeared that a modified approach would be required, and the present scheme developed.

The preload and locking methods evaluated in this study included:

- (1) Breechblock--Interrupted male threads on the fuel assembly are rotated from the loader to interrupted female threads in the receptacle or reverse to accomplish transfer and locking. Detent action on a flange face is used to secure latching action. Preload is developed by thread pitch. This scheme was rejected for reasons of excessive weight, susceptibility to hangup, position sensitivity of the latching arrangements, and excessive heat conducting areas.
- (2) Autoclave--Locking fingers on the fuel assembly are rotated into engagement with receptacles by cam surfaces. Preloading and locking are accomplished simultaneously by means of a nut driven forward into the fuel assembly which cams the locking fingers into position. This scheme was rejected for reasons of complexity, difficulty in reliably interlocking the latching and pickup functions, and inability to conform readily to the fuel assembly package configuration.

~~CONFIDENTIAL~~

MND-3393

0315087030

~~CONFIDENTIAL~~

- (3) Sliding lock fingers--In this arrangement, the preload is applied as an axial force prior to actuation of the latching and pickup mechanisms. By rotary actuation, independent mechanisms accomplish the release of the fuel assembly from the loader, and engagement of the fingers by means of a cam incorporated in the fuel assembly.

Arrangement (3) appeared to offer the simplest technique for accomplishing the preload and locking functions. Due to the maximum weight of 100 pounds for the fuel assembly, the scheme required that the preload be raised from approximately 1500 pounds (SNAP 17A) to 10,000 pounds (design criteria). Since the fuel configuration is a narrow rectangle in its loading face, it was decided to use two pickup points and two latching mechanisms, dividing the load between them to improve stability and reduce local stresses and deflection.

To simplify the actuation required, a method (see Fig. VI-8) was devised wherein the function of engaging and disengaging the fuel assembly from the loader, and actuating the lock fingers were incorporated in the same operation. This reduces the access hole size for inserting the pickup pins and preload sleeves into the fuel assembly face. The minimization of the opening in the insulating material covering the fuel assembly was of prime concern in the design of the loader to obtain minimal heat losses.

Since the single motion actuation of the fuel pickup and receptacle unlock requires an overlap to prevent inadvertent disengagement of the fuel assembly, a condition exists wherein the mechanism could fail with the fuel assembly locked to both the receptacle and the loader. To improve the reliability in this area, the rotary actuation is accomplished with two air motors geared in parallel to the pickup pin and cam driver. This provides a redundant drive in which either actuator is capable of independently performing the transfer with the other free wheeling. In case of hangup, the drives can be operated together to recover in either direction.

Another device for accomplishing the fuel assembly pickup is to have a pickup rod with spring-loaded locking balls. The spring loading would be greater than any external shock (see Appendix M), to assure that the fuel assembly will not be disengaged at any time except when it is locked in the receptacle (shipping cask or generator) where the preload of 10,000 pounds will allow the springs to depress, enabling the removal of the pickup rod and cam driver. This type of pickup eliminates the problem wherein the rotating mechanism could fail with the fuel assembly locked to both the receptacle and the loader. It also eliminates the design problem of rotary overlap and realignment.

~~CONFIDENTIAL~~

MND-3393

~~CONFIDENTIAL~~

~~CONFIDENTIAL~~

0315587030 VI-17

Alternate devices for accomplishing the fuel assembly pickup were considered in the loader design. One scheme used an air-actuated spring return piston inside a hollow pickup pin to drive out a set of locking balls. This concept was rejected for reasons of increased complexity and sensitivity to foreign matter, with reduction in overall loader reliability as a consequence. A second approach, using an internal camming rod to actuate a spring-loaded locking dog, was rejected for reasons of increased complexity and introduction of an additional actuation.

An alternate arrangement was developed in which the operation of the pickup pin was independent of the lock-finger cam drive. This required two individual rotary actuators. In this scheme, the pickup pin was interlocked to the preload sleeve to prevent release from the fuel assembly until full preload was applied. However, this scheme depends upon an instrumented signal of completed pickup actuation before release of the receptacle lock. An apparent disadvantage of this scheme is that faulty signalling can introduce a condition wherein the loader is disengaged from the fuel assembly before the receptacle lock is completed.

The pickup designs requiring only one actuation, which is common with the lock-finger camming motion using either spring-loaded locking balls or pickup pins, are considered to be the most simple and inherently reliable of the schemes examined.

Preliminary design evaluation of the proposed loader configuration indicates that materials of construction for the pickup and cam-driven parts can be of the stainless steel family. Maximum stresses in the locking balls or pickup pins should not exceed 15,000 psi, including shock and vibration loads. Maximum stresses in the preload mechanism should not exceed 15,000 psi assuming maximum preloads of 10,000 pounds total. Guide rod stresses are estimated not to exceed 40,000 psi maximum combined stresses under worst case loads due to misalignment and preload reaction.

In the present scheme, the fuel loader assembly does not require an independent drive in parallel with the direction of loading. This feature, which is used in the SNAP 17A design as a redundant drive to ensure withdrawal from the payload fairing, is made unnecessary by the fact that the loading direction is parallel to the direction of service tower withdrawal. This means that in case of machine carriage drive failure, the loader can be removed from fairing engagement by means of the service tower.

The loader is suitable for either a statically cooled assembly or a dynamically cooled unit. Changes in package sizes, weights, thermal capacity, or methods of fuel element assembly will not substantially af-

~~CONFIDENTIAL~~

MND-3393

03172281030

CONFIDENTIAL

fect the loader operation. The loader design is compatible with changes in preload, clearances, insertion stroke, and length of pickup pin engagement requirements.

A brief investigation was made into the feasibility of fueling operations involving the installation of prefueled generators into the payload. The results of this inquiry were to establish that the disadvantages incurred heavily outweighed any advantages. The sole factor tending toward this scheme was that the fuel assembly installation could be conducted under hot cell conditions where environment control and ease of access could simplify installation and test. However, the radiation conditions at the launch site would be essentially the same for the complete assembly, and all safety and reliability requirements would be virtually identical. In addition, a larger, bulkier and more difficult to manipulate package would be involved in the final installation. The interface requirements for the generator and payload attachments would then include both electrical and coolant elements in addition to the necessary mechanical attachments.

Essentially the same arguments pertain to the prospect of carrying the preassembly operations to the payload level. In this case, the erection and attachment problems are still further complicated by the bulk of equipment and difficulty of manipulation.

2. Launch Safety and Recovery

a. Launch safety

Operating safety in avoiding any malfunction or accident which might result in a radiation hazard to personnel or damage to the launch vehicle has been integrated into the fuel handling system concept. The following requirements have been evaluated and are presented as the minimal to assure the safety of the fueling operation.

- (1) Mechanical and electrical interlocks to guarantee proper sequential operations.
- (2) Position mechanical stops to prevent collision between fuel handling equipment and the launch vehicle or service tower.
- (3) Redundant fastening methods, electrical circuits and air supply lines to avoid droppages, stoppages or hangup of equipment.
- (4) Limitation of accelerations and loading capability of the fueling machine to avoid overstress of interface members.
- (5) Safety programs for instruction of personnel in radiation hazards.

CONFIDENTIAL

~~CONFIDENTIAL~~

0319581030

VI-19

- (6) Provision of safety equipment and devices such as catch nets, lanyards, and equipment counts to prevent foreign objects from interfering with machine operation, and to preclude damage to the launch vehicle due to dropped objects.
- (7) Standard operating procedures to cover all credible malfunction and emergency situations.

b. Recovery

From the prior investigations during Phase I of the SNAP 17A program, a broad picture of the recovery requirements engendered by various accidental or mission abort situations has been delineated.

In the earliest credible situation--a complete machine power failure with sources exposed--can be reduced by proper use of the service tower gantry crane. If the fuel assembly is still in the cask, sufficient shadow shielding is provided by the cask to allow personnel to approach the area and perform the necessary tasks to recover operability. If the fuel assembly is in the payload, the service tower can be withdrawn and the recovery tasks accomplished under minimal shadow shielding. If the fuel assembly is in the loader, the service tower can be withdrawn to a preselected location where the 10-ton gantry crane can be used to dismount the machine from its supports and drop the machine into a shield pit.

In the case of accidental abort where the launch vehicle is destroyed on the pad after fueling operations are completed, suitable shielded recovery vehicles will be required to locate, disengage and recover the fuel assembly or fuel elements.

~~CONFIDENTIAL~~

MND-3393

0317281030

DECLASSIFIED

VI-20

~~CONFIDENTIAL~~

BLANK

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

~~CONFIDENTIAL~~

VII-1

VII. NUCLEAR SAFETY

A. SAFETY PHILOSOPHY

The nuclear safety philosophy for the Sr-90 space power supply is primarily concerned with the degree of containment, accountability of the fuel and its radiation effects. The radiological characteristics and the quantity of the radionuclide required for the advanced 250-watt system emphasize the need for a sound safety program.

The proposed 250-watt static system will contain approximately 9.0×10^5 curies of Sr-90 and the dynamic system, about 7.2×10^5 curies.

An acceptable safety approach must be derived from the principle that the general public shall not be exposed to any undue hazards, particularly those resulting from handling and shipping accidents, launch aborts, re-entry, and normal operation of the radioisotopic thermoelectric generator. Regardless of the methods comprising the safety approach, they must consider:

- (1) Potential radiobiological hazards associated with environmental radioactive contamination.
- (2) Establishment of component re-entry burnup and launch pad integrity.
- (3) Partial burnup regions.
- (4) General safety requirements with respect to mission phases--prelaunch, launch, and postmission disposal.

From the discussion, it is obvious that stringent design criteria must be established to satisfy the safety philosophy. The specific nuclear design criteria that have been established for the advanced 250-watt radioisotope thermoelectric generator (RTG) are as follows:

- (1) Sufficient shielding shall be provided during shipment of the radioisotope fuel to comply with Interstate Commerce Commission regulations for shipment of radioactive materials. These regulations permit maximum dose rates of 200 mr/hr at the surface and 10 mr/hr at one meter from the shipping cask surface.
- (2) The fuel shipping cask will satisfy all requirements as set forth in the Code of Federal Regulations, Title 10, Part 72.

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

~~CONFIDENTIAL~~

- (3) The radioisotope fuel capsule will remain intact if exposed to the effects of propellant detonation and conflagration on the launch pad.
- (4) The fuel capsule will be designed to survive terminal velocity impact upon a rigid medium. Such impact might result from an abort at an altitude where aerodynamic heating effects are negligible.
- (5) The fuel containment structures will collectively resist hydrostatic pressure and seawater corrosion at depths up to 1000 feet for a period of time sufficient to permit reasonable recovery attempts (to depths of approximately 100 feet) or acceptable sea concentrations at the time of release.
- (6) The entire generator will be completely destroyed and the Sr-90 fuel will be dispersed as micron-size particles at altitudes above 100,000 feet by the effects of aerodynamic heating during normal re-entry following orbital departure.
- (7) The gray area or partial burnup zone, which is an inherent weakness in a re-entry burnup design, will be considered acceptable only if it occurs over deep ocean or uninhabited land areas.
- (8) The generator shall be handled so as to prevent ignition of the rocket fuels during all launch pad operations.

B. FUEL CONTAINMENT

1. Design Considerations

The proposed 250-watt isotopic generator represents the largest space application of Sr-90. All space mission generators to date, except the SNAP 17A generators currently under development, have employed alpha-emitting isotopic fuels. Since the primary fuel containment structure, the fuel capsule, is the basic safety element of the RTG, the design for space application is of paramount importance to the safety of the isotopic power system. The following specific considerations must be reflected in its design:

- (1) The capsule must adhere to all of the safety design criteria. This means that it must survive all handling and launch accidents and be completely destroyed by aerodynamic heating effects during re-entry.
- (2) The containment materials must be chemically compatible with the isotope fuel form.

~~CONFIDENTIAL~~

DECLASSIFIED

MDD-3893

~~CONFIDENTIAL~~

03:15:08:70:30

VII-3

- (3) The fuel capsule design must be optimized for minimum weight and maximum containment capability.
- (4) The exterior surfaces of the capsule must be suitably decontaminated after being filled with fuel and sealed.
- (5) The fuel capsule assembly must be designed for easy handling and installation in the generator at the launch site.

2. Configuration

Based primarily upon experimental information of the SNAP 17A impact test program, a capsule configuration with hemispherical ends has been selected (Fig. VII-1). The welds for the end caps have been designed to allow the impact energy to flow into the sidewall without overstressing the weld area. In addition, the hemispherically shaped ends will allow less stress concentration per unit area upon impact. A significant weight decrease was achieved with the choice of a wall thickness of 0.100 inch rather than the thicker walls of previously suggested designs. This selection was prompted by recommendations based on the SNAP 17A program--that a thinner wall is more ductile.

3. Material Selection and Evaluation

a. Fuel capsule material

Initial plans favored the choice of Haynes-25 for the fuel capsule material for both the dynamic and static generator systems. However, as the stringent thermal requirements of the static system became more clearly defined, it was obvious that the Haynes-25 would not meet structural specifications at the high temperatures. An examination of possible materials for the static system resulted in the selection of TD nickel* as the capsule material with a thin outer casing of platinum for corrosion resistance.

The basic criteria used as a guide in the investigation and selection of the materials were:

- (1) High impact tensile strength and comparative stress to rupture in the operating temperature range.
- (2) Oxidation and sublimation resistance at high temperature.
- (3) Seawater corrosion resistance.

* A super nickel alloy with 2 vol % thoria dispersed as submicron size particles with the nickel matrix.

~~CONFIDENTIAL~~

MND-3393

03:17:28:10:30

CONFIDENTIAL

Fuel capsule--dynamic system

Fig. VII-1. Fuel Capsule--Static System

CONFIDENTIAL

WMD-3393

CONFIDENTIAL

0315087030
~~CONFIDENTIAL~~

VII-5

- (4) Weldability.
- (5) Fabricability.

b. Material evaluation

Based on a materials investigation and a review of previous Martin SNAP material studies, Haynes-25 was found to most closely satisfy the fuel containment structure criteria for the dynamic system at operation temperatures of 1600° to 1800° F. At the operating temperatures of 1800° to 2000° F for the static system, however, Haynes-25 was found to be unsatisfactory due to poor tensile properties above 1800° F.

The capsule material for the static system must adhere to the following specific requirements:

- (1) Must be able to survive air exposure at 2000° F for periods up to 30 days with an accompanying weight loss (or gain) of less than 1%.
- (2) Must be able to survive air exposures for periods of up to 100 years at temperatures from 1000° to 100° F (decreasing over the 100-year period).
- (3) Must be able to survive five years in a 10,000-mile orbit (at pressures of 10^{-10} mm Hg) without significant sublimation weight loss at temperatures of 1800° to 2000° F.
- (4) Must have a melting point of approximately 3000° F.
- (5) Must have a yield strength of greater than 10,000 psi at 2000° F to survive a low altitude abort.

Due to the requirements for high temperature yield strength, air oxidation resistance and five-year integrity at 10^{-10} torr and 2000° F, a double capsule construction appears to be mandatory since no single metal or alloy seems to meet all the requirements. (A possible exception is Pt 40% Rh although its high melting temperature causes undesirable atmospheric burnup characteristics.)

Hence, an inner capsule of TD nickel will satisfy the 10,000-psi yield strength and 3000° F melting point requirements. Comparative plots of several materials may be found in Figs. VII-2 through VII-6. An outer capsule of thin platinum will fulfill the 2000° F for 30 days of air oxidation resistance and serve as an effective barrier to the evaporation of the inner nickel capsule at 2000° F and 10^{-10} mm Hg vacuum.

~~CONFIDENTIAL~~

MND-3393

031712081030

DECLASSIFIED

VII-6

CONFIDENTIAL

Fig. VII-2. Tensile Strength--TD Nickel

Fig. VII-3. Creep Rupture Behavior--TD Nickel

CONFIDENTIAL

DECLASSIFIED

MND-3393

0310587030

CONFIDENTIAL

VII-7

Fig. VII-5. Comparative Ultimate Tensile Strengths at Elevated Temperatures

Fig. VII-6. Comparative Stress to Rupture

CONFIDENTIAL

MND-3393

0310587030

~~CONFIDENTIAL~~
DECLASSIFIED

In addition, platinum possesses excellent seawater corrosion resistance. From an impact standpoint, both TD nickel and platinum have a face-centered cubic crystal structure and exhibit no ductile to brittle transition temperature.

4. Impact

a. Terminal velocity

It is likely that the fuel capsule will experience maximum forces if aborted from the launch vehicle prior to orbital injection and impacted upon a rigid material such as granite. Based on a safety philosophy of absolute containment of the radionuclide fuel in the biosphere environment, the fuel capsule would have to remain intact if aborted from the launch vehicle during the ascent phase of operation and impacted on the earth's surface.

The maximum free-fall impact velocity occurs when the re-entry body has attained terminal velocity. In this evaluation, three different re-entry modes or orientations were investigated: tumbling, 0-degree angle of attack, and 90-degree of attack where the angle of attack, α , is defined as the angle between the velocity vector and the longitudinal axis of the body. The terminal velocity of a body is that velocity at which the drag force, D_f , is equal to the weight of the body, W_b . Applying $D_f = W_b$ as the boundary condition, the drag force expressed as a function of velocity is

$$D_f = 1/2 \rho C_d A V^2 = W_b$$

where

ρ = density of atmosphere (slugs/ft³)

C_d = drag coefficient of body (dimensionless)

A = reference area of body (ft²)

V = velocity of body (fps)

Solving this equation for the terminal velocity, V_t , at any altitude yields

$$V_t = \sqrt{2 W_b / \rho C_d A}$$

~~CONFIDENTIAL~~
DECLASSIFIED

~~CONFIDENTIAL~~

MIND-3393

03145507030
~~CONFIDENTIAL~~

VII-9

Terminal velocities at sea level, 3000 feet, and 5000 feet for the bodies considered are presented in Table VII-1. Impact at these velocities will result in placing the maximum impact energy upon the system. Three bodies are examined: the Haynes-25 fuel capsule of the dynamic system, the TD nickel-platinum fuel capsule of the static system, and the Agena D launch vehicle with an assumed payload. Previous studies (SNAP 9A and SNAP 17A) assume a tumbling re-entry mode for the capsules due to the high aerodynamic instability of a body during free fall. This, along with the fact that the maximum altitude of the PMR terrain is around 3000 feet, leads to velocities of 269 fps for the Haynes-25 capsule and 267 fps for the TD nickel-platinum capsule.

From this equation, it can be seen that the terminal velocity of a body is directly proportional to the square root of the weight and inversely proportional to the square root of the reference area, in this case the cross-sectional area of the capsule. This criterion represents an important concept in the design of the fuel capsule. While the change from a thick to a thinner wall will tend to increase the velocity because of a decrease in area, the weight loss results in a more significant velocity decrease. This is shown in the data in Table VII-2 and the corresponding curve of terminal velocity versus capsule weight as a function of wall thickness in Fig. VII-7.

It should also be noted that as the wall thickness decreases, less heat is required for aerodynamic burnup. This represents another significant advantage of using a thin wall in satisfying the design criteria.

b. Impact design tests

Determining the structural integrity of a particular capsule design subjected to terminal velocity impacts at various angles of incidence can be accomplished only by an extensive test program. Such a program has been conducted for the SNAP 17A utilizing the rocket sled track at the Aberdeen Proving Grounds. The capsules, preheated to operating temperatures and suspended at various impact angles above the track, are subjected to the collision forces of 167-pound granite blocks carried on the rocket sled at speeds approaching the terminal velocity of the capsule. A detailed report of the test program and the results and recommendations are given in Appendix N. The capsule configurations are shown in Fig. VII-8. Examination of the SNAP 17A specimens has suggested several changes which have been incorporated into the 250-watt capsule. They are as follows:

- (1) Most of the initial capsule ruptures occurred at the weld (Appendix N). Thus, the welds for the 250-watt capsules will be redesigned to eliminate points of stress concentration.

~~CONFIDENTIAL~~

MND-3393

031712281030

TABLE VII-1

250-Watt Generator Terminal Velocity Study

<u>Body</u>	<u>Weight (lb)</u>	<u>Length (in.)</u>	<u>Outer Diameter (in.)</u>	<u>Area (ft²)</u>	<u>C_D</u>	<u>Orientation (deg)</u>	<u>Terminal Velocity (fps)</u>		
							<u>Sea Level</u>	<u>3000 ft</u>	<u>5000 ft</u>
Haynes-25 fuel capsule (dynamic system)	4.29	8.48	2.00	0.0218	0.735	$\alpha = 0$	476	497	511
					4.34	$\alpha = 90$	197	206	213
					2.5	Tumbling	258	*269	278
TD nickel fuel capsule (static system)	4.20	8.48	2.00	0.0218	0.735	$\alpha = 0$	470	492	505
					4.34	$\alpha = 90$	194	203	209
					2.5	Tumbling	254	*267	274
Agena D	15,800	324	60	19.6	4.39	Tumbling	396	*414	425

*Most probable re-entry mode.

CONFIDENTIAL

MMD-3393

CONFIDENTIAL

TABLE VII-2

Variation of Terminal Velocity of Haynes-25 Fuel Capsule with Change in
Reference Area and Capsule Weight

<u>Capsule Wall Thickness (in.)</u>	<u>Cross-Sectional Area (in. ³)</u>	<u>Capsule Weight (lb)</u>	<u>Terminal Velocity (fps)</u>
0.090	3.0775	4.2477	270.69
0.100	3.14	4.29	269.31
0.110	3.203	4.333	268.0
0.120	3.267	4.3767	266.68
0.130	3.331	4.4206	265.43
0.140	3.396	4.469	264.3
0.150	3.462	4.509	262.94
0.160	3.528	4.554	261.8

~~CONFIDENTIAL~~

MND-3393

~~CONFIDENTIAL~~

~~CONFIDENTIAL~~

Fig. VII-7. Terminal Velocity as a Function of Capsule Wall Thickness

~~CONFIDENTIAL~~

MND-3393

~~CONFIDENTIAL~~

CONFIDENTIAL

MND-3393

a. Six-Capsule Design

b. One-Capsule Design

Fig. VII-8. Capsule Designs

CONFIDENTIAL

VII-13

~~CONFIDENTIAL~~
~~DECLASSIFIED~~

- (2) It is possible that inadequate heating may have produced a cold weld. This, along with weld material impurities causing porosity, could have further weakened the weld strength. Hence, it is planned to use a butt weld for maximum weld strength.
- (3) The strength of materials, such as Haynes-25 and the Hastelloy family, rapidly decreases at temperatures above 1800° F. TD nickel superalloy exhibits much higher structural values at the high temperatures of the static system.
- (4) The capsule impact tests have revealed that a critical ratio of wall-to-end cap thickness exists; this value being around 2/1. Thus, the 250-watt capsules are designed with this ratio allowing for higher ductility.
- (5) SNAP 17A capsules with wall thicknesses as low as 0.080 inch have been tested. The results were successful at zero degrees impact, but for a 45-degree impact, five of nine capsules failed. Of these failures, however, four were due to weld ruptures while the other was caused by a secondary impact. Hence, in consideration of Items (1) and (2), the 250-watt capsules have been designed with a 0.100-inch wall, allowing for higher ductility in addition to significant lightweight features.
- (6) In lieu of the extended lip on the SNAP 17A single capsule design or the truncated conical end cap on the six-capsule design (see Fig. VII-8), a hemispherical end has been designed into the 250-watt capsule. Upon impact, a spherical body presents a more uniformly fixed surface for abrasion. This, along with the elimination of sharp edges and protrusions, reduces stress concentrations in and around the impact area, tending to enhance the capsule strength at critical incident angles.

Only through an adequate test program can the structural integrity of the capsule be established and alterations, if necessary, recommended. However, from the knowledge and experience gained in previous programs (SNAP IA, III, 7, 9A, and 17A), there is confidence that the capsule can be designed to terminal velocity specifications.

c. Aerodynamic convection cooling

A major factor in assessing the overall safety of the 250-watt RTG is the post-impact integrity of the fuel capsules. Since the integrity of the capsule depends to a large extent upon its temperature at the time

~~CONFIDENTIAL~~~~DECLASSIFIED~~
MND-3393

~~CONFIDENTIAL~~

VII-15

of earth impact, it will be necessary in future studies to determine impact temperature as a function of launch vehicle abort altitude. In such studies, the fuel capsules are assumed to be released at various points along the ascent trajectory and a heat transfer model is utilized to consider the internal heat source, aerothermodynamic heating, and convection and radiation cooling of the capsule in the nonaeroheating portion of the trajectory.

In previous studies (SNAP 17A), it has been found that the impact temperature of the fuel capsule decreases as the abort altitude increases.

d. Ground burial and potential meltdown

Future studies will also include the determination of the probability and conditions of earth burial of the 250-watt fuel capsules on free fall terminal velocity impact. Such a test was conducted at Aberdeen Proving Grounds for the SNAP 17A program. Eight SNAP 17A capsules were dropped from a helicopter at an altitude of 5000 feet. This altitude was sufficient to achieve the terminal velocity of about 225 fps. The results showed crater depths ranging from three to eight inches with a soil cover from three inches to no cover at all. It is apparent that the probability of burial of the 250-watt fuel capsules upon terminal velocity is largely dependent upon the soil type. Other factors, such as a horizontal velocity component and the orientation at impact, may have some effect.

If it is found that there is a chance for ground burial of the 250-watt fuel capsules, as the tests seem to indicate, it will also be necessary in later studies to examine the time-temperature characteristic of the fuel capsule burial after an earth impact at terminal velocity. The purpose will be to determine if and when the fuel capsule would melt after the impact. Release of radioactive fuel into the environment due to clad failure can only be allowed if this release is completely confined or localized.

5. Launch Pad Incident

One of the most serious, potential problems of any missile launching is that of a launch pad abort, the magnitude of the problem becoming even more serious with the presence of radioactive material aboard the missile. The use of strontium-90 for the 250-watt RTG presents a very hazardous problem should any of the radionuclide be released during a pad incident. Therefore, the integrity of the generator and fuel capsule must be assessed under a launch pad abort environment.

Two of the most destructive launch pad accidents are missile fuel tank rupture due to overpressurization or destruct system failure and

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED
~~CONFIDENTIAL~~

that of fallback after liftoff due to propulsion system failure. Both result in a violent explosion, producing a strong thermal shock wave followed by a short duration fireball of intense heat, ending in residual burning of the fuel. The first of these aborts arises from fuel tank rupture prior to liftoff, the maximum effect occurring with the ignition and spontaneous combustion of all the fuels and oxidizers. The second, fallback after liftoff, occurs with the explosion of the first stage booster causing fallback of the entire vehicle; the second booster stage exploding upon impact on the surface. Although the single* explosion of the combined boosters produces a shock wave of slightly higher intensity than the sequence of explosions, the second type of abort is considered to be the more destructive since the separate explosions lead to longer duration of the fireball.

This section examines the structural and thermal integrity of the Sr-90 fuel capsules during exposure to the shock of the missile fuel tank rupture and thermal environment of the missile fallback abort. The first analysis deals with the overpressures of various booster explosions while the second analysis studies the thermal effects of the fireball.

Since the availability of literature and information involving aborts of this type are extremely limited, and it is difficult to predict with a high degree of certainty, the ability of any system to withstand the effects of such an adverse environment, any theoretical analysis should be justified by a test program.

6. System Description

The present version for the dynamic generator is based upon a fuel capsule assembly of 14 Haynes-25 fuel capsules arranged in two parallel planes of seven capsules each. The fuel assembly of the static generator is an arrangement of 18 TD nickel fuel capsules in two parallel planes of nine each. An adapter module housing the generator, along with electronic gear, will be located atop the Agena D below the nose cone shroud. The surface skin of this adapter will serve as the radiator area of the dynamic heat rejection system.

The fuel capsules for both generator systems have the same configuration--cylindrical with hemispherical ends. The Haynes-25 capsule is designed with a 0.100-inch wall while the TD nickel capsule wall is 0.090 inch with an outer 0.010-inch layer of platinum.

*In an actual abort, there may be a series of explosions, the initial blast followed intermittently by explosions of lesser intensity as the propellant vapors mix. However, for the purpose of this report, there is only concern for the initial detonation of each stage, this producing the greatest shock reverberations.

DECLASSIFIED
~~CONFIDENTIAL~~
MND-3393

~~CONFIDENTIAL~~

VII-17

The launch vehicle consists of two missile boosters, the first stage being the Atlas utilizing LOX/RP-1 fuels and the second being the Agena-D with hypergolic IRFNA/UDMH propellants. The payload consists of the adapter section and the satellite nose.

7. Missile Explosion on Launch Pad

a. Approach

The shock overpressure generated by an exploding missile on the launch pad may be the most severe dynamic forces to which the generator could be subjected. A study by the Space Technology Laboratory of the intense shock wave forces of an LOX/RP-1 fueled Atlas missile explosion has produced two empirical equations simulating shock environment (Ref. 1). The first equation is that predicting the average pressure

$$P = 593/Z^3 - 28.8/Z^2 + 20.7/Z.$$

The second is an expression of the pressure at the 98% confidence level, that is to say, 98% of the shock front overpressures will be below this value,

$$P = 9862/Z^3 - 187.9/Z^2 + 52.8/Z$$

where,

$$Z = R/W^{1/4}$$

P = average side on overpressure (psi)

R = distance from explosion (ft)

W = total weight of propellants (lb)

To derive these equations, several assumptions had to be made. It was assumed that the missile tanks ruptured such that a mass propellant spill occurred, that the total propellant weight in the missile at spill time was equal to the effective weight, and that an ignition source was present at the time of tank rupture. Although these equations were developed to apply specifically to the Atlas LOX/RP fuel, they may be used as well for other explosive fuels if the TNT equivalence is the same as that for LOX/RP. A 10% equivalence means essentially that 100 pounds of TNT will produce the same blast effects as 1000 pounds of propellant. The TNT equivalence of the Agena-D propellants is taken to be anywhere from 2 to 10%. However, test programs involving these fuels have revealed that the thermal effects of hypergolics greatly exceed the mechanical effects and, hence, the explosive characteristics are often considered negligible (Ref. 2).

~~CONFIDENTIAL~~

MFD-3393

DECLASSIFIED

~~CONFIDENTIAL~~

VII-18

Inspecting these equations for the shock overpressures, one notes that as the distance, R , decreases, the overpressure, P , increases as the inverse cube of R , going off to infinity as R approaches zero (Fig. VII-9). Thus, for distances much less than 100 feet, one may expect the resulting calculations to be conservative.

b. Results and conclusions

Three credible explosions were considered. Table VII-3 supplies the pertinent data of the Atlas/Agena-D missile, and Table VII-4 gives the locations, approximate distances from the explosion to the fuel block in the adapter module, and the resulting overpressures.

TABLE VII-3
Atlas/Agena-D Data

<u>Missile</u>	<u>Height (ft)</u>	<u>Fuel</u>	<u>Oxidizer</u>	<u>Propellant Weight (lb)</u>	<u>TNT Equivalent (%)</u>
Atlas	72	RP-1	LOX	244,500	10
Agena-D	20.6	UDMH	IRFNA	14,100	2-10

TABLE VII-4
Distances from Explosion to Fuel Block

<u>Explosion Location</u>	<u>Distance (ft)</u>	<u>$\bar{P}$ (psi)</u>	<u>P (98%)</u>
A. At Atlas engines	93.85	11.13	132.55
B. At Atlas propellant tank junction	57.85	37.12	547.6
C. At center of mass of all propellants	55.35	42.87	645.6

Since the dimensions of the proposed adapter module and the fuel assembly location within the module have not been specified, it is assumed the fuel assembly is located at a distance of 1.25 feet above the Agena-D vehicle (Ref. 3) (see Fig. O-1, Appendix O).

In Explosions A and B, only LOX/RP-1 fuel explosions were considered. Explosion C uses the total weight of all the propellants, taking the IRFNA/UDMH to be 10% TNT equivalent. This assumption that the Agena fuels explode is justified in view of a conservative approach (Ref. 2).

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

VII-19

Fig. VII-9. Explosion Overpressure versus Distance from Explosion--LOX RP-1 Fuels

~~CONFIDENTIAL~~

MND-3393

0370201030

~~CONFIDENTIAL~~

It was assumed that the fuel capsule alone is subjected to the maximum shock overpressure of 645.6 psi. The structural integrities of the fuel capsules were examined (Appendix O) and it was found that 4480 psi are needed to rupture the Haynes-25 capsule, and 1930 psi are needed for the TD nickel capsule rupture. The analysis is conservative in that the shock absorption effects of the generator and the missile structure are neglected. It is therefore reasonable to conclude that even if the generator and fuel block are destroyed by a launch abort explosion(s), the capsules will withstand the shock of even the most severe missile blast.

8. Thermal Effects of Fireball

a. Approach

Following the strong thermal shock wave of the missile explosion, a large fireball of intense heat is formed. Although its duration is only a matter of a few seconds, the high temperatures and enormous amounts of energy released could prove detrimental to an RTG.

Only a limited amount of knowledge exists concerning missile fireballs, and the available sources of information are so varied in content that one can only speculate as to the thermal characteristics of any given fireball. From the information at hand, however, a reasonable approximation of a simulated environment can be obtained. A compilation of Refs. 2 and 4 through 11 produced data, both theoretical and experimental, of some fireball models. To achieve theoretical results, several assumptions and conditions must be established. These are:

- (1) Mass spillage of propellants.
- (2) Rapid rate of initial growth to fireball to linear dimensions exceeding the height of the missile by a factor of two or more.
- (3) Subsequent liftoff and rise due to buoyancy of the hot combustion products.
- (4) The drifting of the fireball clear of the pad due to the normal rise of hot gases and ground winds.
- (5) Participation of only a fraction of the initial propellants in the violent reacting fireball (for the Atlas only about 6% of the available LOX enters into the combustion).
- (6) Subsequent pool fires and minor explosions of spilled fuel and vapors for much longer duration than the fireball but of a lesser intensity.

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

0315587030

VII-21

- (7) The fireball temperature taken constant during the duration (this will tend to produce conservative results).
- (8) Radiant heat transfer greatly overshadowing convection and conduction effects.
- (9) Heat losses by radiation from the fireball to the surroundings considered negligible.
- (10) Emissivity of combustion, $\epsilon_g = 1$.*

Table VII-5 gives a theoretical temperature profile of an Atlas LOX/RP-1 missile fireball. Since no information on the IRFNA/UDMH fireball is available, the characteristics of the Titan II 1/2 scale tests utilizing $N_2O_4/0.5$ UDMH- 0.5 N_2H_4 are used, the propellant chemical composition and weight (15,800 pounds) being similar to the 14,100 pounds of the Agena-D IRFNA/UDMH.

TABLE VII-5.

Theoretical Temperature Profile of Burning Atlas Missile (Ref. 4)

<u>Temperature</u> (°F)	<u>Duration</u> (sec)	<u>Time</u>	
		<u>Sec</u>	<u>Min</u>
6000	Few microseconds	0	0
4500	4	4	0.067
3000	3	7	0.12
2000	490	497	8.3
1500	700	1197	20.0

*Question may arise as to credibility of such high theoretical emissivity. The fireball is an extremely violent reaction, stirring up great quantities of dust and foreign particles which form countless cavities or pockets of concentrated material. In view of these dense pockets, large beam lengths of over 200 feet, and absence of specific luminosity data for radiation of the combustion products H_2O and CO_2 , the assumption $\epsilon_g = 1$ is justified, although conservative (Ref. 6).

~~CONFIDENTIAL~~

MND-3393

0317281030

~~CONFIDENTIAL~~
DECLASSIFIED

b. Results and conclusions

As mentioned previously, for the sake of conservatism, the capsule alone was considered subjected to the fireball environment. Now the Atlas fireball, which occurs first, is assumed to last for a period of 4.95 seconds after which its temperature drops rapidly. However, somewhere during the first five seconds the missile topples and the second fireball of the Agena stage occurs. The 4500° R temperature of the hypergolic propellants will be somewhat lower than the 5100° R of the RP fuel with higher carbon content (Ref. 6) and is assumed to last for 5.41 seconds, making a total fireball duration of $4.95 + 5.41 = 10.36$ seconds.

Assuming infinite conductivities of the capsules and fuel, a preliminary analysis compared the heat absorbed by the capsules in this time interval to the heat required to entirely melt the capsules. Calculations showed that 1361.5 Btu are required to melt the TD nickel capsule and 1240.2 Btu to melt the Haynes-25 fuel capsule, thereby exposing the fuel. However, from a consideration of the temperature profiles, the corresponding average heat flux values of 248 and 134 Btu/ft²-sec produce only 722 Btu to the Haynes-25 capsule and thus, at first approximation, it appears the capsule will maintain its integrity.

For a more rigorous analysis, a heat transfer and ablation study of the exposed capsule has been performed. The method of solution was programmed on an IBM 7094 digital computer according to the Transient Heating Digital Analyses for Structural Design (Ref. 12). This program (Martin Company FB029) handles arbitrarily arranged and selected structural elements with temperature-dependent material properties. Facets considered are one-dimensional conduction, radiation heat loss and ablation. Equations of curves of enthalpy versus temperature are utilized in handling variable specific heat and phase changes such as melting. The temperatures are calculated for finite increments of time and, to increase accuracy, the heat balance equations are written as functions of the average temperature gradients over a time interval rather than the temperature gradients at the beginning of the interval. Simultaneous equations are then solved for each interval of time.

A parametric study (Appendix O) was performed to determine the times at which the capsule walls will ablate (thereby allowing a fuel release) when subjected to a constant heat input. The results for the Haynes-25 fuel capsule are given in Table VII-6.

~~CONFIDENTIAL~~
DECLASSIFIED MND-3393

~~CONFIDENTIAL~~

VII-23

TABLE VII-6

Haynes-25 Ablation Times

<u>Average Flux</u> <u>(Btu/ft²-sec)</u>	<u>Fuel Exposure Time</u> <u>for Haynes-25 (sec)</u>
150	15
175	12.7
189	11.3
200	10.5
250	8.2
300	6.4

Values of 150 and 300 Btu/ft²-sec applied for a 20-second period were not enough to meet the TD nickel capsule. Hence, the integrity of the TD nickel capsule in a fireball is beyond question.

From the analysis it is found that a heat rate of 204 Btu/ft²-sec is needed to melt the Haynes-25 capsule within the fireball duration time of 10.36 seconds. This is the critical heat flux, and any value greater than this may present a definite hazard to the capsule.

The question now arises as to what flux is obtainable in a fireball. The best experimental information available is that of the results of the Titan II one-half scale tests conducted by the Bureau of Mines (Refs. 2, 7, 8 and 13). Values measured by calorimeters recorded average heat transfer rates ranging from 50 to 175 Btu/ft²-sec. Considering the maximum average of 175, the Haynes-25 capsule will melt at 12.7 seconds. This, however, is beyond the maximum fireball duration and, hence, the capsule will maintain its integrity for 10.36 seconds. It is possible that values higher than 175 Btu/ft²-sec can be produced in a fireball. Just how much higher is uncertain, and one can only hypothesize as to the values. By considering the temperature profiles of the LOX/RP and IRFNA/UDMH fuels, the average theoretical heat flux is found to be 254 Btu/ft²-sec (Appendix O). This value is above the critical value and hence the fuel would be exposed in 8.2 seconds. This, however, is conservative since the thermal absorption effects of the generator are not considered.

In summary, it was found for the Haynes-25 capsule that:

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED
~~CONFIDENTIAL~~

- (1) Subjected to a heat flux value above $204 \text{ Btu/ft}^2\text{-sec}$, the capsule will burn within 10.36 seconds.
- (2) Subjected to an experimental flux of $175 \text{ Btu/ft}^2\text{-sec}$, the capsule will not burn.
- (3) The following should be considered in examining Items (1) and (2):
 - (a) The theoretical flux is conservative in view of the previous assumptions or Conditions 1, 2, 7, 9 and 10.
 - (b) It is assumed that the capsule is positioned at the base of the fireball hemisphere. This implies maximum heating and a view factor of one for the entire fireball duration. This is highly improbable in an actual abort due to Conditions 3 and 4.
 - (c) Much of the available heat will go into the surrounding structures. The analysis is very conservative in that it considers the capsule alone subjected to the fireball.
 - (d) It is likely that the capsule will be subjected to only part or none of the fireball radiation since it may be shielded by the missile structure or thrown clear of the fire.
 - (e) The analysis does not consider any fire fighting equipment or emergency procedures which will most certainly reduce the destructive effects of a pad fire.
 - (f) The theoretical flux is based upon an ideal mixing ratio of fuel to oxidizer (for LOX/RP this is around three to one and for N_2O_4 /UDMH around two to one). This is highly improbable in an actual abort.
 - (g) To January 30, 1964, the unofficial success record of Atlas/Agena-B and D-type launches is 18/23 or 0.780. Of the five launch failures, only one was an actual launch pad abort, occurring at PMR on September 9, 1961; the failure due to faulty electrical connections with the umbilical. Thus, the launch pad failure is 1/23 or 0.0435.

In view of these considerations, and relying heavily upon the experimental fireball data, it may be concluded that both the Haynes-25 and TD nickel capsules will withstand the fireball environment.

CONFIDENTIAL
DECLASSIFIED MND-3393

~~CONFIDENTIAL~~

VII-25

C. AEROSPACE SAFETY EVALUATION

1. Vehicle and Assumed Trajectory

The two-stage launch vehicle for the 250-watt RTG program is an Atlas/Agena-D missile. The first stage booster, the Atlas, utilizes approximately 171,000 pounds of liquid oxygen and 76,000 pounds of RP-1 hydrocarbon fuel in delivering a thrust of 385,500 pounds. The second stage Agena-D booster utilizes the hypergolic propellants, unsymmetrical dimethylhydrazine (UDMH) as the fuel and inhibited red fuming nitric acid (IRFNA) as the oxidizer, in producing a thrust of 16,000 pounds in a vacuum. A description of both missiles and their guidance and control, propulsion and destruct systems is presented in Appendix P.

a. Launch sequence

During a typical launch sequence, all Atlas engines are fired on the ground, and when sufficient thrust has been obtained, the vehicle rises from the launcher. There are six principal milestones in the powered portions of an Atlas/Agena-D flight. These are: vertical rise, pitch over, staging, sustainer cutoff, vernier cutoff and upper-stage separation. However, staging is the only milestone that will be discussed since it is the most pertinent.

The staging operation prepares for and accomplishes the jettisoning of the booster engine package. It is initiated by a guidance system command from the ground as a function of pre-established guidance equations, and controlled by the flight programmer. After staging, the vehicle flight attitudes in pitch and yaw are maintained through thrust vector control of the sustainer engine, and the roll attitude is maintained by differential gimbaling of the vernier engines. The flight path is adjusted by ground guidance correction signals which torque the autopilot pitch and yaw displacement gyros. A sustainer stage pitch program, if required, originates in the flight programmer. Sustainer engine cutoff discrete signal (SECO), vernier engine cutoff discrete (VECO), start Agena D timer discrete, and initiate Agena separation discrete, all initiated by guidance, are enabled by the flight programmer at approximately guidance staging discrete (GSD) + 56 seconds.

2. Credible Aborts

During the normal sequence of events of a nominal launch and ascent trajectory, there are several points at which an abort or a malfunction resulting in an abort is most likely to occur. These points can be predicted by examination of the sequence of events in the trajectory. The credible abort points for a 5000-mile circular polar orbit, the possible cause of the abort, and the resultant effect are shown in Tables VII-7 and VII-8.

~~CONFIDENTIAL~~

MND-3393

CONFIDENTIAL

TABLE VII-7
Abort Causes and Effects

<u>Time (sec)</u>	<u>Cause of Abort</u>	<u>Possible Effect</u>
T-0.8	Atlas engine(s) malfunction	Unpredictable path of payload
T+15	Failure of Atlas programmer to control pitch or roll program	Launch vehicle path entering unsafe area
T+65	Maximum dynamic pressure	Failure of a critical component
T+133.5	Failure of Atlas programmer to activate BECO or stop pitch control	Vehicle in uncontrollable mode
T+136.7	Sustainer engine not centered, first stage not jettisoned	Damage to sustainer engine; excess weight on vehicle; degradation of vehicle performance reducing chance of success
T+280.7	Failure of Atlas programmer to activate SECO	Trajectory of vehicle uncertain
T+300.4	Failure of MK II to activate VECO	Trajectory of vehicle uncertain
T+302.9	Failure of separation system	Agna unable to provide thrust
T+361.8	Agna-D engine malfunctions	Trajectory of payload uncertain
T+581.5	Failure of Agna-D first burn cutoff	Trajectory of payload uncertain
T+6437.7	Agna-D engine malfunction	Trajectory of payload uncertain

CONFIDENTIAL
MND-3393

TABLE VII-8
Nominal Ascent Trajectory

TABLE VII-8 Nominal Ascent Trajectory

Time from Launch (sec)	Vehicle Weight (lb)	Altitude (ft)	Relative Velocity (fps)	Latitude (deg)	Longitude (deg)	<u>Instantaneous Impact Point</u>		Apogee Altitude (naut mi)	Perigee Altitude (naut mi)	
0	279,845	438	0	34.644N	120.593W	--	--			Liftoff
65.0	178,624	38,912	1,705	34.595N	120.595W	34.288N	120.607W			Maximum dynamic pressure
133.724	71,688	201,640	8,908	33.880N	120.617W	27.241N	120.906W			BECO
136.727	63,536	212,148	8,982	33.813N	120.619W	27.086N	120.913W			Jettison booster package
200.0	46,002	410,095	11,377	32.176N	120.675W	22.410N	121.119W			Jettison nose firing
280.844	24,597	618,170	17,065	29.223N	120.787W	9.000N	121.712W			SECO
300.353	24,471	660,867	17,012	28.345N	120.822W	8.935N	121.715W			VECO
305.353	15,807	670,776	16,994	28.120N	120.831W	8.935N	121.715W			Atlas/Agena-D separation
349.799	15,807	740,227	16,871	26.129N	120.914W	8.934N	121.715W			Agena ullage ignition
363.099	15,728	754,517	16,853	25.535N	120.940W	8.918N	121.716W			First ignition main
535.0	6,350	727,007	25,443	16.199N	121.355W	62.202S	123.964W			Last impact point
540.0	6,077	722,884	25,861	15.858N	121.370W	--	--	367.4	72.2	In orbit
582.522	3,773	691,573	30,303	12.694N	121.507W	--	--	5015	115.2	Agena shutdown
6425.65	3,773	30,358,818	13,245	9.618S	34.107E	--	--	5000	114.1	Second Agena ullage ignition
6462.37	2,501	30,359,205	16,942	9.042S	33.959E	--	--	5002	4997.8	Second Agena shutdown
6947.64	2,501	30,355,313	16,953	0	32.011E	--	--	5002.5	4997.6	Orbit injection

~~CONFIDENTIAL~~

3. Re-entry Ablation Analysis

Based on preliminary investigations of strontium compound fuel forms (Ref. 21), an encapsulation material must ablate by approximately a 200,000-foot altitude for the fuel form to experience complete ablation by the 100,000-foot altitude required to obtain satisfactory ablation and dispersion of the strontium fuel form.

To achieve early ablation of the encapsulating material, the 250-watt system has been designed to release the individual generator capsules at altitudes of about 325,000 feet, which provides higher heating rates for the individual capsules than if they were re-entering as part of the generator fuel assembly (Ref. 22). An ablative release mechanism, in the form of an aluminum retainer band, is used to hold the capsules and generator together until early re-entry heating (at about 325,000 feet) causes the band to melt and release the generator assembly and individual fuel capsules for maximum re-entry heating.

The re-entry analysis utilizes two computer programs to predict re-entry ablation; a trajectory and heat flux program (Ref. 23); and a heat transfer and ablation program (Ref. 24). Each program is designed for use on the IBM 7094 digital system. The trajectory and heat flux program determines the velocity, altitude, angles and heating rates as a function of time for a given orbital decay. The heat transfer and ablation program corrects the heating rates for capsule geometry and tumbling modes, calculates heat transfer into the capsule, and calculates mass loss of the capsule until the heat flux of re-entry drops to almost zero or until the capsule is completely ablated. Calculation of mass loss is accomplished by melting, vaporization, sublimation, oxidation, etc., as dictated by the material properties of the capsule or fuel form. For this study, the mechanism of melting was used to calculate mass loss or ablation of the encapsulation and fuel form.

a. Trajectory and heat flux

The re-entry environment and heat flux generation can be sufficiently described by two air flow regimes, free molecular flow and a transition of continuum flow region (Ref. 25). For this study a free molecular flow model was used to establish the re-entry heat flux during the early high altitude stage of re-entry and the transition or continuum flow model for the second stage of re-entry. This results in a calculated heat flux value which is smaller in magnitude but more accurate than if a transition region had been assumed for the complete re-entry. The free molecular flow region was defined as existing down to the altitude where the heat flux generated by either region was equal, i. e., free molecular flow heat fluxes were used until they were equal in magnitude to that which a continuum model would produce and, at that point, the continuum model was used for the remainder of the re-entry. This transition altitude is a function of the size of the incoming object. For the 250-watt generator fuel capsules, it was 260,000 feet.

~~CONFIDENTIAL~~

MND-3393

~~CONFIDENTIAL~~

VII-29

Peak aeroheating for the fuel capsules was experienced at an altitude of 205,000 feet. As the capsule slowed down in the dense atmosphere, the effective heat flux or aeroheating became negligible at about 110,000 feet.

b. Heat transfer and ablation

The heat transfer (three-dimensional) and ablation (one-dimensional) program utilized a melting mechanism to calculate mass loss. The program corrected the heat flux data generated by the trajectory code to the geometry of the fuel assembly up to the time the retaining band had ablated, and then corrected for the individual capsule geometry for the remainder of re-entry.

The analytical model used to calculate ablation of the retaining band is shown in Fig. VII-10 where the ablation of 10 elements, one at a time, constituted breakthrough of the band and the resultant release of the individual capsules. Because an infinite band length was assumed for the program and the fact that mechanical stress will break the band before ablation is complete, the ablation altitude is felt to be conservative.

Figure VII-10 shows a model of the fuel capsule used in the ablation analysis. The eight inner elements represent the strontium fuel form while the three outer elements represent the encapsulation. During programming of this model, heat is always being conducted through the capsule (proportional to the various thermal conductivities, etc.) while the outer element is in the process of ablation. This results in a condition where the first few outer elements of fuel may be in a molten state before the encapsulation has ablated. During this study, partial melting of the fuel was always accomplished before the encapsulation acquired sufficient heat to ablate. As a result, upon encapsulation burnup, some of the fuel was also released to the atmosphere in the molten state.

4. Results

a. Ascent re-entry

One of the assumed mission requirements of the 250-watt RTG program is a circular 10,000-mile polar orbit. Since neither the payload nor the ascent trajectory has been defined to date, this discussion is based upon the data evolved during Phase I of SNAP 17A. This system calls for a circular polar orbit at an altitude of 5000 miles, the payload put into orbit by the Atlas/Agena-D launch vehicle from the Pacific Missile Range (PMR). Although this information yields no specific conclusions for the 250-watt system ascent study, significant comparisons can be noted.

~~CONFIDENTIAL~~

~~MND-3393~~

~~03710201030~~

DECLASSIFIED
CONFIDENTIAL

*Based on tumbling-spinning cylinder with respect to velocity vector.

Fig. VII-10. Re-Entry Ablation Models

CONFIDENTIAL

DECLASSIFIED MND-3393

~~CONFIDENTIAL~~

03:15:47:030

VII-31

The results from the aerospace safety evaluation of the SNAP 17A system reveal for the abort study from the nominal ascent trajectory that the partial burnup zone extremes extend from 8° N latitude and 122° W longitude to 85° S latitude and 42° E longitude. The near point of this zone with respect to the launch site (PMR) was established by the strontium-90 fuel capsule re-entering initially. The far point was partially established though not confined to the satellite/radioisotope thermoelectric generator gravity gradient system (GGS) re-entering initially. It is likely that, although the ascent trajectory and payload will be different, the partial burnup area for the 250-watt RTG system will be within this general area.

b. Results of re-entry ablation analysis

Dynamic system. The generator retaining band was exposed to aero-heating at an altitude of 400,000 feet and after 666 seconds, ablated at an altitude of 329,000 feet. Based on this capsule release altitude, six runs were programmed to describe encapsulation ablation as a function of release altitude to indicate the allowable margin of retainer band ablation altitude which could still permit encapsulation ablation at about 200,000 feet. As shown in Fig. VII-11, capsules released to the re-entry environment at altitudes of 275,000 feet or higher will ablate at or before an altitude of 200,000 feet. A capsule released at 250,000 feet will reach 183,400 feet before the encapsulation has ablated, and capsules released at 225,000 and 200,000 feet will not experience complete encapsulation ablation at all, i. e. , the capsules will fall to earth with only partial ablation of the encapsulation having occurred.

Because of the differences in melting point and thermal conductivities between the Haynes-25 and Sr-90 fuel form, the outer elements (Fig. VII-10) of the fuel form are sometimes in a molten state prior to the ablation of the last element of encapsulation. Figure VII-12 illustrates the ablation element history of the two outer elements of encapsulation and three outer elements of the fuel form for the capsule released at 325,000 feet. As seen from the figure, the capsule cools slightly from its initial orbital operating temperatures while in the early free molecular flow region, but starts increasing in temperature and enthalpy at about 300,000 feet. At 204,500 feet the second element of encapsulation ablates, together with the outer element of fuel which reached its ablative enthalpy earlier at about 210,000 feet. Although an element of encapsulation of the dynamic capsule model requires 40% less heat to ablate than an element of the fuel form, its melting temperature is 400° F higher than the fuel form which allows the fuel to reach a molten state before the encapsulation.

Static system. The generator retaining band was exposed to aero-heating at an altitude of 400,000 feet and after 666 seconds ablated at

~~CONFIDENTIAL~~

MND-3393

03:12:28:030

DECLASSIFIED
CONFIDENTIAL

Fig. VII-11. Encapsulation Burnup Altitude as a Function of Capsule Release Altitude

CONFIDENTIAL

DECLASSIFIED

MND-3393

✓

Fig. VII-12. Ablation Element History for A Capsule Release at 325,000 Feet

~~CONFIDENTIAL~~

an altitude of 329,000 feet. Based on this capsule release altitude, four runs were programmed to describe the encapsulation ablation as a function of release altitude to indicate the allowable margin of retainer band ablation altitude which could still permit encapsulation ablation by about 200,000 feet.

As shown in Fig. VII-13, capsules released to the re-entry environment at altitudes above 250,000 feet will ablate at or above 200,000 feet. A capsule released at 225,000 feet will reach 190,000 feet before the encapsulation has ablated, and capsules released at 200,000 feet or less will not experience complete encapsulation ablation at all, i. e., the capsules will fall to earth with only partial ablation of the encapsulation having occurred. The retainer band ablation altitude is a very conservative number since the band will break before it ablates.

Because of the differences in melting point and thermal conductivities between the platinum and the TD nickel and fuel form, the elements of the TD nickel and the outer elements of the fuel are in a molten state prior to the ablation of the single element of platinum. Figure VII-14 illustrates the element ablation history of the platinum, the two elements of TD nickel, and the two outer elements of fuel for the capsule released to the re-entry environment at 300,000 feet.

Since the platinum has a very high melting point, sufficient heat is transferred into the TD nickel and fuel to create internal melting before the platinum has time to reach its melting or ablation point.

c. Conclusions of re-entry ablation analysis

Based on the re-entry ablation results, it is predicted that the encapsulation material will be ablated at altitudes greater than 200,000 feet even if the prediction of ablation (neglecting the fact the band will break) for the generator retaining band is in error by as much as 80,000 feet. Furthermore, since it has been shown that some of the strontium fuel form is already in a molten state at 200,000 feet, the ultimate nuclear safety verification of re-entry ablation and strontium dispersion is excellent.

5. Fuel Dispersion

a. Seawater release

Although the Atlas/Agena-D launch vehicle has a high reliability, if an abort were to occur during the first two minutes after takeoff, there is a high probability of ocean impact in water of shallow or intermediate depth. The ocean bottom profile along the missile track is shown in Fig. VII-15. The first 4.7 nautical miles of the missile track are over land. The water depth reaches 200 feet at about two miles and the edge

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

Fig. VII-13. Encapsulation Burnup Altitude as a Function of Capsule Release Altitude

~~CONFIDENTIAL~~

Fig. VII-14. Ablation Element History for Capsule Released at 300,000 Feet

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

Fig. VII-15. Bottom Profile Along 182-Degree Azimuth from Point Arguello

~~CONFIDENTIAL~~
~~CONFIDENTIAL~~

of the continental shelf is reached at about 70 nautical miles. The fuel container is designed to resist seawater corrosion for several years, after which time the radiostrontium would be released. It is expected that this release would be gradual since corrosion would probably first open only small holes in the container, and the radiostrontium fuel is in the form of a slightly soluble chemical compound. However, in the following study an instantaneous release of the entire payload is assumed since this gives a maximum water concentration and represents a worst case situation.

Diffusion calculations. Calculations have been made using a diffusion equation that was developed by McEwen (Ref. 26) and used by Joseph and Sender (Ref. 27), the International Atomic Energy Agency ad hoc committee on waste disposal (Ref. 28), and the National Academy of Sciences committee on waste disposal in the Atlantic and Gulf coastal waters (Ref. 29). It is

$$P = \frac{Q}{2 \pi h K^2 t^2} e^{-\frac{r}{Kt}}$$

where:

P = activity concentration of the nuclide in the sea (curie/m³)
 (equivalent to $\mu\text{c/cc}$)

Q = activity of the released material (curies)

h = vertical thickness of the diffusion layer (meters)

K = diffusion velocity (meters/sec)

r = distance from source (meters)

t = time after release (sec)

The quantity, h , is equal to the thickness of the mixed layer for deposition in shallow water. For deposition in the thermocline*, or below, it is determined by the vertical distribution produced by thermal currents from the hot isotope. In this study the value of 50 meters has been chosen. K is conservatively chosen as 5×10^{-3} m/sec (Refs. 27 and 30). Q varies with time according to the relation:

$$Q = Q_0 e^{-\lambda t}$$

* A very stable layer of water, with little vertical diffusion beneath the mixed layer.

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

0315087030
~~CONFIDENTIAL~~

VII-39

where:

Q_0 = activity at time of release (curies)

λ = disintegration constant (sec^{-1})

Since Sr-90 is a long-lived isotope, the decay can be neglected ($\lambda = 7.91 \times 10^{-10} \text{ sec}^{-1}$).

The results of these calculations are shown in the graphs of Figs. VII-16 and VII-17. Figure VII-16 gives the activity concentration versus time for various radial distances from the source, and Fig. VII-17, the activity versus distance for various times after release. The calculations have been made for the fuel activity of 724,000 curies.

Hazards evaluation criteria. The ultimate hazard resulting from a sea release of radioactive isotope would be realized if the isotope were ingested directly or indirectly by the consumption of contaminated sea life. Two different approaches have been used in evaluating the potential hazard of the release of strontium in the waters of PMR.

The first of these was used in the study of the possible release of fission products from a nuclear rocket. It was developed in Refs. 31 and 32. It considers a single nonrecurring event and its effect on the sea environment. It evaluates the hazard by determining the activity which may be ingested by the consumption of fish assumed to have come into equilibrium with the sea environment. The following assumptions are made:

- (1) Man ingests an average of $15,200 \text{ cm}^3$ of fresh water in one week.
- (2) If a man obtains substantially his entire protein requirements for one week by eating fish, he will consume about 1500 grams.
- (3) A factor, S, relating the radiation exposure guide for the general population to that for radiation workers is introduced; it is taken to be 1/10.
- (4) A single incident exposure factor E_i is introduced. It is assumed that one year of exposure may be received in a single nonrecurring event. E_i is, therefore, taken as 50.

The criterion established is that the radioactivity in the fish consumed should not exceed that ingested by drinking water with the MPC_w for the isotope of interest.

~~CONFIDENTIAL~~

WD-3393

0317281030

DECLASSIFIED

CONFIDENTIAL

VII-40

Fig. VII-16. Ocean Activity Concentration Versus Time Since Release

CONFIDENTIAL

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

VII-41

Fig. VII-17. Ocean Activity Concentration Versus Distance from Release

~~CONFIDENTIAL~~

MND-3393

0171201030

~~CONFIDENTIAL~~
DECLASSIFIED

$$\text{Thus, } 1500 P f_c f_d \leq 15,200 \times \text{MPC}_w \times E_i \times S$$

where:

P = concentration of radioactivity in the seawater ($\mu\text{c}/\text{cm}^3$)

f_c = fish concentration factor; the ratio of the concentration of the element in the fish body to that in the seawater.

f_d = isotope dilution factor; the ratio of the atomic percent of the radioactive isotope in the seawater to the atomic percent of the element.

MPC_w = maximum permissible concentration (Radiation Protection Guide) of the isotope for radiation workers ($\mu\text{c}/\text{cc}$).

A maximum permissible concentration of the seawater, MPC_{sw} , for a particular nuclide may be calculated by solving for P when the expression becomes an equality; i. e.,

$$\text{MPC}_{sw} = \frac{15,200 \times \text{MPC}_w \times E_i \times S}{1500 f_c f_d} \quad (1)$$

Since strontium is an element that occurs naturally in seawater in measurable amounts, f_d is a variable. It is given approximately by

$$f_d = \frac{PA}{C}$$

where:

A = reciprocal activity of the nuclide ($\text{gm}/\mu\text{c}$)

C = natural abundance of the element in seawater (gm/cm^3)

Substituting in Eq (1) gives

$$(\text{MPC}_{sw})^2 = p^2 = \frac{15,200 \text{MPC}_w E_i S C}{1500 f_c A} \quad (2)$$

For strontium-90, MPC_w is $10^{-6} \mu\text{c}/\text{cm}^3$, f_c is taken as 10, C is $8 \times 10^{-6} \text{ gm}/\text{cc}$ and A is $7.02 \times 10^{-9} \text{ gm}/\mu\text{c}$. Then

~~CONFIDENTIAL~~
DECLASSIFIED

09:15:58:70:30
~~CONFIDENTIAL~~

VII-43

$$(\text{MPC}_{\text{sw}})^2 = \frac{15,200 \times 10^6 \times 50 \times 0.1 \times 8.0 \times 10^{-6}}{1500 \times 10 \times 7.02 \times 10^{-9}}$$

and

$$\text{MPC}_{\text{sw}} = 7.6 \times 10^{-2} \mu\text{c/cc}$$

This development of an expression for the MPC_{sw} is somewhat roundabout. A more direct development could be made in terms of the increase of body burden. Actually the eating of the 1500 grams of fish in equilibrium with water containing this MPC_{sw} of strontium-90 would result in an addition to the body burden in the bone of $6.84 \times 10^{-3} \mu\text{c}$. The resulting dose rate to the bone would be 1.33 mrem/wk.

The postulate in this model that the fish immediately come into equilibrium with the ambient water is highly conservative. Small organisms with short life cycles may come into equilibrium with the environment in a few hours but it is improbable that adult food fish would ever come into equilibrium with the strontium-90 contaminated water. Ophel (Ref. 33) found concentration for Sr-90 in fresh water perch of about 3000, but these were reached only after five years by fish that had spent their entire lives in the contaminated water.

The second approach, examined for check and comparison, is that of Dr. Isaacs, et al., in Ref. 34. They were examining an entirely different situation, the maximum permissible continuous concentration that is acceptable in seawater due to waste disposal therein. As in the foregoing analysis, they were concerned with ingestion of the radioactivity through the food chain. They have made an extensive study of the effect of the growth condition on the activity to be expected in the fish body.

They propose the following equation for calculating the maximum permissible continuous concentration, MPCC, for a nuclide when the limiting intake is determined by the body burden:

$$\text{MPCC} = \frac{S q' I_{\text{ne}}}{I_{\text{nb}}'} \times \frac{K + B}{B}$$

where:

q' = activity of the radioactive isotope in the critical organ when the body burden has been acquired (μc)

~~CONFIDENTIAL~~

MND-3393

03:12:29:10:30

~~CONFIDENTIAL~~
DECLASSIFIED

- I_{ne} = mass concentration of the total element (or carrier) in seawater (gm/cc)
- $I_{nb'}$ = total mass of the element (or carrier) in the critical organ (gm)
- K = physical decay constant of the nuclide (day^{-1})
- B = biological decay constant of the element for man (day^{-1})
- MPCC = maximum permissible continuous concentration for seawater ($\mu\text{c/cc}$)

For strontium-90, $q' = 2 \mu\text{c}$, $I_{ne} = 8.2 \times 10^{-3} \text{ gm/kg}$, $I_{nb'} = 0.13 \text{ gm}$, $K = 6.9 \times 10^{-5} \text{ day}^{-1}$, $B = 3.8 \times 10^{-5} \text{ day}^{-1}$, and S is taken as 0.1. Using these values, the MPCC is found to be $3.4 \times 10^{-5} \mu\text{c/gm}$ (or $\mu\text{c/cm}^3$).

Lines indicating the MPC_{sw} and the MPCC have been drawn on Figs. VII-16 and VII-17. It is observed that the MPC_{sw} is exceeded over an area with a radius of 128 meters for 3.48×10^4 seconds, or 0.403 days. The MPCC is exceeded to a radius of 6.07×10^3 meters for 7.02 days.

These calculations have considered only the effect of turbulent diffusion. Tidal and nontidal currents will also contribute to the dispersion of the radiostrontium but it is not possible to make a quantitative estimate.

Countermeasures and conclusions. The results of this analysis indicate that the release of even an entire payload of the radiostrontium is not an intolerable accident. Hazardous levels of activity would exist for such short times and over such small areas that the chance of an individual ingesting a significant quantity of radioactivity is virtually nonexistent.

If the aborted vehicle were to fall in shallow water near shore, efforts will be made to recover it. It is expected that recovery can be almost certainly made to depths of 100 feet and with some probability to 200 feet. For impact in deeper water, the contamination would probably not reach the surface, but the opportunity for fish to receive some activity would remain. In this case, and if a generator in shallow water is not recovered, it may be desirable to make periodic examination of the suspected area for radioactivity. If unexpectedly high levels of activity are found it would be possible to restrict fishing until the activity is dispersed. Many areas in this region are subject to restric-

~~CONFIDENTIAL~~
DECLASSIFIED

~~CONFIDENTIAL~~

VII-45

tion during missile launches and for gunnery exercises, so the facilities for patrolling are available. Periodic inspections of the fish catch for radioactivity could also be made. A difficulty in making analyses of the water and fish is that it is not possible to predict the time of release of the radioactivity so the inspections would have to be carried out on a long term basis.

b. Airborne release

The fuel capsule is designed to withstand impact from a height onto the launch pad, the temperatures of a launch pad and the overpressure due to a propellant detonation. The fuel capsules are further surrounded by a fuel assembly, generator and the satellite structure so that any release is extremely improbable. Nevertheless, calculations were performed to indicate the radiological hazard consequent to such an event.

Source term. Even if the fuel containment is violated, presenting some opportunity for release of the fuel, it is still very difficult to define a source term for any airborne diffusion. The fuel is pelletized, or has been compressed by step pressing, and has been sintered to some extent either in an oven, or by self-heating after pressing. Certainly it is not a fine powder that may easily become airborne, and it will not have been subjected to continuous high temperatures sufficient to cause volatilization. In the following study of a hypothetical release, it has been postulated that 0.1% of the entire loading is released over a period of 20 minutes.

Diffusion. The diffusion of the radioactivity has been calculated by the use of Sutton's equation which in its general form for a continuous point release is

$$\chi = \frac{2Q}{\pi\mu C_y C_z x^{(2-n)}} e^{-z^2/C_z^2 x^{(2-n)}} e^{-y^2/C_y^2 x^{(2-n)}} \quad (1)$$

where:

- χ = activity concentration (curie/in.³, equivalent to $\mu\text{c}/\text{cm}^3$)
- Q = release rate (curie/sec)
- μ = wind velocity (in. /sec)
- C_y = lateral diffusion coefficient ($\text{m}^{n/2}$)
- C_z = vertical diffusion coefficient ($\text{m}^{n/2}$)
- x = distance from source (m)

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

CONFIDENTIAL

n = stability index (dimensionless)

y = horizontal distance from centerline of plume (m)

z = vertical distance from centerline of plume (m)

Calculations are customarily made for the points on the ground under the centerline of the plume; in this case the second exponential term becomes unity.

Meteorological conditions. Diffusion conditions are dominated by the subsidence inversion that prevails about 80% of the time. The height of the base of this inversion varies with the season being highest in summer (July) and lowest in winter (December). During 1960, the average height for the region of the Pacific Area Launch Complex 2 (PALC) was 1400 feet. Within the marine layer beneath the inversion base, diffusion conditions are good but the inversion base places an effective lid on the diffusion.

PALC 2 is at an elevation of about 400 feet. The inversion base is often below this and is sometimes at sea level. Diffusion within the inversion is quite limited. The inversion base serves as a boundary for diffusion from above as well as from below. When the inversion base is below the elevation of PALC 2, points on the ground below the elevation of the inversion base are effectively protected from the radioactive plume.

If the inversion base is at sea level, no ground points are protected in this way but vertical diffusion within the inversion layer is limited and the plume will move away from the source horizontally, producing slight concentrations at lower elevations.

Analytical models. On the basis of these conditions, two meteorological models have been adopted for analysis. The first of these postulates that PALC 2 is within the marine layer with the inversion base at 300 meters elevation. At large distances, the radioactivity becomes uniformly distributed vertically through the marine layer. This requires a modification of Eq (1), giving

$$\chi = \frac{Q}{\pi^{1/2} \mu C_y x^{(2-n)/2} h} \quad (2)$$

where h = thickness of diffusion layer (m). The lateral dispersion is postulated to be of the usual form, and for off-axis points can be found

by using the term $e^{-y^2/C_y^2 x^{(2-n)}}$.

CONFIDENTIAL

DECLASSIFIED

MND-3393

0315507030
~~CONFIDENTIAL~~

VII-47

The second model assumes that the inversion base is at sea level. The concentration at various points is calculated using appropriate values of the parameters in Eq (1).

Topographic considerations. The cloud concentrations have been calculated at three distances, 12,000, 16,000 and 40,000 meters. The first of these is approximately the distance to Lompoc, the nearest town having an elevation of 93 feet, and a population of about 12,000. A height of land with an elevation of more than 800 feet is interposed on the direct line from PALC 2 to Lompoc; a plume of activity to reach Lompoc would have to follow a sinuous course, generally northward into the Santa Ynez Valley, and then eastward up the valley. The second distance, 16,000 meters, is that to Jalama Beach. On the direct line from PALC 2, the ground rises to 2170 feet in El Tranquillon, but it is perhaps credible that radioactivity could reach Jalama Beach by a sinuous course. The distance of 40,000 meters is that to Gaviota, a place name that represents the closest approach of Highway 101 to NMFLPA.

Diffusion parameters. C. L. Newcombe, et al., in their study of the Point Arguello environment have suggested the use of the meteorologic parameters as follows:

	<u>Marine Layer</u>	<u>Inversion Layer</u>
μ (m/sec)	3.6	3.6
C_g ($m^{(n/2)}$)	0.24	0.12
C_z ($m^{(n/2)}$)	0.14	0.05
n	0.25	0.50

In the calculations made, these values were used: $Q = 0.6$ curie/sec, $h = 300$ m. The elevation of the source was taken as 120 meters. The release was considered to take place in 20 minutes.

Dose rates. Cloud concentrations in themselves give little information concerning the hazard to the receptor. Of more interest is the activity of radionuclide inhaled, and the integrated lifetime dose received. In an airborne release of radiostrontium, the principal dose to a receptor in the cloud path is incurred by inhalation. The activity inhaled is calculated directly.

$$I = XBt$$

CONFIDENTIAL

MND-3393

0317201030

DECLASSIFIED

~~CONFIDENTIAL~~

where:

I = activity inhaled (μc)

B = breathing rate (cm^3/sec)

t = exposure time (sec)

It is assumed that the standard man inhales 20,000 liters ($2.0 \times 10^7 \text{ cm}^3$) of air in 24 hours. The average breathing rate is consequently $232 \text{ cm}^3/\text{sec}$. However, it is usually assumed that half of the 20,000 liters is inhaled during the more active eight hours of the day. The breathing rate during this period is consequently $347 \text{ cm}^3/\text{sec}$ (Ref. 36).

The most significant assessment of the potential radiation hazard from inhalation is obtained by a calculation of the integrated lifetime dose to the critical organ accruing from the activity inhaled. This may be calculated by the method proposed by Burnett (Ref. 37). The applicable equation is:

$$D' = \frac{73.8 f_a \Sigma FE (RBE) n T_E}{m}$$

where:

D' = lifetime dose for activity inhaled ($\text{rem}/\mu\text{c}$)

f_a = fraction of activity inhaled that remains in the critical organ

$\Sigma FE(RBE)n$ = energy per disintegration delivered to the critical organ, considering the relative biological effectiveness (RBE) of the radiation, and n the relative damage factor for nuclides deposited in the bone (mev)

T_E = effective half life of the activity in the critical organ (days)

m = mass of the critical organ (gm)

For the inhalation of strontium-90, a distinction should be made between soluble and insoluble forms. The bone is the critical organ for the soluble form and the effective half life is long. For the insoluble form, the lung is the critical organ and the residence time of the activity is relatively short. In the subsequent calculations, the

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

VII-49

values used for the parameters for strontium-90 with its daughter product, yttrium-90, are given in the following (Ref. 36).

<u>Parameter</u>	<u>Insoluble</u>	<u>Soluble</u>
f_a	0.12	0.12
$\Sigma FE(RBE)n$	1.1	5.5
T_E	120	6.4×10^3
Critical organ	Lung	Bone (including marrow)
Mass	1000	10,000
$D' \text{ rem}/\mu\text{c}$	1.18	31.1

Conclusions. Results for computations using the analytical models described are given in Table VII-9.

TABLE VII-9

First Model; Uniform Vertical Dispersion in the Marine Layer

<u>Place</u>	<u>Distance (meters)</u>	<u>Cloud Concentration ($\mu\text{c}/\text{cc}$)</u>	<u>Activity Inhaled (μc)</u>	<u>Lifetime Dose (millirem)</u>
Lompoc	12,000	3.66×10^{-7}	0.102	120
Jalama Beach	16,000	2.83×10^{-7}	0.079	92.5
Gaviota	40,000	1.285×10^{-7}	0.036	42.1

Second Model; Ground Based Inversion

<u>Place</u>	<u>Distance (meters)</u>	<u>Elevation (meters)</u>	<u>Concentration ($\mu\text{c}/\text{cc}$)</u>		<u>Lifetime Dose (millirem)</u>
			<u>Plume</u>	<u>Ground</u>	
Lompoc	12,000	30	1.348×10^{-5}	1.150×10^{-6}	377
Jalama Beach	16,000	0	8.76×10^{-6}	5.03×10^{-7}	165
Gaviota	40,000	0	2.21×10^{-6}	1.08×10^{-6}	354
(Maximum)	32,140	0	3.06×10^{-6}	1.13×10^{-6}	370

~~CONFIDENTIAL~~

MND-3393

~~DECLASSIFIED~~
~~CONFIDENTIAL~~

The maximum exposure at sea level for the inversion case is found to occur at 32,140 meters where it amounts to 370 millirems. The integrated lifetime doses in Table VII-8 have been calculated, assuming that the radiostrontium is in an insoluble form. In this case the lung is the critical organ and the greater part of the so-called lifetime dose is received in the first few months. If the radiostrontium is in a soluble form, the critical organ is the bone and the integrated lifetime dose is larger by a factor of 31.1/1.18. However, the dose would now be spread over 50 years with the dose rate for the first year, which would be greatest, not being excessive. Examination of the tabulated results shows that the integrated doses that might be received by receptors at these points are not excessive. The maximum permissible dose for the general public is 500 millirem per year and this is not exceeded in any case.

6. High Altitude Dispersion of Sr-90

In the advanced 250-watt generator mission, the plan calls for burnup of the payload, including the radiostrontium fueled generator, upon re-entry. In a successful mission, this re-entry will not take place until after the elapse of several hundred years when the radioactivity will have decayed to low levels. In the improbable case of an unsuccessful mission terminated by an abort at near orbital velocity, or the attainment of only a short lived orbit, the re-entry will result in the insertion into the mesosphere of the total strontium-90 inventory of the satellite system.

In this section, the subsequent tropospheric distribution and ground deposition of the strontium-90 is calculated using a modification of a fallout model developed for the consideration of bomb debris. The resulting atmospheric concentration is compared to the maximum permissible atmospheric concentration (MPC_a) and the atmospheric burden and ground deposition to that produced by bomb testing. It is found that the tropospheric concentration is several orders of magnitude below the MPC_a .

It is concluded that the re-entry burnup of the 250-watt RTG after a successful mission presents no significant hazard.

a. Fallout estimation

Stebbins (Ref. 38) has proposed that the fallout from the injection of radioactive material into the atmosphere can be fairly well predicted by assuming a half-residence time of material injected into the mesosphere of five years, for the stratosphere of two years, and for the troposphere of 21 days. Equations for this analytical model have been fully developed in the SNAP 9A report (Ref. 39).

~~CONFIDENTIAL~~

MND-3393

~~DECLASSIFIED~~

0000000000
~~CONFIDENTIAL~~

VII-51

Bombs exploded on or near the surface produce a great deal of local fallout and inject into the troposphere and stratosphere. Detonations far enough above ground that the fireball does not reach the earth's surface produce practically no local fallout. For detonations at higher altitudes, and for high-yield detonations at any altitude there is some injection into the mesosphere.

In this section, the result of injection of the fuel load of the 250-watt generator mission into the stratosphere is examined in a similar manner. The injection due to burnup on re-entry, or near-orbital abort, will actually be into the mesosphere, so the treatment overestimates the maximum ground deposition that will be produced.

b. Effect of burnup re-entry on inventory

It can be shown that for injection into the stratosphere, the following equations apply:

$$A_1 = A_0 e^{-(k_1 + \lambda)t}$$

$$A_2 = \frac{k_1 A_0}{k_2 - k_1} \left[e^{-(k_1 + \lambda)t} - e^{-(k_2 + \lambda)t} \right]$$

$$A_3 = \frac{A_0}{k_2 - k_1} \left[k_1 e^{-(k_2 + \lambda)t} - k_2 e^{-(k_1 + \lambda)t} + (k_2 - k_1) e^{-\lambda t} \right]$$

where:

A_0 = initial activity (curies)

A_1 = activity in stratosphere (curies)

A_2 = activity in troposphere (curies)

A_3 = activity on ground (curies)

k_1 = residence time constant for stratosphere (day^{-1})

k_2 = residence time constant for troposphere (day^{-1})

λ = radiological decay constant (day^{-1})

~~CONFIDENTIAL~~

MND-3393

0000000000

DECLASSIFIED

~~CONFIDENTIAL~~

Also

$$\frac{dA_2}{dt} = \frac{k_1 A_o}{k_2 - k_1} \left[(k_2 + \lambda) e^{-(k_2 + \lambda)t} - (k_1 + \lambda) e^{-(k_1 + \lambda)t} \right]$$

and

$$\frac{dA_3}{dt} = \frac{A_o}{k_1 - k_2} \left[k_1 (k_2 + \lambda) e^{-(k_2 + \lambda)t} - k_2 (k_1 + \lambda) e^{-(k_1 + \lambda)t} + (k_2 - k_1) \lambda e^{-\lambda t} \right]$$

The parameters used are:

$$A_o = 7.24 \times 10^5 \text{ curies}$$

$$k_1 = 0.95 \times 10^{-3} \text{ day}^{-1}$$

$$k_2 = 3.3 \times 10^{-2} \text{ day}^{-1}$$

$$\lambda = 6.85 \times 10^{-5} \text{ day}^{-1}$$

It is found that the maximum tropospheric burden is 2.26×10^4 curies, occurring at 110 days. The maximum ground deposition is 6.63×10^5 , occurring at 2870 days.

For injection of radioactivity into the upper atmosphere, the fallout is distributed fairly uniformly in the hemisphere of injection between the 20th and 70th parallels of latitude, as shown by Fig. VII-18, adapted from Refs. 40 and 41. The area of this zone is 5.4×10^{14} square meters. If it is assumed that at the time of maximum ground activity, 80% of it is deposited in this zone, the average ground concentration is 9.83×10^{-10} curie/m², equivalent to 2.55 mc/mi². This may be compared with the deposition in the northern hemisphere during 1962 due to bomb testing of 17 mc/mi² (Fig. VII-18).

The troposphere extends to a height of 10,700 meters (standard atmosphere). The volume of the zone between 20° and 70° latitude is, consequently, 5.78×10^{18} cubic meters. If it is assumed that 80% of the tropospheric inventory is uniformly distributed through this volume there is, at the time of maximum concentration, 3.12×10^{-15} curies/m³ (or μc/cc). This may be compared with the maximum permissible con-

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

0310587030

~~CONFIDENTIAL~~

VII-53

Fig. VII-18. Total Sr-90 Deposition During 1962 Versus Latitude Band

~~CONFIDENTIAL~~

MND-3393

03170281030

DECLASSIFIED

~~CONFIDENTIAL~~

centration for air (MPC_a) for nonoccupational workers for a 168-hour week. For strontium-90 in the soluble form, this is $10^{-10} \mu\text{c/cc}$; for the insoluble form, it is $2 \times 10^{-9} \mu\text{c/cc}$. These values are seen to exceed by several orders of magnitude the predicted tropospheric concentration derived from the burnup of a 250-watt RTG fuel load.

c. Orbital lifetime

The orbital lifetime of a satellite depends upon the altitude of perigee, the eccentricity of the orbit, and the $W/C_D A$ of the body. The satellite using the 250-watt generator has been assumed to be in orbit at about 10,000 nautical miles. The lifetime of a satellite in an orbit at this altitude will be measured in thousands of years. The re-entry after this time will be random, but probably some form of satellite scavenging will be in effect in that period. For a fuel load of strontium-90, the activity will have decreased by a factor of more than 1000 after 280 years. Consequently, re-entry after a truly long lived orbital residence presents no significant radiological hazard. The problem of atmospheric contamination by the 250-watt RTG arises only if there is a launch thrust or guidance failure which results in an immediate re-entry at near orbital velocity or in the achievement of only a short lived orbit. Short lived in this case should be interpreted as less than 300 years.

d. Burnup characteristic

In the preceding discussion, the term re-entry burnup has been assumed to mean that the radioactive fuel is subject to mechanical ablation and aerothermodynamic effects which reduce it above 100,000 feet altitude to molecular form or submicron particles as in the debris of nuclear bomb detonations. Aerothermodynamic studies under way indicate that this may not be possible and that the particulates from the so-called burnup may be in the range from 50 to 100 microns. If this is the case, the bomb fallout model would not be applicable. Particles in this size range would not become distributed worldwide but would fall at velocities that may be calculated with some assurance by the application of Newtonian dynamics, or Stoke's Law. Their trajectories would, however, be very complex depending on factors that include their size, density, altitude, velocity at time of formation and the wind velocities encountered. The area in which deposition would take place would be limited, but would be determined by these factors and the point of origin. This topic should be investigated.

e. Conclusions

It has been shown in the preceding discussion that in the burnup of the radioisotopic fuel load of a 250-watt RTG mission into molecular

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

03115047030
~~CONFIDENTIAL~~

VII-55

and submicron form would produce an increase in the atmospheric concentration that is insignificant compared to the MPC_a . It has also been pointed out that the problem does not arise for a successful 250-watt RTG mission, and the reliability of the launching system is high. It can be noted that if the 250-watt generator were to burn up in an early re-entry, the present atmospheric burden of strontium-90 (June 1, 1964) would be increased by 25%, but this would still be three or four orders of magnitude below the MPC_a .

D. REFERENCES

1. Smalley and Anderson, "The Explosive Potential of Liquid Oxygen and RP-1 Missiles," (STL), GM-TR-59-00579, January 30, 1959.
2. Telephone Conversation with Mr. Chris Saros, Cambridge Plant, Denver, Colorado, April 15, 1964.
3. "Launch Pad Abort Environmental Evaluation," MNSP-RE-1664, April 17, 1964.
4. "Nuclear Safety Test Report for the Space Version of the Present SNAP III Thermoelectric Generator," MND-P-2358, Martin-Nuclear.
5. "Safety Test Report for the SNAP 9A Thermoelectric Generator, Transit Mission," MND-P-2804, Martin-Nuclear.
6. "Analysis of Launch Facility Thermal Environment During a Pad Incident," DS-38-61, Martin Company.
7. "Titan II-1/2 Scale Tests Data," Martin Company, Denver Division.
8. Telephone Conversation with Mr. G. Manelis, Cambridge Plant, Denver, Colorado, June 1, 1964.
9. "SNAP 9A Radioisotope-Fueled Generator Final Safety Analysis for Transient Mission," MND-P-2775-R, Martin-Nuclear.
10. Oslake, J. J., et al., "Explosive Hazards of Rocket Launchings," Aeronutronic Division of Ford Motor Company, U-108-98, November 30, 1960.
11. Sallis, D. V. and Boogar, E. R., "Transient Heating Digital Analysis for Structural Design," RM-63, December 1960.

~~CONFIDENTIAL~~

MND-3398

031712241030

DECLASSIFIED
CONFIDENTIAL

12. "SNAP Programs--Upper Atmosphere Experience Re-entry Study Final Summary Report," Martin-Nuclear, April 1963.
13. "Titan II - Dyna-Soar Destruct Test and Analysis, Report, March 1962," ER 12269, Martin-Baltimore.
14. "Transient Heating of the Sr-90 Generators During the Ascent Phase," MNSP-VT-1589, Martin-Nuclear.
15. "Beryllium Safety Analysis on Surveyor Radioisotope Thermo-electric Generator," MNSP-EC-LH-1627, Martin-Nuclear.
16. "SNAP 9A Pu-238 Fueled Thermoelectric Power Supply for Auxiliary Space Power, Final Report, Vol. I and II," MND-P-3098, Martin-Nuclear.
17. Formulas for Stress and Strain, Roark
18. Heat Transmission, 3rd Edition, McAdams
19. "31st Inventory of Aerospace Power," Aviation Week, March 16, 1964.
20. Saelman, B. , "Design Equations and Charts for Pressurized Cylinders and Spheres," Lockheed Aircraft Corporation, Burbank, California.
21. Osmeyer, W. E. , "Strontium-90 Space Fuel Form Re-entry and Ablation Analysis," MNSP-WO-1703, Martin-Nuclear, 1964.
CONFIDENTIAL
22. Nelson, D. K. , "Behavior of SNAP 10A During Orbital Re-entry," 1964 AIAA Meeting, Washington, D.C.
23. "Trajectory and Heat Flux Computer Program UB003," Martin-Nuclear, 1964.
24. Sallis, D. V. and Boogar, E. R. , "Transient Heating Digital Analysis for Structural Heating," RM-63, Martin-Nuclear, 1963.
25. Cheng, H. K. , "The Blunt Body Problem in Hypersonic Flow at Low Reynolds Number," IAS Meeting, N. Y. , 1963.
26. McEwen, G. F. , Transactions of the American Geophysics Union, 31, pp 35 to 46, 1950.
27. Joseph, J. and Sender, H. , "Horizontal Diffusion in the Sea," Deutsche Hydrog Zeit 11, p 49, 1958.

CONFIDENTIAL

DECLASSIFIED
MND-3393

0315587030
~~CONFIDENTIAL~~

VII-57

28. "Radioactive Waste Disposal in the Sea," Report of ad hoc panel under the chairmanship of H. Brynielsson, International Atomic Energy Agency, February 1960.
29. Radioactive Waste Disposal into Atlantic and Gulf Coast Waters, Publication 655, National Academy of Sciences, National Research Council.
30. Munk, W. H., Ewing, G. C. and Revelle, R. R., "Diffusion in Bikini Lagoon," Transactions of the Amer Geophys Union, 30, p 59, 1949.
31. Boehmer, C., Riggs, C., Watcher, J. and Weiner, R., "Final Report; Nuclear Rocket Safety Study," MND-2517, Martin-Nuclear, August 1961. SRD
32. "RIFT Final Technical Summary Report, Vol. V, Nuclear Safety," NASA-CR-61-3, Martin Company, December 1961. CRD
33. Ophel, I. L., The Fate of Radiostrontium in a Freshwater Community, In Schultz, V., and Klement, A. W., Jr., Radioecology, Reinhold Publishing Company, New York, 1963.
34. Disposal of Low-Level Radioactive Waste into Pacific Coast Waters, National Academy of Sciences-National Research Council Publication 985.
35. Health and Safety Laboratory HASL-115, "Fallout Program--Quarterly Summary Report," October 1, 1961 (USAEC--New York Operations).
36. International Commission on Radiological Protection, Report of Committee II, 1959.
37. Burnett, T. J., "Reactors, Hazard Versus Power Level," Nuclear Science and Engineering, 2, pp 382 to 393, 1957.
38. Stebbins, A. K., "HASP Second Special Report on High Altitude Sampling Program," DASA 539B, August 1961.
39. "SNAP 9A Radioisotope-Fueled Generator; Final Safety Analysis for Transit Mission," MND-P-2775-2, Martin-Nuclear, March 1963. SECRET
40. Eisenbud, M., Environmental Radioactivity, McGraw-Hill, New York, 1963.
41. Health and Safety Laboratory HASL-104, "Fallout Program--Quarterly Summary Report," (USAEC--New York Operations).

CONFIDENTIAL

MND-3393

031712291030

DECLASSIFIED

VII-58

~~CONFIDENTIAL~~

BLANK

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

0115587030
~~CONFIDENTIAL~~

A-1

APPENDIX A

THERMOELECTRIC ANALYSIS

The thermoelectric analysis for the modules of the dynamic and static systems was performed by a digital program* developed by the Martin Company. The program input includes conversion material properties, element lengths, electrical contact resistivities, and hot and cold junction temperatures. The program output includes thermoelectric efficiency, number and size of elements for a desired electrical output power. The results are presented in Figs. A-1 through A-4 for various hot and cold junction temperatures and contact resistivities. For the dynamic system study, realistic contact resistivities were used (Fig. A-1), and an end-of-life hot junction temperature of 925° F (Fig. A-1) was used to give a reasonable beginning-of-life hot junction temperature of approximately 1015° F.

The thermoelectric materials properties were obtained from the SNAP 21A program for segmented couples and the SNAP 17A program for SiGe alloy couples. The properties used are those in effect on the two programs as of May 15, 1964.

The segmented couples associated with the modules of the dynamic system consist of variably doped lead tin telluride on the N leg and a lead telluride-bismuth telluride combination on the P leg. These materials are employed to maximize the efficiency obtained from each element by utilizing each material in its optimum temperature range. This range is determined from figure of merit versus temperature curves. (That temperature range for which each material has the highest figure of merit is optimum.) The segmented couple arrangement is shown in Fig. A-5. The temperatures at which the figures of merit intersect (T_M) were determined to be 495° and 455° F for N and P legs, respectively, as indicated in Figs. A-6 and A-7. The length of thermoelement material for each element was calculated from the relation:

$$\frac{\ell_2}{\ell_1} = \frac{k_2}{k_1} \frac{(T_M - T_C)}{(T_H - T_M)}$$

and

$$\ell_1 + \ell_2 = 0.5 \text{ inch}$$

*MND-P-2372, "Development of a Thermoelectric Optimization Code for the IBM 709," Martin Company.

~~CONFIDENTIAL~~

MND-3353

01172801030

DECLASSIFIED

A-2

~~CONFIDENTIAL~~

Fig. A-1. Thermoelectric Efficiencies for PbSnTe-BiSbTe Segmented Elements

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

Fig. A-3. Thermoelectric Efficiencies for PbSnTe-BiSbTe Segmented Elements

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

~~CONFIDENTIAL~~

0315587030

A-5

Fig. A-4. Silicon Germanium Alloy Thermoelectric Efficiency Versus Temperature

~~CONFIDENTIAL~~

MND-3893

0317228030

~~CONFIDENTIAL~~

Fig. A-5. Segmented Element Arrangement

where

T_C = cold junction temperature

T_M = intersection temperature

= 495° F for N element

= 455° F for P element

k_1 = average thermal conductivity of hot end material over temperature range, $T_H - T_M$

k_2 = average thermal conductivity of cold end material over temperature range, $T_M - T_C$

l_1 = segment length of hot end material

l_2 = segment length of cold end material

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

MIND-3393

CONFIDENTIAL

Fig. A-6. Figure of Merit--N Leg of Segmented Couple

CONFIDENTIAL

REF ID: A60760

~~CONFIDENTIAL~~

Fig. A-7. Figure of Merit--P Leg of Segmented Couple

~~CONFIDENTIAL~~

MND-3393

CONFIDENTIAL

B-1

APPENDIX B

DYNAMIC SYSTEM RADIATOR AREA AND TEMPERATURE PARAMETRIC STUDY

A parametric study of radiator temperatures and areas required to reject the waste heat in the dynamic system has been conducted. Variables were radiator temperature, radiator area, heat to be rejected, orbital altitude and vehicle position in the orbit. Average "temperatures of space" were calculated for the various orbits to obtain a typical set of design curves for the required radiator area.

To determine the required radiator size, it is necessary to find the effective sink temperature to which heat can be radiated. If it is assumed that the orbiting vehicle has no internal heat production, the surface equilibrium temperature will be the same as the sink temperature. In the following calculations the orbiting vehicle was assumed to be cylindrical, and the surface equilibrium temperature was determined at four positions on the surface at 90-degree angular intervals. This was accomplished by the relationship* for the vehicle at a given orbital altitude and location with respect to the sun and earth.

$$T_S = \left\{ \frac{1}{\sigma} \left[\frac{\alpha}{\epsilon} S F_S + \frac{\alpha}{\epsilon} A S F_{E(SR)} + \frac{(1 - A)}{4} S F_{ET} \right] \right\}^{1/4}$$

where

- T_S = temperature of surface ($^{\circ}R$)
- F_S = solar view factor
- $F_{E(SR)}$ = albedo view factor
- F_{ET} = earth thermal radiation view factor
- S = solar constant (443 Btu/hr-ft²)
- A = earth nominal albedo (0.35)
- α = absorptivity of radiator (0.16)
- ϵ = emissivity of radiator (0.9)
- σ = constant (0.1714×10^{-8} Btu/hr-ft²- $^{\circ}R^4$).

*Publication MS-AP-0069, "Radiator Design for Space Vehicles," The Garrett Corporation, AiResearch Manufacturing Company, Los Angeles, California, 1963.

CONFIDENTIAL

MND-3393

DECLASSIFIED

~~CONFIDENTIAL~~

The values for $F_{E(SR)}$, F_S and F_{ET} were determined from MS-AP-0069. These surface temperatures were averaged to determine the effective surface temperature and, hence, the effective sink temperature at a given orbital altitude and position.

The vehicle orbits were taken as polar and circular. Figure B-1 illustrates two views of a typical circular, polar orbit showing four orbital positions. As shown, the axis of the cylinder was always taken as parallel to the earth surface. For each of these positions, the effective surface temperature was determined. These temperatures were averaged to obtain an effective sink temperature for a given altitude. This was done at altitudes of 100, 1000, 10,000 and 20,000 nautical miles above the earth surface. Effective sink temperatures were -123° , -146° , -227° and -267° F, respectively (Table B-1).

TABLE B-1
Effective Sink Temperature

<u>Altitude</u> <u>(naut mi)</u>	<u>Position Temperature</u> <u>(°R)</u>				<u>Average</u> <u>Temperature</u>	
	<u>No. 1</u>	<u>No. 2</u>	<u>No. 3</u>	<u>No. 4</u>	<u>(°R)</u>	<u>(°F)</u>
100	322	421	322	286	337	-123
1,000	286	383	286	299	314	-146
10,000	200	296	200	237	233	-227
20,000	157	251	157	206	193	-267

The area of the radiator was determined from:

$$q = \sigma \epsilon \eta A (T_R^4 - T_S^4)$$

where

q = total heat rejected by surface (Btu/hr)

A = radiator area (feet²)

T_R = radiator temperature (°R)

T_S = sink temperature (°R)

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

CONFIDENTIAL

B-3

ϵ = emissivity (0.9)

σ = constant (0.1714×10^{-8} Btu/hr-ft²-°R⁴)

η = radiator fin efficiency (0.9).

The effect of orbital altitude on the radiator area is shown in Table B-2. As the altitude increases from 100 to 1000 nautical miles, the required radiator area decreases between 0.9 to 2.6%, depending upon the radiator surface temperature. As altitude increases from 1000 to 20,000 nautical miles, the decrease in area is between 2.9 to 6.0%.

TABLE B-2
Effect of Orbit Altitude on Radiator Area

<u>T_R</u> (°F)	<u>q</u> (kw)	<u>Orbital Altitude</u> (naut mi)	<u>Area</u> (ft ²)	<u>Differences</u> (%)
150	2	100	37.2	2.6
		1,000	36.3	0
		20,000	34.1	-6.0
300	6	100	43.7	0.9
		1,000	43.3	0
		20,000	42.1	-2.9

Plots of required area versus radiator temperature were then calculated (with heat rejected as a parameter) from the previous expression for heat rejected as a function of area, radiator temperature and sink temperature. The results for a 10,000-nautical mile orbit are presented in Fig. III-25.

CONFIDENTIAL

MND-3393

DECLASSIFIED

B-4

~~CONFIDENTIAL~~

Fig. B-1. Two Views of Circular Polar Orbit

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

0315507030

C-1

APPENDIX C

RADIATOR PARAMETRIC STUDY COOLANT COMPARISON

A. GENERAL

The coolants Oronite-8515, Coolanol-45, Coolanol-35, Dowtherm-A, Dowtherm-E, Freon-21, FC-75, OS-59, and water were investigated for possible use in the dynamic radiator concept. The bases of the investigation were nuclear radiation stability of the properties (viscosity, thermal conductivity, vapor pressure, density and gas products) and heat transfer characteristics of the various coolants. The coolants are for use at a maximum temperature of 300° F and a dose of 7×10^7 rads (H_2O), * and are considered unsuitable for use if any of the above properties are changed by 10%.

B. COOLANT NUCLEAR RADIATION STABILITY

The results of the investigation are summarized below:

- (1) Oronite-8515 has less than a 10% viscosity change at 1.3×10^7 rads (H_2O) and a 10% density change of 3×10^7 rads (H_2O); therefore, it is considered unacceptable for a dose of 7×10^7 rads (H_2O).
- (2) FC-75 is acceptable for a dose of 7×10^7 rads (H_2O).
- (3) Coolanol-35, Coolanol-45, and OS-59 show large changes in physical properties above 10^7 rads (H_2O), are considered to have excessive chemical reactivity at approximately 10^8 rad (H_2O), measured gas evolution above 10^7 rad (H_2O), and are considered unsatisfactory for a dose at 7×10^7 rads (H_2O).
- (4) Dowtherm-A is considered acceptable for a dose of 7×10^7 rads (H_2O).

* 7×10^7 rads (H_2O) defines a radiation field in which H_2O will absorb 7×10^7 rads in five years.

~~CONFIDENTIAL~~

MND-3393

031712201030

DECLASSIFIED

~~CONFIDENTIAL~~

Fig. C-1. Module Coolant Chamber

DECLASSIFIED
CONFIDENTIAL
MND-3393

- (5) Dowtherm-E has a 10% viscosity change at about 2×10^7 rads (H_2O) and is considered unacceptable for a dose of 7×10^7 rads (H_2O).
- (6) Freon-21 is marginal and its acceptability for a dose of 7×10^7 rads (H_2O) would have to be verified experimentally.
- (7) Water was considered a problem at 7×10^7 rads (H_2O) if there were evidence of an ozone release caused by ionizing radiation. No experimental evidence was found to indicate that ozone release is a limiting factor related to its use in a cooling system; therefore, from a nuclear radiation viewpoint, water is a suitable coolant.

C. COOLANT HEAT TRANSFER CHARACTERISTICS

The waste heat from the thermoelectric system is transferred from the module cold junction to the radiator by the coolant. This heat is initially accumulated by the coolant in the module coolant chamber as shown in Fig. C-1.

Coolant heat transfer characteristics were investigated determining the difference between the diaphragm surface and bulk fluid temperatures, $T_{\text{bulk}} - T_{\text{diaphragm}}$, for the various coolants. The smaller the temperature difference, the better the coolant heat transfer characteristics. The heat transfer correlation (Ref. Appendix B) used in this investigation is as follows:

$$T_{\text{bulk}} - T_{\text{diaphragm}} = \frac{27.0 M_F^{0.467} A_F^{0.8} \ell q}{K_F^{0.667} C_{P_F}^{0.333} A_w^{0.8}}$$

where

M = dynamic viscosity

A_F = 0.03 foot^2 = cross-sectional area of the module coolant chamber perpendicular to the direction of flow

ℓ = 0.79 foot = length of module coolant chamber in direction of flow

~~CONFIDENTIAL~~

q = 200 watts = heat transferred by coolant

K = thermal conductivity

C_p = heat capacity

A = 1.123 feet² = cross-sectional area of diaphragm

w = 1500 Btu/hr = flow rate of coolant through module coolant chamber.

Typical coolant flow rate, w , and waste heat, q , values are held constant throughout the investigation to enable the heat transfer characteristics of each coolant to be compared on the basis of their properties only. All coolant properties are evaluated at a typical, average film temperature, $1/2 (T_{\text{diaphragm}} - T_{\text{bulk}})$ of 200° F and are presented in

Table C-1. Properties for coolants Oronite-8515 and Dowtherm-E are unavailable and, consequently, are not considered. The results of using the properties from Table C-1 in the preceding equation for the various coolants are presented in Table C-2.

TABLE C-1

Coolant Thermodynamic Properties at 200° F

<u>Coolant</u>	<u>Heat Capacity (Btu/lb-° F)</u>	<u>Dynamic Viscosity (lb/ft-hr)</u>	<u>Thermal Conductivity (Btu/hr-ft-° F)</u>
Water	1.005	0.72	0.394
Freon-21	0.265	0.60	0.055
FC-75	0.278	1.40	0.035
OS-59	0.523	4.65	0.074
Coolanol-45	0.510	8.30	0.076
Coolanol-35	0.520	4.60	0.073
Dowtherm-A	0.450	2.42	0.070

TABLE C-2

Difference Between the Diaphragm and Bulk Fluid
Temperature for Various Coolants

<u>Coolant</u>	<u>$T_{\text{diaphragm}} - T_{\text{bulk}}$ (°F)</u>
Water	43
Freon-21	225
Coolanol-35	256
Dowtherm-A	309
OS-59	383
FC-75	432
Coolanol-45	502

~~CONFIDENTIAL~~

DECLASSIFIED MND-3393

091507030
~~CONFIDENTIAL~~

C-5

D. CONCLUSIONS

From a nuclear radiation stability viewpoint, water, FC-75 and Dowtherm-A are all considered acceptable for use as coolants. However, it is evident from Table C-2 that water possesses the best heat transfer characteristics and, therefore, will be used as the coolant in the dynamic system. The incompatibility of water with the aluminum tubing of the radiator for a five-year period is a possible problem. This is alleviated by lining the aluminum tubing with stainless steel which has a high corrosion resistance to water.

CONFIDENTIAL

MND-3393

091228030

C-6

DECLASSIFIED

~~CONFIDENTIAL~~

BLANK

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

APPENDIX D

COOLANT SYSTEM PARAMETRIC STUDY

A. SYSTEM DESCRIPTION

The basic cooling system consists of a cooling channel around the cold junction of the thermoelectric module, a circulating pump and a space radiator (Fig. D-1). Previous studies (Appendix C) indicate water to be the most efficient coolant. The wall construction of the generator between the cold junction and the coolant is shown in Fig. D-2. Basic terminology used in this appendix may be found in Table D-1.

The basic construction of the radiator consists of "D" tubes brazed around the circumference of the vehicle skin. A typical cross section of a "D" tube is shown in Fig. D-3. Its wall thickness of 0.010-inch stainless steel with 0.010-inch aluminum on the outside was held constant for this study. The tube diameter, d_o , was varied to determine the optimum or near optimum system weight. The tube spacing, $2L_F$, and the number of tubes were determined based on the required radiator surface area.

B. ANALYTICAL PROCEDURE

The basic approach in determining the optimum tube diameter and flow rate was to investigate the fuel thermal inventory as a function of flow rate and radiator tube diameter. The optimum flow which minimizes the thermal inventory can be determined by examining the behavior of the system. For example, the thermal inventory is dependent on the cold junction temperature (for a constant hot junction temperature, taken to be 925° F) and pumping power. These, in turn, are dependent on the flow rate. For a fixed heat rejection temperature, T_R , the cold junction temperature decreases as the flow rate increases. This results in an increased thermoelectric efficiency and, hence, a decrease in fuel thermal inventory. However, at some flow rate, the pumping power begins to become significant and the thermal inventory goes through a minimum value after which it increases rapidly as the flow rate increases. This minimum point was determined for a range of "D" tube diameters from 0.375 to 0.75 inch. Utilizing the minimum thermal inventory corresponding to an optimum flow rate for each diameter, the fuel block weight was calculated assuming a constant power density. To this was added the tube weight including meteoroid bumper and the contained water coolant. Finally, a system weight composed

DECLASSIFIED

D-2

~~CONFIDENTIAL~~

Fig. D-1. Basic Cooling System

Fig. D-2. Generator Wall Construction

Fig. D-3. Cross Section of D Tube

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

TABLE D-1
Nomenclature

ΔP	= system pressure drop
k_f	= $4f \frac{L_R}{d_e}$ = resistance factor for losses in radiator tubes
f	= fanning friction factor
L_R	= radiator tube length = 14 feet
d_e	= "D" tube effective hydraulic diameter
g_c	= gravitational constant
w	= coolant flow rate
ρ	= coolant density
A_{CR}	= tube cross-sectional area
k_m	= resistance factor for losses in the distribution headers from expansion, contraction and turning
R_i	= internal radius and "D" tubes
P_{pump}	= pumping power
η_p	= pump efficiency
η_m	= motor efficiency
T_C	= cold junction temperature
T_R	= radiator fin root temperature = 180° F
T_D	= diaphragm surface temperature
ΔT_a	= temperature drop between cold junction and diaphragm surface
Q_c	= heat transferred by coolant
ΔX_i	= thickness of cold junction (Al_2O_3 and Al_2O_3) diaphragm interfaces
K_A	= argon thermal conductivity
A_C	= cross-sectional area of thermoelements
A_D	= diaphragm surface area
T_B	= coolant bulk fluid temperature
ΔT_b	= temperature drop across coolant boundary layer in module coolant chamber
h_B	= diaphragm surface coefficient of heat transfer
k	= coolant thermal conductivity

DECLASSIFIED

~~CONFIDENTIAL~~TABLE D-1 (continued)

C_p	= coolant heat capacity
μ	= coolant dynamic viscosity
ℓ	= length of module coolant chamber
A_f	= module coolant chamber cross-sectional area perpendicular to the directional flow
h_c	= "D" tube surface coefficient of heat transfer
A_{RT}	= radiator tube cross-sectional area
A_T	= radiator tubes inside surface area
ΔX_{AL}	= thickness of aluminum casing
K_{AL}	= thermal conductivity of aluminum
A_{AL}	= cross-sectional area of aluminum casing
ΔX_{SS}	= thickness of stainless steel casing
K_{SS}	= thermal conductivity of stainless steel
A_{SS}	= cross-sectional area of stainless steel casing
η_c	= converter efficiency
η_I	= inverter efficiency
$\eta_{T/E}$	= thermoelectric efficiency
K_I	= module insulation thermal conductivity
A_I	= module insulation cross-sectional area
ℓ_I	= module insulation thickness
T_H	= hot junction temperature = 925° F
η_T	= system thermal efficiency
S	= radiator surface area
η_o	= radiator surface effectiveness
ϵ_T	= radiator surface emissivity
σ	= Stefan-Boltzmann constant
T_S	= effective sink temperature (Ref. Appendix B)
n	= number of tubes
R_o	= outside radius of "D" tubes (Ref. Appendix D, Fig. D-3)
L_F	= half center-to-center distance between tubes
η_F	= radiator tube fin efficiency
K	= radiator material thermal conductivity (aluminum)
δ	= radiator skin thickness = 0.05 inch

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

0315587030
~~CONFIDENTIAL~~

D-5

of these items was plotted versus diameter as shown in Fig. III-27. By cross plotting, a plot of weight versus thermal inventory was developed as shown in Fig. III-28. Thus, the tradeoff between these parameters can be evaluated.

C. PUMPING POWER

The total system pressure drop consists of the drop in the module coolant chambers, the radiator distribution headers and tubes, and the interconnecting piping. Preliminary calculations indicated that for the module coolant chamber width of 0.25 inch, the pressure drop for flows up to 8000 lb/hr is negligible (< 0.01 psi). This is also true of the interconnecting piping because of its short length. The system pressure drop was therefore computed using the following equation for the radiator:

$$\Delta P = \frac{k_f}{2g_c} \left(\frac{W^2}{\rho A_{CR}^2} \right) + \frac{k_m}{2g_c} \left(\frac{W^2}{\rho A_{CR}^2} \right)$$

A conservative estimate of k_m is 3. This was determined by assuming that the coolant travels through two 90-degree turns, one contraction and one expansion. For each turn, normal practice is to set $k = 0.82$ (Ref. 1, p 27). For a sharp-corner contraction, $k = 0.50$, and a sharp-corner expansion, $k = 1.00$ (Ref. 2). No pressure recovery was considered. This k_m of 3 ($\sum k_i$) appears to be realistic for a distribution header large enough to limit the velocity to about 1 fps.

The hydraulic diameter for the "D" tubes was computed from

$$d_e = \frac{2\pi R_i}{\pi + 1}$$

The pumping power to be supplied by the thermoelectric module was computed from

$$P_{\text{pump}} = \frac{W \Delta P}{\eta_p \eta_m}$$

where η_p (pump efficiency) was assumed to be 90%. The motor efficiency was assumed to be 60%.

A plot of pumping power as a function of tube diameter and flow rate is shown in Fig. D-4. The tube length, L_R , was held constant at

CONFIDENTIAL

MND-3393

0315587030

~~CONFIDENTIAL~~

14 feet (approximately 90% of vehicle circumference). Utilizing approximately all of the vehicle circumference minimizes the radiator length and the number of radiator tubes.

D. OPTIMIZATION OF THERMAL INVENTORY, WEIGHT, AND RADIATOR TUBE DIAMETER AND FLOW RATE

The thermal inventory depends on the difference between the cold junction temperature, T_C , and the radiator fin root temperature, T_R . There exist three primary temperature gradients between these points. These are computed as follows:

- (1) Temperature drop between the cold junction and module diaphragm. This drop is due to the contact resistance of the cold junction (Al_2O_3 and Al_2O_3) diaphragm interfaces. For lack of data on the interface conductances, the interface gaps (filled with argon) were each assumed to be 250 microinches thick (surface finish of 125 microinches on each material); therefore,

$$\Delta T_a = T_C - T_D = \frac{Q_c \Delta X_i}{k_A} \left(\frac{1}{A_c} + \frac{1}{A_D} \right)$$

- (2) Temperature drop across the module coolant chamber film. The average temperature drop across the coolant boundary layer was computed from

$$\Delta T_b = T_D - T_B = \frac{Q_c}{h_B A_D}$$

where

$$h_B = \frac{0.037 k^{0.667} C^{0.333} p}{M^{0.467} \ell^{0.2}} \left(\frac{W}{A_f} \right)^{0.8}$$

This correlation for h_B (Ref. 3, p 170) applies to turbulent flow over a flat plate. It was used in preference to the Dittus-Boelter correlation since the latter applies only to fully developed flow. Since the coolant chamber length is only 9.375 inches, the flow will not be fully developed over a major portion of the length. The correlation of h_B is an integrated average which includes the boundary layer growth from inlet to length, ℓ .

~~CONFIDENTIAL~~

DECLASSIFIED MND-3393

0315587030
~~CONFIDENTIAL~~

D-7

- (3) Temperature drop between coolant and fin root temperature, T_R . The average temperature drop across the radiator tube boundary layer and tube wall was computed from

$$\Delta T_C = T_B - T_R = Q_C \left(\frac{1}{h_c A_T} + \frac{A X_{AL}}{k_{AL} A_{AL}} + \frac{\Delta X_{SS}}{k_{SS} A_{SS}} \right)$$

where

$$h_c = 0.023 \left(\frac{w}{A_{RT}} \frac{d_e}{M} \right)^{0.8} \left(\frac{\mu \text{ cp}}{k} \right)^{0.4}$$

The total temperature drop between the cold junction, T_C , and radiator fin root, T_R , is therefore $\Delta T_a + \Delta T_b + \Delta T_c$; therefore,

$$T_C - T_R = Q_c \left[\frac{\Delta X_i}{k_A A_c} + \frac{\Delta X_i}{k_A A_D} + \frac{1}{h_B A_D} + \frac{1}{h_c A_T} + \frac{\Delta X_{AL}}{k_{AL} A_{AL}} + \frac{\Delta X_{SS}}{k_{SS} A_{SS}} \right] \quad (1)$$

The quantity of heat, Q_C , which must be removed by the coolant is the heat through the thermoelements and module insulation minus the power produced by the elements. This is a function of the pumping power, thermoelectric efficiency and cold junction temperature; therefore,

$$Q_C = \frac{1}{\eta_{T/E}} \left[\frac{250w}{\eta_c} + \frac{10w}{\eta_I} + \frac{P_{\text{pump}}}{\eta_I} \right] + \frac{k_I A_I (T_H - T_C)}{\ell_I} - \left[\frac{250w}{\eta_c} + \frac{10w}{\eta_I} + \frac{P_{\text{pump}}}{\eta_I} \right] \quad (2)$$

The variation of $\eta_{T/E}$ with T_C is given in Appendix A, Fig. A-2. Thus, for a fixed value of T_R and tube diameter, it is possible to determine values of w , T_C , Q_C and P_{pump} which satisfy Eqs (1) and (2), Fig. D-4 and the thermoelectric efficiency data from Appendix A. This was done by an iteration technique for various values of tube diameter. The total heat required (thermal inventory) was then computed from

~~CONFIDENTIAL~~

MND-3393

03170291030

DECLASSIFIED

D-8

~~CONFIDENTIAL~~

Fig. D-4. Pumping Power versus System Flow

~~CONFIDENTIAL~~

DECLASSIFIED

MMD-3393

0315587030
~~CONFIDENTIAL~~

D-9

$$Q_{\text{total}} = \frac{1}{\eta_T \eta_{T/E}} \left[\frac{250w}{\eta_c} + \frac{10w}{\eta_I} + \frac{P_{\text{pump}}}{\eta_I} \right]$$

The resulting plot of thermal inventory as a function of flow rate for various tube diameters is shown in Fig. III-26. This plot indicates the optimum flow rate (that which gives the minimum thermal inventory) for each tube diameter.

The value of T_R was selected at 180° F as the minimum surface temperature which effectively utilizes the vehicle skin as a radiating surface. Preliminary calculations indicated that a surface effectiveness of 95% could be achieved by seven rows of tubes running over approximately 90% of the vehicle circumference. The characteristics of the radiator surface for each tube diameter investigated were then determined as follows:

The value of Q_c at the optimum flow rate for each tube diameter was determined as previously described. A surface effectiveness of η_o was then assumed and the surface area was computed from

$$S = \frac{Q_c}{\eta_o \epsilon_r (T_R^4 - T_S^4)}$$

The fin length was then calculated from

$$S = 2n (L_f + R_o) L_R$$

or

$$L_F = \frac{S}{2nL_R} - R_o$$

Utilizing this value of L_F , the fin efficiency, η_F , was computed from Ref. 4, Fig. 2-12, for

$$\lambda = \frac{\sigma \epsilon_T L_F^2 R_R^3}{k \delta}$$

where

k = radiator material thermal conductivity (aluminum)

δ = radiator skin thickness (0.05 inch).

~~CONFIDENTIAL~~

MND-3395

0317281030

DECLASSIFIED
~~CONFIDENTIAL~~

Having obtained η_F , the surface effectiveness was computed from

$$\eta_o = \frac{\eta_F L_F R_o}{L_F + R_o}$$

The resulting value of η_o was then compared with the assumed value. The process was repeated until η_o was matched. Typical results obtained for 0.5-inch diameter tube are as follows:

$$Q_c = 3215 \text{ watts}$$

$$\eta_o = 95\%$$

$$S = 45.4 \text{ feet}^2$$

$$L_F = 2.53 \text{ inches}$$

$$\eta = 7$$

$$T_R = 180^\circ \text{ F}$$

$$\eta_F = 95\%$$

E. RESULTS

Figure III-26 shows the variation of thermal inventory as a function of flow rate and tube diameter. In the range of flows up to about 1000 lb/hr, the pumping power is insignificant for diameters greater than 0.375 inch. In this flow range, the thermal inventory is dependent on the temperature difference between the cold junction and radiator which decreases as the flow increases. The decreasing temperature difference results in an increasing thermoelectric efficiency (for a constant hot junction temperature) and, hence, decreasing thermal inventory. As the flow increases further, the pumping power becomes significant until finally it is controlling, and the thermal inventory increases rapidly. It is evident from Fig. III-26 that, for a given tube diameter, the thermal inventory is very sensitive to flow rate. Because of the effect of thermal inventory on fuel and fuel capsule weight, it is apparent that generator weight will be minimum for the minimum thermal inventory requirement.

The tradeoff between thermal inventory and system weight as a function of tube size was investigated. The system weight consisted of the weight of the tube, meteoroid bumper, fuel (including capsule) and coolant. Assuming a constant fuel-capsule weight density, ρ , the fuel weight was determined from

$$W_{\text{fuel}} = \rho (Q_{\text{inventory}})_{\text{min}}$$

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

where $(Q_{\text{inventory}})_{\text{min}}$ is the minimum thermal inventory for the various diameters obtained from Fig. III-26.

A summary of system weights is shown in Fig. III-28, corresponding to an optimized flow rate. It is evident that the changes in system weight (69 to 75 pounds) and thermal inventory (4200 to 3900 watts) are not relatively large (<10%) for the range of "D" tube sizes considered. However, this is true only for an optimized flow rate for each tube size. For other than an optimized flow rate, the changes in these parameters are very sensitive to flow rate as indicated in Fig. III-26. Since the system parameters are relatively insensitive to "D" tube diameters for optimized flow rates, any value within the range considered could be used as a reasonable design point. Based on that evaluation, a typical "D" tube diameter of 0.5 inch was selected as the design point. The system parameters for this tube size are given in Table D-2.

TABLE D-2
System Design Point Parameters

	<u>0.5-Inch "D" Tube</u>
Thermal inventory (end of life) (watts)	3980
Net power output (watts)	250
Weight (pounds)	
Tubes	5.62
Bumper	1.20
Coolant	3.54
Fuel--capsules	<u>59.20</u>
Total	69.54
Optimum flow rate (lb/hr)	3000
Pumping power (watts)	7
Control system power (watts)	10
Cold junction temperature (° F)	240
Thermoelectric efficiency (%)	8.9
Number of radiator tubes	7
Length of radiator tubes (feet)	14
Radiator surface area (feet ²)	45.4
Tube spacing (inches)	5.56
Radiator fin root temperature (° F)	180

DECLASSIFIED

~~CONFIDENTIAL~~TABLE D-2 (continued)

	<u>0.5-Inch "D" Tube</u>
Radiator surface effectiveness (%)	95
Heat rejected at radiator (watts)	3215
Generator thermal efficiency (%)	83

F. REFERENCES

1. WAPD-217, "The Calculation of Pressure Drop and Flow Distribution within a Reactor Vessel in a Pressurized Water Nuclear Reactor System," August 1959.
2. Crane Technical Paper No. 410, "Flow of Fluids through Valves, Fittings, and Pipes," PGA-26.
3. Giedt, "Principles of Engineering Heat Transfer," Van Nostrand, 1958.
4. MS-AP-0069, "Radiator Design for Space Vehicles," Garrett Corporation--AiResearch Company, Los Angeles, California.

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

03 JUL 1930
~~CONFIDENTIAL~~

E-1

APPENDIX E

DYNAMIC SYSTEM RADIATOR ARMOR REQUIREMENTS

A stainless steel lined aluminum tube was selected for the dynamic system radiator. The composite tube consists of a 10-mil stainless steel tube with a 10-mil thickness of aluminum extruded onto it. Between the tube and space is the vehicle skin which was assumed to be 50 mils thick. Additional armor is provided by a strip of aluminum on the outside of the vehicle skin.

The probability of success was calculated for several armor thicknesses and for tube diameters used in the cooling system optimization study.

As given in Ref. E-1, the expression for the probability of no penetration of meteoroids through a given thickness of metal in space is

$$P_s = \left[\frac{1}{e} \right]^T \alpha A(\psi)^{3\beta} (t)^{-3\beta} F$$

where:

P_s = probability of no penetrations or probability of success

T = length of time exposed

A = area exposed to meteorite bombardment

t = thickness of metal (or depth of penetration)

α = meteoroid influx rate

ψ = a constant dependent on properties of the meteoroids, the target metal and the directional distribution of the meteoroids.

β = a constant related to the meteoroid influx distribution.

F = a correction factor for oblique incidence.

In Refs. E-2 and E-3, ψ is given as

$$\psi = \frac{a\gamma}{2.54} \left(\frac{6}{\pi} \right)^{1/3} (\rho_p)^{-1/3} \left(\frac{62.4 \rho_p}{\rho_t} \right)^\phi \left(\frac{\bar{v}}{C} \right)^\theta$$

~~CONFIDENTIAL~~

MND-3393

03 JUL 1930

~~CONFIDENTIAL~~
DECLASSIFIED

and from the expression for P_s , the thickness, t , required for a given probability of success is

$$t = \frac{a\gamma}{2.54} \left(\frac{6}{\pi}\right)^{1/3} (\rho_p)^{-1/3} \left(\frac{62.4 \rho_p}{\rho_t}\right)^\phi \left(\frac{\bar{V}}{c}\right)^\theta \left[\frac{\alpha AT}{-\ln P_s}\right]^{1/3\beta} \left[\frac{2}{3n\theta\beta+2}\right]^{1/3\beta}$$

where:

t = required single material armor thickness (in.)

a = thin plate and spall adjustment

γ = 2, an experimental constant

ρ_p = meteoroid particle density (0.44 gm/cm³)

ρ_t = target material density (lb/ft³)

ϕ = 1/2, an experimental constant

$\bar{V}$ = average meteoroid velocity (98,400 fps)

c = speed of sound in target material

$$= 12 \sqrt{\frac{E_t g}{\rho_t}}$$

E_t = Young's modulus at target temperature (lb/in.²)

g = 32.2 fps²

θ = 2/3

α = 2.66×10^{-11}

β = 1.34

} constants for meteoroid flux distribution suggested by NASA as latest values, December 1963

A = exposed target surface (ft²)

T = mission time (days)

P_s = probability of no penetration of metal of thickness t

n = 1, for isotropic flux distribution where oblique penetrations are dependent on the normal component of velocity.

~~CONFIDENTIAL~~

DECLASSIFIED MFD-3393

011507030
~~CONFIDENTIAL~~

E-3

The final term, $F = \left[\frac{2}{3n\theta\beta + 2} \right]$, is a correction factor to change oblique incidence in isotropic flux distributions to effective normal incidence.

By appropriate rearrangement and insertion of the suggested values, the expression for thickness can be written as a function of vehicle and mission quantities alone:

$$t = (\text{constant}) \left[E_t^2 \rho_t \right]^{-1/6} \left[\frac{AT}{-\ln P_s} \right]^{1/4}$$

where the constant is

$$C = \alpha^{1/4} g^{-1/3} (12)^{-2/3} \left[\frac{a\gamma}{2.54} \left(\frac{6}{\pi} \right)^{1/3} (\rho_p)^{-1/3} (62.4 \rho_p)^{1/2} (\bar{V})^{2/3} \right] \\ \cdot \left[\frac{2}{3n\theta\beta + 2} \right]^{1/4} \\ C = 2.6$$

Therefore,

$$t = 2.6 \left[E_t^2 \rho_t \right]^{-1/6} \left[\frac{AT}{-\ln P_s} \right]^{1/4}$$

and, solving for P_s ,

$$P_s = \exp \left[\frac{-(2.6)^4 \left[E_t^2 \rho_t \right]^{-2/3} AT}{t^4} \right]$$

The probability of success has been calculated using the vehicle skin, the tube wall and additional armor for the conditions presented in Table E-1.

Because the probabilities of a meteoroid penetrating the aluminum and of penetrating the steel are dependent in a complex manner, weighted averages for the composite thickness were utilized with the single material equations previously presented. The expression for the average Young's modulus and density are as follows:

~~CONFIDENTIAL~~

MND-3393

011507030

~~CONFIDENTIAL~~

- (1) For 0 in armor thickness

$$\bar{E} = \frac{6 E_{Al} + E_{ss}}{7}$$

$$\bar{\rho} = \frac{6 \rho_{Al} + \rho_{ss}}{7}$$

- (2) For 25 mils of aluminum armor

$$\bar{E} = \frac{8.5 E_{Al} + E_{ss}}{9.5}$$

$$\bar{\rho} = \frac{8.5 \rho_{Al} + \rho_{ss}}{9.5}$$

- (3) For 50 mils of aluminum armor

$$\bar{E} = \frac{11 E_{Al} + E_{ss}}{12}$$

$$\bar{\rho} = \frac{11 \rho_{Al} + \rho_{ss}}{12}$$

For all calculations, the following values of E and ρ were used

$$E_{Al} = 10 \times 10^6 \text{ lb/in.}^2 \text{ (6061 aluminum)}$$

$$\rho_{Al} = 0.1 \text{ lb/in.}^3$$

$$E_{ss} = 28 \times 10^6 \text{ lb/in.}^2 \text{ (316 stainless steel)}$$

$$\rho_{ss} = 0.29 \text{ lb/in.}^3$$

The results of the calculations are presented in Table E-2.

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

0315587030
~~CONFIDENTIAL~~

E-5

TABLE E-1
Radiator Tube Armor Parameters

<u>Aarmor Thickness (in.)</u>	<u>Total Thickness</u>		<u>Tube Diameter (in.)</u>	<u>Area to be Protected (ft²)</u>
	<u>Steel (in.)</u>	<u>Aluminum (in.)</u>		
0	0.010	0.060	0.375	3.06
0.025	0.010	0.085	0.500	4.08
0.050	0.010	0.110	0.625	5.11

NOTE:

Number of tubes = 7

Length of each tube = 14 feet.

TABLE E-2
Probability of Success as a Function
of Radiator Tube Diameter and Armor Thickness

<u>Tube Diameter (in.)</u>	<u>Probability of Success</u>			
	<u>0*</u>	<u>0.010*</u>	<u>0.025*</u>	<u>0.050*</u>
0.375	0.909	0.943	0.967	0.987
0.500	0.882	0.925	0.956	0.982
0.625	0.853	0.907	0.946	0.978

*Armor thickness in inches.

REFERENCES

- E-1. Publication MS-AP-0069, "Radiator Design for Space Vehicles," AiResearch Manufacturing Company.
- E-2. Loeffler, I. J., Liblein, S. and Clough, N., "Meteoroid Protection for Space Radiators," ARS Space Power Systems Conference, Paper No. 2543-62, September 25 through 28, 1962.
- E-3. Loeffler, I. J., "Meteoroid Protection for Space Vehicles," Lecture No. 10 NASA, Lewis Advanced Study Program, 1962 to 1963.

~~CONFIDENTIAL~~

MND-3393

0317281030

E-6

DECLASSIFIED

~~CONFIDENTIAL~~

BLANK

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

CONFIDENTIAL

F-1

APPENDIX F

DYNAMIC SYSTEM TEMPERATURE DISTRIBUTION AND THERMAL LOSS

A. DYNAMIC SYSTEM TEMPERATURE DISTRIBUTION

The design point for this system is the end of a five-year mission, and the system is optimized for this condition. The complete design point temperature distribution has been determined. For the beginning of life, only the hot side temperature distribution was determined to verify that material (thermoelectric elements, fuel and capsules) temperature limitations were not exceeded.

The method of determining each temperature at its respective position is detailed in the following paragraphs.

1. Radiator Fin Root Temperature (design point)

The value of radiator fin root temperature was selected at 180° F as the minimum which effectively utilizes the vehicle skin as a radiating surface (Ref. Appendix D).

2. Coolant Bulk Fluid Temperature (design point)

The temperature drop from the radiator fin root to the coolant, ΔT_c , is composed of the drops across the aluminum and stainless steel casings of the tubes and the coolant film within the tubes. This total temperature drop is given by

$$\Delta T_c = Q_c \left[\frac{1}{h_c (w) A_t} + \frac{\Delta X_{Al}}{k_{Al} A_{Al}} + \frac{\Delta X_{ss}}{k_{ss} A_{ss}} \right]$$

and is negligible for a nominal design value of $Q_c = 3215$ watts and 10.5-inch tubes with an optimized flow rate, w , of 3000 lb/hr (Ref. Appendix D). Therefore, the bulk fluid temperature is 180° F.

3. Diaphragm Surface Temperature (design point)

The temperature drop from the coolant bulk to the diaphragm is given by

$$\Delta T_b = \frac{Q_c}{h_B (w) A_D} = 30^\circ \text{ F}$$

CONFIDENTIAL

MND-3293

DECLASSIFIED

~~CONFIDENTIAL~~

where values of Q_c and flow rate (w) are the same as previously indicated (Ref. Appendix D). Therefore, the diaphragm surface temperature is 210° F.

4. Cold Junction Temperature (design point)

The temperature drop from the diaphragm surface to the cold junction is composed of the drops across the diaphragm (Al_2O_3 and Al_2O_3) cold junction interfaces and is given by

$$\Delta T_a = Q_c \frac{\Delta X_i}{k} \left(\frac{1}{A_c} + \frac{1}{A_D} \right) = 30^\circ \text{ F}$$

where Q_c is the same as previously indicated (Ref. Appendix D). Therefore, the cold junction temperature is 240° F.

5. Hot Junction Temperature

The maximum operating temperature of the PbSnTe thermoelements is 1000° F. Therefore, this was taken to be the beginning-of-life hot junction temperature. For a five-year life Sr-90 system, the temperature difference between the hot and cold junction will decrease approximately 13% from the beginning-of-life value. Therefore, the design point hot junction temperature was taken to be 925° F.

6. Hot Plate Surface Temperature

From experience with SNAP generators, the temperature drop from the hot junction, across the electrical insulator and corresponding interfaces, to the hot plate is approximately 50° F. Therefore, beginning-of-life hot plate surface temperature is 1050° F while at the design point it is 975° F.

7. Fuel Capsule Front Wall Temperature

An analytical solution of the fuel capsule temperature distribution is not practically possible, and therefore the IBM code TIGAMM was employed for this problem. The problem was reduced to a two-dimensional one by investigating a disk of unit depth in the center of one fuel capsule and neglecting the effects at the capsule ends. By symmetry arguments, only one-half the capsule need be investigated (see following sketch).

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

0315087030
~~CONFIDENTIAL~~

F-3

Temperature gradients within the hot plate are negligible because of the high thermal conductivity of beryllium. Therefore, the hot plate surface facing the capsules is at a beginning-of-life temperature of 1050° F. The corresponding beginning-of-life fuel capsule front wall temperature, determined by TIGAMM, is 1517° F. Only the beginning-of-life fuel capsule temperatures were determined by TIGAMM. However, the fuel capsule front wall temperature is determined by radiation from the fuel capsule to the hot plate. Therefore, knowing the design point hot plate temperature to be 975° F, the end-of-life fuel capsule front wall temperature may be determined from

$$\frac{T_2'^4 - T_1'^4}{T_2^4 - T_1^4} \approx 1.132$$

where

1.132 = factor for Sr-90 isotope decay over the five-year life

T_2' = 1517° F = beginning-of-life fuel capsule front wall temperature

T_1' = 1050° F = beginning-of-life hot plate surface temperature

T_2 = unknown = end-of-life fuel capsule front wall temperature

T_1 = 975° F = end-of-life hot plate surface temperature

~~CONFIDENTIAL~~

MND-3393

0315087030

DECLASSIFIED

~~CONFIDENTIAL~~

Solving this equation for the unknown:

$$T_2 = 1445^\circ \text{ F}$$

8. Fuel Capsule Back Wall Temperature

The beginning-of-life capsule back wall temperature was determined by TIGAMM to be 1796° F . Since the fuel capsule back wall temperature is determined primarily by conduction through the fuel, the end-of-life back wall temperature is given by

$$\frac{T_3' - T_2'}{T_3 - T_2} \approx 1.132$$

where

$$T_3' = 1796^\circ \text{ F} = \text{beginning-of-life fuel capsule back wall temperature}$$

Solving this equation for the unknown:

$$T_3 = 1690^\circ \text{ F}$$

9. Maximum Fuel Temperature

The maximum fuel temperature determined by TIGAMM is 1835° F at the beginning of life.

B. DYNAMIC SYSTEM THERMAL LOSSES

The parasitic thermal losses (heat loss that is not transported through the thermoelectric couples) occur in five components:

- (1) Module insulation.
- (2) Module seal bellows.
- (3) Thermal insulation outside the bellows that also acts as a structural support between the hot and cold plates.
- (4) Capsule assemble support rods.
- (5) Insulation around the fuel capsule assembly on the four sides not occupied by the modules.

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

1. Module Insulation

The heat loss through both* rectangular slabs of module insulation is given by

$$q = \frac{2 k_A}{\ell} (T_H - T_C) = 181 \text{ watts}$$

where

q = total module insulation heat loss

k = thermal conductivity of Min-K 1301 filled with argon
= 0.02 Btu/ft-hr-°F

A = insulation cross-sectional area = 0.942 ft²

T_H = hot junction temperature = 925° F

T_C = cold junction temperature = 240° F

ℓ = module insulation length = 0.5 inch

2. Module Bellows

Around the entire edge of each module is a strip of stainless steel, fabricated as a bellows (i.e., an extended heat transfer length) to reduce the heat loss between the hot and cold surfaces of the module. A sketch of the system follows:

*One generator is composed of two modules, one on each large face of the fuel assembly.

DECLASSIFIED

~~CONFIDENTIAL~~

The heat loss down both module bellows is given by

$$q = \frac{2 k A}{\ell} (T' - T) f = 102 \text{ watts}$$

where

q = bellows heat loss

k = stainless steel thermal conductivity = 10 Btu/ft-hr-°F

ℓ = extended bellows length = 1.3 inches

T' = fuel block surface temperature = 975° F

T = cold plate temperature = 210° F at bellows attachment point

A = $2 (w_1 + w_2) t$ = bellows cross-sectional area = 0.002 ft²

w_1, w_2 = bellows widths = 10.10 and 18.75 inches, respectively

t = bellows thickness = 0.005 inch

f = factor to account for radiation loss from outer surface of bellows = 1.2

3. Module Bellows Insulation

Around both bellows is additional Min-K 1301 insulation as shown in the following sketch.

A variable temperature distribution exists across all faces of this piece of insulation. To reasonably account for this, the insulation was divided into four equal segments and a linear temperature distribution assumed along one side (see following sketch). The heat loss through all the surrounding insulation for both modules is then given by

$$q = \frac{4k}{\ell} \left[\sum_{i=1}^4 \Delta T_i A_i + \sum_{j=1}^4 \Delta T_j A_j \right] = 63 \text{ watts}$$

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

03:05:07:030

F-7

~~CONFIDENTIAL~~

MND-3398

03:05:07:030

DECLASSIFIED

~~CONFIDENTIAL~~

where

q = heat loss

A_i = cross-sectional area to heat flow = 0.062 ft^2

A_j = segment area of other two sides = 0.07 ft^2

$\Delta T_i = \Delta T_j$ = temperature difference across each segment. In particular

$$\Delta T_1 = \frac{975 + 785}{2} - 210 = 670^\circ \text{ F}$$

$$\Delta T_2 = \frac{785 + 595}{2} - 210 = 480^\circ \text{ F}$$

$$\Delta T_3 = \frac{595 + 405}{2} - 210 = 290^\circ \text{ F}$$

$$\Delta T_4 = \frac{405 + 210}{2} - 210 = 100^\circ \text{ F}$$

k = thermal conductivity of Min-K 1301 in vacuum = $0.013 \text{ Btu/ft-hr-}^\circ\text{F}$

ℓ = insulation length = 0.6 inch

i, j = subscripts to indicate the sections of insulation around each bellows.

4. Support Rods

The hot plate assembly is supported from the two beryllium cold plates by a stainless steel tube and a ceramic cup. A sketch of this support structure follows:

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

CONFIDENTIAL

F-9

The heat loss through the four structures is given by

$$q = 4 \left[\frac{k_1 A_1}{\ell_1} + \frac{k_2 A_2}{\ell_2} + \frac{k_3 A_3}{\ell_3} \right] (T_1 - T_2) = 267 \text{ watts}$$

where

q = total heat loss

$K_1 = K_2$ = thermal conductivity of the ceramic = 2 Btu/ft-hr-°F

k_3 = thermal conductivity of steel tube = 10 Btu/ft-hr-°F

ℓ_1 = ceramic sleeve length = 0.05 foot

ℓ_2 = ceramic cup length = 0.125 foot

ℓ_3 = steel tube length = 0.104 foot

A_1 = cross-sectional area of ceramic sleeve = 0.694 in.²

A_2 = cross-sectional area of ceramic cup = 0.589 in.²

A_3 = cross-sectional area of steel tube = 0.0575 in.²

T_1 = hot side temperature = 975° F

T_2 = cold side temperature = 210° F

5. Capsule Assembly

The heat loss through the Min-K insulation directly surrounding the lateral surface of the fuel assembly is given by

$$q = k \left[\frac{2 A_1 \Delta T_1}{\ell_1} + \frac{A_2 \Delta T_2}{\ell_2} + \frac{A_3 \Delta T_3}{\ell_3} \right] = 37 \text{ watts}$$

where

k = thermal conductivity of Min-K in vacuum

$k = 0.014 \text{ Btu/ft-hr-°F}$

A_1 = cross-sectional area of insulation at one of the end faces of the fuel assembly

CONFIDENTIAL

MND-3393

DECLASSIFIED

~~CONFIDENTIAL~~

ℓ_1 = 0.435 square foot = length of end face insulation = 0.266 foot
 ΔT_1 = average temperature drop across the end insulation = 765° F
 ℓ_2 = length of side insulation = 0.216 foot
 ΔT_2 = average temperature drop across one side insulation = 1360° F
 ΔT_3 = average temperature drop across other side insulation = 765° F
 $A_2 = A_3$ = cross-sectional area of side insulation = 0.502 ft²

6. Summary of Parasitic Heat Losses

The following is a summation of the parasitic heat losses:

Module insulation	=	181
Module bellows	=	102
Bellows insulation	=	63
Support rock	=	267
Fuel block insulation	=	<u>37</u>
Total parasitic losses	=	650 watts

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

G-1

APPENDIX G

DYNAMIC SYSTEM PERFORMANCE CALCULATIONS

The required net power from the system is 250 watts. The required powers for the coolant pump and switching circuit controls are 7 and 10 watts, respectively. If both the dc-to-dc converter and dc-to-ac converter are 90% efficient, the gross power required from the generator is

$$\begin{aligned} P_a &= \frac{P_{\text{output}}}{\eta_{\text{converter}}} + \frac{P_{\text{pump}} + P_{\text{controls}}}{\eta_{\text{inverter}}} \\ &= \frac{250 \text{ w}}{0.9} + \frac{7 \text{ w} + 10 \text{ w}}{0.9} \\ &= 297 \text{ watts.} \end{aligned}$$

For hot and cold junction temperatures of 925° and 240°F, respectively, the thermoelectric efficiency (as presented in Appendix L) is 8.9%. Therefore, the heat required by the thermoelements is

$$Q_{\text{elements}} = \frac{P}{\eta_{T/E}} = \frac{297}{0.089} = 3330.$$

The thermal losses, as calculated in Appendix E, are 650 watts. Thus, the total fuel inventory required at the design point is

$$Q_{\text{total}} = Q_{\text{elements}} + Q_{\text{loss}} = 3980 \text{ watts.}$$

The overall system efficiency is

$$\eta_s = \frac{P_{\text{output}}}{Q_{\text{total}}} = 6.28\%.$$

The thermal efficiency is

$$\eta_t = \frac{Q_{\text{element}}}{Q_{\text{total}}} = 83\%.$$

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

~~CONFIDENTIAL~~

The fuel loading at beginning of life is

$$Q_0 = Q_{\text{total}} e^{\lambda T} = 1.132 (Q_{\text{total}}) = 4505 \text{ watts}$$

$$T = \text{mission life} = 5 \text{ years}$$

$$\lambda = \ln. 2 / t^{1/2}$$

$$t_{1/2} = \text{half life of Sr-90} = 28.8 \text{ years.}$$

The curie fuel loading is

$$\text{Curies} = \frac{4505 \text{ watts}}{6.3 \text{ watts/k curie}} = 715,136 \text{ curies.}$$

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

H-1

APPENDIX H

DYNAMIC SYSTEM TEMPERATURE DISTRIBUTIONS AFTER COOLING SYSTEM FAILURE ON THE LAUNCH PAD

In the event of total failure of the dynamic generator cooling system on the launch pad, it is important to determine the maximum fuel capsule temperature to ensure that the capsules do not melt and release the fuel. Since such an event can have very serious consequences, the analysis which follows is conservative in the extreme. It shows that even with no auxiliary cooling, the fuel capsules will not melt. However, they will be at an extremely high temperature and it is therefore suggested that auxiliary cooling be provided in the form of an air movement over the generator surface in the event of total cooling system failure.

Consider the case with no cooling air moving over the generator and the generator completely enclosed in a dead air space formed by the sides of the vehicle, the payload above and the Agena tank below. It will be conservatively assumed that the air around the generator provides no heat transfer and all the heat must be rejected by radiation from the generator cold plates to the sides of the vehicle. It will further be assumed that the payload and Agena vehicle provide no heat sink.

A. TEMPERATURE DROP FROM VEHICLE SKIN TO AIR

The heat to be rejected is approximately 4500 watts or 15,345 Btu/hr. Assume that all the heat must ultimately be rejected to ambient air by natural convection from the sides of the adapter section containing the generator. The skin of the adapter section is a cylinder 5 feet in diameter and 2.5 feet high.

For natural convection, Ref. H-1 suggests the following correlation:

$$\frac{h_c L}{k_f} = 0.13 \left[N_{Gr} N_{Pr} \right]^{1/3} = 0.13X^{1/3}$$

or

$$X = \left(\frac{h_c L}{0.13 k_f} \right)^3 = N_{Gr} N_{Pr}$$

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

H-2

~~CONFIDENTIAL~~

where

N_{Pr} = Prandtl number

N_{Gr} = Grashof number

h_c = area heat transfer coefficient (Btu/hr-ft²-° F)

L = height of cylinder (feet)

K_f = thermal conductivity of fluid (Btu/hr-ft-° F)

The correlation is applicable for

$$10^9 \leq N_{Pr} N_{Gr} \leq 10^{12}$$

Using this equation, the following values were obtained for h as functions of ΔT from Ref. H-1:

h	ΔT	$h\Delta T$
0.95	100	95
1.10	200	220
1.60	500	800
2.00	1000	2000

Since $\frac{q}{A} = h_c \Delta T$, the required value of $h_c \Delta T$ is

$$h_c \Delta T = \frac{15,345}{\pi(5)(2.5)} = 389 \text{ Btu/hr-ft}^2$$

Plotting a curve from the preceding data, we find that $\Delta T \approx 280^\circ \text{ F}$. If we assume a 20% uncertainty factor in the recommended correlation, we find

$$T_{\text{skin}} = 100 + 1.2 (2.8\sigma) = 436^\circ \text{ F}$$

where it has been assumed the ambient air is at 1000° F .

B. TEMPERATURE DROP FROM GENERATOR SURFACE TO VEHICLE SKIN

Consider the temperature drop from the generator to the skin of the vehicle. As mentioned previously, heat transfer will be assumed to be by radiation only. Consider the following configuration:

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

H-3

where surfaces r and s represent the two cold plates of the generator, surface u represents the payload, surface t the side of the vehicle transition piece and surface v the Agena fuel tank. It has been assumed that the sides of the generator provide no radiating area, i.e., the generator has zero thickness. The diameter of the disk representing the generator is such that the area of the disk is the same as the area of the generator cold plate.

First, the various view factors must be computed. Immediately, we have

$$F_{rs} = F_{sr} = 0$$

$$F_{rv} = F_{su} = F_{vr} = F_{us} = 0$$

For parallel concentric disks, Ref. H-2, Fig. 25, yields

$$F_{ru} = 0.79$$

then

$$F_{rt} = 1 - 0.79 = 0.21$$

also

$$F_{uu} + F_{ur} + F_{ut} + F_{uv} + F_{us} = 1$$

and

$$A_r F_{ru} = A_u F_{ur}$$

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

CONFIDENTIAL

Therefore

$$F_{ur} = \frac{A_r}{A_u} F_{ru} = 0.04$$

and

$$F_{ut} = 1 - 0.04 - F_{uv}$$

It is conservative to minimize F_{ut} or maximize F_{uv} . The view factor F_{uv} can be estimated by ignoring the effect of disc r-s. For the ends of a cylinder having length L and diameter D

$$X = \frac{L}{D}$$

$$F = 1 + 2X^2 - 2X\sqrt{1+X^2}$$

In this case

$$X = 0.5$$

$$F_{uv} = 0.38$$

then

$$F_{ut} = 1 - 0.04 - 0.38 = 0.58$$

If the net radiative flux into surfaces u and v is zero, we have one source (s-r) and one sink (t) and a no flux surface (u-v). Surfaces u and v can be considered as one from symmetry considerations. Then let

$$A_R = A_u + A_v$$

$$A_H = A_r + A_s$$

$$A_C = A_t$$

For this case, Ref. H-1 derives the relation

$$A_1 \bar{F}_{12} = A_1 F_{12} + \frac{1}{\frac{1}{A_1 F_{1R}} + \frac{1}{A_2 F_{2R}}}$$

where 1 and 2 are the source and sink and R is the no-flux surface. In this case

CONFIDENTIAL

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

H-5

$$\bar{F}_{HC} = F_{HC} + \frac{1}{\frac{1}{F_{HR}} + \frac{A_H}{A_C F_{CR}}}$$

$$F_{HC} = F_{rt} = 0.21$$

$$F_{HR} = F_{ru} = 0.79$$

$$F_{CR} = F_{tu} = 2 \frac{A_u}{A_t} F_{ut} = 0.59$$

$$\frac{A_H}{A_C} = 0.051$$

thus

$$F_{HC} = 0.95$$

Reference H-1 further derives for this situation

$$\mathcal{F}_{12} = \frac{1}{\left(\frac{1}{\epsilon_1} - 1\right) + \frac{A_1}{A_2} \left(\frac{1}{\epsilon_1} - 1\right) + \frac{1}{F_{12}}}$$

where

$$q = A_1 \mathcal{F}_{12} \sigma (T_1^4 - T_2^4)$$

For the case under consideration, these equations become

$$\mathcal{F}_{HC} = \frac{1}{\left(\frac{1}{\epsilon_H} - 1\right) + 0.051 \left(\frac{1}{\epsilon_C} - 1\right) + 1.05}$$

If it is assumed that both the generator and the inside of the vehicle are coated so that

$$\epsilon_H = \epsilon_C = 0.8,$$

$$\mathcal{F}_{HC} = 0.763$$

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

~~CONFIDENTIAL~~

Therefore

$$T_H^4 = \frac{q_{HC}}{A_H \mathcal{F}_{HC\sigma}} + T_C^4$$

$$= 5.90 \times 10^{12} + T_C^4$$

From the previous calculation, the vehicle skin temperature, T_C , is 436° F. Therefore, the generator surface temperature is:

$$T_H = 1142^\circ \text{ F}$$

C. TEMPERATURE DROP FROM FUEL CAPSULE TO GENERATOR SKIN

Considering the generator to be a slab and neglecting end effects, the following model of the generator may be constructed.

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

CONFIDENTIAL

0315587030

H-7

For a series of thermal resistances

$$q = \frac{\Delta T}{\Sigma R}$$

$$R = \frac{t}{Ak}$$

where

t = thickness

A = heat transfer area

k = thermal conductivity

If we assume that in Zone 1, the air gap between the fuel capsule and the fuel block, heat transfer is entirely by radiation and if we assume that the beryllium ribs in the coolant chamber (Zone 4) cover 20% of the area of Zone 4, we have the following values for the thermal resistances, R 's.

<u>Zone</u>	<u>k</u> <u>Btu/hr-ft-° F</u>	<u>t</u> <u>(ft)</u>	<u>A</u> <u>(ft²)</u>	<u>R</u>
2	43	0.021	1	0.0005
3*	1.0	0.0521	0.3	0.171
4	43	0.021	0.2	0.025
5	43	0.021	1	0.0005

*Conductance of the Min-K was assumed to be negligible compared with that of the PbTe. Here, k values have been conservatively chosen as the minimum values for the temperature range encountered.

From the tabulation, $\Sigma R = 0.174$; therefore, $\Delta T = 7670 \times 0.174 = 1335^\circ \text{ F}$. Thus, the temperature of the hot plate is

$$\begin{aligned} T_{\text{HP}} &= T_{\text{surface}} + \Delta T \\ &= 1142^\circ + 1335^\circ \\ &= 2477^\circ \text{ F} \end{aligned}$$

The radiative temperature drop across Zone 1 can now be calculated. Considering one capsule

CONFIDENTIAL

MND-3393

031712291030

DECLASSIFIED

H-8

~~CONFIDENTIAL~~

$$q_{\text{capsule}} = 1096 \text{ Btu/hr}$$

If we assume all the heat is radiated across one half the capsule side area

$$A_R = \frac{\pi d_c \ell_c}{2} = 25.2 \text{ in.}^2 = 0.175 \text{ ft}^2$$

For concentric cylinders

$$\frac{q}{A} = \frac{\sigma}{\frac{1}{\epsilon_1} + \frac{1}{\epsilon_2} - 1} (T_1^4 - T_2^4)$$

If $\epsilon_1 = \epsilon_2 = 0.8$ (grooved surfaces)

$$T_{FC}^4 = 6.69 \times 10^{12} + T_{FB}^4$$

or

$$T_{FC} = 2540^\circ \text{ F}$$

Summarizing the preceding calculations, we derive the following:

<u>Location</u>	<u>Temperature ($^\circ \text{F}$)</u>
Ambient air	100
Surface of vehicle	436
Surface of generator	1142
Hot plate	2477
Surface of fuel capsule	2540
Melting point of Haynes-25	2425 to 2570

Considering the extreme conservatism of the calculation, it is possible that the capsule will not melt down, although the calculated fuel capsule temperature is in the melting range of Haynes-25. For example, if radiation from the vehicle surface were included, the calculated vehicle surface temperature would be close to 250° F and the surface of the generator approximately 1060° instead of 1142° F . In addition, the launch vehicle and payload will provide heat sinks and some heat rejection. However, to make certain that all safety requirements are met, it is suggested that cooling air be passed over the gen-

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

0315587030
~~CONFIDENTIAL~~

H-9

erator surface if the cooling system fails. The last portion of this appendix is devoted to calculating the amount of air flow that will reduce the fuel capsule temperature to a safe level.

No accurate calculation has been made of the time required for the system to reach the equilibrium temperatures previously calculated. However, conservative estimates, based on the heat capacity of the vehicle skin and structural members in the generator area, and the heat capacity of the generator, indicate stabilization will take at least one hour.

D. GENERATOR TEMPERATURE WITH AIR COOLING

If the generator compartment were vented so that the generator were cooled by natural convection, the fuel capsule temperature would be lowered approximately 100° F. Since this still does not reduce the calculated value of fuel capsule temperature below the melting range of Haynes-25, forced air cooling will be needed.

For forced convection, Ref. H-1 gives the following correlation for flow normal to a surface:

$$N_{RE} = \frac{D_o V \rho}{\mu}$$

= Reynolds number

D_o = important dimension of the surface (other surface dimension is infinite)

V = velocity of gas

ρ = density of gas

μ = viscosity of gas

For air at 100° F

μ = 0.046 lb/ft-hr

k = 0.0157 Btu/hr-ft-°F

ρ = 0.0918 lb/ft³

Assume conservatively that cooling surface area is one square foot.

CONFIDENTIAL

MND-3393

0317291030

DECLASSIFIED

H-10

~~CONFIDENTIAL~~

Then
$$h = \frac{q}{A \Delta T} = 15.4 \text{ Btu/hr-ft}^2\text{-}^\circ\text{F}$$

where we have required ΔT to be 500°F .

If $D_o \approx$ one foot, a conservative estimate of the generator cold plate dimension,

then

$$\frac{hD_o}{k} = 983$$

For turbulent air flow, Ref. H-1 suggests

$$\frac{hD_o}{k} = 0.0239 (N_{Re})^{0.805} = 983$$

Thus

$$N_{Re} = 5.1 \times 10^5$$

and the required air velocity is

$$V = \frac{\mu N_{Re}}{D_o \rho} = 71 \text{ fps}$$

If we assume a duct with a cross-sectional area of 1.5 ft^2 is used to carry the cooling air to the generator, the required air flow is

$$\begin{aligned} W &= 1.5 \times 71 = 106 \text{ ft}^3/\text{sec} \\ &= 6360 \text{ ft}^3/\text{min} \end{aligned}$$

This flow of 100°F air through the duct will limit the generator temperatures to the value shown in the following tabulation

Temperature Distribution with Cooling Air

<u>Location</u>	<u>Temperature ($^\circ\text{F}$)</u>
Ambient air	100
Generator surface	600
Hot plate	1935
Fuel capsule	2050

CONFIDENTIAL

DECLASSIFIED MND-3393

~~CONFIDENTIAL~~

03115087030

H-11

REFERENCES

- H-1. McAdams, "Heat Transmission," McGraw-Hill, 1952.
- H-2. Hamilton, D. C., and Morgan, W. R., "Radiant Interchange View Factors," NACA Technical Note 2836 (NACA-TN2836) December 1952.

~~CONFIDENTIAL~~

~~MND-3308~~

03115087030

H-12

DECLASSIFIED

~~CONFIDENTIAL~~

BLANK

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

APPENDIX I

STATIC SYSTEM RADIATOR OPTIMIZATION

A. CONFIGURATION STUDIES

Several configurations were investigated to determine the lightest fin configuration for the static generator. The simple "string" technique was used together with an assumed fin efficiency to determine the fin root to tip dimension required to give the necessary heat rejection area. The fin root thickness necessary to provide the assumed efficiency was then calculated. The two fin dimensions were used to calculate the fin weight. Nomenclature used in this appendix is defined in Table I-1.

The basic equations used to calculate the various parameters in each configuration follow and the results are summarized using typical values in Table I-2.

TABLE I-1

Radiator Nomenclature

l	=	length of rectangular module base plate
w	=	width of rectangular module base plate
η_f	=	fin efficiency
w_f	=	fin root to tip dimension
T_R	=	fin root and base plate temperature
σ	=	Stefan-Boltzmann constant
ϵ	=	radiator emissivity
t_R	=	fin root thickness
h	=	effective fin area heat transfer coefficient
	=	$N\sigma \epsilon T_R^3, 1 < N < 4$

DECLASSIFIED

I-2

~~CONFIDENTIAL~~

Fig. I-1. Fin Efficiency

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

TABLE I-1 (continued)

k	=	thermal conductivity of fin material
q	=	heat to be rejected by the radiator
v	=	volume of fin material
WT	=	weight of fins
ρ	=	density of fin material
A_R	=	required effective radiator area
	=	$\frac{q}{\sigma \epsilon (T_R^4 - \theta^4)}$
θ	=	effective temperature of space

1. General Equations

$$A_R = \frac{q}{\sigma \epsilon (T_R^4 - \theta^4)}$$

ξ = function of fin efficiency presented in Fig. I-1 (taken from Ref. I-1)

$$= w_f^{3/2} \left[\frac{2h}{k w_f t_R} \right]^{1/2} \text{ for triangular fins.}$$

Transposing

$$\begin{aligned} t_R &= \frac{2h w_f^2}{k \xi^2} \\ &= \frac{2N\sigma \epsilon T_R^3}{k} \left[\frac{w_f}{\xi} \right]^2 \end{aligned}$$

2. Configuration A: "The Cookie Cutter"

$$A_R = \ell w + 2\eta_f w_f (\ell + w)$$

DECLASSIFIED

~~CONFIDENTIAL~~

$$w_f = \frac{A_R - \ell w}{2\eta_f (\ell + w)}$$

For this configuration, experience shows that $N \approx 2$. Thus,

$$t_R = \frac{4\sigma \epsilon T_R^3}{k} \left[\frac{w_f}{\xi} \right]^2$$

$$wT = \rho \left[t_R w_f \ell + t_R w_f w + t_R w_f \sqrt{\ell^2 + w^2} \right]$$

$$= \rho t_R w_f \left[\ell + w + \sqrt{\ell^2 + w^2} \right]$$

3. Configuration B: "The Lazy X"

$$A_R = w\ell + 2\eta_f w_f (\ell + w)$$

$$w_f = \frac{A_R - \ell w}{2\eta_f (\ell + w)}$$

~~CONFIDENTIAL~~

DECLASSIFIED

MIND-3393

For this configuration, $N \approx 3$

$$t_R = \frac{6 \sigma \epsilon T_R^3}{k} \left[\frac{w_f}{\xi} \right]^2$$

$$wT = \rho t_R w_f \ell^2 + w^2$$

4. Configuration C: "The Wagon Wheel"

T = temperature of radiative plate

t_1 = thickness of conducting ribs

t_2 = thickness of radiative plate

R = radius of radiative plate

$$A_R = \pi R w$$

If the temperature drop in the conducting ribs is to be limited

$$\Delta T = \frac{q \bar{R}}{M k w t_1} = 25^\circ \text{ F}$$

where

M = number of conductive ribs

$\bar{R}$ = average length of conductive rib

Therefore, $T = T_R - 25^\circ \text{ F}$

and

$$t_1 = \frac{q R}{M k w \Delta T}$$

$$wT = \rho [M \bar{R} t_1 w + \pi R t_2]$$

DECLASSIFIED ~~CONFIDENTIAL~~

5. Configuration D: "The Side Fin"

$$A_R = lw + 2\eta_f w_f (l + w)$$

$$w_f = \frac{A_R - lw}{2\eta_f (l + w)}$$

For this configuration, $N \approx 3.5$

$$t_R = \frac{7\sigma \epsilon T_R^3}{k} \left[\frac{w_f}{\xi} \right]^2$$

$$wT = \rho w_f t_R (l + w)$$

6. Configuration E: "The Angled Side Fin"

$$A_R = lw + 2\eta_f w_f (l + w) (\sin \phi - \cos \phi)$$

where it is conservatively assumed that the outward view of the fin is limited to the projected length of the fin on a perpendicular dropped from the fin tip to the plane of the base plate. The area is obviously maximum for the maximum value of $(\sin \phi - \cos \phi)$.

~~CONFIDENTIAL~~

DECLASSIFIED MND-3393

00115507030
~~CONFIDENTIAL~~

I-7

Let

$$F(\phi) = \sin \phi - \cos \phi$$

$$\frac{dF(\phi)}{d\phi} = \cos \phi + \sin \phi = 0$$

or

$$\tan(\phi) = \frac{\sin \phi}{\cos \phi} = -1$$

Therefore,

$$\phi_{\max} = 135^\circ$$

$$F(\phi) /_{\max} \sin(135^\circ) - \cos(135^\circ) = 1.414$$

Thus,

$$w_f = \frac{A_R - \ell w}{2.828 \eta_f (\ell + w)}$$

For this configuration, $N \approx 4$

$$t_R = \frac{8\sigma \epsilon T_R^3}{k} \left[\frac{w_f}{\xi} \right]^2$$

$$wT = \rho w_f t_R (w + \ell)$$

7. Configuration Comparison

The configurations are compared for a standard set of conditions in Table I-2. The weights are presented as normalized to the lightest configuration since the basic conditions do not match the actual generator dimensions.

The conditions used for the comparison were:

$$\ell = w = 12.25 \text{ inches}$$

$$\eta_f = 80\%$$

$$T_R = 600^\circ \text{ F}$$

$$\epsilon = 0.80$$

$$k = \text{conductivity of Be at } 600^\circ \text{ F}$$

$$= 79 \text{ Btu/hr-ft-}^\circ\text{F (Ref. I-2)}$$

~~CONFIDENTIAL~~

MND-3393

00171228030

DECLASSIFIED

I-8

~~CONFIDENTIAL~~

Shaded area occupied by thermocouples.

Fig. I-2. Radiator Plate

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

q = 2500 watts for one module
 $\rho = 0.067 \text{ lb/in.}^3$ (Ref. I-2)
 $\theta = 0^\circ \text{ R}$

TABLE I-2
Radiator Configuration Comparison--Static System

<u>Configuration</u>	<u>A</u>	<u>B</u>	<u>C</u>	<u>D</u>	<u>E</u>
N	2.0	3.0	--	3.5	4.0
t_R (in.)	2.48	3.72	--	4.34	3.51
w_f (in.)	14.26	14.26	--	14.26	10.09
Normalized weight	1.21	1.07	2.09	1.76	1.0

B. OPTIMIZATION OF SELECTED CONFIGURATION

The radiator configuration selected for the generator is E, the "angled side fin." However, the actual radiator is not quite so simple as that presented in the previous section because the thermocouples are concentrated in the center of the baseplate and there is a band of material between the thermocouple area and the root of the angled fins. The actual radiator plate is shown in Fig. I-2. In addition, the fins are filled in at the corners for structural reasons, but this added area has not been considered in the radiator calculations.

The "string" analysis of this radiator is similar to the analysis presented in the previous section except that the band of material between the thermocouple area and the root of the fin proper must be assigned an efficiency of its own. Let this efficiency be η_1 . Then, conservatively,

$$A_R = lw + 2\eta_1 (ly + wx + 2xy) + 2\eta_f w_f (l + w + x + y)(\sin \phi - \cos \phi)$$

As before,

$$\sin \phi - \cos \phi /_{\max} = 1.414 \text{ for } \phi = 135^\circ$$

DECLASSIFIED

~~CONFIDENTIAL~~

Therefore,

$$\eta_f w_f = \frac{A_R - \ell w - 2\eta_1 (\ell y + wx + 2xy)}{2.828 (\ell + w + x + y)}$$

where A_R will be defined as

$$A_R = \frac{q}{\sigma \epsilon T_R^4}$$

For the system under investigation

$$T_R = 600^\circ \text{ F} = 1060^\circ \text{ R}$$

$$\sigma = 1.7123 \times 10^{-9} \text{ Btu/hr-ft}^2\text{-}^\circ\text{R}^4$$

$$\epsilon = 0.8$$

$$q = 2500 \text{ watts for one module}$$

Therefore, $A_R = 715 \text{ in.}^2$ for the generator,

$$\ell = 18.5 \text{ inches}$$

$$w = 9.5 \text{ inches}$$

$$x = 1.38 \text{ inches}$$

$$y = 3.25 \text{ inches}$$

$$\eta_1 \approx 85\%, \text{ based on the temperature distribution for the } 3/4\text{-inch plate as determined in Appendix J.}$$

Therefore,

$$h_f = \frac{4.335}{\eta_f}$$

also $N \approx 4$ and for beryllium $k = 79 \text{ Btu/hr-ft-}^\circ\text{F}$

Therefore,

$$t_R = \frac{8\sigma \epsilon T_R^3}{k} \left[\frac{w_f}{\xi} \right]^2 = 0.01376 \left[\frac{w_f}{\xi} \right]^2$$

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

03:15:08:10:30

I-11

Finally, the weight of fin material is given by

$$\begin{aligned} WT &= \rho t_R w_f (\ell + w + x + y), \rho = 0.067 \text{ lb/in.}^3 \\ &= 2.19 w_f t_R \end{aligned}$$

The equations for w_f , t_R and fin weight have been used to conduct a study of the variations in these parameters as a function of efficiency. Weight versus fin efficiency is presented in Fig. IV-8. The minimum weight occurs for a fin efficiency of 60%. For this value of fin efficiency,

$$WT = 6.6 \text{ pounds for one module}$$

$$w_f = 7.25 \text{ inches}$$

$$t_R = 0.42 \text{ inches}$$

The adequacy of this design has been demonstrated by a computer calculation which is presented in Appendix J. The calculation shows that the temperatures in the thermoelement area can be maintained at an average value of 600° F if the module baseplate is approximately 0.75 inch thick. This is the configuration that has been used in the generator design.

~~CONFIDENTIAL~~

MND-3393

03:12:28:10:30

DECLASSIFIED

~~CONFIDENTIAL~~REFERENCES

- I-1. Schneider, "Conduction Heat Transfer, " Addison-Wesley.
- I-2. Brush Beryllium Co., "Beryllium in Aerospace Structures. "

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

03:15:08:70:30

J-1

APPENDIX J

STATIC SYSTEM TEMPERATURE DISTRIBUTIONS

A. TEMPERATURE DISTRIBUTION AT DESIGN POINT--END OF FIVE-YEAR LIFE

The design point hot and cold junction temperatures serve to establish the design point and beginning of life temperatures. These design point temperatures are

Hot junction temperature 1500 °F

Cold junction temperature 610 °F.

Based on these, the temperature on the module radiator plate just behind the thermocouples is 600 °F. To verify that the approximate techniques used to estimate fin size give the correct temperature in the thermoelement area of the module, a more sophisticated technique was used to calculate the temperature distribution in the radiator. The more accurate calculation was performed by means of a numerical technique utilizing the Martin IBM 7094 code, TIGAMM. The radiator temperature distribution was calculated for 1/2- and 3/4-inch module baseplate thicknesses.

TIGAMM is a Martin version of the Code TIGER II written by KAPL (KAPL 2044, May 24, 1959, or TID 4500, 14th edition). The code is the same as TIGER II, except that the input format has been simplified.

Given any odd-shaped structure which can be represented by a three-dimensional field, its geometry and physical properties, boundary conditions, and internal heat generation rates, TIGAMM will calculate and give as output the steady state or transient temperature distributions in the structure as a function of time. Both the boundary temperatures and internal generation rates may vary arbitrarily as functions of time. In addition, the code can handle surface-forced convection, free convection, or radiation, giving as output the temperatures and surface heat fluxes for points representing the surface of the structure.

The model used in the analysis is shown in Fig. J-1. Only one-quarter of the radiator need be considered from arguments of symmetry. The fins on the layout are shown as direct extensions (no cant)

~~CONFIDENTIAL~~

MND-3398

03:17:28:10:30

DECLASSIFIED

J-2

~~CONFIDENTIAL~~

Fig. J-1. One-Quarter of Radiator--Top View

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

CONFIDENTIAL

0310587030

J-3

of the baseplate, but in the code are analyzed with the 45-degree cant they possess by using the appropriate radiation view factors. The thermoelements are mounted on only the portion of the baseplate shown in Fig. J-1. The remainder of the baseplate acts as a fin.

The fuel inventory for the entire generator at the end of life is 4990 watts. This heat was properly apportioned between the area to which the elements are mounted and the area in which insulation surrounds the module. The emissivity of beryllium was taken as 0.8 and its conductivity as 80 Btu/ft-hr-°F.

The results are shown in Tables J-1 and J-2 for the 1/2- and the 3/4-inch plates, respectively. The temperatures shown are those for each of the nodes used in setting up the code.

The average temperature in the thermoelement area for the 1/2-inch plate is 651°F. The average temperature in the thermoelement area of the 3/4-inch plate is 612°F, which is within 2% of the desired value of 600°F.

It is apparent that the optimum thickness from a thermal and weight standpoint would be tapered so as to be thin in the center and thickest at the edge of the thermoelement area, because the heat conducted through the plate to the fins increases as the edge of the thermocouple area is approached. This particular configuration has not been investigated in detail, but proper adjustment of the taper angle will yield a very similar temperature distribution.

B. TEMPERATURE DISTRIBUTION AT BEGINNING OF FIVE-YEAR LIFE

At the beginning of the five-year mission, the Sr-90 fuel will generate 1.132 times the heat required at the five-year design point. Thus, the beginning of life thermal inventory of the generator is

$$q_{\text{BOL}} = 1.132$$

$$q_{\text{T}} = 1.132 \times 4990 = 5648 \text{ watts (t)}$$

where the subscript "BOL" refers to beginning of mission life conditions.

CONFIDENTIAL

MND-3893

0310587030

CONFIDENTIAL

TABLE J-1

Temperature Distribution in 1/2-Inch Radiator in °F

496	500			488			470			449			434			Fin				
510	510			498			478			456			440							
525	523			509			488			465			447							
543	537			523			500			473			453							
563	564	553	559	554	538	539	530	513	510	499	483	478	470	459		Fin				
585	583	579	577	571	562	555	545	533	522	510	497	486	476	467	459	451	443	434	426	417
607	606	602	598	592	583	574	563	550	536	521	507	494	482	472	463	454	444	435	427	418
634	632	628	623	617	608	597	585	570	553	534	517	502	489	477	467	457	447 438 430 424			
664	662	659	653	646	637	625	610	593	573	548	527	510	494	481	469	455				
688	686	683	677	662	659	646	630	611	588	560	536	517	500	485	474	464				
706	704	700	694	686	675	661	644	624	599	569	543	521	504	489	476	466				
717	715	711	705	696	685	671	654	632	606	575	548	526	507	491	477	461	451	442	434	427
723	721	717	711	702	690	676	658	636	610	577	550	528	508	492	479	468				

Thermoelement portion of plate

CONFIDENTIAL

MND-3393

CONFIDENTIAL

TABLE J-2

Temperature Distribution in 3/4-Inch Radiator in °F

506	507			497			483			467			456			Fin				
516	515			505			490			473			461							
527	525			514			498			479			466							
540	536			524			506			486			471							
555	555	547	551	547	535	536	529	516	513	506	493	490	484	475	474	Fin				
570	570	566	564	559	553	547	540	530	522	513	504	496	488	481	476	470	463	457	450	443
586	585	582	579	574	568	561	552	543	532	522	511	501	493	485	478	471	464	457	451	444
604	603	601	597	592	585	577	567	556	544	531	518	507	497	489	481	474	466	459	453	448
626	624	622	618	612	605	596	585	573	558	541	526	513	502	492	483	473				
643	641	638	634	628	620	611	599	585	569	549	532	518	505	495	486	479				
655	654	651	646	640	632	621	609	594	576	555	537	521	508	497	488	480	469	462	456	450
663	662	659	654	647	639	629	616	600	582	559	540	524	510	499	489	477				
667	666	663	658	651	643	632	619	603	584	561	542	526	512	500	490	482				

Thermoelement portion of plate

CONFIDENTIAL

MND-3393

~~CONFIDENTIAL~~

The radiator temperature will be

$$\begin{aligned} T_{R_{BOL}} &= \sqrt[4]{1.132} T_R = 1.03 \times 1060 \\ &= 1091^\circ R \\ &= 631^\circ F. \end{aligned}$$

Heat conduction through the thermoelectric system is primarily by conduction. Thus, the temperature drop through the thermoelectric system will be proportional to the heat conducted, to a good approximation. (At the design point, 10% of the heat is lost through the insulation and supports. This heat loss is primarily by radiation.) Therefore,

$$\begin{aligned} (T_H - T_C)_{BOL} &= 1.132 (T_H - T_C) \\ &= 1.132 \times 890 \\ &= 1008^\circ F \end{aligned}$$

and

$$\begin{aligned} (T_C - T_R)_{BOL} &= 1.132 (T_C - T_R) \\ &= 1.132 \times 10 \\ &= 11.3^\circ F. \end{aligned}$$

Thus

$$\begin{aligned} T_{C_{BOL}} &= T_{R_{BOL}} + 11.3 \\ &= 642^\circ F \end{aligned}$$

and

$$\begin{aligned} T_{H_{BOL}} &= T_{C_{BOL}} + 1008 \\ &= 1650^\circ F. \end{aligned}$$

~~CONFIDENTIAL~~

MND-3393
~~CONFIDENTIAL~~

Heat transfer from the fuel capsules to the thermocouple hot shoes is entirely by radiation. Heat transfer within the fuel capsule is by conduction through the capsule wall and the fuel itself. An analytical solution of the fuel capsule temperature distribution is impossible and, therefore, the IBM code TIGAMM was used for this problem.

The problem was reduced to a two-dimensional one by investigating a disk of unit depth in the center of one fuel capsule and neglecting end effects at the top and bottom of the capsule. By symmetry arguments, only one-half the capsule need be investigated (Fig. J-2).

Temperature distributions for four sets of conditions were determined. Two capsule configurations were each investigated for two beginning of life hot junction temperatures (1550° and 1650°F) corresponding to design point hot junction temperatures of 1400° and 1500°F, respectively. The two capsule configurations investigated are shown in Fig. J-2. The first capsule contains only fuel in a superalloy capsule. This basic capsule contains approximately 15% void volume in the central cylinder. The second capsule configuration fills this void volume with a strip of high conductivity material, such as beryllium or molybdenum, running axially the entire length of the capsule. The materials properties used in the calculation were

Thermal conductivity of capsule	14.8 Btu/hr-ft-°F
Thermal conductivity of fuel	1.02 Btu/hr-ft-°F
Thermal conductivity of conductive strip	40 Btu/hr-ft-°F
Emissivity of fuel capsule surface	0.5 Btu/hr-ft-°F.

The important temperatures for each configuration are presented in Table J-3.

TABLE J-3
Beginning of Life Fuel Capsule
Temperature Distribution

	<u>Temperature (°F)</u>		<u>Maximum Fuel</u>
	<u>Capsule Front Wall</u>	<u>Capsule Back Wall</u>	
Configuration A			
$T_{H_{BOL}} = 1550^{\circ}\text{F}$	1800	2068	2132

DECLASSIFIED

J-8

~~CONFIDENTIAL~~

Fig. J-2. Capsule Temperature Gradient Configurations

~~CONFIDENTIAL~~

DECLASSIFIED MND-3393

TABLE J-3 (continued)

	<u>Temperature (°F)</u>		
	<u>Capsule Front Wall</u>	<u>Capsule Back Wall</u>	<u>Maximum Fuel</u>
$T_{H_{BOL}} = 1650^{\circ}\text{F}$	1870	2136	2200
Configuration B			
$T_{H_{BOL}} = 1550^{\circ}\text{F}$	1813	1936	1969
$T_{H_{BOL}} = 1650^{\circ}\text{F}$	1884	2008	2040

The actual fuel capsule will not be made with an axial metal strip, but rather with radial metal disks. If the same ratio of metal to fuel is maintained, the temperature distributions will be approximately the same. There will be small axial gradients in this case, but approximate calculations indicate they will not be more than 20°F.

From the machine-calculated beginning of life temperatures, the design point fuel capsule temperatures can be estimated by assuming that the temperature difference between the capsule front wall and the hot junction is given by

$$T_{FW}^4 - T_H^4 = \frac{q}{\gamma}$$

where γ is a constant.

Using the previously determined beginning of life conditions, we have

$$\gamma = \frac{q_{BOL}}{(T_{FW}^4 - T_H^4)_{BOL}}$$

Then, at the design point

$$T_{FW}^4 = \frac{q}{\gamma} + T_H^4$$

DECLASSIFIED

~~CONFIDENTIAL~~

$$T_{FW}^4 = \frac{q}{q_{BOL}} \left(T_{FW}^4 - T_H^4 \right)_{BOL} + T_H^4$$

but

$$\frac{q}{q_{BOL}} = \frac{1}{1.132}$$

$$\begin{aligned} \left(T_{FW}^4 - T_H^4 \right)_{BOL} &= (1884 + 460)^4 - (1650 + 460)^4 \\ &= 1.037 \times 10^{13} \end{aligned}$$

Then

$$T_{FW} = 1740^\circ \text{ F}$$

If we assume that all the heat transfer within the capsule occurs by conduction, then, in general, for temperature drops in the capsule

$$\Delta T \Big|_{\text{design point}} = \frac{\Delta T_{BOL}}{1.132}$$

For the capsule back wall temperature, we have

$$\Delta T_{BOL} = 2008 - 1884 = 124^\circ \text{ F}$$

$$\Delta T_{\text{design point}} = 109^\circ \text{ F}$$

$$T_{\text{back wall}} = 1849^\circ \text{ F}$$

For the maximum fuel temperature at the design point, we find that

$$T_{\text{fuel}} \Big|_{\text{max}} = 1878^\circ \text{ F}$$

~~CONFIDENTIAL~~

MIND-3393

DECLASSIFIED

APPENDIX K

STATIC SYSTEM THERMAL LOSSES

The parasitic thermal losses in the static system may be divided into the following areas:

- (1) Module insulation loss.
- (2) Side insulation loss.
- (3) Fuel core support structure.

The primary thermal insulation in the static generator is reflective foils. To minimize corrosion and oxidation of the foils before launch and to reduce weight, titanium will be used for the foils. The foils will be separated either by a thin flame-sprayed coat of ThO_2 on one side or by thin quartz fiber sheets. Sleeves of electrically insulating quartz fiber insulation will be used around the thermocouples in the module to prevent couple-to-couple shorts through the foils.

A. MODULE INSULATION LOSS

The module insulation has the following analytical configurations:

If we define the mean or average area as:

$$A_M = \frac{A_O + A_i}{2}$$

$$A_O = 16 \times 21.25 = 340 \text{ in.}^2$$

DECLASSIFIED
~~CONFIDENTIAL~~

$$A_i = 9.5 \times 18.5 = 176 \text{ in.}^2$$

$$A_M = 258 \text{ in.}^2$$

From the mean area must be subtracted the area of the thermocouples and the area of the insulating sleeves.

The area of the thermocouples is:

$$A_{el} = N(A_N + A_P)$$

$$N = \text{numbered couples in module} = 100$$

$$A_N = \text{area of N element} = 0.137 \text{ in.}^2$$

$$A_P = \text{area of P element} = 0.120 \text{ in.}^2$$

$$A = 25.7 \text{ in.}^2$$

The area of the sleeves is:

$$\begin{aligned} A_S &= N\pi(r_o^2 - r_i^2) \\ &= N\pi((0.39)^2 - (0.29)^2) \\ &= 21.4 \text{ in.}^2 \end{aligned}$$

Therefore, the area of foils is:

$$A_f = A_M - A_{el} - A_S = 211 \text{ in.}^2$$

The heat loss per unit area for the foils is based on experimental data developed in the SNAP 13 program. (See SNAP 13 Quarterly Progress Report No. 10, MND-3060-17, May 1964.) Experimental data show that for 20 foils, one side with emissivity of 0.05 and the other coated with ThO_2 of emissivity 0.75, the loss factor is less than $0.1 \frac{\text{watt}}{\text{cm}^2}$ between

temperatures of 1200°K (1700°F) and ambient. An equivalent emissivity can be obtained with two surfaces each with emissivity 0.1; thus, there is considerable confidence that titanium foil can be used with similar results. If we use the SNAP 13 area loss value and increase it by a factor of 3 to allow for "shine" around the couples for higher foil emissivity and for end effects we have, conservatively,

$$C = 0.06 \frac{\text{watt}}{\text{cm}^2} = 0.39 \frac{\text{watt}}{\text{in.}^2} \text{ for 100 foils}$$

~~CONFIDENTIAL~~

DECLASSIFIED
MND-3393

Using this number, we find the loss through the foils is

$$q_{\text{foil}} = CA_{\text{foil}} = 0.39 \times 211 = 83 \text{ watts for one module}$$

The loss through the insulating sleeves can be estimated from the formula

$$q = k \frac{A}{\ell} \Delta T$$

$$k = 0.55 \frac{\text{Btu}}{\text{hr-ft-}^\circ\text{F}} \text{ (J-M Dyna Quartz)}$$

$$A = A_S$$

$$\ell = 0.75 \text{ in.}$$

$$\Delta T = 1500^\circ - 600^\circ = 900^\circ \text{ F}$$

$$q_{\text{sleeve}} = 34 \text{ watts(t) for one module}$$

B. SIDE INSULATION LOSSES

The side insulation covers the four sides of the generator not occupied by the thermoelectric module. The pieces have the following analytical configuration:

There are two long and two short pieces with the following dimensions:

Side	w_i	l_i	w_o	l_o
Long	5	19	7	21.25
Short	5	10	7	16.25

DECLASSIFIED

~~CONFIDENTIAL~~

For the long sides:

$$A_o = 7 \times 21.25 = 149 \text{ in.}^2$$

$$A_i = 5 \times 19 = 95 \text{ in.}^2$$

$$A_M = \frac{A_o + A_i}{2} = 122 \text{ in.}^2$$

For the short sides:

$$A_o = 7 \times 16.25 = 114 \text{ in.}^2$$

$$A_i = 5 \times 10 = 50 \text{ in.}^2$$

$$A_M = 82 \text{ in.}^2$$

The total mean side area is:

$$A_{\text{side}} = 2 A_{M_{\text{long}}} + 2 A_{M_{\text{short}}} = 408 \text{ in.}^2$$

$$q_{\text{side}} = CA_{\text{side}} = 0.394 \times 408 = 161 \text{ watts (t)}$$

C. FUEL CAPSULE SUPPORT STRUCTURE

A simplified thermal model of the fuel capsule support structure is a cone with a ball-and-socket joint at the narrow end.

The mean area of the conical support is 0.188 in.^2 and the material is Hastelloy C. Assume that there is a temperature drop through the fuel capsule structure and through the ball-and-socket joint such that the hot

~~CONFIDENTIAL~~

DECLASSIFIED

MEND-3393

0015587030
~~CONFIDENTIAL~~

K-5

end of the cone is at the hot junction temperature and the cold end is at the radiator temperature. This assumption is conservative because there are two radiation gaps between the fuel capsule and the hot end of the cone, one between the capsule and the fuel capsule structure, and one between the ball, which is part of the fuel capsule structure, and the socket. Because there is only one radiation gap between the fuel capsules and the hot junction, it is unlikely that the temperature of the hot end of the cone is any higher than the hot junction temperature. Therefore,

$$q_{\text{cone}} = k \frac{A}{\ell} \Delta T = 16 \text{ watts (t)}$$

$$\Delta T = 1500^{\circ} - 600^{\circ} = 900^{\circ} \text{ F}$$

$$A = 0.188 \text{ in.}^2$$

$$\ell = 2.58 \text{ in.}$$

$$k = 10 \text{ (Hastelloy C) Btu/hr-ft-}^{\circ}\text{F}$$

Since there are four such structures in the generator, the total loss is 64 watts.

The parasitic thermal losses in the static system are summarized in Table K-1.

TABLE K-1

Static Generator Thermal Losses

<u>Item</u>	<u>Loss (watts (t))</u>
Module insulation (2)	
Sleeves	68
Foils	166
Side insulation	161
Fuel support structure	64
Total	<u>459</u>

~~CONFIDENTIAL~~

MND-3393

0015587030

K-6

DECLASSIFIED

~~CONFIDENTIAL~~

BLANK

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

L-1

APPENDIX L

STATIC SYSTEM PERFORMANCE CALCULATIONS

The required net power from the system is 250 watts. If the voltage setup and regulator device is 90% efficient, the gross power required from the generator is

$$P_g = \frac{P_N}{0.90} = \frac{250}{0.9} = 278 \text{ watts (e)}$$

For the selected hot and cold junction temperatures of 1500° and 610° F, respectively, the thermoelectric efficiency is 6.13% (Ref. Appendix A). Therefore, the heat required by the thermoelements is

$$Q_{el} = \frac{P_g}{\eta_{TE}} = \frac{278}{0.0613} = 4530 \text{ watts (t)}$$

The thermal losses, as calculated in Appendix K, are 460 watts (t). Thus, the total fuel inventory required at the design points is

$$Q_T = Q_{el} + Q_{loss} = 4990 \text{ watts (t)}$$

and the overall system efficiency is

$$\eta_s = \frac{P_N}{Q_T} = 5.01\%$$

The fuel loading at the beginning of life is given by

$$Q_o = Q_T e^{\lambda T} = (1.132) (Q_T) = 5648 \text{ watts (t)}$$

where

$$T = \text{mission duration} = 5 \text{ years}$$

$$\lambda = \frac{\ln^2}{t_{1/2}}$$

$$t_{1/2} = \text{half life of Sr-90} = 28.8 \text{ years}$$

~~CONFIDENTIAL~~

MND-3393

031229J030

DECLASSIFIED

CONFIDENTIAL

Since Sr-90 produces 6.3 watts per kilocurie, the curie fuel loading is:

$$\text{Curies} = \frac{5648}{6.3} \times 10^3 = 895,400 \text{ curies.}$$

CONFIDENTIAL

DECLASSIFIED

MAY 1993

CONFIDENTIAL

0312587030

M-1

APPENDIX M

FUEL HANDLING SYSTEM--ADVANCED SR-90 SPACE
POWER SUPPLY, 250 WATT(e)
INTERFACE SPECIFICATION
AND
EQUIPMENT SPECIFICATION

CONFIDENTIAL

MND 3393

0312587030

DECLASSIFIED
CONFIDENTIAL

INTERFACE SPECIFICATION

1.0 SCOPE

1.1 Purpose. - This specification defines and details the interfaces between the fueling system supplied by AMF and the facilities, equipment, material, operations and procedures of the Advanced Space Radioisotope Thermoelectric Power Supply, (Short Title - 250 Watt (e) Program.)

1.2 Limitations. - This specification is based on theoretical non-toleranced dimensions existant in the interface opposite the fueling system. Dimensions containing tolerance requirements are indicated safely to provide a maximum envelope capability.

1.3 Other considerations. - Interface considerations such as Safety, Reliability, Accessibility, etc. are treated in the general equipment specification.

1.2 Definitions. - For the purposes of this specification the following nomenclature is used as defined.

Cask: A containment vessel constructed of suitable radiation shielding material for the transport and storage of the radioisotopic fuel.

Fairing: An aerodynamic cover or shell surrounding the payload portion of a launch vehicle, of rigid metallic and/or non-metallic construction.

Fuel: A radioisotopic material (Sr-90) used to provide thermal energy for conversion in a thermoelectric generator.

Fuel Assembly: A combination of fuel elements arranged in a mechanical constraint providing for installation and locking into a suitable receptacle.

Generator: (RTG) A thermoelectric conversion unit providing electrical energy from isotopic fuel, installed within the payload.

Machine, Fueling: A semi-automatic, remote-controlled equipment with self-contained drives and positioning units used for transporting and installing fuel assemblies into generators from casks and vice versa.

DECLASSIFIED
CONFIDENTIAL
MMP-3393

~~CONFIDENTIAL~~

M-3

Payload: The upper portion of a vehicle containing the equipment intended to be launched on space mission by boost sections.

Site: The launch area, including facilities such as launch pad, service tower, umbilical mast, etc; used to accomplish launch mission.

Supplier: The designer and fabricator of the fuel handling system.

1.3 Deviations and Revisions. - This specification shall govern all design parameters affecting the interfaces as listed in Paragraph 3. Neither party to the interface shall revise any feature falling under this specification without concurrence of the other in writing.

In the event of conflict between this specification and any other specification or drawing in the 250 Watt (e) program, this specification shall govern.

2.0 APPLICABLE DOCUMENTS

2.1 Contractor Specifications

Power Supply System Specification
RTG Interface Specification

2.2 Vendor Specifications

Fueling System Equipment Specification

2.3 Other Specifications

Aerospace Corporation
1983.33-010 Fairing Information for Defense Comsat Program
1983.80-018 Launch Site Operations Restraints

2.2 Drawings. - The following drawings depict interface areas:

Generator/Fuel Interface (see Fig. VI-8)
Payload Configuration (see Fig. VI-2)
Service Tower Interface (see Fig. VI-1)

3.0 INTERFACE REQUIREMENTS

3.1 Generator/Fuel

3.1.1 Mechanical. - The fuel assembly shall be an integral unit consisting of several fuel elements mounted in a constraining structure

~~CONFIDENTIAL~~

MND-3293

DECLASSIFIED
~~CONFIDENTIAL~~

suitable for the shock and vibratory loads imposed by the vehicle launch and flight. This design is the responsibility of the RTG designer. The package shall be of rectangular cross-section approximately $4\frac{1}{2}$ " x 14 ", with a $4\frac{1}{2}$ " x $23\frac{1}{2}$ " face installed in the vertical plane. Gross weight shall not exceed 150 pounds.

The fuel assembly shall be restrained in the generator by an integral latching mechanism actuated by the fuel assembly loader. Proper installations shall consist of insertion, preload, actuation of locking fingers, and latching. Four (4) lock fingers engaging flanged areas of the receptacle housing shall be driven outward from the fuel assembly, and latched by means of mechanical cams driven by the fuel assembly loader. The latch arrangement shall provide an interlock preventing release of the latch except by correct engagement of the proper removal device. A guide arrangement incorporated in the generator design shall provide for correct alignment and orientation of the latching parts within an approach envelope of .25 inches radial eccentricity and 2.5° of axial misalignment, assuming worst case thermal expansion differentials.

The latch mechanism shall be capable of restraining a 10,000 pound axial preload between the fuel assembly and generator. The fuel assembly shall insert into the generator with a single straight line motion not exceeding 15 inches from initial engagement.

NOTE:*Represents the assumed configuration for a dynamically cooled fuel assembly/generator package. A statically cooled configuration essentially identical in method of engagement and latching different in overall package dimensions.

3.1.2 Thermal. - The fuel assembly is assumed to produce 4500-5500 thermal watts. The exposed radiating surfaces of fuel element shall have a maximum temperature of 1900°F in still air when confined in the generator. This temperature shall be reached after .5 hours without auxiliary payload cooling.

The generator may be cooled by static or dynamic heat rejection methods. If the latter case pertains, the maximum temperature at the fuel element shall be 1300°F .

The latch mechanism mounting surface shall, under the same conditions, reach maximum temperatures of 1000° static and 500°F dynamic.

Material selections for attaching parts of fuel assembly and generator shall be a responsibility of the RTG designer. The fueling system supplier shall be responsible for selecting appropriate materials in the attaching parts of the fueling machine.

DECLASSIFIED
~~CONFIDENTIAL~~
MND-3393

CONFIDENTIAL

M-5

3.1.3 Radiation. - The fuel element shall consist of approximately 700 Kc of Sr-90 isotope. The unshielded dose rate for this source is approximately 10^4 r/hr. at one foot.

3.2 Shipping Cask/Fuel. -

3.2.1 Mechanical. - The fuel assembly shall be installed, and locked, into the shipping cask in exactly the same manner as in the generator. The mechanical loads imposed on the cask by the fuel assembly shall be determined by the weight of the fuel assembly and transport shock and vibration loads. The mechanical design of this area is the responsibility of the RTG designer.

3.2.2 Thermal. - Exposed radiating surfaces of fuel elements shall have a maximum temperature of 1330° F in still air when confined in the cask.

In the case of a dynamic cooling system, the equilibrium temperature of the fuel core shall be 820° F.

The latch mechanism mounting surface shall, under the same conditions, not exceed temperature of 180° F.

3.2.3 Radiation. - The cask shielding shall be designed to comply with applicable AEC and ICC regulations for storage and shipment of radioisotopes. The shielding design shall further permit an acceptable weekly dose rate for personnel operating at one meter from the cask surface without supplementary shielding. Personnel shall receive a maximum dose rate of 10 MR/hour, restricting access to 10 hours/week, or a total dose of 100 MR/week. Shielding design shall be the responsibility of RTG designer.

3.2.4 Operational. - In consideration of variant requirements for shipping and machine storage casks, the basic shield cask may be supplemented with a removable shipping jacket or container to be supplied with the cask.

3.3 Fuel/Machine. - The fueling machine, specifically, the Fuel Assembly loader, shall engage, unlock, remove, transport, install, lock and disengage the fuel assembly, whether in the shipping cask or generator receptacles.

The fueling machine supplier shall design the engaging and locking devices in conjunction with the fuel assembly designer in compliance with the interfaces described in Paragraph 3.1 and 3.2. The machine shall be designed to meet the requirements of either the static or dynamic cooling system configuration.

CONFIDENTIAL

MDR-3393

037029.030

~~CONFIDENTIAL~~
CONFIDENTIAL

The installation preload requirements of the fuel assembly shall be generated by the fueling machine by reaction in the machine so as to limit reactive forces in the payload to 200 pounds.

This load shall be applied at Agena Station 190 (approx.) and is subject to Agena and Atlas contractor approval. Sway restraint reaction is assumed at Agena Station 260 (approx.) with maximum reactive capacity of 300 pounds.

The fuel assembly loader shall effectively surround, cover or shield the fuel assembly so that accidental collision may be cause rupture or dislodgement of the gripping device. The overall envelope of the cover shall not exceed 11"W x 24"H x 18"D.

3.4 Cask/Machine. - The fuel shall be transported to the machine in a shipping cask. By agreement of both the shielding designer and the machine designer, a supplementary jacket or removable container may be incorporated in the cask design to enable reduction of machine envelope and weight.

The cask shall be mounted in relation to the fueling machine so as to ensure a fixed coordinate or polar reference dimension to the machine degrees of freedom. The cask may be a removable part of the machine proper. Maximum erected weight shall be 18,000 pounds, overall dimensions are not restricted.

The cask closure shall be actuated by a separate device incorporated into the cask support and attached at the time of assembly into the machine. Access envelope at the cask door shall be sufficient to ensure unimpeded entry of the fuel assembly loader portion of the machine within the limits as shown in Paragraph 3.1.1, except that maximum envelope dimensions of the loader protective housing shall be 11" x 24".

The cask door shall be designed to open within a clearance dimension of 28" from the face of the fuel assembly attachment flange.

3.5 Payload/Machine. - The payload arrangement shall be a responsibility of the RTG designer in conjunction with the payload contractor. Packages shall be located within 1/8 inch of true position and deflect not more than 1/16 inch when subjected to 200 lb. maximum load in any coordinate.

3.5.1 Fairing Mounted Package. - In the event that a dynamic cooling system is employed for the RTG, the payload fairing may be used as a thermal sink and radiator. This implies that the fairing may remain with the payload, and that the fairing closure may be an integral part of the fuel/generator package.

~~CONFIDENTIAL~~
CONFIDENTIAL

AND-3393

~~CONFIDENTIAL~~
CONFIDENTIAL

0145087030
~~CONFIDENTIAL~~

M-7

In this instance, the fueling machine source loader shall engage the fuel assembly, attachment device, and fairing closure as a single integral part. The closure shall not require separate latching arrangements. The closure penetration to permit access to the fuel assembly latch shall be subject to design acceptance of the payload and fairing contractor.

3.5.2 Independent Mounted Package. - In the event a static heat rejection system is employed for the RTG, heat transfer requirements are likely to dictate a deployable fairing to permit direct radiation from the package. In this case the fairing closure shall not be an integral part of the fuel assembly, but a secured part of the fairing proper.

The fairing opening shall be of adequate size to permit free access of the fueling machine and fuel assembly within the approach envelope as specified in Paragraphs 3.1.1, and 3.3.

Suitable latching devices shall be provided for the closure such that engagement will be automatic when the door is in shut position. The door shall be spring loaded to return to fully open position on either failure of the latch, or on deliberate actuation of a latch release device. The door shall remain fully open against loads equivalent to a 50 knot wind. The fairing designer shall specify the closing force or moment necessary to complete door closure, but in no case shall applied force exceed 50 pounds on any point on the door surface.

The force necessary to actuate the latch release shall be 25 pounds maximum. Method of actuation shall be a straight line motion normal to the fairing. The striker shall be of sufficient size to accommodate a relative displacement between striker and actuator of $\pm 1/2$ inch radial and 10° angle. The release striker shall permit a minimum of 2 inches overtravel in the direction of actuation, and be flush with the joining in the unactuated state.

The latch release shall be displaced from the closure which it operates by a sufficient distance to permit free opening of the door without relocation of the release actuating device. An optional method of payload access shall be recommended by the fairing designer to circumvent latch release failure.

3.5.3 Mechanical Position Reference. - Suitable recessed receptacles shall be provided by the fairing contractor, in location and detail configuration specified by the fueling machine supplier. These receptacles shall be used to facilitate relative location determination between payload and fueling machine. Locations of receptacles shall be referenced to generator/fuel assembly centerline within $\pm 1/8$ inch. Maximum mechanical load induced at receptacles shall be 25 pounds.

~~CONFIDENTIAL~~

MND-3393

0145087030

DECLASSIFIED
~~CONFIDENTIAL~~

3.5.4 Visual Position Reference. - Suitable reference marks, intended for visual collimation of fueling machine and payload shall provide by fairing contractor in locations and configurations determined by the fueling machine designer. Typical locations are shown on AMF dwg. 89-92-SK4091.

3.6 Vehicle/Machine

3.6.1 Position. - The assumed launch vehicle is the Atlas-Agena D with a NIMBUS-EOGO type fairing. This puts the payload area at an elevation of approximately 100 feet above the vehicle launch restraints. Considering the moment capability of the launch restraints and the flexure of the vehicle, a maximum unrestrained load of 200 pounds shall be applied by the fueling machine at the payload area in a direction normal to the fairing along any axis. The load is to be applied through the generator mounting.

3.6.2 Stability. - The Atlas-Agena maximum deflection from the vertical is assumed to be 2.5 inches at Station 200 with a frequency of .4 cycles per sec. This deflection, due to various wind and loading effects, is considered to be the sum of a steady-state wind load with a superimposed variable load due to aerodynamic flutter induced by velocity and azimuth wind transients. Approximately 1/2 inch deflection in -x direction at Station 502 is due to warpage after LOX tanking when measured at Station 502. The Agena is assumed loaded.

3.6.3 Operational Restraints. - All isotopic fueling operations shall be accomplished prior to loading of Atlas LOX. However, in the event of a launch emergency, and it is impossible to off-LOX; Sr-90 fuel assemblies must be removed under explosive conditions.

No fueling operations shall commence in winds greater than 20 knots unless sway restraint can confine total amplitude of motion to 1/2 inch, with umbilical sails not deployed.

Fueling machine loading axis shall be in the X-X direction with respect to the vehicle. See payload configuration drawing Fig. VI-1, etc., for definition of coordinate axes.

Sway restraint loads imposed by the fueling system shall be developed at an appropriate station level on the launch vehicle near the payload attachment. Such loads shall not exceed a maximum load determined by the Agena contractor. Load distribution information shall be generated by the fueling machine supplier and accepted by the appropriate interface parties.

3.7 Site/Machine. - The launch site shall consist of the launch complex and other range facilities utilized in the performance of an isotope fueled generator mission.

DECLASSIFIED
~~CONFIDENTIAL~~
MND-3393

~~CONFIDENTIAL~~

M-9

Ground support equipment required to transport, assemble, erect and service the fuel handling system shall be considered site-available equipment. Special handling devices required for transport, assembly, installation and recovery of isotopic fuel assemblies shall be considered a part of the equipment specified and furnished by the fueling system supplier.

3.7.1 Site Requirements. - As a result of the unique requirements by the isotope fuel handling problem modifications must be made at the selected launch site. These include, but are not limited to:

- Installation of air and electric power service
- Installation of control and instrumentation cabling
- Installation of control equipment in blockhouse or other locations specified by fueling machine contractor
- Installation of nuclear instrumentation
- Installation of remote controls and modification to site equipment where nuclear hazard precludes manual or local operation, i. e. , umbilical wind sails and cable take-ups
- Modifications to launch procedures, countdowns, maintenance and service procedures, and safety regulations

For discreet values, locations and procedural requirements refer to Equipment specification.

3.7.2 Service Tower Modifications. - The fueling machine and cask support rack shall be supported at the payload elevation on the service tower.

The service tower shall be modified structurally to provide the fueling machine with a rigid mounting and operating clearances as specified by the fueling machine supplier.

Air lines and electrical power and instrumentation cabling shall be installed as required by fueling machine design.

Radiation protection equipment shall be added to the tower, such as shadow shielding at tower truck control cab, etc.

Power and instrumentation disconnects shall be relocated or re-motized to enable operation and service under radiation conditions.

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED
~~CONFIDENTIAL~~

3.7.2 Service Tower Modifications (cont.). - Service tower movement system shall have provisions to permit local or remote re-positioning within $\pm 1/2$ inch of nominal launch vehicle or pad centerline.

A surveillance system consisting of closed circuit television cameras and monitors shall be provided by the fueling machine supplier for installation on the service tower.

For definition of responsibilities refer to the Equipment specification.

3.7.3 Operational Restraints. - The mode of fuel insertion is along the X-X axis, that is, from the NORTH SIDE of the erected vehicle. Refer to payload configuration interface drawing. RTG elevation shall be a minimum of 5 feet above the top of the umbilical mast. This allows a clear removal path for the service tower with fueling machine in place.

At all times during the exposure of the fuel assembly from the shield cask a radiation level exists within a 1200 foot radius of the fuel assembly of 2.5 Mr/hr. Rigorous safety procedures under supervision of a qualified health physics staff are required to insure minimal hazard to launch area personnel. Restricted area plots shall be set up and monitored for radiation level at all times that fuel assemblies are on the launch site.

3.7.4 General. - The foregoing interface data is predicated on the use of PMR Palc No. 1. In the event that a change of site or launch vehicle is made, all interface data shall be reviewed and revised as required to insure appropriate restraints are incorporated in the fuel handling system design.

~~CONFIDENTIAL~~
DECLASSIFIED
MND-3393

EQUIPMENT SPECIFICATION

1.0 SCOPE

1.1 Scope. - This specification covers semi-automatic, remote controlled handling systems for use in installing Sr-90 radioisotopic fuel assemblies in thermoelectric power supplies intended for space applications.

2.0 APPLICABLE DOCUMENTS

2.1 Government Documents. - The following documents of the issue in effect on date of invitation for bids or request for proposal, form a part of the specification to the extent specified herein. In the event of conflict between this specification and any document referenced herein, this specification shall govern.

SPECIFICATIONS

Military

MIL-R-27542	Reliability Programs
MIL-I-26600	Interference Control Requirements
MIL-Q-9858	Quality Program Requirements
MIL-W-8611	Welding, Metal Arc and Gas, Steels and Corrosion and Heat Resistant Alloys - Process for
MIL-E-4970	Environmental Testing, Ground Support Equipment, General Specification for

STANDARDS

Military

MS 33586 (ASG)	Metal, Definition of Dissimilar
MIL-STD-803	Human Engineering Criteria for Aircraft Missile and Space Systems, Ground Support Equipment
MIL-STD-810	Environmental Test Methods

DECLASSIFIED

~~CONFIDENTIAL~~

PUBLICATIONS

National Bureau of Standards

Handbook H28

Screw Thread Standards

USAF

MCP71-650

Ground Support Equipment, Provisioning

2.2 Other Publications. - The following documents form a part of this specification to the extent specified herein. Unless otherwise indicated, the issue in effect on date of invitation for bid shall apply.

2.2.1 Specifications

Environmental Specification Aerospace Corporation. -
1931.70-014

Power Supply System Specification

Interface Specification

(Copies of the above documents may be obtained from the
procuring activity or as directed by the contracting officer.)

3.0 REQUIREMENTS

3.1 Interface Data. - All interface data shall be controlled by the
Interface specification.

3.1.1 Mission. - Unless otherwise specified in the procurement document, equipment supplied under this specification shall be designed to support an aerospace mission. This mission shall require the timely installation of a radioisotopic fuel assembly into a thermoelectric generator. Launch window and other mission criteria dictate that all procedures be reversible within minimum time boundaries consistent with reliable operations.

3.1.2 Launch Site and Facilities. - Unless otherwise specified in the procurement document, equipment supplied under this specification shall be designed to be compatible with the particular launch site and facilities specifically referenced in the interface specification. The procuring agency may specify any additional launch site and facility constraints not contained in the interface specification at the time of invitation for bid to this specification.

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

0110001001
~~CONFIDENTIAL~~

M-13

3.1.3 Vehicles and Payload. - Unless otherwise specified in the procurement document, the launch vehicle and payload configuration as shown in the interface specification shall govern the arrangement and general design of the fuel handling equipment.

3.1.4 Fuel Assembly and Generator. - Unless otherwise specified in the procurement document, the Fuel Assembly and generator arrangement shown in the interface specification shall govern the detail design of the fuel handling machine. The procuring agency will specify, at the time of invitation for bids, which design alternatives allowed by specification shall be used.

3.1.5 Environment. -

3.1.5.1 Ambient Conditions. - The entire fueling system shall be designed to withstand, without deleterious effects on reliable operation, the pre-launch environmental conditions as specified in Aerospace Corporation Document No. 1931.70-014, Environmental Conditions.

3.1.5.2 Incident Radiation. - Portions of the fueling system will be exposed to radiation from unshielded strontium-90 sources. Unless otherwise specified in the procuring document, dose rates in accordance with the interface specification shall be the governing factor in material selections or other detail design considerations involving radiation.

3.1.6 Interface Responsibility. - The supplier of the fuel handling system shall be responsible for establishing all constraints on such interface factors as: role of human workers, time of machine performance, modifications to launch site, detail arrangement and location of controls, personnel safety, and any other requirements not specified in the interface specification. The supplier shall be responsible for maintaining liaison with the procuring agency to assure correct and timely exchange of interface data.

3.2 Performance Characteristics. -

3.2.1 General Design. - The fueling system shall be capable of transferring one or more fuel assemblies from shield casks to payload receptacles through use of a semi-automatic, remote-controlled fueling machine. Auxiliary equipment required to assure timely and correct transfer shall be integrated into the control system for the fueling machine functions.

3.2.2 Operations. - The fueling system shall be designed to accomplish the functions as shown in Table I. The sequence of operations, and methods of confirming correct actuation may be modified by the supplier to suit detail design considerations only if the over-all reliability of the fueling system can be demonstrably improved. The operating cycle shall start from the following conditions:

CONFIDENTIAL

MND-3393

0110001001

~~DECLASSIFIED~~
~~CONFIDENTIAL~~

- (a) Vehicle unrestrained except for hold down jacks.
- (b) Service tower positioned on vehicle centerline within 1/2 inch.
- (c) Fueling machine assembled on service tower mount.
- (d) Shield cask(s) positioned in service tower.

TABLE I

<u>Function</u>	<u>Method of Verification</u>	
	<u>Visual</u>	<u>Instrument</u>
1. Actuate sway restraint on vehicle	x	x
2. Position machine at cask(s)	x	x
3. Open cask door(s)	x	
4. Position machine to locate at fuel assembly	x	x
5. Engage and lock guide rods		x
6. Engage fuel assembly in machine loader		x
7. Release fuel/receptacle lock		x
8. Release guide rods		x
9. Withdraw fuel assembly		x
10. Reposition machine at payload	x	x
11. Open fairing door (See Note A)	x	x
12. Engage and lock guide rods		x
13. Insert fuel assembly in receptacle		x
14. Engage fuel/receptacle lock		x
15. Disengage fuel assembly from loader		x
16. Release guide rods		x
17. Withdraw machine	x	x
18. Close fairing door (See Note A)	x	
19. Disengage sway restraint	x	x
20. Remove service tower to storage position	x	

NOTE (A) Fairing closure may be an integral part of the fuel assembly.
Refer to interface specification for detail requirements.

~~DECLASSIFIED~~
~~CONFIDENTIAL~~
MND-3393

~~CONFIDENTIAL~~

M-15

3.2.3 Reversible Operations. - The fueling machine shall be designed to perform the operational sequence in reverse from any point in the order of events. Any sequence interlocks designed to assure correct normal operation shall be provided with suitable over-ride mechanisms to obtain this reversability. The handling system shall be designed to perform the operations of defueling (transfer fuel assemblies from payload to cask) as a normal operating sequence.

3.2.4 Operating Speeds. - All fueling machine linear motions shall be single speed driven at a nominal two (2) feet per minute. All angular or rotational motions shall be single speed driven at a nominal two (2) revolutions per minute.

3.2.5 Operating Loads. - The fueling machine shall be capable of transporting a fuel assembly weighing a maximum of 150 pounds.

3.2.6 Shock and Vibration. - When transporting or handling the fuel assembly, and installing the fuel assembly into the payload, the shock and vibration loads imposed by the fueling machine shall be limited to the following:

Shock, any axis	2 g
Vibration, any direction, 0-45 cps	2 g peak

3.2.7 Set-Up and Checkout Operations. - The equipment supplier shall be responsible for establishing all procedures necessary to insure that the initial machine installation complies with requirements for position, level and altitude.

Static alignment of the position transducers, machine carriage, and sway restraint assembly shall be accomplished using the actual measured locations of the respective items on the launch vehicle payload.

Local controls for the four machine carriage drives shall be utilized for setting of limit switches and stops, and for verification of machine positional settings with the remote control console.

3.3 Equipment Configuration. -

3.3.1 General. - The basic fueling machine shall be a service tower mounted device. The service tower shall be used to position the machine in a predetermined location which facilitates the transfer of fuel assemblies. The shield cask(s) shall be mounted in the service tower in a position which is accessible to the fueling machine for proper engagement of the stored fuel assemblies. The fueling machine shall be a "Traveler" type, that is, it shall be mounted in a carriage pro-

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED
~~CONFIDENTIAL~~

viding three coordinate axes of motion and an azimuthal drive. A single gripping and actuating device, mounted on this carriage, shall be designed to perform the necessary operations with the fuel assembly(ies) as required by Table I. The fueling machine shall be designed substantially in conformance with Fig. VI-1.

3.3.2 Equipment Components. - One fuel handling system shall consist of the items in quantities as shown in Table II.

TABLE II

<u>Component Name</u>	<u>Quantity/Set</u>
Position Transducer	2
Sway Restraint Assembly	1
Shield Cask	1 (See Note A)
Cask Support Assembly	1
Fueling Machine	1
Fueling Machine Support Bracket	1
TV Surveillance Camera W/ Monitors	3
Fairing Closure Actuator Assembly	1 (See Note B)
Operator Control System	1
Service Tower Remote Connector	1
Radiation Detection and Signalling Equipment	1

NOTE (A) The Interface Specification shall govern the number and size of shield casks required based on fuel assembly design.

NOTE (B) The requirement for fairing door actuators is dependent upon fuel assembly design.

3.3.3 Space Envelope. - The service tower mounted components of the Fuel Handling System shall be designed to accomplish the transfer functions within the space envelope as shown in the Interface Specification. Minimum operating clearances of three (3) inches shall be main-

DECLASSIFIED
~~CONFIDENTIAL~~
MFD-3393

0915087030
~~CONFIDENTIAL~~

M-17

tained between all parts in relative motion to tower structure and such stationary structure. The shield cask shall be located 180° in machine azimuth from the payload location, at the same elevation, and equally spaced from the machine azimuth centerline as the payload.

3.4 Design Requirements. -

3.4.1 General Design. -

3.4.1.1 Materials. - Materials used in the manufacture of the Fuel Handling System shall be of high quality and suitable for the intended purpose. MIL-STD-143 shall be used as a guide in the selection of suitable specifications and standards for all materials, parts, processes and equipment.

3.4.1.1.1 Metals. - Metals used shall be corrosion-resistant types or suitably protected against corrosion to the extent required by environmental conditions. The use of dissimilar metals as defined in MS 33586 shall be avoided.

3.4.1.1.2 Non-Metals. - Organic materials such as rubber or plastics shall be avoided or used with caution due to radiation levels encountered. Wood or wood products shall not be used.

3.4.1.1.3 Lubricants. - Lubricants adversely affected by gamma radiation shall be avoided. Dry film lubricants shall be selected in preference to liquid or semi-liquid types.

3.4.1.1.4 Bearing Surface. - All sliding or rotating bearing surfaces shall be fabricated from corrosion resistant materials or equivalent.

3.4.1.2 Parts. -

3.4.1.2.1 Commercial Parts. - AN and MS parts shall be used where standard commercial parts are not available for a particular application.

3.4.1.2.2 Parts Specifications. - All parts specified for use in this equipment shall comply with the detail requirements of this specification. Exception to these requirements may be taken only in the case where qualified AN or MS parts suitable for the application do not comply in all particulars as to materials and finish.

3.4.1.3 Finishes. - All finishes shall be specified to meet the environmental conditions per 3.1.5.

3.4.1.4 Threads. - All threads shall conform to National Bureau of Standards Handbook H28. Unified or American National Thread Series

~~CONFIDENTIAL~~

MND-3393

0915087030

DECLASSIFIED

~~CONFIDENTIAL~~

shall be used for threaded parts or fasteners. Special thread pitches and diameters shall not be used for fasteners. Power screws and jacks shall use Acme threads wherever required.

3.4.1.5 Hydraulics. - No hydraulic components shall be used in this equipment.

3.4.2 Detail Design Requirements. -

3.4.2.1 Position Transducer. - A mechanical-electrical position transducer shall be provided to determine and display the relative location of the fueling machine to the payload. The transducer shall be mounted on the fueling machine so as to maintain a fixed but manually adjustable position with respect to a fuel assembly carried in the machine. Two such transducers, located and arranged to sense machine alignment to the payload in the three coordinate axes of motion and in azimuth, shall be provided.

3.4.2.1.1 Transducer Range. - The transducer shall have a minimum longitudinal stroke of 12 inches. In addition, gymbal action of the plunger shall provide for a minimum conical displacement of 5° included angle. Maximum induced longitudinal load shall be 25 pounds.

3.4.2.1.2 Transducer Accuracy. - The mechanical to electrical conversion and read-out shall have a maximum total error equivalent to .05 inches of stroke and .2° in angle.

3.4.2.1.3 Transducer Package. - A transducer package substantially in conformance with Fig. VI-5 shall be considered to meet the requirements of this specification.

3.4.2.2 Sway Restraint Assembly. - A resilient sway restraint mechanism shall be provided to reduce relative motion between the launch vehicle and the service tower mounted machine. The restraint shall be a positive locking collar remotely operated by air devices. An inflatable boot shall be used to engage the launch vehicle. The residual relative motion shall have a maximum total amplitude of 1/2 inch in the horizontal plane.

3.4.2.2.1 Restraint Range. - The mechanism shall be capable of engaging a diameter of 65 inches within a range of 5 inches maximum total eccentricity. Engagement and lock-on shall not cause the launch vehicle to deflect from its static centerline by more than 1/2 inch. Maximum induced load on the vehicle shall be 300 pounds.

3.4.2.2.2 Restraint Assembly Package. - A restraint mechanism substantially in conformance with Fig. VI-4 shall be considered to meet the requirements of this specification.

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

CONFIDENTIAL

0315087030

M-19

3.4.2.3 Shield Cask. - The shield cask for the storage and transport of fuel assemblies shall not be provided by the fuel handling system supplier. Interface specification requirements shall be observed by the handling system supplier in the general design of the system.

3.4.2.4 Shield Cask Support Assembly. - A support assembly consisting of rigid structural members and cask door actuators shall be provided with the handling system. The support members shall be designed to be compatible with the service tower structure, and shall support the shield cask loads in such a manner as to facilitate installation of the casks utilizing the service tower gantry crane. A typical cask design is shown in Fig. VI-3.

The door actuating devices shall be air operated by remote control. Suitable sensing devices shall be provided to signal both open and closed condition. No provisions for locking or unlocking of shield cask doors shall be required.

The handling system supplier shall be responsible for the design of a secure method of attachment of the support assembly to the service tower.

The cask support shall have provisions for manually adjusting the cask position, level and attitude with respect to the machine.

The equipment designer shall be responsible for compliance with all interface requirements of the cask supplier and the service tower contractor.

3.4.2.5 Fueling Machine. -

3.4.2.5.1 Machine Drive System. - For the purposes of this specification, the three coordinate axes of machine motion shall be defined as follows:

"X" axis = generally North-South line, + "X" to North.
"Y" axis = generally East-West line, + "Y" to West.
"Z" axis = vertical line, + "Z" is up.

The pitch and yaw axes are parallel to the "Y" and "Z" axes respectively. Azimuth motion shall be in the horizontal plane, with position direction defined as clockwise when viewed from above.

The machine drive system shall consist of four (4) independent drive trains to propel the fuel assembly gripping device in the X, Y, Z and azimuth directions. The drives shall be arranged such that the sequence of independent motion proceeds from the service tower support through the "Y", Azimuth, "X", and "Z" motions in that order to the gripper.

Each coordinate drive shall consist of a three phase AC induction type motor direct coupled to a mechanical power train which

CONFIDENTIAL

MND-3393

0315087030

~~DECLASSIFIED~~
~~CONFIDENTIAL~~

propels the machine carriage. All drive motors shall be provided with motor end electrical brakes. The drives shall be reversible in operation. The "Z" drive shall be self-locking in the final drive stage in the event of power train failure.

Drive ranges shall be sufficient to comply with payload configuration dimensions as specified in Interface Specification. Positive limit steps shall be provided on all drive carriages in addition to motor cut-out limit switches.

3.4.2.5.2 Machine Position Readout System. - Each of the four machine drives shall be provided with a position sensing device. This device shall be arranged to pick off relative motion between the successive drive stages, but shall not be installed as part of the drive power train. Over-all readout error at the position display shall not be greater than $\pm 1/4$ inch or 1° of angle. Sensing devices shall be suitable for readout on a digital display.

3.4.2.5.3 Fuel Assembly Gripper. - The operations of engaging the fuel assembly, locking and unlocking of latching mechanisms, insertion in cask or payload, and preloading of fuel assembly insulations or release springs shall be provided in a gripper assembly.

The gripper shall be capable of supporting rigidly a gross fuel assembly weight of 150 pounds.

The gripper assembly shall be provided with suitable mechanisms which will produce the positional and loading requirements of the Interface Specification. The gripper mechanisms may be operated by air or electro-mechanical actuators. Hydraulic actuators shall not be used.

The gripper head shall be provided with a protection cover, shield, or bonnet which shall prevent accidental dislodgement of the fuel assembly due to impact with other objects. See 3.4.3.

The gripper shall be mounted on a resilient gimbal mount which shall minimize reactive forces on the fuel assembly due to insertion misalignment.

The gripper mount shall be capable of elastically absorbing up to 3 inches of longitudinal overtravel in the machine "X" drive with a reactive load of not more than 50 pounds.

The gripper mechanism, gimbal mount and overtravel absorber shall be provided with appropriately located limit sensing devices which shall signal end positions of all motions and operations.

~~CONFIDENTIAL~~

~~DECLASSIFIED~~ MND-3393

3.4.2.5.4 Cooling Package. - The fueling machine supplier shall be responsible for incorporating, if required, a cooling system in the gripper assembly. The capacity shall be sufficient to avoid deleterious effects on operation of the fuel assembly and gripper mechanism under worst case temperature conditions as specified in the Interface Specification. Cooling medium may be air or inert gas.

3.4.2.5.5 Electrical Service. - The fueling machine supplier shall be responsible for furnishing electrical and control circuit connections to the fueling machine from the service tower base. All connections shall be protected from flexing due to extreme machine motions.

3.4.2.6 Fueling Machine Support Bracket. - A structural steel support bracket shall be provided for mounting the fueling machine in the service tower. The bracket shall be designed to contain the fueling machine within position boundaries in a rigid manner. Live and dead loads due to machine weight, wind pressure, accelerations, and reaction of insertion loads shall be transmitted into main load carrying members of the service tower. All stress and deflection calculations shall comply with best structural engineering practices including suitable factors of safety.

Suitable rails or tracks shall be provided in the support bracket for mounting the "Y" drive carriage.

3.4.2.7 TV Surveillance System. - A closed circuit television system of three cameras and three monitors shall be provided for remote visual surveillance of all fueling operations. The system shall include two remotely controlled cameras with pan, tilt and zoom controls for continuous area surveillance; on separate monitors and one variable focus fixed camera collimated to the gripper assembly for gross alignment and operation monitoring. Suitable floodlighting shall be provided to assure adequate illumination levels during day or night operations. Camera controls shall be located on the control console.

3.4.2.8 Fairing Closure Actuators. - Suitable actuators shall be provided for opening and closing fairing doors on the payload. Actuators shall be submounted on the gripper assembly. Actuators may be air or electro-mechanical operated. Range of stroke, load capability, position, and method of operation shall be consistent with requirements of the Interface Specification.

3.4.2.9 Operator Controls. -

3.4.2.9.1 Remote Control Console. - An integrated control console shall be provided for operation, surveillance and checkout of the Fuel Handling System. The console shall be suitable for installation

DECLASSIFIED
~~CONFIDENTIAL~~

within the launch control building at the selected launch site. The console shall be arranged for ease of operation by one individual. Human factors engineering shall be of prime concern in the console design. "Human Engineering Guide for Equipment Designers" (University of California Press, 1960) shall be utilized to optimize the console design. See 3.4.4.

It shall be a specific requirement that machine drive control switches be three position, spring return to "STOP", pistol grip type.

TV monitors shall be integrated in the console design.

All main power-on switches, over-rides or interlock bypass switches shall be key-locked.

A key locked permissive switch shall be provided for switching machine drive controls to a local control station.

Actuation of the local control permissive shall lock out all remote controls for the machine drives, fuel assembly gripper and sway restraint assembly.

3.4.2.9.2 Local Control Station. - A local pendant-type control switch station shall be provided at the fueling machine support bracket area. This station shall have provisions for control of the four machine positioning drives only, to be used for local control during set-up, check out, calibration of transducers, collimation of TV cameras and adjustment of drive position detectors.

A green signal light shall be provided on the switch station to indicate when local control permissive is in effect.

3.4.2.10 Power and Control Cabling. - Cabling to motors, actuators, controls, limit switches, transducers, etc., shall be festooned or supported by reel-type takeups. No conduit or metallic raceways shall be used except where cabling alone would be exposed to mechanical damage from moving parts. Multiconductor cabling shall be used wherever possible, except where space or routing requirements dictate single conductor harnessing. Cabling from service tower base to machine shall be provided with suitable redundant circuits to meet reliability requirements under environmental conditions.

3.4.2.11 Grounds. - Static grounds of all 220 VAC or higher voltages shall be directed to earth ground by bus bar connection to the service tower. Tower voltages may be grounded by bare conductor to the machine.

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

CONFIDENTIAL

M-23

3.4.2.12 Service Tower Remote Connections. - An umbilical connector of suitable circuit capacity shall be provided. Connector shall be designed for redundant circuit capability, and provisions made for local or remote operation under adverse environmental conditions. Connector shall be capable of proper engagement within $\pm 1/2$ inch of nominal launch pad to service tower alignment.

3.4.2.13 Radiation Detection. - The equipment supplier shall furnish four (4) devices suitable for gamma radiation detection to be located on the fueling machine, service tower at payload elevation, at the service tower base, and at the fuel storage area. These devices shall provide visual indication of radiation levels and audible alarms in the event levels exceed permissible values during fueling operations.

3.4.2.14 Pneumatic Power Package. - The Fuel Handling System shall be provided with a suitable air supply system sufficient for the needs of the sway restraint and other air actuated devices incorporated in the Fuel Handling System design. Operating power for the compressor shall be drawn from the service tower electrical system provided by the Fuel Handling System supplier.

3.4.3 Reliability. -

3.4.3.1 Service Life. - Equipment supplied to this specification shall have a minimum service life of 100 hours without major overhaul. Preventive maintenance and minor component replacement, lubrication, and adjustment provisions shall be based on a minimum operating cycle time of six hours under worst combination of conditions of environment per 3.1.5.

3.4.3.2 Redundancy and Derating. - All components subject to wear, degradation of strength, insulation capability or corrosion-resistance, whether due to effects of environment, relative motion or radiation shall be suitably derated from their nominal design limits. Derating shall be accomplished by applying a suitable multiplier to the maximum design load. This shall produce a calculated value which when applied to the deteriorated component in question shall yield a safe condition at end-of-life. At the option of the supplier, and subject to approval by the procuring agency, parallel or series redundant members, each of capacity not less than a single safe member may be used in lieu of derating.

3.4.3.3 Fail-Safe Features. - The equipment supplied shall be fail-safe in the ability to engage and disengage the fuel assembly from the receptacle latch. In addition, the portion of the fueling machine directly supporting, containing or gripping the fuel assembly shall be incapable of releasing the fuel assembly except under condition of correct engagement in the proper receptacle. Other fail-safe features incorporated in the design shall not be at the expense of basic machine simplicity and ease of operation.

CONFIDENTIAL

MND-3393

DECLASSIFIED

~~CONFIDENTIAL~~

3.4.3.4 Reliability Plan. - A reliability program shall be developed by the equipment supplier in accordance with MIL-R-27542 as applicable to ground support equipment.

3.4.4 Human Factors. - The design of the fueling system shall contain provisions for remote control of the fueling machine on a semi-automatic control mode. A human operator shall be utilized as the connecting link between successive machine operations. This operator shall monitor, both visually and by means of remote electrical indicators, the proper completion of machine motions and actuations. The operator shall be responsible for initiating all machine functions on confirmation of correct position. MIL-STD-803 shall be the general design guide.

3.4.5 Equipment Interference. - All electrical systems shall be designed to minimize conducted or radiated electromagnetic or electrostatic interference signals which may affect payload or telemetry electrical equipment operations. The equipment designs shall be responsible for determining maximum acceptable decibel levels for the equipment in compliance with MIL-I-26600 as applicable to ground support equipment.

3.4.6 Workmanship. - The workmanship of the Fuel Handling System shall be of sufficiently high quality to insure satisfactory operation consistent with the requirements of this specification. Visual defects not consistent with the method of fabrication shall be cause for rejection of the item for rework or replacement.

3.4.7 Finish. -

3.4.7.1 Mechanical Finish. - All exposed fabricated metal parts shall be free from burrs, excessive weld spatter or corrosion products. Structural members shall be cut and welded in accordance with good commercial practice.

3.4.7.2 Protective Finish. - All exposed metal surfaces shall be cleaned to remove dust, scale, dirt, lubricants, etc., by any suitable means not resulting in the deposit of possible contaminants. Stainless steel surfaces shall not be wire brushed.

All carbon steel surfaces shall be thoroughly cleaned and given two coats of a good quality rust inhibiting primer. Assembly surfaces shall be protected with a rust preventive coating.

All aluminum parts shall receive a suitable paint base primer coat of "Iridite" or equivalent.

All exterior surfaces shall be given two coats of good quality grey machinery enamel, except for the fuel gripper head cover.

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

~~CONFIDENTIAL~~

03 05 87 030

M-25

3.4.8 Nameplates and Markings. - The end item and each replaceable major assembly or component shall be clearly and permanently marked with the manufacturers name and part number. In addition, the end item shall have a metal nameplate affixed in a prominent location containing the unit nomenclature, serial number, and parts list or technical manual number.

3.4.9 Maintenance and Accessibility. - All items subject to wear and tear in normal operation shall be designed for ease of maintenance. Lubrication fittings, assembly hardware, and accessibility of the part for replacement shall be capable of removal from the equipment without disassembly of other major items.

3.4.10 Special Tools. - Requirements for special tools shall be avoided in favor of standard hand or power operated tools. Special consideration shall be given to use of standard tools for such functions as assembly and disassembly, adjustments and calibrations, and emergency recovery or removal of failed parts.

4.0 Quality Assurance Provisions. -

4.1 Inspections Requirements. - The FHS supplier shall be responsible for the performance of all inspections requirements prior to submission for Martin inspection and acceptance. Inspection requirements shall be as specified in MIL-I-45208A.

4.2 Testing. -

4.2.1 General. -

Tests performed on equipment furnished under this Specification shall consist of qualification tests, and acceptance tests to assure equipment performance in accordance with the design requirements. Qualifications tests shall be performed on sub-components to verify design adequacy and to demonstrate a minimum of equipment capability and reliability. The tests are intended to evaluate performance of equipment and are intended to be more severe than field conditions in order to provide better assurance of locating faults and to compensate for the statistical limitations of small sample sizes. Qualification test conditions are not intended to be severe enough to exceed reasonable safety margins. Acceptance tests are intended to demonstrate proper functioning and performance of the equipment prior to delivery. These tests are comparable to field environment in severity, but are intended to be mild enough to avoid fatigue, or wearing out of the equipment, yet severe enough to detect and eliminate premature failures. At completion of test components shall be restored to as new condition.

4.2.2 Test Methods. - Tests required hereunder may be per-

~~CONFIDENTIAL~~

MND-3303

03 05 87 030

~~CONFIDENTIAL~~

formed on individual sub-components and on sub-components assembled into sub-assemblies. The pattern of testing will originate with the smallest practical component test and culminate with an overall system test.

Required tests may be performed separately, or where practicable in combination with each other. The sequence shall be considered unspecified. However, the sequence of tests as actually accomplished shall be documented in test reports. .

4.2.2.1 Measurements. - Instruments and test equipment used in test measurement shall conform to specification MIL-C-45662a requirements.

4.2.2.2 Failure and Re-test. - If a failure, malfunction or out-of-tolerance performance degradation occurs during or after a test, the tests shall be discontinued. The deficiency, including any design defect, shall be corrected and the pertinent environmental procedures repeated until completed successfully. If the corrective action substantially affects the significance of results of previously completed tests of the sequence, such tests shall also be repeated. A complete record shall be made of such failures and the corrective actions taken.

4.2.2.3 Performance Check Under Standard Conditions (Reference run). - Prior to conducting environmental tests, the equipment shall be instrumented and checked for satisfactory performance under ambient room conditions. This performance check shall be made in accordance with the approved test procedures. A record shall be made of all data necessary to determine complete operational and performance characteristics. This test will be repeated on the completion of the qualification tests.

4.2.3 Qualification tests: Equipment Operating. -

<u>Test Article</u>	<u>No. of Units/ Systems Tested</u>	<u>Test to be Performed</u>	<u>Paragraph Reference</u>
Fuel assembly loader	1	Temperature	4.2.3.1
		Humidity	4.2.3.2
		Salt spray	4.2.3.3
		Rain	4.2.3.4
		Sunshine	4.2.3.5
		Sand and dust	4.2.3.6
Probe assembly	1	Temperature	4.2.3.1
		Humidity	4.2.3.2
		Salt spray	4.2.3.3
		Rain	4.2.3.4
		Sunshine	4.2.3.5
		Sand and dust	4.2.3.6

~~CONFIDENTIAL~~

DECLASSIFIED MND-3393

~~CONFIDENTIAL~~

03:15:07:030

M-27

<u>Test Article</u>	<u>No. of Units/ Systems Tested</u>	<u>Test to be Performed</u>	<u>Paragraph Reference</u>
Fairing door actuator	1	Temperature Humidity Salt spray Rain Sunshine Sand and dust	4.2.3.1 4.2.3.2 4.2.3.3 4.2.3.4 4.2.3.5 4.2.3.6
Fuel assem- bly loader carriage	1	Temperature Humidity Salt spray Rain Sunshine Sand and dust	4.2.3.1 4.2.3.2 4.2.3.3 4.2.3.4 4.2.3.5 4.2.3.6
Fuel assem- bly loader	1	Thermal tests	

4.2.3.1 Temperature tests. - All tests shall be performed at room ambient conditions of the following conditions. Surrounding air temperature will range from a minimum of 25° F to a maximum of 140° F.

4.2.3.2 Humidity Tests. - The humidity test shall be performed in accordance with Specification MIL-STD-810 Method No. 507.

4.2.3.3 Salt, Fog Test. - This test shall be performed in accordance with MIL-STD-810 Method No. 509.

4.2.3.4 Rain Test. - This test shall be performed in accordance with MIL-STD-810 Method No. 506.

4.2.3.5 Sunshine Test. - This test shall be performed in accordance with MIL-STD-810 Method No. 510.

4.2.3.6 Sand Dust. - This test shall be performed in accordance with MIL-STD-810 Method No. 510.

4.2.3.7 Thermal Test. - The system components which comprise the fuel assembly loader shall be mounted in a test fixture which has a thermal device capable of simulating conductive and radiation heat transfer characteristics of the fuel assembly under operating conditions.

During the test the fuel assembly loader shall be maintained at pressure and temperature conditions of 4.2.3.1.

~~CONFIDENTIAL~~

MND-9398

03:12:08:030

DECLASSIFIED
~~CONFIDENTIAL~~

4.2.4 Prototype fuel handling components delivered by the contractor to government agencies or other companies shall be subjected only to the following acceptance tests before delivery.

4.2.4.1 Performance Check. - Each sub-component shall be subjected to a performance check which entails complete operation of the unit in accordance with Specification requirements. Each of the sub-components shall be demonstrated to perform in accordance with an approved procedure which outlines the operational requirements of the sub-component.

4.2.4.2 Sub-system tests. - Upon successful completion of the component performance test program the components shall be assembled into sub-assemblies for further testing. This testing shall again demonstrate that the equipment performs in procedure accordance with the requirements of this Specification. An approved procedure shall be the basis of this test program.

4.2.4.3 System tests. - System test entails a full scale factory test and involves the entire control system, fuel handling system, sway restrainer, and mock-up missile and fuel storage equipment. The purpose of this program is to demonstrate that the fuel handling equipment satisfies the requirements of the Specification. An approved procedure shall be the basis of this test program.

4.2.4.4 Site testing. - The final test program is the testing of the equipment at site. A dummy satellite shall be used during this test program. An approved procedure shall be the basis of this test program.

5.0 Preparation for Delivery. -

5.1 Preservation. - All exposed bearing surfaces shall be coated with a suitable non-corrosive protective covering. Bearing surfaces exposed to physical damage such as nicks or dents shall be further protected with suitable rigid or semi-rigid covering.

All gearboxes requiring fluid lubricants shall be drained and slushed with a corrosion preventive compound.

All ports, fittings, connectors and access openings shall be capped, plugged or covered with a disposable shipping closure.

5.2 Packaging. - The Fuel Handling system shall be packaged for shipment in accordance with the best commercial practice in a manner insuring acceptance by common carrier at the lowest applicable rate. Crating, skidding and dunnage shall be minimized

~~CONFIDENTIAL~~

DECLASSIFIED MND-3393

CONFIDENTIAL

M-29

consistent with the necessary protection and handling requirements. ICC regulations for interstate transport shall be observed.

6.0 Notes. -

6.1 Intended use. - The equipment covered by this specification is intended for transporting and handling Strontium-90 radioisotopic fuel assemblies in performing fueling and defueling operations. These operations are for the purpose of installing fuel assemblies in 250 watt (e) thermoelectric generators which will be launched into space missions by Atlas/Agena D vehicle.

6.2 Ordering Data. -

6.2.1 Procurement documents for Fuel Handling Equipments shall call out this specification by title, number and date of revision applicable at the time of invitation to bid. The Interface specification appropriate to the intended mission shall be called out by title, number and date of revision. Options or alternative designs shall be specified in the procurement document only.

6.2.2 Engineering data. - Unless otherwise specified in the procurement document, the following data articles shall be furnished by the equipment supplier. All articles shall comply in format and quality of reproduction to supplier's commercial standards.

<u>Article</u>	<u>Quantities</u>		<u>Purpose</u>	
	<u>Repro</u>	<u>Non-repro</u>	<u>Info.</u>	<u>Approval</u>
1. Design Drawings and data (final) General Arrangement drawings Major Assemblies & sub-assys. Schematics Interconnection & piping diagrams Bills of material Specifications	2			✓
2. Technical Manuals (includes lubrication and routine maintenance, trouble- shooting, operation procedures and parts list)		20		✓
3. Provisioning parts list	1	3		✓
4. Test Reports	1	3		✓
5. Detail drawings, calculating, general design information		3	✓	

CONFIDENTIAL

MND-3393

DECLASSIFIED

~~CONFIDENTIAL~~

6.2.2.1 Releases. - Prior to release for fabrication, the supplier shall submit to the procuring agency one (1) reproducible copy of items in article 1 above including electrical and pneumatic schematic diagrams for approval. Written approval, or approval with comments shall be required before release for fabrication of any assembly or major component. Such approval shall not relieve the supplier from meeting all requirements of this specification unless specifically waived in writing by procuring agency.

Items in Article 5 shall not be submitted to procuring agency unless specifically requested, - and shall not be subject to approval except by agreement of the supplier.

Preliminary provisioning data, including long-lead time item, shall be submitted within ninety (90) days from receipt of design approval.

Final data for articles 1-4 shall be submitted at the time of shipment of equipment. Data required for the rework or modification of existing launch site facilities shall be submitted on a schedule to be established by the procuring agency in the procurement document.

6.2.3 Field Service and Technical Training Support. - Following installation, checkout and acceptance of the FHS at the launch site, the procuring agency shall be responsible for further equipment maintenance, operation or repair. To assist in the orderly transition of responsibility from supplier to buyer, the supplier shall provide instruction personnel for a period, commensurate with the equipment complexity, which will provide capable training of a first team of instructors, maintenance personnel, and equipment operators. A maximum of six such members shall be trained at the supplier's facility, or a maximum of twelve at the launch site. Cost of subsistence supplies, tools and travel for the trainees shall be borne by the procuring agency. Instructional material shall be provided by the suppliers.

6.3 Equipment and services furnished by others. -

6.3.1 Equipment. - The following equipment shall be supplied by the procuring agency:

- a) Shipping cask
- b) Dummy fuel assemblies
- c) Transport and erection equipment for fueling machine and shipping cask installation in service tower.
- d) Interconnecting cabling from service tower connector to control console in block house.

~~CONFIDENTIAL~~

DECLASSIFIED MND 3393

0311507030
~~CONFIDENTIAL~~

M-31

- 6.3.2 Services. - The following services shall be furnished by the procuring agency:
- a) Electric power 220 VAC, 3 phase 60 cycle, wattage to be determined.
 - b) Electric power 110 VAC, single phase 60 cycle, wattage to be determined.
 - c) Interconnecting cable installation between service tower connector and block house.

~~CONFIDENTIAL~~

MND:3393

03112291030

DECLASSIFIED

~~CONFIDENTIAL~~

BLANK

~~CONFIDENTIAL~~

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

N-1

APPENDIX N

SNAP 17A IMPACT TEST PROGRAM

The objectives of the fuel capsule impact test program are to evaluate different design parameters, using appropriate terminal velocities, temperatures, angle of impact, etc., and to develop a feasible fuel capsule design.

Experience gained on previous impact test programs (capsule design, testing method, capsule support and specimen heating) was utilized in the SNAP 17A impact test program. To achieve the optimum fuel capsule design, the test program was subdivided into three series. Each test series consisted of the impact test, an analysis of the test results and fuel capsule design modifications based on the test results. This method of testing permitted a broad investigation into the design parameters and offered a logical sequence in the selection of the final fuel capsule design.

The objective of the fuel capsule impact test program was to evaluate different fuel capsule designs and to determine a feasible fuel capsule that complies with the Nuclear safety design criteria. Basically, the capsule must contain the radionuclide under all earth impact conditions.

To test the macroscopic earth impact effects, design parameter (weld, shape, etc.), and the impact characteristics of a particular design, the test was subdivided into three test series (Fig. N-1):

- Series A - Initial study of macroscopic impact effects and design parameters to establish the most severe test conditions and to reduce the number of design parameters.
- Series B - Fuel capsule feasibility testing based on Series A to determine optimum design parameters and establish a feasible fuel capsule design.
- Series C - Development test of the fuel capsule design in Series B to evaluate the feasible design.

Due to the nature of this program, a continuous test firing schedule could not be achieved because information developed in each test series

~~CONFIDENTIAL~~

MND-3392

DECLASSIFIED

N-2

~~CONFIDENTIAL~~

Fuel Capsule Design

Impact Test Parameters

Series	Material	Temperature (°F)	Velocity (fps)	Impact Angle (deg)
Series A (14 capsules)	Haynes-25	850	250	0
		1350		45
		1600		90
Series B (14 capsules)	Haynes-25	850	250	0
		1350		45
Series C (8 capsules)	Haynes-25	1200	221	45
	Hastelloy C			
	Hastelloy N			

Fig. N-1. Fuel Capsule Design

~~CONFIDENTIAL~~

DECLASSIFIED MND-3393

0315587030
~~CONFIDENTIAL~~

N-3

affected the design in the manufacture of the test specimens (fuel capsule) for the next test series. The interim period between test series was limited to the time required for data reduction, design change, manufacture, fabrication and instrumentation.

The method of impact testing employed in this test program was the turn-around method, in which a target of large mass compared to the test specimen is impacted against the stationary specimen. This test method provides a very conservative approach to the design of the fuel capsule. The advantages of the turn-around method are:

- (1) Better control of the specimen impact temperature.
- (2) Fuel capsule impact angle variance capability.
- (3) Multi-capsule test per firing.
- (4) Better fuel capsule instrumentation.

Test data reduction. All capsules are checked initially for surface cracks using a fluorescent penetrant technique (Zyglo). This test is a sensitive nondestructive method of detecting minute discontinuities (cracks) that are open to the surface. The procedure consists of applying fluorescent liquid penetrant which enters into the discontinuities. The excess penetrant is then removed and the specimen is viewed under ultraviolet radiation or black light. Minute amounts of the penetrant seeping out through cracks or pores start to fluoresce, thus making these discontinuities visible. Penetrant is often circled in re-emerging from discontinuities by the application of a thin, powder-like film of developer material, which acts as a blotter. Lines indicate cracks or similar discontinuities. The spread of an indication gives a rough evaluation of the size of the discontinuity beneath the surface. Of necessity, inspection is confined to surfaces.

The fluorescent penetrant test was followed by a He pressure test to determine if any of the impacted capsules had ruptured.

The procedure for the pressure test is as follows:

- (1) Three capsules are placed in a tube-like chamber.
- (2) The chamber is sealed and He gas is then introduced until the chamber pressure is 400 psi. This pressure is maintained for 20 minutes.
- (3) A valve on the chamber is then opened; this allows the He to escape rapidly and reduce the chamber pressure to one atmosphere.

~~CONFIDENTIAL~~

MND-3393

0315587030

DECLASSIFIED
CONFIDENTIAL

- (4) The capsules are removed from the chamber as fast as possible and immersed in alcohol.
- (5) If any ruptures are present in the capsules, they are made visible by the bubbling action in the alcohol caused when the He gas escapes. (The gas enters the capsules through the ruptures.) If the rupture is too large, the He will escape during the interval required to remove the capsule from the chamber and submerge in the alcohol.

Following this test, all capsules are sectioned through ruptured or impacted areas for metallographic examination.

All information from the preceding test is analyzed, and capsule design modifications are made.

The results of the 36 fuel capsules impacted are as follows:

<u>Tested</u>	<u>Wall Thickness (in.)</u>	<u>Number of Failures (He leak test)</u>
7	0.150	2
6	0.125	No leaks
12	0.100	4
11	0.080	5

Of the 11 failures, 9 were due to initial rupture in the weld and two were caused by secondary impacts with the sled track structure.

Based on the test results, the following recommendations which may be applied to the 250-watt capsule design were made:

- (1) Examination of sectioned impact specimens indicated that the ratio of end cap thickness to capsule wall thickness should be approximately 2.0 for maximum energy absorption.
- (2) Reduce the cylinder wall thickness to ensure more energy absorption in the cylinder.
- (3) Relocate the weld further away from the tip of the end cap.
- (4) Incorporate an automatic welding process ensuring consistency in the weld penetration.

CONFIDENTIAL
DECLASSIFIED
MND:3393

CONFIDENTIAL

0310587030

N-5

- (5) Investigate the effects of having a hemispherical end cap.

The maximum damage which occurred to the 80-mil fuel capsule was minute cracks in the weld area. Since the most stringent test parameters were imposed on the test specimens, it is indicated from the test results that the 80-mil fuel capsule will probably contain the radionuclide fuel.

CONFIDENTIAL

MND-8383

0310587030

~~DECLASSIFIED~~
~~CONFIDENTIAL~~

BLANK

~~CONFIDENTIAL~~
~~DECLASSIFIED~~
MMD-8393

CONFIDENTIAL

O-1

APPENDIX O

SHOCK OVERPRESSURE AND THERMAL EFFECTS OF FIREBALL

A. SHOCK OVERPRESSURE

<u>Missile Data</u>	<u>Atlas</u>	<u>Agena-D</u>
Height (ft)	72	20.6
Fuel	LOX/RP-1	IRFNA/UDMH
Fuel weight (lb)	244,500	14,100
TNT equivalent (%)	10	10
Predicted average pressure: $\bar{P} = 593/Z^3 - 28.8/Z^2 + 20.7/Z$		
Pressure at 98% confidence level: $P_{98\%} = 9862/Z^3 - 187.9/Z^2 + 52.8/Z$		

where

$$Z = R/W^{1/4}$$

P = average side on overpressure (psi)

R = distance from explosion to fuel block (ft)

W = total weight of propellants (lb).

Figure O-1 shows the approximate locations of the various explosions at points A, B and C. For an explosion at point C, which is at the propellant center of mass, we get:

$$Z = R/W^{1/4} = 55.35/255,600^{1/4} = 2.47 \text{ ft/lb}^{1/4}$$

$$\bar{P} = 593/(2.47)^3 - 28.8/(2.47)^2 + 20.7/2.47 = 42.87 \text{ psi}$$

$$P_{98\%} = 9862/(2.47)^3 - 187.9/(2.47)^2 + 52.8/(2.47) = 645.6 \text{ psi.}$$

For explosions at points A and B, the following overpressures are obtained:

	<u>A</u>	<u>B</u>	<u>C</u>
Distance (ft)	93.85	57.85	55.35
P _{ave} (psi)	11.13	37.12	42.87
P _{98%} (psi)	132.55	547.6	645.6

CONFIDENTIAL

MND-3393

DECLASSIFIED

O-2

~~CONFIDENTIAL~~

Fig. O-1. Atlas/Agenda-D Launch Vehicle

~~CONFIDENTIAL~~

DECLASSIFIED MND-3393

CONFIDENTIAL

O-3

To examine the structural integrity of the fuel capsules, we apply the formula for a uniform lateral load on a cylinder with ends held circular (Ref. O-1).

$$P = 0.807 ET^2/\ell r \sqrt[4]{\frac{1}{(1-\nu^2)^3} \frac{t^2}{r^2}} \quad (\text{O-1})$$

where

P = unit external pressure

E = modulus of elasticity = 24.9×10^6 psi for Haynes-25
(1650° F) and 11.5×10^6 psi for
TD nickel (2000° F)

t = wall thickness = 0.100 inch

r = mean radius = 0.95 inch

ν = Poisson's ratio = 0.33

ℓ = length of capsule = 6.48 inches

Solving, we find that at capsule deformation P = 11,500 psi for the Haynes-25 capsule and P = 5330 psi for the TD nickel capsule (the structural support of the platinum casing has been neglected).

For a second consideration, we make use of the equation for a thick-walled cylinder (greater than one-tenth the radius) with ends free, subjected to external radial pressure only (Ref. O-2).

$$\sigma = \frac{P_o (b^2 + a^2)}{(b^2 - a^2)} \quad (\text{O-2})$$

where σ = the maximum hoop or circumferential stress. (Here, we choose it to be the ultimate tensile stress: for Haynes-25 at 1650° F, $F_{TU} = 42,700$ psi; for TD nickel at 2000° F, $F_{TU} = 18,400$ psi)

and

Po = unit applied load (to be found)

a = capsule inner radius = 0.90 inch

b = capsule outer radius = 1.00 inch.

Solving for Po,

$$P_o = \sigma \frac{(b^2 - a^2)}{b^2 + a^2} = 1.05$$

CONFIDENTIAL

MND-3393

~~CONFIDENTIAL~~
~~CONFIDENTIAL~~

and

$P_1 = 4480$ psi for Haynes-25 capsule

$P_2 = 1930$ psi for TD nickel capsule.

The fuel capsules will certainly withstand the shock overpressures of a launch abort.

B. THERMAL EFFECTS OF FIREBALL

The following data for the fuel and fuel capsules are used:

	<u>Fuel</u> <u>Sr Compound</u>	<u>Capsule Materials</u> <u>Haynes-25</u>	<u>TD Nickel</u>	<u>Platinum</u>
Weight, M (lb)	2.25 (dynamic) 1.87 (static)	2.04	1.81	0.413
Specific heat, CP (Btu/lb-° F)	0.226	0.11	0.107	0.032
Melting point (° F)	2480	2570.2	2650	3224
Heat of fusion, l_f (Btu/lb)	168	110	128.8	49
Thermal conduc- tivity, R (Btu/° F- in. -sec)	2.63×10^{-5}	3.45×10^{-4}	6.65×10^{-4}	9.03×10^{-4}

We first find the total heat required to melt the capsule walls. Assuming an average operating temperature of 1950° F for the TD nickel capsule and neglecting the heating effects of the beryllium spacers, we find:

- (1) Heat required to raise fuel from 1950° F to platinum melting temperature of 3224° F:

$$Q = mc_p \Delta T = (1.87) (0.226) (1274) \quad 535.1 \text{ Btu}$$

- (2) Heat of fusion of fuel:

$$Q = l_f m = (168) (1.87) \quad 314.2 \text{ Btu}$$

- (3) Heat to raise TD nickel from 1980° to 3224° F:

$$Q = (1.81) (0.107) (1274) \quad 242.1 \text{ Btu}$$

~~CONFIDENTIAL~~

DECLASSIFIED
MND-3893

CONFIDENTIAL

O-5

- (4) Heat of fusion of TD nickel:

$$Q = (1.81) (128.8) \quad 233.1 \text{ Btu}$$

- (5) Heat to raise platinum to its melting temperature:

$$Q = (0.413) (0.032) (1274) \quad 16.1 \text{ Btu}$$

- (6) Heat of fusion of platinum:

$$Q = (0.413) (49) \quad 20.2 \text{ Btu}$$

Total heat required to completely melt capsule wall, $Q_T = 1360.8 \text{ Btu}$

Similarly, for the Haynes-25 capsule initially at 1700° F , we find that $Q_T = 1240.2 \text{ Btu}$ is needed to reach the capsule melting temperature at 2570.2° F .

The determination of structural temperatures as a function of time and geometrical coordinates can be obtained by solving the appropriate heat transfer problem. However, let us first make some preliminary calculations in predicting the capsule integrity.

Based upon the temperature profiles for the Atlas, along with measured test results (Refs. O-3 and O-4) and the theoretical and test results of the Titan II one-half scale test model (Refs. O-4 through O-8), we choose the first fireball of the LOX/RP-1 propellants to last for 4.95 seconds. A few seconds after the first-stage explosion (the exact moment dependent on the tip-over time of the vehicle), the IRFNA/UDMH fuels ignite, forming a second fireball of 5.41 seconds duration. The average Atlas flame temperature is taken as 5100° R , several hundred degrees higher than the 4500° R assumed for the hypergolic propellants.

For convenience, we assume infinite thermal conductivities for both the fuel and the capsule materials, implying identical surface and bulk temperatures. Neglecting convection and conduction effects also (Ref. O-4) we may express the net heat transfer rate between the fireball and capsule as

$$\phi = \frac{\gamma \epsilon_c \sigma}{3600} (\epsilon_g T_g^4 - \alpha_g T_c^4) \quad (\text{O-3})$$

where

ϕ = heat flux ($\text{Btu}/\text{ft}^2\text{-sec}$)

γ = view factor = 1

CONFIDENTIAL

MINI-3393

CONFIDENTIAL

~~CONFIDENTIAL~~
DECLASSIFIED

ϵ_c = emissivity of capsule surface = 0.8

ϵ_g = emissivity of gases = 1.0

α_g = absorptivity of gas at temperatures $T_g = 1.0$

σ = Stefan-Boltzmann constant = 0.1714×10^{-8} Btu/ft²-hr-°R

T_g = environmental temperature (gases)

T_c = capsule temperature.

Letting $T_g = 5100^\circ \text{ R}$ and $T_c = 2160^\circ \text{ R}$ (1700° F) for 4.95 seconds, we find that, for the Haynes-25 capsule,

$$\phi = \frac{(0.8)(1714 \times 10^{-8})(5.1^4 - 2.16^4) \times 10^{12}}{3600} = 248 \text{ Btu/ft}^2\text{-sec}$$

Assuming infinite k, the heat absorbed in this time is

$$Q = \phi AT = (248)(53.25)(4.95) = 454 \text{ Btu}$$

where

A = capsule surface area.

This raises the average capsule temperature from 1700° F to $T_2 = Q/\Sigma Mcp + T_o = 454/0.733 + 1700^\circ \text{ F} = 2318^\circ \text{ F}$.

The heat flux of the 4500° R fireball is

$$\phi = \frac{(0.8)(0.1714 \times 10^{-8})(4.5^4 - 2.78^4) \times 10^{12}}{3600} = 134 \text{ Btu/ft}^2\text{-sec}$$

Hence,

$$Q = \phi AT = \frac{(134)(53.25)(5.41)}{144} = 268 \text{ Btu}$$

are absorbed in the second fireball. However, $454 + 268 = 722 \text{ Btu}$ are not enough to melt the capsule and, judging from our preliminary analyses, it appears that the capsules will withstand the thermal environment.

We now turn to the more complex transient heat problem. For this, a heat transfer and ablation study is programmed on an IBM 7094 digital computer. The program used in this study is Transient Heating

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

~~CONFIDENTIAL~~

O-7

Digital Analysis for Structural Design (Ref. O-9). Models are set up to represent both capsules, the model for the dynamic fuel capsule being comprised of 35 elements in all--five for the Haynes-25 and thirty for the Sr-90 fuel. The model for the static capsule is somewhat simplified, containing one element for the platinum, two for the TD nickel, and eight for the Sr-90 fuel. By considering the heat transfer of each of these elements over small successive increments of time, the temperature distribution of all the elements can be found and the heat balance equations written as functions of the average temperature gradients over a time interval. The simultaneous equations are then solved for each time interval and one can then predict the time at which the capsule walls will completely ablate, thereby allowing a fuel release.

The problem at hand considers a unit depth of an infinitely long cylinder subjected to a constant heat input. Only radial heat transfer is considered, the lateral flow being negligible. Because the available literature produces such varied results concerning heat transfer rates of fireballs, one must use a certain amount of discretion in choosing reasonable values. Thus, we select parameters of 150, 175, 189, 200, 250 and 300 Btu/ft²-sec and apply these values as constant heat inputs to the capsule. A curve of heat flux versus capsule melting time is given in Fig. O-2 which shows that, for the Haynes-25 capsule to melt in 10.36 seconds, a heat flux of 204 Btu/ft²-sec or more is required.

Therefore, the maximum average of 175 Btu/ft²-sec recorded by the Bureau of Mines in the Titan II one-half scale tests (Ref. O-5) will not be sufficient to expose the fuel. However, the gross flux found from the theoretical temperatures of the preliminary calculation is

$$Q_1 = \frac{\epsilon_g \sigma T_{g1}^4}{3600} = \frac{(1)(0.1714 \times 10^{-8})(5.1^4 \times 10^{12})}{3600} = 320 \text{ Btu/ft}^2\text{-sec}$$

for the first fireball, and

$$Q_2 = \frac{\epsilon_g \sigma T_{g2}^4}{3600} = \frac{(1)(0.1714 \times 10^{-8})(4.5^4 \times 10^{12})}{3600} = 195 \text{ Btu/ft}^2\text{-sec}$$

for the second. This gives an average gross flux of

$$\begin{aligned} Q_{ave} &= \frac{1}{\tau} \sum_{n=1}^i \phi_n t_n = \frac{\phi_1 t_1 + \phi_2 t_2}{t_1 + t_2} \\ &= \frac{(300)(4.95) + (195)(5.41)}{4.95 + 5.41} = 254 \text{ Btu/ft}^2\text{-sec} \end{aligned}$$

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

O-8

~~CONFIDENTIAL~~

Fig. O-2. Capsule Melting Time as Function of Fireball Heat Flux

~~CONFIDENTIAL~~

DECLASSIFIED MND: 3393

03145587030
~~CONFIDENTIAL~~

O-9

From the curve, it is seen that with this theoretical heat rate, the capsule will fail in 8.2 seconds and, hence, the fuel will be exposed.

REFERENCES

- O-1. Formulas for Stress and Strain, Roark.
- O-2. Saelman, B., "Design Equations and Charts for Pressurized Cylinders and Spheres," Lockheed Aircraft Corporation, Burbank, California.
- O-3. "Nuclear Safety Test Report for the Space Version of the Present SNAP III Thermoelectric Generator," MND-P-2358, Martin-Nuclear.
- O-4. "Analysis of Launch Facility Thermal Environment During a Pad Incident," DS-38-61, Martin Company.
- O-5. "Titan II--1/2 Scale Tests Data," Martin Company, Denver Division.
- O-6. Telephone Conversation with Mr. Chris Saros, Cambridge Plant, Denver, Colorado, April 15, 1964.
- O-7. Telephone Conversation with Mr. G. Manelis, Cambridge Plant, Denver, Colorado, June 1, 1964.
- O-8. Oslake, J. J., et al., "Explosive Hazards of Rocket Launchings," Aeronutronic Division of Ford Motor Company, U-108-98, November 30, 1960.
- O-9. "SNAP Programs--Upper Atmosphere Experience Re-Entry Study Final Summary Report," Martin-Nuclear, April 1963.

~~CONFIDENTIAL~~

MND-2398

03145587030

DECLASSIFIED

CONFIDENTIAL

BLANK

CONFIDENTIAL

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

P-1

APPENDIX P

DESCRIPTION OF VEHICLE AND ASSUMED TRAJECTORY

A. ATLAS

The two-stage launch vehicle (Fig. P-1) for the 250-watt RTG program is an Atlas/Agena D which is used primarily for space programs. The Atlas (Ref. P-1), noted as SLV-3B, is comprised of (1) the booster section, (2) the sustainer or tank section and (3) the interstage adapter. The booster section, which is jettisonable, consists of two booster engines, an aft engine fairing assembly, a fire shield assembly, two forward nacelle door assemblies, and thrust longerons. The sustainer or tank section supplies fuel to the booster, sustainer and vernier engines during the flight; it is retained for the full duration of the Atlas flight, and at staging only the two booster engines are jettisoned. The interstage adapter is only a transition section between the Atlas and Agena D vehicles.

The Atlas standardized space launch vehicle (SLV-3B) receives its thrust from two 165,000-pound thrust booster engines, one 57,000-pound thrust sustainer engine, and two vernier engines which add a total of 1500 pounds of thrust. At sea level the total thrust is 385,500 pounds. The two booster engines are independently gimbal-mounted to provide directional control and stability during the first-stage powered flight. During the sustainer stage, the sustainer engine provides directional control of the vehicle by gimbaling in any direction about the pitch and yaw axes. This engine is locked out of the control system during the booster portion of the flight. The function of the two gimbled vernier engines is to assist in providing roll and attitude control about all axes and to provide "fine" control of the velocity vector. These engines, prior to launch, are started before the booster and sustainer engines and they continue to provide thrust after sustainer engine cut-off.

1. Propellants

The propellants (Table P-1) used for the Atlas space launch vehicles are liquid oxygen (approximately 171,000 pounds) and RP-1 hydrocarbon fuel (approximately 76,000 pounds). The propellants are supplied to the combustion chambers under pressure from centrifugal pumps (turbopumps). Liquid oxygen and RP-1 are burned in two gas generators and the resulting hot gases drive the turbines of the propellant pumps.

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

P-2

~~CONFIDENTIAL~~

Fig. P-1. Atlas-Agena D Configuration

~~CONFIDENTIAL~~

MND-3393

DECLASSIFIED

TABLE P-1
Propellant Data

<u>Vehicle</u>	<u>Engine</u>	<u>Fuel</u>	<u>Oxidizer</u>	<u>Thrust at Sea Level (lb)</u>	<u>Specific Impulse at Sea Level (sec)</u>	<u>Fuel Flow (lb/sec)</u>	<u>Oxidizer Flow (lb/sec)</u>	<u>Fuel Density (lb/ft³)</u>	<u>Oxidizer Density (lb/ft³)</u>
Atlas	Booster (2)	RP-1	Liquid oxygen	330,000	251	397	904	50.45	71.38
	Sustainer (1)	RP-1	Liquid oxygen	57,000	215	81	184	50.45	71.38
	Vernier (2)	RP-1	Liquid oxygen	1,050* 1,500**		4	2.0* 2.5**	50.45	71.38
Agena D	Main	UDMH	IRFNA	1,600 (vac)					

*Tank fed
**Pump fed

MND-3396

~~CONFIDENTIAL~~

~~CONFIDENTIAL~~

~~DECLASSIFIED~~
~~CONFIDENTIAL~~

2. Guidance System

The Atlas (SLV-3B) space launch vehicle utilizes the General Electric guidance system, which consists of two subsystems. One subsystem measures the position of the vehicle and provides a command link with the ground, and the other measures the components of the velocity by continuous wave radar.

The components of the airborne guidance system consist primarily of three canisters. One canister contains a continuous wave (cw) radar beacon, the second one contains a monopulse radar beacon, and the third contains the decoder which operates in conjunction with the pulse beacon. Operation of this guidance system is as follows.

The pulse beacon receives a pulse coded signal from the ground station. This signal contains discrete command information and steering commands. The pulse beacon sends a return signal to the ground station for measurement of the vehicle's position. The decoder decodes the pulse message from the ground station and distributes this information to the various vehicle systems. The continuous wave beacon receives a double side-band suppressed carrier signal from the ground station and generates a return signal which lies between the frequencies of the two side bands received.

The ground-based components of the GE guidance system include a monopulse radar system capable of measuring the position of the vehicle and of transmitting a pulse coded message to the vehicle-borne guidance system; a rate-measuring device (cw radar) which employs doppler-shift techniques to measure the vehicle's velocity; and a computer which accepts the position and velocity coordinates of the vehicle and computes real-time steering and control commands.

3. Autopilot

The Atlas vehicle, like all missiles and space boosters having no stabilizing fins or movable air surfaces, is aerodynamically unstable and incapable of flying a predetermined course without an autopilot. This autopilot incorporates three main functions, as follows:

- (1) It senses the attitude and any changes in attitude about the pitch, yaw and roll axes by means of displacement gyros.
- (2) It changes the relationship of the thrust vector to the center of gravity by causing gimbaling of any of the five engines.
- (3) It selects the engine or engines to be gimbaled for attitude control during a specific flight phase, and it provides for programmed maneuvers.

~~DECLASSIFIED~~
~~CONFIDENTIAL~~
MND-3393

~~CONFIDENTIAL~~

P-5

The principal components of the Atlas autopilot consist of five separate packages:

- (1) Three packages: programmer assembly, servoamplifier assembly, and displacement gyro assembly. (One rate gyro for roll control is also included with the displacement gyros.)
- (2) The adapter-mounted autopilot package contains the pitch and yaw rate gyros, and it is mounted inside the Agena adapter.
- (3) The fifth package, ten actuator assemblies, is located in the aft portion of the sustainer section.

The following is a brief description of the operation of the autopilot system. The displacement gyros sense the attitude and changes in attitude from an initial reference. The changes and variations in attitude are then transmitted to the engines' servomechanisms which gimbal the applicable engine or engines to correct the vehicle's attitude and to realign it with the initial reference. Damping is provided, as necessary, by the rate gyros, and an integrator, included in the system, compensates for steady-state errors. The programmer, through the autopilot, rolls the vehicle to a predetermined attitude, pitches it into a predetermined trajectory, and sequences timed commands during flight.

B. AGENA D

The Agena D vehicle as shown in Fig. P-2 consists of the (1) forward section, (2) tank section, (3) aft section and (4) booster adapter section. The spaceframe provides the aerodynamic and structural shape of the Agena D vehicle and houses and supports the various vehicle system components and modules.

The Agena D forward section carries guidance, flight control electronics, telemetry, command, tracking, electrical power, and propellant pressurization equipment. The forward section also provides mounting provisions for the payload, and program optional equipment.

Fuel and oxidizer necessary for operation of the main rocket engine are stored in the Agena D tank section. This section also provides the aerodynamic surface and supporting structure between the forward and aft sections. Fuel tank capacity is 553.31 gallons while oxidizer tank capacity is set at 738.0 gallons.

~~CONFIDENTIAL~~

MND-3393

0171228.030

DECLASSIFIED

P-6

CONFIDENTIAL

Fig. P-2. Agena D

CONFIDENTIAL

DECLASSIFIED

MND-3393

~~CONFIDENTIAL~~

P-7

The aft section is the structural portion of the Agena D vehicle to which the rocket engine, ullage rockets, and pneumatic altitude control thrust valves are attached. Because of the tension loading design, the aft section is a lightweight structure with a high load capability.

The booster adapter section is the interconnecting structure between the Agena D vehicle and the first-stage booster. Prior to separation of the Agena D vehicle from the first-stage booster during flight, the adapter section encloses the vehicle aft section. Two retrograde rockets, which effect separation of the Agena D vehicle and the first-stage booster, are mounted in the adapter section and are enclosed by exterior fairings. A vehicle self-destruct system is also installed in the adapter section.

1. Propulsion System

The propulsion system provides the final thrust necessary for the Agena D vehicle to perform missions as an intermediate stage booster or as an orbital vehicle. After launching and upon completion of the thrust phase by the Atlas first-stage booster, the Agena D and its first-stage booster separate. Following separation, the Agena D vehicle continues its programmed space mission with thrust being provided by the Agena D propulsion system.

The propulsion system consists principally of a rocket engine with its propellant-flow and electrical-control equipment, and the propellant subsystem and equipment that are necessary to support the rocket engine operation.

A USAF Model XLR 81-BA-9 (Bell Aerosystem Company Model 8096) liquid bipropellant rocket engine system with a single combustion chamber powers the Agena D. The propellants utilized for engine operation are unsymmetrical dimethylhydrazine (UDMH) as the fuel and inhibited red fuming nitric acid (IRFNA) as the oxidizer. This engine develops a rated thrust of 16,000 pounds in a vacuum for a total duration of 240 seconds.

2. Guidance and Control System

Agena D guidance and control system functions include vehicle flight altitude control; vehicle ascent, orbital, or spatial trajectory control; vehicle velocity control; and timing and sequence control of the vehicle's programmed operations. The guidance and control system can be programmed to achieve a vehicle circular orbit, to correct the launch trajectory to modify the vehicle's orbit, and to effect payload recoveries using rocket engine thrust for braking. The system can be programmed to accomplish altitude maneuvers, perform

~~CONFIDENTIAL~~

MND-3393

03712291030

~~DECLASSIFIED~~
~~CONFIDENTIAL~~

active or semiactive vehicle control, and to stabilize the Agena D vehicle vertically or horizontally in orbit.

3. Destruct System

No information describing the destruct system onboard the Atlas launch vehicle was available and, therefore, this system is not discussed in this document. The destruct system located in the Atlas/Agena D adapter section and in the Agena D vehicle itself is described herein.

The self-destruct system provides a means of destroying the program satellite during the orbital boost phase of flight in the event an uncontrollable condition occurs and wherein continued flight would constitute a hazard to property and personnel. The system consists principally of a shaped explosive destruct charge, a destruct charge initiator, four auxiliary destruct batteries, two premature separation switches (also known as destruct lockout switches), and related destruct system circuitry. All system components are installed in the booster adapter section. The destruct charge initiator and batteries are adjacent to each other on the outside of the adapter, just aft of the vehicle separation plane. The two premature separation (destruct lockout) switches are inside the adapter.

The self-destruct system is capable of being actuated either by a command signal from the Range Safety Officer or automatically upon premature separation of the Agena D vehicle and booster. The system is electrically connected with the first-stage booster destruct system to provide the capability for simultaneous destruction of both vehicles by the ground command signal transmitted to the booster destruct system. Destruction may be effected any time between lift-off and booster thrust cutoff. Safety features are incorporated into the system to prevent accidental detonation of the destruct charge during prelaunch checkout on the launch pad and until the normal separation of the Agena D and booster occurs during flight.

An optional command destruct module may be installed in the Agena D vehicle to provide the additional capability of the vehicle destruct after separation of the Agena D and first-stage booster. The command destruct module also provides capability for performing functions of the self-destruct system. The self-destruct system hardware may therefore be removed from the vehicle whenever the command destruct module is installed. The command destruct module is installed on the side of the propellant tank assembly and destroys the vehicle by means of an explosive charge that penetrates the propellant tanks. The command destruct module includes a receiver and antenna which receive the fire signal from the Range Safety Officer.

~~CONFIDENTIAL~~
~~DECLASSIFIED~~
MIND:3393

~~CONFIDENTIAL~~

P-9

4. Separation

Two separation operations are accomplished by the Atlas SLV-3:
(1) separation of the booster section from the sustainer sections and
(2) separation of the sustainer section from the upper stage or payload section.

The booster section separates on command from the flight control subsystem, whereas the upper stage can be separated by a command initiated in the upper stage itself. At the end of the predetermined booster flight period, a staging command from the ground guidance system initiates a programmer subroutine which locks the sustainer engine. The booster engines then shut down and a pyrotechnic-activated device is ignited which enables pressurized helium gas to release ten separation fittings. Fluid and pneumatic lines uncouple, and the booster, booster engines, turbopumps, and associated equipment, together with the skirt structure, move away from the vehicle along the jettison guide rails, thus lightening the load by approximately 7000 pounds.

The mechanism that provides for separation of the SLV-3 from the Agena upper stage includes an attachment and release device which secures the Agena to the forward end of the Atlas vehicle during powered flight. After vernier engine cutoff, the Atlas SLV-3 flight control subsystem, in response to a signal originated by the Agena upper stage, detonates three pyrotechnic devices which actuate a mechanism that separates the Atlas vehicle from the upper stage adapter (Atlas/Agena adapter). The adapter remains attached to the forward end of the Atlas, and rollers installed on the Agena equipment rack guide the upper stage away from the sustainer along channels incorporated in the adapter.

After mechanical separation has occurred, two solid-propellant retarding rockets are fired to give the Atlas a velocity different from that of the Agena, to allow for complete, unhindered escape of the Agena upper stage. Complete disengagement takes 1.5 seconds.

C. REFERENCES

- P-1. "Atlas SLV Fact Book," Report from General Dynamics/Astronautics, Confidential.
- P-2. "Agena D Vehicle Familiarization," Lockheed report LMSC-A075695, SSK-T62-2, April 15, 1962, Confidential.
- P-3. "Nominal Ascent Reference Trajectory Program 369," TOR-169(3111)-1, Volume I, Aerospace Corporation, May 31, 1963, Confidential.

~~CONFIDENTIAL~~

WMD-3393

DECLASSIFIED
~~CONFIDENTIAL~~

- P-4. "Nominal Ascent Reference Trajectory Program 369," TOR-169(3111)-1, Volume II, Aerospace Corporation, May 31, 1963, Secret.

CONFIDENTIAL
~~DECLASSIFIED~~
TOR-3393

~~CONFIDENTIAL~~

Q-1

APPENDIX Q

GENERAL SAFETY

The sections entitled Licensing and PMR Interfacing which follow are general presentations of the contractor responsibilities involving the RTG on the Pacific Missile Range (PMR), and of the various generator, missile, and personnel interfaces at the launch site.

A. LICENSING

1. Contractor Responsibilities

The agency responsible for performing work involving nuclear components on the Pacific Missile Range (PMR) will prepare the required detailed work procedures and submit them to the Director of Range Support for approval prior to the scheduling of the work. This will demand adherence to the following:

- (1) The Range User contemplating using ionizing radiations on the PMR will provide three copies of the applicable Atomic Energy Commission (AEC) and/or State of California license(s) prior to the arrival of the source of radiation.
- (2) Unlicensed assemblies, such as SNAP units, will require the Range User to submit to the Range Safety Office complete hazard evaluation of the potential release of any radioactive materials.
 - (a) The Range User may propose hazard areas in connection with launch complex operations, these proposals subject to approval of COMPMR.
 - (b) The execution of the radiation policy for radiobiological safety will be carried out in accordance with the criteria of:
 - (i) Title 10, Code of Federal Regulations (AEC).
 - (ii) National Bureau of Standards Handbooks 60 and 69.
 - (iii) NAVMEDP-1325.

~~CONFIDENTIAL~~

WMD-2393

DECLASSIFIED
~~CONFIDENTIAL~~

- (c) The range regulations for the use of radioisotopic fuel capsules are to be found in COMPMRINST 5100.2C, Appendix A. (There are no existing Air Force regulations or safety documents governing the ground handling of Sr-90 fuel cells at VAFB or NMFA.)
- (d) Trajectory and aerodynamic requirements applicable to the nuclear unit must be submitted at least 60 days prior to first launch.

Requirements pertaining to the nose fairing containing the RTG are:

- (i) Expected effects of destruct explosion including estimates of the number and approximate weights of pieces. This should apply to the effects of the destruct system of the launch vehicle on the nose fairing and of the nose fairing itself, if a destruct system is used.
 - (ii) Impact dispersion data for various stages. In the case of the nose cone, a statement as to the maximum range and lateral deviations which can occur because of variations in drag, winds, side lift, or other effects is desired.
 - (iii) Re-entry burnup conditions. At what phases of the flight could the payload burn up?
 - (iv) Expected impact point for each stage. Should the stages or payload fail to separate as well as experience destruct failure, where will the RTG land?
- (3) Since the use of nuclear power at the PMR presents many new problems pertaining to storage, operational procedures, recovery, and safety, several changes in the physical plant of the launch site may be necessary. Because of modifications made by other programs presently using the PALC-1 and PALC-2 launch stands, the exact configuration of these structures for the 250-watt RTG launch is not yet determined. Therefore, the contractor will specify any requirements for acceptance of the facility or modifications, and present these requirements to the Air Force Space Systems Division. A lead-time of six months is necessary for launch complex installations. If required, the contractor will participate in the acceptance tests.

~~CONFIDENTIAL~~

DECLASSIFIED
MND-3393

0310587030
~~CONFIDENTIAL~~

Q-3

The contractor shall define his respective management responsibilities for the system safety effort necessary to accomplish the objectives. In this, he must establish procedures to assure:

- (a) Definition of safety requirements.
- (b) Preparation and implementation of a System Safety Engineering Plan (SSEP).
- (c) Accomplishment of safety analysis including interface requirements.
- (d) Submittal of required reports.
- (e) Management responsibility for a planned and engineered safety program.

The general requirements for the preceding procedures are described at length in BSD 62-41.

2. Shipping Cask Safety Requirements

Safe handling of the fuel during shipment is dependent upon the design of the shipping cask. The Sr-90 fuel source is classified by the ICC as a Group I, Class D poison, denoting radioactive materials that emit gamma rays only, or both gamma and electrically charged corpuscular rays. The design and shipping requirements which are to be applied to the design of this equipment are as follows:

- (1) Radioactive materials, such as strontium, that present special hazards due to their tendency to remain fixed in the human body for long periods of time must be packed inside metal containers approved by the Bureau of Explosives, in addition to the prescribed ICC packing (Specification 2R).
- (2) All of the radioactive materials must be packed and shielded such that the degree of fogging of undeveloped film under conditions normally incident to transportation (24 hours at 15 feet from the package) will not exceed that produced by 11.5 milliroentgens of penetrating gamma rays of radium filtered by 1/2 inch of lead.
- (3) Containers for more than 4000 millicuries must have the name RADIOACTIVE MATERIAL and the permit number stamped, embossed, or otherwise permanently applied so that they will not be obliterated by fire.

~~CONFIDENTIAL~~

MND-2398

0310587030

~~UNCLASSIFIED~~~~CONFIDENTIAL~~

- (4) Means must be provided for applying a seal so that the outer container cannot be opened without destroying the seal.
- (5) The cask must be designed such that the gamma radiation will not exceed 200 mr/hr at the outside surface or 10 mr/hr at a distance of one meter from any surface of the source.
- (6) The cask must be able to withstand a standard one-hour fire (i.e., temperature of 1700°F for 60 minutes as defined by the National Fire Protection Association) without radiating greater than 1 r/hr measured in air at any cask surface.
- (7) Materials which might be damaged by a one-hour standard fire must be insulated from fire effects, if used.
- (8) No material within the system must approach within 300°F of its failure temperature during transport.
- (9) At all times during transport, the surface temperature of the cask must not exceed 180°F.
- (10) Lead shielding or other equally effective shielding material must be encased in steel or other suitable material such that shielding will neither flow away nor lose its efficiency in a fire. The casing material must be 1/8 inch thick for six inches or less of shielding or 1/4 inch thick for more than six inches of shielding.
- (11) The smallest dimension of any outside shipping container must not be less than four inches.
- (12) The shielding must be supported within the outer container such that it can neither change position nor open under any conditions.
- (13) Containers weighing more than 500 pounds must be fitted with skids or designed so as not to create excessive pressure on small areas of the carrier deck. Gross weight must be marked on containers destined for water shipment if the weight exceeds 500 pounds.
- (14) Sections of the shield must be so designed that radiation cannot be beamed at joined points.
- (15) Outer containers, where practicable, must have joints 100% welded or brazed, with the closure secured by a positive

~~UNCLASSIFIED~~~~CONFIDENTIAL~~~~DECLASSIFIED~~

MND-3393

CONFIDENTIAL

UNCLASSIFIED

Q-5

fastening device capable of withstanding severe impact without failure.

- (16) The lid fastening must survive a force equivalent to 60 times the lid weight for 16 milliseconds, without exceeding its ultimate tensile strength.
- (17) The container must be designed to withstand any vibrations normally incident to transportation. This is defined by the Association of American Railroads to be equivalent to a four-foot fall.
- (18) The container must withstand the forces generated in a 30-foot fall onto a rigid target media without release of radioactive material or loss of shield integrity.
- (19) The cask, as a single beam, must support 10 times its own weight without exceeding its ultimate tensile strength.
- (20) Any lifting device must be of sufficient strength to lift six times the loaded cask weight without exceeding the yield strength of the material.
- (21) Any device attached to the cask that may be used for transport tie-down must withstand a static force with components as follows: vertical component equal to two times the loaded cask weight; horizontal component equal to 10 times the loaded cask weight, without exceeding the ultimate strength of the material.

The recovery of the fuel capsule after a launch pad accident or early abort will be facilitated if the capsules are separable from the wreckage material, thereby allowing a quick return to the original shipping cask. If isolation cannot be assured, however, it will be necessary to provide a cask meeting shipping requirements at the launch site as a standby measure for shipment to the processing plant or a waste disposal facility.

In the improbable event that the fuel containment is violated, the material released will be recovered as fully as possible and mixed with a concrete slurry in standard waste drums for transportation to a waste disposal facility.

B. PMR INTERFACING

The following is a discussion of some of the launch activities and the existing constraints and problems involved in the use of the RTG

CONFIDENTIAL

MND-3393

UNCLASSIFIED

DECLASSIFIED
~~CONFIDENTIAL~~

power supplies. It is assumed that the launch will take place from the Naval Missile Facility at Point Arguello, Vandenberg Air Force Base.

- (1) Since the temperature of the uncooled static capsule in air during loading operations may reach 1950°F, the possibility of an explosion exists should any propellant vapor be present. Since there is flexibility in the propellant loading of the Atlas/Agena D, it is recommended that the fueling be accomplished after the RTG loading.
- (2) A supply of cooling medium into the nose fairing is required to maintain the payload ambient air within prescribed temperature limits prior to liftoff. Since this cooling is critical, a backup source shall also be provided.
- (3) The weight of the RTG loading mechanism must not exceed the safe loading on either of the PALC-1 or PALC-2 launch stands, the maximum capacity of the hoists being 10 tons.
- (4) The installation of the RTG loading equipment on the launch stand shall not require any undue complications or restrictions in the travel of the launch stand.
- (5) The dynamic deflection of the Atlas/Agena D due to wind forces will require a constraining mechanism to permit remote fueling.
- (6) Launch site test procedures and coordination of countdown operations pertaining to the loading and checkout of the RTG will be submitted by the contractor.
- (7) The RTG contractor will carry out day-to-day radiation surveys upon arrival of the generator at VAFB and will be responsible for the briefing of involved personnel on emergency procedures, the issuance of film badges, and stand-by emergency assistance during launch.
- (8) The question of whether to destruct the RTG or attempt its recovery after an abort requires consideration as to the dispersion of the radioactive material. (No special recovery vehicles for radioactive materials are presently available at VAFB.)
- (9) If, prior to launch but after or during the propellant fueling, it becomes necessary to remove the RTG fuel from the payload back into the storage container, there exists the possibility of the hot RTG igniting a propellant spill or vapor

~~CONFIDENTIAL~~

DECLASSIFIED MND-3393

0316587030
~~CONFIDENTIAL~~

Q-7

leak during this removal. Thus, procedures of removal allowing for maximum safety must be examined and recommended.

- (10) To adapt the umbilical mast, it must be permissible to make minor modifications to the mast, such as the addition of liquid coolant lines or a cooling air duct. However, any major modifications to the umbilical mast should not be assumed at the present time.
- (11) Since the umbilical mast is located in front of the PALC-1 complex, it is necessary to rotate this mast to a horizontal position during booster erection and payload installation. If RTG loading procedures require access to the launch stand hoist for lifting any RTG equipment after booster checkouts have started, it will become necessary to disconnect the umbilical and lower the mast. There is no such interference at PALC-2.
- (12) A study of recovery techniques, available recovery equipment, and the topography around the launch site pertaining to radioactive release into the sea or on the ground after an abort will demand careful consideration.
- (13) The question of disposal of the launch rocket and satellite in the event of an early abort requires consideration of the use of the escape tower principle used in manned flights to remove the entire payload from the Atlas/Agena D booster. This would greatly enhance recovery operations and reduce the problem of dispersion after destruct.
- (14) Required licenses for the RTG at PMR must be obtained prior to the arrival of the fuel.
- (15) The use of an RTG at PMR will present many new problems pertaining to storage, operational procedures, recovery and safety. Therefore, any requirements and/or changes in the launch complex that are necessary to launch the satellites should be specified as early as possible, since a six-month lead time is required to make modifications.
 - (a) The RTG fueling machine installation on PALC-1 or PALC-2 shall be completed and checked out at least six calendar weeks prior to first launch.
 - (b) The RTG fueling machine shall be ready for a simulated countdown at least four weeks before launch.

~~CONFIDENTIAL~~

MND-3393

0316587030

~~UNCLASSIFIED~~

~~CONFIDENTIAL~~

- (c) Positioning of the RTG fueling machine cannot start until completion of payload operations and removal of portable test equipment.
- (d) For each countdown, the RTG fueling machine shall be ready to start remotely controlled loading operations after completing preparations for tower removal, which normally occurs at 100 to 200 minutes before launch.
- (e) A maximum time of 60 minutes shall be allowed for the completion of RTG loading.
- (f) After completion of RTG loading, the launch stand shall remain clear of unprotected personnel until the tower is removed a safe distance from the launch vehicle.
- (g) The design of the RTG machine and support equipment shall permit a holding time of 200 minutes from completion of RTG loading operations to launch.
- (h) In the event of a launch cancellation or abort occurring after RTG loading, the machine and support equipment shall permit a further holding time of 70 minutes for return of the launch stand. The RTG remote unloading operations shall be completed no longer than 60 minutes after return of the launch stand.

C. REFERENCES

- Q-1. "Specifications for Shipping Containers; Interstate Commerce Commission Regulations, " Tariff 15, paragraphs 73.391, 73.393.
- Q-2. "Permits--Radioactive Materials, " Bureau of Explosives and Freight Loading and Container Section, 25-16-174.
- Q-3. "Summary Report of AEC Symposium on Packaging and Regulatory Standards for Shipping Radioactive Materials, " TID-7651.
- Q-4. "Permits--Spent Fuel Elements, " Bureau of Explosives, 25-16-174.
- Q-5. "Launch Site Operations Constraints for the Use of RTG in MACS, " MACS Program Office, Aerospace Corporation.

~~UNCLASSIFIED~~

~~CONFIDENTIAL~~

~~DECLASSIFIED~~ MND-3393