This is a preprint of a paper intended for publication in a journal or proceedings. Since changes may be made before publication, this preprint is made available with the understanding that it will not be cited or reproduced without the permission of the author.

UCRL - 74357

PREPRINT

Conf-721202--13

LAWRENCE LIVERMORE LABORATORY

University of California/Livermore, California

LASERS FOR FUSION SYSTEMS

T. J. Burgess

December 6, 1972

NOTICE

This report was prepared as an account of work sponsored by the United States Government. Neither the United States nor the United States Atomic Energy Commission, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness or usefulness of any information, apparatus, product or process disclosed, or represents that its use would not infringe privately owned rights.

This paper was prepared for submittal to Proceedings of the 1972 IEEE Nuclear Science Symposium, Dec. 4-8, 1972, Miami Beach, Florida.

MASTER

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

leg

T.J. Burgess

Lawrence Livermore Laboratory, University of California
Livermore, California 94550Abstract

The principles of initiating fusion by lasers and high-energy laser system technology are reviewed. Non-linear optical propagation at high intensities in laser amplifiers is described and is related to the system requirements for a laser used to produce fusion.

Introduction

In this paper we review those aspects of laser technology pertaining to the optical initiation of thermonuclear fusion. Rather than speculate about as-yet-undeveloped fusion reactors, we consider the relationship between the principles of initiating fusion by lasers and laser system design. We show that, with current technology, the development of a laser to demonstrate "breakeven" fusion is a formidable systems problem.

Principles of Fusion Initiation by Lasers

With the advent of the laser, it is possible to store energy at relatively low mean power in a population inversion of an atomic or molecular system. This energy can then be delivered in a collimated, coherent, intense optical pulse in a time of 10^{-10} sec or less. In addition, these coherence properties enable this ultrashort pulse to be focused into a diffraction-limited volume of approximately 10^{-8} cm³, yielding a very high energy density.

When energy is delivered to a pellet of thermonuclear fuel very rapidly by a laser, the resulting plasma can be inertially confined. The confinement time is the time required for a rarefaction wave to propagate from the boundary of the burning fuel to the center. For a sphere of hot plasma, this time is proportional to the radius, r , divided by the speed of sound (about 10^8 cm/sec).

Analogous to the low density CTR Lawson criterion, an inertially confined, laser-heated plasma must satisfy the condition $\rho r > 1$ g/cm² at a temperature of 5 to 10 keV for an efficient burn, where ρ is the mass density. These values of ρr can be achieved by spherical compression to super-high densities¹ (10^3 to 10^4 times liquid density). From purely geometric considerations, compression increases the density faster than it decreases the radius. This density increase reduces the fuel mass and laser energy required for a thermonuclear burn. With a sufficiently large ρr product, α -particles produced by the burn are absorbed within the reacting volume, providing further heating.

Compression to super-high density can be obtained with an appropriately shaped laser pulse uniformly irradiating the pellet. It has been shown¹ that the optimum laser pulse intensity dependence is closely proportional to $(1 - t/\tau)^{-2}$ where τ is the transit time of the initial shock wave. The initial laser intensity increases relatively gradually, generating a

barely supersonic shock wave. A low density atmosphere is ablated from the pellet, imploding the core and smoothing perturbations of the incident energy deposition and implosion symmetry. The laser intensity is then varied so that the compression is isentropic.

Because lasers are definitely energy limited, very small pellets must be compressed to super-high densities, both to minimize the fuel mass required and to obtain at least as much fusion energy output as laser pulse energy input. This is defined as "breakeven" fusion. The inertial confinement time is small; therefore the laser pulse must be short. For a 10^4 J shaped laser pulse, the last half of the energy must be delivered in 10^{-10} sec. For a 10^3 J pulse, this time shortens to 2×10^{-11} sec. This yields a prescription for the laser.

Nd:Glass Laser Technology

The details of the generation and diagnostics of ultrashort laser pulses have been presented by DeMaria, et al² and Duguay, et al³, respectively. It is the goal of this section to review the current status of the technology of large laser systems with application to thermonuclear fusion. We will confine the scope of this discussion to neodymium-doped glass laser.

The Oscillator

The schematic of a typical laser system is shown in Fig. 1. The oscillator (A, Fig. 1) is mode-locked² to produce a pulse train of ultrashort pulses (of the order of 10^{-10} sec or less) and a separation of a few nanoseconds. The energy of each pulse is only a few millijoules. The wavelength is 1.06μ (near infrared). Mode-locking is accomplished by the introduction of a saturable absorber in the optical resonant cavity of the laser oscillator. Nonlinearities due to the presence of the saturable absorber couple (or "lock") the longitudinal resonances of the optical resonator into phase synchronization. These resonances can then be considered as the equivalent of the elements of a Fourier series. Because the spectral extent of this space of Fourier components is very broad, the resultant pulse is very short.

In principle, a mode-locked oscillator should produce a pulse duration equal to the inverse of the bandwidth of the laser gain medium. However, with Nd:glass oscillators this is not the case, due to the nonlinear optical propagation processes which occur in the laser medium (treated in the next section). Nd:glass oscillators typically produce a pulse duration much longer than the inverse bandwidth of the gain spectral width. The "unused" bandwidth results in subpicosecond amplitude modulation of the pulse envelope and/or a frequency chirp of the optical carrier.

The oscillator and small-diameter preamplifiers of a large Nd:glass laser system utilize a crystalline material (neodymium doped yttrium aluminum garnet - Nd:YAG) as the laser medium, since this material is

*This work performed under the auspices of the U.S. Atomic Energy Commission.

Fig. 1. Schematic diagram of large laser system: (A) oscillator; (B) switch-out; (C) rod amplifier; (D) beam expansion telescope; (E) disk amplifier.

much less susceptible than glass to nonlinear effects. In addition to the minimization of nonlinear optical propagation effects, this material has a relatively high thermal conductivity compared to glass, permitting a fast repetition rate. This is especially useful for diagnostic and alignment purposes. Nd:YAG is currently available only in small diameters due to the limitation imposed by crystal growing technology.

The duration of the individual pulses emitted by the oscillator can be increased by the introduction of interferometric bandwidth limiters in the resonant cavity. Typically, a mode-locked Nd:glass oscillator produces a 5 to 10 psec pulse, although the bandwidth will permit 0.4 psec, and a Nd:YAG oscillator produces a bandwidth-limited 8 psec pulse.

The Switch-Out

The switch-out (B, Fig. 1) is a gated electro-optic shutter used to select a single pulse from the train produced by the mode-locked oscillator and to transmit it to the amplifier chain. The window width of the shutter is adjusted to select only one pulse.

Accompanying this pulse is a "pedestal" comprised of amplified spontaneous emission which is always present in the oscillator cavity. Although of low intensity relative to the laser pulse, this pedestal could contain a great deal of energy since it is coupled to the optical amplifier chain during the duration of the switch-out window width. This extraneous and unprogrammed background energy could be further amplified to both degrade system performance and disturb the time-dependent intensity at the fuel pellet.

The detection and measurement of background energy and spurious satellite pulses is currently a developmental effort.

The Amplifier Chain

A chain of laser amplifiers is required to increase the pulse energy since the oscillator and switch-out provide only a few millijoules. The amplifier chain consists of a series of individual stages of sequentially increasing aperture (C, D, C, D, Fig. 1). This aperture increase is needed to keep the pulse energy per unit area below the breakdown value, minimizing damage to the amplifiers as the total energy increases. Beam expansion telescopes are used between the stages.

Although the glass host material can be cast in large diameters, the maximum aperture of a rod amplifier is limited by optical pumping considerations. At large diameters, neodymium ions at the center of the rod are screened from the flashlamp pump light by those near the rod surface. Therefore an annular distribution of population inversion is created, reducing the effective lasing aperture of the rod.

This problem can be circumvented by using disks in the final amplifier stages in place of rods (E, Fig. 1). The disks are placed in the beam at the Brewster's angle to eliminate interface reflections for the laser polarization. The flashlamps are arrayed around the disks so that the pump light enters the material through the broad faces. Since each disk is thin compared to the diameter, a uniform population inversion is established, both axially and radially.

The maximum aperture of a disk amplifier is determined by the transverse and circumferential depletion modes of the population inversion. In an amplifier, the maximum population inversion is synchronized to the arrival time of the laser pulse. Unless care is taken before arrival of the laser pulse, spontaneous emission processes in the amplifier can deplete the energy storage. This process is termed "prelasing." Transverse and circumferential prelasing are minimized by limiting the disk diameter and suppressing reflections at the edge. Longitudinal prelasing in the backward direction is controlled by inserting optical isolators in the beam line. In the forward direction, this could be controlled by fast optical shutters.

For a 10-10 sec pulse, an experimental number for the damage threshold of laser glass is about 10 J/cm². The practical limit of laser rod diameter is about 6.4 cm. Using the more conservative figure for damage threshold of 4 J/cm² yields a total output energy of 130 J from the largest diameter rod stage. This more conservative figure is used because of nonuniformities in the population inversion and because a rod of this size is very expensive to replace. A typical diameter for a disk is 14 cm. When inclined at the Brewster's angle, this provides an aperture of 45 cm². Using the larger damage threshold figure (because disks cost less than rods) yields a maximum output of 450 J from a multi-element disk amplifier.

Increased knowledge about the damage mechanisms and the ability to design larger diameter disk amplifiers will raise this energy. However, these estimates assume a uniform, smoothly varying laser beam cross-section. The presence of "hot spots" (due to nonlinear effects, diffraction, or interference) will cause localized damage at overall energy levels much less than these estimates.

Multichannel Systems

When the aperture limit for the amplifier chain has been attained, it is then necessary to split the beam into two or more parts. This beamsplitter is followed by additional amplification up to the aperture limit in each channel (Fig. 2). Each of these beams can be split and amplified. Subdivision into many parallel channels can be taken as far as system stability and reliability will permit. The result is to multiply the maximum energy output of an amplifier chain by the number of parallel channels.

The outputs from these channels are deflected to impinge upon the target chamber and focusing lenses,

Fig. 2. Schematic diagram of multichannel laser system (isolators not shown).

equally spaced through 4π steradians. This serves to irradiate the fuel pellet in a nearly uniform manner.

To implement multichannel laser systems will require development of optical components such as beamsplitters and turning prisms which will endure these very high pulse intensities. Development is also required of low loss, high extinction optical isolators to protect the laser system from reflections by the target plasma.

Nd:glass lasers are only about 0.1% efficient. Therefore a 10^4 J system will require about 10 MJ of energy storage to drive the flashlamps.

The Effects of Nonlinear Propagation

In this section we review some aspects of the nonlinearities in the propagation of very intense

optical pulses through inverted media, i.e., media in which a population inversion has been established. The effects considered are gain saturation and nonlinear index of refraction.

Gain Saturation

Saturation of the gain of a laser amplifier occurs at high photon flux, causing distortion of both the time and radial intensity dependence of the pulse. In the low intensity region, small-signal conditions hold and all parts of the pulse are amplified as an exponential function of distance. However, as the pulse is amplified the leading portion contains sufficient photons to deplete the population inversion

by stimulated emission. The photons in the trailing portion of the pulse encounter this depleted inversion and therefore are amplified less. Preferential amplification of the leading edge causes it to steepen relative to the pulse tail, yielding distortion of the time dependence of the pulse. An initially symmetrical pulse will thus have its shape "skewed forward."

The pulse generated by a well designed oscillator has Gaussian radial dependence of the intensity. The center region, being initially more intense, encounters gain saturation sooner than the edge region. The edge region continues to be amplified exponentially, causing the edge intensity "to catch-up" with that in the center. The pulse then propagates uniformly, saturating the amplifier across the entire aperture, except for truncation effects at the extreme edge.

Nonlinear Index of Refraction

At very high intensities, the index of refraction of all optical materials becomes dependent on the pulse intensity. This causes three effects: material damage (self-focusing); pulse shape distortion (self-steepening); and pulse spectral broadening beyond the gain spectral width of the amplifier chain (self-phase modulation).

The index of refraction of all materials can be expressed as a function of the optical electric field, E , of the light wave as

$$n = n_0 + n_2 |E|^2$$

where n_0 is the low intensity index, n_2 the optical Kerr constant characteristic of the material, and $|E|^2$ is a time average proportional to the pulse intensity. For materials with electronic polarizability, this perturbation to the index occurs on a time scale of the order of 10^{-14} sec.

A pulse of Gaussian radial dependence will propagate through the laser chain with the edge region moving faster than the center. This occurs because the intensity (and hence the index of refraction) is greater in the center. This radial velocity distribution with a maximum at the edge causes the wavefront to become convergent towards the center and the pulse self-focuses. Once this process begins, it occurs with ever-increasing speed because focusing serves to increase the center intensity even more. Damage to the laser material happens when the center intensity exceeds the damage limit. This phenomenon is accentuated by hot spots in the beam.

The nonlinear index of refraction also distorts the pulse time dependence. The pulse maximum will propagate at a lower velocity than both the leading and trailing edges due to the intensity-dependent index. Therefore, in a frame of reference moving with the pulse maximum, the leading edge will run forward and the trailing edge will catch-up. In the limit, the pulse shape becomes triangularly shaped, with the intensity maximum at the very end. This is termed self-steepening.

Because the different intensity components of the pulse propagate at different velocities, radial and time-dependent phase differences occur. This time-dependent self-phase modulation creates frequency sidebands which broaden the pulse spectrum. Broadening of the pulse spectrum outside of the spectral width of the amplifying medium transfers energy outside the gain spectrum, decreasing system performance. Interference effects among these sidebands result in the presence of picosecond and subpicosecond amplitude modulation of the pulse envelope. High-frequency amplitude modulation can also lead to temporal hot spots which will self-focus.

Other nonlinearities exist such as stimulated Raman scattering, stimulated Brillouin scattering, and non-

linear absorption due to two-photon absorption. The effects on the pulse shape resulting from gain saturation will be superimposed on those produced by nonlinear index of refraction; however, the exact interrelationships are complex. Computer codes are being written to study them.

Conclusion

We have reviewed the laser pulse requirements for thermonuclear burn, the technology of short-pulse, high-energy laser systems, and presented a phenomenological description of the nonlinear propagation processes which occur in them.

These nonlinear processes lead to distortion of the pulse shape in both time and space, catastrophic self-focusing of the beam, and broadening of the pulse spectrum. These effects must be accounted for in order to develop a system that will provide a pulse of well-characterized shape.

To achieve such a system, each of the elements must be designed for optimum performance and durability. Also, the system as a whole must be computer modeled and designed to minimize propagation nonlinearities. It is very important to reduce the probability of damage both to maximize the number of shots between component failures and to reduce the system downtime required for optical alignment after the replacement of a damaged component.

The system must also be designed to function in the vicinity of a small thermonuclear explosion. Radiation vulnerability of the optical components must therefore be considered.

Due to the complexity of a large system, the controls and interlocks must be computerized. As much as possible, the diagnostic information should be computer processed also.

Let us define a laser system of 10^4 J pulse energy at the target in a total duration of 0.1 nsec as one suitable to produce breakeven thermonuclear fusion. This design goal is considered in order to allow pulse shaping after the amplification. A good approximation of a shaped pulse could be constructed by a superposition of time delayed pulses from the many parallel channels. This enables pulse shaping independently of nonlinear processes in the amplifiers. We have seen that our present technology requires probably 20 parallel channels of amplification to yield this energy. It is not unreasonable to expect that computer designed disk amplifiers and laser systems will reduce this number to 6 to 10 parallel channels. Given the present reliability of laser system elements, a 20-channel system is probably too complex to function with any degree of reliability. A 6 to 10 channel system, with improved component reliability, seems feasible. This remains, however, a formidable systems problem.

References

1. J. Nuckolls, L. Wood, A. Thiessen, G. Zimmerman, "Laser Compression of Matter to Super-High Densities," Proc. 7th International Quantum Electronics Conference (Montreal, May 1972).
2. A.J. DeMaria, W.H. Glenn, Jr., M.J. Brienza, and M.E. Mack, "Picosecond Laser Rules," Proc. IEEE, 57 (1) 2-25 (Jan. 1969).
3. M.A. Duguay, J.W. Hansen, S.L. Shapiro, "Study of the Nd:Glass Laser Radiation," IEEE J. Quant. Elect., QE-6 (11) 725-743 (Nov. 1970).