RECEIVED BY DTIC SEP 23 1968

LEGAL NOTICE

This report was prepared as an account of Government sponsored work. Neither the United States, nor the Commission, nor any person acting on behalf of the Commission:

A. Makes any warranty or representation, expressed or implied, with respect to the accuracy, completeness, or usefulness of the information contained in this report, or that the use of any information, apparatus, method, or process disclosed in this report may not infringe privately owned rights; or

B. Assumes any liabilities with respect to the use of, or for damages resulting from the use of any information, apparatus, method, or process disclosed in this report.

As used in the above, "person acting on behalf of the Commission" includes any employee or contractor of the Commission, or employee of such contractor, to the extent that such employee or contractor of the Commission, or employee of such contractor prepares, disseminates, or provides access to, any information pursuant to his employment or contract with the Commission, or his employment with such contractor.

ANNUAL REPORT

COMPUTER SYSTEMS RESEARCH

SEPTEMBER 1, 1967 to AUGUST 31, 1968

PART A: PROFESSOR GEAR; PART B: PROFESSOR POPPELBAUM

MASTER

This document summarizes the research performed on contract AEC 1469 and provides references to the many publications throughout the year. In the two paragraphs below some highlights of Parts A and B respectively are given so as to acquaint the reader with the major trends in our work.

The major achievement of Part A during this period has been the completion of the graphic programming system using a remote graphic terminal on the ILLIAC II time-sharing system. This system was successfully demonstrated at a graphics conference held in Urbana and aroused much audience interest. A second highlight of the year's activities has been the implementation of the numerical section of the automatic differential equation solve. It has made it possible to integrate stiff equations with a thousand-fold improvement in speed. Details of Part A can be found starting at page 3.

The work in Part B has led to the satisfactory completion of the two advanced hybrid systems, the "Tri-Color Cartograph" and the "Information Redistribution Bandwidth Compression": It has effectively become possible to color regions of a tri-color tube by the simple action of pointing a light pen, and it has also become possible to reduce the bandwidth in the transmission of line drawings with less than 32 elements by a factor of well over 10--this without loss of definition and in real time. A major breakthrough occurred in our electro-optics work where the feasibility of On-Line Fourier Transformations, with a KDP crystal as the original information carrier, was demonstrated. It should be underlined that this system

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency Thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

will be at the basis of work in the area of 3D displays. Details will be found starting at page 15.

ANNUAL REPORT PART A
SOFTWARE SYSTEM RESEARCH
SEPTEMBER 1, 1967 to AUGUST 31, 1968

1. Summary

The program for the last contract period covered the following items:

- A-1. Graphic programming research on a flow chart programming system
- A-2. Implementation of a subsystem within the 360 system to provide terminal facilities
- A-3. Implementation of numerical programming packages
- A-4. Terminal design in a multi-processor system
- A-5. Support of Illiac II for research use

The work in each of these sections is described below.

Project A-1 has come to a stage of success in that an operating flow chart programming system is now complete. Work on part A-2 has continued throughout the year. The numerical work proposed by part A-3 has had considerable success. Part of a remote graphic terminal has been designed as under A-4, and the Illiac II has provided a small scale time showing service for support of these projects.

2. The Flow Chart Programming System and Related Graphics Projects

The objective of this project has been to explore the ways in which a remote graphic terminal can be used to aid in the programming process. The use of flow charts as the form of the program has been studied in relation to questions concerning the hardware requirements and limitations of the terminal and transmission speed between the terminal and the main computer. From a software standpoint, the properties of flow charts have been exploited to provide better debugging capabilities and ease of subroutining. The short term result of this project has been the implementation of a system on the DEC 338 and the ILLIAC II which enables the user to draw flow charts and execute them.

The flow chart is drawn completely at the remote terminal. It can be edited without any interaction with the main computer, thus reducing the effective load on the time sharing system. Flow charts can be transmitted between the terminal and the ILLIAC in a symbolic list structured form for display or execution. The language used inside the flow chart boxes is currently a polish prefix language with a number of built in primitive operations for arithmetic and list manipulation. The user can define any character sequence as a new primitive by means of a flow chart subroutine. The language is executed, by an interpreter, directly from the list structured symbolic form. Flow charts can be traced visually during execution by slowing down the execution rate, and various forms of debugging by trapping at control points or data points are possible. The name of a datum can be given to a subroutine, for example, so that whenever that datum is referenced, a trap occurs to the subroutine. Since each symbolic name acts like a stack for new definitions, the preceding definition is available "underneath" the present one, so that the accessing of any data can be monitored. A typical flow chart with two subroutines is shown in Figure 1, while its use via the DEC 338 teletype is shown in Figure 2.

A start has been made on the implementation of a similar system on the IBM 360/DEC-338 combination. The current status of the work is reported in [3], [13], and [14].

Figure 1. INTG and INTG₁ Routines

Underline indicates output from the ILLIAC II. Comments in lower case.

LOAD: transmit the flowchart poly to the ILLIAC II

SETIME 2: set the time in seconds to be taken between executing boxes

MTRACE < POLY > : trace the flowchart poly

= GRAPH POLY 1 : PRINT GRAPH: execute poly with the argument 1, store
result in graph

GRAPH =2.00000000000000 printed value of graph from ILLIAC II

= GRAPH POLY 2 : PRINT GRAPH: the argument is 2

GRAPH =9.00000000000000

= GRAPH POLY 0:PRINT GRAPH: the argument is 0

GRAPH =3.00000000000000

= GRAPH POLY - 0 2:PRINT GRAPH: the argument -2

GRAPH =3.00000000000000

LOAD: transmit the flowcharts INTG and INTG1

MTRACE < INTG1 >: trace the flowchart INTG1

= GRAPH INTG - 0 1 1 < POLY > : PRINT GRAPH: integrate poly from -1
to 1

GRAPH =4.8333330154418 result

= GRAPH INTG - 0 1 2 < POLY > : PRINT GRAPH: integrate poly from -1
to 2

GRAPH =9.6665039062500 result

Figure 2, Text Communication with ILLIAC II

A package has been implemented in Fortran which provides the user with a drawing language. It works under the batch system and enables a library of drawings to be built up. They can be output on the CalComp. The work was the basis for a Master's thesis [1].

3. Automatic Integration of Ordinary Differential Equations

The goal of this project is to handle ordinary differential equations completely automatically using a combination of symbolic and numerical techniques. The equations will be input in symbolic form, either into a batch processing system or on-line via a remote terminal, and the user will only be required to specify initial values, where printing should occur, when to stop, and what accuracy is desired. The package will choose the order of the method and the step size automatically. A terminal-oriented package has previously been implemented for the ILLIAC II system and is reported in [30]. That package relied on a question-answer mechanism with the user to determine many of the parameters of the method. Since that time a greater understanding of the numerical problems of stiffness has been achieved and is reported in [31]. New methods were reported there and these are now used in that package. In addition numerical schemes for automatic controlling the order as well as the step size have been developed and tested extensively. These results will be reported at IFIPS this summer. See [15]. The details of the automatic control are set down in [9].

The current status of this project is that the numerical part of the package has been implemented, debugged, and numerically tested. It has had considerable success handling sets of equations that it was previously not possible to integrate. In particular, sets of equations arising from a chemical reaction problem caused by the exposure of solutions to radiation has been handled in conjunction with Dr. Fricke. This problem had previously failed on the packages at the Danish Risø National Laboratory and the Argonne National Laboratory. The symbolic phases of the package include a syntax-directed compiler which is now operational on the 360, and a symbolic differentiator followed by a compiler which is intimately linked to the syntax-directed compiler. The differentiator is written and partially debugged. The supervisory section of the program is almost completely debugged and it is now hoped to have an initial package available for the user in late summer.

4. Remote Graphic Terminals

The objective of this project is to determine in what way low-cost remote graphic terminals can be constructed from a system point of view. These terminals should be capable of communicating over low-speed phone lines and providing minimum computational facilities in the terminal itself to reduce the interference on the central computer for trivial tasks. Currently a single terminal is in development. It uses a disk for display refresh and backup storage, and a small core for providing minimum computational capabilities. The associated computer will primarily contain flexible block transfer instructions for moving data to and from the disk display file and the core, and to and from the core and auxiliary devices such as telephone lines, teletype, and the data area of the disk. Consideration must also be given to the implementation of instructions which generate the necessary information on disk for graphical display. The display will be driven by incremental code because it is felt that this is the most economical way. See, for example, [6]. It is also planned to consider the provision of "pointing devices" at a low cost. One technique to be considered is the use of a comparator to determine coincidence between an analog input signal and a beam deflection voltage. This is shown in Figure 3. It is a device found on most graphical input systems which do not use a light pen. Note that a comparator typically consists of two greater than or equal tests and an AND circuit. By adding the additional logic with the inputs L and M in Figure 3 the comparator can be turned into a greater-than-or-equal or a less-than-or-equal circuit. The inputs ϕ_x and ϕ_y serve to override the effect of the x and y comparisons. In its normal state with all three pairs of inputs L, M and ϕ set to zero, the output I occurs when the pointing device is in the vicinity of the CRT spot. By turning on ϕ_y , and driving the beam horizontally across the scope, (blanking if desired), an output will occur when only the x's match. This will take some time in practice because of the need to drive the scope through 1024 separate x positions if it is incremental. It can be done faster by also turning on L_x and going through a binary chopping process on the x deflection system. In this way the D to A converters of the scope system and the comparators of the pointer system can be used to effect a fast A to D conversion to determine the x-y position

of the point device. This could be done at the end of each display cycle automatically, thus reducing the effort on the part of the programmer in pen tracking. The "tracking cross" can be implemented in hardware at a very low cost. One way is to generate a sine and cosine signal and feed them into the points marked "x-cross" and "y-cross" in Figure 3 during the origin gap at the end of a display cycle. This will generate a small circle in the current position of the x-y register--which should have previously been set by the comparison steps. An actual cross could be generated, possibly more cheaply than a circle, by a circuit similar to the one shown in Figure 4.

One of the objectives of this project is to provide a useful experimental set up for graphical terminal design of a type that can easily be modified. In association with this one of the thesis topics now being started is an investigation of general micro programming control, and problems such as taking a given task, specified as a sequence of micro instructions each involving micro commands, and converting them into a different set of micro instructions. The purpose for doing this is to find the "best" set of micro instructions, but a program which can handle such conversions could also be used to convert software written for one configuration into software for another configuration with similar capabilities.

The present status of this project is that the disk, core, and graphic CRT display have been received. The disk, which is a data disk in-contact head device with 3000 bits per inch per track at 3 megacycles is being tested and appears to be very satisfactory. The core has been connected to control logic and checked out so that it is ready to be hooked to the CPU. The display controller has been built and checked out. It appears to be impossible to drive the present display above 1 megacycle, but a different Hewlett-Packard display was tested and it was found that we could handle 2 megacycles. Currently we are planning to hook it to the disk and run it at 1 1/2 megacycles or more in order to achieve maximum bit density on the disk. Before designing and constructing the CPU it has been decided to connect the disk to the 338. This will provide back-up storage for the 338 as an additional benefit, but it is principally being done in order to make it possible to generate programs and interpret for the new display CPU before it is constructed so that a number of designs can be considered.

Figure 3

Circuit

Cross Display

Signals

Picture

Figure 4. Cross Generation

5. On-Line Computation

Currently the ILLIAC II time sharing system provides a Fortran compile and execute system for a number of campus users. This means that the user has to learn, in addition to Fortran, the terminal language for this particular system. The effort in the new system is to provide a comprehensive computational system in which only one language is used. This language will be a subset of PL/I. Using the technique of APL, any input character string will be either a program line or a command depending solely on whether it contains a line number or not. If it contains a line number it will be saved as part of the current program, although it will be syntax analyzed immediately in order to allow the programmer to correct simple errors as soon as possible. If it does not contain a line number it will be executed immediately. If it is of the form of a simple arithmetic statement then it will provide a simple computational facility for the user. If it calls a previously defined subroutine then it will cause that subroutine to be interpretively executed.

The present status of this project is that Pass I, which handles the syntax analysis, is nearing completion. Pass II, which takes the symbolic polish output of Pass I and converts it to an absolute polish form where all symbolic references now point to tables, is planned and programming has started. Pass III which will execute the absolute polish form is partially coded and programs to interface with OS and with the ASP partition are being checked out. The 360 part of the system will operate in a partition of the 50. ASP will be in another partition. The auxiliary storage accessing will generally be handling the ASP partition while the interpretation will be done in the lower priority on-line computational partition. At the moment the PDP-7 will only be used to collect complete lines of characters and act as a multiplexor to the teletypes. After some experience has been gained it may be possible to move some of the syntax analysis over to the PDP-7. This work has been described in the Quarterly Reports listed in the bibliography.

6. Numerical Studies

A small group has been involved in the writing, collection and testing of numerical procedures in Fortran for use on any of the Department of Computer Science's computers. The major effort at the moment is in two areas. New schemes are being investigated for the numerical quadrature of functional integrals. Results have been reported in [12]. The other effort involves the preparation and testing of numerical procedures. Programs have been written here, obtained from Argonne, SHARE and the IBM scientific subroutine package. When more than one version was available they have been tested. In general the programs from Argonne and Illinois have proved better than those in SHARE. A recent project has involved the generation of random test matrices with known inverses, and using them to test various matrix routines. Sample results are shown in Figure 5. Matrices of order of 100 were generated by similarity transformations of a diagonal matrix. The diagonal elements were randomly generated with a distribution uniform on interval (0,1). The x-axis in Figure 5 shows condition number scaled by 10. This condition number is $||A|| ||A^{-1}||$ where

$$||A|| = \max_{1 \leq i \leq n} \sum_{j=1}^m |a_{ij}|$$

The y axis shows relative error in the inverse computed using subroutine DGELG (scientific subroutine package routine). Relative error here means

$$\frac{||A^{-1} - A^{-1}_{\text{computed}}||}{||A^{-1}||}$$

and norm is as defined above.

Remark: It is interesting to note that the error is closely proportional to the condition number rather than being spread over a broad range.

Some of this work has been reported in [8], [10], and [11].

Figure 5

ANNUAL REPORT PART B
PATTERN PROCESSING AND MEMORY RESEARCH
SEPTEMBER 1, 1967, TO AUGUST 31, 1968

1. Introduction and Summary

The proposed program for the last contract period covered the following items:

- B-1. Tricolor Cartograph
- B-2. On-line Fourier Transform
- B-3. Variable Interlacing
- B-4. Redistribution Bandwidth Compression
- B-5. Electroluminescent Store
- B-6. Creep Vidicon
- B-7. TRANSFORMATRIX

as well as some clean up work in the PARAMATRIX and ARTRIX projects of the two previous years.

In order to give an overall view of the achievements of the contract since its inception, Sections 4, 5, and 6 below summarize all the work done in the areas of Hybrid Circuit Research, Stochastic Information Processing, and Electro-Optics. The main feature to be noted is that projects B-1 and B-4 of last year's proposal were brought to successful conclusion: They, as well as the PARAMATRIX and ARTRIX projects, show the figure 100 in brackets after the project title in order to indicate their completion.

Both the operation of the Tricolor Cartograph and that of the Information Redistribution Bandwidth Compression system have been very satisfactory indeed. In the case of the Tricolor Cartograph, the feasibility of our on-line coloring scheme for regions defined by their boundaries (and not necessarily simply connected) has been proven. It is to be noted that the use of five megacycle hybrid circuitry together with man-machine feedback leads to a capability which cannot be equalled by a digital computing system of reasonable size. In the case of the Information Redistribution Bandwidth Compression scheme, extraordinarily

good definition of the "synthetic lines" reconstituted from the timing information sent over a narrow channel was observed. There is no doubt that such schemes are practically viable and affordable at reasonable cost.

Although project B-2 of last year's proposal is not completed, a major breakthrough was obtained in May of this year. It turned out that due to our exceedingly stringent conditions on optical flatness in the Ardenne Tube, it became effectively possible to produce an On-Line Fourier Transform from the video charge distribution on a KDP crystal and that this Fourier Transform was of sufficient quality to reconstitute the original image optically. In it's present state, the system has a definition of slightly less than 100 lines, but the near future will hopefully increase this a by factor 5. Even so, a minimum of 10,000 points are processed (with the appropriate gray scale) within $1/30$ of a second: That this performance is far beyond that of digital methods using the Fast Fourier Transform is evident.

Projects B-5 and B-6 were dropped from last year's program due to lack of funds and/or personnel. Project B-5 will not be taken up again in its original form because of sweeping changes in technology. The Creep Vidicon and TRANSFORMATRIX, however, appear in this year's proposal together with a whole series of new projects in the 3D-Display area.

2. Goals of the 1469-P Hardware Research Group

The overall goal of the Hardware Research Group is the exploration of new and uncommon forms of information encoding and processing. Four main areas are under investigation:

1. Hybrid digital-analog circuits and systems
2. Stochastic computing circuits and systems
3. Electro-optical devices and systems
4. Display devices and systems

3. History of the Group

The present Hardware Research Group started about 10 years ago as the Circuitry Research Group in charge of the implementation of Illiac II. It was responsible for the following technical innovations:

- 1) Current steering flip-flops and logic
- 2) Variable topology circuits
- 3) Flow gating
- 4) Selector gating
- 5) High sensitivity flip-flops with built-in gates
- 6) Speed independent computing circuits

More recently the group was responsible for high speed circuit research and championed the following ideas:

- 1) Virtual load two-wire information transfer
- 2) Auto-pump tunnel diode circuits
- 3) Active transmission lines

Three years ago, thanks to AEC financing, larger scale operations were made possible and led to contributions in the area of:

- 1) Multi-megacycle hybrid circuits
- 2) Stochastic computing circuits
- 3) Electro-optical processing
- 4) Static "intelligent" displays

4. Hybrid Circuit Research

4.1 PARAMATRIX (100) [Main project of 65/66 proposal]

The fundamental PARAMATRIX system shown in Figure 1 allows the digitization of an incoming line drawing or bubble chamber photograph into a 32 x 32 array of binary signals, in such a way that the digitization is preceded by electronic translation, rotation and magnification of the image. The system scans the output matrix and for each point, x_i, y_j forms

$$X_{ij} = (x_i \cos + y_j \sin) m+a$$

$$Y_{ij} = (-x_i \sin + y_j \cos) n+b$$

A very fast flying spot scanner decides in about one micro-second whether (X_{ij}, Y_{ij}) is on the input slide: If yes, matrix point x_i, y_j is made 1, otherwise it is left at the zero level. The circuits in PARAMATRIX combine analog and digital signals in the most intimate manner, meaning that all information signals are analog, while all steering signals are digital. All circuits are capable of 2 megacycle operation with .3% accuracy and allow a swing from -10 volts to +10 volts.

Figure 1. PARAMATRIX Block Diagram

4.2 ARTRIX (100) [Main project of 66/67 proposal]

The ARTRIX system, shown symbolically in Figure 2, has essentially the same properties as the MIT SKETCHPAD system, but differs from it by the fact that no back-up digital computer and core memory are necessary. The graphical information is stored in four memotron-vidicon pairs and on-line video processing gives the desired geometrical constructions on the display monitor. Drawing a circle with a given center and a given radius is accomplished by generating an expanding spiral which, upon touching a point on the circumference, is "frozen" and displayed for its last turn. ARTRIX allows construction of straight lines and circles, parallel translation, labelling and erasure.

Figure 2. ARTRIX Block Diagram

4.3 Tricolor Cartograph (100) [Project B-1 of last proposal]

The TRICOLOR CARTOGRAPH is an on-line hybrid machine with a tricolor display tube and a video storage disc. On-line hybrid processing allows the operator to indicate the inside of a region delineated by a boundary and to color it red, green or blue at his choice by pushing an appropriate button. The overall principle is shown in Figure 3: The light pen generates a vertical through the indicated point and the hybrid computer colors every scan line intersecting this vertical between the boundary that is to the left and the boundary that is to the right of it. If portions of the area are not colored in this way, a slight movement of the pen will correct the situation.

Figure 3. Operation of Tricolor Cartograph

4.4 Information Redistribution Bandwidth Compression System (100)

[Project B-4 of last year's proposal]

In this system the times taken for a scanning beam to move from the lefthand edge to successive intersections of the lines of a drawing are measured electronically and stored as numbers in a sequence of 32 registers (see Figure 4). While the next line is being scanned and the results stored in a second group of 32 registers, the numerical contents of the first set of registers are read out at steady 2 microsecond intervals. The receiver stores the contents of the registers, and the beam of the display CRT is lit up at the times indicated by the receiving register. It is easy to see that in this fashion the worst case for bandwidth, i.e. all 32 lines for instance in the upper lefthand corner, is eliminated by taking a whole line scanning interval of 64 microseconds to transmit the necessary information. It is possible to complement the system by an automatic bandwidth adaptor such that 16 kilocycles of bandwidth are necessary for each line in the drawing.

Figure 4. Principle of the IRBC System

4.5 Vista System (Variability Interlaced Scan Television Apparatus)

(20) [Project B-3 of last year's proposal]

The VISTA System, shown symbolically in Figure 5, explores the possibility of synchronized pseudo random scanning in which the number of lines per frame is made a function of the variation in information content in adjacent frames. To this effect a video disc stores the successive frames, and the integrated output of a difference amplifier (connected between two tracks) controls the number of lines in digital steps, i.e. 512, 256, 128, 64, 32, and 16. In order to compensate for small line numbers, the receiver contains a variable persistence display, in which the integration constant is made inversely proportional to the number of lines. In extreme cases, i.e. when nearly static displays are to be transmitted, the system will integrate over 32 frames and use a one second build-up time for its output. If all information changes between two frames, the integration time will be reduced to 1/30 second and a 512 line frame is transmitted. The principal goal of the project is to explore the elimination of picture roll by the pseudo random scanning system, as well as the use of variable scan rate vidicons and variable persistence output devices.

5. Stochastic Information Processing

5.1 Fundamental Idea of Stochastic Representation (100)

The goal of stochastic variable representation inside computers is to simplify to the utmost the hardware necessary for the fundamental operations of arithmetic. To this end an arrangement according to Figure 6 is used to convert an analog voltage δ into a random pulse sequence such that pulses can only occur in given time slots, and that the probability of the occurrence represents the (normalized) variable value. It is evident that multiplication of two variables can be simply obtained by running the corresponding pulse sequences into an AND circuit: The probability of an output pulse is equal to the product of the input probabilities. Two types of processing have been investigated: One in which the operations of arithmetic are done by feedback steering of appropriate random pulse generators, and the other using purely digital processing. The latter type is now favored because of the potentially much higher precision that can be

Figure 5. Block Diagram of the Vista System

obtained. This precision is of the order of 10% for an average sample of 100 pulses, 1% for a sample of 10,000 pulses and .1% for 1,000,000 pulses. Buffering has to be used to store pulses in case of coincidences in addition, non-presence of a pulse in the subtrahend in subtraction, etc. It is interesting to note that the rules corresponding to the four fundamental operations of arithmetic shown in Figure 7, and realized in the general computation element, are:

1. Multiplication: Put out a pulse when pulses come in simultaneously.
2. Addition: Put out a pulse if a pulse comes in on one line or the other (by an OR circuit) and store a pulse occurring on coincidence until a free slot is found in the output sequence.
3. Subtraction: Subtract the subtrahend pulse from the minuend pulse if present, otherwise on the next occasion when a minuend pulse occurs.
4. Division: For each dividend pulse, start an output sequence of pulses upon occurrence of the next divisor pulse which lasts until one more divisor pulse occurs.

More recently a system of representation was investigated in which numbers are represented as quotients, the numerator and denominator being represented by random pulse sequences. It can be proved that in this representation no buffer storage is necessary and that all operations of arithmetic can be done with combinatorial logic only.

5.2 TRANSFORMATRIX (20) [Project B-7 of last year's proposal]

TRANSFORMATRIX is an application of stochastic processing in which the light values furnished by a 32 x 32 photodiode matrix are transformed into 1024 stochastic sequences. These sequences are multiplied one by one by 1024 weights, defined by a weight matrix or more exactly by their stochastic sequences. The result of the multiplication and addition of all terms is displayed on a 32 x 32 output matrix, the coefficient matrix being a function of the output point. The 1024 x 1024 coefficients necessary to do this operation define all possible (quantized) translations, rotations, magnifications, convolutions, conformal mappings and even Fourier Transforms. The principle of the system is shown in Figure 8. In the model presently being designed, the coefficients corresponding to each output point are calculated by a small special purpose computer, illustrating the fact that memory space and computational ability are often interchangeable.

Figure 6. Analog to Stochastic Conversion

Figure 7. The Four Fundamental Operations using Stochastic Sequences

Figure 8. TRANSFORMATRIX Principle

6. Electro-Optical Work

6.1 On-Line Fourier Transform (80)

The On-Line Fourier Transform System is shown in Figure 9 and consists essentially of an Ardenne tube, illuminated by a continuous laser, and an optical system forming a spatial Fourier Transform in the focal plane of a lens. The Ardenne tube contains a KDP crystal which is scanned by an electron beam, so that the charge distribution represents a video picture. This charge distribution is translated into a modification of the state of polarization of the laser light, which can be detected by an analyzer between the lens and the Ardenne tube: Essentially we have an instant transparency, produced electronically. During the month of May, the feasibility of the system was demonstrated by producing the on-line fourier transform of a video picture with a resolution of approximately 100 lines. The quality of the transform was sufficient to reconstitute the original image optically.

Figure 9. OLFT System

6.2 Noise Elimination Project (50)

As shown in Figure 10, periodic noise superimposed on a video signal corresponds to a striation of the picture. This striation varies from one frame to the next by translation only and the Fourier Transform of the striation remains constant. Periodic noise in interplanetary television can therefore be eliminated by sending a sequence of frames of the form "noise only", "video plus noise", etc. It is then possible to subtract the Fourier Transform of the noise from the Fourier Transform of the composite signal for noise elimination purposes: The inverse transform of the difference contains much less noise.

Figure 10. Periodic Noise in Adjacent Video Frames

Bibliography for 1469 -- Gear

Reports and Theses

1. Henderson, D. A., A Graphics Display Language, Department of Computer Science Report #240, August, 1967, M.S. Thesis.
2. Otis, A. B., Jr., An Analog Input/Output System for the ILLIAC II, Department of Computer Science Report #246, September, 1967, M.S. Thesis.
3. Richardson, F. K., Graphical Specifications of Computation, Department of Computer Science Report #257, April, 1968, Ph.D. Thesis.

File Numbers

4. Lopeman, Harold F., Information on the DEC 360 Communication Control Unit, Department of Computer Science File #738, October, 1967.
5. Richardson, F. K., A User's Description of the Computer Aided Programming System (CAPS) Programs on the DEC 331, Department of Computer Science File #739, December, 1967.
6. Carter, C. E., et al., A Status Report on the Design and Construction of a Remote Graphics Terminal, Department of Computer Science File #742, February, 1968.
7. Otis, A. B., Jr., Programming the PDP-7 2701 Channel, Department of Computer Science File #747, March, 1968.
8. Gear, C. W., A Set of Simple Test Matrices for Eigen Value Programs, Department of Computer Science File #751, April, 1968. Submitted to Math. Comp.
9. Gear, C. W., The Control of Parameters in the Automatic Integration of Ordinary Differential Equations, Department of Computer Science File #757, May, 1968.

Publications

10. Fosdick, L. D., A Special Case of the Filon Quadrature Formula, *Math. Comp.* 22, No. 101, January, 1968.

To be Published or Presented

11. Chase, S. M., and Fosdick, L. D., An Algorithm for Filon Quadrature, Accepted for the Communications of the ACM.
12. Fosdick, L. D., and Jordan, H. F., Approximation of a Conditional Wiener Integral, Accepted for the Journal of Computational Physics.
13. Gear, C. W., Lo, T-Y, and Richardson, F. K., A Computer Aided Programming System, Proceedings of the Graphics Conference held at the University of Illinois. Expected publication date, June, 1968. Benjamin Press.
14. Gear, C. W., Graphical Computer Aided Programming Systems, to appear in the Proceedings of the International Graphics Conference to be held at Brunel University, London, July, 1968.
15. Gear, C. W., Automatic Integration of Stiff Ordinary Differential Equations, to be presented at the IFIPS Conference, 1968.
16. Jordan, H. F., and Fosdick, L. D., Three Particle Effects in the Pair Distribution Function for He⁴ Gas, Accepted for The Physical Review.
17. Greninger, Larson, Automatic Programming Methods with Microprogrammed Control, Ph.D. thesis proposal, May, 1968.

Display User's Memoranda

18. Richardson, F. K., The Hardware Connection Between the PDP-8 and the PDP-7/630, DUM #2, August 3, 1967.
19. Richardson, F. K., A Description of the PDP-8 Program SYSTEM, DUM #4, August 10, 1967.
20. Richardson, F. K., Light Pen Sense Indicate Flipflop, DUM #5, August 21, 1967.
21. Richardson, F. K., A Note on the Five Fingered Keyboard, DUM #6, August 21, 1967.
22. Richardson, F. K., Stopping the Display from the PDP-8, DUM #7, August 21, 1967.
23. Richardson, F. K., Memory Testing, DUM #8, August 25, 1967.
24. Richardson, F. K., Memory Testing and Idle Use of the 338, DUM #9, September 13, 1967.

25. Richardson, F. K., Memory Test Routine for Use on the Idle 338, DUM #10, November 21, 1967.
26. Richardson, F. K., The Inclusion of Additional Switches with the Joy Stick Package and the Attachment of the Resulting Device to the PDP-8, DUM #11, January 29, 1968.

Quarterly Progress Reports

27. July - September, 1967
28. October - December, 1967
29. January - March, 1968

Earlier Papers Referenced

30. Gear, C. W., Numerical Integration of Ordinary Differential Equations at a Remote Terminal, Proceedings 21st National ACM Conference, August, 1966.
31. Gear, C. W., Numerical Integration of Ordinary Differential Equations, Math. Comp. 21, #98, pp. 146-156.

BIBLIOGRAPHY (Relevant to 1469 - Poppelbaum)

QUARTERLY TECHNICAL PROGRESS REPORTS

1967 - I, II, III, IV.

1968 - I

Report	Title	Author	Date
249	A Slide Scanner Input for Paramatrix (M.S. Thesis)	L. Ryan	10/67
255	Analog Computation with Random Pulse Sequences (Ph.D. Thesis)	C. Afuso	1/68
Not yet assigned	Electro-optical Switching Matrix (Ph.D. Thesis)	T. Koo	6/68
	On the Solution of Systems of Boolean Equations (M.S. Thesis)	H. S. Schweitzer	6/68
	Storage of Analog Variables in Delay Lines (M.S. Thesis)	L. H. Wallman	6/68

PUBLICATIONS OF W. J. POPPELBAUM

- "Adaptive On-Line Fourier Transform", Proceedings of the Symposium on Automatic Photo Interpretation, Washington, D.C., May 31 to June 2, 1967.
- "Hybrid Graphical Processors", Manchester Computer Technology Conference, Manchester University, Manchester, England, July, 1967.
- "The Phastor, A Simple Analog Storage Element", with D. Aspinall, Manchester Computer Technology Conference, Manchester University, Manchester, England, July, 1967.
- "Stochastic Computing Elements and Systems" with C. Afuso and J. W. Esch, Fall Joint Computer Conference, 1967.
- "Paramatrix puts Digital Computer in Analog Picture and Vice Versa", with M. Faiman and E. Carr, Electronics Magazine, pps. 99-108, September 4, 1967, Vol. 40, #18.
- "What is Next in Computers?", Advances In Computers, Vol. 9. [To be published]
- "Opto-Electronic Switching Matrix", with T. Koo, St. Louis, Mo. Micro-electronics Conference, June, 1968. [To be published]
- "Uncommon Electro-Optics for Display and Processing" with M. Faiman, Wescon, 1968. [To be published]