PERFORMANCE EVALUATION OF A CERAMIC CROSS-FLOW FILTER
ON A BENCH-SCALE COAL GASIFIER

Westinghouse Principal Investigators
D. F. Ciliberti and T. E. Lippert

Sixth Quarterly Report
January 1, 1986 - March 31, 1986

Contract Number DE-AC21-84MC21338

DOE Project Officer: Randall J. Dellefield
Department of Energy
Morgantown Energy Technology Center
P.O. Box 880
Collins Ferry Road
Morgantown, WV 26505

DISCLAIMER

This report was prepared as an account of work sponsored by the United States Government. Neither the United States nor the United States Department of Energy, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, mark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

PATENT STATUS

This technical report is being transmitted in advance of DOE patent clearance and no further dissemination or publication shall be made of the report without prior approval of the DOE Patent Counsel.

TECHNICAL STATUS

This technical report is being transmitted in advance of DOE review and no further dissemination or publication shall be made of the report without prior approval of the DOE Project/Program Manager.

OVERALL PROGRAM OBJECTIVES

The Department of Energy is currently supporting a program that will aid in the development of cross flow filtration technology as applied to combined cycle power generation with coal gasification. The stated overall goal is to gain information on both the operational and economic feasibility of the implementation of cross flow filtration in various gasifier options. Westinghouse has prepared a comprehensive program that will lead directly to these program goals in an efficient manner.

The proposed program is composed of three major technical tasks. Task 1 is directed at the design and actual test of a cross flow filter at a DOE bench scale gasifier. Task 2 is composed of several smaller theoretical and experimental efforts that are intended to firm up areas where engineering and design principles are lacking or considered inadequate. The third task is intended to integrate the results of the first two tasks in a conceptual design and cost analysis such that proper economic perspective for the filter concept can be gained. A brief summary of the approach taken in the technical tasks is presented in the following discussion.

In the conduct of Task 1, we will design, fabricate, install, and operate a cross flow test system at the AGC. The actual test article will incorporate provisions for a scaled down cross flow element that will accommodate all of the gasifier flow. From this element, we will gain information on filtration parameters such as efficiency, pressure drop, and cleanability. The element will be instrumented with high speed differential pressure transducers that will allow us to quantify the pulse jet parameters that are required for successful blow back cleaning. These will subsequently serve as inputs to scaling models for full size module calculations.

In Task 2 we propose to conduct a series of independent tests. The efforts center on the following areas: 1) a task to develop a filter element with improved mounting and delamination properties, 2) a task to refine our model that describes the dynamics of pulse jet cleaning, 3) a task to quantify the dust cake properties of char and sulfur sorbent fines, and 4) a chemical stability test of the cross flow filter in a simulated gasifier environment.

The third technical task will involve the integration of new test data and model refinements into a sound conceptual design for at least three gasifier systems. Westinghouse personnel that have had past and current responsibility for commercial gasification systems design and cost analysis will assume the primary responsibility for this task. We are confident that the approach of coupling a sound scientific data base and scaling methodology with a broad systems understanding and capability will result in a sound conceptual design and costing basis.

PROJECT SUMMARY FOR THE SIXTH QUARTER (January-March 86)

Early in this quarter we had intentions of carrying out some extended design principle efforts that were aimed at quantifying the improvements made in filter delamination resistance. This was to have been accomplished by pulse jet cleaning samples of cross flow filters at HTHP conditions at higher and higher pressures until they failed. Coors was to supply a pair of once fired filters (1X), a pair of twice fired filters (2X) and a pair of twice fired and coated elements (2XC). The actual testing did not follow the original plan for two reasons. First, one entire shipment of elements from Coors was returned because of obvious flaws and secondly, it appeared that there might be a chance for additional testing at METC, so that filters which were successfully tested to the maximum normal pulse pressure were saved for possible use at METC rather than being taken on to destruction.

In this period relatively short duration tests at high pulse pressures have been carried out on four different filters that have included all of the improvements that Coors has made to date. As indicated in Table I, we have had very good results with both the 2X and 2XC filters. It is interesting to note that even one of the two, 1X filters tested resisted delamination at very high pulse pressures.

More recently it has become clear that we would not be able to carry out any further testing at the METC gasifier. It was determined, however, that additional long term testing would be valuable for demonstration of improved filter mechanical properties and filter stability. We have embarked, therefore, on a long term 1000 cycle test of a 2XC filter in the HTHP test facility at the Westinghouse R&D Center. This test is being conducted in many roughly 10 hour

Table I

CROSS FLOW FILTER TEST RESULTS

Coors Shipment	Filter Designation	Filter Preparation	Test Date	Comments
1	WCXF 6	1X	2/6-12	Tested 4 days, 38 cycles, 15 hours: Worked very well, 99.9% efficiency with baseline Delta P of 8-10 in wg at 15.5 ft/min. Pulsed at Pressures to 500 psig giving internal pulse of 7 psi.
1	WCXF 7	1X	2/1	Failed by delamination first day. Pulsed at 300 psig giving internal pulse of 2 psi.
1	WCXF 8	2X	1/20-22	Tested 3 days, 25 cycles, 14 hours: Performed very well, 99.95+% efficiency with baseline pressure drop of 10-15 in wg at 15.5 ft/min. Pulsed to 350 psig giving internal pulse of 3.5 psi.
2	WCXF 9	2X	N/A	All returned to Coors because of obvious cracks in front face.
2	WCXF 10	2X	N/A	
2	WCXF 11	2XC	N/A	
3	WCXF 12	2XC	2/18 -	Initial test one day 17 cycles with efficiency greater than 99.9%. Currently using this filter in 1000 cycle test, with 350 cycles accumulated over 12 test days and 80 hours. Has been pulsed to 500 psig but current program using 400 psi pulses. Baseline stability good at 9-12 in wg at 13 ft/min.

periods so that a large number of thermal cycles on the filter are achieved. At this time about 80 hours of test and 350 cycles have been achieved over 12 test days. The performance of the filter has been outstanding with efficiencies greater than 99.95% and baseline pressure drops from 10 to 12 in wg at a relatively high filter face velocity of 13 ft/min.

PROJECT STATUS FOR JANUARY

TASK 2 - Filter Element Testing

The primary effort during the month of January was focused on the design principles testing task. Consensus had been reached among DOE, Westinghouse and Coors personnel that it would be beneficial to carry out testing to quantify the effects of multiple firing and slip coating on the elements resistance to delamination. To do this, it was agreed that Coors would supply three pairs of elements; two identical elements having been once fired (1X), two identical elements twice fired (2X), and two identical elements twice fired and slip coated (2XC). The plan was to put these filters in service for a short time at HTHP conditions and then to expose them to ever increasing pulse pressures until they failed.

In actuality, two subsequent issues arose that modified this plan somewhat. First, the possibility arose that Westinghouse might be able to do an additional 100 hours of testing at the METC gasifier. This created a need for at least one (preferably two) good proven filter elements. We decided, therefore that elements that could withstand pulses in excess of the maximum expected, would not be taken on up to failure. For our purposes this meant that elements withstanding a 500 psig pulse (causing about an internal pulse greater than 6 psi) would be saved for possible use in extended METC testing. The second event that modified the original plan was the fact that the second shipment of test filters from Coors all had obvious flaws that precluded testing them, and they were returned. These filters included a pair of 2X filters and one 2XC filter.

The elements received from Coors for this task are summarized in the following table:

Table I

<u>Shipment</u>	<u>Filter Description</u>	<u>Preparation</u>	<u>Comment</u>
1	WCXF 6	1X	--
1	WCXF 7	1X	--
1	WCXF 8	2X	--
2	WCXF 9	2X	All cracked and returned to Coors
2	WCXF 10	2X	
2	WCXF 11	2XC	
3	WCXF 12	2XC	Small "Chips" in corner of flange- OK to test

In the month of January we were able to test two of these filters, WCXF 8 and WCXF 7.

WCXF 8 Testing

WCXF 8 was the first element tested that had been modified to retain its original porosity after two consecutive high firings. The element "as received" is shown in Figure 1. It was noted that the flange was slightly thicker than the filter mount could accommodate, so a somewhat clumsy shim arrangement was used as shown in Figure 2.

WCXF-8 (2x) 1-14-86

Figure 1 - WCXF 8 Cross Flow Filter As Received

Figure 2 - WCXF 8 Mounted and Shimmed In Filter Holder

The filter was installed in the system and an attempt was made to determine the cold pressure drop vs flow characteristics of the filter. The system was configured for relatively low flow, which meant that we could not achieve very high filter velocities, because as we increased the flow the fully open back pressure valve caused higher and higher system pressures, which resulted in a nearly constant volumetric flow through the filter and a velocity of about 5 ft/min over the available mass flow range. At this velocity the pressure drop was extremely low, being less than 1 in wg.

At mid day the high temperature and pressure testing was initiated as the system was brought to a flow of 240 lbm/hr at a pressure and temperature of 150 psig and 1425°F. These conditions gave a filter velocity of approximately 15.5 ft/min. At these conditions the initial pressure drop was again quite low at 2.5 in wg. Figure 3 presents a summary of the pressure drop vs time history of subsequent testing which occurred over three test days. During the initial period of rapid conditioning baseline pressure drops rose from about 2.5 in wg to a final value of about 15 in wg. During this period the trigger pressure drops were allowed to rise from an initial value of 13 in wg to a final value of 30 in wg. As the test progressed the cleaning pulse was increased from 250 psig for 0.1 sec to final values of 350 psig for 0.1 sec. This cleaning regimen yielded moderate cleaning pulses ranging from 0.75 to 3.75 psi. During the 2-1/2 days of test, about 14 hours of actual HTHP filtration time was accumulated which included three thermal cycles and 25 cleaning cycles. Throughout the test period the overall average efficiency was measured at 99.95%, with an average inlet loading of 1727 ppm.

FIG. (3), CROSSFLOW FILTER, WJCF-8, $A = 11 \text{ ft}^2$ (1-20/21/22-86,
 $T = 774^\circ \text{C}$, $P = 150 \text{ PSIG}$, $V_s = 15.5 \text{ ft}^3/\text{min}$,
 $\eta = 99.95\%$, $C_s = 1727 \text{ RPM}$

After the third day of testing the filter was removed for inspection, prior to a planned test with very high pulses. Figures 4 and 5 show the filter in its "as removed" and partially cleaned state. As revealed in Figure 4 the general condition of the filter was quite good indicating adequate cleaning and no delamination. When the filter was removed from the mount it was determined that one corner of the flange had cracked (Figure 6) and as seen in Figure 7, it was determined that the piece was physically loose from the flange. It can be seen that this break did not compromise the flange seal and result in a leak. We feel that this break was due to the makeshift shim arrangement used and was not a direct result of normal testing. A decision was made to modify the mounting assembly to make it deeper and slightly wider and longer in order to accommodate the new filters. It was also decided that no further testing should be done on WCXF 8 at this time since it appeared that we would be conducting additional tests at METC, and WCXF 8 was the only new, proven element available.

WCXF 7 Testing

Filter element WCXF 7 (Figure 8) was also one of the new, more porous filters received from Coors and it had only been fired once (1X). Cold flow testing in the system confirmed a high porosity similar to that observed for WCXF 8. On 1/29/86 the filter was tested at HTHP conditions of 1450°F, 150 psig and a filter face velocity of 15.5 ft/min. As the pressure drop trace presented in Figure 9 indicates the test appeared uneventful from the pressure drop perspective. As with WCXF 8, the initial HTHP pressure drop was only a few inches of water. The first cycle was long and quite straight as is typical of a first exposure to dust. Pulse cleaning was initiated at 200 psig and increased to 300 psig causing internal pressure pulses of 0.6 to 2 psi.

Figure 4 - WCXF 8 Cross Flow Filter As Removed
After HTHP Testing

Figure 5 - WCXF 8 After HTHP Test With Outer Surface
Partially Cleaned

Figure 6 - WCXF 8 Showing Crack in Corner of
Mounting Flange

Figure 7 - WCXF 8 Showing Break in Corner of Mounting Flange
Note No Leak in System

Figure 8 - WCXF 7 Once Fired Cross Flow Filter as Received

FIG (9), CROSS FLOW FILTER WCF-7 (1-29-86)
 $T = 1450^{\circ}F$, $P = 150 \text{ PSIG}$, $V_f = 15.7 \text{ FT/min}$
 $C = 1935 \text{ PPM}$, $\eta = 99.7\%$

During this test outlet samples indicated a significant, and worsening, leak in the system as consecutive samples indicated sample rates of 0.048, 0.124, 0.160, 0.226 mg/min. Because of the observed leak rate, the filter was removed for inspection after the first day. As shown in Figure 10 the filter looked as if it had been cleaned adequately, however, it appeared that a delamination had occurred about four layers from one end. When the filter was removed from the mount, there was an obvious deposit of dust under the suspect channel as shown in Figure 11. When the element was completely removed (Figure 12) from the mount, it was determined that a total delamination had occurred, and that a break had occurred in one end plate. The end plate break may likely have been caused by the mounting jig, as it had not yet been modified, however, the delamination appeared to be typical of those observed in the past. It was noted that the failed layer occurred at a plane that had bowed considerably during firing as shown in Figure 13. The significance of this observation is not clear and will be discussed with technical personnel at Coors.

Figure 10 - WCXF 7 After One Day of Test Shows Delamination

Figure 11 - WCXF 7 Removed from Mount Showing Dust Deposit
Below Failure Site

Figure 12 - WCXF 7 Cross Flow Filter Failure After
One Day of Test

Figure 13 - WCXF 7 Filter Showing Bow in Surface Along
Which Delamination Occurred

PROJECT SUMMARY FOR FEBRUARY

During the month of February the work remained focused on the task of testing filter elements in the bench-scale test facility at Westinghouse R&D. During this period we have tested the second once fired (1X) cross flow filter and carried out tests on a twice fired and coated element (2XC).

As part of a test plan to quantify the effects of multiple firing and dip coating we had received a pair of 1X, 2X and 2XC filters. The shipment containing the 2X and one of the 2XC filters was returned to Coors because all three filters had developed similar cracks. Figure 14 shows the cracks across the front sealing face. The actual crack has been highlighted in the photo to enable the path to be seen. Figure 15 shows a closeup of the crack across the front face, and Figure 16 indicates the fact that the crack penetrated all the way through the flange. This photo illustrates the degree to which the back face of these filters had slumped. We feel that this slumpage may have imparted some bending stress to the front face causing subsequent failure. The elements have been returned for Coors appraisal.

In spite of the difficulty with the two, 2X and the first 2XC filter we proceeded with test work on WCXF6 which is the 1X twin of WCXF7 that had been tested previously. As noted in the January report WCXF7 had delaminated the first day in use. On 2/6/86 WCXF6 was mounted in the filter holder and installed in the system for cold flow characterization. As with all of the most recent Coors filters, the resistance to flow was very low being less than 1 in wg at a face velocity of 5 ft/min. Immediately after the cold flow testing, the HTHP test was initiated with a face velocity of 15.5 ft/min at 1450°F and 150 psig. The results of the

Figure 14 - Coors Cross Flow Filters That All Had Developed Similar Cracks During Fabrication

Figure 15 - Close Detail of Crack Across Front Face of Coors
Cross Flow Filter

Figure 16 - Coors Cross Flow Filter Showing Crack Through Flange and the Degree of Slumping at Back Face of Filter Elements

next several days of test are summarized in Figure 17. As can be seen in the chart, the initial pressure drop across the filter was about 4 in wg and it climbed to 14 in wg over about a 70 minute period with an average inlet loading of 2500 ppm. Cleaning during the first day consisted of 0.1 sec pulses from a reservoir charged to 250 to 310 psig, which generated internal cleaning pulse pressures of from 1 to 2 psi. During the second day of test, conditions were held constant with pulse jet cleaning at 310 psig, and performance appeared to be quite stable, however, by mid afternoon the dust feeder ran out and forced a close of testing for the day. During the first two days of test the rate of dust collection in the outlet sampler was quit constant at about 0.025 g/min and 0.032 g/min.

During the third day of operation (2/10/86) the filter again performed well, with a baseline pressure drop of 10 in wg at the usual filter face velocity of 15.5 ft/min. During this day a decision was made to explore higher cleaning pulse pressures in order to determine the filter's resistance to delamination. Accordingly, the pulse pressures were increased from 300 to 350 to 400 and finally to 450 psig over the course of the day. These pulses generated cleaning pressure rises of 4 to 6 psi. Performance of the filter appeared to be stable again, however, an increase in dust concentration at the filter outlet was observed. The rate of dust collection for the day started at the previous test days level of 0.033 mg/min but subsequent samples indicated rates of 0.036, 0.054 and 0.071 mg/min.

Although the leak was not very great, we decided to remove the filters for inspection of both the element and its seals. The filter was cleaned and thoroughly inspected, however, no sign of failure was detected. Similarly, an

Figure 17 - CROSSFLOW FILTER WCF-6 $A = 1.1 \text{ FT}^2$ (2/6-7-12/86)
 TEMP. = 1450°F , $P = 150 \text{ PSI}$, $V_f = 15.5 \text{ FT}^3/\text{MIN}$.
 $\eta = 99.90\%$, $C = 2.523 \text{ PPM}$

external examination of the gasketing did not reveal any explanation for the penetration, however, since the filter was not removed from the mount, the possibility of a gasket leak did exist. The filter was replaced in the unit and made ready for additional testing.

On 2/12/86 the system was brought to normal operating conditions, and after three cleaning cycles at 450 psig the pulse pressure was raised to 500 psig thereby generating internal pulses of up to 7 psi. Filter performance over the course of the test day was excellent with stable, straight, pressure drop traces, indicative of good cleaning. The penetration, however was relatively high at about 0.14 mg/min which was about double the previous test day's highest value. This time the penetration remained virtually constant over the entire test day.

Having survived the intense 500 psig cleaning pulses, a decision was made to stop testing on this element and save it for possible testing at METC. When the filter was removed from the unit it was found to be in very good shape with excellent cleaning as shown in Figure 18. The element was removed from the mount and cleaned in an attempt to determine where the small leak in the system was coming from. A careful examination of the dismounted element and its gasket offered no clue as to the source of the leak. Figure 19 presents the leak rate plotted against pulse pressure, test day and the number of pulses included in each sample. From these plots it appears that the average leak rate depends on the pulse pressure and or test time, however, it was surprising to find little correlation with the number of pulses included within a sample.

Figure 18 - Cross Flow Filter WCXF6 "As Removed"
from HTHP Testing

Average Filter Leak Rate (mg/min)
as function of pulse pressure

Average Filter Leak Rate (mg/min)
as function of pulses per sample

Average Filter Leak Rate (mg/min)
as function of cumulative test days

Figure 19 - Average Filter Leak Rate
for WCXF6 as Function of
Various Operating Parameters

In way of a summary, then, we were pleased to find that a once fired (1X) filter could be fabricated such that it would withstand very high cleaning pulse pressures. This could be a significant cost benefit for a commercial system. Secondly, we are unable to find a reasonable explanation for the small but observable leak in the system.

The second filter tested during the month of February was WCXF12, which is a twice fired and dip coated element. In spite of a minor flaw at one corner of the sealing face (Figure 20) we were able to mount the element and seal it well. On 2/17/86 the element was cold flow tested in the test rig and it was determined that the filter had not lost any permeability by being twice fired as the pressure drop at 5 ft/min was less than 1 in wg. On the following day HTHP testing was initiated at the following conditions: temperature 1450°F, pressure 150 psig, and a filter velocity of 15.5 ft/min with an average dust loading of 2650 ppm. The pressure drop/time chart for this test is shown in Figure 21. After the first few cleaning cycles at 200-300 psig, the pulse reservoir was brought to 510 psig and it remained at this level for the remaining 13 pulses of the day. By the end of the day a relatively stable cycle had been established running between 8 to 15 in wg over roughly a 15 minute period. As in the previous test, the leak rate appeared to increase with pulse pressure, going from 0.025 mg/min at 200-300 psig pulses to typical values of 0.082 mg/min at the 500 psig pulse level. As indicated in Figure 21, the overall average efficiency for the filter unit was calculated to be 99.92%. Having demonstrated the ability to survive 500 psig pulses, testing on this filter was stopped, and the unit was removed for inspection. As shown in Figure 22 the pulse cleaning regimen had been quite successful in maintaining the filter. A peculiar dust had developed between one face of the filter and the clean side plenum as seen in Figure 23. This is an artifact of the test

Figure 20 - Cross Flow Filter WCXF12 Twice Fired and Slip Coated - Note Small Flaw at Corner of Flange

TIME (HOUR)

TIME (HOUR)

Figure 21 - CROSSFLOW FILTER WCXF-12 $A = 1.1F^2$ (2-18-86)
 $T = 1450^\circ F$, $P = 150 \text{ PSIG}$, $V_f = 15.5 \text{ FT/min}$
 $\eta = 99.92\%$, $C_m = 2649 \text{ PPM}$

Figure 22 - Cross Flow Filter WCXF12 After HTHP Testing
Shows Very Good Cleaning by 500 psig Pulses

Figure 23 - Deposit Formation Between WCXF12 and Clean Side Gas Plenum of Test Rig

rig and would not be a problem in a commercial design, as the blank filter top would be oriented toward the clean plenum in this design. The filter was vacuumed clean and removed from the mount for inspection. The filter and seals were found to be in excellent condition.

Programmatic Issues:

By the end of February it began to appear that there was little chance for additional testing at the METC gasifier because of continued operating problems in the test rig. We currently began evaluation of alternative testing programs and planed to offer DOE some form of extended testing at the R&D Center.

PROJECT STATUS FOR MARCH

During March a consensus was achieved between DOE and Westinghouse that extended testing of an improved cross flow filter would be of great value. It was agreed that Westinghouse would attempt to carry out a 1000 cycle test on one of the improved Coors cross flow filters in order to demonstrate long term stability and improved resistance to delamination. The testing was to be carried out in the Westinghouse 4THP PFBC simulator, in a start stop fashion in roughly 10 hour increments. This mode of operation is intended to expose the filter to many thermal cycles as well as pulse cleaning cycles.

The filter chosen for this test was WCXF12, a twice fired and coated element (2XC). This element had been tested one day previously and had displayed excellent operating characteristics.

Testing to date has been carried out at essentially constant conditions as indicated below:

Pressure	150 psig
Temperature	1450°F
Mass Flow	200 lbm/hr
Filter Velocity	13 ft/min
Dust Concentration	3000-3300 ppr
Pulse Pressures	300-400 psig
Trigger Pressure Drop	20-25 in wg
Base Line Pressure Drop	8-12 in wg

Overall this long term testing has gone very well with excellent filter performance and minimal problems with the system. The entire pressure drop history to date is

presented in Figure 24, sheets 1 to 6. Generally the efficiencies recorded are above that which we can measure (>99.95%) and the baseline pressure drop has been quite steady at from 8 to 12 in wg. One feature of daily operation is the fact that there is a gradual increase in baseline pressure drop and/or shortening of cycle times over the course of a day. This loss is, however, in large part regained on start up the next day. This behavior is typical of virtually all filter systems we have tested in the test rig, and is by no means specific to operation of the cross flow filter.

The first day of the long term test was 3/13 and as is shown in Sheet 1 of Figure 24, the baseline pressure drop was about 8 in wg at a filter velocity of 13 ft/min. It should be noted that the very first exposure of this filter to dust occurred on 2/18/86 (Figure 21). At this time the clean baseline pressure drop was 5 in wg at 15.5 ft/min or about 4 in wg if corrected to a velocity of 13 ft/min. The increase in baseline from 4 to 8 in wg is a typical reflection of the initial irreversible loss in permeability that all rigid filters experience in testing. It is important to note that on 4/1/86 (sheet 6 of Figure 24), the freshly cleaned filter exhibited a baseline pressure drop of only 6 in wg which is an excellent sign that the initial loss of permeability had been minimal over the test period.

In the course of testing the pulse pressure has been increased twice, the first time was on 3/17 (hour 20) when it was raised from 300 to 350 psig. The second increase occurred on 3/19 (hour 35) when it was raised to its current level of 400 psig. At this level, the internal pulse rises measured are from 5.5 to 6 psig.

Start of Test

(3-13/14-86)

Figure 24 - CROSS FLOW FILTER WCXF-12
1 of 6

$T = 1450^{\circ}F$, $P = 150$ PSIG, $V_f = 13$ FT/min

$C_w = 3293$ PPM, $\eta = 99.99\%$

Feed Noz. Plug
down 2 hr

3/14 3/17

Increase
Pulse from 300 to 350 PSIG

3/17 3/18 Small Plug in Combustor

TIME (Hour)

TIME (Hour)

FIG. (24), (3-14/17/18-86)

2 of 6

$T = 1450^{\circ}F$, $P = 150$ PSIG, $V_t = 13$ FT/min.

$C_{w} = 3293$ PPM, $\gamma = 99.99$ %

Small Plug at Vessel
inlet

TIME (HOUR)

Start 400 PSIG
Pulses

TIME (HOUR)

Blow Out ΔP
Lines

end 3/19

TIME (HOUR)

FIG. (24) CROSS FLOW FILTER WCKF-12 (3-19-86)

3 of 6 $T = 1450^{\circ}F$, $P = 150$ PSIG, $V_f = 13$ FT/min

$C_W = 3293$ PPM, $\gamma = 99.99\%$

FIG (24), CROSS FLOW FILTER WCF-12 (3-21/24-86)
406
T = 1450°F, P = 150 PSIG, $V_f = 13 \text{ FT/min.}$
 $C_w = 3180 \text{ PPM, } \beta = 99.97\%$

Blow Out ΔP
Lines

4:04 PM

end 3/24

Sample black with
soot

ΔP spikes TIME (HOUR)

Lower flow to 175 L/min/hr ΔP spikes TIME (HOUR)
/ (11.5 ft/min) $\rightarrow$ To 51.2 PSI, Temp to 1800°F

blow out
AP lines

Filter out for inspection. Found damp crusty deposits.

cleaned Filter
... Restart

FIG (24), CROSS FLOW FILTER WEXF-12 (3-26-8C/4-1-8C)
6 of 6
TIME (HOUR)
T = 1450°F, P = 150 PSIG, V_f = 13 FT/min
C₁₂ = 3180 PPM, η = 99.97 %

Other than a few minor dust deposit problems the test ran smoothly until 3/26 (sheet 6 of Figure 24) when some operating problems were encountered. During this day temperature control became a problem with several unexplained temperature excursions that were accompanied by unsteady pressure drop data. Further evidence of trouble occurred when the filter outlet sample showed signs of soot. Finally, in the mid afternoon both the air and gas compressors kicked out requiring a system restart. When the system was started again temperature control was not effective so a decision was made to shut down and determine the cause of the observed trouble. It was determined that the thermocouple used to control the system temperature had failed, which explained the temperature control problem. We also discovered that a dust deflector in the filter vessel had caused a build up of dust that covered over the filter vessel inlet. Since the deflector is only required for bag filters so it was removed.

The filter was removed for inspection and it was found to be covered with dark, damp looking crusty deposit (Figure 25) that was quite unlike any deposit observed to date. The face of the filter vacuumed fairly easily, however, several of the channels were filled with the crusty deposit and had to be blown clean with high pressure air. A large crusty deposit had accumulated between the filter element and the clean air plenum as shown in Figure 26. This was easily removed and came out in large chunks that were saved for subsequent analysis if desired. We are not certain of the exact sequence of events leading to the deposits, however it does seem to be related to the difficulty with the fuel control system and the high temperature spikes and fuel rich operating conditions that existed for the day in question.

Figure 25 - Cross Flow Filter WCXF 12 after Trouble with
Temperature Control, Dust Deposit Wet and Crusty

Figure 26 - Cross Flow Filter WCXF 12 Showing Crusty Dust Deposit
Accumulated Between Filter and Clean Gas Plenum

The filter was cleaned (Figure 27) and replaced in the unit for further test. As indicated on Sheet 6 of Figure 24 the initial pressure drop on 4/1 was quite low at about 6 in wg indicating the fact that no significant damage had been done to the filter. We plan to continue on in the long term test with this filter.

Figure 27 - Cross Flow Filter WCXF 12 - Cleaned and Ready
To Be Replaced in Unit for Test

*Budget & milestones
removed.
ds*

END

**DATE
FILMED**

9 / 1 / 92