**ANNUAL REPORT FOR 1979 ON
RESEARCH, DEVELOPMENT AND DEMONSTRATION OF
LEAD-ACID BATTERIES FOR
ELECTRIC VEHICLE PROPULSION
Contract No. 31-109-38-4207**

by

**Exide Management and Technology Company
(Formerly ESB Technology Co.)**

MASTER

**ARGONNE NATIONAL LABORATORY, ARGONNE, ILLINOIS
Operated for the U. S. DEPARTMENT OF ENERGY
under Contract W-31-109-Eng-38**

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency Thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

DISCLAIMER

Portions of this document may be illegible in electronic image products. Images are produced from the best available original document.

The facilities of Argonne National Laboratory are owned by the United States Government. Under the terms of a contract (W-31-109-Eng-38) among the U. S. Department of Energy, Argonne Universities Association and The University of Chicago, the University employs the staff and operates the Laboratory in accordance with policies and programs formulated, approved and reviewed by the Association.

MEMBERS OF ARGONNE UNIVERSITIES ASSOCIATION

The University of Arizona
Carnegie-Mellon University
Case Western Reserve University
The University of Chicago
University of Cincinnati
Illinois Institute of Technology
University of Illinois
Indiana University
The University of Iowa
Iowa State University

The University of Kansas
Kansas State University
Loyola University of Chicago
Marquette University
The University of Michigan
Michigan State University
University of Minnesota
University of Missouri
Northwestern University
University of Notre Dame

The Ohio State University
Ohio University
The Pennsylvania State University
Purdue University
Saint Louis University
Southern Illinois University
The University of Texas at Austin
Washington University
Wayne State University
The University of Wisconsin-Madison

NOTICE

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government or any agency thereof, nor any of their employees, make any warranty, express or implied, or assume any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represent that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, mark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

Printed in the United States of America
Available from
National Technical Information Service
U. S. Department of Commerce
5285 Port Royal Road
Springfield, VA 22161

NTIS price codes
Printed copy: A10
Microfiche copy: A01

ANL/OEPM-79-8

Annual Report for 1979 on
RESEARCH, DEVELOPMENT AND DEMONSTRATION OF
LEAD-ACID BATTERIES FOR
ELECTRIC VEHICLE PROPULSION

Prepared for
The Office for Electrochemical Project Management
Argonne National Laboratory
Under Contract No. 31-109-38-4207

By
Exide Management and Technology Company
Yardley, Pennsylvania

DISCLAIMER

This book was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

June 1980

ACKNOWLEDGEMENTS

The Annual Report was prepared by the ANL-EV Project Team at the ESB Technology Company. The work as performed and reported herein was by:

Mr. H. A. Fuggiti

Mr. D. L. Beals

Mr. T. W. Blickwedel

Mr. C. H. Carr

Mr. C. J. Daly

Dr. I. S. Klein

Ms. D. E. Nairn

Mr. J. B. Ockerman

Mr. A. J. Ragolia

Ms. L. M. Reddell

Mr. W. N. Sonneborn

Mr. E. L. Wasser

In addition, the contribution and efforts of our associates at the various EXIDE Corporation facilities made much of this work possible.

Special thanks are due Mrs. D. L. Pagliaro and Mrs. E. J. Wilkes for their diligence and skill in typing and collating this report.

TABLE OF CONTENTS

	<u>Page</u>
ACKNOWLEDGEMENTS-----	-ii-
LIST OF TABLES-----	-iv-
LIST OF FIGURES-----	-v-
LIST OF PHOTOGRAPHS-----	-vii-
1.0 EXECUTIVE SUMMARY-----	-ix-
1.1 ISOA BATTERY PROGRAM-----	-1-
1.1.1 FP-1 Factorial Experiment-----	-1-
1.1.2 Positive Plates-----	-3-
1.1.3 Negative Plates-----	-4-
1.1.4 Separators-----	-4-
1.1.5 Battery Assembly-----	-5-
1.1.6 Testing - Characteristics-----	-7-
1.1.7 Testing - Life Cycle-----	-49-
1.1.8 Present Status-----	-53-
1.1.9 Preliminary Evaluation of Results and Tentative Conclusions-----	-54-
1.1.10 Work Programmed for the Next Year-----	-54-
1.1.11 Overview of Work with Respect to ISOA Goals-----	-56-
1.2 FP-2 EXPERIMENT-----	-56-
1.2.1 Work Performed Since Last Annual Report-----	-56-
1.2.2 Work Programmed for Next Year-----	-59-
1.3 TP-1 HISTORY-----	-59-
1.3.1 Work Performed Since Last Annual Report-----	-60-
1.3.2 Work Programmed for Next Year-----	-66-
1.4 ADVANCED LEAD ACID BATTERY-----	-66-
1.4.1. Negative-----	-66-
1.4.2 Positive-----	-84-
1.4.3 Electrolyte-----	-121-
1.4.4 Advanced Battery Preliminary Conclusions and Future Work-----	-123-
1.4.5 Measuring the Heat Generated in EV Batteries-----	-129-
1.5 THE BIPOLAR BATTERY-----	-132-
1.5.1 Experimental-----	-136-
1.6 SINGLE POINT WATERING SYSTEM-----	-161-
1.7 SUPPORT FUNCTIONS-----	-167-
1.7.1 Test Laboratory-----	-167-
1.7.2 Quality Control/Quality Assurance-----	-177-
REFERENCES-----	-178-
APPENDIX NO. 1 - FP-2 Life Cycle Separator Test-----	-179-
APPENDIX NO. 2 - TP-1 Positive & Negative Group Weights & Millivolt Drop Test Results-----	-193-

LIST OF TABLES

<u>Table</u>	<u>Page</u>
1-28	Characteristics Test Data----- 9-48
29	Preliminary Evaluation of ISOA Battery Performance----- 55
30	FP-2 Separator Test----- 58
31	Properties of Grid Materials----- 68
32	Lightweight Negatives - Type B----- 75
33	Typical Electrode Voltages vs Cadmium----- 84
34	Tubular Grid Parameters----- 86
35	Design Parameters for Cells Containing Tubular Electrodes- 88
36	Cycle Life Behavior of Cell T18----- 91
37	Cycle Life Behavior of Cell T19----- 92
38	Cycle Life Behavior of Cell T21----- 93
39	Cycle Life Behavior of Cell T22----- 94
40	Tubular Electrode Spine Study - Positive Electrode Performance----- 98
41	Tubular Electrode Spine Study - Cell Performance----- 99
42	Design Parameters for Cells Containing Composite Positive Electrodes----- 106
43	Design Parameters for Cells Containing Flat Pasted Plate Positive Electrodes----- 111
44	Cycle Life Behavior of PP3 and PP5----- 114
45	Cycle Life Behavior of PP7 and PP8----- 115
46	Cycle Life Behavior of PP9 and PP10----- 116
47	Behavior of Advanced Battery Containing Flat Pasted Plates 120
48	The Effect of Acid Circulation on Battery Performance----- 122
49	Bipolar Battery Design and Test Data----- 151
50	Design Data (10 x 11 cm Bipolar Battery)----- 153
51	Weight Analysis Data (10 x 11 cm Bipolar Cell)----- 158
52	Data Record General Format----- 173

LIST OF FIGURES

<u>Figure No.</u>		<u>Page</u>
1	Lightweight Composite Negative Grid - Type A-----	70
2	Discharge Behavior of Lightweight Negative Grids - Type A-----	71
3	Cycle Performance of Battery 105-9 (Lightweight Negative Grids - Type A)-----	73
4	Cycle Performance of Cell N1-3 (Lightweight Negative Grids - Type A)-----	74
5	Electroformed Copper Grid, Lead Plated, Type B (Lightweight Negative Grid Construction)-----	77
6	Metal Plastic Composite - Type B (Lightweight Negative Grid Construction)-----	78
7	Pasted Plate - Type B - Lightweight Negative Grid Construction-----	79
8	Cycle Performance of Cell N1-4 (Lightweight Negative Grids - Type B)-----	80
9A	Post Mortem Cell N1-4, Surface of Negative Plate 150X	81
9B	Surface of Negative Plate, Region A 1500X-----	81
9C	Surface of Negative Plate, Region B 1500X-----	82
9D	EDX of Region A on Negative Plate Surface-----	82
9E	EDX of Region B on Negative Plate Surface-----	83
9F	Copper Map of Negative Plate Surface-----	83
10	The ISOA Tubular Grid-----	87
11	Cycle Life Behavior of Tubular Cells-----	95
12	Voltage-Time Characteristics for Advanced Tubular Electrode Cell Design (Cell T22)-----	96
13	Single vs. Double Spine Performance-----	100
14	Composite Positive Electrode - Unpasted-----	102
15	Composite Positive Electrode - Flush Pasted-----	103
16	Composite Positive Electrode - Complete-----	104
17	Cycle Life Behavior of Composite Plate Cell (C1)-----	109

LIST OF FIGURES

<u>Figure No.</u>		<u>Page</u>
18	Cycle Life Behavior Composite Plate Cell (C2, C3)-----	110
19	Voltage-Time Behavior for Cell PP10 (Advanced Flat Plate Positive)-----	117
20	Voltage-Time Behavior for Cell PP5 (Advanced Flat Pasted Plate Positive)-----	118
21(A)	Voltage-Time Characteristics for Battery 1507-2-----	119
21(B)	Advanced Negative Grid Radial Rib - Type A Construc- tion-----	124
21(C)	Advanced Negative Grid - Lead Lug Insert-----	125
22	The Entralpy Voltage of Lead-Acid Cells-----	131
23	ΔG & ΔH Variation with the State of Charge-----	133
24	The Discharge Behavior of Lead-Acid EV Cells-----	134
25	Anodic Corrosion Test-----	137
26	PbO_2 Penetration in Matrix at 5 mA/cm^2 -----	138
27	Bipolar Plate Construction-----	139
28	Ti-Pb Barriers for Bipolar Battery After Masking for Positive and Negative Pasting-----	141
29	Ti-Pb Bipolar Electrodes After Pasting-----	142
30	Schematic of Bipolar Cladding Assembly-----	145
31	4-Volt Bipolar Cell Construction-----	147
32	Ti-Pb Bipolar Electrodes and Cell Components-----	148
33	Assembled 12-Cell Bipolar Battery-----	149
34	Cycle Data 4-Volt Bipolar Battery-----	152
35-38	Performance of 10 x 11 cm, 12 Cell, Bipolar Battery Discharge Curves-----	154
39	10 x 11 cm, 12 Cell, Bipolar Battery (7.38 Ahr. Theo.)	159
40(A)	Single Point Watering System Modified Vent Plug-----	162
40(B)	Modified Vent Plug - Cross Section-----	163

LIST OF FIGURES (contd)

<u>Figure No.</u>		<u>Page</u>
41	Battery/Installation Schematic-----	164
42	Battery Installation - Sebring Sv 48 Vehicle----	165
43	Chassis Mounted Flame Arrestors-----	166
44	Typical Teletype Printout-----	172
45	Data Printout Example-----	175
46	CRT Charge/Discharge Plot-----	176

LIST OF PHOTOGRAPHS

<u>Photo #</u>		<u>Page</u>
1	CLADEx Tubing (70-2)-----	61
2	Positive Spine, Bottom Bar & Plate (70-3)-----	62
3	TP-1 Rubber Ribbed Separator (71-2)-----	63
4	TP-1 Plastic Ribbed Envelope & Ribbed Sheet (71-3)--	64
5	TP-1 Containers-Standard & Low Sediment Ribs (71-4)-	65
6	TP-1 and FP-1 Negative Grids (72-2)-----	67

THIS PAGE
WAS INTENTIONALLY
LEFT BLANK

1.0 Executive Summary

The Statement of Work for Research, Development and Demonstration of Lead-Acid Batteries for Electric Vehicle Propulsion under Contract 31-109-38-4207 requires two separate phases of development effort.

An initial phase titled, "Improved State-of-the-Art" hereafter called ISOA, comprises three factorial experiments to evaluate a variety of component combinations. The proper analysis of data and selection of components will result in a battery for EV propulsion which will be an improvement over the present industry standard (ESB EV-106). This battery will also meet the following ISOA goals as established by ANL: -

1. Capacity @ 3 Hr Discharge	20-30 Kw-hr
2. Size in cm	29.5 H x 40.6 W x 264 L
3. Specific Energy	40 W-hr/Kg
4. Specific Power	100 W/Kg for 15 sec. Avg.
5. Duty Cycle	4-8 Hr Charge
2-4 Hr Discharge
6. Cycle Life	800 cycles to 80% Depth
7. Price/Energy at
10,000 Battery Production	\$50/kW-hr (1977-\$)
8. Energy Efficient	>60% Across Battery Terminals
9. System Voltage	120 V D.C.

Two factorial experiments include flat or pasted type positive and negative plates. Experiment No. 3 includes a tubular type positive plate with a flat or pasted type negative plate.

Factorial Experiment No. 1 has 96 batteries under test which include 32 component variables. These batteries have completed initial discharge characteristics at three temperature modes and are presently on life cycle test.

Factorial Experiment No. 2 has been delayed beyond the initial time schedule due to difficulties in the optimization of the computer grid design by our subcontractor, Battelle Columbus Laboratories. The study is expected to be completed during December 1979 with battery assembly and testing to follow. The interim time is being utilized to perform preliminary testing on a series of eleven new separator type materials recently introduced commercially for lead-acid battery use.

The third experiment, with tubular positive plates, includes 128 batteries with 32 variables. These batteries have been assembled and are now starting discharge characteristics and cycle life capability testing.

The second phase of the "Statement of Work" is a study to design an Advanced Lead-Acid Battery (Advanced) meeting the following ANL goals:

1. Capacity @ 3 Hr Discharge	30-40 Kw-hr
2. Size in cm	29.5 H x 40.6 W x 264 L
3. Specific Energy	60 Whr/Kg
4. Specific Power	150 W/Kg for 15 sec. Avg.
5. Duty Cycle	4-8 Hr Charge
204 Hr Discharge
6. Cycle Life	1000 Cycles to 80% Depth
7. Price/Energy at
10,000 Battery Production	\$40/kW-hr (1977-\$)
8. Energy Efficient	>60% Across Battery Terminal
9. System Voltage	120 V D.C.

Numerous innovative approaches are under study to increase the utilization of the active chemical components in a lead-acid battery of both the flat, pasted type and the tubular type positive plates. Included are lead oxide preparation, paste additives, material densities, and plate processing. Studies are also underway to reduce the battery weight by the elimination of the lead grid structures used in the negative plates through the use of plated plastic grids and plated copper foil grids.

This work is still in the component and cell state of testing hence evaluation of the probability of achieving the advanced goals is not reliable, and has not been made at this time.

The practicality of designing a single point water system is being investigated. This would permit adding water to each cell of the battery from a single source outside of the vehicle via a manifold system. Several types of filler plugs adaptable to a manifold system have been designed and are under test.

A four-cell battery with end terminals below the battery top which will allow the batteries to be mated and connected without any live electrical connection above the battery is being designed for review and analysis by ANL. If successful, this design will provide protection from accidental electric shock or shorting across the battery tops.

1.1 ISOA Battery Program

1.1.1 FP-1 Factorial Experiment History

Before receiving the present contract, the ESB Technology Company conducted a Cost and Design Study and suggested the investigation of many variables directed toward improving the existing EV 106 battery.

The variables chosen for study were:

- o Positive plate composition - 4 variables.
- o Separator materials - 2 variables.
- o Cell construction - outside positive and outside negative plates.

Present EV batteries are design limited by the positive active material and its reactions. The weight breakdown of the EV 106 shows:

o Positive active material	5.57 Kg
o Positive plates	8.51 Kg
o Negative active material	5.65 Kg
o Negative plates	8.56 Kg
o Electrolyte	8.40 Kg
o Container and Cover	1.01 Kg

Design improvements involve parameters of both dependent and independent variables. The program master schedule did not allow sequential testing of variables. The factorial experiment had to provide data on various components concurrently.

The following tabulation shows the 32 variables that were tested. FP-N1 negative plates were used in all batteries.

<u>Exp. Batt. Spec. No.</u>	<u>Pos. Plate Code</u>	<u>Separator* Type</u>	<u>Construction**</u>	<u>Final Sp.Gr.</u>
5716	FP-P1	R	ON	1.285
5717	"	R	OP	"
5718	"	P	ON	"
5719	"	P	OP	"
5720	FP-P2	R	ON	"
5721	"	R	OP	"
5722	"	P	ON	"
5723	"	P	OP	"
5724	FP-P3	R	ON	"
5725	"	R	OP	"
5726	"	P	ON	"
5727	"	P	OP	"
5728	FP-P4	R	ON	"
5729	"	R	OP	"
5730	"	P	ON	"
5731	"	P	OP	"
5758	FP-P1	R	ON	1.315
5759	"	R	OP	"
5760	"	P	ON	"
5761	"	P	OP	"
5762	FP-P2	R	ON	"
5763	"	R	OP	"
5764	"	P	ON	"
5765	"	P	OP	"
5766	FP-Pe	R	ON	"
5767	"	R	OP	"
5768	"	P	ON	"
5769	"	P	OP	"
5770	FP-P4	R	ON	"
5771	"	R	OP	"
5772	"	P	ON	"
5773	"	P	OP	"

*Separator Type

R = Microporous Hard Rubber supplied by Ameract.

P = Daramic supplied by W. R. Grace Co.

**Cell Construction

ON = Outside negative plates.

OP = Outside positive plates.

NOTE: All positive plates wrapped top to bottom with 0.1 mm glass obtained from Dexter Glass Co.

1.1.2 Positive Plates

All four plate variations used AC2GW grids whose specifications are:

- o Thickness 1.83 mm
- o Alloy 6% Sb-lead
- o Weight 97.1 gm nominal

Quality Control data taken during plate manufacture were:

- o Plate Code FP-P1
 - Grid Thickness 1.92 mm
 - Grid Weight 101.7 gm
- o Dry Plate Data
 - Dry density 4.54 - 4.67 gm/cc
 - Dry active material weight 193.7 - 195.3 gms
- o Plate Code FP-P2
 - Grid Thickness 1.92 mm
 - Grid Weight 101.7 gm
- o Dry Plate Data
 - Dry density 4.25 - 4.28 gm/cc
 - Dry active material weight 157.9 - 166.9 gm
- o Plate Code FP-P3
 - Grid Thickness 1.92 mm
 - Grid Weight 101.7 gm
- o Dry Plate Data
 - Dry density 3.94 - 4.05 gm/cc
 - Dry active material 149.5 - 153.8 gm

- o Plate Code FP-P4
 - Grid Thickness 1.92 mm
 - Grid Weight 101.7 gm
- o Dry Plate Data
 - Dry density 4.00 - 4.03 gm/cc
 - Dry active material 155.2 - 179.8 gms

1.1.3 Negative Plates

FP-1 Factorial Experiment negative plate nomenclature is FP-N1. The FP-N1 uses the GW grid whose specifications follow:

- o Thickness 1.47 mm
- o Alloy 0.19% Ca Lead
- o Weight 75 gm nominal

Quality Control data taken during plate manufacture were:

- o Plate Code FP-N1
 - Grid Thickness 1.43 mm
 - Grid Weight 73.5 gm
- o Dry Plate Data
 - Dry density 4.86 gm/cc
 - Dry active material 158.8 - 160.5 gm

1.1.4 Separators

Quality Control Data as Received:

- o Microporous Hard Rubber

Length	171.0 mm	Std. Dev. 0.369
Width	165.1 mm	Std. Dev. -0-
Thickness	1.4 mm	Std. Dev. 0.01

- o Daramic

Length	171.7 mm	Std. Dev. 0.52
Width	162.4 mm	Std. Dev. 0.52
Thickness	1.5 mm	Std. Dev. 0.02

1.1.5 Battery Assembly

Thirty-two battery specifications were prepared. The Experimental Battery Specifications (EBS) are 4 digit numbers used throughout the report, followed by a 3 digit battery serial number.

For cell identification and Quality Control, the following were purchased:

- o Experimental Battery labels and serial number labels
- o Electrically heated numbering head to permanently identify containers and covers
- o Steel numbering set and type holder to identify the negative strap of each cell

Representative cells were assembled at the EXIDE Corporation to check assembly procedures and component fit.

Thirty-four-hundred positive plates were hand wrapped with glass mat and hand stacked with the proper separators and negative plates.

Ninety-six batteries were built, three per each specification. A total of two-hundred eighty-eight 23-plate cells, they were hand stacked and burned. They were built in two groups; one of 72 batteries and one of 24. Each negative strap was stamped with its battery specification number.

The first group of 72 batteries was assembled with FP-P1, FP-P2 and FP-P3 positive plates.

The second group of 24 batteries was built with FP-P4 positive plates.

The positive to negative ratios of the dry active material weights, by specification, are shown below:

Batt. Spec. Nos.		Total Pos.	Total Neg.	Ratio
<u>1.285 Acid</u>	<u>1.315 Acid</u>	<u>Gms</u>	<u>Gms</u>	<u>P/N</u>
5716	5758	5958	5536	1.08
5717	5759	6499	5074	1.28
5718	5760	5958	5536	1.08
5719	5761	6499	5074	1.28
5720	5762	4940	5536	0.89
5721	5763	5389	5074	1.06
5722	5764	4940	5536	0.89
5723	5765	5389	5074	1.06
5724	5766	4940	5536	0.89
5725	5767	5389	5074	1.06
5726	5768	4940	5536	0.89
5727	5769	5389	5074	1.06
5728	5770	4940	5536	0.89
5729	5771	5389	5074	1.06
5730	5772	4940	5536	0.89
5731	5773	5389	5074	1.06

The 96 batteries were divided into 3 lots. Listed below are the 32 EBS numbers and the serial number of each lot:

<u>EBS No.</u>	<u>Lot 1A</u>	<u>Lot 1B</u>	<u>Lot 2</u>	<u>Lot 3</u>
5716	001		002	003
5717	007		008	009
5718	014		015	013
5719	019		020	021
5720	025		026	027
5721	031		032	033
5722	037		038	039
5723	043		044	045
5724	049		050	051
5725	055		056	057
5726	061		062	063
5727	069		068	067
5728		074	075	073
5729		079	080	081
5730		087	085	086
5731		091	093	092
5758	004		005	006
5759	010		011	012
5760	016		017	018
5761	022		023	024
5762	028		029	030
5763	034		035	036
5764	040		041	042
5765	046		047	048
5766	052		053	054

<u>EBS No.</u>	<u>Lot 1A</u>	<u>Lot 1B</u>	<u>Lot 2</u>	<u>Lot 3</u>
5767	058		059	060
5768	064		065	066
5769	070		071	072
5770		077	078	076
5771		082	083	084
5772		088	089	090
5773		094	096	095

1.1.6 Testing - Characteristics

At the EXIDE Management & Technology Company, before testing, intermediate cell leads were attached to all the batteries so individual cell voltages could be recorded.

The characteristics testing regime is as follows:

<u>Cycle</u>	<u>Disch. Rate Amps</u>	<u>Disch. Rate Hrs.</u>	<u>Starting Temp °C</u>
1	40	5	25
2	60	3	25
3	75	2	25
4	140	1	25
5	10	20	25
6	240	.5	25
7	40	5	0
8	60	3	0
9	75	2	0
10	140	1	0
11	240	.5	0
12	40	5	0
13	60	3	40
14	75	2	40
15	140	1	40
16	240	.5	40

Recharging is done in two steps - a high-rate mode and a low-rate mode. The high-rate mode is controlled at 40 amperes to 90 percent of the discharge capacity. The low-rate mode is held at 5 amps until a total of 115 percent of the discharge capacity is reached.

Twenty-four hours is allotted for recharging (during characteristics testing only) but a shorter time can be used if all conditions are met.

Shown below is an example of a recharge regime for a battery of 200AH capacity (previously discharged 100% or 200AH).

Capacity restored at high-rate mode (90% of 200AH)	180AH
Time in high-rate mode (180AH - 40A)	4.5 Hrs
Desired total recharge (115% of 200AH)	230AH
AH input in low-rate mode (230AH - 180 AH)	40AH
Time in low-rate mode (50AH - 5A)	10.0 Hrs
Total charging time	14.5 Hrs
Temperature adjustment time available	9.5 Hrs.

Two major problems delayed the testing program - the lack of batteries built with FP-P4 plates and a late delivery of the newly purchased automatic testing equipment.

To minimize delays, the program was revised to:

- o Conduct characteristics tests on the 24 batteries completed (Lot 1A) but not wait for those to be built with the second batch of FP-P4 plates (Lot 1B).
- o Use the in-house manually operated test equipment.

After the automatic test equipment was installed, Lots 1B (8 batteries) and 3 (32 batteries) were tested together.

The data gathered - 16 cycles for Lot 1A and 12 cycles for Lots 1B and 3 are shown in Tables 1 through 28.

On June 6, 1979, the characterization testing equipment malfunctioned causing damage to the environmental chamber and interrupting the testing program of Lots 1B and 3. A Government Property Damage Report was issued to ANL on July 3, 1979.

On July 20, 1979, during Discharge Cycle 11 - 240A @ °C - a low resistance short was accidentally placed on 24 of the 40 batteries of Lots 3 and 1B. The discharge lasted about 5 minutes and damaged 3 batteries - EBS 5719/021, EBS 5722/039 and EBS 5757/067. EBS 5727/067 was irreparably damaged, the other two batteries were repaired and replaced in the test circuit. There was some minor damage to the wire insulation of the three test positions which was repaired.

DISCHARGE DATA

LOT 1A

Cycle No. 1 at 40 Amps 25 CDischarge Date 11/30/78

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	001	4.43	177	1033	35.4
5717	"	R	OP	"	007	4.42	177	1028	35.1
5718	"	P	ON	"	014	4.78	191	1121	38.2
5719	"	P	OP	"	019	4.77	191	1116	37.7
5720	FP-P2	R	ON	"	025	4.44	178	1036	37.0
5721	"	R	OP	"	031	4.46	178	1042	37.3
5722	"	P	ON	"	037	4.61	184	1080	38.7
5723	"	P	OP	"	043	4.73	189	1110	39.7
5724	FP-P3	R	ON	"	049	4.22	169	983	35.7
5725	"	R	OP	"	055	4.33	173	1013	36.9
5726	"	P	ON	"	061	4.50	180	1057	38.2
5727	"	P	OP	"	069	4.70	188	1106	40.3
5758	FP-P1	R	ON	1.315	004	4.36	174	1018	35.1
5759	"	R	OP	"	010	4.43	177	1037	35.3
5760	"	P	ON	"	022	4.71	188	1106	37.7
5761	"	P	OP	"	016	4.74	190	1110	38.0
5762	FP-P2	R	ON	"	028	4.46	178	1045	37.4
5763	"	R	OP	"	034	4.49	180	1053	37.7
5764	"	P	ON	"	040	+	+	+	+
5765	"	P	OP	"	046	+	+	+	+
5766	FP-P3	R	ON	"	052	4.45	178	1045	37.8
5767	"	R	OP	"	058	4.13	165	969	35.1
5768	"	P	ON	"	064	4.65	186	1098	39.6
5769	"	P	OP	"	070	4.59	184	1084	39.2

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.*** ON = Outside negative plates
OP = Outside positive plates

+ No Data Available

TABLE I
CHARACTERISTICS TEST DATA

Cycle No. 1 at 40 Amps 25 C

LOT 1B

Discharge Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5728	FP-P4	R	ON	1.285	074	4.28	171.0	998.9	35.0
5729	"	R	OP	"	079	4.21	168.5	984.4	35.2
5730	"	P	ON	"	087	4.79	191.6	1122.5	39.1
5731	"	P	CP	"	091	4.58	183.1	1067.7	37.5
5770	"	R	ON	1.315	077	4.44	177.7	1042.2	36.6
5771	"	R	CP	"	082	4.87	194.8	1153.2	40.4
5772	"	P	ON	"	088	4.79	191.4	1130.5	40.2
5773	"	P	OP	"	094	4.81	192.3	1135.4	39.5

-10-

- * Experimental Battery Specification No.
- ** R = Microporous Hard Rubber supplied by Amerace.
- P = Daramic supplied by W. R. Grace Co.
- *** ON = Outside negative plates
- OP = Outside positive plates
- + No Data Available

TABLE I (CONTINUED)

Cycle No. 1 at 40 Amps 25 C

LOT #3

Discharge Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	003	4.03	161.1	934.2	32.2
5717	"	R	OP	"	009	3.83	153.1	889.1	30.2
5718	"	P	ON	"	013	4.60	184.1	1068.8	37.2
5719	"	P	OP	"	021	4.12	164.7	961.1	32.5
5720	FP-P2	R	ON	"	027	4.09	163.4	949.6	35.9
5721	"	R	OP	"	033				
5722	"	P	ON	"	039	4.61	184.3	1077.0	38.6
5723	"	P	OP	"	045	4.54	181.6	1061.5	38.0
5724	FP-P3	R	ON	"	051	4.15	166.2	964.5	35.2
5725	"	R	OP	"	057	4.13	165.4	961.5	35.0
5726	"	P	ON	"	063	4.60	184.1	1073.3	39.2
5727	"	P	OP	"	067	4.67	186.9	1100.3	39.8
5728	FP-P4	R	ON	"	073	4.15	166.2	966.8	34.4
5729	"	R	OP	"	081	4.24	169.5	989.3	35.6
5730	"	P	ON	"	086	4.56	182.3	1069.3	37.7
5731	"	P	OP	"	092	4.64	185.5	1081.9	38.4
5758	FP-P1	R	ON	1.315	006	4.27	170.7	999.6	34.7
5759	"	R	OP	"	012	4.16	166.4	974.3	32.9
5760	"	P	ON	"	018	4.92	196.8	1156.4	39.4
5761	"	P	OP	"	024	4.75	190.1	1119.2	38.0
5762	FP-P2	R	ON	"	030	4.39	175.6	1032.8	37.0
5763	"	R	OP	"	036	4.25	170.2	999.2	35.6
5764	"	P	ON	"	042	4.99+	199.0	1171.7	42.9
5765	"	P	OP	"	048	4.91	196.5	1158.5	41.5
5766	FP-P3	R	ON	"	054	4.52	180.7	1061.4	38.7
5767	"	R	OP	"	060	4.40	176.1	1033.3	37.7
5768	"	P	ON	"	066	4.93	197.2	1164.1	42.3
5769	"	P	OP	"	072	4.70	187.8	1109.3	40.4
5770	FP-P4	R	ON	"	076	4.53	181.3	1065.4	38.4
5771	"	R	OP	"	084	4.49	179.5	1059.4	37.1
5772	"	P	ON	"	090	4.91	196.3	1167.8	40.4
5773	"	P	OP	"	095	4.71	188.8	1113.5	38.4

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.

P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates

OP = Outside positive plates

+ Equipment Malfunctions

TABLE 2
CHARACTERISTICS TEST DATA

LOT 1A

Cycle No. 2 at 60 Amps at 25C

Date 12/1/78

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	001	2.49	149	872	29.9
5717	"	R	OP	"	007	2.51	151	871	29.7
5718	"	P	ON	"	014	2.77	166	972	33.1
5719	"	P	OP	"	019	2.82	169	985	33.2
5720	FP-P2	R	ON	"	025	2.57	154	894	31.9
5721	"	R	OP	"	031	2.60	156	907	32.4
5722	"	P	ON	"	037	2.60	160	935	33.5
5723	"	P	OP	"	043	2.67	167	979	35.0
5724	FP-P3	R	ON	"	049	2.79	156	897	32.1
5725	"	R	OP	"	055	2.64	158	922	33.6
5726	"	P	ON	"	061	2.75	165	965	34.9
5727	"	P	OP	"	069	2.92	175	1028	37.5
5758	FP-P1	R	ON	1.315	004	2.54	152	885	30.5
5759	"	R	OP	"	010	2.65	159	927	31.6
5760	"	P	ON	"	016	2.79	167	982	33.6
5761	"	P	OP	"	022	2.84	170	999	34.1
5762	FP-P2	R	ON	"	028	2.65	158	930	33.3
5763	"	R	OP	"	034	2.66	160	932	33.4
5764	"	P	ON	"	040	2.84	170	1003	36.1
5765	"	P	OP	"	046	2.84	171	1004	35.8
5766	FP-P3	R	ON	"	052	2.67	160	940	34.0
5767	"	R	OP	"	058	+	+	+	+
5768	"	P	ON	"	064	+	+	+	+
5769	"	P	OP	"	070	+	+	+	+

-12-

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates
OP = Outside positive plates

+ No Data Available

TABLE 3
CHARACTERISTICS TEST DATA

Cycle No: 2 at 60 Amps 25 C

LOT 1B

Discharge Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5728	FP-P4	R	ON	1.285	074	2.62	157.4	920.9	32.2
5729	"	R	OP	"	079	2.63	157.8	921.3	33.0
5730	"	P	ON	"	087	2.97	178.6	1052.0	36.7
5731	"	P	OP	"	091	2.94	176.5	1034.0	36.4
5770	"	R	ON	1.315	077	2.74	164.9	969.9	34.1
5771	"	R	OP	"	082	2.86	172.1	1015.7	35.6
5772	"	P	ON	"	088	2.94	177.0	1050.0	37.3
5773	"	P	OP	"	094	3.05	183.3	1086.5	37.8

-13-

- * Experimental Battery Specification No.
- ** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.
- *** ON = Outside negative plates
OP = Outside positive plates

+ No Data Available

TABLE 3 (CONTINUED)

Cycle No. 2 at 60 Amps 25 C

LOT #3

Discharge Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	003	2.49	149.9	870.9	30.1
5717	"	R	OP	"	009	2.44	146.8	852.0	28.9
5718	"	P	ON	"	013	2.84	171.2	988.6	34.8
5719	"	P	OP	"	021	2.58	155.0	902.6	30.5
5720	FP-P2	R	ON	"	027	2.56	153.6	894.5	31.9
5721	"	R	OP	"	033	2.61	155.8	904.9	32.3
5722	"	P	ON	"	039	2.89	173.6	1017.2	36.5
5723	"	P	OP	"	045	2.94	176.7	1034.4	37.1
5724	FP-P3	R	ON	"	051	2.60	156.0	909.4	33.2
5725	"	R	OP	"	057	2.65	159.1	926.5	33.7
5726	"	P	ON	"	063	2.89	173.9	1018.2	37.2
5727	"	P	OP	"	067	3.02	183.7	1079.4	39.0
5728	FP-P4	R	ON	"	073	2.51	150.8	877.9	31.3
5729	"	R	OP	"	081	2.68	160.8	938.5	33.8
5730	"	P	ON	"	086	2.75	165.5	974.2	34.4
5731	"	P	OP	"	092	2.99	179.9	1052.4	37.3
5758	FP-P1	R	ON	1.315	006	2.61	156.8	920.1	32.0
5759	"	R	OP	"	012	2.70	162.5	951.5	32.2
5760	"	P	ON	"	018	3.13	188.3	1113.1	37.9
5761	"	P	OP	"	024	3.11	187.0	1104.8	37.4
5762	FP-P2	R	ON	"	030	2.75	165.5	973.4	34.9
5763	"	R	OP	"	036	2.76	165.7	974.4	34.7
5764	"	P	ON	"	042	3.10	186.3	1102.4	40.4-
5765	"	P	OP	"	048	3.10	186.0	1100.5	39.4
5766	FP-P3	R	ON	"	054	2.80	168.4	992.5	36.2
5767	"	R	OP	"	060	2.78	167.0	982.6	35.8
5768	"	P	ON	"	066	3.12	187.5	1111.1	40.4-
5769	"	P	OP	"	072	3.08	185.1	1096.4	40.0
5770	FP-P4	R	ON	"	076	2.78	167.3	987.9	35.6
5771	"	R	OP	"	084	2.84	170.5	1005.7	35.2
5772	"	P	ON	"	090	2.98	179.1	1066.6	36.9
5773	"	P	OP	"	095	3.10	186.3	1103.4	38.1

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.

P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates

OP = Outside positive plates

+ Equipment Malfunctions

TABLE 4

CHARACTERISTICS TEST DATA

Cycle No. 3 at 75 Amps 25C

Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.70 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	001	1.93	145	836	28.6
5717	"	R	OP	"	007	1.99	149	856	29.2
5718	"	P	ON	"	014	2.16	162	939	32.0
5719	"	P	OP	"	019	2.22	166	959	32.4
5720	FP-P2	R	ON	"	025	1.92	144	828	29.6
5721	"	R	OP	"	031	0.02	151	869	31.1
5722	"	P	ON	"	037	1.99	149	865	31.0
5723	"	P	OP	"	043	2.13	160	930	33.3
5724	FP-P3	R	ON	"	049	1.92	144	823	29.9
5725	"	R	OP	"	055	1.99	149	861	31.3
5726	"	P	ON	"	061	2.02	152	882	31.9
5727	"	P	OP	"	069	2.20	165	961	35.0
5758	FP-P1	R	ON	1.315	004	1.94	145	840	29.0
5759	"	R	OP	"	010	2.08	156	901	30.7
5760	"	P	ON	"	016	2.15	161	937	32.1
5761	"	P	OP	"	022	2.22	166	966	32.9
5762	FP-P2	R	ON	"	028	2.00	149	865	30.9
5763	"	R	OP	"	034	2.03	152	880	31.5
5764	"	P	ON	"	040	2.12	159	931	33.5
5765	"	P	OP	"	046	2.16	162	945	33.7
5766	FP-P3	R	ON	"	052	1.98	149	862	31.2
5767	"	R	OP	"	058	1.87	140	862	31.2
5768	"	P	ON	"	064	2.08	156	914	33.0
5769	"	P	OP	"	070	2.11	158	921	33.3

-51-

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates
OP = Outside positive plates
+ No Data Available

TABLE 5
CHARACTERISTICS TEST DATA

Cycle No. 3 at 75 Amps 25 C

LOT 13

Discharge Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5728	FP-P4	R	ON	1.285	074	1.88	141.1	815.9	28.6
5729	"	R	OF	"	079	1.95	146.6	846.4	30.3
5730	"	P	ON	"	087	2.14	160.6	934.6	32.6
5731	"	P	OF	"	091	2.12	159.3	925.0	32.5
5770	"	R	ON	1.315	077	2.09	157.1	914.5	32.2
5771	"	R	OP	"	082	2.13	160.0	935.4	32.8
5772	"	P	ON	"	088	2.21	165.5	973.0	34.6
5773	"	P	OP	"	094	2.35	176.2	1033.7	36.0

-91-

- * Experimental Battery Specification No.
- ** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.
- *** ON = Outside negative plates
OP = Outside positive plates
- + No Data Available

TABLE 5 (CONTINUED)

Cycle No. 3 at 75 Amps 28 C

LOT #3

Discharge Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	003	1.84	138.4	797.4	27.5
5717	"	R	OP	"	009	1.86	139.7	804.0	27.3
5718	"	P	ON	"	013	2.18	163.8	942.9	32.8
5719	"	P	OP	"	021	1.89	142.0	819.0	27.7
5720	FP-P2	R	ON	"	027	1.95	146.4	845.8	30.2
5721	"	R	OP	"	033	1.96	147.7	851.4	30.4
5722	"	P	ON	"	039	2.16	162.3	942.8	33.8
5723	"	P	OP	"	045	2.18	164.3	954.3	34.2
5724	FP-P3	R	ON	"	051	1.97	148.0	855.1	31.2
5725	"	R	OP	"	057	2.01	151.3	874.0	31.8
5726	"	P	ON	"	063	2.16	161.8	939.4	34.3
5727	"	P	OP	"	067	2.28	170.9	994.9	36.0
5728	FP-P4	R	ON	"	073	1.93	144.7	835.4	29.8
5729	"	R	OP	"	081	1.98	147.3	858.9	30.9
5730	"	P	ON	"	086	2.06	154.5	899.8	31.7
5731	"	P	OP	"	092	2.21	166.0	963.5	34.1
5758	FP-P1	R	ON	1.315	006	2.01	150.9	877.5	30.5
5759	"	R	OP	"	012	2.05	153.8	893.5	30.2
5760	"	P	ON	"	018	2.36	177.1	1036.6	35.3
5761	"	P	OP	"	024	2.34	175.4	1026.7	34.8
5762	FP-P2	R	ON	"	030	2.03	152.2	890.5	31.9
5763	"	R	OP	"	036	2.10	157.9	920.6	32.8
5764	"	P	ON	"	042	2.33	174.8	1024.8	37.5
5765	"	P	OP	"	048	2.32	174.3	1021.2	36.5
5766	FP-P3	R	ON	"	054	2.09	156.8	914.5	33.3
5767	"	R	OP	"	060	2.10	156.0	900.1	33.2
5768	"	P	ON	"	066	2.34	175.5	1029.2	37.4
5769	"	P	OP	"	072	2.27	170.6	998.5	36.4
5770	FP-P4	R	ON	"	076	2.05	154.2	900.0	32.5
5771	"	R	OP	"	084	2.15	161.3	941.0	32.9
5772	"	P	ON	"	090	2.21	166.3	979.1	33.9
5773	"	P	OP	"	095	2.22	166.6	979.7	33.8

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.

P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates

OP = Outside positive plates

+ Equipment Malfunctions

TABLE 6
CHARACTERISTICS TEST DATA

Cycle No. 4 at 140 Amps at 25 C

LO- 1A

Date 12/11/78

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.65 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	001	.884	124	791	23.7
5717	"	R	OP	"	007	.899	126	700	23.9
5718	"	P	ON	"	014	.993	139	783	26.7
5719	"	P	OP	"	019	1.010	141	792	26.7
5720	FP-P2	R	ON	"	025	.850	119	664	23.7
5721	"	R	OP	"	031	.898	126	701	25.1
5722	"	P	ON	"	037	.894	125	704	25.2
5723	"	P	OP	"	043	.962	135	759	27.2
5724	FP-P3	R	ON	"	049	.853	119	668	24.2
5725	"	R	OP	"	055	.894	125	701	25.5
5726	"	P	ON	"	061	.904	127	714	25.8
5727	"	P	OP	"	069	.995	139	789	28.8
5758	FP-P1	R	ON	1.315	004	.890	125	698	24.1
5759	"	R	OP	"	010	.935	131	733	25.0
5760	"	P	ON	"	016	.993	139	809	27.0
5761	"	P	OP	"	022	1.024	143	789	27.6
5762	FP-P2	R	ON	"	028	.886	124	696	24.9
5763	"	R	OP	"	034	.904	127	709	25.4
5764	"	P	ON	"	040	.960	134	762	27.4
5765	"	P	OP	"	046	.974	136	774	27.6
5766	FP-P3	R	ON	"	052	.923	129	727	26.3
5767	"	R	OP	"	058	.857	120	674	24.4
5768	"	P	ON	"	064	.974	136	777	28.0
5769	"	P	OP	"	070	.985	138	781	28.2

* Experimental Battery Specification No.

TABLE 7

** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.

CHARACTERISTICS TEST DATA

*** ON = Outside negative plates
OP = Outside positive plates

+ No Data Available

Cycle No. 4 at 140 Amps .25 C

Discharge Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5728	FP-P4	R	ON	1.285	074	.88	123.2	683.5	23.9
5729	"	R	OP	"	079	.91	127.1	705.5	25.2
5730	"	P	ON	"	087	.99	138.5	778.9	27.2
5731	"	P	OP	"	091	.99	139.3	781.1	27.5
5770	"	R	ON	1.315	077	.97	135.7	758.6	26.7
5771	"	R	OP	"	082	.98	137.0	771.2	27.0
5772	"	P	ON	"	088	1.00	139.8	796.4	28.3
5773	"	P	OP	"	094	1.07	149.4	849.2	29.5

- * Experimental Battery Specification No. TABLE 7 (CONTINUED)
- ** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.
- *** CN = Outside negative plates
OP = Outside positive plates
- + No Data Available

Cycle No. 4 at 140 Amps 25 C

LOT # 3

Discharge Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	003	.88	122.9	679.2	23.4
5717	"	R	OP	"	009	.87	121.8	673.3	22.8
5718	"	P	ON	"	013	1.03	144.8	809.5	28.2
5719	"	P	OP	"	021	.90	125.9	694.4	23.5
5720	FP-P2	R	ON	"	027	.90	125.9	699.9	25.0
5721	"	R	OP	"	033	.91	128.2	712.7	25.4
5722	"	P	ON	"	039	1.00	140.5	789.5	28.4
5723	"	P	OP	"	045	1.01	141.2	793.1	28.4
5724	FP-P3	R	ON	"	051	.91	127.1	707.6	25.8
5725	"	R	OP	"	057	.94	131.5	730.6	26.6
5726	"	P	ON	"	063	.98	137.1	796.6	28.1
5727	"	P	OP	"	067	1.03	144.2	811.3	29.3
5728	FP-P4	R	ON	"	073	.88	123.6	687.5	24.5
5729	"	R	OP	"	081	.91	128.2	712.9	25.7
5730	"	P	ON	"	086	.93	130.8	738.5	26.0
5731	"	P	OP	"	092	1.02	142.9	803.3	28.5
5758	FP-P1	R	ON	1.315	006	.93	130.8	729.2	25.3
5759	"	R	OP	"	012	.94	131.5	732.0	24.8
5760	"	P	ON	"	018	1.09	152.4	860.0	29.3
5761	"	P	OP	"	024	1.06	148.8	841.0	28.5
5762	FP-P2	R	ON	"	030	.94	132.1	738.5	26.4
5763	"	R	OP	"	036	.95	132.6	742.5	26.4
5764	"	P	ON	"	042	1.06	149.0	846.4	31.0
5765	"	P	OP	"	048	1.05	147.6	837.8	30.0
5766	FP-P3	R	ON	"	054	.97	135.5	759.3	27.7
5767	"	R	OP	"	060	.97	136.2	671.7	24.5
5768	"	P	ON	"	066	1.06	148.0	839.7	30.5
5769	"	P	OP	"	072	1.01	141.4	800.9	29.2
5770	FP-P4	R	ON	"	076	.95	133.4	748.5	27.0
5771	"	R	OP	"	084	.99	138.6	778.5	27.2
5772	"	P	ON	"	090	1.01	142.0	810.2	28.0
5773	"	P	OP	"	095	.98	138.0	787.6	27.2

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.

P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates

OP = Outside positive plates

+ Equipment Malfunctions

TABLE 8
CHARACTERISTICS TEST DATA

LOT 1A

Cycle No. 5 at 10 Amps at 25 C

Date 12/13/78

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.80 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	001	23.01	230	1374	47.1
5717	"	R	OP	"	007	23.08	231	1374	46.9
5718	"	P	ON	"	014	24.80	248	1490	50.7
5719	"	P	OP	"	019	25.06	251	1496	50.5
5720	FP-P2	R	ON	"	025	23.86	239	1427	51.0
5721	"	R	OP	"	031	24.22	242	1444	51.7
5722	"	P	ON	"	037	24.93	249	1493	53.4
5723	"	P	OP	"	043	26.13	261	1564	55.9
5724	FP-P3	R	ON	"	049	21.11	211	1262	45.8
5725	"	R	OP	"	055	21.33	213	1274	46.4
5726	"	P	ON	"	061	22.44	224	1346	48.7
5727	"	P	OP	"	069	23.71	237	1431	52.2
5758	FP-P1	R	ON	1.315	004	20.81	208	1247	43.0
5759	"	R	OP	"	010	21.88	219	1311	44.7
5760	"	P	ON	"	016	22.40	224	1347	45.9
5761	"	P	OP	"	022	22.90	229	1374	47.1
5762	FP-P2	R	ON	"	028	23.43	234	1408	50.4
5763	"	R	OP	"	034	23.31	233	1398	50.1
5764	"	P	ON	"	040	24.23	242	1465	52.5
5765	"	P	OP	"	046	25.19	252	1517	54.1
5766	FP-P3	R	ON	"	052	21.68	217	1306	47.3
5767	"	R	OP	"	058	21.12	211	1770	46.0
5768	"	P	ON	"	064	22.70	277	1375	49.6
5769	"	P	OP	"	070	23.16	232	1397	50.5

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.

*** DN = Outside negative plates
OP = Outside positive plates

+ No Data Available

TABLE 9
CHARACTERISTICS TEST DATA

Cycle No. 5 at 10 Amps 25 C

LCT 1B

Discharge Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5728	FP-P4	R	ON	1.285	074	20.05+	200.5	1187.2	41.6
5729	"	R	OP	"	079	"	"	1188.9	42.5
5730	"	P	ON	"	087	"	"	1199.7	41.8
5731	"	P	OP	"	091	"	"	1194.6	42.0
5770	"	R	ON	1.315	077	"	"	1209.1	42.5
5771	"	R	OP	"	082	"	"	1213.3	42.5
5772	"	P	ON	"	088	"	"	1218.6	43.3
5773	"	P	OP	"	094	"	"	1217.2	42.3

-22-

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.

P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates

OP = Outside positive plates

+ Equipment Malfunctions - Dischg. Terminated by Faulty Timer

TABLE 9 (CONTINUED)

Cycle No. 5 at 10 Amps 25 C

LOT #3

Discharge Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	003	20.05	200.5+	1192.9	41.2
5717	"	R	OP	"	009	"	"	1194.1	40.5
5718	"	P	ON	"	013	"	"	1206.6	42.0
5719	"	P	OP	"	021	"	"	1197.2	40.5
5720	FP-P2	R	ON	"	027	"	"	1203.0	43.0
5721	"	R	OP	"	033	"	"	1200.7	42.9
5722	"	P	ON	"	039	"	"	1209.0	43.4
5723	"	P	OP	"	045	"	"	1209.9	43.4
5724	FP-P3	R	ON	"	051	"	"	1203.2	43.8
5725	"	R	OP	"	057	"	"	1208.0	44.1
5726	"	P	ON	"	063	"	"	1214.8	44.0
5727	"	P	OP	"	067	"	"	1199.2	42.7
5728	FP-P4	R	ON	"	073	"	"	1200.2	43.2
5729	"	R	OP	"	081	"	"	1210.0	42.7
5730	"	P	ON	"	086	"	"	1208.6	42.8
5731	"	P	OP	"	092	"	"	1211.3	42.1
5758	FP-P1	R	ON	1.315	006	"	"	1212.4	41.0
5759	"	R	OP	"	012	"	"	1224.4	41.7
5760	"	P	ON	"	018	"	"	1223.9	41.5
5761	"	P	OP	"	024	"	"	1215.4	43.5
5762	FP-P2	R	ON	"	030	"	"	1216.1	43.3
5763	"	R	OP	"	036	"	"	1227.2	45.9
5764	"	P	ON	"	042	"	"	1226.8	43.9
5765	"	P	OP	"	048	"	"	1218.6	44.4
5766	FP-P3	R	ON	"	054	"	"	1219.8	44.5
5767	"	R	OP	"	060	"	"	1228.4	44.7
5768	"	P	ON	"	066	"	"	1224.2	44.6
5769	"	P	OP	"	072	"	"	1217.9	43.9
5770	FP-P4	R	ON	"	076	"	"	1223.1	42.8
5771	"	R	OP	"	084	"	"	1228.3	42.5
5772	"	P	ON	"	090	"	"	1228.1	42.4
5773	"	P	OP	"	095	"	"		

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.

P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates

OP = Outside positive plates

+ Equipment Malfunctions - Dischg. Terminated by Faulty Timer

TABLE 10

CHARACTERISTICS TEST DATA

Cycle No. 6 at 240 Amps at 25 C

LOT 1 A

Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.50 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	001	.464	111	592	20.3
5717	"	R	OP	"	007	.478	115	607	20.7
5718	"	P	ON	"	014	.528	127	682	23.2
5719	"	P	OP	"	019	.546	131	701	23.7
5720	FP-P2	R	ON	"	025	.419	101	535	19.1
5721	"	R	OP	"	031	.452	108	574	20.5
5722	"	P	ON	"	037	.466	112	602	21.6
5723	"	P	OP	"	043	.502	120	649	23.2
5724	FP-P3	R	ON	"	049	.427	103	544	19.7
5725	"	R	OP	"	055	.455	107	566	20.6
5726	"	P	ON	"	061	.466	112	604	21.8
5727	"	P	OP	"	069	.518	124	674	24.6
5758	FP-P1	R	ON	1.315	004	.423	102	539	18.6
5759	"	R	OP	"	010	.468	112	594	20.2
5760	"	P	ON	"	016	.524	126	675	23.1
5761	"	P	OP	"	022	.544	130	702	23.9
5762	FP-P2	R	ON	"	028	.444	107	567	20.3
5763	"	R	OP	"	034	.452	108	576	20.6
5764	"	P	ON	"	040	.506	121	656	23.6
5765	"	P	OP	"	046	.528	127	684	24.4
5766	FP-P3	R	ON	"	052	.472	113	605	21.9
5767	"	R	OP	"	058	.416	100	531	19.3
5768	"	P	ON	"	064	.503	121	656	23.7
5769	"	P	OP	"	070	.509	122	661	23.9

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates
OP = Outside positive plates

+ No Data Available

TABLE 11

CHARACTERISTICS TEST DATA

Cycle No. 6 at 240 Amps 25 C

LOT 1 B

Discharge Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5728	FP-P4	R	ON	1.285	074	.45	107.1	567.7	19.9
5729	"	R	OP	"	079	.46	110.9	588.1	21.0
5730	"	P	ON	"	087	.50	120.8	651.3	22.7
5731	"	P	OP	"	091	.50	119.7	644.7	22.7
5770	"	R	ON	1.315	077	.48	116.1	617.1	21.7
5771	"	R	OP	"	082	.49	118.3	636.6	22.3
5772	"	P	ON	"	088	.51	122.1	667.6	23.7
5773	"	P	OP	"	094	.54	130.3	711.0	24.7

-25-

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.

P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates

OP = Outside positive plates

+ Equipment Malfunctions

TABLE 11 (CONTINUED)

Cycle No. 6 at 240 Amps 25 C

LOT #3

Discharge Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	003	.44	103.8	548.2	18.9
5717	"	R	OP	"	009	.43	102.0	538.6	18.6
5718	"	P	ON	"	013	.54	127.2	683.4	23.8
5719	"	P	OP	"	021	.45	106.8	561.	19.0
5720	FP-P2	R	ON	"	027	.47	111.7	593.4	21.2
5721	"	R	OP	"	033	.46	111.0	589.3	21.0
5722	"	P	ON	"	039	.53	127.3	687.6	24.7
5723	"	P	OP	"	045	.53	128.3	691.6	24.8
5724	FP-P3	R	ON	"	051	.46	111.4	593.0	21.6
5725	"	R	OP	"	057	.48	114.1	604.8	22.0
5726	"	P	ON	"	063	.51	121.6	653.4	23.9
5727	"	P	OP	"	067	.53	128.0	687.4	24.9
5728	FP-P4	R	ON	"	073	.44	106.8	567.6	20.2
5729	"	R	OP	"	081	.46	111.0	588.8	21.2
5730	"	P	ON	"	086	.48	114.3	617.8	21.8
5731	"	P	OP	"	092	.52	124.4	670.2	23.8
5758	FP-P1	R	ON	1.315	006	.45	107.9	575.6	20.0
5759	"	R	OP	"	012	.43	103.0	547.7	18.5
5760	"	P	ON	"	018	.56	134.3	726.8	24.8
5761	"	P	OP	"	024	.55	130.9	708.5	24.0
5762	FP-P2	R	ON	"	030	.48	114.1	609.6	21.8
5763	"	R	OP	"	036	.49	116.5	621.0	22.1
5764	"	P	ON	"	042	.55	131.5	715.7	26.2
5765	"	P	OP	"	048	.54	130.3	707.6]	25.3
5766	FP-P3	R	ON	"	054	.49	116.9	625.9	22.8
5767	"	R	OP	"	060	.49	118.1	631.0	23.0
5768	"	P	ON	"	066	.54	130.2	708.6	25.8
5769	"	P	OP	"	072	.52	124.1	673.8	24.6
5770	FP-P4	R	ON	"	076	.48	115.7	620.3	22.4
5771	"	R	OP	"	084	.50	120.1	644.8	22.6
5772	"	P	ON	"	090	.54	128.7	704.9	24.4
5773	"	P	OP	"	095	.51	123.0	673.1	23.2

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.

P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates

OP = Outside positive plates

+ Equipment Malfunctions

TABLE 12

CHARACTERISTICS TEST DATA

Cycle No. 7 at 40 Amps at 0 C

LOT 1 A

Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.70 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	001	3.72	149	858	29.3
5717	"	R	OP	"	007	3.77	151	867	29.6
5718	"	P	ON	"	014	4.09	164	952	32.4
5719	"	P	OP	"	019	4.16	166	963	32.5
5720	FP-P2	R	ON	"	025	3.69	148	854	30.5
5721	"	R	OP	"	031	3.85	154	888	31.8
5722	"	P	ON	"	037	3.86	154	897	32.1
5723	"	P	OP	"	043	4.05	162	940	33.6
5724	FP-P3	R	ON	"	049	3.64	145	842	30.6
5725	"	R	OP	"	055	3.76	150	869	31.6
5726	"	P	ON	"	061	3.79	151	889	32.2
5727	"	P	OP	"	069	4.00	160	937	34.2
5758	FP-P1	R	ON	1.315	004	3.70	148	857	29.5
5759	"	R	OP	"	010	3.89	156	886	30.2
5760	"	P	ON	"	016	4.06	162	947	32.3
5761	"	P	OP	"	022	4.02	161	934	32.2
5762	FP-P2	R	ON	"	028	3.79	152	880	31.5
5763	"	R	OP	"	034	3.86	154	895	32.1
5764	"	P	ON	"	040	3.95	158	924	33.2
5765	"	P	OP	"	046	4.02	161	941	33.5
5766	FP-P3	R	ON	"	052	4.20	168	981	35.5
5767	"	R	OP	"	058	4.03	161	939	34.0
5768	"	P	ON	"	064	4.29	172	1010	36.4
5769	"	P	OP	"	070	4.21	168	988	35.7

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates
OP = Outside positive plates

+ No Data Available

TABLE 13
CHARACTERISTICS TEST DATA

Cycle No: 7 at 40 Amps 0 C

LOT 1 B

Discharge Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5728	FP-P4	R	ON	1.285	074	3.71	148.3	861.8	30.2
5729	"	R	OP	"	079	3.89	155.6	904.4	32.4
5730	"	P	ON	"	087	3.98	159.3	932.8	32.5
5731	"	P	OP	"	091	3.95	158.1	923.7	32.5
5770	"	R	ON	1.315	077	3.75	150.2	882.0	31.0
5771	"	R	OP	"	082	3.73	149.1	880.5	30.8
5772	"	P	ON	"	088	3.59	143.5	853.6	30.3
5773	"	P	OP	"	094	3.63	145.3	864.8	30.1

-28-

* Experimental Battery Specification No.
 ** R = Microporous Hard Rubber supplied by Amerace.
 P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates
 OP = Outside positive plates

+ No Data Available

TABLE 13 (CONTINUED)

Cycle No. 7 at 40 Amps 0 C

LOT # 3

Discharge Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	003	3.62	145.0	840.6	29.0
5717	"	R	OP	"	009	3.59	143.7	831.9	28.2
5718	"	P	ON	"	013	4.08	163.1	953.0	33.2
5719	"	P	OP	"	021	3.88	155.2	900.3	30.4
5720	FP-P2	R	ON	"	027	3.79	151.5	881.7	31.5
5721	"	R	OP	"	033	3.85	154.1	895.2	32.0
5722	"	P	ON	"	039	4.11	164.4	960.3	34.5
5723	"	P	OP	"	045	4.02	160.7	939.5	33.7
5724	FP-P3	R	ON	"	051	3.82	152.7	899.2	32.4
5725	"	R	OP	"	057	4.01	160.3	932.7	33.9
5726	"	P	ON	"	063	4.13	165.2	965.7	35.3
5727	"	P	OP	"	067	4.10	164.1	962.8	34.8
5728	FP-P4	R	ON	"	073	3.73	149.0	869.0	31.0
5729	"	R	OP	"	081	3.84	153.8	894.2	32.2
5730	"	P	ON	"	086	3.83	153.4	900.5	31.8
5731	"	P	OP	"	092	4.12	164.8	963.7	34.2
5758	FP-P1	R	ON	1.315	006	3.55	142.0	831.9	28.9
5759	"	R	OP	"	012	3.43	137.1	802.9	27.2
5760	"	P	ON	"	018	3.82	153.0	904.7	30.8
5761	"	P	OP	"	024	3.63	145.3	861.6	29.2
5762	FP-P2	R	ON	"	030	3.78	151.2	886.8	31.8
5763	"	R	OP	"	036	3.76	150.4	882.7	
5764	"	P	ON	"	042	3.92	156.9	929.2	34.0
5765	"	P	OP	"	048	3.62	144.8	860.8	30.8
5766	FP-P3	R	ON	"	054	3.83	153.4	901.2	32.8
5767	"	R	OP	"	060	3.79	151.5	981.2	35.8
5768	"	P	ON	"	066				
5769	"	P	OP	"	072	3.58	143.2	848.0	30.9
5770	FP-P4	R	ON	"	076	3.87	154.7	911.4	32.9
5771	"	R	OP	"	084	3.79	151.5	894.0	31.3
5772	"	P	ON	"	090	3.97	158.8	943.9	32.6
5773	"	P	OP	"	095	3.32	132.7	793.6	27.4

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.

P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates

OP = Outside positive plates

+ Equipment Malfunctions

TABLE 14

CHARACTERISTICS TEST DATA

Cycle No. 8 at 60 Amps at 0 C

LOT 1 A

Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.70 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	001	2.15	129	738	25.3
5717	"	R	OP	"	007	2.20	132	752	25.6
5718	"	P	ON	"	014	2.34	140	808	27.5
5719	"	P	OP	"	019	2.34	140	805	27.2
5720	FP-P2	R	ON	"	025	2.12	127	729	26.0
5721	"	R	OP	"	031	2.24	134	767	27.4
5722	"	P	ON	"	037	2.23	134	769	27.5
5723	"	P	OP	"	043	2.32	139	799	28.6
5724	FP-P3	R	ON	"	049	2.16	129	740	26.8
5725	"	R	OP	"	055	2.23	134	766	27.9
5726	"	P	ON	"	061	2.28	137	788	28.5
5727	"	P	OP	"	069	2.30	138	803	29.3
5758	FP-P1	R	ON	1.315	004	2.24	134	770	26.5
5759	"	R	OP	"	010	2.36	142	813	27.7
5760	"	P	ON	"	016	2.37	142	820	25.8
5761	"	P	OP	"	022	2.33	140	805	27.8
5762	FP-P2	R	ON	"	028	2.20	132	757	27.1
5763	"	R	OP	"	034	2.22	133	765	27.4
5764	"	P	ON	"	040	2.33	140	809	29.1
5765	"	P	OP	"	046	2.32	139	807	28.7
5766	FP-P3	R	ON	"	052	2.25	135	778	28.1
5767	"	R	OP	"	058	2.01	121	693	25.1
5768	"	P	ON	"	064	2.31	139	805	29.0
5769	"	P	OP	"	070	2.20	132	765	27.6

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.*** ON = Outside negative plates
OP = Outside positive plates

+ No Data Available

TABLE 15

CHARACTERISTICS TEST DATA

Cycle No. 8 at 60 Amps 0 C

LOT 1 B

Discharge Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5728	FP-P4	R	ON	1.285	074	2.25	134.8	776.5	27.2
5729	"	R	OP	"	079	2.37	142.0	817.7	29.2
5730	"	P	ON	"	087	2.41	144.5	838.7	29.2
5731	"	P	OP	"	091	2.38	142.5	826.7	29.1
5770	"	R	ON	1.315	077	2.30	137.6	799.5	28.1
5771	"	R	OP	"	082	2.25	134.7	788.0	27.6
5772	"	P	ON	"	088	2.06	123.7	730.7	26.0
5773	"	P	OP	"	094	2.09	125.1	740.1	25.7

-31-

- * Experimental Battery Specification No.
- ** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.
- *** ON = Outside negative plates
OP = Outside positive plates
- + No Data Available

TABLE 15 (CONTINUED)

Cycle No. 8 at 60 Amps 0 C

LOT # 3

Discharge Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	003	2.23	133.5	765.7	26.4
5717	"	R	OP	"	009	2.20	132.3	757.9	25.7
5718	"	P	ON	"	013	2.46	147.9	857.8	29.9
5719	"	P	OP	"	021	2.38	142.9	820.9	27.8
5720	FP-P2	R	ON	"	027	2.32	139.4	804.0	28.7
5721	"	R	OP	"	033	2.37	142.0	817.6	29.2
5722	"	P	ON	"	039	2.50	150.0	870.5	31.2
5723	"	P	OP	"	045	2.43	145.9	846.9	30.4
5724	FP-P3	R	ON	"	051	2.37	141.8	818.0	29.8
5725	"	R	OP	"	057	2.48	148.4	855.8	31.1
5726	"	P	ON	"	063	2.53	151.7	879.9	32.2
5727	"	P	OP	"	067	2.50	149.6	870.0	31.5
5728	FP-P4	R	ON	"	073	2.29	136.9	790.9	28.2
5729	"	R	OP	"	081	2.35	140.9	811.7	29.2
5730	"	P	ON	"	086	2.32	139.1	809.8	28.6
5731	"	P	OP	"	092	2.48	148.9	864.6	30.6
5758	FP-P1	R	ON	1.315	006	2.17	130.0	754.5	26.2
5759	"	R	OP	"	012	2.09	125.2	725.9	24.5
5760	"	P	ON	"	018	2.23	133.7	785.0	26.8
5761	"	P	OP	"	024	2.14	128.2	754.2	25.6
5762	FP-P2	R	ON	"	030	2.31	138.4	803.8	28.8
5763	"	R	OP	"	036	2.29	137.4	798.8	28.4
5764	"	P	ON	"	042	2.31	138.9	816.8	29.9
5765	"	P	OP	"	048	2.10	126.1	744.6	26.7
5766	FP-P3	R	ON	"	054	2.33	140.1	815.2	29.7
5767	"	R	OP	"	060	2.33	140.1	815.9	29.8
5768	"	P	ON	"	066				
5769	"	P	OP	"	072	2.17	130.0	764.3	27.8
5770	FP-P4	R	ON	"	076	2.35	141.1	823.4	29.7
5771	"	R	OP	"	084	2.31	138.9	811.3	28.4
5772	"	P	ON	"	090	2.34	140.7	829.1	28.7
5773	"	P	OP	"	095	1.99	119.6	709.0	24.5

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.

P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates

OP = Outside positive plates

+ Equipment Malfunctions

TABLE 16

CHARACTERISTICS TEST DATA

Cycle No. 9 at 75 Amps at 0 C

LOT 1 A

Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.70 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	001	1.58	119	677	23.2
5717	"	R	OP	"	007	1.60	120	685	23.4
5718	"	P	ON	"	014	1.75	131	756	25.7
5719	"	P	OP	"	019	1.78	133	764	25.8
5720	FP-P2	R	ON	"	025	1.61	121	693	24.8
5721	"	R	OP	"	031	1.68	126	720	25.8
5722	"	P	ON	"	037	1.68	126	724	25.9
5723	"	P	OP	"	043	1.74	130	750	26.8
5724	FP-P3	R	ON	"	049	1.62	121	696	25.2
5725	"	R	OP	"	055	1.65	124	709	25.8
5726	"	P	ON	"	061	1.69	126	729	26.4
5727	"	P	OP	"	069	1.69	127	738	26.9
5758	FP-P1	R	ON	1.315	004	1.58	118	678	23.4
5759	"	R	OP	"	010	1.65	124	709	24.2
5760	"	P	ON	"	016	1.68	126	703	24.8
5761	"	P	OP	"	022	1.62	122	728	24.2
5762	FP-P2	R	ON	"	028	1.62	122	700	25.0
5763	"	R	OP	"	034	1.62	122	799	25.0
5764	"	P	ON	"	040	1.72	129	748	26.9
5765	"	P	OP	"	046	1.71	128	741	26.4
5766	FP-P3	R	ON	"	052	1.67	125	722	26.1
5767	"	R	OP	"	058	1.50	112	647	23.4
5768	"	P	ON	"	064	1.68	126	730	26.3
5769	"	P	OP	"	070	1.60	120	697	25.2

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates
OP = Outside positive plates

+ No Data Available

TABLE 17
CHARACTERISTICS TEST DATA

Cycle No. 9 at 75 Amps 0 C

Lot 1B

Discharge Date 7/16/79

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5728	FP-P4	R	ON	1.285	074	1.60	120.2	678.8	23.8
5729	"	R	OP	"	079	1.66	124.2	701.8	25.1
5730	"	P	ON	"	087	1.68	125.9	718.8	25.1
5731	"	P	OP	"	091	1.63	122.4	698.0	24.5
5770	"	R	ON	1.315	077	1.58	118.6	678.0	23.8
5771	"	R	OP	"	082	1.46	109.1	629.2	22.0
5772	"	P	ON	"	088	1.19	89.5	521.3	18.5
5773	"	P	OP	"	094	1.17	87.8	512.9	17.8

-34-

- * Experimental Battery Specification No.
- ** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.
- *** ON = Outside negative plates
OP = Outside positive plates
- + Equipment Malfunctions

TABLE 17 (CONTINUED)

Cycle No. 9 at 75 Amps 0 C

Lot #3

Discharge Date 7/16/79

FBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.70 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	003	1.57	118.3	667.0	23.0
5717	"	R	OP	"	009	1.49	112.1	632.3	21.4
5718	"	P	ON	"	013	1.67	124.9	712.3	24.8
5719	"	P	OP	"	021	1.61	120.6	681.4	23.0
5720	FP-P2	R	ON	"	027	1.59	119.2	676.0	22.8
5721	"	R	OP	"	033	1.58	118.7	672.3	24.0
5722	"	P	ON	"	039	1.72	129.0	735.1	26.4
5723	"	P	OP	"	045	1.60	120.0	685.2	24.6
5724	FP-P3	R	ON	"	051	1.72	129.2	730.8	26.7
5725	"	R	OP	"	057	1.72	128.8	724.1	25.5
5725	"	P	ON	"	063	1.71	128.4	733.6	26.8
5727	"	P	OP	"	067	1.57	117.7	676.2	24.5
5728	FP-P4	R	ON	"	073	1.63	122.5	696.1	24.8
5729	"	R	OP	"	081	1.62	121.6	689.6	24.8
5730	"	P	ON	"	086	1.70	127.5	730.0	25.7
5731	"	P	OP	"	092	1.69	127.0	727.7	25.8
5758	FP-P1	R	ON	1.315	006	1.50	112.2	642.1	22.3
5759	"	R	OP	"	012	1.41	105.7	605.2	20.5
5760	"	P	ON	"	018	1.32	99.1	574.3	19.6
5761	"	P	OP	"	024	1.30	97.8	567.7	19.3
5762	FP-P2	R	ON	"	030	1.62	121.5	693.0	24.8
5763	"	R	OP	"	036	1.51	113.4	650.0	23.2
5764	"	P	ON	"	042	1.31	98.1	571.1	20.9
5765	"	P	OP	"	048	1.24	92.7	539.1	19.3
5766	FP-P3	R	ON	"	054	1.62	121.9	698.1	25.4
5767	"	R	OP	"	060	1.60	119.6	685.7	25.0
5768	"	P	ON	"	066	1.43	107.1	621.6	22.6
5769	"	P	OP	"	072	1.27	95.3	552.8	20.1
5770	FP-P4	R	ON	"	076	1.59	119.0	683.0	24.6
5771	"	R	OP	"	084	1.47	110.2	636.7	22.3
5772	"	P	ON	"	090	1.27	95.3	556.8	19.3
5773	"	P	OP	"	095	1.30	97.5	568.1	19.6

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.*** ON = Outside negative plates
OP = Outside positive plates

+ Equipment Malfunctions

TABLE 18

CHARACTERISTICS TEST DATA

Cycle No. 10 at 140 Amps at 0 C

LOT 1 A

Date 1/2/79

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. VPC	Cap. A.H.	Watt Hrs.	Whr/ Kg
5716	FP-P1	R	ON	1.265	001	.795 Δ	158.8	884	30.29
5717	"	R	OP	"	007	.794 Δ	159.1	881	30.06
5718	"	P	ON	"	014	.858 Δ	172.0	964	32.83
5719	"	P	OP	"	019	.854 Δ	171.2	957	32.30
5720	FP-P2	R	ON	"	025	.680	95.4	520	18.58
5721	"	R	OP	"	031	.695	97.4	532	19.03
5722	"	P	ON	"	037	.754	105.5	581	20.80
5723	"	P	OP	"	043	.760	106.4	588	21.04
5724	FP-P3	R	ON	"	049	.680 ΔΔ	95.2	498	18.07
5725	"	R	OP	"	055	.673	94.3	515	18.74
5726	"	P	ON	"	061	.722 ΔΔ	106.4	581	21.02
5727	"	P	OP	"	069	.680	95.2	531	19.36
5758	FP-P1	R	ON	1.315	004	.689	96.4	530	18.27
5759	"	R	OP	"	010	.701	98.1	539	18.36
5760	"	P	ON	"	016	.724 ΔΔΔ	101.3	562	19.25
5761	"	P	OP	"	022	.696	97.5	540	18.42
5762	FP-P2	R	ON	"	028	.680	95.2	522	18.68
5763	"	R	OP	"	034	.661	92.5	508	18.21
5764	"	P	ON	"	040	.743	104.0	576	20.71
5765	"	P	OP	"	046	.718	100.6	559	19.91
5766	FP-P3	R	ON	"	052	.739	103.4	567	20.51
5767	"	R	OP	"	058	.624	87.3	478	17.33
5768	"	P	ON	"	064	.720	100.8	562	20.27
5769	"	P	OP	"	070	.679	95.1	530	19.15

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace. TABLE 19
P = Daramic supplied by W. R. Grace Co.*** ON = Outside negative plates
OP = Outside positive plates

+ No Data Available

CHARACTERISTICS TEST DATA

Δ Data invalid due to equipment malfunction.

ΔΔ Discharged stopped before 4.8 battery voltage-pos. cell V 1.571

ΔΔΔ Hrs. to VPC extrapolated from Dischg. curve which ended at .720 hrs. and 4.9 volts.

Cycle No. 10 at 140 Amps 0 C

LOT # 1 B

Discharge Date 7/18/79

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5728	FP-P4	R	ON	1.285	074	.76	106.2	586.5	20.6
5729	"	R	OP	"	079	.78	108.6	600.5	21.5
5730	"	P	ON	"	087	.74	103.8	579.4	20.2
5731	"	P	OP	"	091	.73	102.0	569.6	20.0
5770	"	R	ON	1.315	077	.69	96.6	537.5	18.9
5771	"	R	OP	"	082	.64	89.1	502.3	17.6
5772	"	P	ON	"	088	.50	69.7	397.7	14.1
5773	"	P	OP	"	094	.50	70.4	402.3	14.0

-37-

- * Experimental Battery Specification No.
- ** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.
- *** ON = Outside negative plates
OP = Outside positive plates
- + Equipment Malfunctions

TABLE 19 (CONTINUED)

Cycle No. 10 at 140 Amps 0 °C

LOT # 3

Discharge Date 7/18/79

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.65 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	003	.75	105.4	578.8	20.0
5717	"	R	OP	"	009	.71	99.7	548.5	18.6
5718	"	P	ON	"	013	.73	101.9	569.2	19.8
5719	"	P	OP	"	021	.80	111.7	615.2	20.8
5720	FP-P2	R	ON	"	027	.73	102.6	567.4	20.3
5721	"	R	OP	"	033	.76	107.2	591.5	21.1
5722	"	P	ON	"	039	.77	108.0	600.6	21.6
5723	"	P	OP	"	045	.71	100.1	557.6	20.0
5724	FP-P3	R	ON	"	051	.80	112.2	617.6	22.5
5725	"	R	OP	"	057	.81	114.0	630.2	22.9
5726	"	P	ON	"	063	.77	107.5	597.4	21.8
5727	"	P	OP	"	067	.69	96.8	542.9	19.6
5728	FP-P4	R	ON	"	073	.78	108.8	603.4	21.5
5729	"	R	OP	"	081	.75	105.2	581.4	20.9
5730	"	P	ON	"	086	.75	105.7	590.9	20.8
5731	"	P	OP	"	092	.75	105.2	587.7	20.8
5758	FP-P1	R	ON	1.315	006	.66	91.8	512.1	20.4
5759	"	R	OP	"	012	.62	86.8	482.4	16.3
5760	"	P	ON	"	018	.55	76.7	434.4	14.8
5761	"	P	OP	"	024	.56	79.2	447.7	15.2
5762	FP-P2	R	ON	"	030	.75	104.4	580.2	20.8
5763	"	R	OP	"	036	.67	94.5	528.1	18.8
5764	"	P	ON	"	042	.55	77.3	440.0	16.1
5765	"	P	OP	"	048	.52	73.0	415.2	14.9
5766	FP-P3	R	ON	"	054	.72	100.3	560.3	20.4
5767	"	R	OP	"	060	.72	101.4	565.8	20.6
5768	"	P	ON	"	066	.61	85.2	483.1	17.6
5769	"	P	OP	"	072	.55	77.2	437.4	15.9
5770	FP-P4	R	ON	"	076	.70	97.0	545.7	19.7
5771	"	R	OP	"	084	.64	90.2	508.7	17.8
5772	"	P	ON	"	090	.48	67.6	389.3	13.5
5773	"	P	OP	"	095	.56	78.4	445.2	15.4

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.

P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates

OP = Outside positive plates

+ Equipment Malfunctions

TABLE 20

CHARACTERISTICS TEST DATA

Cycle No. 11 at 240 Amps at 0 C.

LOT 1 A

Date 1/4/79

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	001	.328	79.2	417	14.29
5717	"	R	OP	"	007	.337	81.0	424	14.47
5718	"	P	ON	"	014	.349	83.9	441	15.02
5719	"	P	OP	"	019	.350	84.2	447	15.09
5720	FP-P2	R	ON	"	025	.337	80.8	426	15.22
5721	"	R	OP	"	031	.353	84.8	445	15.92
5722	"	P	ON	"	037	.354	85.0	449	16.08
5723	"	P	OP	"	043	.359	86.1	457	16.35
5724	FP-P3	R	ON	"	049	.346	83.1	437	15.86
5725	"	R	OP	"	055	.347	83.4	434	15.80
5726	"	P	ON	"	061	.351	84.3	448	16.21
5727	"	P	OP	"	069	.349	83.8	449	16.37
5758	FP-P1	R	ON	1.315	004	.398 Δ	95.6	515	17.76
5759	"	R	OP	"	010	.398 Δ	95.6	515	17.55
5760	"	P	ON	"	016	.404 Δ	96.9	526	18.01
5761	"	P	OP	"	022	.397 Δ	95.4	518	17.67
5762	FP-P2	R	ON	"	028	.346	83.0	437	15.64
5763	"	R	OP	"	034	.344	82.5	435	15.59
5764	"	P	ON	"	040	.362	86.7	461	16.58
5765	"	P	OP	"	046	.355	85.1	454	16.17
5766	FP-P3	R	ON	"	052	.356	85.5	452	16.35
5767	"	R	OP	"	058	.311	74.4	392	14.21
5768	"	P	ON	"	064	.352	84.4	452	16.30
5769	"	P	OP	"	070	.334	80.1	428	15.47

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates
OP = Outside positive plates

+ Data Not Available

Δ Data invalid due to equipment malfunction

TABLE 21

CHARACTERISTICS TEST DATA

Cycle No. 11 at 240 Amps 0 °C

LOT 1 B

Discharge Date 7/21/79

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.60 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5728	FP-P4	R	ON	1.285	074	.34	82.0	428.9	15.0
5729	"	R	OP	"	079	.34	82.7	433.7	15.5
5730	"	P	ON	"	087	.32	76.4	404.8	14.1
5731	"	P	OP	"	091	.32	75.8	401.5	14.1
5770	"	R	ON	1.315	077	.28	67.0	343.2	12.1
5771	"	R	OP	"	082	.26	62.7	334.5	11.7
5772	"	P	ON	"	088	.21	51.5	278.0	9.9
5773	"	P	OP	"	094	.22	53.5	289.5	10.1

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.

P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates

OP = Outside positive plates

+ Equipment Malfunctions

TABLE 21 (CONTINUED)

Cycle No. 11 at 24C Amps 0 C

LOT # 3

Discharge Date 7/21/79

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.60 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	003	.31	74.8	389.2	13.4
5717	"	R	OP	"	009	.29	69.7	363.8	12.3
5718	"	P	ON	"	013	.33	79.9	423.9	14.8
5719	"	P	OP	"	021	.33	78.7	410.9	13.9
5720	FP-P2	R	ON	"	027	.31	74.3	389.1	13.9
5721	"	R	OP	"	033	.31	75.1	394.1	14.1
5722	"	P	ON	"	039	.34	82.0	435.0	15.6
5723	"	P	OP	"	045	.32	77.2	409.4	14.7
5724	FP-P3	R	ON	"	051	.34	81.7	427.9	15.6
5725	"	R	OP	"	057	.35	83.5	438.7	16.0
5726	"	P	ON	"	063	.34	82.4	436.3	15.9
5727	"	P	OP	"	067				
5728	FP-P4	R	ON	"	073	.32	76.6	402.5	14.3
5729	"	R	OP	"	081	.31	75.5	395.0	14.2
5730	"	P	ON	"	086	.34	80.9	430.6	15.2
5731	"	P	OP	"	092	.34	81.4	432.6	15.3
5758	FP-P1	R	ON	1.315	006	.28	67.7	357.5	12.4
5759	"	R	OP	"	012	.26	62.7	329.5	11.1
5760	"	P	ON	"	018	.28	67.4	361.2	12.3
5761	"	P	OP	"	024	.28	68.1	364.9	12.4
5762	FP-P2	R	ON	"	030	.32	75.7	398.2	14.3
5763	"	R	OP	"	036	.30	72.1	380.1	13.5
5764	"	P	ON	"	042	.29	69.0	370.9	13.6
5765	"	P	OP	"	048	.28	66.6	357.4	12.8
5766	FP-P3	R	ON	"	054	.30	72.2	382.5	13.9
5767	"	R	OP	"	060	.30	72.2	383.8	14.0
5768	"	P	ON	"	066	.26	63.2	340.5	12.4
5769	"	P	OP	"	072	.24	57.3	307.7	11.2
5770	FP-P4	R	ON	"	076	.29	68.9	368.8	13.3
5771	"	R	OP	"	084	.27	64.2	344.2	12.0
5772	"	P	ON	"	090	.18	42.1	231.6	8.0
5773	"	P	OP	"	095	.25	59.1	318.2	11.0

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.

P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates

OP = Outside positive plates

+ Equipment Malfunctions

TABLE 22

CHARACTERISTICS TEST DATA

Cycle No. 12 at 40 Amps at 40 C.

LOT 1 A

Date 1/8/79

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	001	4.43	177.1	1040	35.64
5717	"	R	OP	"	007	4.44	177.5	1039	35.45
5718	"	P	ON	"	014	4.91	196.3	1163	39.61
5719	"	P	OP	"	019	5.01	200.4	1180	39.82
5720	FP-P2	R	ON	"	025	4.45	177.9	1044	37.31
5721	"	R	OP	"	031	4.60	183.9	1078	38.57
5722	"	P	ON	"	037	4.74 ¹	189.6	1120	40.10
5723	"	P	OP	"	043	5.12	205.0	1209	43.25
5724	FP-P3	R	ON	"	049	4.47 ²	178.8	1053	38.21
5725	"	R	OP	"	055	4.54 ³	181.5	1066	38.81
5726	"	P	ON	"	061	4.81 ⁴	192.3	1139	41.21
5727	"	P	OP	"	069	5.06 ⁵	202.3	1199	43.71
5758	FP-P1	R	ON	1.315	004	4.35 ⁶	174.0	1025	35.34
5759	"	R	OP	"	010	4.62	184.9	1089	37.10
5760	"	P	ON	"	016	4.92 ⁷	196.9	1169	40.03
5761	"	P	OP	"	022	5.08	203.1	1203	41.03
5762	FP-P2	R	ON	"	028	4.26 Δ	170.6	1017	36.39
5763	"	R	OP	"	034	4.71	188.5	1113	39.89
5764	"	P	ON	"	040	4.98 $\Delta\Delta$	199.0	1187	42.68
5765	"	P	OP	"	046	5.18	207.4	1234	43.96
5766	FP-P3	R	ON	"	052	4.70 $\Delta\Delta\Delta$	188.1	1116	40.38
5767	"	R	OP	"	058	4.70 ⁰	178.8	1059	38.40
5768	"	P	ON	"	064	5.70	202.8	1212	43.71
5769	"	P	OP	"	070	5.14 ⁰⁰	205.6	1226	44.31

TABLE 23 - CHARACTERISTICS TEST DATA

	1	Discharge stopped center cell at 1.700 volts
	2	" " " " " 1.695 "
+	3	" " " " " 1.697 "
	4	" " " " " 1.697 "
*	5	" " " " " 1.688 "
**	6	" " " " " 1.698 "
	7	" " positive" " 1.075 "
	Δ	" center " " 1.679 "
***	$\Delta\Delta$	" negative" " 1.699 "
	$\Delta\Delta\Delta$	" center " " 1.697 "
	⁰	" negative" " 1.700 "
	⁰⁰	" center " " 1.694 "

NOTE: Due to the high quantity of early failures at the relatively low rate of 40 amps, and a temperature of 40 C, it is felt the problem was equipment malfunction.

Cycle No. 12 at 40 Amps 40 C

LOT 1 B

Discharge Date 7/27/79

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5728	FP-P4	R	ON	1.285	074	4.57	182.8	1071.6	37.5
5729	"	R	OP	"	079	4.70	188.1	1102.3	39.4
5730	"	P	ON	"	087	5.08	203.2	1197.8	41.8
5731	"	P	OP	"	091	5.02	200.9	1181.2	41.5
5770	"	R	ON	1.315	077	4.88	195.2	1157.2	40.2
5771	"	R	OP	"	082	5.01	200.5	1193.4	41.8
5772	"	P	ON	"	088	5.20	207.9	1241.3	44.1
5773	"	P	OP	"	094	5.39	215.7	1286.0	44.7

-43-

- * Experimental Battery Specification No.
- ** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.
- *** ON = Outside negative plates
OP = Outside positive plates
- + Equipment Malfunctions

TABLE 23 (CONTINUED)

Cycle No. 12 at 40 Amps 40 C

LOT # 3

Discharge Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	003	4.45	178.4	1043.5	36.0
5717	"	R	OP	"	009				
5718	"	P	ON	"	013	5.12	205.0	1204.5	41.9
5719	"	P	OP	"	021	4.52	181.2	1061.0	35.9
5720	FP-P2	R	ON	"	027	4.69	187.7	1103.5	39.4
5721	"	R	OP	"	033	4.63	185.5	1087.5	38.8
5722	"	P	ON	"	039	5.14	205.8	1212.7	43.5
5723	"	P	OP	"	045	5.13	205.5	1212.2	43.5
5724	FP-P3	R	ON	"	051	4.72	188.8	1109.3	40.5
5725	"	R	OP	"	057	4.75	190.0	114.9	40.5
5726	"	P	ON	"	063	5.08	203.1	1206.9	44.1
5727	"	P	OP	"	067				
5728	FP-P4	R	ON	"	073	4.47	178.7	1049.8	37.4
5729	"	R	OP	"	081	4.71	188.3	1105.0	39.8
5730	"	P	ON	"	086	4.96	198.6	1174.0	41.4
5731	"	P	OP	"	092	5.17	206.9	1218.1	43.2
5758	FP-P1	R	ON	1.315	006	4.83	193.1	1141.5	39.7
5759	"	R	OP	"	012	4.68	187.1	1107.6	37.4
5760	"	P	ON	"	018	5.36	214.3	1272.5	43.4
5761	"	P	OP	"	024	5.31	212.4	1260.8	42.8
5762	FP-P2	R	ON	"	030	4.90	195.9	1159.6	41.5
5763	"	R	OP	"	036	4.89	195.7	1160.6	41.3
5764	"	P	ON	"	042	5.39	215.5	1282.3	47.0
5765	"	P	OP	"	048	5.39	215.6	1281.5	45.9
5766	FP-P3	R	ON	"	054	4.89	195.6	1160.9	42.3
5767	"	R	OP	"	060	4.92	196.8	1168.0	42.6
5768	"	P	ON	"	066	5.31	212.2	1263.8	46.0
5769	"	P	OP	"	072	5.18	207.2	1231.7	44.9
5770	FP-P4	R	ON	"	076	4.69	187.6	1115.5	40.2
5771	"	R	OP	"	084	5.06	202.3	1205.2	42.2
5772	"	P	ON	"	090	5.05	202.0	1212.6	42.0
5773	"	P	OP	"	095	5.12	204.7	1223.1	42.2

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.

P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates

OP = Outside positive plates

+ Equipment Malfunctions

TABLE 24

CHARACTERISTICS TEST DATA

Cycle No. 13 at 60 Amps at 40C

LOT 1 A

Discharge Date 1/11/79

Date _____

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	001	2.79	167.5	978	33.52
5717	"	R	OP	"	007	2.76	165.8	1125	32.96
5718	"	P	ON	"	014	3.19	191.1	1125	38.32
5719	"	P	OP	"	019	3.20	192.1	1125	37.97
5720	FP-P2	R	ON	"	025	2.82	169.1	936	35.24
5721	"	R	OP	"	031	2.88	172.6	1105	35.96
5722	"	P	ON	"	037	3.08	184.8	1084	38.81
5723	"	P	OP	"	043	3.28	196.5	1153	41.25
5724	FP-P3	R	ON	"	049	2.90	173.8	1016	36.86
5725	"	R	OP	"	055	2.92	175.0	1020	37.13
5726	"	P	ON	"	061	3.16	189.6	1115	40.34
5727	"	P	OP	"	069	3.30	199.2	1167	42.54
5758	FP-P1	R	ON	1.315	004	2.79	167.5	980	33.79
5759	"	R	OP	"	010	1.28 Δ	76.6	463	15.78
5760	"	P	ON	"	016	3.24	194.2	1145	39.21
5761	"	P	OP	"	022	3.26	196.7	1152	39.29
5762	FP-P2	R	ON	"	028	2.96	177.3	1042	37.28
5763	"	R	OP	"	034	2.97	178.2	1045	37.46
5764	"	P	ON	"	040	3.30	197.7	1170	42.07
5765	"	P	OP	"	046	3.38	202.6	1197	42.64
5766	FP-P3	R	ON	"	052	3.08	184.6	1086	39.29
5767	"	R	OP	"	058	2.83 ΔΔ	169.6	998	36.18
5768	"	P	ON	"	064	3.36	201.6	1197	43.17
5769	"	P	OP	"	070	3.36	201.6	1193	43.11

Δ Dischg. stopped positive cell at 1.480 volts

ΔΔ " " negative " " 1.648 "

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.*** ON = Outside negative plates
OP = Outside positive plates

+ No Data Available

TABLE 25

CHARACTERISTICS TEST DATA

Cycle No. 14 at 75 Amps 40 C

LOT 1 A

Discharge Date 1/16/79

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.75 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	001	2.17	162.8	947	32.45
5717	"	R	OP	"	007	2.16	161.8	938	32.00
5718	"	P	ON	"	014	2.47	185.3	1085	36.96
5719	"	P	OP	"	019	2.49	186.6	1088	36.72
5720	FP-P2	R	ON	"	025	2.13	160.6	932	33.31
5721	"	R	OP	"	031	2.18	163.5	948	33.92
5722	"	P	ON	"	037	2.34	175.8	1027	36.77
5723	"	P	OP	"	043	2.49	186.6	1089	38.96
5724	FP-P3	R	ON	"	049	2.16	162.1	942	34.18
5725	"	R	OP	"	055	2.18	163.7	950	34.58
5726	"	P	ON	"	061	2.36	177.2	1036	37.48
5727	"	P	OP	"	069	2.43	186.3	1091	39.77
5758	FP-P1	R	ON	1.315	004	2.21	165.5	972	33.52
5759	"	R	OP	"	010 +				
5760	"	P	ON	"	016	2.53	190.1	1124	38.49
5761	"	P	OP	"	022	2.56	192.2	1133	38.64
5762	FP-P2	R	ON	"	028	2.32	173.9	1025	36.67
5763	"	R	OP	"	034	2.34	174.4	1027	36.81
5764	"	P	ON	"	040	2.50	187.6	1107	39.80
5765	"	P	OP	"	046	2.59	194.6	1150	40.97
5766	FP-P3	R	ON	"	052	2.32	174.0	1025	37.08
5767	"	R	OP	"	058	2.15	161.7	949	34.41
5768	"	P	ON	"	064	2.51	188.0	1103	39.96
5769	"	P	OP	"	070	2.51	188.4	1108	40.04

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates
OP = Outside positive plates

+ No Data Available

TABLE 26

CHARACTERISTICS TEST DATA

Cycle No. 15 at 140 Amps at 40 C

LOT 1 A

Discharge Date 1/24/79

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	001	.907	126.2	710	24.33
5717	"	R	OP	"	007	.900	126.0	705	24.05
5718	"	P	ON	"	014	1.056	147.3	853	28.64
5719	"	P	OP	"	019	1.074	151.3	740	28.79
5720	FP-P2	R	ON	"	025	.941	131.1	740	26.45
5721	"	R	OP	"	031	.972	136.1	763	27.30
5722	"	P	ON	"	037	1.040	145.7	826	29.57
5723	"	P	OP	"	043	1.107	155.0	881	31.52
5724	FP-P3	R	ON	"	049	.985	137.9	780	28.30
5725	"	R	OP	"	055	.683	95.6	529	19.26
5726	"	P	ON	"	061	1.072	150.1	855	30.93
5727	"	P	OP	"	069	1.109	155.3	881	32.11
5758	FP-P1	R	ON	1.315	004	.979	137.1	779	26.86
5759	"	R	OP	"	010	1.020	143.1	812	27.67
5760	"	P	ON	"	016	1.162	162.7	932	31.79
5761	"	P	OP	"	022	1.157	161.9	931	31.88
5762	FP-P2	R	ON	"	028	1.032	144.5	824	29.48
5763	"	R	OP	"	034 +				
5764	"	P	ON	"	040	1.117	156.4	895	32.13
5765	"	P	OP	"	046	1.159	162.2	930	33.13
5766	FP-P3	R	ON	"	052	1.080	151.2	863	31.22
5767	"	R	OP	"	058	.986	138.1	786	28.50
5768	"	P	ON	"	064	1.151	161.1	925	33.36
5769	"	P	OP	"	070	1.153	161.4	924	33.39

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.*** ON = Outside negative plates
OP = Outside positive plates

+ No Data Available

TABLE 27

CHARACTERISTICS TEST DATA

Cycle No. 16 at 240 Amps at 40 C

LOT 1 A

Date 1/29/79

EBS No.*	Plate Type	Sep.**	Const.***	Final Sp.Gr.	Ser. No.	Hrs. 1.60 VPC	Cap. A.H.	Watt Hrs.	Whr/Kg
5716	FP-P1	R	ON	1.285	001	.446	107.1	577	19.77
5717	"	R	OP	"	007	.443	106.4	571	19.48
5718	"	P	ON	"	014	.535	238.4	700	23.84
5719	"	P	OP	"	019	.548	131.5	714	24.10
5720	FP-P2	R	ON	"	025	.453	108.8	586	20.94
5721	"	R	OP	"	031	.458	109.9	591	21.14
5722	"	P	ON	"	037	.506	121.5	659	23.59
5723	"	P	OP	"	043	.534	128.2	695	24.87
5724	FP-P3	R	ON	"	049	.471	113.1	610	22.13
5725	"	R	OP	"	055	.450	108.0	580	21.11
5726	"	P	ON	"	061	.528	126.7	688	24.89
5727	"	P	OP	"	069	.537	128.9	698	24.45
5758	FP-P1	R	ON	1.315	004	.451	108.3	589	20.31
5759	"	R	OP	"	010	.460	110.3	599	20.51
5760	"	P	ON	"	016	.550	131.7	726	24.86
5761	"	P	OP	"	022	.541	130.1	714	24.35
5762	FP-P2	R	ON	"	028	.483	115.9	629	22.50
5763	"	R	OP	"	034	.494	118.6	651	23.33
5764	"	P	ON	"	040	.527	126.5	691	24.85
5765	"	P	OP	"	046	.546	131.0	722	25.72
5766	FP-P3	R	ON	"	052	.513	123.1	675	24.42
5767	"	R	OP	"	058	.459	110.2	597	21.65
5768	"	P	ON	"	064	.554	133.0	728	26.25
5769	"	P	OP	"	070	.547	131.3	719	25.98

* Experimental Battery Specification No.

** R = Microporous Hard Rubber supplied by Amerace.
P = Daramic supplied by W. R. Grace Co.

*** ON = Outside negative plates
OP = Outside positive plates

+ No Data Available

TABLE 28

CHARACTERISTICS TEST DATA

1.1.7 Testing - Life Cycle

The life-cycle generally consists of 2.4 hours at a constant 60 amperes (80% of the 3-hr rate of 60A) followed by a two-step recharge. Step one is at 40 amperes (5-hr rate) until 2.37 volts per cell is reached and step two at a constant 5 amperes (24-hr rate) until 125 percent of the discharge is returned to the battery.

The schedule is 1-1/2 cycles each 24 hours with a catchout cycle (a complete discharge to final voltage and recharge) every two weeks.

The life-cycle regime is subject to change as data is gathered.

The laboratory has 3 identical life cyclers numbered I, II and III. Each life cycle tester is divided into seven loops. Each loop accepts eight batteries. The battery positions of each loop are:

- o Loop 1 - battery position 1 to 8
- o Loop 2 - battery position 9 to 16
- o Loop 3 - battery position 17 to 24
- o Loop 4 - battery position 25 to 32
- o Loop 5 - battery position 33 to 40
- o Loop 6 - battery position 41 to 48
- o Loop 7 - battery position 49 to 56.

In an attempt to reduce test time, Lot 2 (32) batteries were placed on life cycle testing without being given characteristics tests. The test regime from Cycle 1 through 91 are as follows except where noted: -

<u>Cycle</u>	<u>Mode</u>	<u>Loops</u>	<u>Dischg</u>	<u>O.C.</u>	<u>High Charge</u>	<u>Low Charge</u>	<u>O.C.</u>
1 thru 5	Rate-Amps	1-4	60	0	40	5	0
	Voltage Limit	1-4	1.7	-	2.5	-	-
	Time in Mode-Hrs	1-4	2.4	1.05	3.5	8.0	1.05
5 thru 10	Rate-Amps	1-4	60	0	40	5	0
	Voltage Limit	1-4	1.7		2.4		
	Time in Mode-Hrs	1-4	2.4	0	3.5	8.0	1.05

Between Cycles 10 and 11, the low charge time was extended to 18 hrs. as an equalizing charge.

<u>Cycle</u>	<u>Mode</u>	<u>Loops</u>	<u>Dischg</u>	<u>O.C.</u>	<u>High Charge</u>	<u>Low Charge</u>	<u>O.C.</u>
11 thru 13	Rate-Amps	1-4	60	0	40	5	0
	Voltage Limit	1-4	1.7	-	2.5	-	-
	Time in Mode-Hrs	1-4	2.4	1.05	2.9	8.6	1.05
14 and 15	Rate-Amps	1-4	60	0	40	5	0
	Voltage Limit	1-4	1.7	-	2.5	-	-
	Time in Mode-Hrs	1-4	2.4	1.05	2.6	8.6	1.05
16 thru 19	Rate-Amps	1-4	60	0	40	5.5	0
	Voltage Limit	1-4	1.7	-	2.5	-	-
	Time in Mode-Hrs	1-4	2.4	1.05	2.9	8.6	1.05

The charging mode of the original test regime was designed to limit the charge voltage. This prevented all the batteries from being fully charged making an equalizing charge necessary between Cycles 10 and 11.

At Cycle 11, the regime was changed to give the batteries 10 percent overcharge. This also proved inadequate so at Cycle 13 the overcharge was increased to 13 percent.

Between Cycles 19 and 20, the electrolyte specific gravities were adjusted.

The life cycle test regime after Cycle No. 19 is as follows:

<u>Cycle</u>	<u>Mode</u>	<u>Loops</u>	<u>Dischg</u>	<u>O.C.</u>	<u>High Charge</u>	<u>Low Charge</u>	<u>O.C.</u>
20 to 23	Rate-Amps	1-4	60	0	40	5.5	0
	Voltage Limit	1-4	1.7	-	2.5	-	-
	Time in Mode-Hrs	1-4	2.4	1.05	2.9	8.6	1.05
24 to 29	Rate-Amps	1-2	60	-	40	5.5	0
	Rate-Amps	3-4	60	-	40	5.9	0
	Voltage Limit	1-4	1.7	-	2.5	-	-
	Time in Mode-Hrs	1-4	2.4	1.05	2.9	8.6	1.05
30 to 31	Rate-Amps	1	55*	0	40	5.5	0
	Rate-Amps	2	57*	0	40	5.5	0
	Rate-Amps	3-4	60	0	40	5.9	0
	Voltage Limit	1-4	1.7	-	2.5	-	-
	Time in Mode-Hrs	1-4	2.4	1.05	2.9	8.6	1.05

*1.15 Hrs at 60 A discharge completed at new rate.

32 to 37	Rate-Amps	1	55	0	36.4+	5.4	0
	Rate-Amps	2	57	0	37.7+	5.7	0
	Rate-Amps	3-4	60	0	40	5.9	0
	Voltage Limit	1-4	1.7	-	2.5	-	-
	Time in Mode-Hrs	1-4	2.4	1.05	2.9	8.6	1.05

+2.4 Hrs. chg. at 40A, chg. completed at new rate. This regime should overcharge by 15 percent.

The discharge rates vary because they are the three-hour rates for their respective loops.

<u>Cycle</u>	<u>Mode</u>	<u>Loops</u>	<u>Dischg</u>	<u>O.C.</u>	<u>High Charge</u>	<u>Low Charge</u>	<u>O.C.</u>
38 to 41	Rate-Amps	1	55	0	36.4	5.4	0
	Rate-Amps	2	57	0	37.7	5.7	0
	Rate-Amps	3-4	58 ^x	0	40.0	5.9	0
	Voltage Limit	1-4	1.7	-	2.5	-	-
	Time in Mode-Hrs	1-4	2.4	1.05	2.9	8.6	1.05

^x1.75 hrs at 60 A discharge completed at new rate.

42 Low Charge Time Changed to 20 hrs to equalize batteries.

43 to 51	Rate-Amps	1	55	0	36.4	5.4	0
	Rate-Amps	2	57	0	37.7	5.7	0
	Rate-Amps	3-4	58	0	38.3**	5.7	0
	Voltage Limit	1-4	2.4	-	2.5	-	-
	Time in Mode-Hrs	1-4	2.4	1.05	2.9	8.6	1.05

** .53 hrs at 40 A charge completed at new rate.

52 to 71	Rate-Amps	1	55	0	36.4	5.4	0
	Rate-Amps	2	57	0	37.7	5.7	0
	Rate-Amps	3-4	58	0	38.3	5.7	0
	Voltage Limit	1-4	1.7	-	2.5	-	-
	Time in Mode-Hrs	1-4	2.4	1.09	2.9	8.6	1.05

Notes: On Charge Cycle 57, no data was provided on the teletype printer.

On Charge Cycle 65, the total AH were increased on each loop to 195 percent of the previous discharge capacity. Each loop's AH charge is shown below:

Loop 1 267 AH
Loop 2 269 AH

Loop 3 271 AH
Loop 4 271 AH

The test regime from Cycle 72 to 91 is as follows except where noted:

Rate-Amps	1	55	0	36.4	5.4	0
Rate-Amps	2	57	0	37.7	5.7	0
Rate-Amps	3-4	58	0	38.3	5.7	0
Voltage Limit	1-4	1.7	-	2.5	-	-
Time Hrs.	1-4	2.4	1.09	2.9	8.6	1.05

For Cycles 75 and 81, the total ampere-hours of charge was increased from 152 AH for some batteries to bring them to full charge. they are listed below:

Loop	Battery Position No.	Battery Serial No.	Total AH Cycle	
			75	81
1	3	015	202	182
1	4	020	202	182
1	7	038	202	182
1	8	044	202	182
2	12	068	208	162
2	16	093	208	182
3	19	017	260	216
3	20	023	260	216
4	31	089	226	176

1.1.8 Present Status

Lot 1A has finished its characteristics testing and will be put on life-cycle testing.

Lot 2 continues on life-cycle testing and is being evaluated for short life batteries.

Lots 1B and 3 continue on characteristics testing which will be followed by life-cycle testing.

1.1.9 Preliminary Evaluation of Results and Tentative Conclusions

The 32 configurations were designed to find the interdependence of the various battery components. They are as follows:

- o Four positive plates: 1 pasted with a standard positive paste gray oxide.
 - 1 pasted with a mixture of red leady oxide with special additive.
 - 2 pasted with gray oxide with 2 levels of special additive.
- o Two separators - 1 microporous rubber and 1 microporous plastic.
- o Two electrolyte gravities - 1.285 and 1.315.
- o Two element construction - outside negative plates (12 negatives and 11 positives) and outside positive plates (12 positives and 11 negatives).
- o Characteristics

Following characteristics cycle 2, (60 ampere discharge (3-hr rate) @ 25°C), an analysis was made of the data. The batteries which produced 38 WH/Kg (95% of the 40 WH/Kg goal) or more was tabulated and shown on Table 29.

Nine of the design variable batteries (or 28%) exhibited performance of 38 AH/Kg or more at the 3-hour rate and 25°C.

The construction variables of the 9 highest performance batteries are listed below:

<u>EBS No.</u>	<u>Pos. Plate</u>	<u>% GOX</u>	<u>% RL</u>	<u>% HUP</u>	<u>Outside Plate</u>	<u>Sep.</u>	<u>Sp.Gr.</u>
5727	FP-P3	100	-	1/2	Pos	Plastic	1.285
5730	FP-P4	100	-	1/4	Neg	Plastic	1.285
5764	FP-P2	90	10	1/2	Neg	Plastic	1.315
5765	FP-P2	90	10	1/2	Pos	Plastic	1.315
5768	FP-P3	100	-	1/2	Neg	Plastic	1.315
5769	FP-P3	100	-	1/2	Pos	Plastic	1.315
5771	FP-P4	100	-	1/4	Pos	Rubber	1.315
5772	FP-P4	100	-	1/4	Neg	Plastic	1.315
5773	FP-P4	100	-	1/4	Pos	Plastic	1.315

The highest performance of the 9 designs at Cycle 2 was from EBS 5764, EBS 5768 and EBS 5771 all gave 40.4 WH/Kg. The best at Cycle 12 - 40 A at 40°C - was from EBS 5764 at 47.0 WH/Kg.

1.1.10 Work Programmed for the Next Year

Finish characteristics testing of Lots 1B and 3 and start life-cycle testing.

Put Lot 1A on life-cycle testing.

Evaluate the characteristics and life-cycle data to aid in the FP-2 design.

TABLE 29

PRELIMINARY EVALUATION OF ISOA BATTERY PERFORMANCE
WATT HOURS PER KILOGRAM

WAIT HOURS PER KILOGRAM													
Temp	25	25	25	25	25	0	0	0	0	0	40	40	
Rate amps	60	75	140	10	240	40	60	75	140	240	40	60	
Cycle	2	3	4	5	6	7	8	9	10	11	12	13	
EBS #	5727												
Ser. # Lot #	069	37.5	35.0	28.8	52.2	24.6	34.2	29.3	26.9	19.4	16.4	43.7	
Ser. # Lot #	067	39.0	36.0	29.3	44.0	24.9	34.8	31.5	24.5	19.6	ΔΔ	ΔΔ	
EBS #	5771*												
Ser. # Lot #	082	40.4	32.8	27.0	42.5	22.3	30.8	27.6	22.0	17.6	11.7	41.8	
Ser. # Lot #	084	35.2	32.9	27.2	42.8	22.6	31.3	28.4	22.3	17.8	12.0	42.2	
EBS #	57730*												
Ser. # Lot #	087	39.1	32.6	27.2	41.8	22.7	32.5	29.2	25.1	20.2	14.1	41.8	
Ser. # Lot #	086	34.4	31.7	26.0	42.7	21.8	31.8	28.6	25.7	20.8	15.2	41.4	
EBS #	5772*												
Ser. # Lot #	088	40.2	34.6	28.3	43.3	23.7	30.3	26.0	18.5	14.1	9.9	44.1	
Ser. # Lot #	090	36.9	33.9	28.0	42.5	24.4	32.6	28.7	19.3	13.5	8.0	42.0	
EBS #	5773*												
Ser. # Lot #	094	39.5	36.0	29.5	42.3	24.7	30.1	25.7	17.8	14.0	10.1	44.7	
Ser. # Lot #	095	38.1	33.8	27.2	42.4	23.2	27.4	24.5	19.6	15.4	11.0	42.2	
EBS #	5764												
Ser. # Lot #	040	36.1	33.5	27.4	52.5	23.6	33.2	29.1	26.9	20.7	16.6	42.7	
Ser. # Lot #	042	40.4	37.5	31.0	45.9	26.2	34.0	29.9	20.9	16.1	13.6	47.0	
EBS #	5765												
Ser. # Lot #	046	35.8	33.7	27.6	54.1	24.4	33.5	28.7	26.4	19.9	16.2	44.0	
Ser. # Lot #	048	39.4	36.5	30.0	43.9	25.3	30.8	26.7	19.3	14.9	12.8	45.9	
EBS #	5768												
Ser. # Lot #	064	Δ	33.0	28.0	49.6	23.7	36.4	29.0	26.3	20.3	16.3	43.7	
Ser. # Lot #	066	40.4	37.4	30.5	44.7	25.8	Δ	Δ	22.6	17.6	12.4	46.0	
EBS #	5769												
Ser. # Lot #	070	Δ	33.3	28.2	50.5	23.9	35.7	27.6	25.2	19.2	15.5	44.3	
Ser. # Lot #	072	40.0	36.4	29.2	44.6	24.6	30.9	27.8	20.1	15.9	11.2	Δ	
Δ No Data Available													
ΔΔ EBS 5727/067 Irreparably damaged													

1.1.11 Overview of Work with Respect to ISOA Goals

To date, some batteries have achieved ISOA goals except for the cycle life, and testing is in progress.

1.2 FP-2 Experiment

A subcontract to Battelle Columbus Laboratories for a grid design study was approved by ANL on 4 May 1978.

The work completed by Battelle is described in their Phase A Report ANL Contract 31-109-38-4207-ESB-2, a copy of which is available on request from ANL. Address requests to Dr. N. P. Yao, Office for Electrochemical Project Management, Bldg. No. 205, Argonne National Laboratories, 9700 South Cass Avenue, Argonne, Illinois 60439.

1.2.1 Work Performed Since Last Annual Report

1.2.1.1 Battelle Phase A Study

A. The Battelle Phase A program was to develop computer modelling techniques for the optimization of grid designs.

A mathematical modelling technique was designed for lead-acid battery grids and plates. The modelling effect was focused on improving the grid designs, to improve conductivity of the grids and to minimize grid weight.

Several modifications of grid design were considered, including conductor lug location and discontinuities of grid bars at the top-center of positive plates to change the current flow.

Criteria investigated were voltage drop at the conductor lug and current density over the plate. More uniform current density distribution was associated with better active material utilization, hence longer life. Lower voltage drops were associated with better specific energy and power densities when considered in conjunction with better active material utilization.

Two grids were designed, an orthogonal and a radial concept. Battelle's conclusions are that cell voltage loss can be lowered by at least 0.05 and 0.08 volts, and the current density variability distribution halved.

B. Preliminary recommendations are as follows:

- o The program describing radial and expanded metal grid designs should be completed.
- o The orthogonal model should be optimized by an iterative program in which grid conductivities will be related to the calculated grid current.
- o The models developed should be used to study the significance of varying plate lengths to width ratios.

C. Status

Battelle is preparing a grid mold in accordance with the computer design, to cast grids for laboratory evaluation and confirmation of the design.

1.2.1.2 Separator Studies

Plastic separators from Japan, of several configurations recently became available for testing in the U.S. A test lot of synthetic pulp plastic-impregnated separators was obtained domestically for test.

Eleven batteries were built to test the new types of separators as well as some standard plastic separators. They were built with over-the-partitions welds so only one variable was present. They were manually tested for 7 discharge cycles. The data gathered is shown in Table 30.

They were then delivered to the testing laboratory for life cycle testing and have reached 21 cycles.

Their test regime is as follows:

<u>Dischg</u>	<u>Time</u>	<u>O.C.</u>	<u>Chg.</u>	<u>Time</u>	<u>Chg.</u>	<u>Time</u>	<u>O.C.</u>
48A	2.4 hrs	1.09 hrs	31.8 A	2.9 hrs	5.6 A	8.6 hrs	1.05 hrs

The data gathered from the life cycle test are shown in Appendix No. 2.

The types of separators in the batteries are listed below:

Manufacture A-1, Batt 9A envelopes - Negative Plate
Manufacture A-1, Batt 9B envelopes - Positive Plate

Manufacture A-2, Batt 10A envelopes - Negative Plate
Manufacture A-2, Batt 10B envelopes - Positive Plate

Manufacture A-3, Batt 11A envelopes - Positive Plate
Manufacture A-3, Batt 11B envelopes - Negative Plate

Manufacture B-1, Batt 12 envelopes - Negative Plate
Manufacture B-2, Batt 13 envelopes - Negative Plate
Manufacture B-1, Batt 14 envelopes - Positive Plate
Manufacture B-2, Batt 15 envelopes - Positive Plate

Manufacture C, Batt 16 envelopes - Negative Plate.

It is too early in the test regime to draw any conclusions.

TABLE 30
FP-2 SEPARATOR TEST

		BATTERY NUMBER										
		9A	9B	10A	10B	11A	11B	12	13	14	15	16
Plate Enveloped		Neg.	Pos.	Neg.	Pos.	Pos.	Neg.	Neg.	Neg.	Pos.	Pos.	Neg.
Separator Thick- ness (mm)		0.8	0.8	0.8	0.8	1.3	1.3	1.02	1.3	1.02	1.3	1.3
Cycle	Rate Amps	CAPACITY IN AMPERE HOURS TO 1.75 VPC (Volts per Cell) 25 to 37°C										
1	10	172.6	183.3	175.4	173.6	181.1	181.6	180.4	174.7	182.9	179.4	180.5
2	40	140.7	142.7	140.7	142.0	147.5	146.8	146.8	151.9	155.3	152.1	156.1
3	60	136.0	136.3	137.3	136.8	136.9	138.9	138.9	145.4	146.6	142.6	151.6
4	75	143.0	147.2	150.2	146.9	136.8	146.6	144.8	145.6	144.6	138.8	149.4
5	140	113.2	117.6	118.8	122.0	112.2	118.2	114.9	116.5	114.3	109.4	115.1
6	10	230.9	236.7	234.6	235.8	229.0	229.2	235.7	234.8	239.0	234.0	234.3
7	75	153.2	157.5	149.0	157.2	153.4	150.0	150.7	165.0	157.3	160.4	167.3

1.2.2 Work Programmed for Next Year

A. Battelle Subcontract

Complete fabrication of the grid mold which will provide grids in accordance with the computer design.

Cast grids and evaluate in the laboratory to provide data for comparison of the new grid design versus the present day orthogonal grid design.

Submit Final Report of all work, findings, conclusions and recommendations.

B. EXIDE Management & Technology Co.

Analyze separator test data and select most promising for use in the assembly of the FP-2 batteries.

Procure necessary positive and negative molds for the plates of the FP-2 batteries.

Prepare Experimental Battery Specifications for the assembly of batteries to be tested under the FP-2 factorial experiment.

Assemble and start testing of batteries as required.

1.3 TP-1 History

Deep cycle service has proven the superiority of tubular positive plates. Standard tubing configurations are 8mm square or round. Power requirements of the ISOA program dictate a rectangular tube shape rather than square or round. Through innovative filling techniques and corrosion resistant alloys for the grid, we expect to develop a positive plate capable of meeting the peak load requirements while maintaining the deep cycle capabilities of this design.

Thirty-two battery configurations were designed for the TP-1 experiment. They are:

- o Four positive plates
- o Two separators
- o Two electrolyte specific gravities
- o Two acid volumes above the plates.

1.3.1 Work Performed Since Last Annual Report

Thirty-two Experimental Battery Specifications (EBS 5809 to 5840) were prepared.

Two types of braided glass tubing was manufactured by our supplier. A "standard" braid as is used in industrial battery application and a lighter braid made with fewer strands of glass than the standard. In order to improve the diffusion on electrolyte to the active material.

The "standard" tubes were shaped and set with phenolic resin and given two post-shaping applications of phenolic resin. The lighter tubes were only shaped and set with no additional phenolic applications. See Photograph No. 1 "CLADEx Tubing."

A production injection grid mold was designed and grids were cast in 9 percent SbPb alloy at ESB's Sumter, S. C. factory. See Photograph No. 2 "TP-1 Positive Spine, Bottom Bar and Plate."

Bottom bars were molded in four colors to identify the four types of positive plates. See Photograph No. 2.

The above components and Pb_3O_4 were sent to ESB's facility in Trenton, N. J. Two methods of filling the positive plates with Pb_3O_4 were tried; one was successful. About 1,250 of each of the positive plates were filled. The plate part numbers and their characteristics are shown below:

<u>Pt. No.</u>	<u>Tube</u>	<u>A.M. Fill Wt. Gms.</u>	<u>Bottom Bar Color</u>
85617	Standard	210-220	Black
85195	Light	210-220	Natural (White)
85618	Standard	240-250	Beige
85616	Light	240-250	Red

Two 1.0mm (.040") thick separators were selected; one was ribbed microporous rubber and the other ribbed microporous polyethylene envelopes. See Photograph No. 3 "TP-1 Rubber Ribbed Separator."

The envelopes were made by thermo-welding a sheet approximately 343mm long by 168mm wide to 171mm by 168mm. See Photograph No. 4 "TP-1 Plastic Ribbed Envelope and Ribbed Sheet."

The two electrolyte gravities were 1.285 and 1.315.

In one set of cells, the acid volume above the plates is standard. In the other set, acid volume is higher than standard. This was achieved by reducing the height of the sediment ribs in the bottom of the container from about 16mm to 6.3mm. See Photograph No. 5 "TP-1 Containers - Standard and Low Sediment Ribs."

4mm X 14mm
LIGHT WEIGHT
CLADEX
TUBING

4mm X 14mm
STANDARD
CLADEX
TUBING

8mm SQUARE
CLADEX
TUBING

Photo #1 - CLADEX Tubing (70-2)

TP-1 POSITIVE SPINE

TP-1 POSITIVE PLATE

TP-1 BOTTOM BAR

Photo #2 - Positive Spine, Bottom Bar & Plate (70-3)

TP-1 RUBBER RIBBED SEPARATOR

Photo #3 - TP-1 Rubber Ribbed Separator (71-2)

TP-1 PLASTIC RIBBED ENVELOPE

TP-1 PLASTIC RIBBED SHEET
BEFORE HEAT SEALING INTO
AN ENVELOPE

Photo #4 - TP-1 Plastic Ribbed Envelope & Ribbed Sheet (71-3)

Photo #5 - TP-1 Containers - Standard & Low Sediment Ribs (71-4)

The TP-1 negative grid is the same as the FP-1 except for conductor lug location. The grid mold is inserted and can be used to produce both types of negative grids. See Photograph No. 6 "TP-1 and FP-1 Negative Grids."

The TP-1 battery has 3 cells each of which consists of 21 plates; 10 positives and 11 negatives.

All of the plates that went into the TP-1 batteries were weighted in groups of 10 positives and 11 negatives and the weights recorded.

The plates and separators (or envelopes) were assembled into elements. The positive and negative plates were welded into their respective groups in the cast-on-strap (COS) machine. As the elements were removed from COS machine, they were put into containers and their EBS numbers were stamped on the negative strap. As this was done, the weights of the groups and their assigned EBS and serial numbers were recorded. The battery containers were also labeled with the EBS and serial number.

The elements were then resistance welded through a hole in the intercell partition of the container. In the industry, it is called through-the-partition construction and is abbreviated TTP. After welding, each weld was given a millivolt drop test at 200 amperes in order to check weld quality. The resistance values averaged less than 2 micro ohms.

The lists of the positive and negative group weights, EBS numbers and serial numbers and millivolt drop are shown in Appendix 2.

Four batteries were built per each EBS for a total of 128 batteries. They were assigned Lot numbers 4 through 7.

Lot 6 was formed first and is scheduled to be put directly on life-cycle testing. Battery EBS 5823/155 of Lot 6 was damaged and was replaced with Battery EBS 5823/156.

Lot 4 will be formed next and put on characteristics testing when FP-1 Lot 3 has completed its characteristics regime.

Lot 5 will follow Lot 4 with Lot 7 held in reserve.

1.3.2 Work Programmed for Next Year

Test TP-1 batteries for life-cycle and characteristics. Evaluate the data and present conclusions.

1.4 Advanced Lead Acid Battery

1.4.1 Negative

An important approach taken to improve the energy density of the lead-acid battery has focused on reducing the weight of the negative grid. In the advanced lead-acid designs now considered, a 100 percent lead negative grid accounts for 11-12 percent of the total battery weight. By substituting lightweight materials such as plastic or copper, a savings of 50 to 75 percent in the grid weight is anticipated. This corresponds to a 6-9 percent reduction in the overall battery weight with no loss in the delivered energy.

Photo #6 - TP-1 and FP-1 Negative Grids (72-2)

TP-1 NEGATIVE GRID (1.5mm)
WITH IN-LINE LUG

FP-1 NEGATIVE GRID (1.5mm)
WITH OFF-SET LUG

The negative grid has a two-fold function: (1) it is conductive and carries electrons to and from the active material involved in the electrochemical reaction, (2) it acts as a rigid matrix to hold the negative active material, and to allow handling and assembly of the negative plate. In 100 percent lead grids, both functions are served by the lead, a material which does not have an exceptionally good conductivity and has a high material density. The major advantage of lead grids is that they are easy to fabricate. The rationale taken in developing a lightweight alternative has been to use plastic as the matrix material for grid rigidity, copper as the electronic conductor, and a thin coating of lead on the copper to render it electrochemically inert. Per unit volume, plastic has less than 10 percent the weight of lead so that an all plastic grid designed to contain the same amount of negative active material as a standard lead grid is 1/10 as heavy. From the data in Table 31, it can also be shown that for a given grid geometry, copper is nearly 16 times as conductive as lead. Therefore, a grid design which incorporates copper as the primary conductor can offer a substantial weight reduction. Exposed copper would, however, reduce the hydrogen overvoltage and present problems during charge. To eliminate this from happening, a thin (.025 to .050 mm) coating of lead on the copper is needed.

TABLE 31

Properties of Grid Materials^(1,2)

	<u>Density (g/cm³)</u>	<u>Resistivity (microhm cm)</u>
ABS Plastic	1.08	∞
Copper	8.92	1.77
Lead	11.37	22

A simple calculation was made to determine the relative weights of a standard lead grid and a copper, plastic, lead composite grid with identical geometry (volume) and conductivity. The standard grid was 1.47 mm thick. The composite was also 1.47 mm - 1.34 mm plastic with a .04 mm copper, and .0250 mm lead coatings. If the weight of the lead grid is arbitrarily assigned a value X, and its resistivity is assigned a value Y, the composite has a weight 0.277X and a resistivity 0.8Y. The composite weighs less than 25 percent of the lead grid yet is more conductive. In the composite, plastic comprises 35 percent, copper 35.6 percent, and lead 29.4 percent of the total grid weight. Two different types of composite lightweight grid constructions were built and tested in batteries. Both types incorporated the rationale developed above.

1.4.1.1 Lightweight Negative Grid - Type A

An automotive grid mold was available for molding plastic grids, and several hundred ABS grids were made. Although the automotive grid size (14.5 cm X 12.3 cm X 0.14 cm) is considerably smaller than the one proposed for the EV battery (15.8 cm X 15.4 cm X 0.14 cm), use of these plastic grids permitted us to quickly arrive at some preliminary conclusions regarding the behavior of lightweight negative composite grids in a lead acid battery.

The ABS plastic grids (wt = 5 gms) had a thin layer (wt = 0.6 gms) of electroless copper applied by conventional techniques. First, a chromic acid etch, followed by stannous chloride sensitization, and palladium chloride catalyzation, and then they were placed into the electroless plating bath. The amount of copper deposited by the electroless process was not sufficient to provide adequate grid conductivity, so additional copper (2.5 g/grid) was applied by conventional electroplating techniques from a copper sulfate bath. The electroless deposit therefore only serves as a substrate for electroplating copper on an otherwise non-conductive plastic grid. Lead plating from a lead fluoboric bath followed (5 g/grid), generally after attaching the lead lug to be used later in paralleling the plates into the negative group. Plating thicknesses for the cells reported 0.05 to 0.075 mm of copper and 0.075 to 0.125 mm of lead. Composite negative grids with lead lugs attached weighed 20-25 gms compared to 47 gms for the cast lead control. Figure 1 is a photograph of the plastic grid, the plated grid with attached lug, and the control.

A paste containing 100 percent GOX was made and applied to the lightweight grids using standard techniques. Seven-plate cells were constructed with outside positives and were placed in automotive size containers. Acid gravity after formation was adjusted to 1.280.

A milliohmmeter was used to check the resistances of the composite grids and that of a lead control. One set of milliohmmeter probes was placed on the grid lug and the other set on the bottom of the grid frame diagonally opposite to the lug. Both the resistances of the lightweight composite and the control were between 3 and 4 milliohms. We, therefore, felt certain that sufficient conductivity was built into the grid with the plated copper as a conductor so that the cell performance would equal the control.

In Figure 2, discharge curves for cells with both the plated lightweight grid and a cast lead control are shown. The current density at the 15 ampere rate on automotive size plates corresponds to a 75 ampere discharge for the conventional EV 106 battery. No significant differences were observed in either closed circuit voltage or utilization of active material at any of the rates tested (9, 12, or 15 amps).

ABS Plastic Grid
Wgt. 5 gm.

ABS Plastic Grid
Plated with Lug Attached
Wgt. 26 gm

Cast Lead Grid
Wgt. 47 gm

LIGHTWEIGHT COMPOSITE
NEGATIVE GRID - TYPE A

FIGURE 1

DISCHARGE BEHAVIOR OF LIGHTWEIGHT NEGATIVE GRIDS - TYPE A

FIGURE 2

The technique for reliably attaching the current collecting lug to the plastic is a major obstacle in the development of the lightweight negative grid - Type A. Two methods were tried: (1) the lugs were copper plated, dipped in solder flux, dipped in molten tin, and then in molten lead. Although a cell was built using conventional burning techniques, this method does not appear suitable for production, (2) another method was to mechanically attach lead straps and then solder through the molded hole in the lug of the plastic grid. A photograph of this lug configuration is shown in Figure 1. This method also has several drawbacks and only appears suitable for laboratory cell assembly.

A 6-cell battery (105-9) with seven plate elements containing lightweight negatives - Type A was designed and constructed. The cells were made negative limiting and contained 64 Ahrs of formed active material in the negative group. The battery was placed on extended life testing to determine if the copper plated plastic negative significantly deteriorates with cycling. Over the first 25 cycles, load voltages and cell capacities were normal. However, subsequent cycling indicated a gradual but continuous decay in performance. After initially holding steady at 30 Ahr, cell capacity dropped over 25 percent to 22 Ahr (Figure 3). Reference readings and a post mortem of one cell in the 6-cell battery clearly showed that the drop in capacity could not be attributed to deterioration of the negative. Even though the initial ratio of positive active to negative active material was 1.8, the cells became positive limiting. Reference readings showed the negative was -0.23V vs Cd and the positive was 1.86V vs Cd at the end of discharge. The cell post-mortem also revealed massive shedding of the pasted positive automotive plate while the negative remained intact. Average weight loss of negative active material was approximately 6 percent per plate, a loss small enough to be attributed to handling and disassembly.

A 3-plate negative group from Battery 105-9 was rebuilt into Cell N1-3, one of the four cells in Battery N1. Cells N1-5 and N1-6 were controls which contained cast lead negative grids, and Cell N1-4 contained lightweight negative grids - Type B discussed later in the report. All the cells in Battery N1 contained four thin tubular positives (ISOA - TP1 design) cut to automotive plate size dimensions. The ratio of formed positive to negative active material weight was 2.7/1.0 to insure that the cells were negative limiting. All cells in Battery N1 contained the same amount of negative and positive active material.

The negative group in Cell N1-3 has undergone over 240 cycles at 100 percent depth of discharge (60 cycles as part of Battery 105-9 and 180 cycles as part of Battery N1). The cell behavior in Battery N1 as a function of cycle number at a constant 10 ampere discharge is shown in Figure 4. Also shown is the Ahr capacity and efficiency of Cell N1-6, a control. No significant variance in cell performance has been noted indicating that very little deterioration of the Type A lightweight negative grid construction has occurred. The test will continue for 500 cycles, after which, Cell N1-3 will be disassembled and a post-mortem of the negative plates performed.

Cycle Performance of Battery 105-9
(Lightweight Negative Grids - Type A)

FIGURE 3

Cycle Performance of Cell N1-3
(Lightweight Negative Grids - Type A)

FIGURE 4

1.4.1.2 Lightweight Negative Grid - Type B

An experimental lightweight negative grid was made and identified as Type B. The overall grid consists of three sections sandwiched together. The top and bottom sections are inert plastic webs or nets such as Conwed® or Vexar®. The central section is made of a thin (0.5 mm) electroformed copper substrate with a typical grid geometry. The copper is then coated with 0.0375 mm lead to render it electrochemically inert in a lead-acid cell. The purpose of the lead-coated copper section is to provide electrical conductivity only. It is very thin and by itself is not rigid enough to serve as a matrix to retain the negative active material. The active material is primarily retained in the plastic net placed on either side of the metal grid. The configuration of the plastic net is such that each pellet in the net contains a section of metal grid to insure that no region of the active material becomes isolated and inaccessible to electrolyte.

The Type B lightweight grid has an overall thickness of 1.4-1.52 mm. Lamination of the grid is accomplished by placing the plastic nets on either side of the lead coated copper and ultrasonically bonding the plastic nets to each other through the holes in the metal portion of the grid. Ultrasonic is the preferred technique for bonding the plastic since it minimizes distortion of the lead while melting the plastic to the point where a tack weld is created.

Table 32 summarizes some of the physical parameters of the Type B lightweight negative grids.

TABLE 32

Lightweight Negatiaves - Type B

	<u>Thickness</u>	<u>Wt</u>	<u>Comments</u>
	(mm)	(g)	
Copper	.05	4.5	
Lead	.04	10.6	Plated on both sides of copper
Plastic Net	0.94	8.3	Thickness before pressing, Conwed® 5 x 7 strands to the inch
Overall	1.44	23.4	Thickness after assembly

A purchase order was issued to the Inco Research and Development Center (IRDC) to electroform the copper grids. A photograph of the grid is shown in Figure 5. Initial attempts at electroforming focused on an automotive grid geometry (14.5 cm X 12.3 cm) and it is this type of grid which was experimentally evaluated. The electroforming process was successfully applied to making the automotive grid and future work will involve a scale-up to the EV size. A milliohm meter was used to check the resistance of the Type B grid. One set of probes was placed on the grid lug and the other set on the bottom of the grid frame diagonally opposite to the lug. The resistance was 2.5 milliohms, nearly 15 percent less than the control. Figure 6 shows the final composite grid, included are the metal central section which carries current and the plastic net to retain the negative active material.

A paste containing 100 percent GOX was made and applied to grids of this type using standard techniques. A 7-plate cell (N1-4) was constructed with outside positives, and acid gravity after formation was adjusted to 1.280. The negative group contained 64 Ahr of formed active material. The positive group consisted of thin tubular plates (ISOA - TP-1 design) cut to automotive size dimensions, and the ratio of formed positive to negative active material weight was 2.7/1.0 making it a negative limiting cell. A photograph of a typical pasted negative is shown in Figure 7.

The major advantages of the Type B construction over the Type A are (1) electroless plating does not have to be used, and (2) the lug is metallic (copper coated with lead) rather than plastic and poses no problems for assembling the negative group using standard burning techniques. The major drawback of the Type B grid is the need to adapt the new and unique operations that go into making it from a laboratory curiosity into a feasible production process.

After assembly into Cell N1-4 in Battery N1, the Type B lightweight grids were placed on automatic cycling. N1-4 cycled at 100 percent depth of discharge at a current of 10 amperes (9.3 ma/cm^2). The behavior of N1-4 as a function of cycle number is shown in Figure 8. After holding steady for the first 30 cycles, its performance began to deteriorate. Between Cycles 30 and 70, the capacity dropped linearly from 24 to 18 Ahrs. The capacity drop was accompanied by a low negative charge voltage, -0.04V vs Cd compared to -0.20V for the controls. After 7- cycles, the test run was terminated and a post-mortem of the cell performed. Reddish discolorations were observed on the surface of the negative active material and the presence of copper was confirmed using the scanning electron microscope. Figure 9A is a photograph of the area in question magnified 150X. Region A corresponds to the reddish discolored surface, and Region B is the normal plate surface. Figure 9B is a scanning electron micrograph of Region A (1500X) and Figure 9C is an SEM of Region B (1500X). The differences in surface morphology are obvious indicating that Region A is atypical of the negative plate. Energy dispersion X-ray (EDX) of Region A shows it to be primarily copper with some lead (Figure 9D) whereas EDX of Region B indicates lead (Figure 9E). A copper map was made of the areas in question, and Figure 9F clearly shows where copper is present (indicated by white dots).

ELECTROFORMED COPPER GRID,
LEAD PLATED, TYPE B LIGHTWEIGHT
NEGATIVE GRID CONSTRUCTION

FIGURE 5

METAL PLASTIC COMPOSITE
TYPE B
LIGHTWEIGHT NEGATIVE GRID
CONSTRUCTION

FIGURE 6

PASTED PLATE - TYPE B
LIGHTWEIGHT NEGATIVE GRID
CONSTRUCTION

FIGURE 7

CYCLE PERFORMANCE OF CELL N1-4
(LIGHTWEIGHT NEGATIVE GRIDS - TYPE B)

FIGURE 8

FIGURE 9A: Post Mortem Cell N1-4, Surface of Negative Plate 150X

FIGURE 9B: Surface of Negative Plate, Region A 1500X

FIGURE 9C: Surface of Negative Plate, Region B 1500X

FIGURE 9D: EDX of Region A on Negative Plate Surface

FIGURE 9E: EDX of Region B on Negative Plate Surface

FIGURE 9F: Copper Map of Negative Plate Surface

Apparently, the copper deposit reduced the hydrogen over-voltage⁽³⁾ at the negative and prevented complete charging of the negative active material. In a conventional cell design which is positive limiting, copper dissolution from the grid and subsequent deposition on the plate during charge would never be expected to occur (cf Table 33).

TABLE 33
TYPICAL ELECTRODE VOLTAGES VS CADMIUM

Positive Electrode, cell fully charged	2.5V
Positive Electrode, cell fully discharged, cell negative limiting	2.1V
Positive Electrode, cell fully discharged, cell positive limiting	1.9V
Copper dissolution at negative	0.7V
Negative Electrode, cell fully discharged, cell negative limiting	0.4V
Negative Electrode, cell fully discharged, cell positive limiting	0.2V
Negative Electrode, cell fully charged, with copper poisoning	-0.05V
Negative Electrode, cell fully charged - no copper present	-0.20V

However, Cell N1-4 was (1) made negative limiting in order to determine the effect of lightweight negative grids on the negative active material utilization, and (2) it was the limiting cell in a series of four, and conceivably the negative potential could have dropped to the point where copper dissolution occurred (+0.72V vs. Cd). Other than the copper deposition on the plate surface, the post-mortem revealed no abnormalities in the negatives containing the Type B lightweight grid construction, and further work with these grids appears warranted.

1.4.2 Positive

In terms of development, the positive electrode is the single most important part of the advanced lead-acid battery. As presently envisioned, it comprises 40 percent of the total battery weight (the positive grid 15 percent and the positive active material 25 percent). Three different types of positive electrodes were investigated - tubular, composite, and pasted flat plate. Unfortunately, no one electrode is categorically superior to the rest; each has associated with it, both advantages and disadvantages.

1.4.2.1 Tubular Electrode

The major advantage of the tubular electrode design is that it makes for a long life positive. By encapsulating the positive active material in a porous phenolic impregnated woven glass fiber tube, shedding is retarded and the rate of positive grid corrosion minimized. Earlier work⁽⁴⁾ showed that the preferred oxides for filling the tubes are 2 to 4 microns in diameter, and consist of either GOX (nominally 70 percent PbO and 30 percent finely divided lead) or Red Lead (nominally 73 percent Pb₃O₄ and 27 percent PbO or Pb). A slight difference in maximum cell capacity and active material utilization was noted when using 100 percent GOX rather than 100 percent Red Lead. GOX is less expensive than Red Lead and is therefore preferred from a cost point of view. However, positives containing 100 percent Red Lead reach full capacity within 1 to 3 cycles whereas those with 100 percent GOX take 10 to 20 cycles - which is unacceptable for most users. A compromise aimed at optimizing oxide cost and the rate of positive active material formation settled on the use of 90 percent GOX and 10 percent Red Lead. After 5 to 6 cycles, use of the positive material reaches a maximum value.

In contrast to flat plates which are pasted with a mixture of oxide, sulfuric acid, and water, tubular positive plates have generally been filled with dry oxide powder. The powder is introduced in the space between the tube wall and the centrally located lead spine. The process is considerably aided by vibration or shaking which is needed to achieve the required fill density. An optimum fill density exists above which utilization of the active material is poor, yielding a low energy density, and below which washout occurs and plate life is short. The optimum density should ideally result in a tubular electrode which combines long life and good utilization. In this advanced work, two fill densities were investigated. These values were lower than normal, however, the ISOA-TP-1 study investigates tubular electrodes with higher pack densities and additional experiments at this higher level would have been redundant. Furthermore, the primary focus of the advanced battery program has been to review any means possible for maximizing the utilization of the active material. Lower fill densities should be a step in this direction since accessibility of the positive active material to the electrolyte is improved and the reaction step:

is less likely to be rate limiting.

The tubular grid used in this study was the same as the one designed for the ISOA-TP-1 battery. Typical grid dimensions are listed in Table 34. Each tube contains two lead spines. A photograph of the grid and tubes is shown in Figure 10.

TABLE 34
TUBULAR GRID PARAMETERS

No. of Tubes per Plate	11
Grid Weight - lead only (g)	121.7
Active Spine Length (cm)	15.30
Spine Length (cm)	16.0
Twin Spine Weight per Tube (g)	7.7
Volume of Spine (cc)	0.675
Weight of 11 Tubes + Bottom Bar (g)	18
Inside Tubing Dimensions:	
Avg Width (cm)	1.40
Avg Thickness (cm)	0.32
Cross Section per Tube (cm ₂)	0.45
Volume per Tube for Filling (cc)	(15.3)(.45) - .675 = 6.21
Tube Wall (mm)	0.35
Tube Thickness (cm)	.33
Surface to Volume Ratio (cm ⁻¹)	7.67

After the tubes were filled with oxide, they were "soaked" in sulfuric acid. This step sulfates the active material and binds it together transforming it from a loose packed powder into a rigid matrix. Alternatively, the plates could have been "dipped" in sulfuric but earlier work⁽⁴⁾ indicated that GOX containing plates exhibit somewhat better utilization when "soaked."

Although 22 tubular cells have been designed, built, and tested over the last twelve months, only four (T-18, 19, 21 and 22) will be discussed in detail. They represent the best cells to date with tubular electrodes and contain the improvements and refinements in design which resulted from earlier work.

Table 35 summarizes cell design parameters. Like with all other advanced lead-acid EV cell designs, the only constraint placed on the element configuration was that it must fit into a standard EV-106 container.

THE ISOA TUBULAR GRID

FIGURE 10

TABLE 35

Design Parameters for Cells Containing Tubular Electrodes

A. <u>Positive Electrode</u>	<u>T18</u>	<u>T19</u>	<u>T21</u>	<u>T22</u>
1. Type of Oxide	A	B	C	D
2. Positive Plate				
a) Grid Type	TP-1	TP-1	TP-1	TP-1
b) Grid Weight (g)	140	140	140	140
c) Weight of Powder Fill (g)	216	205	205	212
d) Weight of Plate (g)	356	345	345	352
e) Weight of Soaked Plate (g)	407	381	385	398
f) Formed Active Material (g)	235	214	220	230
g) Theoretical Ahrs	53.6	48.0	49.4	51.8
h) Cured Thickness (mm)	4.52	4.32	4.32	4.25
3. Positive Group				
a) Number of Plates	9	9	10	11
b) Weight of Formed Active Material (g)	2115	1926	2200	2540
c) Weight of Group Formed (kg)	3.69	3.50	3.93	4.38
d) Theoretical Ahrs	473	432	494	570
B. <u>Negative Electrode</u>				
1. Type of Oxide		100%	GOX	
2. Negative Plate				
a) Grid Type	1GW	1GW	2GW	2GW
b) Grid Weight (g)	105	105	95	95
c) Paste per Plate (g)	190	190	152	185

TABLE 35 (continued)

B. <u>Negative Electrode</u>	<u>T18</u>	<u>T19</u>	<u>T21</u>	<u>T22</u>
2. Negative Plate				
d) Dry Active Material per Plate (DAM)(g)	180	180	144	175
e) Formed Active Material per Plate (FAM)(g)	169	169	135	168
f) Theoretical Ahrs	43.8	43.8	35	43.5
g) Cured Thickness (mm)	2.16	2.16	1.98	2.10
3. Negative Group				
a) Number of Plates	10	10	11	10
b) Weight of FAM (g)	1690	1690	1485	1680
c) Weight of Group Formed (Kg)	2.94	2.94	2.74	3.00
d) Theoretical Ahrs	438	438	385	435
C. <u>Electrolyte</u>				
1. Sp Gr when Charged	1.30	1.30	1.30	1.30
2. Volume per Cell (cc)	1900	1900	1900	1900
3. Weight per Cell (Kg)	2.47	2.47	2.47	2.47
4. Theoretical Ahrs	264	264	264	264
D. <u>Separators</u>				
1. Type	Dimpled Daramic Envelopes			
2. Thickness Dimple (mm)		0.760		
3. Thickness Backweb (mm)		0.254		
4. Weight per Cell (g)	80	80	85	90
E. <u>Other</u>				
1. Container Weight (g)		240		
2. Cover Weight (g)		80		
3. Total Cell Weight (Kg)	9.50	9.31	9.55	10.28

All of cells in Table 35 are still on test and are performing well. The cycle life characteristics of T18, T19, T21, and T22 are summarized in Tables 36, 37, 38, and 39, respectively. The end of discharge is marked by a 1.5 volt cutoff regardless of the discharge rate. Periodic cadmium reference readings show that throughout the cycle test, all cells have remained positive limiting. In Cells T18 and T19, there was no attempt to optimize the design of the whole cell and there was present excess electrolyte and negative. The cells were primarily built to examine the long life behavior of the positive under deep cycling. In T21 and T22, an attempt was made to design the individual components so as to maximize the energy density of the total cell. Cells T18 and T19 contain 19 plate elements with outside negatives; whereas T21 and T22 contain 21 plate elements with outside negatives positives respectively.

The cycle life behavior of Cells T18, T19, and T21 is shown in Figure 11. The results indicate that tubular positives (T19, T21) filled to lowest density initially exhibit better utilization of the active material. Over the first 40 cycles, to 100 percent depth of discharge, a 2 to 3 percent average improvement occurs. With further cycling, however, the lowest fill density electrodes begin to show some deterioration whereas tubes filled to medium density continue to discharge at a steady rate. After 90 cycles, the active material use for the medium fill density exceeds that of the lowest density. It is therefore recommended that any further work with thin, ISOA type, tubular electrodes be restricted to medium fill densities.

A critical factor influencing the energy density of a cell, is the utilization of the positive active material. A simple way to improve utilization of the tubular electrode for a given oxide powder fill density and discharge rate is to maximize the surface area of the positive group. This reduces the rate of electrochemical reaction per unit surface area (the current density) without altering the diffusion rate of the electrolyte, and in effect, enhances accessibility of the positive active material to sulfate ions needed for discharge. With the plate thickness of the tubular ISOA grid held as a constraint, maximizing the surface area of the positive group means placing as many plates as possible into the EV cell compartment while still retaining positive limitation. This was done in Cell T22. The surface area of a typical thin tubular plate is 500 cm². For an eleven plate group, this corresponds to a current density of 11.8 mA/cm² at a 75 amp discharge. Typical voltage - time traces for T22 at 40, 60, 75 and 140 amps are shown in Figure 12. The results are also summarized below:

Discharge Current	Current Density(mA)	Capacity (Ahrs)	Positive AM Use(%)	Avg. Disch. Voltage	Cell	
					Ahr/ Kg	Whr/ Kg
40	6.26	213	37.2	1.96	20.7	40.6
60	9.40	194	34.0	1.94	18.9	36.7
75	11.80	175	30.7	1.89	17.0	32.1
140	21.94	140	24.6	1.82	13.6	24.8

TABLE 36

Cycle Life Behavior of Cell T18

<u>Cycle No.</u>	<u>Current (Amps)</u>	<u>Time (Min)</u>	<u>Init. Temp (°F)</u>	<u>Init. SP GR</u>	<u>Final SP GR</u>	<u>Capacity (Ahr)</u>	<u>Pos. Eff.* (%)</u>	<u>Neg. Eff. (%)</u>	<u>Acid Eff. (%)</u>	<u>Ahr/Kg</u>
1	60	75	84	1.285	1.215	75	15.9			
4	60	129	92	1.314	1.210	129	34.2			
8	60	162	86	1.325	1.205	162				
18	60	162	92	1.290	1.145	162				
24	60	172	88	1.290	1.155	172	36.4	39.2	65.1	18.1
29	60	171	92	1.310	1.155	171				
36	60	171	90	1.280	1.150	171				
Cell placed on extended cycling in Battery Test Lab.										
46	40	248				165	34.9	37.7	62.5	17.4
56	40	265				177				
66	40	272				182	38.5	41.6	68.9	19.2
76	40	269				180				
86	40	263				175				
96	40	263				175				
106	40	264				176	37.2	40.2	66.7	18.5

*Efficiency

TABLE 37

Cycle Life Behavior of Cell T19

Cycle No.	Current (Amps)	Time (Min)	Init. Temp (°F)	Init. SP GR	Final SP GR	Capacity (Ahr)	Pos. Eff.* (%)	Neg. Eff. (%)	Acid Eff. (%)	Ahr/Kg
1	60	81	85	1.270	1.160	81	18.8			
4	60	122	88	1.270	1.160	122	28.2			
8	60	151	82	1.295	1.165	151	34.9			
18	60	163	88	1.326	1.170	163	37.7	37.2	61.7	17.5
29	60	159	93	1.290	1.140	159				
39	60	161	88	1.312	1.155	161				
	60	154	90	1.304	1.550	164	38.0	37.4	62.1	17.6
63	60	161	90	1.295	1.155	161				
70	60	157	82	1.310	1.160	157	36.3		59.4	
Cell placed on extended cycling in Battery Test Lab										
80	40	245				164	38.0	37.4	62.1	17.6
90	40	243				162				
100	40	234				156				
106	40	232				155	36.1	35.4	58.7	16.6

*Efficiency

TABLE 38

Cycle Life Behavior of Cell T21

Cycle No.	Current (Amps)	Time (Min)	Init. Temp(°F)	Init. SP GR	Final SP GR	Capacity (Ahr)	Pos. Eff.* (%)	Neg. Eff. (%)	Acid Eff. (%)	Ahr/Kg
1	60	147	83	1.316	1.140	147	29.9	38.2		
4	60	164	86	1.285	1.145	164	33.2	42.6		
8	60	190	90	1.130	1.145	190	38.5	49.3		
16	60	191	84	1.320	1.140	191	38.7	49.6	72.3	20.0
26	75	139	86	1.320	1.160	174	35.2	45.2		18.2
32	60	184	88	1.314	1.145	184	37.2	47.8		
39	60	186	90	1.316	1.130	186	37.7	48.3		19.5
46	60	182	92	1.310	1.135	182	36.8			
56	60	175	92	1.310	1.140	175	35.4			
64	60	170	91	1.300	1.150	170	34.4			
66	40	282	85	1.300	1.115	188	38.0			19.7
67	60	174	87	1.302	1.130	174	35.2			18.2
68	75	132	89	1.290	1.145	165	33.4			17.3
70	140	54	84	1.290	1.185	126	25.5			13.2

TABLE 39

Cycle Life Behavior of Cell T22

Cycle No.	Current (Amps)	Time (Min)	Init. Temp(°F)	Init. SP GR	Final SP GR	Capacity (Ahr)	Pos. Eff.* (%)	Neg. Eff. (%)	Acid Eff. (%)	Ahr/ Kg	Whr/ Kg
1	60	100	95	1.260	1.095	100	17.5				
5	60	179	88	1.280	1.130	179	31.4				
8	60	185	86	1.300	1.140	186	32.6	42.7	70.5	18.1	
14	60	201	92	1.320	1.140	201	35.2	46.2	76.1	19.6	38.0
18	40	320	88	1.320	1.115	213	37.3	48.9	80.7	20.7	40.6
19	60	194	89	1.318	1.125	194	34.0	44.6	73.5	18.9	36.7
20	75	144	90	1.300	1.125	175	30.7	40.2		17.0	32.1
22	140	60	86	1.290	1.160	140	24.6	32.2		13.6	24.8

Cycle Life Behavior of Tubular Cells

Cycle No.

FIGURE 11

Voltage-Time Characteristics for Advanced Tubular
Electrode Cell Design (Cell T22)

Cycle	Current	Avg. Voltage
• 18	40A	1.96
Δ 19	60A	1.94
□ 21	75A	1.89
x 22	140A	1.82

FIGURE 12

T22 represents the best tubular plate cell built to date. Even so, the results as shown above are disappointing, particularly at the high discharge rates, and the performance is substantially inferior to that of pasted flat plate cells discussed later in this report. Part of the problem may be caused by the fact that tubular electrodes are nearly 50 percent thicker than flat plate electrodes. The positive active material is not nearly as accessible to the electrolyte even though low fill densities are specified. This is particularly true at the 140 amp discharge rate. A possible solution would be to make the tubular electrodes thinner, thereby increasing the surface area of the group. Manufacturing them, however, becomes a problem and tube dimensions become more difficult to hold. Also, the tube wall becomes a substantial portion of the total electrode thickness and the room left for the positive active material is reduced.

1.4.2.2 Analysis of Single vs Double Spine Tubular Grid

The ISOA thin tubular grid design is based on having two spines per tube. Although a savings in lead can be achieved if only one spine per tube is used, a detrimental effect on positive active material use and overall battery energy density may result. Therefore, a study was made to evaluate the merits of a single vs a double spine grid.

A series of ISOA, TP-1 grids (cf Figure 10) were sectioned into current collectors for 20 single-tube positive electrodes. Ten single-tube collectors with two spines per grid were maintained as controls, and ten single tube collectors were changed by removing one spine and reshaping the top bar to centrally locate the remaining spine. The tubes were filled with 100 percent Red Lead and were soaked in standard density sulfuric acid. Negatives and separators were cut down from GW negatives and microporous rubber separators to a width of 1.6 cm. The elements were assembled in special containers designed to include a reference electrode compartment connected to the main cell compartment through a microporous ceramic plug. The cells contained excess electrolyte. The cells were formed in 1.060 acid. Following formation, conditioning discharges were made to insure performance stability, then five discharges were run at 0.13, 0.35, 0.55, 0.75 and 1.5 amperes. Cell data are summarized in Table. 40.

TABLE 40

Tubular Electrode Spine Study - Positive Electrode Performance

<u>Single Spine Electrode</u>				<u>Twin Spine Electrode</u>			
Amperes	Hrs.* Disch.	Utilization Based on Formed Active Material	(Ahr/Kg) Based on Total Tube	Amperes	Hrs.* Disch.	Utilization Based on Formed Active Mat'l	(Ahr/Kg) Based on Total Tube
0.130	19.1	120	81.2	0.130	20.2	128	77.5
0.35	5.85	98.3	66.9	0.350	6.36	108	65.7
0.55	3.29	87.4	59.1	0.55	3.60	96.5	58.4
0.75	2.22	80.2	54.3	0.75	2.47	90.2	54.6
1.50	0.85	61.5	41.8	1.50	0.96	70.3	42.6

*To 1.95 volts vs. cadmium reference

The data show that the energy density at the 3-hr rate of the total single spine electrode is approximately that of the double spine electrode even though utilization of the positive active material is less. This comes about because the added weight of positive active material now included due to the removal of one spine volume is nearly 60 percent less than the weight of spine removed. But a more important consideration is the effect of the twin spine vs. single spine tubular construction on the total battery efficiency. If we assume 1) that the weight of the positive group is 40 percent of the total battery weight for the case of the single spine tubular design, and 2) since the battery is positive limited, both the single spine and twin spine designs have the same weight requirements for cell container, negative group and electrolyte, hence Table 41 can be constructed.

TABLE 41

Tubular Electrode Spine Study - Cell Performance

Single Spine

<u>Amperes</u>	<u>Hrs.</u>	<u>Ahrs.</u>	<u>Total Positive gm</u>	<u>Total Cell gms</u>	<u>Ahrs. per Kg Total Cell</u>
0.130	19.1	2.48	30.5	76.4	32.5
0.350	5.85	2.05	"	"	26.9
0.55	3.29	1.81	"	"	23.7
0.75	2.22	1.67	"	"	21.9
1.50	0.85	1.28	"	"	16.8

Twin Spine

<u>Amperes</u>	<u>Hrs.</u>	<u>Ahrs.</u>	<u>Total Positive gm</u>	<u>Total Cell gm</u>	<u>Ahrs. per Kg Total Cell</u>
0.130	20.2	2.63	33.9	79.8	32.9
0.350	6.36	2.23	"	"	27.9
0.55	3.60	1.98	"	"	24.8
0.75	2.47	1.85	"	"	23.1
1.50	0.96	1.44	"	"	18.0

Clearly, if the total battery is considered, the twin spine tubular construction gives a better energy density at all the rates tested. Furthermore, it is less likely that positive grid corrosion would be a mode of battery failure since twice as much spine volume is present. The results summarized in Tables 40 and 41 are graphically presented in Figure 13.

Single vs. Double Spine Performance

FIGURE 13

1.4.2.3 Tubular Positive Electrodes - Conclusions and Future Work

A. Fill densities for thin tubular electrodes must be carefully controlled. Although greater utilization of the positive active material initially is obtained with lower fill densities, cycle life is not as good.

B. Use of Type B oxide powder mixture is recommended.

C. Two spines per tube rather than one spine maximizes the overall cell energy density.

D. Maximum cell capacity and energy density is obtained with an 11-plate group, 21-plate element, outside positives.

E. Cell performance, i.e., energy density, capacity and load voltage, is not as good with tubular electrodes as with flat pasted plates. Performance particularly drops off at discharge rates above 75 amps. This is due to the relatively low surface area, and greater plate thickness inherent to the tubular construction. Low fill densities intended to overcome these characteristics do not.

F. Further work with the tubular plate electrode for use in advanced lead-acid EV batteries will be held in abeyance until the life testing of FP-1 and TP-1 batteries progresses. Cells built to data will continue cycling to failure.

1.4.2.4 Composite Positive Electrode

An experimental composite electrode designed as an alternative to the tubular plate was built and tested. This composite positive electrode consists of (1) a lead grid with either orthogonal or tubular spine geometry, (2) two layers of inert polypropylene Conwed® net placed on either side of the lead grid, (3) positive active material pasted into the open structure of the plastic net, and (4) inert glass mat placed on either side of the net. The lead portion of the composite provides electrical conductivity whereas the plastic net primarily serves as a matrix for holding the positive active material. Its geometry is such that each pellet in the net contains a section of the lead grid to insure that no region of the active material becomes isolated and inaccessible to electron transfer. Lamination of the grid is accomplished by placing the plastic nets on either side of the lead, hot pressing the combined sandwich enough to flow the plastic so that the nets just contact each other through the gaps in the lead grid, and then ultrasonically welding the plastic to form a permanent bond (Figure 14). After this step, the active material is flush pasted on the grid exposing the plastic net structure (Figure 15). Following the cure, glass mat is placed on either side of the electrode and heat sealed to the surface of the exposed plastic net (Figure 16). This last operation locks in the positive active material in a pellet bounded by glass mat at the face and plastic net at the perimeter. Shedding should be significantly reduced and positive electrode life increased. The plate shown in Figures 14, 15 and 16 contains a typical ISOA tubular spine grid as the electronic conductor and Conwed® net, 3 X 3 strands to the inch.

COMPOSITE POSITIVE
ELECTRODE-UNPASTED

FIGURE 14

COMPOSITE POSITIVE
ELECTRODE-FLUSH PASTED

FIGURE 15

COMPOSITE POSITIVE
ELECTRODE-COMplete

FIGURE 16

Four different composite plate constructions were tested in Cells C1, C2, C3, and C4 (cf Table 42). The type of lead grid, the net spacing, and the paste density were varied in an attempt to maximize positive active material.

All of the above cells are still on test and are performing well. They remain positive limiting and are being cycled at 100 percent depth of discharge to a 1.5 volt cutoff. Figures 17 and 18 show the cycle life behavior of Cells C1, C2, and C3 and they exhibit <2 percent drop in capacity per 100 cycles. Also included in the graph is the positive active material use.

The capacity of Cell C1 was lower than expected and this was found to be related to the large amount of plastic in the plate construction (nearly 18.4 cc/plate) and to the type of lead geometry used. In Cell C2, the tubular spine grid was replaced with an orthogon grid and utilization of the positive active material increased by nearly 25 percent. In Cell C3, the pellets of the Conwed® net were opened up from 3 X 3 strands to the inch to 1.5 X 1.5 strands to the inch which corresponded to a reduction of 33 percent in the net volume. This too improved the performance of the composite positive electrode. Typical data for the 60 ampere discharge rate are:

<u>Cell</u>	<u>Cycle</u>	<u>Time (Mins.)</u>	<u>Capacity (Ahrs.)</u>	<u>Init. Temp. (F°)</u>	<u>Init. SP GR</u>	<u>Positive Active Material Use (%)</u>
C1	15	119	119	87	1.285	27.4
C2	15	132	132	88	1.275	30.4
C3	15	150	150	87	1.280	32.8

At a discharge rate of 60 amps, utilization of the positive active material in Cell C4 was between 38 and 39 percent. Because the amount of formed positive active material is considerably less than in tubular electrodes, the overall capacity of C4 is only 158 Ahrs (vs a maximum value of 191 Ahr for T21 and 201 Ahr for T22 at the 60 ampere rate). Some of the difference can be eliminated by increasing the paste density and by using an outside positive construction. This should increase the capacity of the group to 180 Ahrs.

Typical data for C4 are:

<u>Cycle</u>	<u>Current (Amps)</u>	<u>Capacity (Ahrs)</u>	<u>Pos. Use(%)</u>	<u>Neg. Use(%)</u>	<u>Acid Use(%)</u>	<u>Ahr/ Kg</u>
16	60	158	39.8	41.9	60.8	18.3
50	50	163	41.0	43.2	62.7	18.9

TABLE 42

Design Parameters for Cells Containing Composite Positive Electrodes

	C1	C2	C3	C4
A. <u>Positive Electrode</u>				
1. Type of Oxide	100% GOX plus additive	100% GOX plus additive	100% GOX plus additive	Mix B
2. Positive Plate				
(a) Lead Grid Type	ISOA Tubular Spine	GW Orthogonal	GW Orthogonal	GW Orthogonal
(b) Lead Weight (g)	122	83	83	83
(c) Plastic Net Wt. (g)	18	13	12	12
(d) Plastic Net Geometry (Strands/inch)	3 X 3	3 X 3	1.5 X 1.5	1.5 X 1.5
(e) Plastic Net Bulk Density (Kg/m ³)	0.293	0.293	0.195	0.195
(f) Glass Mat Thickness (mm)	0.304	0.304	0.304	0.304
(g) Paste/Plate (g)	182	170	180	163
(h) Cured Weight/Plate (g)	171	157	166	143
(i) Formed Weight/Plate (g)	176	161	170	148

TABLE 42 (cont'd)

	C1	C2	C3	C4
(j) Theoretical Ahrs	39.4	36.1	38.1	33.0
(k) Total Composite Plate Wt. Formed (g)	316	262	265	243
(l) Plate Thickness (mm)	3.11	3.5	3.3	3.4
3. Positive Group				
(a) Number of Plates	11	12	12	12
(b) Weight of Formed Active Material (g)	1936	1932	2040	1776
(c) Weight of Group Formed (g)	2.68	3.34	3.38	3.11
(d) Theoretical Ahrs	434	434	457	397
B. <u>Negative Electrode</u>				
1. Type of Oxide		100% GOX		
2. Negative Plate				
(a) Grid Type		GW		
(b) Grid Weight (g)		83		
(c) Paste per Plate (g)	123	123	123	123
(d) FAM/Plate (g)	112	112	112	112
(e) Theoretical Group	29.0	29.0	29.0	29.0

TABLE 42 (cont'd)

	C1	C2	C3	C4
3. Negative Group				
(a) Number of Plates	12	13	13	13
(b) Weight of FAM (g)	1344	1456	1456	1456
(c) Weight of Group Formed (Kg)	2.50	2.68	2.68	2.68
(d) Theoretical Ahrs	348	377	377	377
C. <u>Electrolyte</u>				
1. Sp Gr when Charged			1.300	
2. Volume per Cell (cc)	1950	1875	1875	1875
3. Weight per Cell (Kg)	2.53	2.43	2.43	2.43
4. Theoretical Ahrs	271	260	260	260
D. <u>Separators</u>				
1. Type			Dimpled Daramic Envelopes	
2. Thickness Dimple (mm)			0.760	
3. Backweb Thickness (mm)		0.254		
4. Weight per Cell (g)	85	95	95	95
E. <u>Other</u>				
1. Container Weight (g)		240		
2. Cover Weight (g)		80		
3. Total Cell Weight (Kg)	9.11	8.85	8.89	8.63

Cycle Life Behavior of Composite Plate Cell (C1)

FIGURE 17

Cycle Life Behavior of Composite Plate Cell (C2, C3)

FIGURE 18

1.4.2.5 Flat Pasted Plate Electrode

The flat plate electrode is the simplest and cheapest positive electrode to construct and exhibits the best performance of all those tested. It is made by pasting an orthogonal cast lead grid with a mixture of fine oxides, water, and sulfuric acid. The pasted plate is then cured and dried. As indicated earlier, this type of electrode can be made thin to enhance acid penetration into the positive active material, and it contains no inert material such as plastic or glass which tend to increase the current density on the electrode surface. These factors make for good utilization. The only disadvantage of the flat pasted plate construction is that it is not conducive to long life. Several cells were built in which a proprietary additive, aimed at decreasing plate shedding and increasing life, was added to the positive paste formulation.

Although many different types of flat pasted plate electrodes were investigated over the last year, the six most significant ones are summarized in Table 43. The main parameters varied were paste density, additives and plates per positive group.

TABLE 43

Design Parameters for Cells Containing Flat Pasted Plate Positive Electrodes

	<u>PP3</u>	<u>PP5</u>	<u>PP7</u>	<u>PP8</u>	<u>PP9</u>	<u>PP10</u>
<u>A. Positive Electrode</u>						
1. Type of Oxide	Mixture B					
a) Additive	Yes	No	No	Yes	No	No
2. Positive Plate	Orthogonal					
a) Lead Grid Type	1GW	1GW	1GW	1GW	2GW	1GW
b) Lead Weight (g)	105	105	105	105	95	105
c) Paste per Plate (g)	172	172	172	172	172	172
d) DAM* per plate (g)	155	155	152	154	164	162

TABLE 43 (cont'd)

	<u>PP3</u>	<u>PP5</u>	<u>PP7</u>	<u>PP8</u>	<u>PP9</u>	<u>PP10</u>
e) FAM** per plate (g)	159	157	153	158	166	164
f) Theoretical Ahrs	35.7	35.2	34.3	35.4	37.2	36.8
g) Cured Thickness(mm)	2.26	2.59	2.61	2.31	2.18	2.16
3. Positive Group						
a) Number of Plates	15	15	15	15	15	15
b) Weight of FAM* (g)	2385	2355	2295	2370	2490	2624
c) Wt. of Group Formed (Kg)	4.125	4.100	3.950	3.970	4.035	4.400
d) Theoretical Ahrs	536	528	514	531	558	589

*DAM Dry Active Material

**FAM Formed Active Material

B. Negative Electrode

1. Type of Oxide

100% GOX

2. Negative Plate

a) Lead Grid Type

GW

b) Grid Weight (g)

83

c) Paste per Plate (g) 123 123 123 123 130 118

d) DAM per plate (g) 118 118 118 118 123 115

e) FAM per plate (g) 112 112 112 112 118 110

f) Theoretical Ahrs 29.0 29.0 29.0 29.0 30.6 28.5

g) Cured Thickness(mm) 1.58 1.58 1.58 1.58 1.60 1.47

3. Negative Group

a) Number of Plates 14 14 14 14 14 15

b) Weight of FAM (g) 1568 1568 1568 1568 1722 1650

c) Wt. of Group Formed (Kg) 2.88 2.88 2.88 2.88 3.00 3.05

d) Theoretical Ahrs 406 406 406 406 428 428

TABLE 43 (cont'd)

	<u>PP3</u>	<u>PP5</u>	<u>PP7</u>	<u>PP8</u>	<u>PP9</u>	<u>PP10</u>
C. <u>Electrolyte</u>						
1. Sp Gr Charged			1.30			
2. Volume per Cell (cc)	2025	2000	2000	2000	1975	1960
3. Weight per Cell (Kg)	2.63	2.60	2.60	2.60	2.568	2.548
4. Theoretical Ahrs	281	278	278	278	275	272
D. <u>Separators</u>						
1. Type	R i b b e d D a r a m i c E n v e l o p e s					
2. Thickness Rib (mm)		0.940				
3. Thickness Backweb (mm)		0.304				
4. Weight per Cell (g)	100	100	100	100	100	105
E. <u>Other</u>						
1. Container Weight (g)			240			
2. Cover Weight (g)			80			
3. Total Cell Wt. (Kg)	10.06	10.0	9.85	9.87	10.02	10.42

Cells PP7 and PP8 are no longer on test. Both exhibited capacity decay with cycling, and a post-mortem of these cells showed massive shedding of the positive active material. The performance characteristics of the above cells are summarized in Tables 44, 45 and 46. The end of discharge is marked by a 1.5 volt cutoff regardless of the discharge rate. Periodic cadmium reference readings show that throughout the cycle test, all cells have remained positive limiting.

The voltage-time characteristics of Cells PP5 and PP10, the two best performers, at various rates of discharge are shown in Figures 19 and 20.

Cell construction in Battery 1507-2 is identical to PP9 except that 1GW grids were used for the positive instead of the lighter 2GW. The battery weighed 31.4 Kg, consisted of three cells, and contained 558 ampere hours of positive active material per cell. Voltage-time characteristics are shown in Figure 21(A). Table 47 summarizes actual performance data as well as the projected behavior based on design modifications for the advanced battery.

TABLE 44

Cycle Life Behavior of PP3 and PP5

Cycle No.	Current (Amps)	Time (Min)	Init Temp (°F)	Init SpGr	Final SpGr	Capacity (Ahr)	Pos Use %	Neg Use %	Acid Use %	Ahr/Kg	Whr/Kg
PP3											
4	60	178	91	1.285	1.130	178	33.2	43.8	63.3		
11	60	194	86	1.312	1.145	194	36.2	47.8	69.0	19.3	
20	60	190	88	1.310	1.115	190	35.4				
30	60	190	86	1.306	1.110	190	35.4	46.8	67.6		
40	60	189	87	1.306	1.110	189	35.3				
43	40	317	84	1.306	1.085	211	39.4	51.9	75.1	21.0	
44	60	191	87	1.304	1.105	191	35.6			19.0	
45	75	147	88	1.310	1.115	184	34.3			18.3	
47	140	62	83	1.295	1.160	145	27.0			14.4	
PP5											
4	60	202	91	1.315	1.100	202	38.2	49.7	72.7	20.2	
13	60	205	90	1.290	1.085	205	38.8	50.5	73.7	20.5	
20	60	198	88	1.306	1.110	198	37.5			19.8	
27	60	203	90	1.300	1.105	203	38.4	50.0	73.1	20.3	
30	40	333	86	1.310	1.080	222	42.0	54.6	79.8	22.2	43.5
31	60	207	89	1.310	1.100	207	39.2	51.0	74.4	20.7	39.7
32	75	157	89	1.285	1.095	196	37.1	48.3		19.6	37.1
34	140	69	88	1.285	1.155	161	30.5			16.1	29.6

TABLE 45

Cycle Life Behavior of PP7 and PP8

<u>Cycle No.</u>	<u>Current (Amps)</u>	<u>Time (Min)</u>	<u>Init Temp (°F)</u>	<u>Init SpGr</u>	<u>Final SpGr</u>	<u>Capacity (Ahr)</u>	<u>Pos Use %</u>	<u>Neg Use %</u>	<u>Acid Use %</u>	<u>Ahr/Kg</u>
PP7										
1	60	193	79	1.265	1.080	193	37.5			19.6
4	60	173	90	1.285	1.120	173	33.6			17.6
7	60	144	91	1.290	1.160	144	28.0			
PP8										
4	60	198	88	1.290	1.100	198	37.3	48.7	71.2	20.1
8	60	197	92	1.310	1.110	197	37.1			20.0
17	60	188	88	1.315	1.115	188	35.4			19.0

TABLE 46

Cycle Life Behavior of PP9 and PP10

<u>Cycle No.</u>	<u>Current (Amps)</u>	<u>Time (Min)</u>	<u>Init Temp (°F)</u>	<u>Init SpGr</u>	<u>Final SpGr</u>	<u>Capacity (Ahr)</u>	<u>Pos Use %</u>	<u>Neg Use %</u>	<u>Acid Use %</u>	<u>Ahr/ Kg</u>	<u>Whr/ Kg</u>
PP9											
5	60	202	82	1.285	1.085	202	36.2	47.2	73.4	20.2	
13	60	208	91	1.304	1.085	208	37.3	48.6	75.6	20.8	40.1
19	60	203	84	1.306	1.085	203	36.4				
23	40	325	80	1.306	1.085	217	38.9	50.7	78.9	21.7	42.4
30	75	152	86	1.295	1.105	190	34.0			19.0	36.2
31	140	70	84	1.302	1.145	166	29.7			16.6	30.6
PP10											
5	60	206	89	1.302	1.090	206	35.0	48.1	75.7	19.8	
7	60	209	86	1.295	1.090	209	35.5				
10	40	336	86	1.302	1.060	234	39.8	54.7	87.1	22.4	44.0
11	60	216	89	1.304	1.085	216	37.7	50.5	79.4	20.7	40.2
12	75	168	91	1.285	1.085	206	35.0	48.1	75.7	19.8	38.1
14	140	75	87	1.290	1.120	175	29.8			16.8	31.1

Voltage-Time Behavior for Cell PP10
(Advanced Flat Pasted Plate Positive)

Cycle	Current	Avg. Voltage
• 10	40A	1.96
Δ 11	60A	1.94
□ 13	75A	1.93
x 14	140A	1.85

FIGURE 19

Voltage-Time Behavior for Cell PP5

(Advanced Flat Pasted Plate Positive)

Cycle	Current	Avg. Voltage
• 30	40A	1.96
Δ 31	60A	1.92
□ 33	75A	1.895
x 34	140A	1.84

Voltage-Time Characteristics for Battery 1507-2

Cycle	Current	Avg. Voltage
• 8	60A	5.84
Δ 9	75A	5.83
□ 10	140A	5.66
x 11	40A	5.89

TABLE 47

Behavior of Advanced Battery Containing Flat Pasted Plates

<u>Cycle No.</u>	<u>Current (Amps)</u>	<u>Time (Mins)</u>	<u>Capacity (Ahrs)</u>	<u>Average Voltage</u>	<u>Pos AM Use(%)</u>	<u>A Whr/Kg</u>	<u>B Whr/Kg</u>	<u>C Whr/Kg</u>	<u>D Whr/Kg</u>
8	60	212	212	5.84	38.0	39.4	40.5	41.5	44
9	75	163	204	5.83	36.6	37.8	38.8	39.7	41
10	140	73	170	5.66	30.5	30.6	31.4	32.2	34
11	40	333	222	5.89	39.8	41.6	42.7	43.7	46

NOTES:

- 1) All battery data taken for initial battery temperature of 90°F, initial Sp Gr of 1.310.
- 2) Capacity taken to 4.5V cutoff for all rates.
- 3) Whr/Kg column A based on actual data.

Whr/Kg column B projected based on using 2GW (95g) grids instead of 1GW (105g) grids for the positive, and through the partition intercell construction rather than over the partition construction.

Whr/Kg column C projected based on using a 3I plate element (cf Cell PP10).

Whr/Kg column D projected based on using a lightweight plastic grid.

The energy densities projected in column D are realistic values for utilization of the positive active material. These values can be obtained by only using lighter weight materials and redesigning the battery elements. In the event that a breakthrough arises in improving the use of the positive active material by 20 percent (i.e., from 38 to 45.6% @ the 60 amp discharge rate), the projected energy densities would increase by another 7 percent.

1.4.3 Electrolyte

The effect on performance of acid circulation during discharge only through a typical EV size cell was determined. Electrolyte was introduced in the top of the cell container and removed from the bottom using a Cole Parmer No. 7017 Masterflex Pump (peristaltic type). A manifold exit pipe was placed at the cell bottom to insure good acid distribution. A cell identical in construction to PP9 (cf Table 43) was used for this test. Cell capacity was monitored as electrolyte was pumped on alternate cycles. Typical capacity values for 60 ampere discharges are:

Cycle No.	Cell Capacity No Pumping (Ahr)	Cycle No.	Cell Capacity Pumping (Ahr)	Flow (ml/min)	Average Residence Time (mins)
5	202	4	202	590	3.35
7	203	6	210	590	3.35
9	200	8	208	560	3.53
11	197	10	208	750	2.63
13	208	12	208	590	3.35
15	207	14	208	450	4.39
17	206	16	205	510	3.87
19	203	18	207	550	3.59
21	200	20	207	530	3.73
<u>202.8 + 3.7 Ahr</u>					
		22	<u>204</u>	550	3.59
		<u>206.7 + 1.5 Ahr</u>			

At this rate, the variation in cell capacity due to electrolyte pumping ranged from 0 to 5 percent. The average net improvement was 2.1 percent. Additional data were obtained at 40, 60, 75, and 140 ampere discharges and the results are summarized in Table 48. The initial cell temperature in all cycles listed was 86°F, and the initial specific gravity was 1.300.

TABLE 48

The Effect of Acid Circulation on Battery Performance

Cycle No.	Electrolyte Flow(ml/min)	Current (Amps)	Time (mins)	Capacity (Ahrs)	Positive Active Material Use(%)	Avg. Volt	Capacity (Whrs)	Capacity (Whr/Kg)
24	540	40	336	224	40.1	1.96	439	43.2
25	0	40	325	217	38.9	1.95	423	41.7
26	530	60	206	206	36.9	1.92	396	38.9
28	0	60	199	199	35.7	1.93	384	37.8
29	510	75	159	199	35.7	1.90	378	37.2
30	0	75	152	190	34.0	1.91	363	35.7
31	540	140	73	170	30.5	1.85	314	31.0
32	0	140	70	163	29.2	1.85	302	19.7

The average improvement in cell capacity (Whr/Kg) due to electrolyte circulation was 3.6, 2.9, 4.2, and 4.3 percent, for the 40, 60, 75 and 140 ampere discharge rates, respectively. The net improvement in capacity appears fairly independent of the rate and in part it may be due to the heat energy delivered by the peristaltic action of the pump to the electrolyte. Typically, the final temperature of the cell with circulation is 2 to 3°F higher than without circulation. Although electrolyte pumping does have a significant effect on cell capacity, the improvement is small, and the added expense, design complexity, and pump weight do not appear justified.

1.4.4 Advanced Battery Preliminary Conclusions & Future Work

1.4.4.1 Negative Grid - Type A Plated Plastic

A. Conclusions

1. Deposition of copper on a plastic grid can achieve the same grid conductance as a cast lead control.

2. Electroless copper deposition is needed to make the plastic grid sufficiently conductive for further copper and lead electroplating.

3. The copper deposited by electroless techniques is not enough to provide adequate conductivity and additional copper must be applied using conventional electroplating techniques.

4. Lead must be applied to the copper to render it electrochemically inert and to prevent excessive hydrogen evolution on charge.

5. In order to guarantee that dissolution of the copper does not occur, the cell should be made positive limiting, i.e., the voltage of the negative electrode vs Cd should not rise above +0.5V at the end of discharge.

6. Cells containing Type A lightweight negative grids behave as well as controls under negative limiting conditions. Cell capacity and load voltages match the controls over 200 cycles at full depth of discharge.

7. Type A grids can reduce the overall battery weight from 6 to 8 percent with no loss in the delivered energy.

8. A good technique for attaching the current carrying lug to the grid remains a major problem. The methods used are only feasible on a laboratory scale.

B. Future Work

Future work with the Type A grid will center on scaling it up from automotive size to EV size, and on solving the lug problem. Figures 21(B) and 21(C) (Drawings 6024008 and 6024009) illustrate an advanced negative EV grid which incorporates the features of the Type A lightweight design. In contrast to the standard orthogonal grid geometry, the advanced grid contains current carrying ribs extending radially from the lug. It contains 18 diagonal members which are used to carry the current and 18 horizontal cross members used as a matrix to support the negative active material. The pastable volume of the grid is the same as a standard GW lead cast orthogonal grid. However, it differs in that the total path length of the current carrying members has been increased by 63 percent whereas the total length of the horizontal members has been reduced by 22 percent. The spacing between the horizontal rows is a variable optimized so that the maximum pellet area in any given row equals that of any other row.

To eliminate the problem of the lug and subsequent assembly of the negative plates into a group, the advanced lead acid negative grid specification has provided for a lead lug insert around which the plastic grid will be molded. The lug should weigh less than 5 gms and a detailed drawing of it is found in Figure 21(C). The lug may either be cast or stamped.

REV	DESCRIPTION	DATE	BY
1	ISSUED FOR FABRICATION	11/84	ESS
2	REVISED FOR MOUNTING	12/84	ESS

ADVANCED NEGATIVE GRID
RADIAL RIB
TYPE A CONSTRUCTION
FIGURE 21(B)

NO.	DESCRIPTION
1	.008
2	.008
3	1.156
4	1.156
5	1.041
6	2.161
7	2.541
8	2.541
9	2.541
10	2.541
11	2.541
12	4.186
13	4.186
14	4.186
15	4.186
16	4.186
17	4.186
18	4.186

NOTES
1. RADIAL RIBS ARE EQUALLY SPACED
5° FROM 25° CW TO 60° CW FROM
HORIZONTAL RIB (TOTAL 18 RIBS)

ESS INCORPORATED		TECHNOLOGY CENTER YARISLET, PENNSYLVANIA	C
GRID-RADIAL RIB WITH LENS WIG INSERT			
6024008

Advanced Negative Grid - Lead Lug Insert

FIGURE 21(C)

DESIGN/RELEASE APPROVALS		DRAWN BY	K.D.	DATE	5/30/79	ESB INCORPORATED TECHNOLOGY CENTER YARDLEY, PENNSYLVANIA
APPROVED BY	DATE	ENGINEER		SCALE	2:1 AND 8:1			
		MATERIAL	ALLOY 6B5			LEAD INSERT FOR GRID - RADIAL RIB		
		DO NOT SCALE DRAWING						
		TOLERANCE						
		FRACTION	DECIMAL	ANGLES		DRAWING NO.	6024009	
		± 1/64	.XX ± .010 .XXX ± .005	± 1/4°				B

1.4.4.2 Negative Grid - Type B - Electroformed Copper Grid

A. Conclusions

1. A 0.05 mm thick electroformed copper grid can be used to achieve the same grid conductance as a cast lead control.

2. Lead must be applied to the copper to render it electrochemically inert and to prevent hydrogen evolution on charge.

3. In order to guarantee that dissolution of the copper does not occur, the cell should be made positive limiting, i.e., the voltage of the negative electrode vs Cd should not rise above +0.5 V at the end of discharge.

4. The load voltages of cells containing Type B lightweight negative grids are the same as the controls. Cell capacity at full depth of discharge is 20 percent lower than controls. The reason for the low capacity has not been established although it may be related to excessive gassing and an inability to fully charge the negative plates. More work in this area is needed.

5. Type B grids should reduce the overall battery weight by 5 to 6 percent with no loss in the delivered energy.

6. The lug is metallic and poses no problem in using standard burning techniques to assemble the negative cell group.

B. Future Work

Future work on the Type B grid will center on scaleup from automotive to EV size. Lead plated grids will be assembled into the negative groups of a 3-cell advanced lead acid battery. These grids will have a typical GW orthogonal geometry.

1.4.4.3 Positive Plate - Flat Pasted Type

A. Conclusions

1. Cells built with flat pasted plate positives give the best performance (load voltage, capacity) of the different electrode types tested.

2. The key to obtaining good life with this type of electrode construction is a very tight element pack. A tight pack which is maintained over the life of the battery will reduce active material shedding and inhibit grid corrosion.

3. Maximum cell capacity is obtained by using a minimum separator thickness consistent with ease of assembly - 0.76 mm, maximizing the surface area of the positive group, and the number of plates in the group.

4. Increasing the size of the cell element from 29 to 31 plates does not decrease the active material utilization and results in a better energy density.

5. The effect of paste density, and additives on the life of flat pasted plate positives is still uncertain.

B. Future Work

1. Cells and batteries of the type PP3, PP5 and PP9 will be placed on automatic cycling to determine the effect of these parameters on life. Presumably, the cells built with additives should last longer.

2. A study will be conducted on assembly techniques and materials of construction for producing a tight element pack. The investigation will include the use of glass filled polyester laminates for reinforcing the walls of the battery case. If necessary, the case will be redesigned to prevent bulging of the thin polypropylene material currently in use.

Future work with the pasted flat plate positive electrode will also include constructing additional batteries to verify the above conclusions.

1.4.4.4 Positive Plate - Tubular Type

A. Conclusions

1. Fill densities for thin tubular electrodes must be carefully controlled. Although greater utilization of the positive active material initially is obtained with lower fill densities, life is not as good.

2. Use of Type B oxide powder mixture is recommended.

3. Two spines per tube rather than one spine maximizes the overall cell energy density.

4. Maximum cell capacity and energy density is obtained with an eleven positive plate group, twenty-one plate element, outside positives.

5. Cell performance, i.e., energy density, capacity, load voltage, is not as good with tubular electrodes as with flat pasted plates at discharge rates above 75 amps. This is due to the relatively low surface area, and greater plate thickness inherent in the tubular construction.

B. Future Work

1. Cells built to date will continue cycling to failure.

2. The best performing tubular positive plates will be duplicated and assembled with the lightweight negative plates being developed.

1.4.4.5 Positive Plate - Composite Electrode

A. Conclusions

1. Utilization of the positive active material was the same as with the tubular electrode. Cell performance, i.e., energy density, capacity, load voltage is not as good as with flat pasted plates. This is due to the relatively low surface area, and greater plate thickness inherent to the composite construction. Low paste densities intended to overcome these deficiencies do not.

B. Future Work

1. No further work with the positive composite electrode for use in advanced lead-acid EV batteries is planned unless the life of batteries with flat pasted plate positives is shown to be extremely poor. Cells built to date will continue cycling to failure.

(REST OF PAGE PURPOSELY LEFT BLANK)

1.4.5 Measuring the Heat Generated in EV Batteries

The current emphasis placed on commercializing electric vehicles has spurred the development of advanced lead acid batteries which will have energy and power densities 50-80% greater than lead acid batteries now in use. The electric vehicle is designed to accommodate this high energy battery as a tightly packed modular array, and the engineering aspects of heat generation and removal must be considered. An uncontrolled increase in the lead acid cell temperature could substantially reduce its life.⁽⁵⁾ In order to design a method for controlling the temperature for a tightly packed battery array, the amount of heat generated under typical loading and charging regimes must be determined. In the analysis which follows, a standard thermodynamic approach is used to calculate the heat evolved using the measured battery voltage.

When a battery cycles, heat is generated in three ways: (1) I^2Rt , the Joulean or resistive heat (2) ηIt , the heat due to concentration and activation polarization, and (3) $It \left(\frac{T\Delta S}{\eta F} \right)$, the heat due to changes in entropy of the products and reactants of the electrochemical reaction.

Consider a battery in which the charged state is described as State A and the discharged state as State B. Therefore

At constant pressure, the total heat evolved by the reaction above is described as the difference in the heat content of the two states A and B.

$$\Delta H = H_B - H_A \quad (2)$$

The convention is adopted that ΔH is negative when heat is evolved and positive when heat is absorbed as the system goes from A to B.

Only a portion of ΔH is available for useful work. This quantity is the free energy change for the reaction, ΔG . The remainder of ΔH goes into $T\Delta S$, a measure of the difference in entropy between state B and A. Thus at constant temperature

$$\Delta H = \Delta G + T\Delta S \quad (3)$$

ΔH is positive when heat is absorbed, ΔG is positive when work must be done on the system, and ΔS is positive when the system absorbs heat in going from A to B. The maximum useful work obtainable from a battery going from state A to B is given by

$$\Delta G = \Delta H - T\Delta S \quad (4)$$

Expressing the useful work in terms of electrical energy

$$\Delta G = -\eta FE \quad (5)$$

where ηF is the number of coulombs involved in changing a mole of A to B, and E is the reversible cell potential. For a spontaneous reaction, as in cell discharge, ΔG must be negative.

The application of the Gibbs-Helmholtz equation to Eqn (5) allows us to calculate the ΔH and ΔS of a cell reaction from the temperature coefficient of the reversible emf.

$$\Delta S = - \left(\frac{\partial \Delta G}{\partial T} \right)_p = nF \left(\frac{\partial E}{\partial T} \right)_p \quad (6)$$

and substituting into Eqn (3) and (5)

$$\Delta H = -nF \left[E - T \left(\frac{\partial E}{\partial T} \right)_p \right] \quad (7)$$

Determining the reversible emf and measuring the temperature coefficient for the emf provides the data needed to calculate the heat content and the entropy change of the cell reaction. The quantity ΔH can be related to $E_{\Delta H}$, the enthalpy voltage (6) so that

$$\Delta H = -nF E_{\Delta H} \quad (8)$$

and

$$E_{\Delta H} = E - T \left(\frac{\partial E}{\partial T} \right)_p \quad (9)$$

Under normal cycling conditions, the battery exhibits a voltage which differs from the reversible potential. This voltage, V , can be used to calculate the heat that is absorbed or generated by the system. The quantity $(E-V)$ is a voltage drop equal to the resistive and polarization losses of the cell,

$$(E-V) = IR + \eta \quad (10)$$

or in terms of energy

$$I (E-V)t = I^2 R t + I \eta t \quad (11)$$

Substituting Eqn (9) into Eqn (11)

$$I \left[E_{\Delta H} + T \left(\frac{\partial E}{\partial T} \right)_p - V \right] t = I^2 R t + I \eta t \quad (12)$$

$$I \left[E_{\Delta H} - V + \frac{T \Delta S}{nF} \right] t = I^2 R t + I \eta t \quad (13)$$

$$I t \left[E_{\Delta H} - V \right] = I t \left[IR + \eta - \frac{T \Delta S}{nF} \right] = q \quad (14)$$

where q is the heat generated or absorbed during the cell discharge. A positive quantity indicates heat is evolved whereas a negative quantity indicates heat is absorbed. The opposite is true for a cell which is charging. As expected, Eqn 14 shows that resistive losses for the battery are related to the square of the current while polarization and entropy effects are directly proportional to it. Eqn (14) also shows that in order to fully characterize heat evolution from lead acid batteries, one need only 1) measure the cell voltage, 2) measure the cell current, and 3) know the $E_{\Delta H}$ of the lead acid reaction.

Normally for lead acid cells the governing reaction is:

For a fully charged cell with 1.280 Sp. Gr. electrolyte, the $E_{\Delta H}$ at 25°C is 2.07. Figure 22 shows values for the enthalpy voltage as a function of the electrolyte gravity, a measure of the cell's state of charge. Also shown is

The Enthalpy Voltage of
Lead-Acid Cells

FIGURE 22

the reversible EMF. The data for the reversible EMF and $\frac{\Delta E}{\Delta T}$ (used to calculate $E_{\Delta H}$) were obtained from Vinal ⁽⁷⁾ and represent mean values of the results obtained by several researchers. Equations (5) and (8) were then used to calculate ΔG and ΔH respectively as a function of electrolyte gravity and the values are shown in Figure 23.

In a typical lead acid charging regime a degree of overcharge is used - 10 to 15% above the discharge capacity. At the end of charge, the cell voltage rises to about 2.6 V and it gasses freely. At this point the enthalpy voltage is governed by the electrolysis of water. At 25°C, $-\Delta H$ is 68.3 Kcal/mole⁽⁸⁾, and $E_{\Delta H} = 1.48$ V.

Voltage vs. Coulomb curves for cell PP10, representative of a typical construction for use in advanced lead-acid EV batteries are shown in Figure 24. The curves were obtained at 27°C for 40, 60, 75 and 140 amp discharges. Also plotted is the enthalpy voltage. The value of $F_{\Delta H}$ at a given state of discharge is obtained by first measuring the specific gravity of the cell for a given number of coulombs discharged and then using Figure 23 data to cross plot $E_{\Delta H}$ vs. coulombs. The heat evolved or absorbed by the cell equals the integrated area between the actual cell voltage and the $E_{\Delta H}$ curves, and is summarized below.

Discharged Current (Amps)	Time (Hrs)	Heat Evolved (Calories)	Energy Delivered by Cell (Whrs-Calories)	Heat Evolved/ Energy Delivered
40	5.6	693	439 - 378120	.0018
60	3.6	4641	419 - 360861	.0129
75	2.75	8277	398 - 342775	.0241
140	1.25	16507	324 - 279043	.0590

The data show how important the $T\Delta S$ term is in cooling the battery during discharge. Without the contribution of the entropy, an additional 17,000 calories of heat would be dissipated in a typical discharge. During a charge regime, however, the entropy contributes an additional 17 Kcal term which goes into heating the battery. Fortunately, charging rates are substantially longer than discharge rates so that the additional heat generated can be dissipated over longer periods of time and the temperature buildup minimized. Under those circumstances where high charging rates are needed, the heat generation and heat transfer problems are considerably more severe, and external cooling sources may be needed to maintain the battery temperature.

1.5 The Bipolar Battery

One approach taken for improving the energy density of the lead-acid system has been to use a pile type or bipolar construction. In this configuration the bipolar electrode becomes the partition as well as the connecting strap. It is thought that utilization of the active materials is greater than in conventional batteries because oxidation and reduction of the active mass can occur on either side of the barrier without the possibility of isolating islands of active material.

ΔG and ΔH Variation with the
State of Charge

FIGURE 23

The Discharge Behavior of
Lead Acid EV Cells

FIGURE 24

The major drawback in using the pile battery approach in the lead-acid system is one of materials. Few metals will withstand continuous oxidation and reduction in strong sulfuric acid. The logical cheap material is lead. However, under continuous oxidation during charge and recharge, the lead barrier is gradually oxidized to lead dioxide. When using thin barriers to cut down on weight, they soon become perforated. The electrolyte becomes common to two cells and the perforated barrier becomes a shorted plate.

Titanium is a metal that is both lightweight and inert to sulfuric acid when it is made the positive electrode. It resists the acid by forming a compact protective oxide layer which, incidentally, is also an excellent insulator. At the negative side, it becomes conductive, but unfortunately at the lead potential, it also dissolves readily in sulfuric acid. Therefore, most of the previous work with this metal has been to use it as a grid for holding the positive active material, and to discover ways to circumvent its passivity under anodic conditions. The usual approach has been to electroplate titanium with other metals such as gold or nickel and to cover these with a heavy layer (ca 100 micrometers) of lead. This is expensive because of the use of expanded sheet titanium as a substrate. Also, the life of the grid is limited by the time it takes to convert the electrodeposited lead layer to lead dioxide, which then sheds from the non-lead substrate.

ESB Technology Company in conjunction with IRDC has discovered ways to overcome the passivity of titanium plates, limit the penetration rate due to oxidation, and to utilize titanium in its cheapest form - ground sponge. The plates are made by forming titanium powder as a sheet and sintering it. It is then impregnated with lead. Tests have shown that the composite Ti-Pb structure is conductive, and under continuous anodic exposure to sulfuric acid at 5 mA/cm², the penetration rate can be as low as 25 micrometers a year with 17 percent lead in the matrix. These properties suggest its use as a bipolar barrier for pile batteries.

Since titanium dissolved at the lead potential at the negative, it appeared possible to protect it with a coating of electrodeposited lead. At the negative, a thin coating (ca 25 micrometers) should be sufficient since it cannot be oxidized away. During the past year, substantial progress has been made in perfecting a Titanium-Lead matrix barrier for the bipolar battery. The barrier is electrically conductive and ionically insulating, and serves as the positive and negative electrode in adjacent cells. Several processing steps were needed to produce these barriers. Essentially, these involved the following:

- 1) Impregnation of lead into a porous titanium sheet.
- 2) Attachment or sintering of a Ti-Pb positive grid layer to the barrier.
- 3) Coining or compression of a lead-free sealing area for the positive side.

4) Solder plating and Pb foil cladding of the negative side.

5) Thin Pb plating of the positive grid surface.

Sealing techniques with epoxy materials were used to assemble bipolar cells. This type of construction proved successful in eliminating acid leakage and creepage problems. Initially, small 2.5 cm diameter, 2-cell bipolar batteries were assembled and individually tested for performance. The information was subsequently used to design and construct a scaled-up, 10 x 11 cm, 12-cell bipolar battery. The unit worked well enough to provide the necessary data to determine product feasibility and to evaluate use of a bipolar battery in EV applications.

This work demonstrated that it is technically feasible to design and construct a bipolar electrode for use in lead-acid pile batteries. Although energy densities reached thus far (20 Whr/Kg) have been substantially less than in conventional lead-acid batteries, it is conceivable that further development could result in a pile battery which exceeds the ISOA requirements (40 Whr/Kg @ 3 hr. rate). However, the justification for any future work should also consider negative factors such as substantially higher material costs and undetermined cycle life.

This study suggests that present bipolar battery design offers little advantage over the conventional lead-acid systems for EV applications. Chances of success in meeting the advanced battery goals within the ANL contract time schedule would be remote. Therefore, ESB Technology Company and ANL mutually agreed at a Design Review Meeting held at ANL on 3/13/79 that the bipolar design project be discontinued and that the available manpower be redirected to other areas.

1.5.1 Experimental

1.5.1.1 Ti-Pb Matrix

The properties of lead impregnated into a sintered titanium powder structure were investigated in earlier research⁽⁹⁾. The Ti-Pb barriers studied contained a volume % lead ranging from 17 to 60. After preparing the Ti-Pb matrix barriers, follow-up corrosion and penetration data were obtained by IRDC (Inco Research and Development Center). Some of these data are shown in Figures 25 and 26. The voltage variation in Figure 25 indicates an increase in corrosion. Other, more recent samples have been sent to IRDC for metallographic examination. The data indicate that a volume % of lead suitable for bipolar barriers in a lead-acid battery should be in the range of about 30 percent. Subsequently, this amount was used throughout the latter phase of our work.

A. Small 5 x 5 cm Matrix Barrier

To initially develop a Ti-Pb matrix in sheet form, a rolling process was used at IRDC. Strips with a maximum width of 5 cm and a thickness of about 0.1 cm were produced. From these strips, a 5 cm square bipolar plate was designed, as shown in Figure 27. Centrally located was an annular, coined area 0.6 cm wide with an inside diameter of 2.5 cm. The coined area⁽¹⁰⁾ was provided to minimize lead impregnation and thus prevent electrolytic creepage at the positive electrode. A 2.1 cm diameter disc of expanded titanium was spot welded in the center of the inner uncoined area to hold the active material.

FIGURE 25

FIGURE 26

Ti Powder

Rolled Green Ti Strip

Ti Grid

Sintered Coined Plate

Bipolar Electrode

BIPOLAR PLATE CONSTRUCTION - FIGURE 27

Besides spot welding, several other methods were tried at IRDC to attach the grid to the barrier. Initially, expanded titanium grids were sintered on the matrix plate, but they lost contact during the battery cycling process. This approach was quickly abandoned, its failure related to expansion differences in the metals. Another method consisted of sintering small pieces of the Ti-Pb matrix on top of a matrix barrier of similar composition. These sintered-on pieces were referred to as "bumps" and ranged in size from 0.318 x 0.318 x 0.076 cm thick for the small 5 x 5 cm barrier; to 0.635 x 0.953 x 0.076 cm thick for a larger, scaled-up 10 x 11 cm barrier.

B. Scale-Up 10 x 11 cm Barrier

To more effectively evaluate bipolar construction and battery performance, a scaled up version was designed using data generated from the smaller bipolar assembly. Dimensions for this scaled-up barrier (approximately 10 x 11 x 0.1 cm) were dictated by available matrix stock and processing capabilities at IRDC. Due to the scheduling requirements of the ANL Contract, little time was available for development of a much larger unit. The new barrier contained a square electrode area of approximately 8 x 8 cm and incorporated sintered-on 0.076 cm thick bumps for a grid structure. Compared to the smaller samples, the size of these bumps was generally larger and had a less uniform distribution. All edges of the barrier were also coined with perimeter 0.6 cm wide to facilitate proper sealing on the positive side. Originally, the barrier plate also included a tab for conductive measurements, but this was removed due to faulty welding. The scale-up barriers in grid and pasted form are shown in Figures 28 and 29.

1.5.1.2 Bipolar Electrode

A. Bipolar electrodes were fabricated at the ESB Technology Company using the Ti-Pb matrix barriers purchased from Inco. Either a spot welded-on expanded titanium grid or a sintered-on matrix "bump" structure was used for the positive side of the barrier. In early testing, electrolytic leakage was observed around the spot welds and contributed to a slow shorting effect. Steps were taken to eliminate this problem by spot welding the grids in an inert argon atmosphere. Because of the expense involved in the procedure, the alternative method of a sintered-on "bump" structure was used.

In final preparation, a thin layer of lead, 50 to 100 micrometers, was plated over the entire positive grid area. This was done to promote active material adhesion and utilization.

B. Negative Side

Because of the dissolution of titanium in sulfuric acid at the negative potential which leads to self-discharge, a difficulty arose in preparing the negative face of the bipolar electrode. Initially, it was thought that lead plating the negative side would prevent this reaction; however, porosity in the lead plating slowly enabled acid penetration, resulting in titanium corrosion. We then considered sintering copper foil prior to lead plating. While this appeared good in theory, copper or other metals could not be effectively bonded to titanium. Another approach was to first copper plate the titanium surface, and then replating with lead. On this surface, a lead plated copper grid or lead grid was satisfactorily soldered. Although this showed some improvement, it did not eliminate the basic problems of titanium

7
+

POS.

NEG.

Ti-Pb Barriers
For
Bipolar Battery.
After Masking
For
Pos. & Neg. Pasting.

FIGURE 28

Positive

Negative

Ti-Pb Bipolar Electrodes
After Pasting .

FIGURE 29

corrosion. Wiping heated lead or solder over the surface to fill the pores provided further improvement. It was then realized that plating with solder and cladding on top with a layer of lead foil might provide the protection needed. This method was tried and proved successful. Subsequently, it was used in the assembly of the scale-up bipolar battery.

C. Plating and Cladding

The Ti-Pb bipolar barriers as received from Inco were unplated. These had bumps of 0.076 cm thick matrix material sintered on the positive side and a plain surface on the other side for attaching the negative assembly. The coined area was blocked off with plater's tape (3 M's No. EC470) and the positive was electroplated with two to three mills (0.005 - .008 cm) of lead using the following procedures:

Step 1. Immerse at ambient in alkaline cleaner solution for one minute - 2.0 g/l sodium alkylarysulfonate.

37.5 g/l sodium meta silicate.

Step 2. Rinse with deionized water.

Step 3. Immerse in 10 percent fluoboric acid for 20 seconds.

Step 4. Place in plating bath with pure lead anode and solution - 893 g/l lead fluoborate.

10.5 g/l fluoboric acid. 33 g/l boric acid.

2.5 g/l peptone.

Step 5. Adjust current supply for area to be plated, 10 cm x 10 cm, recommended current density 20 ma/cm² (22.4 minutes/mil). Actual current used was 12 amperes for 31.25 minutes for four (4) plates, or 1.6 AH per plate.

After this operation, it was decided that the titanium tabs spot welded near one corner of the barrier were not attached well, and they were all pulled off. The barriers were then cleaned with an alkaline cleanser, 38 g sodium meta silicate and 2 grams of Naccanol per liter, at room temperature, rinsed in tap water, and acid dipped for 20 seconds in 10 percent by volume of fluoboric acid before being solder plated. At this point, the barriers had been masked off completely on the positive side with plater's tape. Also prepared at this time was a stack of 8 mil (0.020 cm) thick lead sheets cut to cover the negative side of the barrier. These sheets were plated with solder. In plating, one side was against the plating tank so that only the exposed side of the lead sheet was properly coated.

The plating tank consisted of the bottom portion of a polystyrene battery jar whose inside dimensions were 9.5 cm wide by 22.5 cm long by 14.5 cm deep. With the anode centrally located, the tank held three liters of plating solution while filled 1.5 cm from the top. The anode was cast from molten eutectic solder bar (63% Sn, 37% Pb) by pouring it about 0.5 cm deep in a 13 x 22 cm tray fashioned from sheet metal. The cast anode was positioned centrally in the jar and rested on the bottom ribs. It protruded a

a few centimeters above the jar walls that provided a place to attach a battery clip for electrical contact.

The solution was made up from 500 ml of stannous fluoborate stock solution (51% from the Textile Chemical Co.), 180 ml of lead fluoborate stock solution (51% from Allied Chemicals), and 450 ml of fluoboric acid (50% from C. P. Chemicals, Inc.). This was diluted to the three liter mark with DI water, and 15 grams of peptone dissolved in 75 ml of hot DI water were added with stirring.

The plating was done at room temperature. Two Ti-Pb matrix barriers which had been cleaned and etched were placed into the bath along with two of the lead sheets and held against the sides of the tank with spring clips. In turn, these four sheets were connected in parallel to the negative terminal of the constant current source. The current was adjusted to 13.2 A for 10 minutes which allowed just enough time to rinse and dry the previous batch and to alkaline clean the next. The alkaline cleaned pieces were stored in DI water until ready to etch in fluoboric acid. These were drained, but not rinsed before placing into the solder plating bath.

Those removed from the bath were stored in a beaker of DI water while the next batch was being etched and the plating started. The finished parts were removed from the DI water, rinsed in running tap water, rinsed in DI water, dabbed partly dry with a paper towel, and blown dry with a heat gun. The next batch was alkaline cleaned and stored under DI water until needed for the next plating cycle. Each plating cycle took about 12 to 15 minutes.

The finished parts were assembled and cladded together in a hot press as shown schematically in Figure 30. The press platens were heated to 390-400°F and pumped up to a total pressure of 2,000 pounds or 177 psi. The solder quickly melted and some oozed out along the edges of the assembly. The heat was then turned off and the platens were allowed to cool until the oozed solder drops solidified or until a temperature of 330°F was reached. The assembly was removed from the press and the process repeated on the next set.

The negative grids were then prepared using 7.3 x 7.6 cm pieces of expanded lead-calcium (0.1%) - tin (0.5%) alloy sheet, Exmet #20 PB-30-500-1. After the lead surface of the barrier was sanded lightly, it was coated with rosin flux. The grid was positioned with a pasting mask and solder tacked on all four sides and five spots in the center with 63 percent tin solder. The solder grease was then removed by rinsing in two changes of Xylene.

D. Pasting

Thereafter, the barriers were fitted with 60 mil (0.152 cm) thick pasting masks on both sides, weighed, and then submitted for pasting.

FIGURE 30

1.5.1.3 Bipolar Cell and Battery Design

Assembly

The small, 2.5 cm diameter bipolar cells were initially fabricated from Plexiglas tube 3.9 cm O.D. by 2.6 cm I.D. by 1.6 cm long. Both sides had a groove machined in the face to hold 3.2 cm diameter O-rings. To permit gas to escape and to add electrolyte or water, a 0.5 cm diameter hole was drilled through the cell wall. Later, these parts were machined from PVC and polypropylene which are more resistant to battery acid. Some cells were satisfactorily sealed together with epoxy cement, which is normally used with automotive lead-acid batteries. Intercell components included a 0.025 cm thick glass retainer sheet, a 0.075 cm thick Yumicron YBE 0.8 mm separator, and several layers of 0.1 cm thick PVC corrugated sheet used as packing spacers. These parts and the assembled 4 volt bipolar battery used in testing are shown in Figure 31.

The scale-up, 10 x 11 cm bipolar battery was similarly constructed, except that a PVC spacer frame was used exclusively in the assembly. The frame was 10.8 cm wide by 11.8 cm high by 0.876 cm thick, and had a face width of 0.8 cm for sealing purposes. Two 0.5 cm holes were drilled at the top of the frame to allow for electrolyte filling and gas escape. The individual bipolar barrier with pasted positive and negative materials, was epoxy cemented to the spacer frame. The intercell components were then placed within; including the glass retainer sheet, the Yumicron separator, and one layer of PVC corrugated sheet between two pieces of Conwed polyethylene (0.2 cm thick). This composite as shown in Figure 32 provided space for the electrolyte and applied pressure to the active materials on the bipolar barrier. The cell modules were then stacked and epoxy cemented together to form a 12 cell pile battery as shown in Figure 33.

After curing of the epoxy, air pressure tests were made on the individual cells using a special air regulated device. Under conditions of 10 psi (69,000 Pa) and for a hold time of 3 minutes, no apparent leakage was observed. Further, no external leaks were evident after filling with electrolyte, and during formation and cycling.

1.5.1.4 RESULTS AND DISCUSSION

A. Formation

The bipolar batteries were formed over a period of 72 hours in sulfuric acid electrolyte with sp.gr. ranging from 1.060 to 1.080. The charge current was 13.7 mA for an average weight of 2.8 g positive active material for the small cells; and 157.4 mA for an average weight of 32.2 g positive active material for the larger cells (formation was 350 Ahr/Kg of dry positive material). After formation, the electrolyte was removed and replaced with 1.318 sp.gr. sulfuric acid which after dilution with the residual forming acid became about 1.280 sp.gr.

Ti-Pb Bipolar Electrodes
and
Cell Components.

6

FIGURE 32

ASSEMBLED 12-CELL
BIPOLAR BATTERY

FIGURE 33

B. Testing

The small batteries were manually cycled using a combination power supply for charge and discharge. A voltage cutout unit with a timer was incorporated into the circuit and set consistently for 1.70 V. With the larger scale-up battery, conventional automatic cycling equipment was used along with a recorder which monitored voltage versus time. In this manner, two or more cycles were performed per day.

Performance data with the small bipolar batteries are presented in Table 49 and Figure 34. The data summarize the performance of 5 batteries with essentially different grid constructions. The first had plain lead barriers, and was used as the control. The next two batteries which contained Ti-Pb barriers, had Pb plating and Cu + Pb platings, respectively, on the negative sides. These showed poor performance as a result of titanium dissolution and eventual self-discharge. The fourth battery which also contained Ti-Pb barriers and had solder plating with Pb cladding on the negative, gave improved performance with no evidence of corrosion. The fifth battery was constructed similarly to the latter, except that a thin layer of Pb was plated on the positive sides. This last set gave much improved performance and provided an increase in positive active material utilization from 31 to 38 percent. None of these small batteries were tested beyond 30 cycles. Emphasis was to quickly evaluate design and performance data for use in a scaled-up design.

Design data for the scale-up battery are shown in Table 50. Basic construction was similar to the fifth battery of the smaller series, except that it was completely sealed with epoxy resin. Throughout the testing, there was no evidence of abnormal thermal or gassing problems. There was, however, a noticeable dark discoloration of the electrolyte, especially at the end of charge. Chemical analysis indicated that this was mainly lead in the form of sulfide and oxide compounds. During that period, there was also an unaccountable drop in specific gravity from 1.280 to 1.250. Other than the addition of water, no other adjustment was made to the electrolyte.

A thorough evaluation was conducted with the larger unit as indicated by the test performance data in Figures 35-38. Discharges were made at several rates, and the average voltage determined at the 3-hour rate was 1.99. This was slightly higher than with conventional lead-acid systems, and one advantage of a bipolar system. However, the discharge curves taken at the various rates resulted in only modest levels of capacity and positive active material utilization, 2.55 AH and 35 percent, respectively, for the 3-hour rate. Calculations made with the data yielded a low energy density of 16.85 WH/Kg. A projected value based on an optimized cell design increased the energy density to 33.46 WH/Kg; a value still below that of the ISOA and advanced battery goals. The weight analysis comparison between actual and projected values is given in Table 51.

After 30 cycles, there was a steady loss in capacity, accompanied by a drop in total voltage. A reference check of the individual cell voltages indicated that two cells were shorted out and several others showed erratic behavior. These dramatic changes can be seen in Figure 39. After 81 cycles, it was decided to discontinue testing and conduct a post-mortem.

TABLE 49

BIPOLAR BATTERY DESIGN AND TEST DATA2.5 cm Dia., 2 Cell/4 Volt, Bipolar Battery

Battery No.	1	2	3	4	5
Barrier Thickness, cm.	Pb 0.1	Ti-Pb 0.1	Ti-Pb 0.1	Ti-Pb 0.1	Ti-Pb 0.1
Vol % Pb	100	30	30	30	30
Positive Grid	None	0.15 Expanded Ti Spot Welded	0.076 Sintered Bumps	0.076 Sintered Bumps	0.076 Sintered Bumps with 0.01 Pb Plating
Negative Grid	None	0.15 Expanded Ti Spot Welded 0.01 Pb Plating	0.01 Cu + Pb Plating Solder Tacked on Pb Plated Expanded Cu Grid	0.002 Solder Plating with 0.02 Cladded Pb Foil Solder Tacked on 0.152 Expanded Pb Grid	0.002 Solder Plating with 0.02 Cladded Pb Foil Solder Tacked on 0.152 Expanded Pb Grid
Dried Paste Thickness - 0.15 cm					
Positive Wt., g.	2.78	2.79	2.81	2.80	2.81
Negative Wt., g.	2.82	2.82	2.83	2.82	2.83
Electrolyte ML of 1.280 H ₂ SO ₄	13.2	12	12	12	12
Cycles	30	17	26	30	30
Actual Capacity, Ma Hr.	194	118	148	191	238
Positive Active Material Utilization % (Maximum) during	31	19	23.5	30.5	38
Comments	Used as Control	Titanium Dissolution at Negative, Self-discharging	Slower Titanium Dissolution at Negative but still Self-discharging	Improved Performance No Negative Problem	Further Improved Performance

Cycle Data 4 Volt Bipolar Battery

2.5 CM DIA., 2 CELL/4 VOLT, BIPOLAR BATTERY
(627 Ma Hr. THEO.)

FIGURE 34

TABLE 5 0
DESIGN DATA
10 x 11 cm Bipolar Battery

1. 12 Cells
2. 7.38 Ahr/Cell
3. Active Material Positive Negative
 Pasted Wt., g 36.2 42.7
 Cured + Dried, g 32.2 38.1
 Formed, g 32.8 35.8
 Theo Ahr 7.35 9.3
4. Acid = 35 ml per cell (4.50 Ahr.)
5. Barrier: Thickness = 0.1 cm (40 mils)
 Vol % Pb = 30%
6. Active Material Thickness (Neg. or Pos.) = 0.15 cm (60 mils)
7. Bumps = 0.076 cm (30 mils)
8. Mesh (Pb-Ca) = 0.15 cm (60 mils)
9. Negative cladding = 0.02 cm (8 mils) thick Pb.
10. Positive Plating = 0.005 - .008 cm (2-3 mils)
 Pb over bumps
11. Total weight with acid = 3.9 kg.
12. Outside Dimensions - 11 x 12 x 14 cm.
 = 1848 cc - 2.11 g/cc

PERFORMANCE OF 10x11 CM, 12 CELL, BIPOLAR BATTERY
- DISCHARGE CURVES -

FIGURE 35

FIGURE 36

FIGURE 37

FIGURE 38

TABLE 5.1

WEIGHT ANALYSIS DATA10 x 11 cm Bipolar Cell

<u>Measurements</u>	<u>Present Cell</u>	<u>Optimized Cell</u> <u>Estimate</u>
A. Component Weights, gm		
Ti-Pb Barrier	61.67	26.57
Positive Plating	6.8	6.8
Negative Cladding	26.5	9.1
Negative Grid	13.0	12.74
Negative FAM	35.69	22.94
Positive Grid	10.33	10.08
Positive FAM	33.06	33.07
Electrolyte	46.08	39.35
Container/Frame	57.2	
Net Packing	12.13	
Glass Retainer	0.19	16.0 Total
Separator	0.65	
Epoxy Cement	9.92	
B. Avg. Voltage @ 3 hr. rate	1.99	1.99
C. Capacity, Ahr.	2.55	2.97
D. % Use Positive Active Material	35	40
E. Weight per Cell	301.09	176.65
F. Energy Density, Whr/Kg	16.85	33.46

10X11CM, 12 CELL, BIPOLAR BATTERY (7.38 AHr. THEO.)

FIGURE 39

C. Post-Mortem

Opinions on these performance problems were centered around two theories; one that separation and shedding of the positive active material had occurred, and two, that penetration had resulted causing leakage through the barrier wall. To substantiate these suspicions, the battery was cleaned, vacuum dried and disassembled in a fully charged condition. Each shorted cell was sawed in half allowing the barriers and pasted electrodes to remain intact. A close examination revealed that both positive and negative electrodes were in reasonably good condition, except for slight separation around some of the bumps. Thereafter, the cells were air pressurized at 10 psi (69,000 Pa) and held for a period of time. A small, but definite pressure loss was observed. Further, the electrodes with sealed frames were covered with 1.280 sulfuric acid and soaked for 72 hours. The pressurized tests were then repeated and slight bubbles were detected around a few recessed bump areas. Therefore, the inherent quality of some of the Ti-Pb barriers is questionable at this point.

D. Cost Analysis

A preliminary cost estimate to produce the Ti-Pb composite bipolar barriers showed price per barrier assuming a 14 percent after-tax return-on-sales = \$4.73/barrier.

Based on this figure and data for the optimized cell design given in Table 51, a cost of \$95 per Kwh is projected for the barrier alone. IN comparison, the cost established for the ANL advanced battery goals is about \$40 per Kwh. Due to the rather high cost of the barrier itself, a thorough analysis on other costs would not appear to be justified at this stage.

1.5.1.5 CONCLUSIONS AND RECOMMENDATIONS

This work demonstrated that it is technically feasible to design and construct a bipolar electrode adaptable to lead-acid pile batteries. Although performance levels reached thus far have not been comparable to conventional lead-acid batteries, it is conceivable that further development could meet or exceed the ISOA requirements. However, the total analysis for any future work should consider negative factors such as substantially higher material costs, undetermined cycle life, and problems associated with paralleling bipolar batteries to achieve the required EV power and energy levels. Experience suggests that present bipolar battery design offers little advantage over conventional lead-acid systems, and chances of success in meeting the advanced battery goals within the ANL Contract Schedule would be remote. Therefore, it has been decided that the bipolar design project be discontinued.

1.6 Single Point Watering System

A system relying on pressure balance for control of electrolyte level was described in the First Annual Report⁽⁴⁾. A device which operated on the same principle has been fabricated in limited quantity and is under test in an electric vehicle. As shown in Figure 40(A) and Figure 40(B), it is a standard vent plug modified to control level and provide an exhaust path for gases produced by the battery. Operation of the device is explained below with reference to Figure 40(B). When the electrolyte in a cell falls below nominal, there will be a gap between the lower end of the level control tube (Item 5) and the surface of the liquid. Water admitted through one of the ports (Item 7) will flow into the cell through the 3 mm dia. hole in the annular ring (Item 4). Water will continue to enter the cell until the level rises to the lower end of the level control tube. Thereafter, gas displaced by the entering water can no longer be vented and the flow is diverted around the level control tube to the opposite port and, via tubing (not shown), into the level control device in the next cell. At all other times, the device allows for escape of gas generated on open circuit stand or during charge. If the electrolyte level is high enough to block the lower end of the level control tube, gas can reach the external piping via the 3 mm water entry hole. When the level is below normal, an additional path is available through the level control tube and the four holes in the top of Item 1. These devices vent gas satisfactorily at rates of at least 2.5 L/min.

The test vehicle used to evaluate these devices is a Sebring-Vanguard Model SV48. The battery complement of eight 6-volt modules may be considered as two separate 24-volt batteries. Depending on the speed range selected, the drive motor may be supplied with either 24 or 48 V by connecting the separate batteries in parallel or series. The water supply/gas exhaust devices were interconnected as shown schematically in Figure 41 which shows the electrical connections and cell-to-cell piping in separate diagrams. Each 24-volt group has a separate watering circuit. This was done to avoid relatively high voltage gradients across short sections of piping which could lead to sparks and explosion of the battery. Since the gas spaces of all batteries in a circuit are interconnected, a spark at any point could cause explosion in all of the batteries. Until a safe method has been found to prevent propagation of explosions, we have limited the number of cells in a common water supply/gas exhaust circuit to twelve.

The actual installation is shown in Figures 42 and 43. The gas exhaust/water overflow tube from each 24 V group is conducted outside the passenger compartment to flash arrestors mounted to the vehicle frame behind the rear axle. The lines leading to these safety devices are clearly visible in Figure 43.

The procedure followed to add water was to open the closed port of one of the levelling devices marked "WATER" in Figure 41 and attach tubing connected to a water reservoir elevated about 0.5 m above the batteries. Flow from the reservoir was restricted to about 250 ml/min. Filling time per battery was 1-2 min. depending on initial level. Water flow was stopped one minute after overflow from the last cell in the string of 12 and the water source was connected to the second 24 volt group. Level control with this device is good with consistent filling to within ± 3 mm of nominal level.

SINGLE POINT WATERING SYSTEM
MODIFIED VENT PLUG

FIGURE 40(A)

FIGURE 41

BATTERY/INSTALLATION SCHEMATIC

LOAD
CIRCUITS

WATER ADDITION/GAS EXHAUST
CONNECTIONS

BATTERY INSTALLATION -
SEBRING SV 48 VEHICLE

FIGURE 42

CHASSIS MOUNTED FLAME ARRESTORS
FIGURE 43

1.7 Support Functions

1.7.1 Test Laboratory

An automated test facility was designed and installed to meet the testing requirements for batteries constructed for this contract. The equipment was constructed by United Systems Corporation to ESB specifications. The test equipment can be divided into two categories for convenience of description: (1) a characterization system which is used to determine battery performance at different rates and different temperatures, and (2) Three life test systems for completing continuous charge/discharge cycles at room temperature to the end of battery life. The characterization system can test up to 64 batteries at one time and each life test system up to 56 batteries for a total of 232 batteries simultaneously.

1.7.1.1 System Description

Many of the major components of the life test systems and the characterization are identical. Those components that are exclusive to the characterization system are indicated by (*).

A*. Environmental Chamber

The Environmental Chamber was manufactured by Hotpack Corp. This chamber has inside dimensions 1.8 m W x 3.3 m D x 2.23 m H and can control any set temperature within the range of -30°C to +60°C. Batteries are placed on racks three tiers high, single depth, and 6 batteries wide. Individual copper buss bars for every terminal connection are mounted in the side of the chamber.

B. Load Banks

Water-cooled Load Banks were specially designed to control a constant current during charge and discharge. Each Load Bank is a self-contained, rack mounted unit 13.3 cm x 41.9 cm. The units are water-cooled and can dissipate up to 5000 watts at a maximum current of 200 amps. (The units used for life testing are limited to 100 amps by the circuit breaker). Internal protection is provided against over current, over voltage, over temperature, and reverse polarity. Front panel indicator lights are provided for error conditions and panel meters for voltage and current. Three, 10-turn potentiometers are available for setting high-charge current, low-charge current, and the discharge current. Batteries are normally series connected with eight batteries per loop or load module. Two load modules are connected in parallel for characterization tests requiring a discharge current between 200 and 400 amps.

C. Power Relays

A 100 amp double-pole, single throw relay (200 amp for characterization tests) is connected between each battery in the series string. This provides the capability of removing individual batteries at the end of charge or discharge while still maintaining current to those remaining in the circuit. A panel of lights (one for each relay) indicates which circuits are active.

D. Charge Power Supply

Each of the three life test systems has a single charge power supply rated at 72 VDC and 350 amps. The characterization charge supply is water-cooled and is rated at 400 amps. These supplies also provide the 24 VDC for the power relays, 6.5 VDC as a dummy load to the load module and 72 VDC for charging. This permits operation of the load modules to zero volts DC on the input terminals. Current regulation is controlled by the load modules.

E. Water Cooling

All load modules are connected to a single water-to-water closed loop heat exchanger for cooling. Each load module has appropriate shut-off valves for ease in removal if repairs are required. The water outlet from each load module passes through a temperature sensitive valve which controls the flow of cooling water as required. Well water is used for cooling and the flow is also controlled by a temperature sensitive valve. A portion of the cooling water to the load modules passes through a deionizer cartridge to maintain the water conductivity at a low level.

F. Control System

The cycle regime for both the life test systems and the characterization system is controlled by a microprocessor associated with each system. The parameters for charge, discharge, or cycle are set by the operator via the front panel switches. The function of the microprocessor is to set up the test conditions established by the operator, record data at the specified intervals, and transmit the recorded information to the data recording system via a 2-wire serial interface. The control system also contains digital display meters for continuous monitoring of the current test status.

G. Visual Displays and Switches

The following function switches and displays are available to the operator (* indicates characterization system only, ** indicates life test systems only):

1. Visual Displays

- a) *Battery Voltage - Battery voltage for indicated battery number.
- b) **Cell Voltage - The individual cell voltage for the battery number indicated. Three cell voltages for each battery are sequentially monitored.
- c) *Cell Voltage 1,2,3 - Individual cell voltages for the battery number indicated.
- d) *Half Cell Voltage 1,2,3 - Individual half-cell voltages for the battery number indicated.

- e) Cycle Number - The number of charge/discharge cycles completed.
- f) Time - The elapsed time for the present charge-discharge-open circuit condition.
- g) *Cell Current - The Charge/Discharge current for the battery number indicated.
- h) *Battery Temperature - The temperature (°C) for the battery number indicated.
- i) *Ambient Temperature - Temperature within the Environmental Chamber (°C).

2. Control Set Point Switches

- a) High Charge - Time limit for high charge.
- b) Low Charge - Time limit for low charge.
- c) Discharge - Time limit for discharge.
- d) Stabilization - Time limit for the open circuit period following charge or discharge.
- e) High Voltage Limit - Maximum voltage limit for high charge.
- f) Low Voltage Limit - Minimum Voltage limit during discharge.
- g) Δ MV - Voltage difference in millivolts between readings.

3. Function Switches

- a) High Charge - Select switch for the high charge period.
- b) Low Charge - Select switch for the low charge period.
- c) Discharge - Select switch for the discharge period.
- d) Stabilization - Select switch for the stabilization period.

- e) Auto Cycle - Select switch for continuous cycling through charge-open-circuit-discharge-open circuit.
- f) Battery Select - Enables readings for the selected battery to be monitored and displayed.
- g) Loop Select - Enables selecting loop of 8 battery for testing.
- h) Battery Select - Enables selecting battery within the selected loop for testing.

4. Control Switches

- a) Reset - Reinitializes the control microprocessor.
- b) End Mode - Terminate all tests at the end of the mode (Charge, Discharge, Open Circuit) which is currently being executed.
- c) End Cycle - Terminate all tests following the completion of the current charge-discharge-open circuit cycle.
- d) Mode Advance - Immediately terminates the current-charge-discharge-open circuit mode and starts the next sequential test mode.
- e) Start - Initiates testing in the mode selected by the function switches or at the point where testing was interrupted by a power failure, fault condition, or pause condition.
- f) Pause - Removes all loads from the batteries and places them in an open-circuit condition.

The control systems also contain an independent voltage scanner which sequentially measures the voltage of each battery and compares this value to a preset high voltage limit and a preset low voltage limit. If the measured value does not fall between the preset limits, all loads are automatically removed. This scanner is used as a safety back-up to the normal system control. In addition, the characterization system has two independent timers that limit the maximum time that the system can be in charge or discharge. These timers are also used as a safety back-up to the normal control settings.

H. Data Recording System

There is one data recording system dedicated to characterization tests and one to service the three life test systems. The data recording systems each contain a microprocessor, magnetic tape drive unit, and a teletypewriter.

The microprocessor controls all communications to the control systems, magnetic tape unit, and the teletypewriter. Active test positions and battery identification information is entered by the operator via the teletypewriter and stored in the microprocessor. At the completion of the charge and discharge portions of the cycle, final voltages, charge/discharge times, cycle number, and date are printed on the teletypewriter for each active test position. A typical example is shown in Figure 44. Each voltage reading recorded by the control system is transmitted to the data recording system and stored in the memory of the microprocessor. IN addition to the value of the voltage, all other measured values and identifying information for that test position are also transmitted and saved in memory. A total of 25 words are used to uniquely identify all information taken for a single point in time for each active test position. The general format of the record is shown in Table 52. After a total of 32 of the 25-word records have been accumulated, the information is recorded on a 9-track magnetic tape in an 800 work record block.

I. Power Back-Up System

The microprocessors used in the control systems and the data recording systems use solid state memories. In the event of loss of electrical power, the stored information in memory would be lost. To prevent this, a stand-by battery-powered back-up system was installed. This system supplies uninterruptable power to the microporcessors in both the control systems and the data recording systems. Uninterruptable power is also supplied to the magnetic tape drive units, teletypewriters, and load modules. In the event of a power failure, the load relays drop out and all batteries are placed in an open circuit condition. When power is restored, batteries are placed back in test at the point where the interruption occurred. The total time of the test interruption and the time at which it occurred is recorded on magnetic tape.

1.7.1.2 Operating Experience

A number of minor problems associated with the data format and operational modes were resolved following installation. The test system has performed satisfactorily since the final de-bug. The batteries were subjected to three occurrences of unscheduled environmental or load conditions while testing. A failure of the temperature controller for the Environmental Chamber permitted the battery temperature to rise to approximately 90°C following one test. This failure also resulted in some damage to the Environmental Chamber. Operator error resulted in unintentional low resistance loads being applied to a single group of batteries on two different occasions. One battery was damaged

CYCLE 00025

FIGURE 44

79:097:00:35

TYPICAL TELETYPE PRINTOUT

AMBIENT TEMP. DEG. C 026

CHARGE MODE

BATTERY	CELL	HIGH RATE CELL VOLTAGE	LOW RATE CELL VOLTAGE	TIME HOURS	DEG. C
1	1	02.408	02.573	002.34	034
1	2	02.391	02.576	002.34	034
1	3	02.395	02.598	002.34	034
2	1	02.403	02.553	002.42	035
2	2	02.389	02.600	002.42	035
2	3	02.402	02.610	002.42	035
3	1	02.400	02.422	002.76	037
3	2	02.388	02.410	002.76	037
3	3	02.405	02.429	002.76	037
4	1	02.406	02.429	002.93	039
4	2	02.390	02.409	002.93	039
4	3	02.398	02.426	002.93	039
5	1	02.400	02.476	002.60	039
5	2	02.388	02.555	002.60	039
5	3	02.405	02.555	002.60	039
6	1	02.397	02.534	002.52	038
6	2	02.393	02.583	002.52	038
6	3	02.404	02.595	002.52	038
7	1	02.398	02.422	002.71	038
7	2	02.392	02.396	002.71	038
7	3	02.402	02.414	002.71	038
8	1	02.397	02.419	002.65	038
8	2	02.394	02.396	002.65	038
8	3	02.404	02.404	002.65	038
9	1	02.404	02.509	002.55	039
9	2	02.389	02.546	002.55	039
9	3	02.399	02.573	002.55	039
10	1	02.405	02.552	002.53	039
10	2	02.383	02.560	002.53	039
10	3	02.405	02.594	002.53	039
11	1	02.409	02.419	002.78	041
11	2	02.380	02.394	002.78	041
11	3	02.405	02.398	002.78	041
12	1	02.407	02.416	002.81	037
12	2	02.384	02.389	002.81	037
12	3	02.402	02.407	002.81	037
13	1	02.405	02.499	002.26	036
13	2	02.391	02.505	002.26	036
13	3	02.396	02.524	002.26	036
14	1	02.397	02.467	002.27	038
14	2	02.394	02.447	002.27	038
14	3	02.402	02.528	002.27	038
15	1	02.406	02.425	002.64	038
15	2	02.393	02.412	002.64	038

TABLE 52
DATA RECORD GENERAL FORMAT

<u>Word</u>	<u>Meaning</u>
1	2 ascii characters VO
2	year
3	blank
4	Julian date
5	hours
6	minutes
7	seconds
8	seconds/100
9	battery number
10	cycle number
11	mode
12	reason for reading
13	voltage battery
14	voltage cell #1
15	voltage cell #2
16	voltage cell #3
17	half cell voltage cell #1
18	half cell voltage cell #2
19	half cell voltage cell #3
20	current
21	temperature
22	reason for termination
23	error word
24	recording mode
25	blank

battery was damaged as a result of these malfunctions. Performance checks indicated that the other batteries had not lost the ability to maintain capacity. A final determination will be made at the end of the life tests. All batteries were individually fused and a redundant temperature controller was installed in the Environmental Chamber to prevent a reoccurrence of these test errors.

The test system continuously monitors itself for a number of error conditions which could effect the tests. When these conditions occur, the batteries are automatically placed in an open-circuit condition until the error condition is corrected. This automatic error checking has performed reliably to date and has prevented a number of malfunctions from effecting the test results.

1.7.1.3 Data Recovery

The life test represents the most difficult situation for data recovery. The information printed on the teletypewriter is used to follow gradual changes in performance by observing individual end of mode voltages and times. Sufficient information is also available on this print-out to hand calculate amp-hours on charge or discharge.

The magnetic tapes are removed from the data recording system systems periodically. These tapes contain voltage-current-time information for each battery recorded in a totally random basis. Computer programs were developed to process this data on an independent computer system. The first step in this process is to combine all the data collected for each battery for a given cycle in a single file. The program then computes the instantaneous charge/discharge power, and a running sum of accumulated amp-hours and watt-hours. A final summary is then listed for each battery and cycle in the format shown in Figure 45. The charge and discharge curves are then automatically plotted on a cathode ray tube (CRT) screen. This CRT also generates a reproducible paper copy of the image displayed as shown in Figure 46.

1.7.1.4 Data Analysis

It is planned to analyze the test data from the FP-1 and TP-1 experiments by multiple linear regression. This will reveal which of the design variables and their interactions have a significant effect on the response criterion chosen; e.g., watt-hours, cycle life, charge acceptance, etc. The analysis will also indicate the relative magnitude of the significant effects on the response criteria. An analysis of variance of the regression equations will provide F values from which the equations can be accepted or rejected at selected confidence levels thus establishing the validity of the equation linearity assumption.

FIGURE 45

6W215716B0011SJAFF1 FLAT ONB RIBSHTS.975.56128529.13 0102101030100 CHARACTERIZATION

BATTERY NUMBER - 1 TEST POSITION - 1 CYCLE NUMBER - 24

TEST BEGAN: THURSDAY, APRIL 5, 1979

TIME - 19:53:36

DATA PRINTOUT EXAMPLE

INITIAL BATTERY TEMPERATURE - 31.0DEG C

TIME HRS	BATT CURR AMPS	BATT VOLTS	CELL ONE VOLTS	MCELL ONE VOLTS	CELL TWO VOLTS	MCELL TWO VOLTS	CELL THREE VOLTS	MCELL THREE VOLTS	POWER WATTS	WATT HOURS	AMP HOURS	BATT TEMP DEG C	ERROR FLAG
CHARGE O.C.V.		5.929	1.379	2.154	1.973	1.523	1.967	.001					
.00	39.3M	6.067	2.023	2.175	2.319	.799	2.017	.062	242.07	.97	.14	31.0	
.01	39.3M	6.187	2.063	2.218	2.059	.659	2.057	.061	246.85	1.52	.27	31.0	
.02	39.3M	6.241	2.080	2.235	2.077	.270	2.075	.073	249.02	2.52	.41	31.0	
.03	39.3M	6.263	2.088	2.243	2.085	.153	2.083	.074	249.89	3.28	.53	31.0	
.04	40.0M	6.284	2.095	2.251	2.092	.004	2.090	.123	251.36	5.65	.91	31.0	
.13	40.0M	6.304	2.102	2.251	2.098	.122	2.096	.207	252.16	33.34	5.31	31.0	
.22	40.0M	6.324	2.109	2.254	2.105	.118	2.102	.198	252.96	55.93	8.89	31.0	
.30	40.0M	6.344	2.116	2.258	2.111	.126	2.109	.201	253.76	76.69	12.16	31.0	
.39	40.0M	6.364	2.123	2.263	2.118	.127	2.116	.207	254.55	97.45	15.43	31.0	
.47	40.0M	6.384	2.129	2.268	2.124	.132	2.122	.206	255.36	117.70	18.61	31.0	
.54	40.0M	6.404	2.136	2.273	2.131	.131	2.129	.209	256.15	137.95	21.78	32.0	
.62	40.0M	6.424	2.142	2.280	2.138	.129	2.136	.203	256.96	158.26	24.94	32.0	
.70	40.0M	6.444	2.149	2.286	2.144	.131	2.143	.204	257.76	178.64	28.11	32.0	
.78	40.0M	6.464	2.155	2.293	2.151	.143	2.149	.217	258.56	199.07	31.28	32.0	
.86	40.0M	6.484	2.162	2.298	2.158	.130	2.156	.207	259.36	218.85	34.33	32.0	
.93	40.0M	6.504	2.168	2.304	2.164	.131	2.163	.204	260.16	238.70	37.39	32.0	
1.01	40.0M	6.525	2.175	2.307	2.171	.139	2.170	.220	261.00	258.58	40.45	32.0	
1.08	40.0M	6.545	2.182	2.313	2.178	.124	2.177	.207	261.81	278.44	43.52	32.0	
1.16	40.0M	6.566	2.189	2.320	2.185	.135	2.183	.210	262.64	297.79	46.57	32.0	
1.23	40.0M	6.586	2.196	2.325	2.192	.130	2.190	.214	263.44	316.54	49.62	32.0	
1.29	40.0M	6.606	2.203	2.324	2.199	.127	2.197	.205	264.24	335.55	52.67	32.0	
1.35	40.0M	6.626	2.209	2.335	2.205	.132	2.203	.209	265.04	354.51	55.72	32.0	
1.41	40.0M	6.646	2.216	2.342	2.212	.135	2.210	.211	265.84	373.45	58.77	32.0	
1.47	40.0M	6.666	2.223	2.345	2.219	.133	2.216	.211	266.64	392.39	61.82	33.0	
1.53	40.0M	6.686	2.230	2.349	2.225	.140	2.223	.214	267.44	411.34	64.87	33.0	
1.58	40.0M	6.706	2.237	2.353	2.232	.123	2.230	.211	268.24	430.28	67.92	33.0	
1.63	40.0M	6.726	2.243	2.357	2.239	.125	2.236	.211	269.04	449.22	70.97	33.0	
1.68	40.0M	6.746	2.249	2.360	2.245	.135	2.243	.217	269.84	468.16	74.02	33.0	
1.74	40.0M	6.767	2.257	2.361	2.252	.122	2.250	.202	270.63	487.10	77.07	33.0	
1.79	40.0M	6.788	2.264	2.362	2.259	.139	2.257	.209	271.42	506.04	80.12	33.0	
1.83	40.0M	6.808	2.271	2.363	2.266	.130	2.264	.214	272.22	524.98	83.17	33.0	
1.88	40.0M	6.828	2.277	2.363	2.273	.135	2.270	.220	273.02	543.92	86.22	33.0	
1.92	40.0M	6.848	2.284	2.366	2.279	.135	2.275	.218	273.82	562.86	89.27	33.0	
1.96	40.0M	6.868	2.291	2.366	2.286	.145	2.283	.220	274.62	581.80	92.32	33.0	
2.00	40.0M	6.889	2.298	2.363	2.293	.131	2.291	.209	275.42	600.74	95.37	33.0	
2.04	40.0M	6.909	2.304	2.364	2.299	.135	2.297	.217	276.22	619.68	98.42	33.0	
2.08	40.0M	6.929	2.311	2.365	2.306	.142	2.304	.225	277.02	638.62	101.47	33.0	
2.11	40.0M	6.949	2.318	2.367	2.312	.146	2.310	.236	277.82	657.56	104.52	33.0	
2.14	40.0M	6.969	2.325	2.365	2.319	.139	2.317	.249	278.62	676.50	107.57	33.0	
2.18	40.0M	6.989	2.332	2.365	2.326	.149	2.324	.255	279.42	695.44	110.62	33.0	
2.21	40.0M	7.009	2.338	2.365	2.332	.155	2.331	.243	280.22	714.38	113.67	33.0	
2.24	40.0M	7.029	2.345	2.365	2.339	.139	2.337	.254	281.02	733.32	116.72	34.0	
2.27	40.0M	7.049	2.352	2.369	2.345	.154	2.344	.264	281.82	752.26	119.77	34.0	
2.30	40.0M	7.070	2.359	2.365	2.351	.150	2.351	.257	282.62	771.20	122.82	34.0	
2.32	40.0M	7.090	2.366	2.366	2.358	.142	2.357	.256	283.42	790.14	125.87	34.0	
2.35	40.0M	7.111	2.374	2.367	2.365	.137	2.365	.252	284.22	809.08	128.92	34.0	
2.37	40.0M	7.131	2.381	2.367	2.371	.149	2.372	.264	285.02	828.02	131.97	34.0	
2.40	40.0M	7.152	2.388	2.366	2.377	.154	2.378	.296	285.82	846.96	135.02	34.0	
2.42	40.0M	7.174	2.395	2.360	2.384	.165	2.386	.347	286.62	865.90	138.07	34.0	
2.44	40.0M	7.195	2.403	2.371	2.390	.161	2.393	.277	287.42	884.84	141.12	34.0	
2.45	40.0M	7.201	2.405	2.372	2.393	.167	2.395	.257	288.22	903.78	144.17	34.0	
2.45	5.0M	6.959	2.328	2.358	2.312	.144	2.309	.236	289.02	922.72	147.22	34.0	
4.49	5.0M	6.589	2.197	2.290	2.196	.221	2.188	.231	32.94	664.22	100.20	33.0	
4.49	5.0M	6.510	2.204	2.290	2.203	.483	2.195	.180	33.05	664.32	100.21	33.0	
4.50	5.0M	6.530	2.211	2.291	2.210	.523	2.202	.140	33.15	664.40	100.22	33.0	
4.52	5.0M	6.651	2.218	2.292	2.217	.023	2.209	.166	33.25	665.13	100.33	33.0	
4.54	5.0M	6.672	2.225	2.297	2.224	.112	2.215	.180	33.35	666.07	100.47	33.0	
4.59	5.0M	6.592	2.232	2.304	2.230	.140	2.222	.216	33.46	667.53	100.69	33.0	
4.67	5.0M	6.712	2.238	2.311	2.237	.139	2.228	.220	33.56	670.23	101.10	32.0	
4.80	5.0M	6.732	2.245	2.319	2.244	.127	2.235	.210	33.66	674.60	101.75	32.0	
4.99	5.0M	6.752	2.252	2.321	2.250	.125	2.241	.214	33.76	680.89	102.68	32.0	
5.22	5.0M	6.772	2.259	2.323	2.257	.131	2.248	.221	33.86	688.78	103.85	32.0	
5.46	5.0M	6.792	2.266	2.322	2.264	.129	2.255	.218	33.96	697.03	105.06	32.0	
5.73	5.0M	6.812	2.272	2.325	2.270	.138	2.261	.225	34.06	706.20	106.41	32.0	
6.01	5.0M	6.832	2.279	2.328	2.277	.138	2.268	.226	34.16	715.65	107.80	31.0	
6.30	5.0M	6.852	2.285	2.328	2.284	.138	2.275	.227	34.26	725.49	109.23	31.0	
6.56	5.0M	6.872	2.291	2.330	2.291	.129	2.282	.221	34.36	735.64	110.57	31.0	
6.84	5.0M	6.892	2.298	2.330	2.297	.137	2.289	.222	34.46	746.09	111.94	31.0	
7.11	5.0M	6.912	2.305	2.330	2.303	.142	2.296	.227	34.56	756.48	113.30	31.0	
7.37	5.0M	6.932	2.312	2.334	2.309	.140	2.302	.224	34.66	767.25	114.57	31.0	
7.61	5.0M	6.952	2.319	2.333	2.316	.133	2.309	.223	34.75	778.71	115.79	31.0	
7.83	5.0M	6.972	2.326	2.333	2.322	.141	2.315	.227	34.86	789.46	116.90	30.0	
8.04	5.0M	6.992	2.333	2.338	2.328	.133	2.323	.222	34.96	799.88	117.96	30.0	
8.23	5.0M	7.012	2.341	2.339	2.333	.139	2.330	.224	35.05	809.42	118.98	30.0	
8.41	5.0M	7.032	2.348	2.342	2.339	.148	2.337	.231	35.16	819.69	119.79	30.0	
8.56	5.0M	7.052	2.355	2.344	2.345	.143	2.344	.229	35.26	829.99	120.54	30.0	
8.69	5.0M	7.072	2.362	2.343	2.350	.145	2.350	.224	35.36	840.75	121.22	30.0	
8.82	5.0M	7.092	2.370	2.346	2.356	.143	2.357	.230	35.46	851.24	121.85		

60215769N070ISOAFP1 FLAT OPB RIBDARS.405.09131527.67
 60.00 AMPS YEAR, DAY, TIME - 1979 97 1 35 46
 25 PRFLE 30 DEG C BATTERY - 24

FIGURE 46

1.7.2 Quality Control/Quality Assurance

The ESB QA/QC Manual, as approved by ANL on 25 May 1978, has been followed throughout the year for all phases of the ANL Contract.

All meters, shunts, hydrometers and other development laboratory equipment have been identified and calibrated against standard instruments. Labels have been affixed to each item indicating the date of last calibration and the date it must be submitted for recalibration.

The materials purchasing and receiving system has functioned throughout the year with Q.C. reviewing purchase orders before issue and receiving all items planned for use under the ANL Contract.

Under the FP-1 phase of the ISOA portion of the Contract, 32 Experimental Battery Specifications (EBS) have been issued. During assembly of the 96 batteries under ISOA-FP-1, the EBS number was used to record the data of all components used in each test battery.

The TP-1 phase of the ISOA portion of the Contract required an additional 32 Experimental Battery Specifications to enable proper recording of the data on the variables in the 128 batteries assembled for this factorial experiment.

In process, components were properly identified and subjected to the required Q.C. inspections and tests to assure compliance to the individual specifications.

REFERENCES

- (1) CRC Handbook of Chemistry and Physics, Robert C. Weast, Editor, CRC Press, Cleveland, Ohio 1977, pp B-122, C-800.
- (2) *ibid.*, pp (B-109, E-84).
- (3) P. Reutschi, P. Delahay, J.Chem.Phys., 23, 195 (1955).
- (4) Annual Report 1978, ANL Contract No. 31-109-38-4207, Prepared for Argonne National Laboratory by ESB Technology Company.
- (5) S. M. Caulder, A. C. Simon, J. Electrochem.Soc., 121, 1546 (1974).
- (6) S. Gross, Energy Conversion, 9, 55 (1969).
- (7) G. W. Vinal, "Storage Batteries," John Wiley & Sons, New York, 4th Edition, Tables 38 & 40, pp 192-194 (1962).
- (8) W. M. Latimer, "Oxidation Potentials," Prentice Hall, Inc., Englewood Cliffs, N. J., 2nd ed., p 39 (1964).
- (9) U.S. Patent 4,124,746.
- (10) U.S. Patent 4,178,216.

APPENDIX NO. 1

FP-2 LIFE CYCLE SEPARATOR TEST

THIS PAGE
WAS INTENTIONALLY
LEFT BLANK

APPENDIX 1

FP-2 LIFE CYCLE SEPARATOR TEST

BATTERY 9A

CYCLE	DISCHARGE FINAL CELL VOLTAGES				HIGH CHG MODE CELL VOLTAGES			LOW CHG MODE CELL VOLTAGES			LOW CHG AH	TOTAL AH	% OVER CHARGE
					LOW	HIGH		LOW	HIGH				
3	1.95	1.95	1.95		2.37	2.39		2.48	2.49		48	140	22
4	1.94	1.95	1.94		2.39	2.40		2.53	2.60		"	"	"
5	1.94	1.94	1.94		2.40	2.42		2.62	2.65		"	"	"
6	1.93	1.94	1.93		2.41	2.42		2.62	2.66		"	"	"
7	1.92	1.93	1.93		2.40	2.41		2.64	2.68		"	"	"
8	1.93	1.94	1.93		*	2.42		2.63	2.67		"	"	"
9	*	*	*		*	*		*	*		"	"	"
10	*	*	*		2.40	2.41		2.64	2.68		"	"	"
11	1.94	1.94	1.94		2.41	2.42		2.64	2.68		"	"	"
12	1.93	1.93	1.93		2.39	2.40		2.65	2.68		"	"	"
13	1.94	1.94	1.94		2.41	2.42		2.66	2.70		"	"	"
14	1.92	1.92	1.92		*	2.39		2.61	2.65		"	"	"
15	1.93	1.94	1.93		*	2.42		2.52	2.61		"	"	"
16	1.92	1.93	1.93		2.41	2.42		2.61	2.67		"	"	"
17	1.95	1.95	1.95		2.41	2.43		2.68	2.70		"	"	"
18	1.94	1.94	1.94		2.43	2.44		2.69	2.71		"	"	"
19	1.93	1.94	1.93		2.42	2.44		2.68	2.70		"	"	"
20	1.93	1.93	1.93		2.43	2.45		2.69	2.71		"	"	"
21	1.92	1.92	1.92		*	*		*	*		"	"	"
* DATA NOT PRINTED BY TELETYPE													

APPENDIX 1
FP-2 LIFE CYCLE SEPARATOR TEST

BATTERY 98

CYCLE	DISCHARGE FINAL CELL VOLTAGES				HIGH CHG MODE CELL VOLTAGES			LOW CHG MODE CELL VOLTAGES			LOW CHG AH	TOTAL AH	% OVER CHARGE
					LOW	HIGH		LOW	HIGH				
3	1.95	1.95	1.95		2.37	2.39		2.48	2.50		48	140	22
4	1.95	1.95	1.95		2.38	2.38		2.53	2.60		"	"	"
5	1.94	1.94	1.94		2.39	2.40		2.62	2.64		"	"	"
6	1.94	1.94	1.94		2.40	2.41		2.63	2.65		"	"	"
7	1.93	1.93	1.93		2.40	2.41		2.64	2.67		"	"	"
8	1.94	1.94	1.94		2.41	2.42		2.64	2.67		"	"	"
9	*	*	*		*	*		*	*		"	"	"
10	*	*	*		2.39	2.40		2.65	2.67		"	"	"
11	1.95	1.95	1.95		*	*		*	*		"	"	"
12	1.94	1.93	1.94		2.40	2.41		2.65	2.67		"	"	"
13	1.95	1.95	1.95		2.40	2.41		2.67	2.69		"	"	"
14	1.93	1.93	1.93		2.39	2.40		2.62	2.65		"	"	"
15	1.94	1.94	1.95		2.41	2.42		2.54	2.58		"	"	"
16	1.94	1.94	1.95		2.41	2.42		2.63	2.65		"	"	"
17	1.95	1.95	1.95		2.40	2.42		2.68	2.69		"	"	"
18	1.95	1.94	1.95		2.43	2.44		2.68	2.69		"	"	"
19	1.94	1.94	1.94		2.42	2.44			2.69		"	"	"
20	1.94	1.94	1.94		2.43	2.44		2.69	2.70		"	"	"
21	1.94	1.93	1.94		*	*		*	*		"	"	"
* DATA NOT PRINTED BY TELETYPE													

APPENDIX 1
FP-2 LIFE CYCLE SEPARATOR TEST

BATTERY 10A

CYCLE	DISCHARGE FINAL CELL VOLTAGES				HIGH CHG MODE CELL VOLTAGES		LOW CHG MODE CELL VOLTAGES		LOW CHG AH	TOTAL AH	% OVER CHARGE	
					LOW	HIGH	LOW	HIGH				
3	1.95	1.94	1.94		2.38	2.40		2.45	2.47	48	140	22
4	1.95	1.93	1.93		2.39	2.40		2.48	2.52	"	"	"
5	1.94	1.93	1.93			2.41		2.52	2.58	"	"	"
6	1.94	1.92	1.92		2.41	2.42		2.52	2.58	"	"	"
7	1.93	1.91	1.92			2.40		2.53	2.60	"	"	"
8	1.94	1.92	1.92		2.42	2.43		2.51	2.59	"	"	"
9	*	*	*		*	*		*	*	"	"	"
10	*	*	*		2.40	2.41		2.50	2.59	"	"	"
11	1.94	1.92	1.93		*	2.41		2.50	2.59	"	"	"
12	1.93	1.92	1.92		*	2.40		2.49	2.59	"	"	"
13	1.94	1.93	1.94		*	2.41		2.52	2.61	"	"	"
14	1.92	1.91	1.92		2.38	2.39		2.47	2.51	"	"	"
15	1.94	1.92	1.93		2.41	2.42		2.45	2.48	"	"	"
16	1.93	1.92	1.92		*	2.41		2.48	2.53	"	"	"
17	1.96	1.95	1.95		2.41	2.42		2.53	2.63	"	"	"
18	1.95	1.94	1.94		2.42	2.43		2.54	2.64	"	"	"
19	1.94	1.93	1.93			2.43		2.54	2.64	"	"	"
20	1.93	1.92	1.93		2.43	2.44		2.54	2.65	"	"	"
21	1.93	1.92	1.93		*	*		*	*	"	"	"
* DATA NOT PRINTED BY TELETYPE												

APPENDIX 1
FP-2 LIFE CYCLE SEPARATOR TEST

BATTERY 106

CYCLE	DISCHARGE FINAL CELL VOLTAGES			HIGH CHG MODE CELL VOLTAGES			LOW CHG MODE CELL VOLTAGES			LOW CHG AH	TOTAL AH	% OVER CHARGE
				LOW	HIGH		LOW	HIGH				
3	1.95	1.95	1.95	2.38	2.40		2.46	2.47		48	140	22
4	1.95	1.95	1.94	2.38	2.40		2.50	2.51		"	"	"
5	1.95	1.94	1.94	2.39	2.41			2.56		"	"	"
6	1.94	1.94	1.94	2.40	2.42		2.56	2.57		"	"	"
7	1.93	1.93	1.93	2.39	2.41			2.58		"	"	"
8	1.94	1.94	1.94	2.40	2.42		2.56	2.58		"	"	"
9	*	*	*	*	*		*	*		"	"	"
10	*	*	*	2.39	2.41		2.55	2.57		"	"	"
11	1.95	1.95	1.94	2.40	2.41		2.54	2.56		"	"	"
12	1.94	1.94	1.93	2.39	2.41		2.53	2.55		"	"	"
13	1.95	1.95	1.95	2.39	2.41		2.57	2.60		"	"	"
14	1.93	1.93	1.93	2.39	2.40		*	2.51		"	"	"
15	1.94	1.94	1.94	2.41	2.42		*	2.48		"	"	"
16	1.94	1.94	1.94	2.41	2.42		*	2.51		"	"	"
17	1.96	1.96	1.96	2.40	2.42		2.60	2.62		"	"	"
18	1.95	1.95	1.95	2.42	2.44		2.61	2.63		"	"	"
19	1.94	1.94	1.94	2.42	2.44		2.61	2.63		"	"	"
20	1.94	1.94	1.94	2.43	2.45		2.62	2.63		"	"	"
21	1.94	1.94	1.94	*	*		*	*		"	"	"
* DATA NOT PRINTED BY TELETYPE												

APPENDIX 1
FP-2 LIFE CYCLE SEPARATOR TEST

BATTERY 11A

CYCLE	DISCHARGE FINAL CELL VOLTAGES				HIGH CHG MODE CELL VOLTAGES			LOW CHG MODE CELL VOLTAGES			LOW CHG AH	TOTAL AH	% OVER CHARGE
					LOW	HIGH		LOW	HIGH				
3	1.94	1.94	1.95			2.38		2.47	2.48		48	140	22
4	1.94	1.94	1.94		2.38	2.39		2.52	2.55		"	"	"
5	1.94	1.93	1.94		2.39	2.40		2.61	2.63		"	"	"
6	1.93	1.93	1.94		2.40	2.41		2.62	2.64		"	"	"
7	1.93	1.92	1.93		2.39	2.40		2.63	2.66		"	"	"
8	1.94	1.93	1.94		*	2.41		2.63	2.66		"	"	"
9	*	*	*		*	*		*	*		"	"	"
10	*	*	*		*	2.39		2.64	2.67		"	"	"
11	1.94	1.93	1.95		*	2.40		2.64	2.67		"	"	"
12	1.93	1.92	1.94		*	2.40		2.65	2.66		"	"	"
13	1.94	1.94	1.95		2.40	2.41		2.66	2.68		"	"	"
14	1.92	1.92	1.93		2.39	2.40		2.59	2.63		"	"	"
15	1.94	1.93	1.94		*	2.42		2.51	2.53		"	"	"
16	1.94	1.93	1.94		*	2.41		2.62	2.65		"	"	"
17	1.95	1.94	1.95		*	2.41		2.67	2.68		"	"	"
18	1.94	1.93	1.94		*	2.43		2.68	2.69		"	"	"
19	1.93	1.93	1.94		*	2.43		2.68	2.69		"	"	"
20	1.93	1.93	1.93		*	2.44		2.68	2.70		"	"	"
21	1.93	1.92	1.93		*	*		*	*		"	"	"
* DATA NOT PRINTED BY TELETYPE													

APPENDIX 1
FP-2 LIFE CYCLE SEPARATOR TEST

BATTERY 11B

CYCLE	DISCHARGE FINAL CELL VOLTAGES				HIGH CHG MODE CELL VOLTAGES			LOW CHG MODE CELL VOLTAGES			LOW CHG AH	TOTAL AH	% OVER CHARGE
					LOW	HIGH		LOW	HIGH				
3	1.95	1.95	1.94		2.37	2.39			2.48		48	140	22
4	1.94	1.94	1.94		*	2.39		2.54	2.56		"	"	"
5	1.94	1.93	1.93		*	2.41		2.62	2.63		"	"	"
6	1.93	1.93	1.93		2.40	2.41		2.62	2.63		"	"	"
7	1.92	1.92	1.92		2.40	2.41		2.63	2.65		"	"	"
8	1.93	1.93	1.93		2.41	2.42		2.63	2.65		"	"	"
9	*	*	*		*	*		*	*		"	"	"
10	*	*	*		2.40	2.41		2.64	2.65		"	"	"
11	1.93	1.93	1.93		2.40	2.40		2.64	2.65		"	"	"
12	1.92	1.91	1.92			2.40		2.65	2.66		"	"	"
13	1.93	1.93	1.94		2.41	2.42		2.66	2.68		"	"	"
14	1.92	1.91	1.91		*	2.39		2.61	2.63		"	"	"
15	1.93	1.93	1.93		*	2.42		2.52	2.53		"	"	"
16	1.93	1.92	1.93		2.41	2.42		2.63	2.65		"	"	"
17	1.95	1.95	1.95		2.41	2.42		2.68	2.69		"	"	"
18	1.94	1.94	1.94		2.42	2.43		2.68	2.69		"	"	"
19	1.93	1.93	1.93		2.43	2.44		2.68	2.69		"	"	"
20	1.92	1.92	1.93		2.43	2.44		2.69	2.70		"	"	"
21	1.92	1.92	1.92		*	*		*	*		"	"	"
* DATA NOT PRINTED BY TELETYPE													

APPENDIX 1
FP-2 LIFE CYCLE SEPARATOR TEST

BATTERY 12

CYCLE	DISCHARGE FINAL CELL VOLTAGES				HIGH CHG MODE CELL VOLTAGES			LOW CHG MODE CELL VOLTAGES			LOW CHG AH	TOTAL AH	% OVER CHARGE
					LOW	HIGH		LOW	HIGH				
3	1.94	1.95	1.95		*	2.37		2.44	2.46		48	140	22
4	1.94	1.94	1.94		*	2.39		2.47	2.49		"	"	"
5	1.93	1.94	1.94		2.40	2.41		2.50	2.53		"	"	"
6	1.93	1.94	1.93		2.40	2.42		2.49	2.52		"	"	"
7	1.92	1.93	1.92		2.39	2.40		2.50	2.53		"	"	"
8	1.94	1.94	1.93		2.40	2.42		2.49	2.52		"	"	"
9	*	*	*		*	*		*	*		"	"	"
10	*	*	*		2.39	2.40		2.49	2.52		"	"	"
11	1.94	1.95	1.94		2.39	2.41		2.49	2.51		"	"	"
12	1.93	1.94	1.93		*	2.39		2.49	2.51		"	"	"
13	1.95	1.95	1.94		2.40	2.41		2.51	2.52		"	"	"
14	1.93	1.93	1.93		2.37	2.38		2.47	2.48		"	"	"
15	1.94	1.94	1.94		2.41	2.42		2.45	2.46		"	"	"
16	1.94	1.94	1.93		2.41	2.42		2.48	2.50		"	"	"
17	1.96	1.96	1.95		2.40	2.41		2.51	2.53		"	"	"
18	1.95	1.95	1.95		2.41	2.42		2.53	2.55		"	"	"
19	1.94	1.95	1.94		*	2.42		2.52	2.54		"	"	"
20	1.94	1.94	1.93		*	2.43		2.53	2.55		"	"	"
21	1.94	1.94	1.93		*	*		*	*		"	"	"
* DATA NOT PRINTED BY TELETYPE													

APPENDIX 1
FP-2 LIFE CYCLE SEPARATOR TEST

BATTERY 13

CYCLE	DISCHARGE FINAL CELL VOLTAGES				HIGH CHG MODE CELL VOLTAGES			LOW CHG MODE CELL VOLTAGES			LOW CHG AH	TOTAL AH	% OVER CHARGE
					LOW	HIGH		LOW	HIGH				
3	1.96	1.96	1.96		2.34	2.36		2.51	2.52		48	140	22
4	1.96	1.96	1.96		2.38	2.39		2.64	2.65		"	"	"
5	1.96	1.96	1.96		2.39	2.40		*	2.68		"	"	"
6	1.95	1.96	1.95		2.38	2.40		*	2.68		"	"	"
7	1.95	1.95	1.95		2.37	2.39		*	2.69		"	"	"
8	1.96	1.96	1.96		2.38	2.40		*	2.69		"	"	"
9	*	*	*		*	*		*	*		"	"	"
10	*	*	*		2.37	2.38		*	2.70		"	"	"
11	1.96	1.97	1.96		2.37	2.39		*	2.70		"	"	"
12	1.95	1.95	1.95		2.37	2.38		2.70	2.71		"	"	"
13	1.96	1.97	1.96		2.38	2.39		2.71	2.72		"	"	"
14	1.94	1.95	1.94		2.37	2.38		2.67	2.68		"	"	"
15	1.96	1.96	1.96		2.40	2.41		2.64	2.66		"	"	"
16	1.96	1.96	1.96		2.39	2.40		2.69	2.70		"	"	"
17	1.96	1.97	1.96		2.38	2.39		*	2.71		"	"	"
18	1.96	1.96	1.96		2.39	2.40		2.71	2.72		"	"	"
19	1.95	1.96	1.95		2.40	2.41		*	2.72		"	"	"
20	1.95	1.96	1.95		2.41	2.42		2.72	2.73		"	"	"
21	1.95	1.95	1.95		*	*		*	*		"	"	"
* DATA NOT PRINTED BY TELETYPE													

APPENDIX 1
FP-2 LIFE CYCLE SEPARATOR TEST

BATTERY 14

CYCLE	DISCHARGE FINAL CELL VOLTAGES				HIGH CHG MODE CELL VOLTAGES			LOW CHG MODE CELL VOLTAGES			LOW CHG AH	TOTAL AH	% OVER CHARGE
					LOW	HIGH		LOW	HIGH				
3	1.95	1.95	1.95		2.38	2.39		*	2.45		48	140	22
4	1.95	1.95	1.95		2.39	2.40		2.47	2.48		"	"	"
5	1.95	1.94	1.95		*	2.40			2.51		"	"	"
6	1.94	1.94	1.94		*	2.41		2.51	2.52		"	"	"
7	1.94	1.93	1.94		2.40	2.41			2.52		"	"	"
8	1.95	1.94	1.96			2.42		2.50	2.51		"	"	"
9	*	*	*		*	*		*	*		"	"	"
10	*	*	*		2.40	2.41		2.51	2.52		"	"	"
11	1.95	1.94	1.95		2.41	2.42		*	2.51		"	"	"
12	1.94	1.93	1.94		2.39	2.41		2.49	2.50		"	"	"
13	1.96	1.95	1.96		2.40	2.41		2.50	2.51		"	"	"
14	1.94	1.93	1.93		2.39	2.40		*	2.49		"	"	"
15	1.95	1.93	1.94		2.42	2.43		*	2.48		"	"	"
16	1.95	1.93	1.94		2.41	2.42		2.49	2.50		"	"	"
17	1.96	1.95	1.96		2.41	2.42		2.52	2.53		"	"	"
18	1.96	1.95	1.95		2.41	2.42		2.52	2.53		"	"	"
19	1.95	1.94	1.95		2.43	2.44		2.53	2.54		"	"	"
20	1.95	1.94	1.94		*	2.44		2.53	2.54		"	"	"
21	1.95	1.94	1.94		*	*		*	*		"	"	"
* DATA NOT PRINTED BY TELETYPE													

APPENDIX 1
FP-2 LIFE CYCLE SEPARATOR TEST

BATTERY 15

CYCLE	DISCHARGE FINAL CELL VOLTAGES				HIGH CHG MODE CELL VOLTAGES			LOW CHG MODE CELL VOLTAGES			LOW CHG AH	TOTAL AH	% OVER CHARGE
					LOW	HIGH		LOW	HIGH				
3	1.95	1.95	1.95		2.37	2.39		2.47	2.49		48	140	22
4	1.95	1.95	1.95		2.38	2.39		2.51	2.61		"	"	"
5	1.96	1.95	1.95		*	2.39		2.57	2.66		"	"	"
6	1.95	1.95	1.95		*	2.40		2.59	2.68		"	"	"
7	1.94	1.94	1.94		2.39	2.40		2.61	2.69		"	"	"
8	1.95	1.95	1.95		2.40	2.42		2.60	2.69		"	"	"
9	*	*	*		*	*		*	*		"	"	"
10	*	*	*		2.39	2.40		2.62	2.70		"	"	"
11	1.95	1.95	1.95		2.40	2.41		2.62	2.70		"	"	"
12	1.95	1.94	1.94		*	2.39		2.61	2.69		"	"	"
13	1.96	1.96	1.96		2.39	2.40		2.63	2.70		"	"	"
14	1.94	1.93	1.94		2.39	2.40		2.55	2.68		"	"	"
15	1.95	1.95	1.95		2.41	2.42		2.53	2.66		"	"	"
16	1.95	1.95	1.95		2.40	2.41		2.60	2.69		"	"	"
17	1.96	1.96	1.96		2.39	2.41		2.65	2.71		"	"	"
18	1.96	1.95	1.96		2.40	2.41		2.65	2.71		"	"	"
19	1.95	1.95	1.95		2.42	2.43		2.67	2.72		"	"	"
20	1.95	1.94	1.95		2.43	2.44		2.67	2.73		"	"	"
21	1.95	1.94	1.95		*	*		*	*		"	"	"
* DATA NOT PRINTED BY TELETYPE													

APPENDIX 1
FP-2 LIFE CYCLE SEPARATOR TEST

BATTERY 16

CYCLE	DISCHARGE FINAL CELL VOLTAGES			HIGH CHG MODE CELL VOLTAGES		LOW CHG MODE CELL VOLTAGES		LOW CHG AH	TOTAL AH	% OVER CHARGE
				LOW	HIGH	LOW	HIGH			
3	1.96	1.96	1.96	2.37	2.38	*	2.48	48	140	22
4	1.96	1.96	1.96	2.39	2.40	2.53	2.56	"	"	"
5	1.96	1.96	1.96	2.40	2.41	2.61	2.65	"	"	"
6	1.95	1.95	1.95	2.40	2.41	2.62	2.65	"	"	"
7	1.94	1.94	1.95	2.39	2.40	2.63	2.66	"	"	"
8	1.95	1.95	1.96	2.41	2.42	2.63	2.66	"	"	"
9	*	*	*	*	*	*	*	"	"	"
10	*	*	*	2.39	2.40	2.64	2.67	"	"	"
11	1.95	1.96	1.96	2.40	2.41	2.64	2.67	"	"	"
12	1.95	1.94	1.95	2.38	2.40	2.63	2.65	"	"	"
13	1.96	1.96	1.96	2.39	2.41	2.64	2.67	"	"	"
14	1.94	1.94	1.94	2.39	2.40	2.55	2.59	"	"	"
15	1.95	1.95	1.95	2.41	2.42	2.52	2.54	"	"	"
16	1.95	1.95	1.95	2.41	2.42	2.61	2.64	"	"	"
17	1.96	1.96	1.96	2.39	2.41	2.64	2.66	"	"	"
18	1.95	1.96	1.96	2.41	2.42	2.65	2.67	"	"	"
19	1.95	1.95	1.95	2.42	2.43	2.66	2.67	"	"	"
20	1.94	1.95	1.95	2.43	2.44	2.66	2.68	"	"	"
21	1.94	1.95	1.94	*	*	*	*	"	"	"
* DATA NOT PRINTED BY TELETYPE										

THIS PAGE
WAS INTENTIONALLY
LEFT BLANK

APPENDIX NO. 2

TP-1 POSITIVE & NEGATIVE GROUP
WEIGHTS & MILLIVOLT DROP TEST RESULTS

THIS PAGE
WAS INTENTIONALLY
LEFT BLANK

APPENDIX 2

POSITIVE & NEGATIVE GROUP WTS & MILLIVOLT DROP TEST RESULTS

EBS No.	Ser. No.	Plate Part No.	Pos. Group Weights			Neg. Group Weights			Welds Millivolts Drop Test at 200 A		
			Pos.	Cells Gms	Neg.	Pos.	Cells Gms	Neg.			
5809	097	85617	3586	3580	3572	2632	2675	2669	0.9	0.8	
"	098	"	3584	3612	3631	2618	2639	2669	1.0	1.1	
"	099	"	3573	3600	3601	2701	2637	2655	1.1	1.4	
"	100	"	3606	3565	3587	2652	2659	2670	1.1	1.0	
5810	101	"	3669	3613	3554	2585	2576	2551	1.4	1.2	
"	102	"	3527	3597	3593	2566	2544	2544	1.4	1.3	
"	103	"	3567	3669	3679	2546	2546	2574	1.2	0.9	
"	104	"	3621	3692	3607	2567	2594	2570	1.1	0.9	
5811	105	"	3614	3545	3603	2593	2549	2591	1.0	1.2	
"	106	"	3577	3554	3565	2591	2535	2573	0.9	1.0	
"	107	"	3581	3613	3581	2589	2588	2595	0.9	0.7	
"	108	"	3574	3641	3704	2591	2539	2605	1.0	1.2	
5812	109	"	3585	3548	3598	2540	2576	2582	1.0	1.3	
"	110	"	3578	3588	3647	2567	2536	2576	0.9	1.1	
"	111	"	3574	3656	3518	2561	2590	2584	0.9	1.1	
"	112	"	3558	3562	3553	2553	2590	2586	0.9	1.0	
5813	113	85195	3644	3760	3741	2607	2684	2636	2.6	1.1	
"	114	"	3701	3695	3737	2646	2664	2647	1.2	1.3	
"	115	"	3745	3735	3728	2641	2628	2640	0.8	1.0	
"	116	"	3629	3760	3747	2648	2639	2650	1.4	1.0	
5814	117	"	3706	3724	3736	2592	2516	2540	0.9	1.1	
"	118	"	3779	3771	3703	2539	2510	2526	0.9	1.1	
"	119	"	3747	3745	3680	2589	2535	2575	1.0	1.1	
"	120	"	3690	3709	3703	2539	2537	2529	1.0	1.1	
5815	121	"	3725	3699	3727	2653	2698	2662	0.8	1.1	
"	122	"	3721	3699	3726	2649	2656	2650	1.6	1.3	
"	123	"	3711	3665	3719	2653	2613	2614			
"	124	"	3737	3669	3733	2616	2632	2636	1.1	0.9	
5816	125	"	3600	3793	3659	2579	2532	2529	0.9	1.1	
"	126	"	3733	3744	3702	2537	2550	2551	1.6	5.3	
"	127	"	3700	3712	3644	2566	2521	2535	1.0	1.3	
"	128	"	3717	3724	3702	2537	2542	2538	1.1	0.9	
Avg. Wt. of 10 Positive Assemblies (Spines, Tubes & Bott. Bar) =									1,340 gm		
Avg. Wt. of 11 Negative Grids =									792 gm		

POSITIVE & NEGATIVE GROUP WTS & MILLIVOLT DROP TEST RESULTS

-196-

APPENDIX 2

POSITIVE & NEGATIVE GROUP WTS & MILLIVOLT DROP TEST RESULTS

EBS No.	Ser. No.	Plate Part No.	Pos. Group Weights			Neg. Group Weights			Welds Millivolt Drop Test at 200 A	
			Pos.	Cells	Gms	Pos.	Cells	Gms		
5825	161	85617	3609	3586	3536	2604	2585	2581	1.1	1.3
"	162	"	3660	3520	3550	2600	2603	2668	1.3	1.1
"	163	"	3688	3708	3633	2589	2590	2666	1.3	1.1
"	164	"	3	3648	3557	2576	2578	2588	1.1	1.4
5826	165	"	3627	3578	3556	2568	2602	2571	1.3	1.1
"	166	"	3641	3607	3650	2602	2601	2608	1.3	1.1
"	167	"	3624	3556	3535	2598	2577	2578	1.3	1.1
"	168	"	3574	3522	3544	2582	2608	2591	1.4	1.2
5827	169	"	3645	3647	3614	2607	2595	2586	1.1	1.6
"	170	"	3553	3584	3616	2565	2605	2571	1.2	1.5
"	171	"	3574	3551	3630	2591	2595	2582	1.3	1.6
"	172	"	3659	3616	3629	2614	2605	2556	1.1	1.4
5828	173	"	3614	3640	3600	2566	2614	2572	1.3	1.2
"	174	"	3636	3557	3636	2587	2583	2601	1.2	1.6
"	175	"	3617	3640	3608	2606	2566	2575	1.1	0.9
"	176	"	3618	3576	3594	2570	2569	2593	0.8	1.1
5829	177	85195	3795	3670	3710	2588	2593	2585	1.4	1.1
"	178	"	3672	3622	3732	2600	2572	2597	1.1	1.4
"	179	"	3717	3730	3720	2554	2591	2510	1.4	1.1
"	180	"	3609	3641	3654	2520	2606	2615	1.2	1.1
5830	181	"	3687	3749	3692	2609	2593	2569	0.8	0.9
"	182	"	3696	3743	3733	2757	2602	2600	1.3	1.2
"	183	"	3730	3675	3649	2539	2600	2615	0.9	1.1
"	184	"	3740	3739	3706	2717	2617	2615	0.9	1.1
5831	185	"	3736	3743	3658	2606	2583	2621	1.1	1.3
"	186	"	3700	3696	3641	2630	2609	2613	1.3	1.2
"	187	"	3669	3658	3772	2611	2591	2611	1.1	1.6
"	188	"	3619	3716	3630	2609	2614	2615	1.3	1.0
"	189	"	3690	3687	3637	2732	2695	2554	1.5	1.2
5832	190	"	3707	3664	3691	2612	2691	2630	1.0	0.9
"	191	"	3730	3701	3741	2598	2667	2604	0.9	1.2
"	192	"	3641	3695	3670	2722	2712	2531	1.3	1.5
Avg. Wt. of 10 Positive Assemblies (spines, tubes & bott. bar)= 1,340 gm.										
Avg. Wt. of 11 Negative Grids= 792 gm										

APPENDIX 2

POSITIVE & NEGATIVE GROUP WTS & MILLIVOLT DROP TEST RESULTS

EBS No.	Ser. No.	Plate Part No.	Pos. Group Weights			Neg. Group Weights			Welds Millivol Drop Test at 200 A			
			Gms			Gms						
			Pos.	Cells Cen.	Neg.	Pos.	Cells Cen.	Neg.				
5833	193	85618		3968	3800	3839		2618	2655	2639	1.4	1.2
"	194	"		3865	3838	3828		2650	2647	2607	1.1	1.3
"	195	"		3812	3805	3778		2667	2633	2630	1.1	1.4
"	196	"		3856	3810	3906		2647	2649	2645	1.3	1.1
5834	197	"		3859	3788	3818		2609	2671	2658	1.2	1.6
"	198	"		3836	3864	3855		2634	2677	2607	1.2	1.5
"	199	"		3819	3845	3829		2657	2659	2677	1.4	1.1
"	200	"		3902	3856	3800		2580	2608	2577	1.4	1.3
5835	201	"		3914	3878	3557		2636	2662	2653	1.1	1.3
"	202	"		3868	3850	3784		2618	2605	2612	1.4	1.1
"	203	"		3804	3899	3808		2569	2637	2604	1.3	1.2
"	204	"		3822	3818	3835		2608	2604	2644	1.3	1.1
5836	205	"		3916	3910	3823		2612	2639	2606	1.2	1.4
"	206	"		3863	3823	3832		2613	2609	2605	1.4	1.2
"	207	"		3926	3838	3857		2610	2638	2606	1.2	1.4
"	208	"		3861	3836	3866		2601	2612	2604	1.1	1.5
5837	209	85616		3851	3896	3911		2632	2621	2656	1.1	1.6
"	210	"		3876	3850	3886		2659	2597	2642	1.4	1.1
"	211	"		3866	3929	3836		2621	2638	2671	1.1	1.4
"	212	"		3915	3835	3841		2590	2587	2617	1.2	1.3
5838	213	"		3857	3890	3858		2625	2605	2671	1.4	1.2
"	214	"		3872	3856	3873		2598	2598	2582	1.3	1.2
"	215	"		3868	3901	3921		2669	2671	2607	1.3	1.2
"	216	"		3847	3891	3889		2602	2620	2637	1.4	1.2
5839	217	"		3886	3884	3864		2605	2624	2672	1.2	1.4
"	218	"		3879	3854	3913		2621	2606	2610	1.2	1.5
"	219	"		3883	3915	3881		2637	2636	2622	1.4	1.1
"	220	"		3873	3855	3855		2641	2623	2650	1.3	1.2
5840	221	"		3868	3882	3925		2601	2582	2599	1.1	1.5
"	222	"		3883	3893	3883		2659	2627	2597	1.2	1.5
"	223	"		3840	3891	3893		2606	2668	2648	1.4	2.0
"	224	"		3922	3810	3927		2657	2656	2605	1.4	1.1
Avg. Wt. of 10 Assemblies (spines, tubes & bott. bar)=1,340 gm.												
Avg. Wt. of 11 Neg. Grids=792 gm.												

Distribution for ANL/OEPM-79-8

Internal:

J. J. Barghusen	D. Fredrickson	M. V. Nevitt
D. Barney	B. R. T. Frost	E. G. Pewitt
C. Bean	E. C. Gay	D. Poa
E. C. Berrill	J. Geller	J. Rajanwitt
R. Biwer	M. Genger	J. J. Roberts
A. Brown	F. Hornstra	M. F. Roche
L. Burris	C. C. Hsu	H. Shimotake
G. Chapman	J. Klinger	R. K. Steunenberg
A. A. Chilenskas	V. Kremesec	C. Swoboda
C. C. Christianson	A. B. Krisciunas	Z. Tomczuk
G. Cook	M. Kronenberg	A. Tumnillo
D. Corp	W. W. Lark	R. Varma
E. Creamer	T. S. Lee	P. D. Vashishta
S. A. Davis	M. Liu	D. R. Vissers
W. DeLuca	R. Loutfy	D. S. Webster
R. C. Elliott	W. Massey	N. P. Yao (44)
M. Farahat	J. Miller	ANL Contract File
P. R. Fields	W. Miller	ANL Libraries
F. Foster	P. A. Nelson	TIS Files (6)

External:

DOE-TIC, for distribution per UC-94ca (318)
Manager, Chicago Operations and Regional Office, DOE
Chief, Office of Patent Counsel, DOE-CORO
V. Hummel, DOE-CORO
J. Purcell, DOE-CORO
Argonne Universities Association
 President
 C. B. Alcock, U. of Toronto
 W. L. Worrell, U. of Pennsylvania
W. Ahmad, KW Battery, Skokie, IL
R. Alkire, University of Illinois, Urbana
M. Allen, Mechanical Technology Inc., Latham, NY
E. T. Ames, TRW Systems, Redondo Beach, CA
L. Andrews, Electric Vehicle Council, Washington, DC
S. J. Angelovich, Mallory Battery Co., Tarrytown, NY
G. M. Arcand, Idaho State University, Pocatello, ID
R. Aronson, Electric Field Propulsion Corp., Troy, MI
G. N. Ault, NASA-Lewis Research Center, Cleveland
J. D. Baker, Stewart Warner Corp., Chicago
W. Bales, Jet Industries, Inc., Austin
H. Balzan, Chattanooga, TN
K. F. Barber, DOE, Office of Transportation Programs, Washington
T. Barber, Jet Propulsion Laboratory, Pasadena

R. J. Barkley, Compass Industries, Inc., Hermosa Beach, CA
 J. W. Barlass, Westinghouse Electric Corp., Skokie, IL
 T. M. Barlow, Lawrence Livermore Lab.
 D. Barron, Delco-Remy Div., GMC, Anderson, IN
 R. Bassett, Sandia Labs, Albuquerque
 W. Bauer, KW Battery, Skokie, IL
 E. Baumann, LILCO, Mineola, NY
 W. C. Beasley, Union Carbide Corporation, New York, NY
 H. Bell, Arizona Public Service Co., Phoenix
 J. Bellack, Cleveland Electric Illuminating Co., Cleveland
 L. Belove, Marathon Battery Corp., Waco, TX
 C. Berlsterling, C. Franklin Institute, Philadelphia
 W. R. Benn, Great Lakes Carbon Corporation, New York, NY
 D. N. Bennion, Brigham Young University, Provo, UT
 C. Berger, Electrochemical & Water Desal. Technology, Santa Ana, CA
 D. Bergmann, GM Transportation Systems Center, Warren, MI
 J. Dink, Electric Power Research Institute, Palo Alto
 W. S. Bishop, Air Force Aero Propulsion Lab, Wright-Patterson AFB
 K. Blurton, Institute of Gas Technology, Chicago
 D. P. Boden, C&D Batteries, Plymouth Meeting, PA
 J. Bolger, University of California, Berkeley
 D. Borello, Die Mesh Corp., Pelham, NY
 A. Borucka, Borucka Research Co., Livingston, NJ
 P. Bowen, C & D Batteries, Plymouth Meeting, PA
 D. Bowman, United States Postal Service, Washington
 J. C. Boylan, Electric Dynamics Corp., Plainwell, MI
 B. J. Bragg, Bell Laboratories, Murray Hill, NJ
 J. Brennand, General Research Corp., Santa Barbara
 A. F. Brewer, Malibu, CA
 D. C. Briggs, Philco-Ford Corp., Palo Alto
 P. Bro, J. R. Mallory & Co., Inc., Burlington, MA
 J. Broadhead, Bell Laboratories, Murray Hill, NJ
 R. Brodd, Union Carbide Corp., Cleveland
 E. P. Broglio, Eagle-Picher Industries, Joplin, MO
 A. D. Brown, EVE Electric Motor Car, Inc., East Lansing, MI
 P. J. Brown, DOE, Office of Transportation Programs, Washington
 R. A. Brown, Eagle-Picher Industries, Joplin, MO
 S. B. Brummer, EIC Corporation, Newton, MA
 R. Duchholz, Honeywell Corp., Minneapolis
 T. Burgess, Lucas Industries, N. A. Inc., Troy, MI
 H. Burghart, Cleveland State University, Cleveland
 D. Burns, Onan Corporation, Minneapolis
 B. W. Burrows, Gould Inc., Rolling Meadows, IL
 M. Burtgon, Delco Remy Div. of GMC, Anderson, IN
 J. D. Busi, USA Foreign Science & Tech. Center, Charlottesville, VA
 E. Buzzelli, Westinghouse Electric Corp., Pittsburgh
 W. P. Cadogan, Emhart Corp., Hartford, CT
 E. Cairns, Lawrence Berkeley Lab.
 E. Campbell, Electric Vehicle Consultants, Inc., New York, NY
 P. Campbell, University of Southern California, Los Angeles
 J. Campbell, DOT/UMTA, Washington, DC
 R. T. Carpenter, Kimberly Clark Corp. Neenah, WI
 T. V. Carvey, Hughes Aircraft Corp., Culver City, CA
 A. Charkey, Energy Research Corp., Danbury, CT

L. D. Christian, General Electric, Gainesville, FL
 R. C. Chudacek, McGraw Edison Co., Bloomfield, NH
 R. Clark, Sandia Labs., Albuquerque
 J. E. Clifford, Battelle Memorial Institute, Columbus
 J. A. Consiglio, Solva-Tek Associates, Topsfield, MA
 A. R. Cook, ILZRO Inc., New York,
 J. E. Cooper, Aero Propulsion Laboratory, Wright-Patterson AFB
 K. E. Cooper, Trojan Battery Co., Santa Fe Springs, CA
 G. Coraor, E. I. Du Pont de Nemours & Co., Inc., Wilmington, DE
 R. E. Corbett, Lockheed Missiles & Space Co., Sunnyvale
 K. E. Cox, University of New Mexico, Albuquerque
 W. W. Craig, Edward Harding and Co., Chicago,
 D. Crane, United States Postal Service, Washington
 R. A. Crawford, PPG Industries, Barberton, OH
 H. H. Crist, AM General Corp., Wayne, MI
 R. H. Dare, Battronic Truck Corp., Boyertown, PA
 D. Davis, Lawrence Livermore Lab.
 R. J. Dawson, ESB Inc., Madison, WI
 J. Devitt, Denver, CO
 A. N. Dey, P. R. Mallory & Co. Inc., Burlington, MA
 G. A. DiBari, INCO, Suffern, NY
 W. J. Dippold, DOE, Office of Transportation Programs, Washington
 T. P. Dirske, Calvin College, Grand Rapids, MI
 D. DiVirgilio, Lockheed Missiles and Space Co., Inc., Sunnyvale, CA
 D. Douglas, Electric Power Research Institute, Palo Alto
 D. Dow, Detroit, MI
 D. Dunoye, Reston, VA
 T. Dwyer, Corning Glass Works, Corning, NY
 E. F. Echolds, AiResearch Manufacturing Co., Torrance, CA
 M. Eisenberg, Electrochimica Corp., Mountain View, CA
 D. B. Eisenhaure, Charles Stark Draper Lab Inc., Cambridge, MA
 T. Eissenberg, Oak Ridge National Lab., Oak Ridge, TN
 M. W. Ellison, Hughes-Aircraft Corp., El Segundo
 D. Elson, Black and Decker Inc., Towson, MD
 R. English, General Battery Co., Reading, PA
 B. Enserik, Dynamic Science, Phoenix
 R. Enters, McGraw Edison Co., Bloomfield, NJ
 H. Espig, Gould Inc., Rolling Meadows, IL
 A. Ewing, DOE, Office of Transportation Programs, Washington
 G. Farbman, Westinghouse Electric Corp., Pittsburgh
 F. Fedor, Bell Laboratories, Murray Hill, NJ
 R. Fedora, Gould Inc., Rolling Meadows, IL
 W. Feduska, Westinghouse Electric Corp., Pittsburgh
 W. H. Fengler, Meteor Research Limited, Roseville, MI
 F. Feres, KW Battery Company, Skokie, IL
 R. Ferraro, Electric Power Research Institute
 D. T. Ferrell, Exide Corporation, Yardley, PA
 E. Fiss, Duke Power Company, Charlotte, NC
 A. Fleischer, Orange, NJ
 C. W. Fleischmann, C&D Batteries, Plymouth Meeting, PA
 R. F. Fogle, North American Rockwell, Anaheim
 R. T. Foley, American University, Washington, DC
 J. S. Fordyce, NASA-Lewis Research Center, Cleveland
 H. A. Fuggiti, Exide Management and Technology Co., Yardley, PA

T. Fujita, Pasadena, CA
 B. Ganji, KW Battery Co., Skokie, IL
 G. Gelb, Advanced Ground Systems, Long Beach, CA
 J. H. B. George, Arthur D. Little, Inc., Concord, MA
 S. Geppert, Eaton Corporation, Southfield, MI
 L. J. Gerlach, United States Postal Service, Rockville, MD
 J. A. Gilchrist, Chloride America, Tampa
 W. Gillespie, Structural Plastics Inc., Tulsa
 C. Glassman, Transportation Research Center, East Liberty, OH
 H. Glixon, Chevy Chase, MD
 M. Globerman, General Services Administration, Washington
 W. Goldman, Electric Vehicle Engineering, Lexington, MA
 G. Goodman, Globe-Union Inc., Milwaukee
 R. E. Goodson, Purdue University
 J. Gould, Unique Mobility Inc., Englewood, CO
 L. B. Gratt, IWG Corp., San Diego
 H. Grépke, TurElec Inc., Bradenton, FL
 D. Griter, Solar Centra, Mechanicsburg, OH
 E. E. Grough, Lucas Industries Inc., Troy, MI
 R. Guess, General Electric Research Lab, Schenectady
 R. G. Gunther, General Motors Research Labs, Warren, MI
 M. Hadden, Billing Energy Corp., Provo, UT
 G. Hagey, DOE, Division of Technology Overview, Washington
 N. Halterm, Chrysler Corporation, Detroit
 H. Hamilton, University of Pittsburgh
 R. Hamilton, Institute for Defense Analysis, Arlington, VA
 W. Hamilton, General Research Corp., Santa Barbara
 B. Hamlen, Exxon Enterprises Inc., Florham Park, NJ
 D. Hanify, Fiat, Chicago
 K. L. Hanson, General Electric Co., Philadelphia
 W. Harhay, Electric Vehicle Associates, Cleveland
 J. H. Harrison, Naval Ship R&D Center, Annapolis, MD
 G. Hartman, Exide Management and Technology Co., Yardley, PA
 J. Hartman, General Motors Research Labs, Warren, MI
 E. A. Heintz, Airso Speer Carbon Graphite, Niagara Falls, NY
 E. V. Hellman, Gould Inc., Langhorne, PA
 R. Heppenstall, Penn Jersey Suburu Inc., Pennsauken, NJ
 A. Himy, Naval Sea Systems Command, Washington
 V. Hlavin, NASA-Lewis Research Center
 G. Hobbib, Exide Management and Technology Co., Cleveland
 A. Hodgman, General Electric, Gainesville
 R. Hoenburg, Mechanical Technology Inc., Latham, NY
 R. Hudson, Eagle-Picher Industries, Joplin, MO
 J. R. Huff, US Army Mobility Equipment R&D Command, Fort Belvoir, VA
 H. L. Hughes, Oklahoma State University, Stillwater, OK
 J. R. Hunt, International Nickel Co., Washington
 H. R. Ivey, Wood-Ivey Systems Corp., Winter Park, FL
 J. Jacus, Moore Haven, FL
 M. A. Janse, Allegheny Power Service Corporation, Greensburg, PA
 G. H. Jantz, Rensselaer Polytechnic Institute
 L. Jenney, Office of Technology Assessment, U.S. Congress, Washington, DC
 A. W. Johnson, General Electric Co., Philadelphia
 F. Johnson, Department of Industry, Trade and Commerce, Ottawa, Canada
 L. Jokl, MERADCOM, Fort Belvoir, VA

K. R. Jones, Thiensville, WI
 W. J. Jones, Westinghouse Electric Corp., Pittsburgh
 R. E. Jordan, Omega Motors Corp., Garden Grove, CA
 D. Kane, National Motors Corp., Lancaster, PA
 E. Kanter, Gulton Battery Corp., Metuchen, NJ
 N. Kaplan, Harry Diamond Laboratories, Washington
 V. Kapur, Arco Solar Inc., Chatsworth, CA
 R. Kaylor, Kaylor Energy Products, Menlo Park
 J. Keith, Kamon Sciences, Colorado Springs, CO
 H. C. Kelly, OTA, U.S. Congress, Washington
 J. G. Kennard, NASA-Lewis Research Center
 R. L. Kerr, Aero Propulsion Lab., Wright Patterson AFB
 J. A. Kerrella, Delco-Remy Division/GMC, Anderson, IN
 R. A. Keyes, Robert A. Keyes Associates, Martinsville, IN
 R. A. Kingery, Oconomowoc, WI
 R. S. Kirk, DOE, Office of Transportation Programs, Washington
 M. Klein, Energy Research Corporation, Danbury, CT
 G. B. Kliman, General Electric Co., Schenectady
 G. B. Klinean, General Electric Co., Schenectady
 R. C. Knechtli, Malibu, CA
 R. A. Knight, AMF Inc., Stamford, CT
 O. R. Kozak, American Battery Corp., Long Beach, NY
 J. G. Krisilas, Aerospace Corporation, El Segundo, CA
 P. E. Krouse, Exide Management & Technology Co., Yardley, PA
 R. R. Kubalek, St. Joe Lead Co., Clayton, MD
 L. Kulin, Whirlpool Corp. Benton Harbor, MI
 C. M. Langkau, Union Carbide Co., Cleveland
 H. Lauve, Electric Auto Corporation, Troy, MI
 J. Lee, RAI Research Corp., Hauppauge, NY
 I. J. Levine, Consolidated Edison, New York
 K. Levine, St. Joe Minerals Corp., Pittsburgh
 H. Lim, Hughes Research Lab., Malibu, CA
 D. Linden, Little Silver, NJ
 E. L. Littauer, Lockheed Palo Alto Research Laboratory
 A. Long, Zeonics Corp., Fairfax, VA
 E. Long, St. Joe Minerals Corp., Monaca, PA
 M. Lugash, Maxon Industries, Huntington Park, CA
 J. T. Lundquist, W. R. Gracc & Co., Columbia, MD
 T. Lynch, Fiber Materials, Inc., Biddeford, ME
 E. N. Mabuice, Union Electric Co., St. Louis
 J. MacDougall, AT&T, Basking Ridge, NJ
 D. E. Mains, Naval Weapons Support Center, Crane, IN
 J. Maisel, Cleveland State University, Cleveland
 J. S. Makulowich, Electric Vehicle Council, Washington
 V. Manson, National Aeronautics and Space Adm., Washington
 L. S. Marcoux, Hughes Aircraft Company, Los Angeles
 K. Marshall, KW Battery Company, Skokie, IL
 T. W. Martin, United States Postal Service, San Bruno, CA
 A. Masters, Packaged Promotions Inc., Chicago
 S. Matsuda, Thermo Electron Corp., Waltham, MA
 C. E. May, NASA-Lewis Research Center, Cleveland
 E. Meeks, Derl Manufacturing Co., Compton, CA
 N. Merriman, Army Picatinny Arsenal, Dover, NJ
 S. Meschkow, Franklin Research Institute, Philadelphia

J. D. Meiggs, Kaman Sciences Corp., Colorado Springs
 P. Mighdoll, Booz-Allen & Hamilton, Cleveland
 R. P. Mikkelsen, General Dynamics, San Diego
 D. G. Miley, U.S. Naval Ammunition Depot, Crane, IN
 H. Miller, Department of Transportation, Cambridge, MA
 D. K. Miner, Copper Development Associates, Birmingham, MD
 L. J. Minnick, Industrial Research Consultant, Plymouth Meeting, PA
 L. G. Morin, Tarrytown, NY
 F. Morse, University of Maryland, College Park
 A. Moss, Leeson Moos Laboratories, Warwick, RI
 R. Mueller, University of California, Berkeley
 J. H. Muir, Dimension V Inc., Indialantic, FL
 J. P. Mullin, National Aeronautics & Space Administration, Washington
 G. Murphy, Northwestern University
 B. McCormick, Los Alamos Scientific Lab.
 L. R. McCoy, Energy Systems Group, Canoga Park
 R. McKee, McKee Engineering, Palatine, IL
 F. McLarnon, Lawrence Berkeley Lab.
 P. McRay, ILC Technology, Sunnyvale
 W. J. Nagle, NASA-Lewis Research Center, Cleveland
 H. V. Nadham, Bogue Batteries, El Segundo
 L. Nalley, Creative Research Co., Roebuck, SC
 J. Newman, Univ. of California, Berkeley
 J. S. Newton, Newton Engineering Co., Glen Ellyn, IL
 M. M. Nickolson, Atomics International Division, Canoga Park
 A. O. Nilsson, NIFE Incorporated, Lincoln, RI
 J. Norberg, Exide Management & Technology Co., Philadelphia
 A. C. Occhipinti, Kenner, LA
 L. G. O'Connell, Lawrence Livermore Lab.
 G. Odom, Georgia Power Company, Atlanta, GA
 R. Oglesby, GM Transportation Systems Ctr., Warren, MI
 L. Omohundro, Kingery Research & Development, Wake Forest, NC
 E. I. Oustott, Los Alamos Scientific Lab
 R. Osteryoung, Colorado State University, Fort Collins
 B. N. Otzinger, North American Aviation, Downey, CA
 J. P. Overman, Hammond Lead Products Inc., Hammond, IN
 J. E. Oxley, Gould Inc., Rolling Meadows, IL
 E. Papandreas, REI, Lake Worth, FL
 J. S. Parkinson, Johns-Manville R&D Center, Manville, NJ
 J. M. Parry, Arthur D. Little Inc., Cambridge, MA
 E. Patagalia, General Services Administration, Washington
 S. Pauling, Naperville, IL
 J. E. Pavolsky, NASA/Lyndon B. Johnson Space Ctr., Houston
 C. Pax, DOE, Office of Transportation Programs, Washington
 E. Pearlman, Exide Management and Technology Co., Yardley, PA
 G. F. Pezdirtz, DOE, Energy Storage Systems, Washington
 A. G. Plunkett, General Electric R&D Center, Schenectady
 R. A. Powers, Union Carbide Corp., Cleveland
 V. J. Puglisi, Yardney Electric Corp., Pawcatuck, CT
 E. Ramirez, Ametran, Dallas
 E. Raskin, USAF Cambridge Research Laboratory, Bedford, MA
 A. D. Raynard, AiResearch Manufacturing Co., Torrance, CA
 E. C. Read, Exxon Enterprises, Linden, NJ
 H. L. Recht, Atomics International Division, Canoga Park

N. Richie, KW Battery Co., Skokie, IL
 C. Ridgway, Walt Disney World Co., Lake Buena Vista, FL
 E. Rizkalla, DOE, Office of Controller, Washington
 R. A. Rizzo, Globe-Union Inc., Milwaukee
 R. Robert, The MITRE Corporation, McLean, VA
 F. T. Rooney, Bureau of Automotive Maintenance, Norfolk, VA
 L. Rosenblum, NASA-Lewis Research Center, Cleveland
 N. Rosenburg, Department of Transportation, Cambridge, MA
 R. Rosey, Westinghouse Electric Corp., Pittsburgh
 J. Rossmon, Cornell University
 G. Rowland, General Electric, Schenectady
 J. Rubenzer, NASA-Ames Research Center, Moffett Field
 P. H. Rubie, Electric Passenger Cars, Inc., San Diego
 H. E. Ruskie, Naval Intelligence Support Center, Washington
 A. J. Salkind, Exide Management & Technology Co., Yardley, PA
 R. Schmidt, Volkswagen of America Inc., Englewood Cliffs, NJ
 R. T. Schneider, RTS Laboratories, Gainesville, FL
 L. W. Schopen, NASA-Lewis Research Center, Cleveland
 H. J. Schwartz, NASA-Lewis Research Center, Cleveland
 W. R. Scott, TRW Systems Inc., Redondo Beach
 H. Seigel, South Coast Technology Inc., Santa Barbara
 H. Seiger, Harvey Seiger Associates, Waterford, CT
 J. Seliber, Fluid Drive Engineering Co., Wilmette, IL
 E. Seo, Gates Energy Products, Denver, CO
 L. Shahnasarian, Elcar Corp., Elkhart, IN
 R. C. Shair, CENTREC Corporation, Fort Lauderdale
 H. Shalit, ARCO Chemical Corp., Glendolden, PA
 D. W. Sheibley, NASA-Lewis Research Center, Cleveland
 E. Small, Amectran Corporation, Washington
 G. A. Smith, Englehard Industries, Iselin, NJ
 S. Smith, St. Joe Minerals Corp., Monaca, PA
 V. Smith, Delco-Remy Div. GMC, Anderson, IN
 J. Smits, Nevada Operations Office, Las Vegas, NV
 I. J. Soloman, IIT Research Institute, Chicago
 W. C. Spindler, Electric Power Research Institute, Palo Alto
 J. S. Stanley, Dept. of the Army, U.S. Army Foreign Sci. & Tech. Center,
 Charlottesville, VA
 E. J. Steeve, Commonwealth Edison Co., Chicago
 I. Stein, Jet Propulsion Laboratory, Pasadena
 T. A. Stoneham, Marathon Battery Company, Waco, TX
 R. Strauss, Communications Satellite Corp., Clarksburg, MD
 W. E. Strawbridge, Caterpillar Tractor Co., Peoria, IL
 R. L. Strombotne, Transportation Systems Center, Cambridge, MA
 S. Sudar, Rockwell International, Canoga Park
 P. C. Symons, Energy Development Associates, Madison Heights, MI
 F. Tepper, Catalyst Research Corp., Baltimore
 R. Thacker, General Motors Research Labs, Warren, MI
 C. E. Thomas, Chrysler Corp., New Orleans, LA
 F. Thomas, Grumman Aerospace Corp., Bethpage, NY
 G. M. Thur, DOE, Office of Transportation Programs, Washington
 W. H. Tiedemann, Globe-Union Inc. Milwaukee, WI
 C. W. Tobias, University of California, Berkeley
 M. Thorpe, Towson, MD
 A. Topouzian, Ford Motor Co., Dearborn, MI

W. Toth, Society of Automotive Engineers, Inc., Warrendale, PA
 H. Toulmin, Bloomfield, MI
 I. Trachtenberg, Texas Instruments, Dallas
 G. W. Tuffnell, The International Nickel Co., Troy, MI
 D. Turford, Western Mining Corp., Pittsburgh
 G. H. Turney, Western Research Industries, Las Vegas, NV
 E. A. Ulrich, Creative Automotive Research, Whittier, CA
 R. L. Ulrich, General Services Administration, Washington
 T. Ulrich, McGraw-Edison Co., Bloomfield, NJ
 G. Underhill, A. D. Little, Cambridge, MA
 H. B. Urbach, Naval Ship R&D Center, Annapolis, MD
 H. Vaidyanathan, Energy Research Corp., Danbury, CT
 C. J. Venuto, C&D Batteries, Plymouth Meeting, PA
 S. W. Vreeland, General Dynamics, Convair Division, San Diego
 A. Waddell, EBCO Battery Co., Columbus, GA
 E. H. Wakefield, Linear Alpha Inc., Evanston, IL
 R. Walker, University of Florida, Gainesville
 C. H. Waterman, C. H. Waterman Industries, Althol, MA
 G. Way, Troy, MI
 W. Webster, DOE, Division of Energy Storage Systems, Washington
 R. D. Wehrle, Sandia Labs, Albuquerque, NM
 C. Weinlein, Globe-Union Inc., Milwaukee
 S. A. Weinter, Ford Motor Co., Detroit, MI
 M. Weinreb, Consolidated Edison, New York
 E. Y. Weissman, GASF Wynadotte Corp., Wynadotte, MI
 I. Wender, Bureau of Mines, Pittsburgh, PA
 H. B. West, McGraw-Edison Company, Bloomfield, NJ
 M. E. Wilke, Burgess Battery Company, Freeport, IL
 R. Wilks, Lavelle Aircraft Co., Newton, PA
 C. F. Williams, Teledyne Isotopes, Timonium, MD
 H. R. Williams, Detroit Edison Co., Detroit
 J. M. Williams, E. I. DuPont de Nemours & Co., Wilmington, DE
 E. Willhnganz, C&D Batteries, Plymouth Meeting, PA
 N. L. Willmann, Delco-Remy Div. of GMC, Anderson, IN
 R. Willow, Office of Technology Assessment, U.S. Congress, Washington, DC
 J. F. Wing, Booz-Allen & Hamilton Inc., Bethesda, MD
 K. Winters, Chrysler Corp., New Orleans, LA
 T. J. Wissing, Eaton Corp., Southfield, MI
 J. Wooldrige, Boeing Corp., Seattle
 V. Wouk, Petro-Electric Motor Ltd., New York
 R. A. Wynveen, Life Systems Inc., Cleveland
 L. S. Yao, University of Illinois, Urbana
 H. Yoder, Batronic Truck Corp., Boyertown, PA
 M. Yontar, Jersey City, NJ
 J. E. Zanks, NASA-Langley Research Center, Hampton, VA