This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

SLAC/AP--11

DE84 005895

SLAC/AP-11
January 1984
(AP)

THE SECOND ORDER PARTICLE MOTION EQUATIONS
AND
LINEAR CHROMATICITY CALCULATION
IN ACCELERATOR RINGS*

R. Z. Liu⁺

Stanford Linear Accelerator Center
and
Stanford Synchrotron Radiation Laboratory
Stanford University, Stanford, California 94305

A. Introduction

1.) Several recently published papers^{1),2)} deal with CHR (chromaticity) calculation after it was found that some first order factors, which had been ignored by the relevant work done before, turned out to be important for small rings. Taking into account the effects of bending magnets and magnet edges (inclined and/or curved), these papers made surely a great improvement on the problem. However, their results are somehow different from each other and something seems confusing to the author concerning a general expression of the second order particle motion equations, especially for the edge effects. This note joins the discussion with an approach which is similar to that in Ref.1) but results in different formulae.

* Work supported by the Department of Energy, contracts DE-AC03-76SF00515 (SLAC) and DE-AC03-82ER13000 (SSRL).

+ Visiting physicist from the National Synchrotron Radiation Lab., the University of Science & Technology of China, Hefei, China.

MASTER

DISTRIBUTION OF THIS DOCUMENT IS UNLIMITED

2.) The first part of this note presents a thorough study on the second order particle motion equations, both in continuous field and in "hard edges", with emphasis put on the latter. Having quite general conditions and strict mathematical treatments, it provides a sound ground from which many problems can be solved without fear of being misled. Then the linear CHR calculation will be inspected, the first step being a general analytical expression of the transverse oscillation phase increment due to a small disturbance. The expression for the CHR is then readily obtained since tune is the transverse oscillation number per turn and the CHR is the linear dependence of the tune on particle energy/momentum deviation. The last part will give the formulae for practical CHR calculation, which are general enough to include almost all the magnet types commonly used in various accelerator rings and are simpler than can be found elsewhere.

3.) It is noteworthy that some aspects of the CHR calculation are quite similar to those of eta (dispersion) function distortion. Though only intending to find a first order dependence on energy deviation, one has to begin with the second order equations for the both problems. Both of them see sextupoles play a role and see something associated with bending magnets and magnet edges was ignored for a time but may be significant for small rings, though really trivial in big machines. So another note of the author, Ref.3), can be regarded as a sister note of this one. A comparison between the two problems, the CHR calculation and eta function distortion, is interesting.

4.) The following assumptions are taken throughout this note:

a) Single particle (zero current) model. So no interaction between particles or between a particle and its environment is considered.

b) No electric field in the part of orbit to be studied, no particle energy change and no time dependence of magnetic field.

c) In most cases, the ideal orbit lies in a plane, so that a natural orthogonal coordinate system x - y - z , with y -axis fixed vertically, can be referred to and the field components B_x and B_z near the median plane are zero everywhere except in special or misaligned magnets.

c) Particle parameters x , x' , y , y' and δ are small quantities.

d) Hard edge approximation.

B. Second Order Differential Equations in Continuous Magnetic Field

1.) Description of Particle Motion:

Let the natural orthogonal coordinate system (curvilinear system) be adopted and all the symbols, if not specially defined, be conventional such as: azimuthal coordinate z , horizontal displacement x and slope x' , vertical displacement y and slope y' , particle momentum p and the nominal momentum p_0 , momentum deviation $\delta = (p - p_0)/p_0$, ideal orbit curvature radius ρ , particle rigidity $(B\rho)_0 = p_0/e$, and the unit vectors along the three coordinate axes $\vec{e}_x$, $\vec{e}_y$ and $\vec{e}_z$. For highly relativistic electrons, $p = E/c$ and therefore δ is also the energy deviation. ρ is associated with the coordinate system and dependent on z only.

Then the position (x, y, z) of a particle can be described by a vector

$$\vec{r} = \vec{r}_0(z) + x \vec{e}_x + y \vec{e}_y \quad (B-1)$$

where $\vec{r}_0$ corresponds to the point $(0, 0, z)$. Since

$$d\vec{r}_0 = dz \vec{e}_z; \quad d\vec{e}_x = \frac{dz}{\rho} \vec{e}_z; \quad d\vec{e}_y = 0; \quad d\vec{e}_z = -\frac{dz}{\rho} \vec{e}_x;$$

the particle velocity is obtained as

$$\vec{v} = \frac{d\vec{r}}{dt} = \frac{dz}{dt} \left(\left(1 + \frac{x}{\rho} \right) \vec{e}_z + x' \vec{e}_x + y' \vec{e}_y \right) \quad (B-2)$$

Define $\beta_z = (dz/dt) / |\vec{v}|$ and $\Omega = \beta_z' / \beta_z$. It is easy to give

$$\frac{1}{\beta_z} = \left(\left(1 + \frac{x}{\rho} \right)^2 + x'^2 + y'^2 \right)^{1/2} = 1 + \frac{x}{\rho} + \frac{x'^2}{2} + \frac{y'^2}{2} + \dots \quad (B-3)$$

And the acceleration of the particle is given by

$$\begin{aligned} \frac{d\vec{v}}{dt} = & \beta_z^2 |\vec{v}|^2 \left(\left(\frac{2x'}{\rho} + x \left(\frac{1}{\rho} \right)' + \Omega \left(1 + \frac{x}{\rho} \right) \right) \vec{e}_z \right. \\ & \left. + \left(x'' - \frac{1}{\rho} \left(1 + \frac{x}{\rho} \right)' + \Omega x' \right) \vec{e}_x + \left(y'' + \Omega y' \right) \vec{e}_y \right) \end{aligned} \quad (B-4)$$

The particle motion equation in this case is well known as

$$\frac{d}{dt} (m \vec{v}) = e \vec{v} \times \vec{B}$$

with the magnetic field $\vec{B} = B_x \vec{e}_x + B_y \vec{e}_y + B_z \vec{e}_z$.

So one can readily get three equations after several substitutions :

$$\frac{2x'}{\rho} + x \left(\frac{1}{\rho} \right)' + \Omega \left(1 + \frac{x}{\rho} \right) = \frac{1}{(1+\delta)\beta_z} \left(\frac{B_y}{(B\rho)_0} x' - \frac{B_x}{(B\rho)_0} y' \right) \quad (B-5)$$

$$x'' = \frac{1}{\rho} \left(1 + \frac{x}{\rho} \right) + \frac{1}{(1+\delta)\beta_z} \left(\frac{B_z}{(B\rho)_0} y' - \frac{B_y}{(B\rho)_0} \left(1 + \frac{x}{\rho} \right) \right) - \Omega x' \quad (B-6)$$

$$y'' = \frac{1}{(1+\delta)\beta_z} \left(\frac{B_x}{(B\rho)_0} \left(1 + \frac{x}{\rho} \right) - \frac{B_z}{(B\rho)_0} x' \right) - \Omega y' \quad (B-7)$$

Eq. (B-5) establishes the relation between β_z' and the magnetic field. Combined with this relation and the displacement-dependence of the field, Eqs. (B-6) and (B-7) give the differential equations, which describe the particle motion in x and in y planes respectively, up to any order.

2.) Displacement dependence of the field:

Any component B_u ($u = x, y$ or z) of a continuous magnetic field near the ideal orbit can be written as

$$B_u = B_{u0} + x \left(\frac{\partial B_u}{\partial x} \right)_0 + y \left(\frac{\partial B_u}{\partial y} \right)_0 + \frac{x^2}{2} \left(\frac{\partial^2 B_u}{\partial x^2} \right)_0 + xy \left(\frac{\partial^2 B_u}{\partial x \partial y} \right)_0 + \frac{y^2}{2} \left(\frac{\partial^2 B_u}{\partial y^2} \right)_0 + \dots$$

where the subscript 0 denotes the value at $\vec{r}_0(0,0,z)$, i.e. on the ideal orbit. This is why the derivatives with respect to z do not appear in the above expression and the functions B_{u0} , $\left(\frac{\partial B_u}{\partial x} \right)_0$, etc. depend on z only.

In the coordinate system adopted here, Maxwell's equations, $\nabla \cdot \vec{B} = 0$ and $\nabla \times \vec{B} = 0$, take the following appearance :

$$\left(1 + \frac{x}{\rho} \right) \left(\frac{\partial B_x}{\partial x} + \frac{\partial B_y}{\partial y} \right) + \frac{\partial B_z}{\partial z} + \frac{B_x}{\rho} = 0$$

$$\left(1 + \frac{x}{\rho} \right) \frac{\partial B_z}{\partial y} = \frac{\partial B_y}{\partial z} ; \quad \left(1 + \frac{x}{\rho} \right) \frac{\partial B_z}{\partial x} + \frac{B_z}{\rho} = \frac{\partial B_x}{\partial z} ; \quad \frac{\partial B_y}{\partial x} = \frac{\partial B_x}{\partial y}$$

The relations involving the field components and their derivatives of any order can be derived from these equations.

For brevity, a few symbols are defined as follows:

Dipole component $\frac{1}{f_B} = \frac{B_{y0}}{(B\rho)_0}$, therefore $(\frac{1}{f_B})' = \frac{1}{(B\rho)_0} (\frac{\partial B_y}{\partial z})_0$.

Usually $f_B = f$, but there may be difference between them in some cases. The subscript B helps avoid possible confusion.

Quadrupole component $K = \frac{1}{(B\rho)_0} (\frac{\partial^2 B_y}{\partial x^2})_0 = \frac{1}{(B\rho)_0} (\frac{\partial^2 B_x}{\partial y^2})_0$.

Sextupole component $\lambda = \frac{1}{(B\rho)_0} (\frac{\partial^3 B_y}{\partial x^3})_0 = \frac{1}{(B\rho)_0} (\frac{\partial^3 B_x}{\partial x \partial y^2})_0$.

In addition to these three most important components, we define :

vertical dipole component $g_y = \frac{B_{x0}}{(B\rho)_0}$; solenoid component $g_s = \frac{B_{z0}}{(B\rho)_0}$;

rotated quadrupole components $h_H = \frac{1}{(B\rho)_0} (\frac{\partial^2 B_y}{\partial y^2})_0$ and $h_V = \frac{1}{(B\rho)_0} (\frac{\partial^2 B_x}{\partial x^2})_0$;

rotated sextupole component $\lambda_R = \frac{1}{(B\rho)_0} (\frac{\partial^3 B_x}{\partial y^3})_0 = \frac{1}{(B\rho)_0} (\frac{\partial^3 B_y}{\partial x \partial y^2})_0$;

solenoid gradient $h_s = \frac{1}{(B\rho)_0} (\frac{\partial B_z}{\partial x})_0$; and other second order derivatives

$\lambda_H = \frac{1}{(B\rho)_0} (\frac{\partial^3 B_y}{\partial y^3})_0$ and $\lambda_V = \frac{1}{(B\rho)_0} (\frac{\partial^3 B_x}{\partial x^3})_0$. Maxwell's equations tell how

these components are related to each other, such as

$$h_V + h_H + g_s' + \frac{g_y}{f} = 0 ; \quad h_s + \frac{g_s}{f} = g_y' ;$$

$$\lambda_H = - \left(\lambda + \frac{K}{f} + \left(\frac{1}{f_B} \right)'' \right) ;$$

$$\lambda_V = - \left(\lambda_R + \frac{2}{f} h_V + \frac{1}{f} h_H + h_s' \right) .$$

With the above symbols, the first terms of the field expressions are

$$\begin{aligned} B_y &= (B\rho)_0 \left(\frac{1}{\rho_B} + Kx + h_H y + \frac{\lambda}{2} x^2 + \lambda_R xy + \frac{\lambda_H}{2} y^2 + \dots \right) ; \\ B_x &= (B\rho)_0 \left(g_y + h_V x + Ky + \frac{\lambda_V}{2} x^2 + \lambda_{xv} + \frac{\lambda_R}{2} y^2 + \dots \right) ; \\ B_z &= (B\rho)_0 \left(g_S + h_S x + \left(\frac{1}{\rho} \right)' y + \dots \right) \end{aligned} \quad (B-8)$$

3.) Note that the second order terms of B_y and B_x , but only the first order terms of B_z and Ω are useful, if one's interest is limited to no higher than second order. Eq. (B-5) turns out to be

$$\Omega = -x \left(\frac{1}{\rho} \right)' + \left(\frac{1}{\rho_B} - \frac{2}{\rho} \right) x' - g_y y' + \dots \quad (B-9)$$

This equation can also be found from directly differentiating Eq. (B-3) with respect to z , if one is aware that y'' has a zeroth order term g_y and x'' has zeroth order terms $\left(\frac{1}{\rho} \right) - \left(\frac{1}{\rho_B} \right)$.

Now it is not difficult for one to insert Eqs. (B-3), (B-8) and (B-9) into Eqs. (B-6) and (B-7) to obtain

$$\begin{aligned} x'' &= \frac{1}{\rho} - \frac{1}{\rho_B} - \left(K + \frac{1}{\rho} \left(\frac{2}{\rho_B} - \frac{1}{\rho} \right) \right) x + \frac{\delta}{\rho_B} - h_H y + g_S y' \\ &\quad - \left(\frac{\lambda}{2} + \frac{2K}{\rho} + \frac{1}{\rho^2 \rho_B} \right) x^2 - \left(\lambda_R + \frac{2}{\rho} h_H \right) xy - \frac{\lambda_H}{2} y^2 \\ &\quad + \left(K + \frac{2}{\rho \rho_B} \right) \delta x - \frac{\delta^2}{\rho_B} + h_H \delta y - g_S \delta y' + \left(\frac{1}{\rho} \right)' xx' + \left(\frac{1}{\rho_B} \right)' yy' \\ &\quad + \left(h_S + \frac{g_S}{\rho} \right) xy' + g_y x'y' + \left(\frac{2}{\rho} - \frac{3}{2\rho_B} \right) x'^2 - \frac{1}{2\rho_B} y'^2 + \dots ; \\ y'' &= g_y + Ky - g_y \delta + \left(h_V + \frac{2}{\rho} g_y \right) x - g_S x' + \frac{\lambda_R}{2} y^2 \\ &\quad + \left(\lambda + \frac{2K}{\rho} \right) xy + \left(\frac{\lambda_V}{2} + \frac{2}{\rho} h_V + \frac{g_y}{\rho^2} \right) x^2 - K\delta y + g_y \delta^2 \\ &\quad - \left(h_V + \frac{2}{\rho} g_y \right) \delta x + g_S \delta x' + \left(\frac{1}{\rho} \right)' xy' - \left(\frac{1}{\rho_B} \right)' x'y \\ &\quad - \left(h_S + \frac{g_S}{\rho} \right) xx' + \left(\frac{2}{\rho} - \frac{1}{\rho_B} \right) x'y' + \frac{3y}{2} x'^2 + \frac{3g_y}{2} y'^2 + \dots \end{aligned} \quad (B-10)$$

Eq.(B-10) is the most general expression of the second order particle motion equations in continuous magnetic field, given the assumptions in section A stand true. They can serve various purposes after adapted according to various situations.

For example, if magnet errors are being dealt with, only the first order terms are taken into account and one can define horizontal extra dipole component as $g_x = (1/\rho) - (1/\rho_B)$; in non-bending elements, $(1/\rho) = 0$; in orbit steering magnets, $g_x \neq 0$ or $g_y \neq 0$; in rotated quadrupoles, $h_V = -h_H \neq 0$; $g_S \neq 0$ in solenoids and $h_H = h_V = -\frac{1}{2} g_S$ at their edges.

4.) The most common situation in accelerator rings is that there exists a median (symmetric) plane in which the ideal orbit lies and $B_x = B_z = 0$ at any point. Therefore, ignoring magnet errors, one can expect that g_y , g_S , h_H , h_V , h_S , λ_R and λ_V are all zero along the ideal orbit. Eq.(B-10) is then changed to

$$\begin{aligned} x'' = & \frac{1}{\rho} - \frac{1}{\rho_B} - \left(K + \frac{1}{\rho} \left(\frac{2}{\rho_B} - \frac{1}{\rho} \right) \right) x + \frac{\delta}{\rho_B} - \left(\frac{\lambda}{2} + \frac{2K}{\rho} + \frac{1}{\rho^2 \rho_B} \right) x^2 \\ & + \frac{1}{2} \left(\lambda + \frac{K}{\rho} + \left(\frac{1}{\rho_B} \right)'' \right) y^2 + \left(K + \frac{2}{\rho \rho_B} \right) \delta x - \frac{\delta^2}{\rho_B} + \left(\frac{1}{\rho} \right)' x x' \\ & + \left(\frac{1}{\rho_B} \right)' y y' + \left(\frac{2}{\rho} - \frac{3}{2 \rho_B} \right) x'^2 - \frac{1}{2 \rho_B} y'^2 + \dots ; \\ y'' = & K y + \left(\lambda + \frac{2K}{\rho} \right) x y - K \delta y + \left(\frac{1}{\rho} \right)' x y' - \left(\frac{1}{\rho_B} \right)' x' y \\ & + \left(\frac{2}{\rho} - \frac{1}{\rho_B} \right) x' y' + \dots \end{aligned} \quad (B-11)$$

Eq.(B-11) maintains the distinction between ρ and ρ_B for convenience of use in some special cases. For example, ρ and ρ_B both change, but not simultaneously, near an inclined edge; ρ_B differs from ρ in horizontal correctors; and, if the consideration is extended to higher order of energy deviation for off-energy particles, one has to keep in mind that ρ_B can be regarded as to vary with energy but ρ cannot.

However, ρ_B equals to ρ in most cases. Let $\rho_B = \rho$, then one has

$$\begin{aligned}
 x'' &= -\left(K + \frac{1}{\rho^2}\right)x + \frac{\delta}{\rho} - \left(\frac{\lambda}{2} + \frac{2K}{\rho} + \frac{1}{\rho^3}\right)x^2 + \left(K + \frac{2}{\rho^2}\right)\delta x \\
 &\quad + \frac{1}{2}\left(\lambda + \frac{K}{\rho} + \left(\frac{1}{\rho}\right)''\right)y^2 - \frac{\delta^2}{\rho} + \left(\frac{1}{\rho}\right)'xx' + \left(\frac{1}{\rho}\right)'yy' \\
 &\quad + \frac{1}{2\rho}x'^2 - \frac{1}{2\rho}y'^2 + \dots; \\
 y'' &= Ky + \left(\lambda + \frac{2K}{\rho}\right)xy - K\delta y + \left(\frac{1}{\rho}\right)'xy' - \left(\frac{1}{\rho}\right)'x'y \\
 &\quad + \frac{1}{\rho}x'y' + \dots
 \end{aligned} \tag{B-12}$$

These two equations are known to accelerator physicists for a long time. Readers can find formulae equivalent to them, though in different forms, in Refs.1), 2) and even earlier publications, Ref.4) as an example.

Furthermore, for a normally designed magnet element, the field is piecewise constant, that is, $\rho' = 0$ within the magnet. So one gets

$$\begin{aligned}
 x'' &= -\left(K + \frac{1}{\rho^2}\right)x + \frac{\delta}{\rho} - \left(\frac{\lambda}{2} + \frac{2K}{\rho} + \frac{1}{\rho^3}\right)x^2 + \left(K + \frac{2}{\rho^2}\right)\delta x \\
 &\quad + \frac{1}{2}\left(\lambda + \frac{K}{\rho}\right)y^2 - \frac{\delta^2}{\rho} + \frac{1}{2\rho}x'^2 - \frac{1}{2\rho}y'^2 + \dots; \\
 y'' &= Ky + \left(\lambda + \frac{2K}{\rho}\right)xy - K\delta y + \frac{1}{\rho}x'y' + \dots
 \end{aligned} \tag{B-13}$$

for particle motion within a magnet (except the edges), in the assumption that the field varies with azimuthal positions at the magnet edges only. Now it's easy to give the first and/or second order equations for all the commonly used magnet types, such as pure quadrupoles, pure sextupoles, bending magnets with/without transverse gradient, etc.

One special case is vertical bending magnets. Suppose the condition is similar to what is proper to Eq. (B-13) but the bending is on the vertical plane only. A 90 degree rotation of the coordinate system and a subsequent x-y substitution yield

$$\begin{aligned} x'' &= -Kx + \frac{2K}{\rho_y} xy + K\delta x - \frac{1}{\rho_y} x'y' + \dots ; \\ y'' &= \left(K - \frac{1}{\rho_y^2}\right)y - \frac{\delta}{\rho_y} - \left(\frac{2K}{\rho_y} - \frac{1}{\rho_y^3}\right)y^2 + \left(-K + \frac{2}{\rho_y^2}\right)\delta y \\ &\quad + \frac{\delta^2}{\rho_y} + \frac{K}{2\rho_y}x^2 - \frac{1}{2\rho_y}y'^2 + \frac{1}{2\rho_y}x'^2 + \dots \end{aligned} \quad (B-14)$$

where $(1/\rho_y) = -B_{x0}/(B\rho)_0$ is supposed piecewisely constant, K is the same as in the previous equations, B_{y0} and all the sextupole components are supposed to be zero.

C. Main Principles on Hard Edge Effects

1.) A hard edge of a magnet is described by inclining angle θ_e and curving radius r_e as shown on right. The hard edge assumption means that $\vec{B}$ is zero outside the magnet (in drift sections), and that $\vec{B}$ takes the inside magnet value immediately within the effective edges. In the following statements, ρ and all the field components such as $1/\rho_B$ and K are those inside the magnet in question and we will let $\rho_B = \rho$ eventually.

Fig.1 Sign conventions of θ_e , r_e and ρ are all positive as shown above.

2.) Hard edge effects are described in terms of parameter increments Δu (here u is x , x' , y or y'). Δu can be found by formulae containing u_b , the parameter values just before the particle passes the edge, together with the magnet field components and the edge characteristics, θ_e and r_e . The following work will concentrate on deriving those formulae.

The increments are understood as the effect of an impact of the edge field on particle motion. Suppose one is studying particle motion with a tracking program based on the equations in the last section. They are quite accurate within elements where the field is continuous and so all the derivatives are finite. But they don't work at hard edges where some derivatives are infinite. The increments are therefore needed and will work in this way: let z_0 be the nominal z-coordinate of the edge and z the z-coordinate of the particle; track the particle by the preceding equations in region $z < z_0$ to get u_b , make $u = u_b + \Delta u$ when $z = z_0$ and continue tracking in region $z > z_0$; one will then obtain a particle trajectory that agrees accurately with the real trajectory downstream of the edge area. By "accurately" we mean "to second order". Mathematically, expressions of Δu represent the edge effects and, combined with the equations in section B, provide a complete second order description of the particle motion.

Note that the effective magnet edge is not always identical to the "coordinate edge" where $z = z_0$, if θ_e and/or $(1/r_e)$ is not zero. Because $(1/\rho)'$ is infinity at coordinate edges and B_{y0}' is infinity at magnet edges, Δu arises from both kinds of them. The expressions of Δu should take both into account and have a uniform formularization, no matter which edge is passed first. However, the work will be done at each edge (entrance or exit) twice, with the coordinate edge passed first and with the magnet edge passed first respectively, since the procedures to derive Δu in the two situations are quite different and might be confusing. No special attention is paid to "normal edges". If one makes $\theta_e = (1/r_e) = 0$, the formulae will degrade automatically to those for normal edges.

The procedures are as follows:

Suppose the coordinate edge is passed first as shown in Fig.2 (a).

The real trajectory is from point "b" (just before $z = z_0$), via "3" (just after $z = z_0$) and "4" (just before the magnet edge), to "5" (just after the magnet edge) and then forward. One can make an imaginary back step from "5" to "a" (just after $z = z_0$) in an imaginary field which is described by the same formula as at point "5".

Fig.2 (b) shows the other case in which the magnet edge is passed first. Similarly, the real trajectory is from "3", via "4" and "5", to "a" (again, just after $z = z_0$). The magnet edge is crossed between "3" and "4" and the coordinate edge crossed between "5" and "a". An imaginary back step should be taken from "b" (again, just before $z = z_0$) to "3".

Subscripts b, a, 3, 4 and 5 are used to denote where the parameter values are taken. In either case,

$$\Delta u = u_a - u_b = f(u_b, \theta_e, r_e, \rho, \dots).$$

It is clear that the above procedures agree with the understanding of Δu . Suppose one can see particles travelling and he thinks that the magnetic field changes suddenly at z_0 . To his knowledge of particle motion, a particle which is seen far upstream of the edge is expected to arrive at "b" and have u_b as its parameters. But, when it is far downstream, it looks as if it left the edge at "a" with parameters u_a . So in his imagination, the particle jumped from "b" to "a" and parameters u got increments Δu at the moment it passed the edge. As long as the expressions for Δu are correct, such an understanding is well equivalent to what really happened.

Fig.2 Definition of subscripts b,a,etc. in two cases.

3.) Suppose particle motion in magnets can be described by Eq.(B-11). This is true in most cases, where a magnetic median plane exists. Two possibly important exceptions are effects of vertical bending magnet edges and solenoid edges. The expressions for these two kinds of edge effects will be given at the end of next section without derivation.

Except for the edges, the first order particle motion equations are

$$x'' = \frac{1}{\rho} - \frac{1}{\rho_B} - \left(K + \frac{1}{\rho} \left(\frac{2}{\rho_B} - \frac{1}{\rho} \right) \right) x + \frac{\delta}{\rho_B} + \dots ;$$

$$y'' = K y + \dots \quad (C-1)$$

From Eq.(C-1) one can get 4 formulae for the small sectors between the magnet edge and the coordinate edge, either actually or imaginatively,

$$x_f = x_i + x'_i \cdot \Delta z + \frac{1}{2} \left(\frac{1}{\rho} - \frac{1}{\rho_B} \right) \cdot (\Delta z)^2 + \dots ;$$

$$y_f = y_i + y'_i \cdot \Delta z + \dots ;$$

$$x'_f = x'_i + \left(\frac{1}{\rho} - \frac{1}{\rho_B} - \left(K + \frac{1}{\rho} \left(\frac{2}{\rho_B} - \frac{1}{\rho} \right) \right) x_i + \frac{\delta}{\rho_B} \right) \cdot \Delta z + \dots ;$$

$$y'_f = y'_i + K y_i \cdot \Delta z + \dots \quad (C-2)$$

where Δz is the azimuthal coordinate increment covered by the particle, subscript f denotes the final value and i the initial value, respectively, as Δz is got through. Since Δz is a first order small quantity, almost equal to $x_b \cdot \tan \theta_e$ as will be seen, and since higher than second order effects are excluded from consideration, Eq.(C-2) is appropriate to solve u_f in this case.

And, when an edge of any kind is passed, changes in the parameters are expected as

$$x_f = x_i + \int_{\Delta z} x' d\bar{z} ; \quad y_f = y_i + \int_{\Delta z} y' d\bar{z} ;$$

$$x'_f = x'_i + \int_{\Delta z} x'' d\bar{z} ; \quad y'_f = y'_i + \int_{\Delta z} y'' d\bar{z} \quad (C-3)$$

where x'' and y'' can be replaced by using Eq.(B-11) or (B-10), or even more originally, Eqs.(B-6) and (B-7). Δz is a very small distance across the edge, in most cases it is infinitesimal. Therefore, only those terms of x'' or y'' which are "infinite" at the hard edge, either the magnet edge or the coordinate edge, will make sense.

4.) Consider a coordinate edge first. In the expressions for x'' or y'' , only the term $(1/\rho)'$ (introduced by $\Omega = \beta_z'/\beta_z$) is infinite. So the coordinate edge effect is simply represented by

$$x_f = x_i \quad ; \quad y_f = y_i \quad (C-4)$$

$$x'_f = x'_i - \Delta_e \left(\frac{1}{\rho} \right) x_i x'_i \quad ; \quad y'_f = y'_i - \Delta_e \left(\frac{1}{\rho} \right) x_i y'_i \quad (C-5)$$

where the symbol Δ_e is defined as : $\Delta_e = -1$ at an entrance and $\Delta_e = 1$ at an exit.

Note that no actual changes happen either to the particle position nor to its velocity in this case, but the coordinate system with which we describe the particle motion changes so that we have to revise the values of x' and y' . This point is made more clear by simple geometry : Fig.3 shows a particle with $x \neq 0$ going across a coordinate edge at z_0 , along a straight line that intersects x -axis by an angle $\frac{\pi}{2} - \alpha$.

Fig.3 Coordinate edge.

$(1/\rho)$ changes from 0 to a nonzero value at the edge while the particle velocity doesn't change at all. In region $z < z_0$, a z increment dz results in an x increment $dx = dz \cdot \tan \alpha$, so one gets $x' = \tan \alpha$. However, in region $z > z_0$, dz will be accompanied by $dx = (1 + x/\rho) \cdot dz \cdot \tan \alpha$, so one thinks $x' = (1 + x/\rho) \tan \alpha$ which equals to $x'_i + x_i x'_i / \rho$. This is where $\Delta x'$ comes from. Discussion for $\Delta y'$ is similar.

5.) Real magnet edge is much more complicated to cope with. Fig.4 is an entrance case. A particle enters the magnet along line AB at point A (x_i, y_i, z_A), where x-axis intersects the magnet edge face by an angle θ^* . A new coordinate system P-Q-Y is established with its origin at A, P-axis along the normal line of the magnet face and forward, Q-axis along the magnet face and in the median plane, and Y-axis parallel to y-axis of x-y-z system. $\vec{B}$, the field at the edge can be expressed in terms of B_P, B_Q and B_Y , which are connected to B_x, B_y and B_z by

Fig.4 Magnet edge.

$$B_x = \Delta_e B_P \sin \theta^* + B_Q \cos \theta^* ; \quad B_y = B_Y ;$$

$$B_z = B_P \cos \theta^* - \Delta_e B_Q \sin \theta^* \quad (C-6)$$

Here the symbol Δ_e is used to include both entrance and exit cases. The relation among coordinate increments is also revealed by Fig.4, in which point B is on the particle trajectory and very close to A; $dB = P_B - P_A$, $dQ = Q_B - Q_A$ and $dz = z_B - z_A$. So, near A and along AB, one has

$$dP = dz \left(\left(1 + \frac{x}{\rho} \right) \cos \theta^* + \Delta_e x' \sin \theta^* \right) ;$$

$$dQ = dz \left(- \Delta_e \left(1 + \frac{x}{\rho} \right) \sin \theta^* + x' \cos \theta^* \right)$$

$$\text{thus } dz = dP \left(1 - \frac{x}{\rho} - \Delta_e x' \tan \theta^* + \dots \right) / \cos \theta^* ;$$

$$dQ = - \Delta_e \tan \theta^* dP \left(1 + \dots \right) \quad (C-7)$$

Let subscript o denote the value on the median ($y = 0$) plane. One's knowledge about the field at the edge area is as follows: $B_{Po} = B_{Qo} = 0$; there exists a sharp change of B_{yo} from 0 to $(B_p)_o (1/\rho_B + Kx + \dots)$ along P-axis, or rather, across the curve $(r_e + \Delta_e P)^2 + Q^2 = r_e^2$; but B_{yo} itself is finite anywhere. Then Maxwell's equations give

$$\left(\frac{\partial B_y}{\partial y}\right)_o = \left(\frac{\partial^2 B_p}{\partial y^2}\right)_o = \left(\frac{\partial^2 B_Q}{\partial y^2}\right)_o = 0;$$

$$B_p = y \left(\frac{\partial B_y}{\partial p}\right)_o + \dots; \quad B_Q = y \left(\frac{\partial B_y}{\partial Q}\right)_o + \dots;$$

$$B_y = B_{yo} - \frac{1}{2} y^2 \left(\left(\frac{\partial^2 B_y}{\partial p^2}\right)_o + \left(\frac{\partial^2 B_y}{\partial Q^2}\right)_o \right) + \dots \quad (C-8)$$

All the functions with subscript o depend on both P and Q. In addition, from calculus, one is sure that

$$\left(\frac{\partial B_y}{\partial p}\right)_o dp = dB_{yo} - \left(\frac{\partial B_y}{\partial Q}\right)_o dQ;$$

$$\begin{aligned} \left(\frac{\partial^2 B_y}{\partial p^2}\right)_o dp &= d\left(\frac{\partial B_y}{\partial p}\right)_o - \left(\frac{\partial^2 B_y}{\partial p \partial Q}\right)_o dQ \\ &= d\left(\frac{\partial B_y}{\partial p}\right)_o - (dQ/dp) d\left(\frac{\partial B_y}{\partial Q}\right)_o + (dQ/dp)^2 \left(\frac{\partial^2 B_y}{\partial Q^2}\right)_o dp \end{aligned} \quad (C-9)$$

$\left(\frac{\partial B_y}{\partial p}\right)_o$ is known to go to "infinity" on the edge, behaving like δ -

function, since an integration over an infinitesimal length normally across the edge yields

$$\tilde{\Delta} B_{yo}(f) = \int_i^f dB_{yo} = \int_i^f \left(\frac{\partial B_y}{\partial p}\right)_o dp = -\Delta_e (B_p)_o \left(\frac{1}{\rho_B} + Kx\right) + \dots \quad (C-10)$$

The symbol $\tilde{\Delta}$ indicates a difference: $\tilde{\Delta} G(P) = G(P) - G(i)$, where G is any function, "P" is a point on the path, "i" stands for "before the edge" and "f" for "after the edge". Because, inside the magnet, x equals to $x_i + Q \cos \theta^* + \Delta_e P \sin \theta^*$, two more examples are given as

$$\tilde{\Delta} \left(\frac{\partial B_y}{\partial p}\right)_o(f) = - (B_p)_o K \sin \theta^*;$$

$$\tilde{\Delta} \left(\frac{\partial B_y}{\partial Q}\right)_o(f) = - (B_p)_o \Delta_e K \cos \theta^* \quad (C-11)$$

To find how the unknown field components behave, look into B_{yo} again and ignore its slowly varied part, which makes no contributions to the results. As Eq. (C-9) is valid on any path, with dP and dQ arbitrarily related to each other, first consider a path along the magnet edge face, that is, $(r_e + \Delta_e P)^2 + Q^2 = r_e^2$ or $\Delta_e (r_e + \Delta_e P) dP + Q dQ = 0$. Since $|P/r_e| \ll 1$, the path is represented by $dP = -\Delta_e Q dQ/r_e$. We know dB_{yo} along this path is negligible. So, along this path or on the edge face, for the sharply varied part of B_{yo} only,

$$\begin{aligned} \left(\frac{\partial B_y}{\partial Q}\right)_0 &= \Delta_e \frac{Q}{r_e} \left(\frac{\partial B_y}{\partial P}\right)_0 ; \\ \left(\frac{\partial^2 B_y}{\partial Q^2}\right)_0 &= \Delta_e \frac{1}{r_e} \left(\left(\frac{\partial B_y}{\partial P}\right)_0 + Q \left(\frac{\partial^2 B_y}{\partial P \partial Q}\right)_0 \right) \end{aligned} \quad (C-12)$$

$\left(\frac{\partial B_y}{\partial P}\right)_0$ or any other components may be "infinite" only in the sense that the edge width ΔP is infinitesimal, as $\left(\frac{\partial B_y}{\partial P}\right)_0 \cdot \Delta P$ is finite. Therefore, $\left(\frac{\partial B_y}{\partial Q}\right)_0$ and $Q \left(\frac{\partial^2 B_y}{\partial P \partial Q}\right)_0$ are finite on those paths where Q is of the same magnitude order as ΔP .

Now one is ready to solve the problem. Making integrations over a very short length along the particle trajectory, which is characterized by $dQ/dP = -\Delta_e \tan \theta^*$, one obtains

$$\begin{aligned} \int_i^P G(P) B_{yo} dP &= \int_i^P G \left(\frac{\partial B_y}{\partial Q}\right)_0 dP = 0 ; \\ \int_i^P G \left(\frac{\partial B_y}{\partial P}\right)_0 dP &= \int_i^P dB_{yo} = [G(P)] \cdot \tilde{\Delta} B_{yo}(P) ; \\ \int_i^P G \left(\left(\frac{\partial^2 B_y}{\partial P^2}\right)_0 + \left(\frac{\partial^2 B_y}{\partial Q^2}\right)_0 \right) dP &= [G(P)] \cdot \left(\tilde{\Delta} \left(\frac{\partial B_y}{\partial P}\right)_0(P) + \Delta_e \tan \theta^* \cdot \tilde{\Delta} \left(\frac{\partial B_y}{\partial Q}\right)_0(P) \right) \\ &\quad + [-dG/dP + \Delta_e (G/r_e) (1 + \tan^2 \theta^*)] \cdot \tilde{\Delta} B_{yo}(P) \end{aligned} \quad (C-13)$$

where G is a function and $[G(P)]$ is its average value over the integration path, that is, $[G(P)] = (G(P) + G(i))/2$.

Next thing to do is to insert Eqs.(B-6), (B-7), (C-6), (C-7), (C-8), (C-13) and then Eqs.(C-10), (C-11) into Eq.(C-3). A few points have to be noticed:

x' has got a term $\frac{y^2}{2 \cos \theta^*} \left(\frac{1}{(B\rho)_0} \cdot \tilde{\Delta} \left(\frac{\partial B_y}{\partial \rho} \right)_0(P) \right)$, which is δ -function like, rising to "infinity" at the edge. This term brings about a finite increment in x as $\Delta x = - \frac{\Delta_e}{2 \rho_B \cos^2 \theta^*} y^2$, while the particle is in the

"strong" field on the inclined edge. It follows that a z increment must be associated as $\Delta z = - \Delta_e \tan \theta^* \cdot \Delta x$ and, in turn, it causes an additional x' increment $\Delta z / \rho$ if the coordinate system at that point has $(1/\rho) \neq 0$. Though the field has effect only on the particles whose $y_i \neq 0$, y itself, up to second order, remains unchanged. y' gets an increment with a first order term $- y \cdot \tan \theta^* / \rho_B$. This term affects the evaluation of $[G(f)]$, since $[y y'] = y_i (y'_i + y'_f)/2$.

At first thought, the argument that x' is once infinitely high seems unbelievable. But, "hard edge" is only a theoretical assumption under which the edge fringing field width is squeezed to zero and, as a result, off-median-plane field becomes a sharp impact, somehow like δ - or δ' -function. In fact, the x' increment is always proportional to y^2 and is hence a second order quantity. But, a definite second order increment in x must be made, no matter how narrow the edge area is. So, if the edge width is assumed infinitesimal, in this sense, x' has to be "infinite" at some time.

After the equation insertions one arrives at four formulae, which represents the effect of a real magnet edge, characterized by θ^* , r_e and Δ_e . Note that ρ_B is not necessary to equal to ρ .

$$\begin{aligned}
x_f &= x_i - \Delta_e \frac{1}{2\rho_B} y_i^2 (1 + \tan^2 \theta^*) + \dots ; \quad y_f = y_i + \dots ; \\
x'_f &= x'_i - \left(K \tan \theta^* + \frac{1}{2\rho_B r_e \cos^3 \theta^*} \right) y_i^2 + \Delta_e \frac{1}{\rho_B} y_i y'_i \tan^2 \theta^* \\
&\quad + \frac{1}{2\rho_B} y_i^2 \tan \theta^* \left(\frac{1}{\rho} + \left(\frac{1}{\rho} - \frac{\Delta_e}{\rho_B} \right) \tan^2 \theta^* \right) + \dots ; \\
y'_f &= y'_i - y_i \tan \theta^* \left(\frac{1}{\rho_B} + K x_i + \frac{x_i}{\rho \cdot \rho_B} - \frac{\delta}{\rho_B} \right) \\
&\quad + \Delta_e \frac{1}{\rho_B} x'_i y_i (1 + \tan^2 \theta^*) + \dots
\end{aligned} \tag{C-14}$$

$$\text{And } z_f = z_i + \frac{1}{2\rho_B} y_i^2 \tan \theta^* (1 + \tan^2 \theta^*) + \dots \tag{C-15}$$

The problem of edge effects is almost solved by Eqs. (C-2), (C-4), (C-5), (C-14) and (C-15).

D. Expressions for Hard Edge Effects

1.) Case 1 to be studied is shown in Fig. 5. The particle goes across the coordinate edge at T (between "b" and "3") and enters the magnet at A (between "4" and "5"). O is the center of the curved ideal orbit in the magnet and C the center of the curved magnet face. CE is parallel to OT (x-axis at z_0). DE contains A and is perpendicular to CE. It is obvious that

$$r_e \cos \theta_e - r_e \cos \theta_r = AD ;$$

$$r_e \sin \theta_r - r_e \sin \theta_e = x_b + DT$$

$$= x_b + AD \cdot x'_b$$

Fig. 5 Case 1 (entrance)

The solutions of these equations, up to the necessary order, are

$$AD = x_b \cdot \tan \theta_e (1 + x'_b \tan \theta_e) + x_b^2 / (2 r_e \cos^3 \theta_e) + \dots ;$$

$$\tan \theta_r = \tan \theta_e + x_b / (r_e \cos^3 \theta_e) + \dots$$

And, in turn, one can get $z_d = z_4 - z_b$ and $\tan \theta^* = \tan(\theta_r - \frac{z_d}{\rho})$ by

$$z_d = x_b \tan \theta_e (1 + x'_b \tan \theta_e - \frac{x_b}{\rho}) + \frac{x_b^2}{2 r_e \cos^3 \theta_e} + \dots \quad (D-1)$$

$$\tan \theta^* = \tan \theta_e (1 - \frac{x_b}{\rho \cos^2 \theta_e}) + \frac{x_b}{r_e \cos^3 \theta_e} + \dots \quad (D-2)$$

After the geometric work above, the increments we want can be found step by step. Some key points are summarized as the following:

Use Eqs.(C-4) and (C-5) for step 1, with subscripts $i = b$, $f = 3$, and $\Delta_e = -1$; use Eq.(C-2) for the step from "3" ($i = 3$) to "4" ($f = 4$), with $\Delta z = z_d$ as in Eq.(D-1), and note that this is an example where $(1/\rho) \neq 0$ but $(1/\rho_B) = K = 0$; use Eq.(C-14) for step 3, with $i = 4$, $f = 5$, $\tan \theta^*$ given by Eq.(D-2) and note that $(1/\rho) = (1/\rho_B) \neq 0$; and for the imaginary back step from "5" to "a", use Eq.(C-2) again, but this time having $(1/\rho_B) = (1/\rho) \neq 0$ and $\Delta z = -x_b \tan \theta_e + \dots$. Finally, one will obtain four sets of equations and can combine them into

$$x_a = x_b - \frac{1}{2\rho} x_b^2 \tan^2 \theta_e + \frac{1}{2\rho} y_b^2 (1 + \tan^2 \theta_e) + \dots ;$$

$$y_a = y_b + \frac{1}{\rho} x_b y_b \tan^2 \theta_e + \dots ;$$

$$\begin{aligned} x'_a = x'_b + \frac{1}{\rho} x_b \tan \theta_e + ((K + \frac{1}{\rho^2}) \tan \theta_e + \frac{1}{2\rho r_e \cos^3 \theta_e}) x_b^2 \\ - \frac{1}{\rho} \delta x_b \tan \theta_e + \frac{1}{\rho} x_b x'_b (1 + \tan^2 \theta_e) - \frac{1}{\rho} y_b y'_b \tan^2 \theta_e \\ - ((K - \frac{1}{\rho^2} (\frac{1}{2} + \tan^2 \theta_e)) \tan \theta_e + \frac{1}{2\rho r_e \cos^3 \theta_e}) y_b^2 + \dots ; \end{aligned}$$

$$\begin{aligned} y'_a = y'_b - \frac{1}{\rho} y_b \tan \theta_e - ((2K + \frac{1}{\rho^2}) \tan \theta_e + \frac{1}{\rho r_e \cos^3 \theta_e}) x_b y_b \\ + \frac{1}{\rho} \delta y_b \tan \theta_e + \frac{1}{\rho} x_b y'_b (1 - \tan^2 \theta_e) \\ - \frac{1}{\rho} x'_b y_b (1 + \tan^2 \theta_e) + \dots \end{aligned} \quad (D-3)$$

Note that it is no longer necessary to tell ρ_B from ρ .

2.) Fig.6 shows case 2 in which the particle enters the magnet again, but the magnet edge is crossed first. Explanations for symbols in Fig.6 are similar to those in Fig.5.

Geometry tells the relations between lengths and angles:

$$r_e \cos \theta_r - r_e \cos \theta_e = AD ;$$

$$r_e \sin \theta_e - r_e \sin \theta_r = -x_3$$

$$= -x_b + AD \cdot x'_b ;$$

$$\theta^* = \theta_r$$

Fig.6 Case 2 (entrance)

Therefore, $z_d = z_b - z_3$ is given by

$$z_d = AD = -x_b \tan \theta_e (1 + x'_b \tan \theta_e) - \frac{x_b^2}{2r_e \cos^3 \theta_e} + \dots \quad (D-4)$$

$$\tan \theta^* = \tan \theta_e + \frac{x_b}{r_e \cos^3 \theta_e} + \dots \quad (D-5)$$

Note that Eqs.(D-4) and (D-5) agree with Eqs.(D-1) and (D-2), but having $(1/\rho) = 0$. Now the procedure can be briefly described as follows:

The first step is from "b" to "3", along an imaginary backward path with $\Delta z = -z_d = x_b \tan \theta_e + \dots$, as Eq.(C-2) is used in its simplest forms, since the small sector between "b" and "3" is supposed field-free with $(1/\rho) = (1/\rho_B) = K = 0$. Eqs.(C-14) helps make step 2 which is across the magnet edge, from "3" to "4", with $(1/\rho) = 0$ and $\tan \theta^*$ given by Eq.(D-5). Step 3 is then made in the real magnetic field from "4" to "5" and Eq.(C-2) gets new forms once more, with $(1/\rho) = 0$ but $(1/\rho_B) \neq 0$. Now one should believe that to distinguish ρ_B from ρ at the beginning is a safe and easy way to solve complicated problems.

All of these turn out to give

$$z_d = x_b \tan \theta_e \left(1 - x'_b \tan \theta_e - \frac{x_b}{\rho} \left(1 + \frac{1}{2} \tan^2 \theta_e \right) \right) + \frac{x_b^2}{2 r_e \cos^3 \theta_e} + \dots \quad (D-6)$$

while $\tan \theta^*$ is found the same as given by Eq. (D-2). For step 1, it is sufficient to have $\Delta z = -x_b \tan \theta_e$. The following steps can be made one by one readily: Step 2 is across the magnet edge from "3" to "4", the things to note are $\Delta e = 1$ at exit and $\rho_B = \rho$; step 3 from "4" to "5", covering $z = z_d - y_b^2 \tan \theta_e (1 + \tan^2 \theta_e) / (2\rho)$ along a straight line ($(1/\rho_B) = K = 0$) in a "curved" coordinate system ($(1/\rho) \neq 0$); and the last step from "5" to "a". The final results are

$$\begin{aligned} x_a &= x_b + \frac{1}{2\rho} x_b^2 \tan^2 \theta_e - \frac{1}{2\rho} y_b^2 (1 + \tan^2 \theta_e) + \dots ; \\ y_a &= y_b - \frac{1}{\rho} x_b y_b \tan^2 \theta_e + \dots ; \\ x'_a &= x'_b + \frac{1}{\rho} x_b \tan \theta_e + \left(K - \frac{1}{2\rho^2} \tan^2 \theta_e \right) \tan \theta_e + \frac{1}{2\rho r_e \cos^3 \theta_e} x_b^2 \\ &\quad - \frac{1}{\rho} \delta x_b \tan \theta_e - \frac{1}{\rho} x_b x'_b (1 + \tan^2 \theta_e) + \frac{1}{\rho} y_b y'_b \tan^2 \theta_e \\ &\quad - \left(K + \frac{1}{2\rho^2} \tan^2 \theta_e \right) \tan \theta_e + \frac{1}{2\rho r_e \cos^3 \theta_e} y_b^2 + \dots ; \\ y'_a &= y'_b - \frac{1}{\rho} y_b \tan \theta_e - \left(2K - \frac{1}{\rho^2} (1 + \tan^2 \theta_e) \right) \tan \theta_e \\ &\quad + \frac{1}{\rho r_e \cos^3 \theta_e} x_b y_b + \frac{1}{\rho} \delta y_b \tan \theta_e - \frac{1}{\rho} x_b y'_b (1 - \tan^2 \theta_e) \\ &\quad + \frac{1}{\rho} x'_b y_b (1 + \tan^2 \theta_e) + \dots \end{aligned} \quad (D-7)$$

4.) Again, consider the second case of exit which is shown in Fig. 8 with the difference from the preceding one that the coordinate edge is passed first and with the advantage that, in most equations, $(1/\rho) = 0$. The

First two steps, from "b" to "3" and then to "4" (along a curved line in a straight coordinate system) are easy to make with the equations in sect. C. For the x coordinates, one gets

$$x_3 = x_b ; \quad x'_3 = x'_b - \frac{1}{\rho} x_b x'_b ;$$

$$x_4 = x_3 + x'_3 \cdot z_d - \frac{1}{2\rho_B} z_d^2$$

where $z_d = AD = \Delta z$ in step 2. Then the expression of z_d in this case can be found from the geometric relations

$$r_e \cos \theta_r - r_e \cos \theta_e = z_d \quad ;$$

$$r_e \sin \theta_e - r_e \sin \theta_r \approx -x_d$$

which result in

Fig.8 Case 4 (exit)

$$z_d = -x_b \tan \theta_e \left(1 - x'_b \tan \theta_e - \frac{1}{2f_B} x_b \tan^2 \theta_e \right) - \frac{x_b^2}{2r_e \cos^3 \theta_e} + \dots \quad (D-8)$$

and an equation for $\tan \theta^*$, which is the same as Eq.(D-5), or Eq.(D-2) with $(1/\rho) = 0$. In fact, Eq.(D-2) is proved always valid in any case.

After going through the last two steps, from "4" to "5" and then back to "a", with $(1/p)$ equal to zero in all the equations used on the path, again, one will come to the four equations we have got in the last case, if enough attention is paid to keep every first or second order term while any higher order terms are ignored.

5.) In order to present a complete form of the edge effect equations, define some more symbols here:

Edge quadrupole component $K_e = -\frac{1}{\rho} \tan \theta_e$;

Edge sextupole component $\lambda_e = -2 K \tan \theta_e - 1/(\rho r_e \cos^3 \theta_e)$;

and six special sextupole components $\lambda_{x1}^{(1)} = -\frac{2}{\rho^2} t_1$, $\lambda_{x2}^{(1)} = \frac{1}{\rho^2} t_2^3$,

$\lambda_{y1}^{(1)} = -\frac{1}{\rho^2} t_1$, $\lambda_{y2}^{(1)} = \frac{1}{\rho^2} t_2 (1 + t_2^2)$, $\lambda_{xy1}^{(1)} = \frac{1}{\rho^2} t_1 (1 + 2 t_1^2)$,

$\lambda_{xy2}^{(1)} = -\frac{1}{\rho^2} t_2^3$; where $t_e = \tan \theta_e$, the subscript $e = 1$ at an

entrance and $e = 2$ at an exit. Similarly, the definition of Δ_e is just $\Delta_1 = -1$, $\Delta_2 = 1$. The differences in the expressions for $\lambda_{ue}^{(1)}$ (u is x or y) and $\lambda_{xye}^{(1)}$ suggest that the edge sextupole effects vary both with transverse planes (horizontal or vertical) and with edges (entrance or exit).

Eqs.(D-3) and (D-7) are then written as four up-to-second-order edge effect equations

$$x_a = x_b + \Delta_e \frac{1}{2\rho} x_b^2 t_e^2 - \Delta_e \frac{1}{2\rho} y_b^2 (1 + t_e^2) + \dots ;$$

$$y_a = y_b - \Delta_e \frac{1}{\rho} x_b y_b t_e^2 + \dots ;$$

$$x'_a = x'_b - K_e x_b - \frac{1}{2} (\lambda_e + \lambda_{xe}^{(1)}) x_b^2 + \frac{1}{2} (\lambda_e + \lambda_{xye}^{(1)}) y_b^2 \\ + K_e \delta x_b - \Delta_e \frac{1}{\rho} x_b x'_b (1 + t_e^2) + \Delta_e \frac{1}{\rho} y_b y'_b t_e^2 + \dots ;$$

$$y'_a = y'_b + K_e y_b + (\lambda_e + \lambda_{ye}^{(1)}) x_b y_b - K_e \delta y_b \\ - \Delta_e \frac{1}{\rho} x_b y'_b (1 - t_e^2) + \Delta_e \frac{1}{\rho} x'_b y_b (1 + t_e^2) + \dots \quad (D-9)$$

Note that the distinction between u'_a and u'_b is important, due to the fact that there are first order terms in the increments of x' and y' and that, thereby, the derivatives of several functions such as β' and η' may be discontinuous from one side to the other side of an edge.

K_e and λ_e are the only terms that appear in the entrance and exit effect equations with the same sign. Comparing Eq. (D-9) with Eq. (B-12), one will see that K_e and λ_e are equivalent to $\int K(z) dz$ and $\int \lambda(z) dz$ respectively, if he regards a hard edge as a short length with continuous field. Generally speaking, the edge effect can be mainly represented by K_e and λ_e .

For the case where $\theta_e = (1/r_e) = 0$ or what is called a normal edge, Eq. (D-9) gives the same results as given by Eq. (B-12) after the both sides are integrated. Those terms that don't depend on either θ_e or r_e are sometimes called "normal edge terms".

A comparison of Eq. (D-9) with the results in other papers was made. A perfect agreement is found with the expressions in Ref. 4) after parameter transformation, since Ref. 4) uses not only a different approach, Green's functions, but also a different coordinate system, the local rectangular system. But, a major difference is seen with some other papers, Ref. 1) for example, as stated before. This is why most efforts so far in writing this note are made on the edge effects and the procedures are presented in so much detail.

6.) For a vertical bending magnet with inclined and/or curved edges, again, the edge effect equations can be found by a 90 degree coordinate system rotation plus an x-y substitution. The equations are

$$\begin{aligned}
 x_a &\approx x_b + \Delta_e \frac{1}{f_y} x_b y_b t_e^2 + \dots ; \\
 y_a &\approx y_b - \Delta_e \frac{1}{2f_y} y_b^2 t_e^2 + \Delta_e \frac{1}{2f_y} x_b^2 (1 + t_e^2) + \dots ; \\
 x'_a &= x'_b - K_e x_b - (\lambda_{Re} + \lambda_{Rxe}^{(1)}) x_b y_b + K_e \delta x_b \\
 &\quad - \Delta_e \frac{1}{f_y} x_b y'_b (1 + t_e^2) + \Delta_e \frac{1}{f_y} x'_b y_b (1 - t_e^2) + \dots ; \\
 y'_a &= y'_b + K_e y_b + \frac{1}{2} (\lambda_{Re} + \lambda_{Rye}^{(1)}) y_b^2 - \frac{1}{2} (\lambda_{Re} + \lambda_{Ryxe}^{(1)}) x_b^2 \\
 &\quad - K_e \delta y_b + \Delta_e \frac{1}{f_y} y_b y'_b (1 + t_e^2) - \Delta_e \frac{1}{f_y} x_b x'_b t_e^2 + \dots \quad (D-10)
 \end{aligned}$$

where $t_e = \tan \theta_e$, $\frac{1}{\rho_y} = -B_{xo}/(B\rho)_o$, $\lambda_{Re} = -2 K t_e - 1/(\rho_y t_e \cos^3 \theta_e)$,
 $K_e = -\frac{1}{\rho_y} t_e$, $\lambda_{Rx1}^{(1)} = \frac{1}{\rho_y^2} t_1$, $\lambda_{Rx2}^{(1)} = -\frac{1}{\rho_y^2} t_2 (1 + t_2^2)$,
 $\lambda_{Ry1}^{(1)} = \frac{2}{\rho_y^2} t_1$, $\lambda_{Ry2}^{(1)} = -\frac{1}{\rho_y^2} t_2^3$, $\lambda_{Ryx1}^{(1)} = -\frac{1}{\rho_y^2} t_1 (1 + 2 t_1^2)$,
 $\lambda_{Ryx2}^{(1)} = \frac{1}{\rho_y^2} t_2^3$. The sign conventions of θ_e and r_e as well as the

definitions of Δ_e and other symbols are similar to those for horizontal bending magnets.

The solenoid edge effect is described by Eq. (C-4) together with

$$\begin{aligned} x'_a &= x'_b - \frac{1}{2} \Delta_e g_S y_b (1 - \delta) + \dots; \\ y'_a &= y'_b + \frac{1}{2} \Delta_e g_S x_b (1 - \delta) + \dots \end{aligned} \quad (D-11)$$

where $g_S = B_{zo}/(B\rho)_o$ in the solenoid.

E. The Phase Increment due to a Disturbance

1.) In the following statements, u denotes x or y ; β_u , α_u and γ_u are the Twiss functions, η_u the dispersion function and ν_u the tune on u plane; $\Psi_u(s_2|s_1)$ is the phase advance between points s_2 and s_1 , defined

by $\Psi_u(s_2|s_1) = \int_{s_1}^{s_2} (1/\beta_u(z)) dz$. The particle displacement is well

known to be described by

$$u(z) = A \sqrt{\beta_u(z)} \cos(\Psi_u(z|z_o) + \psi_o) \quad (E-1)$$

where the amplitude A and the initial phase angle ψ_o are two arbitrary constants.

Suppose there exists a small disturbance, proportional partly to the displacement (u) and partly to the slope (u') of the particle, in a

short region from point "b" to "a", as shown in Fig.9. The region length

$\Delta z = z_a - z_b$ is so close to zero that

$\beta_{ua} = \beta_{ub}$. But, to include the case

where a magnet edge is crossed, discontinuity of α_u is allowable, that

is, there may be a significant difference

between α_{ua} and α_{ub} , which must

be associated with a focusing strength

f_u between "b" and "a". The quantitative relation of f_u and other parameters are:

The quantitative relation of f_u and other parameters are:

Fig.9 Disturbance region

$$\alpha_{ua} - \alpha_{ub} = f_u \beta_{ub} ; \quad \eta'_{ua} - \eta'_{ub} = - f_u \eta_{ub} \quad (E-2)$$

and, if the disturbance did not exist, one would have

$$u_a = u_b ; \quad u'_a = u'_b - f_u u_b \quad (E-3)$$

It is easy to prove that Eqs.(E-1), (E-2) and (E-3) are consistent.

Now suppose the disturbance is given by

$$u_a = u_b + P \cdot \Delta z \cdot u_b ; \quad u'_a = u'_b - f_u u_b + Q \cdot \Delta z \cdot u_b + R \cdot \Delta z \cdot u'_b \quad (E-4)$$

where P, Q and R are three parameters characterizing the disturbance while f_u is the normal focusing strength.

Since particle motion in the rest of the ring still obeys Eq.(E-1), it is advisable to describe the motion upstream of "b" and that downstream of "a" by Eq.(E-1) with variant A and ψ_o , respectively. Therefore,

$$u_b = A \sqrt{\beta_{ub}} \cos \psi_b ; \quad u_a = (A + \Delta A) \sqrt{\beta_{ua}} \cos(\psi_b + \Delta \psi) \quad (E-5)$$

can be given, with ΔA the oscillation amplitude increment and $\Delta \psi$ the phase increment, both caused by the disturbance. Then, for the first order dependence, one obtains by combining Eqs.(E-2), (E-4) and (E-5)

$$\begin{aligned}\Delta\psi &= (\alpha_{ub}R - \alpha_{ua}P - \beta_u Q) \cdot \Delta z \cdot \cos^2 \psi_b + (R - P) \cdot \Delta z \cdot \sin \psi_b \cos \psi_b ; \\ \frac{\Delta A}{A} &= (\alpha_{ub}R - \alpha_{ua}P - \beta_u Q) \cdot \Delta z \cdot \sin \psi_b \cos \psi_b + P \cdot \Delta z \cdot \cos^2 \psi_b \\ &\quad + R \cdot \Delta z \cdot \sin^2 \psi_b\end{aligned}\quad (E-6)$$

In order to find the tune increment $\Delta\nu_u = \Delta\psi / (2\pi)$ and the relative amplitude increment $\zeta = (\Delta A / A)$ per turn, one has to average Eq. (E-6) over all the possible values of ψ_b , since the effect can be observed only after a great number of turns. Therefore,

$$\Delta\nu_u = \frac{1}{4\pi} (\alpha_{ub}R - \alpha_{ua}P - \beta_u Q) \Delta z \quad (E-7)$$

$$\zeta = \frac{1}{2} (P + R) \Delta z \quad (E-8)$$

The distinction between α_{ub} and α_{ua} was not made in other papers, but it does affect the results if the disturbance takes place at a magnet edge. Of course, no such distinction is necessary when α_u is continuous in a "long" region where the disturbance parameters P , Q and R are continuous and z -dependent. Suppose there exists such disturbance all around the ring, the total first order effect is

$$\begin{aligned}\Delta\nu_u &= \frac{1}{4\pi} \left(\oint (\alpha_u (R-P) - \beta_u Q) dz + \sum_e (\alpha_{ub}R - \alpha_{ua}P - \beta_u Q) \cdot \Delta z \right) ; \\ \zeta &= \frac{1}{2} \left(\oint (P + R) dz + \sum_e (P + R) \cdot \Delta z \right)\end{aligned}\quad (E-9)$$

where the sum $\sum_e$ is calculated for all the points with discontinuous α_u . Here an assumption is implicitly made that the disturbance is so weak that beta function distortion and the coupling between the disturbance sources are negligible. This is suitable for the first order calculation. Note that the oscillation is excited if $\zeta > 0$, or damped if $\zeta < 0$. Q doesn't affect the amplitude while P and R do. The tune is under the influence of any of them.

Eq.(E-9) can be obtained by several parallel methods. The above one is chosen because of its simple mathematics and direct use of Eq.(E-4) as the disturbance description. Two more methods are presented in the next two subsections and the readers who are not interested in them can skip over them to section F.

2.) Transfer matrix multiplication is a powerful tool widely applied. The main points of its correct use in this case are as follows.

Return to the conditions presented in the first several paragraphs of the last subsection. Had the disturbance been removed, the transfer matrix from "b" to "b" through one turn would be

$$M_u(b|b) = M_u(b|a) \cdot \begin{pmatrix} 1 & 0 \\ -f_u & 1 \end{pmatrix} = \cos 2\pi \gamma_u \begin{pmatrix} 1 & 0 \\ 0 & 1 \end{pmatrix} + \sin 2\pi \gamma_u \begin{pmatrix} \alpha_{ub} & \beta_{ub} \\ -\gamma_{ub} & -\alpha_{ub} \end{pmatrix}$$

And, when the disturbance exists, the new transfer matrix is

$$M_u^*(b|b) = M_u(b|a) \cdot \begin{pmatrix} 1 + P \cdot \Delta z & 0 \\ -f_u + Q \cdot \Delta z & 1 + R \cdot \Delta z \end{pmatrix}$$

where the matrix from "a" to "b" (almost one turn), $M_u(b|a)$, remains undisturbed, while $M_u^*(b|b)$ differs from $M_u(b|b)$.

Note that the determinant of matrix $M_u^*(b|b)$ is not unit, but roughly $1 + (P + R) \cdot \Delta z$. This implies an oscillation amplitude increment. It follows the eigenvalues of a one-turn matrix are not $\exp(\pm 2\pi \gamma_u \cdot i)$, but $\exp(\zeta \pm 2\pi(\gamma_u + \Delta \gamma_u) \cdot i)$ instead. So the determinant of $M_u^*(b|b)$ is $\exp(2\zeta) \approx 1 + 2\zeta$, and the trace can be written as

$$T_r = 2 \exp(\zeta) \cos 2\pi(\gamma_u + \Delta \gamma_u) \approx 2(1 + \zeta) \cos 2\pi \gamma_u - 4\pi \cdot \Delta \gamma_u \sin 2\pi \gamma_u$$

Here ζ and $\Delta \gamma_u$ mean the same as defined before. As a proof, the amplitude increment per turn is $A \exp(\zeta) - A \approx \zeta A$. Note that $\zeta / (2\pi)$ can be regarded as the imaginary part of the tune increment. Compare the above expression for T_r with the trace of $M_u^*(b|b)$ as calculated by transfer matrix multiplication, which is

$$T_r = (2 + P \cdot \Delta z + R \cdot \Delta z) \cos 2\pi \gamma_u \\ + (\beta_{ub} Q + (\alpha_{ub} + f_u \beta_{ub}) P - \alpha_{ub} R) \cdot \Delta z \sin 2\pi \gamma_u$$

It is easy to get the expressions for $\Delta \gamma_u$ and ζ . They are exactly the same as obtained by the first method.

3.) Standard function transformation is also able to solve the problem but more suitable for the continuous disturbance case because of the involvement of differential equations.

Without the disturbance, the standard form of the particle motion equation is $u'' + F_u(z) \cdot u = 0$. A transformation with $w = u/\sqrt{\beta_u}$ as a new function and $\theta = \psi_u(z | z_0)/\gamma_u$ as a new variable changes the equation into $(d^2w/d\theta^2) + \gamma_u^2 \cdot w = 0$, and thus gives the solution as $w = A \cos(\gamma_u \theta + \psi_0)$.

When a continuous disturbance characterized by P , Q and R exists, the particle motion is described by two simultaneous equations:

$$u' = v + P \cdot u ; \quad v' = -F_u u + Q \cdot u + R \cdot u'$$

where the function v is equivalent to u' in the original sense but, if $P \neq 0$, not equal to $(\Delta u / \Delta z)$. So the equation of u is

$$u'' + F_u u = (Q + P') u + (P + R) u'$$

The function transformation introduced above turns it into

$$\frac{d^2w}{d\theta^2} - \gamma_u \beta_u (P + R) \frac{dw}{d\theta} + \gamma_u^2 (1 + d_u \beta_u (P + R) - \beta_u^2 (Q + P')) w = 0$$

where P , Q , R and $P' = dP/dz$ are z dependent, and hence are θ dependent periodic functions with the period of $\theta = 2\pi$.

Suppose the solution to this equation is approximately

$$w = A \exp\left(\frac{\zeta}{2\pi} \theta\right) \cos((\gamma_u + \Delta \gamma_u) \theta + \psi_0)$$

where ζ and $\Delta \gamma_u$ mean the same as defined before, both caused by the disturbance and consequently both assumed small quantities. Such a w function satisfies a differential equation which reads

$$\frac{d^2w}{d\theta^2} - \frac{\zeta}{\pi} \frac{dw}{d\theta} + \gamma_u^2 \left(1 + 2 \frac{\Delta \gamma_u}{\gamma_u}\right) w = 0$$

Compare the two differential equations, note that all the θ dependent functions have to be averaged over one turn before they are made equal to invariant parameters, and be aware that

$$dz = \nu_u \beta_u d\theta ; \quad \oint \beta_u p' dz = - \oint \beta_u' p dz = 2 \oint \alpha_u p dz$$

Again, the results agree exactly with those obtained before.

F. The Linear CHR (Chromaticity) Expressions

1.) With the understanding that the tune ν_u is dependent on momentum (energy) deviation by a function $\nu_u(\delta)$, a definition of the linear CHR is introduced as

$$\xi_u = \lim_{\delta \rightarrow 0} ((\nu_u(\delta) - \nu_u(0))/\delta) \quad (F-1)$$

Suppose the second order motion equation on u plane, with magnet edges excluded, is

$$u'' + F_u u = Q_u(z) \delta u + R_u(z) \delta u' + \dots \quad (F-2)$$

And, at a magnet edge denoted by subscript e, u and u' are increased by

$$u_a = u_b + \overline{P_{ue}} \delta u_b + \dots \quad (F-3)$$

$$u'_a = u'_b - f_u u_b + \overline{Q_{ue}} \delta u_b + \overline{R_{ue}} \delta u'_b + \dots \quad (F-4)$$

It is known from the equations in Sections B and D that the normal focusing strengths in the most common case are

$$F_x = K + \frac{1}{\rho^2} ; \quad F_y = -K ; \quad f_x = -f_y = K_e = -\frac{1}{\rho} \tan \theta_e \quad (F-5)$$

The ellipses in Eqs.(F-2) through (F-4) represent a few terms which are proportional to δ^2 , u^2 , $u u'$, u'^2 or the displacement/slope on the other plane, in other words, are either dependent on δ^2 or independent on δ . According to Eq.(F-1), those terms don't affect the linear CHR, though they may affect the higher order CHR, non-linear effect and/or coupling effect.

Provided Eqs.(F-2) through (F-4) are established, a direct use of Eqs.(E-9) and (F-1) gives a general expression of ξ_u as

$$\xi_u = \frac{1}{4\pi} \oint (\alpha_u R_u - \beta_u Q_u) dz + \frac{1}{4\pi} \sum_e \overline{T_{ue}} \quad (F-6)$$

$$\text{with } \overline{T_{ue}} = \alpha_{ub} \overline{R_{ue}} - \alpha_{ua} \overline{P_{ue}} - \beta_u \overline{Q_{ue}} \quad (F-7)$$

2.) With the help of the momentum/energy dispersion functions η_u , the particle motion on u plane can be divided into two parts, momentum dependent closed orbit $\delta \cdot \eta_u$ and transverse oscillation u_β . That is

$$u = \delta \eta_u + u_\beta \quad (F-8)$$

$$\text{And } \eta_u \text{ satisfies } \eta_x'' + (K + \frac{1}{\rho^2}) \eta_x = \frac{1}{\rho}; \quad \eta_y'' + (-K + \frac{1}{\rho^2}) \eta_y = -\frac{1}{\rho}.$$

Suppose the accelerator is so designed that the magnetic field is piecewisely constant. $1/\rho$ is not zero in and only in normal bending magnets; $1/\rho_y$ is not zero in and only in vertical bending magnets; K is not zero in quadrupoles and in combined function bending magnets, where $K = -n/\rho^2$ with n the magnetic field index; and λ is not zero in and only in sextupoles. Other magnetic components are all ignored.

Vertical bending is not common in accelerator design, so usually, in principle, $(1/\rho_y)$ and consequently η_y are zero all around the ring. It can be proved that nonzero η_y affects ξ_u calculation in vertical bending magnets but doesn't affect that in other elements. Therefore, the contribution to ξ_u from vertical bending magnets, treated as a special case, is excluded from consideration for a while and will be described in section G.

A few special points related to a magnet are denoted by the subscripts illustrated in Fig.10, among which "m" denotes the midpoint, "0" just before the entrance, "1" just after the entrance, "2" just before the exit and "3" just after the exit. In other words, at an entrance, $b = 0$, $a = e = 1$; and at an exit, $b = e = 2$, $a = 3$. Note that "e" always denotes the edge point inside the magnet.

Fig.10 Definition of subscripts m, 0, 1, 2 and 3

3.) Inserting Eq.(F-8) into Eq.(B-13) and neglecting the terms that are irrelative to the linear CHR, one comes to two equations which are comparable with Eq.(F-2) :

$$\begin{aligned} x_{\beta}' + F_x x_{\beta} &= \left(K + \frac{2}{\rho^2} \right) \delta x_{\beta} - \left(\lambda + \frac{4K}{\rho} + \frac{2}{\rho^3} \right) \eta_x \delta x_{\beta} + \frac{1}{\rho} \eta_x' \delta x_{\beta}' + \dots ; \\ y_{\beta}' + F_y y_{\beta} &= -K \delta y_{\beta} + \left(\lambda + \frac{2K}{\rho} \right) \eta_x \delta y_{\beta} + \frac{1}{\rho} \eta_x' \delta y_{\beta}' + \dots \end{aligned} \quad (F-9)$$

Eq.(F-9) is valid for continuous and piecewisely constant field magnets. It means

$$\begin{aligned} Q_x &= K + \frac{2}{\rho^2} - \left(\lambda + \frac{4K}{\rho} + \frac{2}{\rho^3} \right) \eta_x ; \quad Q_y = -K + \left(\lambda + \frac{2K}{\rho} \right) \eta_x ; \\ R_x &= R_y = \frac{1}{\rho} \eta_x' \end{aligned} \quad (F-10)$$

4.) The edge effect expressions, Eq.(D-9), are treated in the same way. It is advisable to express $\overline{T}_{ue}$, $\overline{P}_{ue}$, etc. by functions inside the magnet edges, i.e. those with subscript $e = 1$ or 2 . Eq.(E-2) is useful in replacing η'_{ub} by η'_{ue} and other parameters. The transformation is needed only for the entrance. Many terms in Eq.(D-9) are ignored since they have nothing to do with the linear CHR, such as the y^2 or $y y'$ terms in x and x' increments, which seem the most confusing. After being compared with Eqs.(F-3) and (F-4), the results are

$$\overline{P}_{xe} = -\overline{P}_{ye} = \Delta_e \frac{1}{\rho} \eta_{xe} t_e^2 ;$$

$$\overline{R}_{xe} = -\Delta_e \frac{1}{\rho} \eta_{xe} (1 + t_e^2) ; \quad \overline{R}_{ye} = -\Delta_e \frac{1}{\rho} \eta_{xe} (1 - t_e^2) ;$$

$$\overline{Q}_{xe} = K_e - (\lambda_e + \lambda_{xe}^{(2)}) \eta_{xe} - \Delta_e \frac{1}{\rho} \eta'_{xe} (1 + t_e^2) ;$$

$$\overline{Q}_{ye} = -K_e + (\lambda_e + \lambda_{ye}^{(2)}) \eta_{xe} + \Delta_e \frac{1}{\rho} \eta'_{xe} (1 + t_e^2) \quad (F-11)$$

where $\lambda_{ue}^{(2)}$'s are given by $\lambda_{x1}^{(2)} = -\frac{1}{\rho^2} t_1 (1 - t_1^2)$, $\lambda_{x2}^{(2)} = \frac{1}{\rho^2} t_2^3$,

$$\lambda_{y1}^{(2)} = \frac{1}{\rho^2} t_1^3, \quad \lambda_{y2}^{(2)} = \frac{1}{\rho^2} t_2 (1 + t_2^2) .$$

One has to put Eq.(F-11) into Eq.(F-7) twice, for the entrance and for the exit respectively. The distinction between α_{ua} and α_{ub} is important in this step. Then the results can be expressed by α_{ue} , the α_u value inside the magnet, with the help of Eq.(E-2). At last, maybe to a pleasant surprise, one finds two uniform expressions of $\overline{T}_{ue}$ as

$$\overline{T}_{xe} = \beta_{xe} (v_e + \lambda_{xe} \eta_{xe}) - \Delta_e \frac{1}{\rho} \alpha_{xe} \eta_{xe} (1 + 2 t_e^2) ;$$

$$\overline{T}_{ye} = -\beta_{ye} (v_e + \lambda_{ye} \eta_{xe}) - \Delta_e \frac{1}{\rho} \alpha_{ye} \eta_{xe} (1 - 2 t_e^2) \quad (F-12)$$

with $v_e = -K_e + \lambda_e \eta_{xe} + \Delta_e \frac{1}{\rho} \eta'_{xe} (1 + t_e^2) ;$

$$\lambda_{xe} = \frac{2}{\rho^2} t_e^3 ; \quad \lambda_{ye} = \frac{1}{\rho^2} t_e \quad (F-13)$$

Remember that the edge sextupole effects look asymmetric when represented by the equations in section D. Now it is clear that the reason is the evaluation of the parameter u'_b at asymmetric points. If expressed by the functions evaluated at the points that are symmetric with each other, $\overline{T}_{ue}$ is perfectly symmetric. This means that, if all the functions (β_u and η_u) and parameters (θ_e and r_e) in a magnet are in mirror symmetry about the midpoint, the contributions to the linear CHR from the two edges, or more generally, from the two halves are exactly the same. This is true for both x and y planes.

A comparison of Eqs.(F-6) and (F-10) with Eqs.(F-12) and (F-13) shows that a bending magnet edge behaves as a quadrupole-sextupole combined magnet. The effect varies with transverse planes (x or y), having the explicit difference that is seen in λ_{xe} and λ_{ye} ; but it doesn't vary with edges (entrance or exit). It seems interesting that a study for dispersion function distortion³⁾ draws a similar conclusion, giving the "plane dependent sextupole components" λ_{ue} expressed by the exactly same formulae. The terms $\Delta_e \alpha_{ue} \eta_{xe}/\rho$ and $\Delta_e \beta_{ue} \eta'_{xe}/\rho$ don't have factors of θ_e or $(1/r_e)$, so they always exist at bending magnet edges, regardless of what the edges are like. They are "normal edge terms", representing the effect of normal edges (sector magnet edges), or rather, a part of the effect of the banding magnets themselves.

One more conclusion which also seems interesting can be drawn when one tries to calculate the linear dependence of the oscillation amplitude increment per turn on energy deviation and find

$$\int_1^2 R_u dz + (\overline{P_{u1}} + \overline{R_{u1}} + \overline{P_{u2}} + \overline{R_{u2}}) = 0 \quad (F-14)$$

for any kind of magnets. This holds even if $(1/\rho)$ is not constant in the magnet. In that case, a more general expression is derived from Eqs.(B-16) and (B-17), and gives $R_u = (1/\rho)' \eta_x + \eta_x'/\rho$, so that $\int_1^2 R_u dz$ still cancels out $\sum_{e=1,2} (\overline{P_{ue}} + \overline{R_{ue}})$ entirely. This means that the transverse oscillation of a particle with any energy would neither be excited nor be damped, as long as the energy deviation was small and such energy change mechanisms as synchrotron radiation or the compensation from RF cavity was excluded from consideration. Again, this statement is correct for both x and y planes.

5.) The complete expressions of the linear CHR are readily obtained by putting Eqs.(F-10) and (F-12) into Eq.(F-6) :

$$\begin{aligned}
\xi_x &= \frac{1}{4\pi} \oint \left(\frac{1}{\rho} \alpha_x \eta_x' - \left(\kappa + \frac{2}{\rho^2} \right) \beta_x + \left(\lambda + \frac{4\kappa}{\rho} + \frac{2}{\rho^3} \right) \beta_x \eta_x \right) dz \\
&\quad + \frac{1}{4\pi} \sum_e \left(\beta_{xe} (v_e + \lambda_{xe} \eta_{xe}) - \Delta_e \frac{1}{\rho} \alpha_{xe} \eta_{xe} (1 + 2t_e^2) \right) ; \\
\xi_y &= \frac{1}{4\pi} \oint \left(\frac{1}{\rho} \alpha_y \eta_y' + \kappa \beta_y - \left(\lambda + \frac{2\kappa}{\rho} \right) \beta_y \eta_y \right) dz \\
&\quad - \frac{1}{4\pi} \sum_e \left(\beta_{ye} (v_e + \lambda_{ye} \eta_{ye}) + \Delta_e \frac{1}{\rho} \alpha_{ye} \eta_{ye} (1 - 2t_e^2) \right) \quad (F-15)
\end{aligned}$$

where v_e , λ_{xe} and λ_{ye} are given by Eq.(F-13), the integrals are calculated for all the magnets and the sums for all the magnet edges, with α_{ue} and η_{xe}' evaluated inside the magnet.

G. Formulae for Practical Linear CHR Calculation

1.) Eq.(F-15) is a simple theoretical formula and can be evaluated via any numerical integral calculation method. However, it is not very good for practical computer programs, because a step-by-step evaluation and addition usually takes a long time and results in some uncertainty associated with the method, the step length, etc. Ref.5) presents many useful formulae for calculating the function integrals that are used by accelerator physicists most frequently, expressing them in terms of the function values at the both ends or at the midpoint of the magnet. This note will make use of a few such formulae, whose derivation can be found in Ref.5).

First, introduce a piecewise constant $A_{\beta u}$ as

$$A_{\beta u} = F_u \beta_u + \gamma_u \quad (G-1)$$

where F_u is defined by Eq.(F-5). It is easy to prove that $A_{\beta u}' = 0$ as long as $\beta_u' = 0$ in a magnet, since the Twiss functions obey

$$\beta_u' = -2 \alpha_u ; \quad \alpha_u' = F_u \beta_u - \gamma_u ; \quad \gamma_u' = 2 F_u \alpha_u \quad (G-2)$$

Therefore, $A_{\beta u}$ can be evaluated at any point in the magnet being studied, say the midpoint or either one of the ends.

It follows from Eqs.(G-1) and (G-2) that

$$\int_1^2 \alpha_u \eta_x' dz = \sum_{e=1,2} \Delta_e (\alpha_{ue} \eta_{xe}) + \int_1^2 (A_{\beta u} - 2 F_u \beta_u) \eta_x dz \quad (G-3)$$

Inserting Eq.(G-3) into Eq.(F-15), one arrives at

$$\begin{aligned} \xi_x &= \frac{1}{4\pi} \oint \left(- \left(K + \frac{2}{\rho^2} \right) \beta_x + \left(\lambda + \frac{2K}{\rho} \right) \beta_x \eta_x + \frac{1}{\rho} A_{\beta x} \eta_x \right) dz \\ &\quad + \frac{1}{4\pi} \sum_e \left(\beta_{xe} (v_e + \lambda_{xe} \eta_{xe}) - \Delta_e \frac{2}{\rho} \alpha_{xe} \eta_{xe} t_e^2 \right); \\ \xi_y &= \frac{1}{4\pi} \oint \left(K \beta_y - \lambda \beta_y \eta_x + \frac{1}{\rho} A_{\beta y} \eta_x \right) dz \\ &\quad - \frac{1}{4\pi} \sum_e \left(\beta_{ye} (v_e + \lambda_{ye} \eta_{xe}) - \Delta_e \frac{2}{\rho} \alpha_{ye} \eta_{xe} t_e^2 \right) \end{aligned} \quad (G-4)$$

Eq.(G-4) is equivalent to Eq.(F-15), but has some features to be noted: The calculation for $\int \beta_y \cdot \eta_x dz$ is not necessary for bending magnets and neither is that for $\int \beta_x \cdot \eta_x dz$ in a separate function machine where K/ρ is zero all around. The integral $(\int \eta_x dz)/\rho$, which appears in the equations for both ξ_x and ξ_y , is by no means a problem, since it has to be found for momentum compaction factor. A part of the normal edge effect, $-\Delta_e \alpha_{ue} \eta_{xe}/\rho$, is cancelled out.

2.) Three kinds of integrals are involved in Eq.(G-4). The formulae to calculate them are as follows:

a) Case 1. To evaluate the integrals with function values at the both ends of the magnet, under the condition $F_u \neq 0$, one has

$$\begin{aligned} \int_1^2 \beta_u dz &= \frac{1}{2F_u} (A_{\beta u} L + \alpha_{u2} - \alpha_{u1}) ; \\ \int_1^2 \eta_u dz &= \frac{1}{F_u} \left(\frac{L}{\rho} - \eta'_{u2} + \eta'_{u1} \right) ; \\ \int_1^2 \beta_u \eta_u dz &= \frac{1}{3F_u} \left(2 A_{\beta u} \int_1^2 \eta_u dz - \frac{1}{\rho} \int_1^2 \beta_u dz + 2 \alpha_{u2} \eta_{u2} \right. \\ &\quad \left. + \beta_{u2} \eta'_{u2} - 2 \alpha_{u1} \eta_{u1} - \beta_{u1} \eta'_{u1} \right) \end{aligned} \quad (G-5)$$

Note: $L = z_2 - z_1$ is the effective length of the magnet.

b) Case 2. Suppose $F_u = 0$, then

$$\begin{aligned}\int_1^2 \beta_u dz &= \frac{1}{2} (\beta_{u1} + \beta_{u2}) L - \frac{1}{6} \gamma_{ui} L^3 ; \\ \int_1^2 \eta_u dz &= \frac{1}{2} (\eta_{u1} + \eta_{u2}) L - \frac{1}{12} \rho L^3 ; \\ \int_1^2 \beta_u \eta_u dz &= \frac{1}{L} \left(\int_1^2 \beta_u dz \right) \left(\int_1^2 \eta_u dz \right) - \frac{1}{12} (\alpha_{u1} \eta'_{u2} + \alpha_{u2} \eta'_{u1} \\ &\quad - \frac{8}{15} \rho \gamma_{ui} L^2) L^3\end{aligned}\quad (G-6)$$

A special case is for sextupoles where both $(1/\rho)$ and K are zero :

$$\int_1^2 \beta_u \eta_x dz = \frac{1}{2} (\eta_{x1} + \eta_{x2}) \int_1^2 \beta_u dz - \frac{1}{12} (\alpha_{u1} \eta'_{x2} + \alpha_{u2} \eta'_{x1}) L^3$$

Note: Subscript i is either 1 or 2. A piecewise constant can be evaluated at any point in the magnet and "i" is used to denote this arbitrariness, e.g. $\beta_u = F_u \cdot \beta_{ui} + \gamma_{ui}$.

c) Case 3. To evaluate the integrals with function values at the magnet midpoint, it is better to make use of function S_u , defined by

$$S_u(z) = \sum_{n=0}^{\infty} (-F_u)^n z^{2n+1} / (2n+1)! = \begin{cases} \sin(\sqrt{F_u} z) / \sqrt{F_u} , & \text{if } F_u > 0 \\ z , & \text{if } F_u = 0 \\ \sinh(\sqrt{-F_u} z) / \sqrt{-F_u} , & \text{if } F_u < 0 \end{cases} \quad (G-7)$$

It is seen that S_u is the piecewise sine-like solution of the first order non-dispersion particle motion equation $u'' + F_u u = 0$. It is usually known as a transfer matrix element, M_{12} , and, as well as the cosine-like solution $C_u(z) \approx S_u'(z)$, it plays a role in many accelerator physics programs. Besides that, C_u and S_u have many valuable properties and, therefore, can help much in formula simplification. For example, they provide the convenience that most expressions involved will be independent on the sign of F_u . A detailed description for them can be found in the appendix of Ref.5).

Let a few variables be evaluated as

$$Q_1 = 2 S_u \left(\frac{L}{2} \right) ; \quad Q_3 = \frac{1}{12} Q_1^3 ; \quad P_1 = \frac{1}{2 F_u} (L - S_u(L)) ;$$

$$P_2 = \frac{1}{F_u} (L - Q_1) ; \quad P_3 = \frac{1}{F_u} (P_1 - Q_3) \quad (G-8)$$

here F_u is supposed non-zero. If $F_u = 0$, these variables are given by

$$Q_1 = L ; \quad Q_3 = P_1 = \frac{1}{12} L^3 ; \quad P_2 = \frac{1}{2} Q_3 ; \quad P_3 = 0.15 P_2 L^2 \quad (G-9)$$

One can prove that Eq. (G-9) is the mathematical limit of Eq. (G-8) as F_u goes down to zero.

Then the integrals are easy to find by

$$\int_1^2 \beta_u dz = \frac{1}{2} \beta_{um} (L + S_u(L)) + \gamma_{um} P_1 ;$$

$$\int_1^2 \eta_u dz = \eta_{um} Q_1 + \frac{1}{f} P_2 ;$$

$$\int_1^2 \beta_u \eta_u dz = \beta_{um} \eta_{um} (Q_1 - F_u Q_3) + (\gamma_{um} \eta_{um} - 2 \alpha_{um} \eta'_{um}) Q_3$$

$$+ \frac{1}{f} \beta_{um} (P_2 - F_u P_3) + \frac{1}{f} \gamma_{um} P_3 \quad (G-10)$$

A special case is for sextupoles where both $(1/f)$ and K are zero :

$$\int_1^2 \beta_u \eta_x dz = \beta_{um} \eta_{xm} L + \frac{1}{12} (\gamma_{um} \eta_{xm} - 2 \alpha_{um} \eta'_{xm}) L^3 \quad (G-11)$$

3.) Usually, the linear CHR as well as some other machine parameters are obtained by adding up many terms, each of them arising from a magnet.

This routine is represented by

$$\xi_u = \frac{1}{4\pi} \sum_M T_{uM} \quad (G-12)$$

The subscript "M", denoting a magnet, may be "S" for sextupoles, "Q" for quadrupoles, "B" for bending magnets or "e" for bending magnet edges. A bending magnet with its both edges, considered as a whole, is denoted by "Be". The following is how to treat T_{uM} for every type of magnets.

a) Sextupoles are installed in drift sections where $(1/\rho) = K = 0$, and applied for CHR correction. Usually one's knowledge about a sextupole is its effective length and the position of its midpoint, where the machine functions have been found. So Eq.(G-11) is used, giving

$$T_{us} = \overline{sg}_u \cdot \lambda \cdot L \left(\beta_{um} \eta_{xm} + \frac{1}{12} \left(\gamma_{um} \eta_{xm} - 2 \alpha_{um} \eta'_{xm} \right) L^2 \right) \quad (G-13)$$

where the symbol $\overline{sg}_u$ is defined as : $\overline{sg}_x = 1$, $\overline{sg}_y = -1$. The terms that contain L^2 can be ignored, if L and $|\alpha_{um}| L$ are both by far less than β_{um} .

b) Contributions from quadrupoles are the dominant terms of Eq.(G-12) in natural linear CHR calculation. By "natural" we mean no sextupoles are taken into account. Eq.(G-5) is very convenient in this case, yielding

$$T_{uQ} = - \int_1^2 F_u \beta_u dz = \frac{1}{2} \left((-\overline{sg}_u \cdot K \cdot \beta_{ui} - \gamma_{ui}) L - \alpha_{u2} + \alpha_{u1} \right) \quad (G-14)$$

with $i = 1$ or 2 . If the quadrupole has inclined edges, an additional edge effect term arises from either edge as

$$T_{ue(Q)} = - 2 \overline{sg}_u \cdot K \cdot \beta_{ue} \cdot \eta_{xe} \tan \theta_e \quad (G-15)$$

c) For a horizontal bending magnet of any type, Eq.(G-4) is directly turned into

$$\begin{aligned} T_{xB} &= - \left(K + \frac{2}{\rho^2} \right) \int_1^2 \beta_x dz + \frac{2K}{\rho} \int_1^2 \beta_x \eta_x dz \\ &\quad + \frac{1}{\rho} \left(\left(K + \frac{1}{\rho^2} \right) \beta_{xi} + \gamma_{xi} \right) \int_1^2 \eta_x dz ; \\ T_{yB} &= K \int_1^2 \beta_y dz - \frac{1}{\rho} \left(K \beta_{yi} - \gamma_{yi} \right) \int_1^2 \eta_x dz \end{aligned} \quad (G-16)$$

where the integrals are calculated with either Eqs.(G-5) and (G-6), or Eqs.(G-7) through (G-10), depending only on one's preference. Computer time can be saved if this calculation is done together with finding other parameters, such as momentum compaction factor and beam equilibrium size, for which a few useful formulae are also given in Ref.5). It may be noted

that those relatively complicated integrals are required only for bending magnets, and that the variables evaluated by Eq.(G-8) or (G-9) are also useful for calculating the other parameters. It appears recommendable to find $S_u (L/2)$ as well as β_{um} , η_{um} , etc. by making a half-element transfer matrix, namely, by dividing each bending magnet into two halves, with an associated consequence that the machine functions at its midpoint are ready to be displayed. The latter point is desirable for synchrotron radiation facilities. Of course, the functions at the midpoint can be found from the functions at the both edges, and the relevant formulae are also listed in Ref.5). The final results will be equivalent to Eqs.(G-5) and (G-6).

d) Bending magnet edges make their contributions by

$$T_{ue} = \overline{sq}_u \cdot (\beta_{ue} (v_e + \lambda_{ue} \eta_{xe}) - \Delta_e \frac{2}{\rho} \alpha_{ue} \eta_{xe} \tan^2 \theta_e) \quad (G-17)$$

$$\text{with } v_e = \frac{1}{\rho} \tan \theta_e - \eta_{xe} (2 K \tan \theta_e + \frac{1}{\rho r_e \cos^3 \theta_e}) + \Delta_e \frac{1}{\rho} \eta'_{xe} (1 + \tan^2 \theta_e);$$

$$\lambda_{xe} = \frac{2}{\rho^2} \tan^3 \theta_e ; \quad \lambda_{ye} = \frac{1}{\rho^2} \tan \theta_e \quad (G-18)$$

Note: all the functions are evaluated on the inner side of the edge.

e) The last case to be considered in this subsection is vertical bending magnets and their edges. This magnet type is considered as a special case because it is seldom seen in accelerators. An example is rotated wiggler. An inspection into Eqs.(B-14) and (D-10) tells how to evaluate T_{uVB} and T_{uVe} , the contributions from a vertical bending magnet and from one of its edges respectively, by a simple transformation of Eqs.(G-16) through (G-18). The transformation is to exchange x with y , including any functions associated with the transverse planes, to replace ρ by $-\rho_y$ and to replace K by $-K$. Then it is worked out as

$$T_{xVB} = -K \int_1^2 \beta_x dz - \frac{1}{\rho_y} (K \beta_{xi} + \gamma_{xi}) \int_1^2 \eta_y dz ;$$

$$T_{yVB} = (K - \frac{2}{\rho_y^2}) \int_1^2 \beta_y dz + \frac{2K}{\rho_y} \int_1^2 \beta_y \eta_y dz \\ + \frac{1}{\rho_y} ((K - \frac{1}{\rho_y^2}) \beta_{yi} - \gamma_{yi}) \int_1^2 \eta_y dz ;$$

$$T_{uVe} = \overline{sg}_u \cdot (\beta_{ue} (v_{Ve} + \lambda_{Rue} \eta_{ye}) - \Delta_e \frac{2}{\rho_y} \alpha_{ue} \eta_{ye} \tan^2 \theta_e) ;$$

$$\text{with } v_{Ve} = \frac{1}{\rho_y} \tan \theta_e - \eta_{ye} (2K \tan \theta_e + \frac{1}{\rho_y r_e \cos^3 \theta_e}) + \Delta_e \frac{1}{\rho_y} \eta'_{ye} (1 + \tan^2 \theta_e) ;$$

$$\lambda_{Rxe} = -\frac{1}{\rho_y^2} \tan \theta_e ; \quad \lambda_{Rye} = -\frac{2}{\rho_y^2} \tan^3 \theta_e \quad (G-19)$$

The linear CHR problem is well solved by carrying out Eqs. (G-12) through (G-19) in a program. If the machine is multi-fold, say, an end of the beamline is the midpoint of a bending magnet as a symmetry point, one only has to add up $\sum_M T_{uM}$ for one beamline and then multiply it by the number of beamlines.

4.) The above equations are so general as to suit a universal program. Of course, they can be simplified if one is designing a special purpose program for a certain machine type. For instance, in a ring where all the bending magnets are sectors, the edge effect will be simply

$$T_{ue} = \overline{sg}_u \cdot \Delta_e \frac{1}{\rho} \beta_{ue} \eta'_{xe} \quad (G-20)$$

that is the normal edge term.

a) A type of accelerators, separate function synchrotron/storage ring, is perhaps adopted most commonly nowadays in machine design and therefore deserves more attention. In those rings all the bending magnets are flat, or in mathematics language, any element with $(1/\rho) \neq 0$ is featured by

$$K = 0 ; \quad F_x = \frac{1}{\rho^2} ; \quad F_y = 0 \quad (G-21)$$

Putting Eq.(G-21) into Eqs.(G-5), (G-6), and (G-16) finally, one obtains

$$\begin{aligned} T_{xB} &= - \sum_{1,2} \Delta_e \left(\alpha_{xe} + \frac{1}{\rho} \beta_{xe} \eta'_{xe} + \rho \gamma_{xe} \eta'_{xe} \right) ; \\ T_{yB} &= \gamma_{yi} \left(L - \rho \left(\eta'_{x2} - \eta'_{x1} \right) \right) \\ &= - \sum_{1,2} \Delta_e \left(\alpha_{ye} + \rho \gamma_{ye} \eta'_{xe} \right) \end{aligned} \quad (G-22)$$

The expression for T_{yB} is based on the fact that, in this case, γ_y is a piecewise constant and $\gamma_y L = \alpha_{y1} - \alpha_{y2}$. The equation for T_{yB} is thus so similar to that for T_{xB} , except the extra term there, which equals to $-\sum_{1,2} \Delta_e \beta_{xe} \eta'_{xe} / \rho$ and exactly cancels out the normal edge effect term. Consequently, in a separate function machine, the contributions to ξ_u from a bending magnet plus its edges are

$$\begin{aligned} T_{xBe} &= \sum_{1,2} \left(\beta_{xe} \left(-\kappa_e + \lambda_e \eta_{xe} + \frac{2}{\rho^2} \eta_{xe} \tan^3 \theta_e \right) - \Delta_e \left(\alpha_{xe} \right. \right. \\ &\quad \left. \left. + \rho \gamma_{xe} \eta'_{xe} + \frac{1}{\rho} \tan^2 \theta_e \left(2 \alpha_{xe} \eta_{xe} - \beta_{xe} \eta'_{xe} \right) \right) \right) ; \\ T_{yBe} &= \sum_{1,2} \left(\beta_{ye} \left(\kappa_e - \lambda_e \eta_{xe} - \frac{1}{\rho^2} \eta_{xe} \tan \theta_e \right) - \Delta_e \left(\alpha_{ye} + \rho \gamma_{ye} \eta'_{xe} \right. \right. \\ &\quad \left. \left. + \frac{1}{\rho} \beta_{ye} \eta'_{xe} - \frac{1}{\rho} \tan^2 \theta_e \left(2 \alpha_{ye} \eta_{xe} - \beta_{ye} \eta'_{xe} \right) \right) \right) \end{aligned} \quad (G-23)$$

Calculation for integrals is entirely avoided.

b) Two special cases are quite frequently met with and further study has been done for them, in an attempt to express T_{uBe} by functions at the bending magnet midpoint only. Being a bit too complicated, the results help little in practical calculation. However, they really help estimate the contributions to the linear CHR from all the bending magnets in a separate function ring.

Case 1. Sector bending magnets, i.e. $\theta_1 = \theta_2 = (1/r_e) = 0$.

$$T_{xBe} = \left(-\frac{1}{\rho} \beta_{xm} + \rho \gamma_{xm} + (\gamma_{xm}(\eta_{xm} - \rho) - 2\alpha_{xm}\eta'_{xm}) \cos(\theta_B/2) \right) \sin \theta_B \\ + \frac{2}{\rho^2} \beta_{xm}(\eta_{xm} - \rho) \sin^3(\theta_B/2) ;$$

$$T_{yBe} = \rho \gamma_{ym} \theta_B + 2(\eta_{xm} - \rho)(\gamma_{ym} + \frac{1}{\rho^2} \beta_{ym}) \sin(\theta_B/2) \\ + 2\alpha_{ym}\eta'_{xm} \theta_B \cos(\theta_B/2) + \frac{1}{2} \gamma_{ym}(\eta_{xm} - \rho) \theta_B^2 \sin(\theta_B/2)$$

where $\theta_B = L/\rho$ is the bending angle. Suppose θ_B is small, an approximation to first order of θ_B gives

$$T_{xBe} \doteq \theta_B \left(-\frac{1}{\rho} \beta_{xm} + \gamma_{xm} \eta_{xm} - 2\alpha_{xm}\eta'_{xm} \right) ;$$

$$T_{yBe} \doteq \theta_B \left(-\frac{1}{\rho} \beta_{ym} + \frac{1}{\rho^2} \beta_{ym} \eta_{xm} + \gamma_{ym} \eta_{xm} + 2\alpha_{ym}\eta'_{xm} \right)$$

Note that $(\sum_B \theta_B)/(4\pi) = 1/2$. Therefore, in this case, the contributions to ξ_u from all the bending magnets in the ring are roughly half the average value of the functions in the parentheses, however small θ_B is. In general, $\alpha_{xm}\eta'_{xm}$ is more probably negative while $\alpha_{ym}\eta'_{xm}$ more probably positive. Suppose $\eta_{xm} > 0$ in most bending magnets. If $\rho \gg \beta_{um}$ anywhere, i.e. in a big machine, all the bending magnets are likely to contribute to both ξ_x and ξ_y by small positive quantities. In small rings where $\rho \lesssim \beta_{um}$, however, the contributions are often negative.

Case 2. Rectangular (parallel side) bending magnets, with $(1/r_e) = 0$, $\theta_1 = \theta_2 = \theta_B/2$.

$$T_{xBe} = 2 \tan(\theta_B/2) \left(\rho \gamma_{xm} (1 + 2 \tan^2(\theta_B/2)) \right. \\ \left. + (\gamma_{xm}(\eta_{xm} - \rho) - 2\alpha_{xm}\eta'_{xm}) / \cos(\theta_B/2) \right) ;$$

$$\begin{aligned}
T_{yBe} = & -\frac{4}{\rho} \beta_{ym} \tan(\theta_B/2) + \frac{2}{\rho^2} \beta_{ym} (\eta_{xm} - \rho) \sin(\theta_B/2) \tan^2(\theta_B/2) \\
& + \rho \gamma_{ym} \theta_B (1 - \theta_B \tan(\theta_B/2) - 2 \tan^2(\theta_B/2)) \\
& + 2 \gamma_{ym} (\eta_{xm} - \rho) \sin(\theta_B/2) (1 - \frac{1}{2} \theta_B \tan(\theta_B/2))^2 \\
& + 2 \alpha_{ym} \eta'_{xm} (\theta_B \cos(\theta_B/2) (1 + 2 \tan^2(\theta_B/2)) + 2 \sin(\theta_B/2) \tan^2(\theta_B/2))
\end{aligned}$$

The terms of first power of θ_B are

$$T_{xBe} \doteq \theta_B (\gamma_{xm} \eta_{xm} - 2 \alpha_{xm} \eta'_{xm}) ;$$

$$T_{yBe} \doteq \theta_B (-\frac{2}{\rho} \beta_{ym} + \gamma_{ym} \eta_{xm} + 2 \alpha_{ym} \eta'_{xm})$$

In this case, provided $\eta_{xm} > 0$, the contribution to ξ_x from all the bending magnets is probably a small positive number; while that to ξ_y tends to be negative, if β_{ym} is not by far less than ρ , in other words, in small accelerators.

H. Remarks on the Linear CHR Calculation

The equations in section G have the following noteworthy features:

a) They are general enough to cover almost all common magnet types in various accelerator rings. b) They are based on, in the sense "up to second order", the complete particle motion equations and the mathematical treatment is strict. c) They are simpler than presented elsewhere.

Comparison between these equations and their correspondents shows a significant difference with Ref.1), where the formulae of contributions to the linear CHR from an entrance edge and from an exit edge are not symmetric. This is being discussed with the authors. It was the authors of Ref.1) who gave me the first insight into the second order hard edge effects, and this note resulted from trying to follow the approach they had used and, because differences were seen almost at the very beginning, trying to find an agreement. Being relatively simple in mathematics but clear in physics concepts, the approach in Ref.1) is really attractive and reliable. However, to follow it and arrive at a complete picture of

hard edge effects and of the linear CHR needs a very careful treatment and strict handling of many second order terms, some of them so easy to neglect by error. As a matter of fact, I found several times that certain terms were missed in my derivation. Besides, there is something I feel necessary to distinguish in the treatment, e.g. "coordinate edge" and real magnet edge, d_u at the inside or the outside point of an edge; but the distinction is not made in Ref.1).

Ref.2) makes use of δ -function to describe edge effects, and thereby the discontinuity of d_u and η_x' at a hard edge becomes a problem in the treatment. The authors solved it by taking, for example, $(\eta_{xb}' + \eta_{xa}')/2$ as the average value of η_x' at the edge. This is surely an acceptable approach, while the approach of this note completely avoids that problem by, for linear CHR calculation, having all the mathematical treatments strictly in accord with hard edge approximation. It seems the difference between these two approaches, both approximately representing the actual edge fields, is of no practical significance.

The equations in sections G and F are embodied in computer programs, LAMP⁶⁾ for example, and evaluated for SPEAR and the Hefei 800 MeV storage ring. The results differ obviously from those "old" programs that neglect the effects of bending magnets and their edges, but agree very satisfactorily with the programs that have taken the effects into consideration. The natural chromaticities obtained by program LAMP, both for the Hefei ring ($\rho = 2.2 \text{ m}$) and for SPEAR ($\rho = 12.8 \text{ m}$), agree quite well with those given by COMFORTS, a program calculating the CHR with the formulae in Ref.2). The relative differences are less than 10^{-4} .

Acknowledgement

The author is indebted to S.Chen, S.Fang, C.Zhang and N.Huang of Beijing High Energy Physics Institute for their help in the study on edge effects. The author thanks A.W.Chao and M.J.Lee for their kind support and beneficial discussions. Comments and suggestions from J.Jäger are pleasantly acknowledged since they contributed to the discovery of an improper negligence. Discussions with M.H.R.Donald, L.Chen and Y.Kamiya are also helpful.

References

- 1) Chen Senyu, Fang Shouxian and Zhang Chuang, "The First- and Second- Order Edge Field Effect on Particle Motion Described in Curvilinear System", Internal Paper of Beijing High Energy Physics Institute, China, Dec. 1981.
- 2) W.Hardt, J.Jäger and D.Möhl, "A General Analytical Expression for the Chromaticity of Accelerator Rings", PS/LEA/Note 82-5, Nov. 1982.
- 3) R.Z.Liu, "Dispersion Function and Closed Orbit Distortion in Accelerator Rings", to be published.
- 4) K.L.Brown, "A First- and Second- Order Matrix Theory for the Design of Beam Transport Systems and Charged Particle Spectrometers", SLAC-75, Rev.3, Aug. 1972
- 5) R.Z.Liu, "Techniques in Machine Function Integral Calculation", to be published.
- 6) R.Z.Liu, Program "LAMP", March 1983.