VIBRATION STUDY OF THE APS STORAGE RING 0.8 METER QUADRUPOLE MAGNET/MAGNET SUPPORT ASSEMBLY

by

J. A. Jendrzeczyk, M. W. Wambsganss, and R. K. Smith
Materials and Components Technology Division
Argonne National Laboratory

Received
APR 27 1992

BACKGROUND

Several vibration studies relating to the vibration of storage ring components, in particular, the section 3 girder vacuum chamber, and quadrupole magnet were previously reported [1-3]. In [3], the vibration response of the magnet/girder system and the girder, loaded with concrete blocks, with and without the magnet was reported. The Phase I tests (with the magnet mounted on the girder) indicated a dominant mode, with small damping, at a frequency of 7.62 Hz. It was not known if the large displacement response resulted from a coupled magnet/girder resonance or the resonance of either the magnet or girder alone. Therefore, Phase II tests, with the quadrupole magnet removed, but all simulated magnets (concrete blocks) remaining, were conducted. It was shown that the large response was associated with the dynamics of the girder jackscrew/pedestal assemblies. In this study, the 0.8 meter quadrupole is decoupled from the girder and is tested to determine its vibration characteristics.

OBJECTIVES

The objectives of this study are as follows:

- Determine the vibration characteristics (frequency, damping, and mode shapes) of the magnet on prototypic supports (the actual mounting system used to mount the magnet on the girder).
- Measure system response to ambient floor motion.
- Measure the effect of various modifications to determine if the magnet response can be modified to minimize unwanted response

MASTER

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

characteristics. Modifications investigated include support schemes, increasing system damping, and increasing mechanical rigidity.

- Measure system response to coolant flow.
- Determine vibrational characteristics of a large concrete block placed on a concrete floor, including response to ambient floor motions.

TECHNICAL APPROACH

An objective of this study was to measure the dynamic characteristics of the magnet and its support assemblies. To accomplish this, it is necessary to mount the magnet assembly on a surface which does not contribute to its response. For the initial series of tests the magnet was mounted on a 8100 pound concrete shielding block which rested on the 7-inch thick concrete floor of Building 335 Highbay. Due to inherent unevenness in the surfaces between the block and floor, it was subsequently necessary to use a three-point contact between the block and floor. However, even with the three-point contact, block response could be observed. For the majority of tests, the magnet was mounted to or resting directly on the concrete, highbay floor.

A major objective of this study is to determine the effect of the three magnet support jackscrews on the system dynamics. Tests were conducted with and without the jackscrews to isolate their effect.

The magnet itself is assembled with many bolted joints. If the joints were not tight they could influence the dynamic response. Therefore, all loose bolts were tightened, and several schemes were used to increase overall rigidity of the magnet assembly. Several tests were conducted to determine the effect of magnet assembly rigidity on system dynamics.

During operation, the heat generated must be conducted away from the magnet coils. To achieve this, water is circulated through the coils. Even though the magnet weighs 3,800 pounds, because of the very small amplitudes of interest, the possibility of flow excitation requires investigation. Tests were performed at various flow rates up to 4.44 gpm (gallons per minute); design flowrate is 5 gpm.

TEST DESCRIPTION

Test article and mounting methods

The test article is the 0.8-meter quadrupole magnet. For the initial series of tests, it was mounted on an 8,100 pound concrete shielding block, see Fig. 1, assuming that a concrete mass of that size would provide a rigid base. One accelerometer triplet (three accelerometers mounted orthogonally on an aluminum block) was mounted on the top of the magnet to measure magnet response. Its location remained constant for all tests. Another accelerometer triplet was mounted to the top of the concrete shielding block. The exciter, which was mounted to the magnet top with the same bracket used in [3], was only used for specific tests, as noted in the Test Matrix. In the tests where it was not used, it was removed from the magnet. For selected tests, the magnet was mounted to the jackscrew/base assembly and placed on the floor as shown in Fig. 2. For other tests the magnet was placed on the floor without the jackscrew/base assembly, using the magnet mounting brackets as shown in Fig. 3.

Excitation methods

Three force excitation methods were employed: (1) An electrodynamic exciter was used to excite the magnet with either a random or sinusoidal force, with the objective to generate data for use in determining the system resonant frequencies and mode shapes. (2) An impulse force, generated by gently impacting the body of the magnet with a soft mallet, was used to obtain a response time history from which a quick approximation of system dynamics could be determined. (3) Ambient floor motion, representing a reasonable approximation to the actual amplitude levels which the storage ring will experience in the experimental hall, was used to excite the magnet.

Measurement methods

Vibration response was measured using an accelerometer triplet mounted on the top of the magnet, and, where applicable, an accelerometer triplet mounted on top of the concrete block. Accelerometer signals were double integrated to obtain displacements in the frequency range of 5-100 Hz. For the ambient excitation tests, the displacements were recorded on an FM tape recorder. The displacements were analyzed using a HP 5451 C Fast Fourier Spectrum Analyzer with a frequency range of 0-100 Hz and a filter bandwidth of 0.195 Hz. The analysis process was discussed in Appendix F of [3].

Figure 1. Magnet mounted on shielding block

Figure 2. Jackscrew/base assembly on building floor

Figure 3. Magnet on building floor

Specific objectives include determination of vibrational characteristics (natural frequencies, damping, mode shapes, and in some specific tests, magnification factors) of the magnet/jackscrew base assembly.

TEST MATRIX

This series of tests was conducted to gain insight into the dynamic response of the magnet/support system.

Test 1. Excitation: Electrical exciter mounted on top of magnet, providing random excitation in three orthogonal directions; impulse to body of magnet in three orthogonal directions; and ambient floor motion.

Mounting/mechanical conditions: Magnet is mounted using a prototypic support assembly, which is bolted to the concrete block

Measurement objectives: To determine the system resonant frequencies, mode shapes (using the vibration exciter), and system response to low level ambient floor motion. It should be noted that exciter excitation is at a much higher level than that provided by ambient floor motion.

Test 2. Excitation: Electrical exciter mounted on top of magnet providing random excitation in two orthogonal directions (X and Y); ambient floor motion; and impulse to body of magnet in two orthogonal directions (X and Y).

Mounting/mechanical conditions: Magnet is mounted using prototypic supports, with brass shims between support and concrete block, at the three jackscrew locations, to assure three-point contact. The support structure is bolted to the concrete block.

Measurement objectives: To compare system dynamics to those measured in Test 1 and, based on the comparison, to determine the importance of mounting conditions between magnet support structure and block.

Test 3. Excitation: Impulse to body of magnet in two orthogonal directions (X and Y).

Mounting/mechanical conditions: Magnet (with prototypic jackscrews and associated channel iron base removed) is placed on the floor of Building 335. A three-point support is approximated by placing three 3/4-inch nuts between the support and floor, two at the fabricated leg and one at the angle aluminum leg, approximating the jackscrew locations.

Measurement objectives: To measure system dynamics of magnet independent of the jackscrews and concrete block.

Test 4. Excitation: Impulse to body of magnet in two orthogonal directions (X and Y).

Mounting/mechanical conditions: Many of the 3/8-inch hex bolts on the magnet were loose. The bolts were tightened.

Measurement objectives: To determine the effect of the loose bolts on system dynamics, using Test 3 as a reference.

Test 5. Excitation: Impulse to body of magnet in the Y direction.

Mounting/mechanical conditions: A thick piece of metal was clamped as shown in Fig. 4 to each end of one side of the magnet to increase the rigidity of the bolted joints.

Measurement objective: To determine the effect of increased rigidity on system dynamics using Test 3 as a reference.

Test 6. Excitation: Impulse to body of magnet in the Y direction and ambient floor motion.

Mounting/mechanical conditions: Same as Test 3, except that the 3/4-inch nut on the angle aluminum leg is positioned to allow all the weight to bear on the angle.

Measurement objective: To determine the effect of loading of the aluminum angle on system dynamics.

Test 7. Excitation: Impulse to body of magnet in the Y direction.

Mounting/mechanical conditions: A large "C" clamp was used (see Fig. 5) to increase rigidity of one side of the magnet.

Measurement objective: To determine the effect of increased rigidity on system dynamics using Test 6 as a reference.

Test 8. Excitation: Impulse to body of magnet in the Y direction.

Mounting/mechanical conditions: Same as Test 6.

Figure 4. Clamping scheme for Test 5

Figure 5. Clamping scheme for Tests 7 and 9

Measurement objective: To verify that there is no permanent change in system dynamics when the clamp used in Test 7 is removed. Test 6 is used as a reference.

Test 9. Excitation: Impulse to body of magnet in the Y direction.

Mounting/mechanical conditions: This test is identical to Test 7, except the clamp is located on the other side of the magnet.

Measurement objectives: Same as Test 7.

Test 10. Excitation: Impulse to body of magnet in the Y direction.

Mounting/mechanical conditions: Magnet (with prototypic jackscrews and associated channel iron base removed) is placed on the floor of Building 335. Three 3/4-inch nuts are placed between the support and floor, with 1/8-inch neoprene pads placed between the nuts and floor. This test is identical to Test 3 except for the neoprene pads.

Measurement objective: To measure system dynamics with the neoprene pads in the critical (from a mode shape standpoint) location.

Test 11. Excitation: Impulse to body of magnet in the Y direction; ambient floor motion.

Mounting/mechanical conditions: Similar to Test 10, except the neoprene pads are replaced by 3/8-inch diameter ball bearings to more closely approximate an ideal three-point support.

Measurement objective: To determine system dynamics with magnet supported in a close to ideal three-point mount.

Test 12. Excitation: Impulse to body of magnet in the Y direction.

Mounting/mechanical conditions: Magnet is slung from crane using two nylon slings. Small pieces of wood are used to keep the slings from contacting the side of the magnet.

Measurement objectives: To determine the dynamic response of the magnet independent of any supports.

Test 13. Excitation: Impulse to body of magnet in the Y direction:

Mounting/mechanical conditions: Magnet is mounted on the jackscrew base, sitting on, but not bolted to the floor.

Measurement objective: To determine system response of the magnet-magnet support assembly, including the jackscrews where response is not influenced by the concrete block.

Test 14. Excitation: Impulse to body of magnet in the Y direction; ambient floor motion.

Mounting/mechanical system: Magnet is mounted on the jackscrew base, sitting on three 1/8-inch neoprene pads (located at the three jackscrew positions). The assembly is situated on the building floor. Magnet is not bolted down (similar to Test 13).

Measurement objectives: To measure system dynamics of magnet on prototypic supports with neoprene pads between the support base and floor.

Test 15. Excitation: Impulse to body of magnet in two orthogonal directions (X and Y) and ambient floor motion.

Mounting/mechanical conditions: Magnet on jackscrew support base; base is bolted to floor. This test is similar to Test 13.

Measurement objectives: To compare system response to that of Tests 1, 2, and 13.

Test 16. Excitation: Impulse to body of magnet in two orthogonal directions (X and Y) and ambient floor motion.

Mounting/mechanical conditions: Magnet on jackscrew support base; 1/8-inch thick neoprene pads placed between support base and floor at the three jackscrew locations; support base bolted to floor.

Measurement objectives: Determine the effects on system dynamics with and without the neoprene pads (Test 15 is reference).

Test 17. Excitation: Impulse to body of magnet in two orthogonal directions (X and Y).

Mounting/mechanical conditions: Test is identical to Test 16 except the neoprene pads are replaced with 1/16-inch thick teflon.

Measurement objectives: Determine the effect on system dynamics with and without the teflon pads (Test 15 is reference).

Test 18. Excitation: Water flow through magnet coils at flow rates of 1.21 to 4.44 gpm and ambient floor motion.

Mounting/mechanical conditions: Magnet is mounted on jackscrew support base which is bolted to the floor (identical to Test 15).

Measurement objective: To measure system response as a function of water flow through the magnet coils.

RESULTS

In this section the tests results are discussed relative to the measurement objectives listed in the Test Matrix.

Test 1. This test is used to determine the system response, both to forced random excitation and ambient excitation. The observed, dominant response frequencies which were obtained from the power spectral density plots of Appendix A are shown in Table 1; the associated displacements, in microns rms, are shown in Table 2. The forced random excitation is constant for all three orthogonal directions, therefore, the observed response levels (Table 2) give some indication of system damping. For example, in general, for each corresponding frequency/mode the higher the response amplitude, the lower the damping. The largest observed amplitude is 4.39 microns rms corresponding to a Y-direction excitation and measurement. Ambient displacement response will be discussed below in Test 2 results.

Frequency-vibration mode relationship is shown in Table 3. The 8.01 Hz displacement, which was previously observed during vibration testing in Building 335, is associated with the building/site location and has a variable amplitude-time response history. The 11.52 Hz displacement is associated with the concrete block/floor and is not considered a magnet vibration mode. Frequencies of 13.87 Hz and 18.55 Hz are the magnet/base rigid body response in the Y- and X-directions, respectively. The 16.21 Hz displacement response is observed only during ambient testing (Test 2 and Test 24, ambient). Frequencies of 29.69 and 31.25 are associated with the magnet response in the Z-direction. Since they are very low amplitude they will not be discussed.

Damping and response frequencies resulting from impulse tests are shown in Table 7. This data was calculated from the real time plots of Appendix B.

Table 1. System frequencies for Test 1

Measurement Direction	Excitation Direction	FREQUENCY, Hz						
		8.01	11.52	13.87	16.21	18.55	29.69	31.25
Xm	X			x		X		
Ym	X			X		x		
Zm	X					X		
Xb	X	x		x		X		
Yb	X	x		X				
Zb	X	x		x		X		
Xm	Y			X		x		
Ym	Y			X				
Zm	Y			X				
Xb	Y			X		x		
Yb	Y			X				
Zb	Y			X		x		
Xm	Z			x		X		
Ym	Z			X		x		
Zm	Z					X		
Xb	Z			x		X		
Yb	Z					X		
Zb	Z					X		
Xm	AMB.			x		X		
Ym	AMB.			x		x		
Zm	AMB.							X
Xb	AMB.	x	X	x		x		x
Yb	AMB.	x	x	x				
Zb	AMB.	x	X			x		x

NOMENCLATURE:

X,Y,Z - Direction

m - Magnet

b - Block

AMB. - Ambient Excitation

Bold X - Primary response frequency

Table 2. Displacement values for Test 1, (microns, rms)

Measurement Direction	Excitation Direction	FREQUENCY, Hz						
		8.01	11.52	13.87	16.21	18.55	29.69	31.25
Xm	X			0.521		1.925		
Ym	X			1.541		1.064		
Zm	X					2.643		
Xb	X	0.049		0.135		0.279		
Yb	X	0.055		0.273				
Zb	X	0.049		0.066		0.17		
Xm	Y			1.62		0.929		
Ym	Y			4.397				
Zm	Y			0.102				
Xb	Y			0.371		0.131		
Yb	Y			0.783				
Zb	Y			0.163		0.082		
Xm	Z			0.057		0.131		
Ym	Z			0.147		0.09		
Zm	Z					0.015		
Xb	Z			0.014		0.017		
Yb	Z					0.005		
Zb	Z					0.012		
Xm	AMB.			0.022		0.041		
Ym	AMB.			0.068		0.022		
Zm	AMB.						0.007	
Xb	AMB.	0.01	0.013	0.007		0.005		0.003
Yb	AMB.	0.014	0.014	0.014				
Zb	AMB.	0.007	0.011			0.004		0.005

NOMENCLATURE:

X,Y,Z - Direction

m - Magnet

b - Block

AMB. - Ambient Excitation

Bold X - Primary response frequency

Table 3. System frequency assignments

FREQUENCY, Hz	System Frequency Response
8.01	Building response frequency
11.52	Cement block response frequency
13.87	Magnet Y-direction response - Rigid body mode
16.21	Ambient response on magnet
18.55	Magnet X-direction response - Rigid body mode
29.69	Magnet Z-direction response
31.25	Magnet Z-direction response

Response frequencies in the X and Y directions are consistent with the approximations obtained from Table 1. Measured damping is 0.014, 0.012, and 0.096 for the X-, Y-, and Z-directions, respectively. The X- and Y-direction values are less than desired, while the Z-direction damping is at an acceptable level.

Test 2. The magnet support system is shimmed between the support and concrete block at the three jackscrew locations, assuring three-point contact with the block. System frequency response is presented in Table 4. To compare system response, the X- and Y-direction, rigid body mode frequencies, 18.55 Hz and 13.87 Hz, respectively, will be used. In Test 1, both frequencies are observed, with 18.55 Hz being the primary response frequency. Test 2 system frequency response is shifted to 13.87 Hz, which is now the primary response frequency. The same trend is seen in the ambient displacement amplitude of Table 5, which was obtained from the power spectral density plots of Appendix A. Now the system is controlled by the Y-direction rigid body mode (13.87 Hz) which is also coupled to the concrete shielding block (Test 2 block response of Table 5). Wideband ambient system displacement response, Table 6, is approximately the same for both tests, but the effect at specific frequencies is considerable. This shows that the mounting surface can influence the dynamic system response.

Damping values of 0.016 and 0.012 (Table 7) were calculated for the X and Y directions, respectively. The values are consistent with those of Test 1; the response frequencies are reasonably consistent with those of Table 1.

Test 3. The magnet support system, consisting of the channel iron base and jackscrews, was removed. The magnet was supported on building floor using three 3/4-inch nuts as standoffs between the floor and magnet. The nuts were located at the approximate location of the jackscrews. While the system damping remained constant (for Tests 1 and 2), the frequencies increased to approximately 30 Hz and 20 Hz in the X and Y directions, respectively. This can be attributed to the decrease in distance from the center of mass of the magnet to the floor, and/or the increased system stiffness with the removal of the jackscrews.

Test 4. A large number of the 3/8-inch bolts holding the magnet together were loose; they were tightened and then impulse excited. From Table 7 it is seen that the system response, damping and frequency, are consistent with those of Test 3, indicating that the loose bolts had minimal effect.

Test 5. A large piece of metal was clamped to each end of one side of the magnet to increase the stiffness of the bolted joints, as shown in Fig. 4. The magnet was impulse excited in only the Y-direction. As shown in Table 7, there was no apparent change of system dynamics, indicating that the bolted joints were sufficiently stiff as not to influence the system dynamics.

Table 4. Ambient frequency response

Acc. .	FREQUENCY, Hz						
Dir.	8.01	11.52	13.87	16.21	18.95	29.69	31.25
1,X,m			x		X		
1,Y,m			x		x		
1,Z,m							X
1,X,b	x	X	x		x		x
1,Y,b	x	x	x				
1,Z,b	x	X			x	x	x
2,X,m			X	x			
2,Y,m			X	x			
2,Z,m				x		x	X
2,X,b			X				
2,Y,b			X				
2,Z,b			x				X
18,X,m	x	X		x			
18,Y,m	x	x		x	X		
18,Z,m	X	x		x			
18,X,m	x	X	x				
18,Y,m		x			X		
18,Z,m	X	x				x	

NOMENCLATURE:

X,Y,Z - Direction

m - Magnet

b - Block

Bold X - Primary response frequency

**Table 5. Ambient excitation displacement values
(microns, rms)**

Measurement Direction	FREQUENCY, Hz					
	8.01	11.52	13.87	16.21	18.55	29.69 31.25
1,X,m			0.0218		0.041	
1,Y,m			0.068		0.0216	
1,Z,m						0.007
1,X,b	0.0101	0.013	0.0071		0.0053	0.0025
1,Y,b	0.0134	0.014	0.014			
1,Z,b	0.0072	0.011			0.0039	0.0032 0.005
2,X,m			0.069	0.0309		
2,Y,m			0.093	0.0416		
2,Z,m				0.0058		0.0038 0.007
2,X,b			0.013			
2,Y,b			0.021			
2,Z,b			0.006			0.0051
18,X,m	0.0886	0.14	0.0135	0.0288		
18,Y,m	0.0187	0.0162		0.0201	0.029	
18,Z,m	0.084	0.0186		0.0225		
18,X,m	0.0429	0.117	0.0112			
18,Y,m	0.0131	0.0129			0.019	
18,Z,m	0.041	0.0164				0.0091

NOMENCLATURE:

1,2,24 Test number

X,Y,Z - Direction

m - Magnet

b - Block

Bold Number - Primary response

Note: Last Test 24 data is post test measurements

Table 6. Wideband ambient excitation displacement values, (microns, rms)

Measurement Direction	Displacement microns, rms
1,X,m	0.065
1,Y,m	0.098
1,Z,m	0.033
1,X,b	0.036
1,Y,b	0.044
1,Z,b	0.025
2,X,m	0.085
2,Y,m	0.114
2,Z,m	0.034
2,X,b	0.035
2,Y,b	0.044
2,Z,b	0.021
24,X,m	0.181
24,Y,m	0.079
24,Z,m	0.108
24,X,m	0.137
24,Y,m	0.073
24,Z,m	0.068

NOMENCLATURE:

1,2,24 Test number

X,Y,Z - Direction

m - Magnet.

b - Block

Note: Last Test 24 data is post test measurements

Table 7. Damping and system frequency response from impulse excitation tests

Test	Exc. Dir.	Primary Freq.	Secondary Freq.	Damping.
1	X	18.3	13.6	0.014
1	Y	13.6	18.2	0.012
1	Z	5		0.096
2	X	16.6	14	0.016
2	Y	14	16.6	0.012
3	Y	20.3	30	0.012
3	X	20	29.8	
4	Y	20	29.8	0.010
4	X	19.8	29.8	
5	Y	20	24.9	0.013
6	Y	18	25	
7	Y	18.2	25	
8	Y	17.9	25.1	
9	Y	18.1	25.1	
10	Y	11.4		0.095
11	Y	15.9		0.009
12	Y	9.15		0.014
13	Y	18.8		0.015
14	Y	10.5		0.073
15	Y	18.3		0.013
15	X	15.4		0.013
16	Y	12.8		0.030
16	X	11		0.023
17	Y	19		0.017
17	X	11.6		0.012

Test 6. The single 3/4-inch standoff nut was repositioned to allow the magnet weight to bear directly on the aluminum angle. The Y-direction frequency, Table 7, was lowered from approximately 20 Hz to 18 Hz, indicating a reduction in system stiffness, this is reasonable, considering the flexibility of the aluminum angle.

Test 7. A large "C"-clamp, Fig. 5, was clamped to one side of the magnet to increase its rigidity. The measured response frequency, given in Table 7, is consistent with that of Test 6, indicating that the magnet is sufficiently stiff as not to change system dynamics.

Test 8. The "C"-clamp was removed; this test was used to verify that there was no permanent change in system dynamics. This can be confirmed by comparing the response frequencies to that of Test 6, see Table 7.

Test 9. The clamp was positioned on the opposite side of the magnet and impulse tested. Again, no change in frequency response was observed, see Table 7, indicating no change of system dynamics.

Test 10. The magnet mounting conditions are the same as Tests 6-9, except that 1/8-inch thick neoprene pads are placed between the standoff nuts and the floor. This resulted in a significant increase in system damping, and a corresponding reduction in system response frequency, indicating system dynamics are controlled by base/support interface conditions. This type of response would be expected in a system with rigid body response, such as the magnet/support system.

Test 11. The 3/4-inch standoff nuts were replaced with 3/8-inch diameter ball bearings located at the approximate locations of the jackscrews to provide as close as possible a three point support. The system dynamics were changed from Test 3, indicating the sensitivity of the magnet/support system to base conditions.

Test 12. In this test the magnet is slung from a crane with two nylon slings to determine magnet dynamic response independent of support conditions. The results from this test, while generally inconclusive, served to demonstrate that there were no "internal" resonance frequencies associated with the magnet itself.

Test 13. The magnet is mounted to the channel iron/jackscrew base; conditions are similar to Test 1, except the assembly is sitting on the floor. Measured system dynamics are similar to those of Test 1, except the Y-direction frequency and damping are slightly higher. This is to be expected, as the floor provides a stiffer mount than the concrete block.

Test 14. This test is similar to Test 13, except that three 1/8-inch thick neoprene pads are placed between the floor and jackscrew pads at the three jackscrew locations. Changes in system dynamics are similar to those of Test 10. That is, a significant increase in system damping and a corresponding decrease in response frequency are observed.

Test 15. This test is similar to Test 13, except the base is bolted to the floor, in the same manner as in Test 1, in which the base is bolted to the concrete block. Whereas the damping is similar to that of previous tests, the frequency shows more variation. This is attributed to the variation of flatness between the floor and base surfaces.

Test 16. This test is similar to Test 14 (1/8-inch thick neoprene pads between base and floor) except the base is bolted to the floor. Damping increases and response frequency decreases. Damping and frequency changes are not as large as those of Test 14, possibly due to the added compression of the neoprene pads which resulted from bolting the base to the floor.

Test 17. This test is similar to Test 15 except 1/16-inch thick teflon pads are substituted for the 1/8-inch thick neoprene pads. The effect of the teflon pads is negligible; system dynamics are comparable to Test 15. This is due to the increased hardness of the teflon in relation to that of the neoprene.

Test 18. Water is circulated through the magnet cooling coils at flow rates of 1.21 to 4.44 gpm with the magnet mounted on its prototypic support base and the base bolted to the floor. The information presented below was calculated from the power spectral density plots of Appendix C. Table 8 shows the wideband displacement response of the magnet to coolant water flow, including ambient response before and after the flow tests. No trend of increasing displacement with increasing flow can be observed, the variation being the result of normal changes in ambient floor excitation. A more detailed investigation is presented in Table 9, which separates the displacement response by frequencies. Measured displacements at the primary magnet response frequencies of 13.87 Hz and 18.55 Hz are very low; no clear trend of increasing displacement with flowrate was observed. It can therefore be assumed that a small increase in flow velocity from the maximum test value of 4.44 gpm to the design value of 5 gpm will not result in any flow induced response of the magnet.

Concrete Block Dynamics

When the flow data (Test 18) were acquired, a large amount of data were obtained for the concrete block in response to ambient floor motion. Since the flow excitation level of Test 18 was extremely low, the measured concrete block

Table 8. Wideband flow excitation displacement values
(microns, rms)

Flow, GPM	X Disp	Y Disp	Z Disp
	Wideband		
0	0.1807	0.0792	0.1081
1.21	0.1182	0.0756	0.0499
2.17	0.1060	0.0732	0.0380
2.9	0.1291	0.0737	0.0508
3.64	0.1272	0.0898	0.0463
4.44	0.1322	0.0776	0.0503
0	0.1372	0.0735	0.0680

Table 9. Flow excitation displacement values
(microns, rms)

Flow, GPM	X Disp	Y Disp	Z Disp
8.01 Hz			
0	0.0886	0.0187	0.0844
1.21	0.0155	0.0137	0.0105
2.17	0.0153	0.0138	0.0109
2.9	0.0162	0.0109	0.0105
3.64	0.0167	0.0131	0.0106
4.44	0.0172	0.0126	0.0099
0	0.0429	0.0131	0.0411
11.52 Hz			
0	0.1398	0.0162	0.0186
1.21	0.1025	0.0130	0.0140
2.17	0.0914	0.0123	0.0135
2.9	0.1160	0.0151	0.0169
3.64	0.1155	0.0137	0.0158
4.44	0.1180	0.0164	0.0175
0	0.1171	0.0129	0.0164
13.87 Hz			
0	0.0135	0.0069	0.0061
1.21	0.0119	0.0069	0.0062
2.17	0.0090	0.0051	0.0049
2.9	0.0208	0.0072	0.0078
3.64	0.0097	0.0059	0.0047
4.44	0.0107	0.0068	0.0060
0	0.0112	0.0054	0.0052
16.21 Hz			
0	0.0288	0.0201	0.0225
1.21	0.0057	0.0092	0.0043
2.17	0.0052	0.0071	0.0036
2.9	0.0055	0.0087	0.0039
3.64	0.0051	0.0077	0.0036
4.44	0.0052	0.0091	0.0042
0	0.0137	0.0113	0.0103
18.55 Hz			
0	0.0045	0.0292	0.0032
1.21	0.0028	0.0246	0.0031
2.17	0.0022	0.0184	0.0022
2.9	0.0033	0.0248	0.0027
3.64	0.0025	0.0202	0.0026
4.44	0.0023	0.0283	0.0030
0	0.0027	0.0190	0.0029

response can be considered to be all ambient excitation. For this measurement condition, the block was supported by three 1 inch steel nuts placed between the block and floor in the approximate locations shown in Fig. 6. The response frequencies (Table 10) and associated response amplitudes (Table 11) were obtained from the power spectral density plots of Appendix C. Since the data was acquired in parallel with the flow data, the "FLOW, GPM" column Table 11 serves as an identifier; all responses shown can be considered to be the result of ambient floor motion, independent of water flow rate through the magnet cooling coils.

There are four observed frequencies in Table 10, 13.09, 24.61, 25.97, and 29.88 Hz. The 13.09 Hz and 25.97 Hz frequencies are predominantly a Y-direction response. The 24.61 Hz response is associated with both the Y- and Z-directions. The 29.88 Hz response is prevalent in all three response directions.

The displacements, in microns rms, corresponding to the frequencies of Table 10, are shown in Table 11. All of the displacements are low, with the exception of the X-direction response at 29.88 Hz. The randomness to the amplitude levels is a function of the associated ambient excitation, which also exhibits a random level-time history.

CONCLUSIONS

The magnet/support system responds at several distinct frequencies (13.87, 18.55, 29.69 and 31.25 Hz) which are rigid body modes in the X-, Y-, and Z-directions, respectively. Damping is low in the X- and Y-directions, but is higher in the Z-direction. Several other frequencies are observed: 8.01, 11.52 and 16.21 Hz. They are response frequencies of the building or coupled building/concrete block/magnet systems.

The same frequencies were observed in the ambient excitation tests. Amplitude levels of the magnet/base system at their primary response frequencies were fairly low, none greater than 0.093 microns rms at 13.87 Hz, which is within the frequency response of the feedback control system. The 29.69 and 31.25 Hz Z-direction amplitude response levels were very low, the largest was 0.0091 microns rms. The associated damping value was 0.096. This is a very desirable system response, as these frequencies are beyond the upper frequency limit of the feedback control system.

A large number of modifications were investigated and reported. Modifications to stiffen the magnet did not exhibit any significant response change, indicating that it was constructed sufficiently rigid. Magnet support modifications, such as removal of the jackscrew assembly, resulted in a modified

Figure 6. Concrete block test

Table 10. Frequency response of concrete shielding block

FLOW GPM	DIRECTION	Frequency, Hz			
		13.09	24.61	25.97	29.88
0	X				x
0	Y		x	x	x
0	Z		x		x
1.21	X				x
1.21	Y		x	x	x
1.21	Z		x		x
2.17	X				x
2.17	Y	x			x
2.17	Z				x
2.9	X				x
2.9	Y		x	x	x
2.9	Z		x		x
3.64	X				x
3.64	Y	x	x	x	x
3.64	Z		x		x
4.44	X				x
4.44	Y	x	x	x	x
4.44	Z		x		x
0	X				x
0	Y	x	x	x	x
0	Z		x	x	x

Table 11. Ambient excitation displacement amplitude of concrete shielding block, (microns, rms)

FLOW GPM	DIRECTION	Frequency, Hz				Wideband
		13.09	24.61	25.97	29.88	
0	X				0.145	0.167
0	Y		0.034	0.034	0.019	0.073
0	Z		0.024		0.031	0.091
1.21	X				0.179	0.189
1.21	Y		0.025	0.019	0.021	0.075
1.21	Z		0.019		0.039	0.055
2.17	X				0.136	0.146
2.17	Y	0.011			0.015	0.046
2.17	Z				0.031	0.040
2.9	X				0.154	0.164
2.9	Y		0.030	0.030	0.019	0.064
2.9	Z		0.021		0.033	0.050
3.64	X				0.145	0.154
3.64	Y	0.011	0.013	0.016	0.018	0.054
3.64	Z		0.010		0.032	0.043
4.44	X				0.191	0.201
4.44	Y	0.012	0.024	0.029	0.022	0.065
4.44	Z		0.020		0.041	0.055
0	X				0.145	0.155
0	Y	0.011	0.027	0.027	0.019	0.062
0	Z		0.015	0.014	0.031	0.049

system response; considering the response mode shapes, the changes were as expected. The largest and most beneficial modification was to place pads of resilient material (neoprene pads) between the supports and floor; this resulted in a lower response frequency and a significant increase in system damping. While the resilient pads may not be practical in the actual system, they emphasize the effect of mounting parameters on system response associated with the rigid body response modes of the magnet/support system. The jackscrews did not appear to have any significant effect on the system response other than what would be expected from the variation of distance between the center of mass of the magnet and its support base when the jackscrews are removed.

The effect of coolant flow through the magnet coils did not affect the measured response of the magnet; the amplitude response levels were within the measured ambient response. Since there was no increased displacement response with a water flow rate of 4.44 gpm (the maximum flow attainable in this series of tests), no increase is to be expected with an increase of flow velocity to 5.00 gpm (the design flow rate).

The dynamic response of the concrete block is similar to that of the magnet. A rigid body mode response at specific frequencies is exhibited, with the response to ambient floor excitation the largest in the X-direction. This may be the result of a larger X-direction component in the ambient excitation, as the magnet was aligned to the same coordinate system as the block when it was located on the floor. With the exclusion of the 29.88 Hz X-direction response, the measured amplitude levels are consistent with what would be expected for ambient response conditions in a laboratory highbay with normal activity.

REFERENCES

- [1] Wambsganss, M. W., Jendrzeczyk, J. A., and Chen, S. S., "Vibration Study of the APS Magnet Support Assemblies," APS/IN/VIB/90-3, November 1990.
- [2] Jendrzeczyk, J. A., Wambsganss, M. W., and Smith, R. K., "Vibration Study of the APS Vacuum Chamber/Girder Assembly," APS/IN/VIB/91-~~1~~², February 1991.
- [3] Jendrzeczyk, J. A., Wambsganss, M. W., and Smith, R. K., "Vibration Study of the APS Storage Ring 0.8 Meter Quadrupole/Girder Assembly," APS/IN/VIB/91-2, May 1991.

APPENDIX A

Power spectral density plots of Tests 1 and 2

X Magnet Disp. Response

X Block Disp. Response

Y Magnet Disp. Response

Y Block Disp. Response

Z Magnet Disp. Response

Z Block Disp. Response

TEST 1
Ambient Exc.

X Magnet Disp. Response

X Block Disp. Response

Y Magnet Disp. Response

Y Block Disp. Response

Z Magnet Disp. Response

Z Block Disp. Response

TEST 1
Y Excitation

X Magnet Disp. Response

X Block Disp. Response

Y Magnet Disp. Response

Y Block Disp. Response

Z Magnet Disp. Response

Z Block Disp. Response

TEST 1
Z Excitation

X Magnet Disp. Response

X Block Disp. Response

Y Magnet Disp. Response

Y Block Disp. Response

Z Magnet Disp. Response

Z Block Disp. Response

TEST 2
Ambient Exc.

X Magnet Disp. Response

X Block Disp. Response

Y Magnet Disp. Response

Y Block Disp. Response

Z Magnet Disp. Response

Z Block Disp. Response

TEST 1
X Excitation

APPENDIX B

**Real time displacement plots from impulse
excitation tests.**

Test 1, X Direction

Test 1, Y Direction

Test 1, Z Direction

Test 2, X Direction

Test 2, Y Direction

Test 3, X Direction

Test 3, Y direction

Test 4, X Direction

Test 4, Y Direction

Test 5, Y Direction

Test 6, Y Direction

Test 7, Y Direction

Test 8, Y Direction

Test 9, Y Direction

Test 10, Y Direction

Test 11, Y Direction

Test 12, Y Direction

Test 13, Y Direction

Test 14, Y Direction

Test 15, X Direction

Test 15, Y Direction

Test 16, X Direction

Test 16, Y Direction

Test 17, X Direction

Test 17, Y Direction

APPENDIX C

Power spectral density plots of Test 18
(Magnet coolant flow test)

X Magnet Disp. Response

X Magnet Disp. Response

Y Magnet Disp. Response

Y Magnet Disp. Response

Z Magnet Disp. Response

Z Magnet Disp. Response

Ambient Exc.

TEST 18
Flow Exc.

1.21 GPM Flow Exc.

X Magnet Disp. Response

X Magnet Disp. Response

Y Magnet Disp. Response

Y Magnet Disp. Response

Z Magnet Disp. Response

Z Magnet Disp. Response

2.17 GPM Flow Exc.

TEST 18
Flow Exc.

2.9 GPM Flow Exc.

X Magnet Disp. Response

X Magnet Disp. Response

Y Magnet Disp. Response

Y Magnet Disp. Response

Z Magnet Disp. Response

Z Magnet Disp. Response

3.64 GPM Flow Exc.

TEST 18
Flow Exc.

4.44 GPM Flow Exc.

X Magnet Disp. Response

Y Magnet Disp. Response

Z Magnet Disp. Response

Post Test
Ambient Exc.

TEST 18
Flow Exc.

APPENDIX D

**Power spectral density plots of block response
(Ambient excitation)**

X Block Disp. Response

X Block Disp. Response

Y Block Disp. Response

Y Block Disp. Response

Z Block Disp. Response

Z Block Disp. Response

Ambient Exc.

1.21 GPM Flow Exc.

TEST 18
 Flow Exc.

X Block Disp. Response

Y Block Disp. Response

Z Block Disp. Response

2.17 GPM Flow Exc.

X Block Disp. Response

Y Block Disp. Response

Z Block Disp. Response

2.9 GPM Flow Exc.

TEST 18
Flow Exc.

X Block Disp. Response

X Block Disp. Response

Y Block Disp. Response

Y Block Disp. Response

Z Block Disp. Response

Z Block Disp. Response

3.64 GPM Flow Exc.

4.44 GPM Flow Exc.

TEST 18
Flow Exc.

X Block Disp. Response

Y Block Disp. Response

Z Block Disp. Response

**Post Test
 Ambient Exc.**

**TEST 18
 Flow Exc.**

END

**DATE
FILMED**

6 / 5 / 92