LA-UR-82-2268

85011051
PT 1105-3

Los Alamos National Laboratory is operated by the University of California for the United States Department of Energy under contract number 7405 ENG 32

LA-UR--82-2268

TITLE EXCIMER LASER CHEMICAL PROBLEMS

DE85 011051

AUTHOR(S) Roger Tennant and Norman Peterson

SUBMITTED TO Submarine Laser Communication Laser Design Review

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or usefulness of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

MASTER

By acceptance of this article the publisher recognizes that the U.S. Government retains a nonexclusive, royalty-free license to publish or reproduce the published form of this contribution or to allow others to do so for U.S. Government purposes.

The Los Alamos National Laboratory requests that the publisher identify this article as work performed under the auspices of the U.S. Department of Energy.

Los Alamos Los Alamos National Laboratory
Los Alamos, New Mexico 87545

EXCIMER LASER CHEMICAL PROBLEMS*

by

**Roger Tennant
and
Norman Peterson**

**University of California
Los Alamos National Laboratory
P. O. Box 1663
Los Alamos, NM 87545**

*Work performed under the auspices of US DOE.

EXCIMER LASER CHEMICAL PROBLEMS

1.0 Introduction

Techniques need to be developed to maintain XeF and XeCl laser performance over long periods of time without degradation resulting from chemical processes occurring within the laser. The dominant chemical issues include optical damage, corrosion of laser materials, gas contamination, and control of halogen concentration. Each of these issues will be discussed and summarized. The methods of minimizing or controlling the chemical processes involved will be presented.

2.0 Deterioration of Optics

With both XeF and XeCl excimer lasers, a coating is deposited on optics surfaces in contact with laser gas. In the case of XeF the coating results from particulates, fluorocarbons, and F_2 or HF_3 that are present inside the laser. In the studies described in this report, the particulates originate primarily in the preionizer and discharge region where the halogen reacts under discharge conditions with the metals of construction. The worst source of particulates with the Lumonics 861 laser is the spark preionizer. The next worst source is the electrodes. The least worst source is everything else. In the XeF and XeCl systems of interest to the Blue-Green Laser Program, a spark preionizer wouldn't be used; hence, with the types of preionizer envisioned for use (such as x-ray preionization) the worst source of particulates has been eliminated.

At Los Alamos electrodes made of aluminum, stainless steel, copper, brass, Poco graphite, and nickel have been tested. Of these nickel is the most

resistance to erosion under halogen and discharge conditions. For an x-ray window electrode there is a real problem in coming up with a suitable material that will still pass x-rays. To date at Los Alamos, aluminum has been used. Perhaps if a glow discharge can be maintained, a nickel coating on the x-ray window electrodes would hold up well enough to give long life but this is doubtful.

In the presence of uv photons, chlorocarbons and fluorocarbons are photolyzed to carbon which collects on the output coupler. These chlorocarbons and fluorocarbons result mostly from halogen reactions with dielectrics (including O-rings) within the laser. The use of metal optical mounts and fluoroplastics greatly reduce the formation of carbon type residues. For 10^8 pulse life systems such as for XeF, the use of fluoroplastics is probably acceptable. The 10^{10} pulse life systems such as for XeCl 99.95% pure ceramics such as Al_2O_3 and CaF_2 will be required.

To date all of the coatings have been surface deposits when MgF_2 and CaF_2 have been used for optics materials. In most instances, scrubbing with a detergent and water has been sufficient to clean the optics. In general, the metallic chlorides are soluble in water whereas the fluorides are only slightly so.

Several techniques have been used to prevent coatings from accumulating on the optics. Using nickel and nickel coatings has reduced the formation of metallic chlorides and fluorides. Eliminating plastics from preionizers and other components near the discharge and laser beam region has reduced the formation of chlorocarbons and fluorocarbons. Also, flushing the optics with clean rare gas prevents particulate build-up from being as severe a problem. The window flushing configuration which has been in use on the Lumonics laser for the last two years has three radial and three tangential jets which create

a buffer zone over the optics. With this configuration about 1% of the output energy is lost for each 10^7 pulses accumulated as compared to about 1% per 10^6 pulses without the flushing. For the Lumonics laser we have used as little as 5 standard liters per minute of flow at 3 atm pressure per window. The injection flow required will increase as flow rate within the laser increases; hence, an operational XeCl laser may require as much as 100 times more flow than does a Lumonics laser. Another flushing geometry which used all radial flow has also been tested throughout the last year on our Engineering Development System (EDS) laser. Our conclusion is that radial flow alone works very poorly when compared to the mixture of radial and tangential flow, at least at flush flow rates up to 2.5 scfm.

Reviewing the XeCl requirements for maintaining clean optics for a space based 10^{10} pulse systems indicate that flushing optics with a rare gas (i.e. halogen, particulates, and contaminants removed) is probably out of the question. To do such would require a cleanup system about 100 times larger than is required to maintain gas purity. There are several approaches which may work, however. One possibility would be to flush the optics with gas which is filtered and possibly run through a cold heat (130 K) exchanger to remove particulates and chlorocarbons. Unfortunately, Los Alamos experience with this approach indicates that HCl and uv photons at an optic surface still leaves a reaction product - perhaps due to a photochemical reaction of the HCl and the O-ring. Another approach is to filter the particulates out of the laser gas at a sufficient rate to maintain a very low background level of particulates in the laser and to reprocess the laser gas with a getter trap system at a rate sufficient to keep chlorocarbons ^{at} an acceptable level. This approach may work if the laser system has very little plastic materials which form chlorocarbons which may photolyse to carbon on the output coupler or reflector.

Another possibility for keeping particulates off the optics is to use electrostatic techniques such as described in Ref. 1. The basic message is that the optics will have to be actively protected to ensure 10^{10} pulse laser system lifetimes. The next section will show how bad the particulate accumulation can be.

The method for maintaining clean optics with a ground based XeF laser can be significantly different from XeCl. Since XeF with NF_3 requires so much more gas reprocessing there should be plenty of clean gas for flushing optics. The reprocessing rate is of the order of 1 scfm per Joule of laser output. Likewise, since the laser is more accessible, the system lifetime requirement between maintenance periods is probably of the order of 10^8 pulses or less. A 10% energy loss due to dirty optics for 10^8 pulses is attainable with currently demonstrated flushing approaches.

3.0 Materials Summary

To date about 3 (10^8) pulses over about 3 years have been accumulated on the Lumonics 861 laser. During this time and also previously the effects of HCl, NF_3 , and F_2 on various metallic and dielectric parts have been studied. Metals studied include inconel, copper, brass, stainless steel, aluminum, monel, titanium, and nickel. Dielectrics studied include Al_2O_3 , epoxy, kynar, polyethylene, teflon, lexan, plexiglas, Kel-F, PVC, etc.

The various metals that have been studied correspond closely to the order shown in Table I as far as usefulness with F_2 and HCl. That is, of the materials tested, nickel has the lowest corrosion rate of the structural metals for both HCl and F_2 . Platinum and gold were not tested. Table II describes the condition of various metals after prolonged HCl exposure. As it turns out, nickel is the most durable metal tested to date followed by Inconel for HCl and Monel for F_2 as close seconds.

TABLE I

EFFECT OF TEMPERATURE (°F) ON RATE OF CORROSION (MILLI INCH/MONTH)

SAS	MATERIAL	2.5 MIL/MO MO	5 MIL/MO MO	10 MIL/MO MO	50 MIL/MO MO	100 MIL/MO MO	UPPER TEMP FOR CONTINUOUS SERVICE, °F
ENV NO. 1	PLATINUM	2300					2300
	GOLD	1600					1600
	NICKEL	850	950	1050	1250	1300	450
	INCONEL	800	900	1000	1250	1350	900
	316 SS	700	700	900	1100	1200	800
	309 SS	650	750	850	1050	1150	800
	TITANIUM	450	500	650	900	1050	450
	COPPER	200	300	400	600	700	200
	ALUMINUM						
T-2	NICKEL	875	975	1050	1275	1300	
	TITANIUM	900	950	1025	1150	1200	
	INCONEL			550	850	975	
	309 SS			425	550	575	
	307 SS				350	450	
ENV C-12	NICKEL	950	1000	1100	1200	1250	1000
	INCONEL	950	1000	1050	1200	1250	1000
	PLATINUM	900	950	1000	1050	1050	500
	TITANIUM	750	850	900	1000	1000	800
	316 SS	600	650	750	850	900	650
	ALUMINUM	250	300	300	350	350(A)	250
	GOLD	250	300	350	400	400	

(A) IGNITES AT 400 TO 450°F

THE PRESENCE OF AIR WILL LOWER THE ABOVE TEMPERATURES APPRECIABLY

TABLE 2

LASER MATERIALS AFTER HCL EXPOSURE

COPPER - COATING IS FLAKING BADLY

ALUMINUM - UNIFORM WHITE POWDER COATING

BRASS - ZINC LEACHED OUT LEAVING COPPER SURFACE

STAINLESS AND CARBON STEEL - RUSTS AFTER BEING
OPENED TO AIR

MONEL - TURNS GREEN AFTER AIR EXPOSURE

NICKEL - SHOWS LITTLE ATTACK OTHER THAN WHERE
ARCS IMPINGE

Figures 1 through 5 compare the use of nickel electrodes and nickel plated preionizers with Poco graphite electrodes and brass preionizers. All of the parts are from a Lumonics 861 laser. Each set of electrodes and preionizers were run of the order of 10^8 pulses. Note in Figs. 1 and 3 that even with nickel electrodes and nickel plated preionizers there is still noticeable quantities of powder present. Note also in Fig. 1 that the heads of the nickel plated stainless steel screws on the top of the red capacitors are badly eroded - this is one side of a double row of preionizers. The other side - the nickel plated brass screws - are eroded very little. The power in Figs. 1 and 3 contains primarily chlorides of nickel and iron. In Figs. 2, 4, and 5 the amount of powder is much more extensive. In Fig. 2 the red capacitors are entirely covered with white powder. The powder is mostly zinc, copper, and nickel chlorides.

Note in Fig. 2 that the erosion of the brass screw heads on the capacitors is comparable in extent to the erosion of the nickel plated stainless steel screws in Fig. 1. Interestingly enough, there is no evidence of free carbon from the Poco graphite electrodes. Evidently most of the reaction products from the electrodes were a gas as intended. The erosion of the electrode not shown was more extensive. The electrode lifetimes for Poco graphite are not much more than 10^8 pulses; however, when coupled with an x-ray preionizer the particulate generation rate should be quite low. The larger amount of gaseous reaction products did create some problems. For example, a carbon smudge buildup on the optics was difficult to eliminate by gas flushing techniques.

The effect of HCl on stainless steel is shown in Figs. 6 and 7. Figure 6 is where the laser cavity inserts into the EDS. Figure 7 is the ferrofluidic seal package for the EDS. The rust results from ferric chloride absorbing water out of the air over a period of a few days. Figure 6 was taken after

Fig. 1 Particulate accumulation with nickel electrodes and nickel plated spark ionizer.

FIG. 2
Particulate accumulation
with Poco graphite
electrodes and brass
spark preionizer.

Fig. 3 Particulate accumulation
with nickel electrodes
and nickel plated spark
monitoring

Fig. 4 Particulate accumulation
with Poco graphite
electrodes and brass
anode protonizer.

Fig. 5 Particulate accumulations with Poco graphite electrodes and brass spark preionizer.

Fig. 6 Stainless steel after
prolonged exposure
to HCl.

Fig. 7 Stainless steel after
prolonged exposure to
KI.

cleaning with a variety of solvents. The message here is to clean the laser as soon as possible after opening to the air before the rust has a chance to form. Figure 7 was taken before cleaning.

Figure 8 shows part of a brass flow duct insert for the EDS. Note how the surface has had the zinc leached out leaving the copper. The vertical piece is starting to develop wet spots from water absorbed out of the air.

Figure 9 shows the centrifugal fan from the EDS. This fan blade is made from aluminum and has been plated with electroless nickel. Note that after a year's use in an HCl environment, the coating is fairly extensively pitted and chipped. This is typical of nickel plated aluminum - especially the pitting. Aluminum is not the best of materials to try to nickel plate.

Since these pictures were taken, the EDS components have been plated with electroless nickel except for the electrodes. At the moment one electrode is solid nickel and the other is aluminum. The aluminum is being used because of its ability to allow x-ray transmission. Since the nickel plating was completed the secondary formation of chlorides has been greatly diminished with the primary source now being the electrodes. The nickel plating drastically reduces the secondary corrosion and greatly simplifies the cleaning due to a much lower corrosion rate.

Several dielectric materials have also been evaluated. In general, HCl reacts with epoxy on a low level and never really passivates. After three years the epoxy body in the Lumonics 861 was etched back to the fiberglass fibers and has a small but finite gas leak rate. Teflon electrode supports appear to be unaffected by the HCl, the uv photons, and by the discharge. Kynar is also attacked by the chloride ions present; however, the main reaction product is HCl plus some chlorocarbons. The reaction products from HCl and epoxy are primarily CO_2 and chlorocarbons. The CO_2 generation rate decreases

Fig. 8 Brass after prolonged exposure to ICI.

Fig. 9 Nickel plated aluminum
after prolonged exposure
to H₂O.

with time. Other plastics have been avoided because of the studies of fluorine and plastic reactions to be described next.

A variety of materials have been analyzed for potential use in XeF laser construction. Dielectrics studied include plexiglass, epoxy, PVC, lexan, polyethylene, Kynar (PVF2), and Teflon. Metals studied include stainless steel, aluminum, copper, inconel, titanium, and nickel. To develop an understanding of chemical reactions occurring in XeF lasers both static test reaction cells and long duration laser operation have been used. In general the materials used in an XeF laser should be compatible with F_2 regardless of whether F_2 or NF_3 is used as the F-atom source because in a discharge environment F_2 is going to be present anyway. Likewise, passivation of the laser system with F_2 before use will greatly speed up the conditioning process within the laser.

To develop an understanding of the chemical reactions occurring in XeF lasers, a series of static tests were conducted to determine what reaction products are formed when fluorine reacts with various materials. The test cell used is shown in Fig. 10. The circular cell walls are nickel with end plates being the material tested. Viton A O-rings with a halocarbon grease have been used for the vacuum seal. Each test consisted of two parts: first, a cell is evacuated and filled with 30 to 185 torr of fluorine and the pressure decay monitored. After several days of filling, evacuating, and refilling the normalized pressure decay curve becomes reproducible. Figure 11 shows typical pressure decay curves as a function of time. Second, a nearly stabilized gas sample which has been in a cell for at least four hours is analyzed using a time-of flight mass spectrometer. Tables 3, 4, and 5 show a summary of the information obtained. To simplify the mass spectrometer readout, the mass numbers have been rounded off to the nearest whole number and the intensity

MATERIALS COMPATIBILITY TEST CELL

Fig 10

FRACTION OF PRESSURE REMAINING WITH TIME

Fig. 11

TABLE 3
REACTION PRODUCTS OF F₂ WITH VARIOUS MATERIALS
SUM OF EACH COLUMN NORMALIZED TO 100

POSSIBLE SPECIES	Mass Number	PLEXIGLAS	EPON 828	TEFLON	PVC	LEXAN	POLYETHYLENE
	118		2.2				
	100		3.7				
	101		1.0				
	85	0.4	1.3		0.4	0.8	0.5
	82		1.6				
CF ₃	69	5.7	8.4		0.4	2.2	
FO ₂	67		2.0			0.3	
SIF ₂ , COF ₂ , C ₂ H ₅ F ₂	66	1.9	1.4			0.8	
C F ₂ N	51	4.9	1.9			1.3	
COF, SiF	47	4.5	4.3		0.4	2.4	
CO ₂ , C ₃ H ₈	44	26.5	11.5	1.0	0.8	37.9	1.0
F ₂ , C ₃ H ₂	38	14.8	17.8	68.6	56.0	1.3	1.4
	36			0.4	0.4		4.3
CL, OF	35		0.3		0.4		1.0
	32	0.8	1.2	1.9	2.2	0.5	1.4
C F	31	0.8	1.0			0.5	
C ₂ H ₅ , CON	29	1.1	0.8			0.5	
H ₂ , CO, C ₂ H ₄	28	12.5	8.7	6.8	7.3	16.7	12.4
NF	20	11.0	11.1	4.5	11.6	21.0	65.6
F	19	3.4	5.5	14.0	11.6	1.3	3.8
H ₂ O	18	1.9	2.6	0.8	2.2	2.4	5.3
OH	17	0.4	0.7	0.8	0.9	0.5	1.4
O, CH ₄	16	2.3	1.3	0.4	0.9	3.5	0.5
H	14	0.4	0.4	0.4	0.4	0.8	1.0
C	12	0.8	0.7			1.1	1.0
EVERYTHING ELSE		5.76	8.4	0.4	4.1	4.2	0

TABLE 4
REACTION PRODUCTS OF F_2 WITH VARIOUS MATERIALS
SUM OF EACH COLUMN NORMALIZED TO 100

POSSIBLE SPECIES	MASS NUMBER	TEFLON COATED UNFILLED EPOXY	PMF2
	79	0.4	
Cl_2	72	2.2	1.2
Cl_2	70	5.5	2.0
	52	0.5	
BF_2	49	2.8	2.8
BF_2	48	0.8	0.7
COF, SiF	47	0.5	0.4
CO_2	44	0.8	0.5
F_2	38	57.6	64.2
$SiCl$	37	0.4	
$SiCl$	36	0.8	0.5
Cl, OF	35	1.3	0.7
O_2, CNF	32	1.4	1.4
H_2, CO	28	5.4	4.9
HF	20	1.2	1.1
F	19	16.0	17.5
H_2O	18	1.5	1.3
CH	17	0.5	
H	14	0.4	

TABLE 5
REACTION PRODUCTS OF F_2 WITH VARIOUS MATERIALS
SUM OF EACH COLUMN NORMALIZED TO 100

POSSIBLE SPECIES	PASS NUMBER	STAINLESS STEEL F_2	ALUMINUM PLATE F_2	TEFLON F_2	TEFLON COATED EPOXY F_2	PVC F_2
SiF_3	85				0.4	0.4
	79		1.2			
	74		0.4			
Cl_2	72	0.4	3.8		1.7	0.4
	70	0.4	6.3	0.4	3.0	0.9
CF_3	65	0.4	4.0			0.4
	49		4.2		2.7	
	46		1.0		0.6	
COF, SiF	47		1.3		0.8	0.4
	46		0.4			
CO_2, C_2H_2, CH_3, C_3N	44	0.8	1.3	1.0	6.7	0.3
Am, C_2H_4, H_2F_2	40	0.4		0.4		0.4
F_2, C_2H_2	38	71.3	52.4	68.6	9.9	56.0
NE_4	36		0.6	0.4		0.4
Cl_2, HF	35		1.6		0.8	0.4
O_2, CNE, CH_2OH	32	1.2	1.4	1.9	4.1	2.2
H_2, CO, C_2H_4	26	4.0	7.0	6.8	6.6	7.3
HF	20	5.6	1.0	4.5	0.7	11.6
F	19	13.1	12.2	14.0	14.1	11.6
H_2O	18	2.0	2.8	0.8	3.1	2.2
OH	17	0.4	0.6	0.8	0.7	0.9
O, CH_4	16			0.4	1.0	0.9
H	14			0.4		0.4

peaks have been rounded off and normalized to a sum of 100. The smallest number in each column gives an indication of the resulting margin of error. The column labeled "possible species" is a list of potential reaction products present.

From reviewing Tables III, IV, and V several generalities can be derived. First, fluorine reacts with most plastics producing a wide variety of reaction products. Second, the mass spectrometer breaks up the gas molecules quite extensively. Some of the more common reaction products are HF, CO₂, CO, COF₂, CF₄, and H₂O. Of the plastics, Teflon, Kel-F, and Kynar (PVF₂) are the most suitable for fluorine service. A Teflon coating on epoxy is also quite useful as a dielectric material; however, various organic compounds in the coating need to be reacted away with F₂ to produce a stable surface.

Our experience with fluorine and most metals follows Table I fairly closely. That is, nickel is the best material followed by monel, inconel, and stainless steel. Table V shows a mass spectrometer analysis of a 300 series stainless steel and an aluminum plate. The aluminum results show a wide variety of mass number. This is because of a wide variety of substances present in the aluminum plate. A purer alloy should show fewer reaction products. There has been a lot of concern over the years about alloy constituents which will produce volatile fluorides or which are excessively reactive. Some of the elements of concern are chromium, titanium, silicon, sulfur, boron, and phosphorous. The main area of concern is again the discharge region. At Los Alamos where we are using discharge type lasers, we are using pure nickel for the electrodes where possible to avoid volatile fluoride or excessive particulate formation. The ground based XeF system as currently envisioned is an e-beam type running at about 450 K. At this temperature with e-beam excitation CrF₃, CrF₄, and TiF₄ can exist as a gas at appreciable

concentrations. Hence, both titanium and inconel foils will not work very well as foil materials. At Los Alamos several years ago, operating a KrF e-beam laser at room temperature, we were unable to maintain laser output with titanium foils - the laser output would radically decrease in 10 to 12 pulses. With an inconel foil, however, we were able to run the laser at 1 Hz with about 2-3 standard liters per minute bleed rate. Apparently at room temperature the reaction products from the inconel were not important - this may not be the case at 450 K. The next section on gaseous contamination will go into further detail.

4.0 Contamination of Gas Summary

For XeCl, gas contamination is of lesser severity than powders on windows and corrosion of materials. However, it is still a problem that has to be handled properly. Most plastics and epoxies will form chlorocarbon compounds especially in the discharge/preionizer region. The best that can be done is to minimize the contaminant generation rate by minimizing the use of plastics and epoxies, by conditioning the laser thoroughly before using, and by using fluorocarbon plastics or ceramics such as Al_2O_3 instead of common plastics.

Materials other than plastics can also introduce contaminants into the laser gas. Minor constituents of most common structural alloys, solders, and fluxes can provide a source for such elements as tin, lead, silicon, titanium, carbon, sulphur, and phosphorous. All of these elements form chlorides which are volatile at room temperature. Table VI shows typical constituents of materials used in excimer laser construction. The electroless nickel plate with a phosphorous content has been used extensively in the Lumonics 861 and the EDS. Volatile PCl_3 has not been observed. Figures 12 and 13 show vapor pressure vs temperature for compounds which could be formed in an XeCl laser.² Of these only chlorocarbons and CO_2 have been observed in the Lumonics laser as a gas.

COMPOSITION OF MATERIAL IN PER CENT

MATERIAL	Ni (Co)	Co	P	B	Cu	Fe	Cr	C	Mn	S	Si	A	Li	Mo
NICKEL 200	99.4				0.05	0.15		0.06	0.25	0.005	0.05			
ELECTROLESS NICKEL PLATE (NIPPOSITE #65)	98 - 88		2-12											
SULFAMATE BATH NICKEL PLATE	99.4	0.2	0.2								0.09			
ELECTROLESS NICKEL PLATE	98			2										
INCONEL 700	45	28.0				7.0	15.0	0.16	0.10	0.005	0.25	3.0	2.2	3.0
INCONEL 600	11					68.4	18.0	0.10 max						2.5
INCONEL 400	66.15				31.3	1.35		0.12	0.9	0.005	0.15			

VAPOR PRESSURE OF POTENTIAL CONTAMINANTS AS A FUNCTION OF TEMPERATURE

Fig 12

VAPOR PRESSURE OF POTENTIAL CONTAMINANTS AS A FUNCTION OF TEMPERATURE

Fig. 15

AP-1-V-6186A

XeF-Contamination

With XeF, gas contamination is a very severe problem - much greater than powders on windows and corrosion of materials. Whether F_2 or NF_3 is used, the laser discharge will produce F atoms which will react with electrodes and other structural materials within the laser. As stated previously some of the more common contaminants are SiF_4 , CO_2 , HF, COF_2 , CF_4 , CO, and H_2O . With an operating temperature of 450 K; MoF_6 , CrF_5 , CrF_4 , and TiF_4 are also quite probable depending on what foil material is used. Figures 14 and 15 show vapor pressure vs temperature for various fluorides and XeF gases.^{2,3}

The use of NF_3 is a problem all by itself. When NF_3 is used, appreciable quantities of N_2 are formed. At 100 Hz operation N_2 can quickly accumulate to the point where the laser output is severely affected. Various $NxFe_y$ compounds are also formed including N_2F_4 and N_2F_2 .

NF_3 and F_2 in general are not very pure gases. Tables VII and VIII summarize what the worst case military specifications allow as acceptable.^{4,5} It is important to remember that most F_2 and NF_3 applications do not require high purity. In XeF lasers, however, with large F_2 or NF_3 consumption rates the F_2 or NF_3 will be a major contaminant source more so by far than the rare gases.

There has been a lot of discussion over the last 6 or 7 years as to rare gas purity required for excimer lasers. Table IX contains a summary of the worst grade of rare gases available commercially. Also shown is the contribution of contaminants in a typical laser mix of 1% Xe with balance being He, Ar, or Ne at 4 atm pressure. As can be seen, the diluent gas is the worst contributor. From a contaminant level standpoint none of these impurities make a significant contribution. The bottom line is - buy the gas that's cheapest.

VAPOR PRESSURE OF POTENTIAL XeF CONTAMINANTS AS A FUNCTION OF TEMPERATURE

Fig 11

AP I-VG-10 02³

VAPOR PRESSURE OF POTENTIAL XeF CONTAMINANTS AS A FUNCTION OF TEMPERATURE

Fig. 15

Acceptable Chemical Composition of Gaseous Fluorine
As per Mil Spec MIL - P-27405

<u>Composition</u>	<u>Limit, percent b. volume</u>
F_2	97.0
Sum of HF and CO_2	0.5
Noncondensables O_2 , N_2 , He, CF_4	2.5

TABLE 8

Acceptable Chemical Composition of Gaseous Nitrogen Trifluoride

<u>Composition</u>	<u>Limit, percent by weight</u>
NF ₃ (minimum)	98.0
Total Impurities (maximum)	2.0
N ₂ + O ₂ + CO	1.0
CF ₄	1.0
CO ₂	0.1
N ₂ F ₂	0.1
N ₂ O	0.2
HF	0.1
H ₂ O	-65°F dew point

TABLE 9

Least Pure Rare Gas Commercially Available

Gas	Purity	Impurity Contribution for a 1% Xe Laser Mix at 4 atm. microns partial pressure
Xenon	99.9	30.4
Helium	99.995	150.5
Neon	99.996	120.4
Argon	99.998	60.2

Impurities are typically another rare gas, N_2 , O_2 , CO, CO_2 , hydrocarbons, and H_2O

Some of the gaseous impurities formed in excimer lasers can be monitored rather easily. CO_2 , CO , HF , COF_2 , CF_4 , N_2F_4 , NO_2 , NO , N_2O , SF_6 , plus others can be monitored with an infrared spectrophotometer. It should be noted that COF_2 , NO_2 , and NO absorptions overlap in some instances making positive identifications more difficult. Using a 10 cm gas cell, several of these impurities can be monitored simply by flowing the gas through the gas cell while in place in the spectrophotometer. Others can be detected using scale expansion options available on many spectrophotometers. Also, there are variable path length gas cells available from many spectrophotometer suppliers which allow variable path length from 0.75 to 20 m and more if desired.

When the Lumonics 861 lasers has just been cleaned and reassembled it is possible to watch the laser passivate. Static passivation alone does not appear to passivate as well as does running the laser. When running the laser with NF_3 as the F atom source, initially CO_2 , COF_2 , CF_4 , and NF_3 can be seen with a 10 cm cell in a standard Beckman Acculab 9 Spectrophotometer. As the laser conditions the CO_2 , COF_2 , and CF_4 peaks diminish and the NF_3 peak increases (with continuous gas reprocessing and NF_3 injection). Eventually the CO_2 and COF_2 peaks disappear and the CF_4 peak is barely detectable. At this point, by definition, the laser is conditioned and ready for service. With the Lumonics laser running at ~50 Hz this process takes several 8-hour days.

We have started to accumulate calibrations for various contaminants using the Beckman Acculab 9 ir spectrophotometer. Figures 16 and 17 show concentration vs absorption for CF_4 and N_2F_4 respectively. CF_4 has a very strong absorption at 7.8 μm which allows measurement down to concentrations of 10 ppm with only a 10 cm cell length. N_2F_4 on the other hand can only be measured down to about 200 ppm with a 10 cm path length. By using another spectrophotometer available on site with a 20 cm path length resolution of less than 100 ppm

ABSORPTION BY CF_4 AT 7.8 microns IN A 10 cm CELL FILLED WITH 3 atm OF HELIUM

Fig. 16

**ABSORPTION BY N_2F_4 AT 10.4 microns IN A 10 cm
CELL FILLED WITH 3 atm. OF HELIUM**

Fig. 17

is possible. Several 0.75 to 20 m variable path length Wilks cells are also available.

The first use of the CF_4 calibration was to determine the CF_4 impurity level in two different cylinders of NF_3 . Figures 18 and 19 show a CF_4 peak at about 1300 cm^{-1} . Figure 18 has about 80 ppm of CF_4 present in a mixture which is 13,000 ppm NF_3 ; hence, the NF_3 is about 0.6 percent CF_4 . Figure 19 shows about 10 ppm CF_4 ; hence, the NF_3 is about 0.08% CF_4 . Both of these are within the Military Specifications as shown in Table VIII.

The second use of the CF_4 calibration was to determine the buildup of CF_4 vs time in a sealed-off Lumnics 461 laser. Figure 20 shows the buildup as a function of time. Note that more CF_4 forms when more NF_3 is present.

Two of the important gases which cannot be measured by infrared techniques are F_2 and N_2 . F_2 does have a uv absorption at about 250 to 300 nm which can be used if the cell path length is long enough. Monitoring of F_2 will be discussed further in the section on halogen monitoring. The remaining gas to be measured is N_2 . If NF_3 is going to be used as the F-atom source, large amounts of N_2 will be produced. It is anticipated that N_2 will be the main contaminant to be dealt with. Unfortunately, N_2 is quite difficult to measure. With NF_3 present it appears that the best way to measure N_2 is to use a gas chromatograph. Reference 5 details the requirements and indicates the procedure for using a gas chromatograph to analyze NF_3 for nonreactive impurity levels. Reference 5 documents the set of procedures used by the Air Force to ensure quality control on NF_3 bought for DoD Chemical Laser Programs. The gas chromatograph can be used to analyze for N_2 , CO, O_2 , NO, CF_4 , CO_2 , N_2O , SF_6 , and NF_3 content. The reactive fluorine compounds (F_2 , N_2F_4 , NOF , N_2F_2 , COF_2 , etc.) are measured using other techniques. The unfortunate drawback of a gas chromatograph is that it uses a batch process not a continuous process.

Fig. 1A

**ABSORPTION BY 30 torr OF NF_3 IN 3 atm OF HELIUM -
10 cm CELL LENGTH**

Fig 19

Fig. 20

The obvious remaining question about gaseous contaminants is what effect on laser performance do they have? Figure 21 shows the effect of a wide variety of contaminants on KrF laser energy produced. In general any contaminant, including excess F_2 , reduces laser output. Contaminants such as HF , N_2 , air, and excess F_2 affect laser output the least. Other contaminants such as O_2 , CF_4 , CO , SiF_4 , and CO_2 cause a much more severe loss of laser output at much lower concentrations. The data point labeled R/D XeF is from Ref. 6. Arworthy, Landy, and Massie at Rocketdyne have done extensive work on the chemistry of excimer lasers. To arrive at the data point we summed up the total impurities measured by Rocketdyne after a 33 pulse test and added in a N_2 concentration which assumes all unaccountable N atoms end up as N_2 . The N_2 accounted for 79% of the contaminants, F_2 19%, and everything else 2%. After 33 pulses NF_3 was added to bring the NF_3 concentrations back to its original level. The average laser output for pulses 34 through 37 and the first pulse energy were used to arrive at the energy decrease due to contaminants. From studying Fig. 21 the Rocketdyne data point is very close to the KrF data for F_2 and N_2 .

Figure 22 shows the effect of the addition of N_2 to a Lumonics 861 laser. Nitrogen in small concentrations has little or no effect on XeF when F_2 is the F-atom source. However, the effect of N_2 is much more dramatic when NF_3 is the F-atom source. Also note that the decrease in laser output is about the same as with the data point labeled R/D in Fig. 21 and 24. Though not shown in Fig. 22 the initial laser output with NF_3 was slightly less than with F_2 . Also, with F_2 the laser begins to lose at maximum output immediately; however, with NF_3 the laser takes about 7 minutes to reach maximum output. Figure 23 offers an explanation of what is occurring. The partial pressure of NF_3 is decreasing rapidly. CF_4 concentrations as shown in Fig. 10 builds up gradually.

LOS ALAMOS KrF LASER PERFORMANCE

Fig. 21

EFFECT OF NITROGEN ON XeF LASER PERFORMANCE

FIG. 22

PARTIAL PRESSURE vs TIME

- ▲ F_2 PARTIAL PRESSURE BASED ON NF_3 LOST
- ◆ F_2 PARTIAL PRESSURE BASED ON LASER OUTPUT
- N_2 PARTIAL PRESSURE BASED ON NF_3 LOST
- NF_3 PARTIAL PRESSURE MEASURED

Fig. 23

N_2F_2 and N_2F_4 are not detected. Hence, we conclude that the missing N and F atoms are showing up as N_2 and F_2 . Actually, the laser appears to start lasing only when a considerable concentration of F_2 has built-up. The N_2 build-up calculated is shown in Fig. 23. The F_2 partial pressure based on the F-atoms lost from NF_3 is also shown. In the real world part of the F_2 will be lost due to fluoride formation - both CF_4 and metallic fluorides. To obtain an estimate of how much F_2 is present, Fig. 22 and the calculated N_2 concentration is used. This F_2 concentration is labeled F_2 partial pressure based on laser output in Fig. 23.

In Ref. 6 Arworthy et al. have studied the effects of various contaminants on XeF performance. Figure 24 shows averages of the Rocketdyne data plotted as shown in Fig. 20. Several conclusions can be arrived at by studying Fig. 24. Overall, the trends of the effect of contaminants on XeF performance are quite similar to the effects of contaminants on KrF. The effect on CF_4 cannot be assessed due to the small concentration added. Fortunately, the ground based XeF laser does not need to use large quantities of dielectrics such as are common in discharge lasers used at Los Alamos. Hence, CF_4 may be a relatively minor contaminant in the XeF ground based laser. Also fortunately, SiF_4 doesn't appear to show up in very large quantities in the Rocketdyne data. Other contaminants which should be added to a XeF laser to measure the effect include CF_4 , F_2 , and HF.

5.0 Excimer Gas Reprocessing

A wide variety of materials have been used in studies of gaseous contaminant removal. Several room temperature adsorbents have been studied. These include silica gel, activated carbon, soda and lime, and molecular sieve. All of these accumulate gaseous reaction products which eventually severely affect a laser's performance.

Fig. 24

AP-I-VG-10001

Another gas reprocessing approach has been to combine a slow bleed and a dry ice temperature heat exchanger. The laser used was a Tachisto TAC II running at 1 Hz on KrF. The TAC II laser had a plexiglass cavity and a G-10 flashboard. The flow rate was 4 cfm with a cavity pressure of 2 atm and a bleed rate of about 0.5 slm. When the laser operation was started with the heat exchanger at dry ice temperature the laser output leveled off at about 60 mw, which is about 90% of the initial value (see Fig. 25). Once the dry ice bath was removed from the heat exchanger, the laser output dropped by about a factor of 2. Upon recooling the heat exchanger to dry ice temperature, the laser output did not change significantly but remained near the 30 mw level. When laser operation was started with the heat exchanger at room temperature, the output quickly dropped to near the 45 mw point. Initially we believe we are forming partially fluorinated hydrocarbons which with time are transformed to CF_4 and COF_2 . Partially fluorinated hydrocarbons would be frozen out at dry ice temperature but not COF_2 and CF_4 . For the present XeCl system (see Fig. 12) about -140°C is as cold as a heat exchanger could go without removing the Xenon. At -140°C with XeCl all of the likely contaminants identified to date would be frozen out. Hence, this type of cleanup system should work with XeCl. With XeF on the other hand, the coldest the heat exchanger could be is about -160°C . At this temperature NF_3 , N_2 , F_2 , CF_4 , CO , and OF_2 would not be removed. Hence to work with XeF there would have to be no oxygen or carbon in the system and NF_3 could not be used as the F-atom source.

Hot metal getter traps have also been extensively investigated.^{7,8,9} At Los Alamos the primary getter materials used to date are calcium, zirconium, and titanium. At Rocketdyne the primary getter material studied is liquid lithium.⁶ In most cases, the getter takes up much more gas than would be expected from covering its surface with a monomolecular layer before showing

Fig. 25

signs of decreasing effectiveness. It is thought that the gas is either combined chemically with the getter or is adsorbed on its surface. Adsorption is followed by diffusion into the interior of the getter material. In general, a rise in temperature accelerates the absorption of further gas by promoting diffusion. In some instances, a gas which has been absorbed by a getter without forming a chemical compound or a gas which forms a compound that decomposes at higher temperatures may be re-liberated as temperature increases; an example of this behavior is H_2 absorbed on titanium or zirconium. In other cases such as with zirconium or titanium, the reaction products are volatile and can be trapped separately leaving a relatively clean surface on the getter material.

In this study three different sizes of getter trap have been studied - 1 in, 2½ in, and 4 in o.d. Average trap velocities based on trap i.d. have been varied from 0.4 to 21 cm/s. Gas residence times have been varied from about 3.6 s to about 200 s. Getter chip sizes from 2 to 10 mesh have been tested. Calcium, titanium, zirconium, and lithium have been evaluated as getter materials. In this report primarily calcium, zirconium, and lithium will be discussed.

Calcium Getter Trap Studies

The calcium getter trap is the type most commonly used on excimer lasers at Los Alamos. It has been shown to remove halogen sources such as HCl , NF_3 , and F_2 and the most common gaseous contaminants down to concentrations of less than 25 ppm. However, there are a multitude of variables and problems which must be addressed to attain this degree of gas purity for any length of time.

The two most difficult gaseous impurities to remove are N_2 and CF_4 . Until fairly recently N_2 has not been a serious contaminant. Its effect on laser performance (see Figs. 21 and 22) was not particularly serious. Usually the source was an air leak in the laser which was correctable by careful leak checking and by monitoring the ultimate vacuum of the laser system. Likewise it was relatively easy to fill a getter trap with N_2 and to monitor the temperature required for the gas pressure to decrease down to 10 to 20 μ m. However, with the advent of the use of NF_3 with XeF lasers the situation has changed. Now there is a source of large amounts of N_2 which appears to severely tax the getter trap's gettering ability. Clearly a good N_2 monitor is badly needed. CF_4 , on the other hand, is easy to measure by absorption at 7.8 μ m (see Fig. 16).

Based on considerations of getter bed plugging, of maximizing trap chemical lifetime, and of getter bed saturations effects, the following getter bed specifications are recommended as appropriate to maximize getter trap lifetime.

First of all, the operating temperature needs to be at least 650°C or the trap will saturate fairly quickly (see Fig. 26). For sustained runs at Los Alamos, peak getter trap temperatures near the outlet of the getter trap are often near 700°C. As can be seen in Fig. 27 this results in a calcium vapor pressure of about 0.1 torr. The calcium currently is condensed on the stainless steel wool bed filter between the calcium and the end of the getter trap container. Compared to the calcium fluoride collected in this filter, the calcium metal is not noticeable. Secondly, to minimize plugging of the getter bed, the use of two to four mesh calcium turnings is recommended. With two to four mesh size turnings a maximum trap velocity of 7 cm/s and a minimum gas residence time of 10 s will keep HCl and NF_3 concentrations leaving the trap below 25 ppm. The trap velocity was calculated based on the inside diameter of the getter trap container. Lastly, as shown in Fig. 28, when calcium is

KrF LASER AT 2 Hz

Fig. 26

VAPOR PRESSURE OF LITHIUM AND CALCIUM

Fig. 27

H_2 -CaH₂ EQUILIBRIUM PRESSURE

Fig. 28

SS

operated in the range of 650 to 700°C with HCl present eventually the H_2 and CaH_2 in the trap will reach an equilibrium condition. The H_2 pressure will be between 1 and 2 torr. This H_2 present in the laser will help prevent the formation of metallic chlorides and chlorocarbons by scavenging some of the Cl atoms which would otherwise react with structural materials.

Lithium Getter Traps

For small cleanup system requirements such as for a space based XeCl laser a solid metal getter trap has many advantages. However, for a large ground based XeF laser with a very large gas reprocessing requirement a liquid getter trap has many attractive features. For example the getter bed material can be pumped through a side reprocessing loop to prevent the accumulation of reaction products and to ensure a clean reactable surface over long periods of time. Also, the bed plugging problems are eliminated.

Rocketdyne investigators (A. Axworthy, D. Landy, and N. Massie) have summarized their study of a liquid lithium getter trap in Ref. 6. Overall, they have done an excellent job of disclosing the potential superiority of a liquid lithium getter trap system. Here we will add only a couple of comments which may increase slightly the effectiveness of the concept. First of all we feel it is important that CF_4 be removed to a low level. In the Rocketdyne study 30 ppm was used as one of the most difficult contaminants to remove. As shown in Fig. 24, 39 ppm of CF_4 has no effect on laser performance. In Fig. 29 the required temperatures for CF_4 removal as reported by Rocketdyne in Ref. 6 are shown. A temperature of 600°C removes half of the CF_4 which gives 19 ppm of CF_4 remaining in the test gas. As shown in Fig. 24 this concentration will have no effect on laser performance. Figure 27 shows vapor pressure vs temperature for calcium and lithium. We commonly run calcium at a temperature of

PER CENT OF CF_4 REMOVED BY LITHIUM AS A FUNCTION OF TEMPERATURE

700°C. Lithium at 600°C still has a lower vapor pressure than the calcium getter traps extensively used at Los Alamos. Hence, the lithium can be ran at temperatures of over 600°C without plugging problems as long as the condensing point of the lithium is carefully considered. Operating temperature limits will not restrict lithium getter trap usage.

Zirconium Getter Traps

The zirconium getter trap has been studied extensively over the last year for use with both XeF and XeCl. After testing over a wide variety of conditions we conclude that zirconium is not very promising as a getter material. When used with HCl, the lowest attained HCl concentration was 100 ppm. By comparison, calcium is 30 times more effective than zirconium for removing HCl. When used with NF₃ the N₂ is not adequately removed. Also, CF₄ removal is incomplete. Hence, the overall conclusion is that zirconium is no where near as good a getter material as is calcium.

6.0 Clean Up System Development

XeCl Clean UP System Requirements

The space based blue-green laser requirement is for a 100 Hz XeCl laser that will operate for 10¹⁰ pulses. For this study the laser output is assumed to be 4 J/pulse and the discharge volume is 1 l with 20% allowed for discharge spreading effects. Other cleanup system sizes can be estimated by multiplying the following cleanup system specifications by the ratios of discharge volumes times the operating pressure ratios.

In work done at Los Alamos, HCl depletion results in a 10% loss in output energy in 8300 discharges/discharge volume. Re-injection of HCl at this point

will bring the laser output to within 1 to 2% of the original output. The 1 to 2% fall-off in laser output is mostly due to particulates on the optics. With nothing more than HCl injection 25,000 discharges/discharge volume has been demonstrated with a 4 to 5% loss of output energy. Of this 4 to 5% loss of output energy about 2 to 3% is due to gaseous contaminant formation.

In this report a clean-up system will be sized to handle only the gas contamination reprocessing requirement. At this point, due to the amount of clean gas required to keep the optics clean by flushing techniques, it appears that optics flushing will not be practical for a space based laser. Instead, filtering of the laser gas or electrostatic techniques to keep particulates off the optics appear to be more desirable. To prevent chlorocarbon build-up within the laser and subsequent deposition of carbon on the laser optics, the use of plastics and carbon bearing compounds should not be allowed especially in the discharge and laser beam areas. Following is Table X which summarizes the XeCl laser cleanup system requirements. It should be remembered that since gas is being removed out of a reservoir the number of time constants has to be considered. One time constant is the system volume divided by the volume reprocessing rate. In this amount of time 37% of the gas in the reservoir will be reprocessed. In two time constants 86% of the gas will be reprocessed and in three time constants 95% will be reprocessed. Note that for a 10^{10} pulse lifetime, three of these traps would be required with one being in use at a time.

XeF Clean Up System Requirements

The ground based blue-green laser requirement is for a 100 Hz laser that will operate at least $3(10^6)$ pulses between maintenance periods. For this study the laser output is assumed to be 100 J/pulse and the discharge volume

TABLE X

XeCl LASER CLEAN UP SYSTEM

Getter material:	Calcium, 2 to 4 mesh size turnings
Amount of Calcium:	13.8 lbs (based on 50% utilizations)
Getter bed lifetime:	3.3 (10^9) pulses
Getter trap diameter:	6" o.d. with 1/8" thick walls
Getter bed void fraction:	55%
Getter bed length:	53 cm
Getter bed temperature:	650°C
Getter bed container material:	Inconel 600
Gas reprocessing rate:	3.45 standard liters per minute at 4 atm pressure
HC1 consumption:	20 lbs per 10^{10} pulses
Gas velocity in getter bed (based on trap i.d.)	= 0.27 cm/s
Gas residence time:	198 s

is 16 ft. The operating pressure is 3 atm. Other clean up systems can be sized by multiplying the following clean up system specifications by the ratio of discharge volumes times the ratio of pressures.

In work done at Los Alamos with a discharge laser the gas lifetime to a 10% energy loss is 240 discharges/discharge volume with NF_3 and 333 discharges/discharge volume with F_2 . Re-injection of NF_3 or F_2 at this point will restore only part of the initial output. Gaseous contamination for XeF definitely determines the required gas reprocessing rate. In Ref. 6 the gas lifetime to a 10% energy loss with an e-beam system using NF_3 is 3 discharges per discharge volume. The laser was made of monel with the foil material being titanium. At Los Alamos several years ago, a KrF e-beam laser using F_2 would have a gas lifetime to a 10% energy loss of about 3 discharges per discharge volume when using a titanium foil and about 125 discharges per discharge volume when using an inconel 600 foil. The laser was made of stainless steel and copper.

In this report the clean-up system will be sized to handle only the gas contamination reprocessing requirement; however, since the reprocessing rate is so large there should be plenty of clean gas available to flush the optics with. The clean up system is sized for a 10^8 pulse lifetime to keep the gas velocity through the bed and the gas residence time in the bed within acceptable limits. The sizing is based on a gas lifetime of 10% loss in output energy in 240 discharges/discharge volume with NF_3 and 333 discharges/discharge volume with F_2 . Following is Table XI which summarizes the XeF clean up system requirements. Several comments about the system are in order. In an actual system as large as this, it may be more practical to use a liquid lithium getter trap which would make reprocessing and addition of getter material easier. Also, it should be noted that if the gas lifetime in Ref. 6 (three

TABLE XI
XeF CLEAN UP SYSTEM-GENERAL

Number of getter traps:	3 in parallel
Getter material:	titanium 2 to 4 mesh size
Getter bed void fraction:	55%
Getter trap diameter:	12.5" o.d. with 1/4 " thick walls
Getter bed length:	112.5 cm
Getter bed temperature:	650°C
Getter trap container material:	Inconel 600
Amount of Titanium:	367 lbs/trap - minimum, assuming 50% utilizations

Specific for NF_3

Getter trap lifetime:	10^8 pulses
Total gas reprocessing rate:	127 scfm
Gas velocity in each getter bed:	9.1 cm/s (based on trap i.d.)
Gas residence time:	12.3 s
NF_3 Consumption:	380 lbs assuming 0.1% NF_3

Specific for F_2

Getter trap lifetime:	3 (10^3) pulses
Gas reprocessing rate:	92 scfm
Gas velocity in each getter bed:	6.6 cm/s (based on trap i.d.)
Gas residence time:	17.1 s
F_2 consumption:	439.2 lbs assuming 0.1% F_2 or 146.4 lbs for 10^6 pulses

discharges/discharge volume) is encountered in the 100 J/pulse 100 Hz XeF laser a reprocessing rate of 10,200 scfm would be required. Overall, the gas lifetime of XeF is not very good at best. Typically, XeCl will easily have a minimum of 100 and a maximum of 10,000 times longer gas lifetime than XeF.

Status of Clean-up System Development

The general configuration of an excimer clean-up system is as shown in Fig. 30. This configuration has changed very little in last two years. Some of the changes that have occurred include redesign of flow controllers, further design and optimization of particulate filters, and variations of getter material size and bed dimensions.

Figures 31 and 32 show the clean-up system used with the Model 861 Lumonics laser. Figure 31 shows the control panel for the clean up system. Overall, the system is made primarily of stainless steel. The valves shown on the control panel are either Nypro bellows valves or Whitey ball valves. The halogen flow controller in the upper left hand corner was purchased from Airco Specialty Gas Co. It is made primarily from Brooks components. This particular unit is very reliable even when used with fluorine. It has been in continuous use for about three years. The two flow meters readouts to the right of the halogen controller are Teledyne-Mastings products. The flow meters are made of monel. This type of flow meter has been quite reliable except for an occasional electrical component failure due to EMI. Directly below the halogen flow controller is a Teledyne-Mastings flow controller. This unit senses the flow through one of the flow meters and automatically adjusts a throttle valve (valve #1) to maintain the flow at a pre-set value. The commercial valve that comes with the flow controller has created a lot of problems. With time the stem packing develops a leak. If the packing nut is

RARE GAS MONOHALIDE LASER CLEANUP SYSTEM

FIG. 30

Fig. 31 Excimer laser cleanup
system control panel.

Fig. 12 Inertial Laser system.

tightened to the point where no leaks occur, the motor drive unit no longer has the torque sufficient to turn the valve stem. Hence, the approach taken at Los Alamos has been to replace the commercial valve with a Nupro bellows valve and to rework the electronics to be compatible. In the future, we will probably purchase flow controllers from Airco Specialty Gas Co. or MKS Instruments, Inc. MKS offers flow controllers with valves made by Granville-Phillips, Veeco, Brooks, and Bolzers. The Granville-Phillips and Brooks (already used with the Airco flow controller) valves look to be the most durable and useful. Below the 0 to 50 slm flow meter is a dual channel Validyne Model CD23 pressure readout. This unit is used to monitor the compressor inlet and outlet pressures. Below the pressure readout is a Honeywell automatic temperature controller this unit senses the temperature of the getter trap and opens or closes a 60 amp mercury relay which provides power to the electric furnace which heats the getter trap. The getter trap-oven combination is shown in the middle of Fig. 32. The Honeywell temperature controller Model Number R7350C is the most EMI damage resistant of several types tested at Los Alamos. Directly to the left of the temperature controller is a five channel Doric thermocouple readout which is used to monitor critical temperatures around the clean-up system. Typically, temperatures of the getter trap centerline and outer wall, compressor inlet and outlet, and the heat exchanger downstream of the getter trap are monitored. Below the temperature controller is a Hastings 0 to 20 torr vacuum gage. Typically the clean-up system is capable of a 40 to 50 μ m vacuum with most of this pressure being due to outgassing from the getter trap and the particulate filters.

Figure 32 shows the general layout of the clean-up system. In the center of the picture is the clam shell electric furnace. This is the heater for the getter trap. It is a single zone tube furnace manufactured by the Lindberg Co.

The heating element is 2 ft long and is capable of providing up to 2800 W of power to 240 V. The getter trap within the furnace is also made of stainless steel. The trap container is about 4 ft long with a 2-1/2" o.d. and 1/8" thick walls. The ends of the trap are equipped with conflat flanges. Temperatures are monitored on the centerline of the getter trap at two locations and on the outer wall of the steel container. The getter bed is about 30" long and typically consists of 3 lbs of calcium turnings of about 2 to 4 mesh. The rest of the trap (about 9" on each end) is packed with a medium grade stainless steel wool which serves as the first in a series of particulate filters.

Immediately to the right and above the getter trap-oven combination is the heat exchanger. This water jacketed heat exchanger increases the cross sectional of the flow channel a factor of 20 thereby decreasing the flow velocity by a factor of 20. This allows the heat exchanger to be made of stainless steel (a material of poor thermal conductivity) and to still allow a small, but effective package in a straight through design. This straight through design is highly desirable from the standpoint of cleaning. When zirconium or titanium are being used with XeF and zirconium with XeCl ; ZrF_4 , TiF_4 , and ZrCl_4 condense in the heat exchanger and collect in the filters downstream. Occasionally the heat exchanger plugs up and has to be cleaned.

The large-flanged tubing sitting on the floor to the right of the getter trap-oven combination is a distributed bed filter. The inside dimensions of this filter container are 4" in diam and 2 ft long. The filter material transitions from a coarse to a medium to a fine bed of stainless steel wool all of which are lightly packed. Particulates being filtered vary in size from 0.1 to 10 μm . On top of this filter is a smaller final filter which in this case is an Airco Model number 92-3 HCl subum filter capable of removing particles down to 0.2 μm in size with an efficiency of 99.999%. A model 90 is

equally as effective at half the price but does not have removable filter elements. When zirconium or titanium are being used as the getter material ZrF_4 , TiF_4 , or $ZrCl_4$ have gone through the filter at the end of the getter trap, the heat exchanger, the 4" i.d. - 2 ft long distributed bed filter and have plugged the final filter - usually in a fairly short amount of time. If either zirconium or titanium are going to be used as the getter material, the filter design will be a critical issue strongly affecting the lifetime of any reprocessing system. On the other hand, when calcium is the getter material most of the reaction products stay within the getter bed or in the filter at the end of the getter bed. With K_2CO_3 a configuration such as this is capable of running over 10^8 pulse at 150 Hz with a reprocessing rate of 15 slm without plugging the filters. The lifetime limiting factor in the case of calcium is plugging of the getter bed. From the filters the gas next goes through a throttle valve to the compressor. To date the compressors used on the clean up systems at Los Alamos have been Metal Bellows compressors. This type of compressor with the addition of an O-ring groove on the head and a teflon-stainless steel flapper valve assembly require no complicated rotating seals. The two models used satisfactorily are the MB-151 and the MB-601. Model MB-602's have been tested but have been found to not work up to specifications. Both MB-151's and MB-601's have been in operation up to five years without failure. Normal outlet pressures of up to 40 psig are standard with an inlet pressure without bellows damage of up to 15 psig acceptable. In addition, a special high pressure version of the MB601 is available which allows operation up to 100 psig outlet pressure with up to a 20 psig inlet pressure. A high pressure MB601 compressor can pump about 180 standard liters per minute (slm) in the range of 4 to 5 atm pressure and can pump 70 slm at 7 to 8 atm pressure. The bellows material is 350 stainless steel - this is the only bellows material

used at Los Alamos. This material has been used satisfactorily with F_2 , ClF_3 , HCl , and UF_6 with no corrosion problems. Inconel 625 bellows are also available but do not have as good a lifetime as the 316 stainless steel. It is important to remember that the incoming gas has to have the particulates removed. Otherwise, the flapper valve assembly will not work properly and the bellows will accumulate a lot of solid material.

7.6 HALOGEN MONITOR DEVELOPMENT

Over the last six years of excimer laser development at Los Alamos it has become readily apparent that halogen concentration monitors are necessary for long term laser operation. Without a halogen concentration monitor on the laser and on any clean up system, laser operation is pure guess work. Over the last three years a variety of techniques have been investigated for suitability for halogen concentration monitoring. The status of the monitor development effort will be summarized in the paragraphs that follow. The halogen compounds to be discussed here are HCl , HF , and F_2 .

HCl Monitor Development

The most extensively developed halogen monitor system is for HCl detection. Figure 33 shows a typical infrared absorption curve for HCl in a 10 cm cell. The spectrophotometer used was a Beckman Acculab 9. A 10 cm cell path length is very marginal for an accurate HCl concentration measurement. The two options to increase sensitivity are to use a spectrophotometer with a scale expanding option or to increase the optical path length. Path length can be increased by use of a 0.75 to 20 m variable path length Wilks cell or by use of a longer fixed length cell in a single wavelength instrument used for monitoring only HCl . Due to the corrosive nature of the gas in use, variable

ABSORPTION AT $3.4\ \mu\text{m}$ OF HCl
IN 3 atm. OF HELIUM

Fig. 33

path length cells have been avoided due to the internal optics. A variable path length Wilks cell costs nearly as much as a dedicated single wavelength instrument which requires less maintenance.

The type of gas analyzer chosen for modification to the absorption wavelength is a Beckman Model 865 nondispersive infrared analyzer. The specifications of this instrument are shown in Table XII. In general this is a very reliable instrument. It is routinely calibrated by passing a known gas through the gas cell and adjusting the span and zero accordingly. Monitoring HCl does, however, present unique problems. Metallic Chlorides which form out gas appreciable quantities of HCl. HCl concentrations of 500 to 600 ppm from outgassing alone is common. In fact, after a years operation without cleaning the EDS could be evacuated to 10 μ m pressure, filled with rare gas, and then lased at about 2/3 maximum power without any HCl addition at all.

NF₃ Monitor Development

Figure 34 shows how rapidly NF₃ concentration changes in a Lumonics 861 laser. With this rapid a change in concentration with time it is important to have a good on-line NF₃ monitor to identify NF₃ concentration at a given time.

As shown in Fig. 19, NF₃ has several prominent absorption bands in the infrared. Depending on path length and NF₃ concentration to be monitored, any of these could be used for concentration measurement. To use the absorption features at 1940 or 1810 cm^{-1} a path length such as used with the HCl monitor (15.0 in) is required to ensure accuracy at low NF₃ concentrations. Also, the scale expansion option available on some spectrophotometers may be adequate. At Los Alamos the absorption feature at 900 cm^{-1} is being used with a Beckman Acculab 9 Spectrophotometer. The optics being used are barium fluoride. Figure 35 shows the absorption at 900 cm^{-1} for 350 ppm of NF₃. The fact that

TABLE XII
SPECIFICATIONS FOR BECKMAN MODEL 865 HCl CONCENTRATION ANALYZER

Precision:	1% of full scale
Noise:	1% of full scale
Zero drive:	± 1% of full scale per 24 hours
Span drift:	± 1% of full scale per 24 hours
Electronic response time:	Variable, 90% in 0.5 s to 26 s, field selectable
Maximum sensitivity:	25 ppm per small scale division
Sample cell length:	15.0 in (38.1 cm)
Materials in Contact with Sample:	
Windows:	calcium fluoride
Cells:	gold-plated stainless steel
Tubing:	FEP teflon
Fittings:	316 stainless steel
O-rings:	Viton - A
Sample flow rate:	Nominal 500 to 1000 cc/min
Sample pressure:	Maximum 100 psig with special optics
Ambient temperature range:	30° to 120°F (-1 to + 49°C)
Analog Output:	
Standard (Potentiometric):	0 to 10 mV, 0 to 100 mV, 0 to 1V, 0 to 5 VDC (field selectable)
Optional (Current):	4 to 20 mA, 10 to 50 mADC (field selectable)
Optional (Linear Potentiometric):	0 to 10 mV, 0 to 100 mV, 0 to 1V, 0 to 5 VDC (field selectable)
Optical (Linear Current):	4 to 20 mA, 10 to 50 mADC (field selectable)
Power requirements:	115 V ± 15 Vrms 50/60 Hz ± 0.5 Hz 400 W
Enclosure:	General purpose for installations in weather protected area
Overall dimensions:	8 11/16" (220 mm) H 13 1/8" (333 mm) W 27 3/8" (696 mm) D
Instrument weight:	61 lbs (28 Kg)
Shipping weight:	81 lbs (37 Kg)

NF₃ PARTIAL PRESSURE vs TIME

**ABSORPTION BY 800 MICRONS NF_3 IN 3 atm OF
HELIUM - 10 cm CELL LENGTH**

FIG. 35

the optical transmission is falling off at 900 cm^{-1} does make the concentration determination more difficult; however, barium fluoride is more durable in a fluorine environment than are sodium or potassium chloride which give a better infrared transmission.

The fall off could be canceled out by putting identical barium fluoride optics in the reference side of the spectrophotometer. Figures 36 and 37 show calibration curves for NF_3 concentrations of interest for XeF lasers. Note that a 10 cm cell used with a standard spectro photometer gives quite adequate resolution. Hence, most DoD and contractor participants in the Blue-Green Program can quickly bring on-line an NF_3 monitor with equipment already on hand.

F_2 Monitor Development

Fluorine has no absorption in the infrared; however, it does have an absorption feature in the ultraviolet region. Figure 38 shows the ultraviolet absorption feature. It is interesting to note that absorption by fluorine is twice as strong at 248 nm (KrF wavelength) as at 351 nm (XeF wavelength). This seems to go along with the Los Alamos experience that F_2 works better with XeF than NF_3 as long as the F_2 concentration is kept low enough so that F_2 absorption is a minor effect.

To date no on-line F_2 monitor has been used at Los Alamos. Off-line measurements have been made using a Beckman ultraviolet spectrophotometer with a 10 cm cell. In the future, a Cary Spectrophotometer will be used with a 20 cm pathlength cell for better resolution. Also, the possibility of obtaining a uv gas analyzer for F_2 will be investigated.

Another approach to monitoring F_2 which may work is to react the F_2 with a solid which will produce an infrared active gas. A few solids which may

have some promise for an F_2 reaction are carbon, silicon, molybdenum, boron, and calcium carbonate. Reaction products would potentially be CF_4 , SiF_4 , MoF_6 , BF_3 , CO_2 , and COF_2 all of which have infrared absorption spectra.

**ABSORPTION BY NF_3 AT 11.0 microns IN A 10 cm
CELL FILLED WITH 3 atm. OF HELIUM**

Fig. 36

**ABSORPTION BY NF_3 AT 11.0 microns IN A 10 cm
CELL FILLED WITH 3 atm. OF HELIUM**

Fig. 37

AP-1-VG-10218

References

1. S. A. Heenig, App. Opt. 21, No. 3, 565, (1982).
2. Handbook of Chemistry and Physics, 57, D-183, (1976).
3. Private Communications, E. J. Barber, Oak Ridge Gaseous Diffusion Plant, Union Carbide Corp., Nuclear Division, Oak Ridge, Tennessee.
4. MIL-P-27405, Military Specifications Propellant, Fluorine, 22 May (1970).
5. L. A. Dee and W. T. Leyden, "Nitrogen Trifluoride Analytical Procedures," AFRPL-TR-76-89, Dec. 1976, Air Force Rocket Propulsion Laboratory, Edwards AFB, CA 93523.
6. A. E. Axworthy, P. G. Landy, N. A. Massie, "Excimer Laser Gas Processor Study," Third Semiannual Report, Rocketdynamics Division, Rockwell International, 6633 Canoga Avenue, Canoga Park, CA 91304, Contract Number DAAH01-80-C-0781, U. S. Army Missile Command, Redstone Arsenal, AL 35809.
7. J. H. Brannon, "Analysis of Chemical Degradation Products in an e-Beam Pumped Rare-Gas Halide Laser," IEEE J. of Quant. Electron., August, (1982).